

What's added in StationFinder version 3.0

New Buttons in the Toolbar

Band — A new button (before Manual) that opens a Band Selector modal. You pick a standard shortwave or medium wave broadcast band and it automatically sets the frequency search to that band's range and switches to Range mode.

Step — A new button that lets you walk through the results table one row at a time, sending each frequency to the SDR. Left-click steps forward, right-click steps back. After a scan, it only steps through rows where a signal was detected.

Scan / Stop Scan — A major new feature. Clicking it opens a **Pre-Scan Review modal** (see below) rather than immediately starting. Once running, the SDR scans the frequency range and highlights rows where a signal is detected above the SNR threshold. Press Stop Scan to halt; results stay highlighted until you press Clear.

Hop / Stop Hop — Steps through frequencies automatically, sending each one to the SDR after a selected dwell time. A companion **dwell time dropdown** (1/2/4/6/8/10 s) sits beside it. After a scan, it only hops through frequencies with detected signals.

SNR dropdown — A new selector next to Hop for setting the signal-to-noise ratio threshold used during scanning (options from SNR >3 dB up to SNR >35 dB, plus windowed ranges like 5–15 dB).

New Filter Button

Active — A third on-air filter button has been added beside Show All and On Now. After a scan is stopped, this filters the table to only rows where a signal was detected.

Pre-Scan Review Modal (entirely new)

When you click Scan, instead of starting immediately you get a modal panel that shows:

- A **live FFT spectrum** of the current frequency range from the SDR, updating in real time
- A draggable **search range bar** overlaid on the spectrum — you can drag the centre to shift it, or drag the edges to adjust the limits
- Frequency labels for the FFT and the search range
- **Three stat tiles** you can click to adjust: Sample rate, Center frequency, and SNR threshold (left-click increases, right-click decreases)
- A **Database entries in range** count

- A **mode status indicator** showing whether SDRconnect is in AM or SAM mode (required for scanning), with a warning and AM/SAM buttons to switch it if not
 - Cancel, AM, SAM, and **Start Scan** buttons
-

Row Interaction Change

In v2, you had to **double-click** a row to tune the SDR. In v3, a **single click** tunes the SDR. Ctrl-click for the detail panel is unchanged.

IP Address History

The IP address field in v3 has a **dropdown history** — previously entered IP addresses are saved and appear as suggestions below the field.

Disabled Button States

In v3, buttons that aren't currently available (e.g. Step and Hop when no range is set) display at **reduced opacity (0.35)** and are visually grayed out, giving clearer feedback. v2 didn't style disabled tabs this way.

Help Text Updates

The Help modal reflects all the new features, and the bundled ListBuilder reference has been bumped from v1.0 to **v1.1**.

What Stayed the Same

The overall dark theme, layout, column structure, connection panel (WebSocket / CAT COM / Icom CI-V), frequency search modes (Exact/Prefix/Range), Show All/On Now filters, Mode/Language/Source dropdowns, sortable columns, the ILG detail modal, and the browser compatibility warning are all essentially unchanged from v2.