



Commodore PET 8032 and 4032 Diagnostics Manual

Version 1.1 Created in June 2025

Created by Rudy's Retro Intel

The purpose of this manual is to help identifying issues and the repair of a Commodore PET 8032\4032. Excluded from

The PET 8032 boards I used to create this manual is the:

**Universal Dynamic PET
Assy Number 8032090**

For the latest version of this document and other diagnostic manuals, use the links below.

<https://github.com/RudyRetroIntel/Vintage-Computer-Diagnostics>

You can find my videos here.

<https://www.youtube.com/@RudysRetroIntel>

Contributors



Chuck Hutchins - Technical help with his many years of experience on the Commodore computers. Have a look at his collection and knowledge on his YouTube channel: <https://www.youtube.com/@HutchCA>



David Bradley - Provided several PET boards for comparisons which allowed me to take measurement. See his many Commodore related videos here: <https://www.youtube.com/@DRBradleyPhotography>

*"Sharing knowledge, we can ensure that the Commodore PET 8032 computers can be repaired and enjoyed now and into the future.
Rudy's Retro Intel"*


***** This document is based on the work I have performed on my Commodore PET 8032 computer and is provided "as is". I\we do not take any responsibility for errors and\or damages that may occur when repairing your Commodore 8032 and\or 4032 computer. This information is provided freely to all Commodore PET computer owners. Please ensure you know how to perform electronics\electrical work. If not, please contact someone who has these skills before starting. *****

Index

<i>Motherboard Identification</i>	<i>Page 3</i>
<i>Commadore PET Schematic and Other Files</i>	<i>Page 4</i>
<i>Symptoms and Diagnostics Basics</i>	<i>Page 4</i>
<i>8032 Motherboard from Super PET Computer</i>	<i>Page 4</i>
<i>Using a Diagnostic Tool</i>	<i>Page 6</i>
<i>Commodore PET 8032\4032 Symptoms and Diagnostics</i>	<i>Page 7</i>
<i>Not Booting</i>	<i>Page 7</i>
<i>Main RAM Related Issues</i>	<i>Page 15</i>
<i>Booting Correctly, Peripherals\Ports Not Working Properly</i>	<i>Page 16</i>

Motherboard Identification

Below is a picture of the 8032's motherboard. The 4032's motherboard is identical with some changes.



Commodore PET 8032

Original

901465-19: BASIC ROM
901465-20: BASIC ROM
901465-21: BASIC ROM
901465-22: KERNAL ROM
Character ROM: 901447-10

BASIC ROM Bug Fix

901465-23: BASIC ROM
901465-20: BASIC ROM
901465-21: BASIC ROM
901465-22: KERNAL ROM
Character ROM: 901447-10

6545 used in 12"inch screen PETs for
H-Sync and V-Sync

6522 VIA (Versatile Interface Adapter)

6520 PIA (Peripheral Interface Adapter)

Video RAM

4 x 2114 RAM ICs

Main System RAM

16 x 4116 RAM ICs

CPU: 6502 (1 Mhz)

<https://www.youtube.com/@RudysRetroIntel>



Commadore PET Schematic and Other Files

Full schematics, ROMs images, support programs, etc. can be found here:

<https://www.zimmers.net/anonftp/pub/cbm/firmware/computers/pet/index.html>

8032 and 4032 Differences

The 8032 and 4032 are very similar, except for the following:

1. **Video RAM:** 8032 has 4 video RAM ICs. 4032 only has 2 video RAM ICs.
2. **ROMS:** EDIT ROM is different between the two as the EDIT ROM for the 8032 produces 80 columns of text and the EDIT ROM 4032 produces 40 columns of text.
3. **Jumper Wires.** There are jumper wires\connection that are different, depending 40 or 80 column text.
4. **Keyboard:** The 4032 uses a graphical keyboard while the 8032 will use the business keyboard. You cannot interchange them.

Symptoms and Diagnostics Basics

In the following sections, symptoms are presented and diagnoses. Please note that there could be several faulty\failed ICs and\or other issues.

1. Ensure you remove all ICs in sockets and clean the sockets with an electronic cleaner before starting.
2. Press all socketed ICs down to ensure full contact with the socket.
3. Check to ensure the power cable is connected from the 8032 motherboard.
4. Check voltages on all voltage regulators.

The steps above are basic troubleshooting tips and will not be covered in this manual.

8032 Motherboard from Super PET Computer

Since the 8032 motherboard is also used in the Super PET 9000 computer, this document can be used however the following should be noted:

1. Special CHARACTER ROM and jumper wire needed. Check my Super PET diagnostic manual for this information
2. EDIT ROM replacement adapters can be use if computer is an 8032. This option will not work if on a Super PET 9000 computer. Since the Super PET daughter board needs to disable (send "No Rom" signal) to take all the ROM chips off the bus regardless of the address bus, the ROM replace adapter do not appear to work properly.

Correct Boot Screen



The prompt should be:

***** commodore basic 4.0**

31743 bytes free

ready.


NOTE: the green block on the screen should be blanking(flashing) on and off.

Booting to this screen does not mean that the 8032 motherboard is fully working. Further testing is required.

Using a Diagnostic Tool

This diagnostic tool is an excellent way to help determine issues. You can purchase on here:

<https://www.tindie.com/products/tynemouth/pet-diagnostics/> just remove the CPU-6502 IC at **UB14** and place this board into the CPU socket. After setting the switches correctly, the boot will start the diagnostics.



This diagnostic tool will require that the 6545 CRT, video RAM and video support IC are working.

Note: All RAM should show “ – All OK –” and each ROM detected. The two ROM sockets (D12 and D11) are empty and will display “ – EMPTY –”

This diagnostic board will help determine if memory and ROMs are working correctly.

Order of ROM detection is as follows:


- D12 9000-9FFF – Empty socket and used for application(s)
- D11 B000-BFFF – Empty socket and used for application(s)
- D10 D000-DFFF – BASIC 4 ROM – 901465-23 (this version has the fix for BASIC)
- D9 C000-CFFF – BASIC 4 ROM – 901465-20
- D8 D000-DFFF – BASIC 4 ROM – 901465-21
- D7 E000-E7FF – BASIC 4 EDIT ROM
- D6 F000-FFFF - BASIC 4 KERNAL ROM

Commodore PET 8032\4032 Symptoms and Diagnostics

This section will go over the symptoms and diagnostics information without the use of a diagnostics board as mentioned above. Diagnostics with the board (above) is shown in later sections.

Not Booting

Symptoms: Blank screen on boot up. No chirp from speaker.




Diagnoses: Check\replace

1. Ensure there is power to the motherboard. Check for +5VDC and no shorts to ground.
2. Verify that 6502 CPU is working UB14 and that the RESET signal is present on Pin 40. Verify that the clock signal is present on Pin 3.
3. If no REST signal present, check 555 Timer - **UD16**.
4. If no clock signal present, check 7400 – **UF1**.
5. Ensure that there is a video signal on Pins 38 and 39 on the 6545 CRT chip - **UB13**.
6. Verify that the video RAM at **UC4, UC5, UC6, UC7** are working. Video RAM issues is usually the main reason for no video.
7. 74LS383 – **UD3**
8. BASIC ROM - **UD8**
9. 74LS04 -**UE4**
10. 74LS244 – **UE10**

NOTE: Due to the many ICs that could be defective, it is recommended that you use an oscilloscope and schematics for troubleshooting. Using an oscilloscope\schematic to troubleshoot is not covered in this manual.

4032 – Only has 2 video RAM chip **UC4** and **UC5**.

Symptoms: Screen show a complete green background. No chirp from speaker




Diagnoses: Check\replace

1. Follow step in previous section
2. Verify that the following ICs are working:
 1. 7417 - **UD15**
 2. 74LS164 – **UE3**
 3. EDIT ROM – **UD7**
 4. KERNAL ROM – **UD6**
 5. 74LS04 – **UC2 and UD2**
 6. 74LS02 – **UD1**
 7. 74LS10 – **UD4**
 8. 74LS00 – **UD5**
 9. 74LS244 – **UD13 and UD14**
 10. 555 Timer – **UD16**
 11. 74LS74 - **UE1**
 12. 74LS157 - **UE2**
 13. 74LS164 - **UE3**
 14. 74LS00 – **UE5**
 15. 74LS244 – **UE9**
 16. 74LS00 – **UE11**
 17. 74154 Decoder - **UE12**
 18. 74LS10 – **UE13**
 19. 7425 – **UE14**
 20. 74LS04 – **UE15**
 21. Lower RAM range 0000-3FFF (4116) -UA5, UA7, UA9, UA11, UA13, UA15, UA17, UA19


NOTE: Due to the many ICs that could be defective, it is recommended that you use an oscilloscope and schematics for troubleshooting. Using an oscilloscope\schematic to troubleshoot is not covered in this manual.

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace Video RAM 2114 – **UC5 and\or UC7**. Also, 74LS373 – **UB3 and\or UB8**

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace Character ROM – **UA3 and\or 74LS166 – UA2**

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace 74LS244 – UB5 and\or UB9

Symptoms: Boot with chirp but screen not correct.




Diagnoses: Check\replace 74LS244 – UB6 and\or UB7

Symptoms: Boot with chirp but screen not correct.




Diagnoses: Check\replace 74LS 244 – UB9 and\or 74LS10 – UE7

Symptoms: Boot with chirp but screen not correct.




Diagnoses: Check\replace 74LS74 – UB2

Symptoms: Boot with chirp but screen not correct. Characters off screen and roll over to next line.



Diagnoses: Check\replace 74LS74 – UB1

Symptoms: Boot with chirp but screen not correct. Note how part of the green bar is shifted down.




Diagnoses: Check\replace 74LS74 – UC1

Symptoms: Boot with chirp but screen not correct. Note some characters are flickering.



Diagnoses: Check\replace 74LS138 – UC3

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace 74LS157 – UC8

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace 74LS157 -UC9

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace 74LS157 – UC10

Symptoms: Boot with chirp but screen not correct.



Diagnoses: Check\replace BASIC ROM – **UD10**

Main RAM Related Issues

Below is a diagram showing the memory locations and corresponding RAM ICs. The locations shown are ONLY for PET computers that have the CRTC IC – 6545

PET 4016,4032,8032 (12 inch – WITH CRTC)

Address Range	BIT 7	BIT 6	BIT 5	BIT 4	BIT 3	BIT 2	BIT 1	BIT 0
0000-3FFF	UA5	UA7	UA9	UA11	UA13	UA15	UA17	UA19
4000-7FFF	UA4	UA6	UA8	UA10	UA12	UA14	UA14	UA18

Symptoms: Total memory shown: 15359 bytes free

Diagnoses: Check\replace Upper RAM range 4000-7FFF. See image above for IC locations.

Symptoms: Green screen on boot up

Diagnoses: Check\replace Lower RAM range 0000-3FFF. See image above for IC locations.

For lower RAM issues, you will need to use an oscilloscope and\or a diagnostic board to troubleshoot.

For upper RAM issues, you can use an oscilloscope, a diagnostic board to troubleshoot and\or memory test program that could be loaded from floppy drive, tape or SD card reader.

Booting Correctly, Peripherals\Ports Not Working Properly

Symptoms: Not able to read from attach drive or SD card unit attached to IEEE port

Diagnoses: Check\replace MC3446 – **UA20, UB17 and\or UC12**. Also, check\replace 6520 – **UB16 and 7417 – UD15**

Symptoms: DIRECTORY or CATALOG works, however when loading a program, the SEARCH is looking the wrong program.

Diagnoses: Check\replace System RAM related issues. RAM is partially working correctly however it may pass memory tests. Use PETTEST program to determine which ICs are bad. Since you can't load this program from the drive\SD card reader, you will have to use an external diagnostic adapter. You can also, with another working PET, rename the diagnostic software to "t.prg" and try loading it.

Symptoms: Not able to load programs from TAPE drive

Diagnoses: Check\replace 6522 – **UB15, 74LS00 – UD5 and \or 6520 – UB12**. Also check\replace Q2T2222 – **UE16**. Finally, verify that the tape itself is in good condition and that READ head is clean. You can use a cotton swab and some 99% rubbing alcohol to clean it.

Symptoms: Booting and working ok, however no chirp\sound

Diagnoses: Check\replace 6522 – **UB15, 74LS00 – UD5 and \or 6520 – UB12**

Symptoms: User port not working

Diagnoses: Check\replace 6522 – **UB15**

Symptoms: Keyboard not responding. Cannot type on keyboard

Diagnoses: Check\replace 6520 – **UB12 and\or 74LS145 - UC11**