Mittuniversitetet
MID SWEDEN UNIVERSITY

Försättsblad Prov Original

Kurskod	Provkod	Tentamensdatum
DT081A	T101	2025-08-20
Kursnamn	Datateknik AV, Signal- och bildbehandling	
Provnamn	Tentamen	
Ort	Sundsvall	
Termin		
Ämne		

6895642268

Utskriven 2025-08-26 kl. 12:38:20

Mittuniversitetet
MID SWEDEN UNIVERSITY

Department of
Computer and Electrical Engineering (DET)
Roger Olsson (Roger.Olsson@miun.se), 010 142 8698
Mårten Sjöström (Marten.Sjostrom@miun.se), 010 142 8836

2025-08-20. Examination in

DT081A – Signal and Image Processing, 6 hp


Allowed aids	Dictionary, non-programmable calculator and drawing tools (e.g ruler), Physics Handbook, TeFyMa, and formula collection booklet for mathematics/physics courses at MIUN. A collection of formulas is also presented at the end of this exam.
Miscellaneous	Don't forget to: 1. Submit one, or several pages, per solved assignment and NOT several solved assignments per page. 2. Order the handed in pages with the solved assignments in ascending order. 3. Describe and clearly motivate all solutions, assumptions, programming constructs, etc.. 4. Attach all neatly drawn figures that you might want to refer to in a solution. **Failing to follow the above instructions will render point reduction.**

Good Luck!

1. What does the following signal processing concepts mean? Be clear, concise, and relevant.

a) Sampling theorem (1p)
b) Convolution (1p)
c) Finite Impulse Response (FIR) (1p)
d) Spectrogram (1p)
e) Time-invariant system (1p)

2. A time discrete system is defined as below.



1

a) Using the block diagram, explain whether the system is FIR or IIR, causal or non-causal, and justify your answer based on its structure. (2p)
b) Derive the system's difference equation from the block diagram. (2p)

3. Given a discrete-time system described by the difference equation


$$y(n) = x(n) + y(n-1) + 0.5y(n-2)$$

with the input signal

$$x(n) = \begin{cases} 1 & n \geq 1 \\ 0 & n < 0 \end{cases}$$

a) Identify the type of response that the system produces by the given input $x(n)$. (1p)
b) Calculate the first 5 samples of the output $y(0), y(1), \ldots, y(4)$. (2p)
c) The discrete time fourier transform (DTFT) of $y(n)$ can be found to be
$Y(e^{j\Omega}) = X(e^{j\Omega}) + e^{-j\Omega}Y(e^{j\Omega}) + 0.5e^{-2j\Omega}Y(e^{j\Omega})$,
which gives the system's frequency function
$H(e^{j\Omega}) = \frac{Y(e^{j\Omega})}{X(e^{j\Omega})} = \frac{1}{1-e^{-j\Omega}-0.5e^{-2j\Omega}} = \frac{e^{2j\Omega}}{e^{2j\Omega}-e^{j\Omega}-0.5}$.
Evaluate the amplitude magnification $|H(e^{j\Omega})|$ for frequency $\Omega = \frac{\pi}{2}$. (3p)

4. A signal $s(t)$ have been sampled using $f_s = 50$ kHz. The amplitude spectrum of the sampled signal is shown in the figure below for a limited normalized frequency range.




a) Sketch the amplitude spectrum for an extended normalized frequency range by extending axis to $-2\pi < \Omega < 2\pi$. (2p)
b) What is the lowest sampling frequency in Hz that the signal $s(t)$ could be sampled in while still being possible to be reconstructed exactly? Motivate. (3p)

5. An LTI system $H(f)$ is defined by its amplification and phase-shift below. A signal $x(t)$ is fed to the system, giving the output $y(t)$.

a) Give the mathematical relation between amplitudes and phases of the input and the output. (2p)


b) Draw the amplitude spectrum and phase spectrum for the output $y(t)$. (4p)




6. The plots below show the frequency spectra (i to iv) of different window functions with varying window lengths employed in spectrogram analysis.

a) Which window offers the best time resolution when used in a spectrogram? Justify your choice. (2p)

b) Which window function best minimizes spectral leakage (where unwanted frequency components appear away from the main frequency)? Motivate. (2p)



7. The frequency response of a two-dimensional linear system is shown below. Describe its frequency-selective properties and explain its main visual effect on an image.



(3p)

8. The closeup image below has been filtered with 4 different filters.



Match the following kernels (1–5) with the corresponding filtered results (i–v). Justify your choices by explaining how the filter kernels affect the image.

Kernels

$$\begin{bmatrix}0 & 0 & 0\\ 0 & 2 & 0\\ 0 & 0 & 0\end{bmatrix}$$ **1)**

$$\begin{bmatrix}-1 & 0 & 1\\ -1 & 0 & 1\\ -1 & 0 & 1\end{bmatrix}$$ **2)**

$$\begin{bmatrix}-1 & -1 & -1\\ 0 & 0 & 0\\ 1 & 1 & 1\end{bmatrix}$$ **3)**

$$\frac{1}{9}\begin{bmatrix}1 & 1 & 1\\ 1 & 1 & 1\\ 1 & 1 & 1\end{bmatrix}$$ **4)**

$$\begin{bmatrix}0 & -1 & 0\\ -1 & 4 & -1\\ 0 & -1 & 0\end{bmatrix}$$ **5)**

Filter results



i) **ii)** **iii)** **iv)** **v)**

(5p)

9. Given the two matrices representing the input $x(i,j)$ and output $y(i,j)$ of a linear 2D filter: describe the $3x3$ point spread function (PSF) or kernel $h(i,j)$ that transforms $x(i,j)$ into $y(i,j)$. Assume boundary conditions are zero, meaning pixels outside the matrix boundaries of $x(i,j)$ and $y(i,j)$ are zero.

$x(i,j)$

i \ j	0	1	2	3	4	5
0	0	0	0	0	0	144
1	0	112	0	0	0	0
2	0	0	0	224	0	0
3	80	0	64	0	0	0
4	0	0	0	176	0	0
5	0	0	0	0	0	48

$y(i,j)$

i \ j	0	1	2	3	4	5
0	0	14	0	0	18	72
1	14	56	14	28	0	18
2	10	14	36	112	28	0
3	40	18	32	58	0	0
4	10	0	30	88	22	6
5	0	0	0	22	6	24

(6p)