MyoWare IMU v2 — Changelog

All notable changes to `myoware_imu_v2.ino` are documented here. Format: newest session at the top.

2026-03-03 — Session 20: IMU FSR raised — gyro 1000→2000 dps, acc 4→8 g (anti-saturation, balanced)

Changed (`myoware_imu_v2.ino`)

```
// Before:
static constexpr uint8_t  IMU_ACC_FSR_G    = 4;    // one of {2,4,8,16}  -- was 2 (saturated)
static constexpr uint16_t IMU_GYRO_FSR_DPS = 1000; // one of {250,500,1000,2000} -- was 250 (saturated)

// After:
static constexpr uint8_t  IMU_ACC_FSR_G    = 8;    // one of {2,4,8,16}  -- was 4; +-16g rejected (4x resolution loss)
static constexpr uint16_t IMU_GYRO_FSR_DPS = 2000; // one of {250,500,1000,2000} -- was 1000
```

Motivation

Gyro ±1000 dps → ±2000 dps: Fast sports motions (hard tennis swings, throwing, jumping) can exceed ±1000 dps on peak impact. Raising to ±2000 dps eliminates any remaining saturation risk. Resolution drops from 32.8 LSB/dps to 16.4 LSB/dps (half). This loss is acceptable because the ICM-20948 gyro noise floor is ~0.01–0.05 dps — at ±2000 dps, 1 LSB = 0.061 dps, which is right at the noise floor. The granularity loss is masked by sensor noise in practice.

Acc ±4g → ±8g (not ±16g): Tennis/racket impacts typically peak at 4–8g. ±8g covers that range with a safety margin and costs only 2× granularity (4096 LSB/g vs 8192 LSB/g). ±16g was considered but rejected: it would cost 4× granularity (2048 LSB/g), degrading resolution for subtle motion features (fatigue tremor, wrist angle) without meaningful additional headroom.

Axis	Before	After	Resolution change	Rationale
Gyro	±1000 dps / 32.8 LSB/dps	±2000 dps / 16.4 LSB/dps	½	Loss masked by noise floor
Acc	±4g / 8192 LSB/g	±8g / 4096 LSB/g	½	Best balance: covers 4-8g impacts, only 2x coarser

FSR Options Considered for Acc

FSR	LSB/g	1 LSB	Saturation	Verdict
±4g	8192	0.122 mg	4g	Saturates on hard impacts
±8g ← chosen	**4096**	**0.244 mg**	**8g**	Best balance: covers impacts, only 2x coarser
±16g	2048	0.488 mg	16g	Never saturates, but 4x coarser — degrades subtle motion

Why There Is No Protocol or Host-Side Impact

The BLE wire format is **completely FSR-agnostic**. The raw `int16` LSB values (`ax, ay, az, gx, gy, gz`) are transmitted unchanged regardless of FSR setting — the FSR only changes how the sensor hardware maps physical motion to those LSB values.

Every IMU frame already carries the FSR codes in bytes 12–13 of the IMU meta (`FLAG_IMU_META_V2`), transmitted since Session 16:

```
*p++ = accFsrToCode(IMU_ACC_FSR_G);      // 2 = 8g
*p++ = gyroFsrToCode(IMU_GYRO_FSR_DPS); // 3 = 2000 dps
```

`btCentral.py` reads these codes from each frame and applies the correct scale factor automatically — no host-side changes needed:

```
ACC_FSR_CODE_TO_G    = {0: 2, 1: 4, 2: 8, 3: 16}          # code 2 → 8g   ✓
GYRO_FSR_CODE_TO_DPS = {0: 250, 1: 500, 2: 1000, 3: 2000} # code 3 → 2000 dps ✓
acc_map = {2: 16384.0, 4: 8192.0, 8: 4096.0, 16: 2048.0}  # already present
gyr_map = {250: 131.0, 500: 65.5, 1000: 32.8, 2000: 16.4}  # already present
```

Layer	Impact
BLE wire format	✅ None — same packet structure, same byte count

Layer	Impact
`PROTO_VER`	✅ No bump — FSR is a runtime config value, not a structural format change
`PROTOCOL.md`	✅ None — FSR codes 0–3 already documented for all valid values
`btCentral.py`	✅ None — codes 2 and 3 already in both lookup tables
CSV output	✅ None — `acc_fsr_g` and `gyro_fsr_dps` columns show `8` and `2000`
Windows / Android	✅ None — same BLE notifications, same parsing logic

The `btCentral.py` fallback defaults (`cur_acc_fsr_g = 4`, `cur_gyro_fsr_dps = 1000`) are only used for old captures without `FLAG_IMU_META_V2`. New captures always override them from the frame — no fallback update needed.

FSR Lookup Table (Reference)

Code	Acc FSR	LSB/g	Gyro FSR	LSB/dps
0	2g	16384	250 dps	131.0
1	4g	8192	500 dps	65.5
2	**8g** ← new	**4096**	1000 dps	32.8
3	16g	2048	**2000 dps** ← new	**16.4**

2026-03-02 — Revert Massive Watchdog Timeouts (Brown-out Discovery)

Changed

- Reverted the 10x relaxed watchdog timeouts to more reasonable values aligned with the new 5-second host PING interval:
- `HOST_PING_EXPECT_MS`: 20000 → 12000 (12s)
- `HOST_SILENCE_PAUSE_MS`: 50000 → 18000 (18s)
- `HOST_SILENCE_REBOOT_MS`: 300000 → 30000 (30s)

Motivation

It was discovered that the frequent "BLE stalls" that led to the timeouts being massively increased (on 2026-03-01) were actually caused by **ESP32 Brown-out Resets (BOD)** on battery power, not by the Windows WinRT BLE stack silently dropping PINGs. Because the ESP32 was physically resetting due to current spikes during BLE transmission, increasing the software timeouts did not solve the root cause, and just made genuine software-level recovery much slower. The timeouts have been reverted to shorter durations to ensure the watchdog acts quickly when a genuine software stall or host crash occurs.

High-Level Design Summary

System Architecture

Hardware:

- ESP32 WROOM-32E (dual-core Xtensa LX6, 240 MHz)
- ICM-20948 9-axis IMU (I2C, 200 Hz)
- MyoWare EMG sensors: ENV (envelope) + RAW (rectified) channels (ADC DMA, 2000 Hz)
- MAX30105 pulse oximeter (I2C, 25 Hz)
- MAX17048 battery fuel gauge (I2C)
- BLE Nordic UART Service (NUS) for wireless data streaming

Software Stack:

- Arduino ESP32 core 3.3.5 (ESP-IDF 5.3.x)
- FreeRTOS (dual-core scheduler)
- ESP32 ADC Continuous (DMA) driver
- Custom binary protocol with CRC16 for reliable streaming

Task Architecture (Dual-Core)

Core 0 (Protocol CPU):

- `loop()` — BLE TX, host watchdog, LED state machine (~1 kHz)
- BLE stack (callbacks: `onConnect`, `onDisconnect`, `onWrite`)
- `esp_timer` task (priority 22) — runs `imu_timer_cb` at 200 Hz

Core 1 (Sensor CPU):

- `emgDrainTask` (priority 2) — drains ADC DMA at 40 kHz, decimates 10× oversampled results to 2 kHz EMG output
- `imuTask` (priority 2) — reads IMU at 200 Hz (timer-driven)
- `spo2Task` (priority 0) — computes SpO2/HR every ~30 seconds (background)

Priority Rationale:

- Priority 2: Real-time sensor acquisition (EMG, IMU) — must not drop samples
- Priority 0: Background computation (SpO2) — no real-time requirement
- FreeRTOS priority inheritance prevents priority inversion on `wireMutex`

Data Flow

```
Sensors (Core 1)          Ring Buffers (shared)     BLE TX (Core 0)
─────────────────         ─────────────────────     ─────────────────
ADC DMA (40 kHz)   ──→    emgBuf[2048]        ──→   send_emg_frame()
  ↓ emgDrainTask                                      (batched, CRC16)
  oversample 10×
  → 2 kHz output

ICM-20948 (200 Hz) ──→    imuBuf[512]         ──→   send_imu_frame()
  ↓ imuTask                                           (batched, CRC16)
  reads I2C

MAX30105 (25 Hz)   ──→    vitals (atomic)     ──→   send_vitals_frame()
  ↓ spo2Task                                          (every 30s)
  computes SpO2/HR
```

Synchronization Primitives

FreeRTOS Mutexes (with priority inheritance):

- `adcMutex` — protects `adcHandle` (ADC DMA lifecycle) across Core 0 ↔ Core 1
- `wireMutex` — protects I2C bus (`Wire`) across `imuTask`, `spo2Task`, `loop()`

Spinlocks (`portMUX_TYPE`):

- `emgMux` — protects EMG ring buffer (`emgBuf`, `emgHead`, `emgTail`, `emgSeq`, `emgDropped`)
- `imuMux` — protects IMU ring buffer (`imuBuf`, `imuHead`, `imuTail`, `imuSeq`, `imuDropped`)
- `vitalsMux` — protects vitals state (SpO2, HR, battery)
- `hostMux` — protects host heartbeat timestamp (`lastHostPingMs`)

Atomic Variables (GCC built-ins):

- `samplingPaused` — cross-core flag (Core 0 writes, Core 1 reads)
- Uses `__atomic_store_n` / `__atomic_load_n` with `__ATOMIC_RELEASE` / `__ATOMIC_ACQUIRE`
- Ensures memory barrier for cross-core visibility on Xtensa LX6

Volatile (single-writer, atomic hardware):

- `imu_ticks` — 32-bit counter (Core 0 `esp_timer` task writes, Core 1 `imuTask` reads/decrements)
- Lost ticks acceptable (just skips one IMU sample)
- `ledBrightness` — 8-bit value (Core 1 `spo2Task` writes, Core 0 `loop` reads)
- Non-critical display value, 8-bit writes are atomic

Critical Timing Constraints

Task	Rate	Period	Budget	Worst-Case Blocking	Margin
`emgDrainTask`	2 kHz out (40 kHz ADC)	500 µs	~1.6 ms (DMA frame)	10 ms (`adcMutex`)	✅ Acceptable
`imuTask`	200 Hz	5 ms	5 ms	~400 µs (`wireMutex`)	✅ 92% margin
`spo2Task`	25 Hz	40 ms	No deadline	N/A	✅ Background

Key Design Decisions:

1. **ADC DMA** — Hardware-clocked sampling eliminates ISR overhead and BLE radio conflicts
2. **Timestamp back-calculation** — Corrects ~16 ms DMA latency to ~1 µs accuracy
3. **Priority inheritance** — Prevents `spo2Task` (pri 0) from blocking `imuTask` (pri 2) indefinitely
4. **Host watchdog** — Pauses sampling when host is absent (prevents buffer overflow)
5. **Atomic accessors** — Ensures cross-core visibility without expensive mutexes

Tricky Parts & Gotchas

1. ADC DMA Minimum Frequency Floor (Session 17)

- **Problem:** ESP32 ADC continuous driver (IDF 5.x) enforces a minimum `sample_freq_hz` of ~20 kHz
- **Symptom:** `ESP_ERR_INVALID_ARG` abort at `adc_continuous_config()` when `ADC_CONV_FREQ_HZ = 4000`
- **Solution:** Oversample at 40 kHz total (20 kHz/channel), decimate 10× in `emgDrainTask` to yield 2 kHz output
- **Why it's tricky:** The minimum is not enforced at compile time; the abort only fires at runtime when the host connects and triggers `emg_adc_init()`

2. ADC DMA Channel-Order Violations (Session 7, superseded by Session 17)

- **Problem:** BLE radio interference can cause ADC arbiter to skip conversions
- **Symptom:** Two consecutive ENV or RAW results (ENV, ENV, RAW, RAW instead of ENV, RAW, ENV, RAW)
- **Original solution:** Overwrite stale value, count violations in `emgChOrderViolations` for diagnostics
- **Session 17 update:** `emgChOrderViolations` removed — oversampling accumulator counts each channel independently, so strict ordering is no longer required

3. Cross-Core `samplingPaused` Visibility (Session 3)

- **Problem:** `volatile` alone doesn't guarantee memory barrier on Xtensa LX6
- **Symptom:** Core 1 sees stale `samplingPaused` value, continues sampling after pause
- **Solution:** Use `__atomic_store_n` / `__atomic_load_n` with `RELEASE` / `ACQUIRE` ordering
- **Why it's tricky:** ESP32 L1 cache is not coherent between cores for DRAM

4. `adcMutex` Held for 10 ms (Session 13)

- **Problem:** `emgDrainTask` holds `adcMutex` during `adc_continuous_read()` (10 ms timeout)
- **Concern:** Does this block `emg_adc_deinit()` too long?
- **Analysis:** All deinit call sites are non-real-time (disconnect, host timeout)
- **Why it's tricky:** Must hold mutex across entire read to prevent use-after-free

5. Priority Inheritance on `wireMutex` (Session 13)

- **Problem:** `spo2Task` (pri 0) holds `wireMutex`, `imuTask` (pri 2) blocks
- **Solution:** `xSemaphoreCreateMutex()` provides automatic priority inheritance
- **Result:** `spo2Task` temporarily raised to pri 2 while holding mutex
- **Why it's tricky:** Without inheritance, `emgDrainTask` (pri 2) would preempt `spo2Task`, causing unbounded delay

6. EMG Timestamp Back-Calculation (Session 4)

- **Problem:** `micros()` called at pair-emit time, not ADC capture time
- **Error:** Up to 16 ms late (one full DMA frame)
- **Solution:** Capture `frameEndUs` after `adc_continuous_read()`, back-calculate each sample's age
- **Formula:** `actual_t_us = frameEndUs - (numResults - 1 - i) * 250 µs`
- **Why it's tricky:** DMA delivers results in batches; must reconstruct original capture time

7. `esp_timer` Callbacks Are Tasks, Not ISRs (Session 14)

- **Misconception:** `esp_timer` callbacks run in hardware ISR context
- **Reality:** `ESP_TIMER_TASK` dispatch runs callbacks in FreeRTOS task (pri 22)
- **Implication:** Safe to use `__atomic_load_n`, `xSemaphoreTake`, etc. in `imu_timer_cb`
- **Why it's tricky:** ESP-IDF documentation is subtle about this distinction

8. Sequence Number Assignment Under Lock (Session 5)

- **Problem:** `emgSeq++` was outside `emgMux`, causing race with `onConnect()` reset
- **Solution:** Assign `seq` inside `emg_push()` under `emgMux` spinlock
- **Pattern:** Caller sets `s.seq = 0` (placeholder), `emg_push()` overwrites with `emgSeq++`
- **Why it's tricky:** Sequence numbers must be monotonic and gap-free for protocol correctness

9. Battery Read Caching (Session 9)

- **Problem:** `printBatteryStatus()` called `readBattery()` every 1 second (4 I2C transactions)
- **Impact:** ~400 µs I2C bus time, `wireMutex` contention with real-time tasks
- **Solution:** Cache `lastBatteryPct` / `lastBatteryVoltage`, refresh every 10 seconds
- **Why it's tricky:** Debug prints must not impact real-time performance

Protocol Design

Frame Structure:

```
[Header: 14 bytes]
  magic0, magic1 (0xA5, 0x5A)
  proto_ver (0x02)
  flags (CRC16 | IMU_META_V2)
  frame_seq (uint32_t)
  frame_t_us (uint32_t)
  payload_len (uint16_t)

[Payload: TLV format]
  TLV_EMG_BATCH (0x01):
    seq, t_offset, rate, channels, count
    [env, raw] × count

  TLV_IMU_BATCH (0x02):
    seq, t_offset, rate, count, axes_mask
    acc_fsr_code, gyro_fsr_code
    [ax, ay, az, gx, gy, gz] × count

  TLV_VITALS (0x03):
    spo2, hr_x10, age_ms, flags
    brightness, battery_pct, battery_mv

[CRC16: 2 bytes]
  CRC-CCITT over header + payload
```

Key Features:


- **Batching:** Multiple samples per frame (reduces BLE overhead)
- **Timestamp offset:** Relative to frame timestamp (saves 4 bytes per sample)
- **FSR metadata:** Logged in IMU frames for host-side scaling
- **CRC16:** Detects corruption over BLE (Nordic UART is not reliable)

Host Watchdog

Policy:

- Host sends `PING` every ~1 second
- Device expects PING within 2 seconds (warn)
- Device pauses sampling after 5 seconds silence (prevents buffer overflow)
- Device reboots after 30 seconds silence (recovers stuck BLE state)

State Machine:



LED Patterns

Mode	Pattern	Meaning
`LED_DISCONNECTED`	Slow blink (1 Hz)	No BLE connection
`LED_WAIT_HOST`	Double-blink (every 2s)	Connected, waiting for host PING
`LED_STREAMING`	Solid ON	Streaming data to host
`LED_BACKLOG`	Fast blink (16 Hz)	Ring buffer backlog high (MTU too low)
`LED_LOW_BATTERY`	Very fast blink (10 Hz)	Battery < 20%

2026 — Session 19: Fix — BLE Stall After Reconnect (MTU Race + Notification Queue Overflow)

Problem

After a BLE reconnect, the device would send exactly one notification burst then stall completely. The Python health log showed:

```
state=OK  fps=0 notify/s=0  last_notify=225ms last_good=225ms  ping_age=318ms ping_fail=1  recon=1
state=OK  fps=0 notify/s=0  last_notify=1233ms ...
state=WARN ...
state=STALL ...
[BLE] Reconnecting in 0.5s (reason=reconnect_after_resub_9614ms)
```

Two root causes were identified.

Root Cause 1: `maxNotifyPayload` Set Before MTU Negotiation

`onConnect()` captures the MTU immediately:

```
negotiatedMTU    = BLEDevice::getMTU();
maxNotifyPayload = (negotiatedMTU > 3) ? (negotiatedMTU - 3) : 20;
```

BLE MTU negotiation happens **after** the connection event. At the time `onConnect()` fires, `BLEDevice::getMTU()` still returns the default 23, giving `maxNotifyPayload = 20`.

All three send functions require more than 20 bytes of payload:

Function	Min bytes needed	With `maxNotifyPayload=20`
`send_emg_frame()`	36	Returns `false` immediately
`send_imu_frame()`	45	Returns `false` immediately
`send_vitals_frame()`	30	Returns `false` immediately

Result: the device sends **nothing** after reconnect until the MTU is somehow refreshed. The one notification seen in the log came from the previous connection's cached MTU value (some ESP32 BLE stack versions remember the last negotiated MTU across reconnects).

Root Cause 2: BLE Notification Queue Overflow

The TX loop ran every 1 ms and called `send_emg_frame()` whenever ≥5 samples were buffered — approximately every 2.5 ms (400 Hz). The ESP32 BLE stack's internal notification queue holds only 3–5 packets. At a typical Windows BLE connection interval of 30 ms, the stack can drain ~1 packet per interval. The device was queuing 12 packets per interval (30 ms / 2.5 ms), overflowing the queue.

When the queue is full, `esp_ble_gatts_send_indicate()` (called internally by `notify()`) returns `ESP_ERR_NO_MEM`. The Arduino BLE wrapper ignores this error code — notifications are silently dropped. The Python side receives the first packet (before the queue fills), then nothing.

Root Cause 3: `emg_meta` Not Resent After Reconnect (`btCentral.py`)

`consumer_task` only sends the `emg_meta` UDP packet when `sr_hz` changes:

```
if sr_hz and int(sr_hz) != int(st.last_emg_sr_hz):
    udp_send(st, {"k": "emg_meta", ...})
```

After reconnect, `last_emg_sr_hz` still held the previous session's value. The plotter (`sensordata_plotter.py`) never received the sample-rate packet needed to reinitialise its Butterworth LPF and device-time timebase.

Fix 1: Dynamic `maxNotifyPayload` in TX Loop (`myoware_imu_v2.ino`)

Re-read the current MTU at the start of every TX loop iteration:

```
// Refresh maxNotifyPayload from the current negotiated MTU.
// onConnect() captures getMTU() before the central has a chance to
// negotiate a larger MTU, so the value there is often still 23 (→ 20 bytes
// usable), which is too small for any of our frames.  Re-reading it here
// picks up the post-negotiation value (typically 247 → 244 bytes usable).
uint16_t curMTU = BLEDevice::getMTU();
if (curMTU > 3) {
    maxNotifyPayload = curMTU - 3;
}
```

This is a one-liner that costs nothing and ensures the correct MTU is always used, regardless of when the central completes MTU negotiation relative to `onConnect()`.

Fix 2: EMG Frame Rate Limiter (`myoware_imu_v2.ino`)

Added a 20 ms minimum interval between EMG frame sends (≤50 Hz):

```
// Rate-limit EMG frames to ≤50 Hz (one frame per 20 ms).
// At 2000 Hz EMG, 20 ms accumulates ~40 samples; with MTU=247 we can fit
// up to 53 samples per frame, so we always drain the backlog in one shot.
// Sending at 400 Hz (every 2.5 ms) overflows the ESP32 BLE stack's
// notification queue (~3-5 slots at a 30 ms connection interval), causing
// silent notification drops and the "one frame then stall" symptom.
static uint32_t lastEmgSendMs = 0;
if (nowMs - lastEmgSendMs >= 20) {
    lastEmgSendMs = nowMs;
    sent |= send_emg_frame(maxNotifyPayload);
}
```

Throughput analysis:

Parameter	Value
EMG rate	2000 Hz
Frame interval	20 ms
Samples accumulated per interval	~40
Max samples per MTU-247 frame	(244 − 32) / 4 = 53
Frames per second	50
Effective throughput	50 × 40 = 2000 samples/s ✓

Total notification rate (EMG 50 Hz + IMU 50 Hz) = 100 Hz. At 30 ms connection interval: ~3 notifications per interval — within the queue limit.

Fix 3: Reset `last_emg_sr_hz` on Reconnect (`btCentral.py`)

In the reconnect exception handler, reset `last_emg_sr_hz` to 0 so the next `TLV_EMG_BATCH` frame triggers an `emg_meta` UDP send regardless of whether the sample rate changed:

```
# Force emg_meta to be re-sent on the next connection so the plotter
# (sensordata_plotter.py) re-initialises its LPF and timebase.
# Without this, the plotter never receives the sample-rate packet after
# a reconnect because consumer_task only sends emg_meta when sr_hz changes.
st.last_emg_sr_hz = 0
```

Changes Summary

File	Location	Change
`myoware_imu_v2.ino`	`loop()` TX block	Re-read `BLEDevice::getMTU()` each iteration; update `maxNotifyPayload`
`myoware_imu_v2.ino`	`loop()` TX block	Rate-limit EMG sends to ≤50 Hz via `lastEmgSendMs` (20 ms gate)
`btCentral.py`	Reconnect exception handler	`st.last_emg_sr_hz = 0` to force `emg_meta` resend

What Did Not Change

- Protocol format, frame structure, CRC — unchanged
- `send_emg_frame()` internals — unchanged (still batches all available samples)
- IMU send rate — already gated at 20 ms; no change needed
- Vitals send rate — already gated at 30 s; no change needed
- `onConnect()` MTU capture — kept as-is (now just an initial hint, overridden in TX loop)

2026 — Session 18d: Feature — SpO2 Hot-Plug Detection + Android Vitals Display Fix

Problem 1: SpO2 Sensor Had No Hot-Plug Support

Unlike the IMU sensor (Session 18), the MAX30105 SpO2 sensor had no recovery or disconnection detection:

- **Boot without sensor:** Single attempt, no retries → system continues with `max3010xPresent = false`

- **Disconnection mid-session:** No detection → vitals struct kept stale SpO2/HR values indefinitely
- **Reconnection:** No recovery attempts → sensor stayed disabled until reboot

Problem 2: Android App Ignored SpO2/HR Values

The `decodeVitals()` method in `SessionCaptureActivity.java` only extracted battery percentage:

```
// Before (incomplete):
private void decodeVitals(byte[] buf, int valOff, int valLen) {
    final int batt_pct = buf[valOff + 8] & 0xFF;
    runOnUiThread(() -> {
        txtBattery.setText("Battery: " + batt_pct + "%");
    });
}
```

SpO2 and HR fields were present in the vitals frame but never extracted or displayed.

Problem 3: Stale Vitals After Disconnection

When the SpO2 sensor disconnected mid-session:

1. `spo2Task` detected timeout (100 retries) and set `max3010xPresent = false`
2. Computation was skipped, but **vitals struct was not cleared**
3. Vitals frames continued to be sent every 30s with **stale SpO2/HR values**
4. Android app displayed stale values as if they were current

Fix 1: SpO2 Hot-Plug Detection (Firmware)

Implemented the same three-layer strategy as IMU (Session 18):

Layer 1: Recovery Detection (When Sensor Missing)

```
void spo2Task(void* /*param*/) {
  static uint32_t lastRetryMs = 0;
  static constexpr uint32_t RETRY_INTERVAL_MS = 5000;

  for (;;) {
    if (!max3010xPresent) {
      uint32_t now = millis();
      if (now - lastRetryMs >= RETRY_INTERVAL_MS) {
        lastRetryMs = now;

        xSemaphoreTake(wireMutex, portMAX_DELAY);
        bool recovered = maxSensor.begin(Wire, I2C_SPEED_FAST, MAX3010X_ADDR);
        xSemaphoreGive(wireMutex);

        if (recovered) {
          xSemaphoreTake(wireMutex, portMAX_DELAY);
          configureMax3010x();
          xSemaphoreGive(wireMutex);

          max3010xPresent = true;
          Serial.println("[SpO2] Recovered! MAX30105 sensor reconnected.");
        }
      }
      vTaskDelay(1000 / portTICK_PERIOD_MS);
      continue;
    }
    // ... normal operation
  }
}
```

Layer 2: Periodic Health Check

```
// Runs every 5 seconds even during normal operation
uint32_t now = millis();
if (now - lastHealthCheckMs >= HEALTH_CHECK_INTERVAL_MS) {
  lastHealthCheckMs = now;

  xSemaphoreTake(wireMutex, portMAX_DELAY);
  maxSensor.check();
  uint32_t testRead = maxSensor.getIR();
  xSemaphoreGive(wireMutex);

  // MAX30105 library doesn't expose status like ICM-20948
  // Rely on sample collection loop for actual I2C failure detection
}
```

Layer 3: Disconnection Detection (During Sample Collection)

```
for (int i = 0; i < SPO2_BUFFER_SIZE; i++) {
  bool avail = false;
  int retries = 0;
  while (!avail && retries < 100) {  // Timeout detection
    xSemaphoreTake(wireMutex, portMAX_DELAY);
    maxSensor.check();
    avail = maxSensor.available();
    xSemaphoreGive(wireMutex);
    if (!avail) {
      vTaskDelay(1);
      retries++;
    }
  }

  if (retries >= 100) {
    max3010xPresent = false;

    // NEW: Invalidate vitals to prevent stale data
    portENTER_CRITICAL(&vitalsMux);
    vitals.spo2_u16 = 0xFFFF;    // Mark as invalid
    vitals.hr_x10_u16 = 0xFFFF;  // Mark as invalid
    vitals.flags = 0;            // Clear validity flags
    portEXIT_CRITICAL(&vitalsMux);

    Serial.println("[SpO2] Disconnected! Sensor not responding.");
    collectionFailed = true;
    break;
  }
  // ... collect sample
}
```

Fix 2: Android Vitals Display (SessionCaptureActivity.java)

Rewrote `decodeVitals()` to extract all vitals fields:

```
private void decodeVitals(byte[] buf, int valOff, int valLen) {
    if (valLen < 11) return;

    final int spo2_u16 = u16le(buf, valOff);      // Offset 0-1
    final int hr_x10_u16 = u16le(buf, valOff + 2); // Offset 2-3
    final int age_ms = u16le(buf, valOff + 4);     // Offset 4-5
    final int flags = buf[valOff + 6] & 0xFF;      // Offset 6
    final int batt_pct = buf[valOff + 8] & 0xFF;   // Offset 8
    final int batt_mv = u16le(buf, valOff + 9);    // Offset 9-10

    final boolean spo2Valid = (flags & 0x01) != 0;
    final boolean hrValid = (flags & 0x02) != 0;

    runOnUiThread(() -> {
        // Update SpO2 display
        if (spo2Valid && spo2_u16 <= 100) {
            txtSpo2.setText("SpO2: " + spo2_u16 + "%");
        } else {
            txtSpo2.setText("SpO2: N/A");
        }

        // Update Heart Rate display
        if (hrValid && hr_x10_u16 < 0xFFFF) {
            float hr_bpm = hr_x10_u16 / 10.0f;
            txtHeartRate.setText(String.format(Locale.US, "HR: %.1f bpm", hr_bpm));
        } else {
            txtHeartRate.setText("HR: N/A");
        }

        // Update Battery display
        if (batt_pct <= 100) {
            txtBattery.setText("Battery: " + batt_pct + "%");
        } else {
            txtBattery.setText("Battery: N/A");
        }
    });
}
```

Complete Hot-Plug Support Matrix

Feature	IMU (ICM-20948)	SpO2 (MAX30105)	Status
Boot detection	10 retries × 500ms	Single attempt	Both OK
Recovery when missing	Every 5s	**Every 5s**	**Both complete**
Disconnection (sampling)	Per-sample check	**Retry timeout (100 attempts)**	**Both complete**
Disconnection (paused)	Periodic health check	**Periodic health check**	**Both complete**
Vitals invalidation	N/A	**Clears vitals on disconnect**	**Complete**
Graceful degradation	System continues	System continues	Both OK

Key Differences: IMU vs SpO2 Detection

Aspect	IMU	SpO2
Status field	`myICM.status` (explicit I2C error code)	No status field in MAX30105 library
Detection method	Check `myICM.status` after `getAGMT()`	Timeout counter (100 retries × 1ms)
Detection timing	Immediate (per-sample)	~100ms delay (timeout accumulation)
Task priority	Priority 2 (real-time)	Priority 0 (background)

Expected Behavior After Fixes

Scenario 1: Boot without SpO2 sensor

```
[Setup] Initializing MAX3010x...
[Setup] [WARN] MAX3010x not found; continuing without SpO2/HR.
[Android] SpO2: N/A, HR: N/A
```

Scenario 2: SpO2 sensor reconnected during session

```
[SpO2] Recovered! MAX30105 sensor reconnected.
[Vitals] SpO2=98 HR=72.0 Bright=0x1F IR=50000 RED=30000
[Android] SpO2: 98%, HR: 72.0 bpm
```

Scenario 3: SpO2 sensor disconnected mid-session

```
[Vitals] SpO2=98 HR=72.0 ...
[SpO2] Disconnected! Sensor not responding during sample collection.
[Vitals] SpO2=NA HR=NA ...
[Android] SpO2: N/A, HR: N/A  ← Immediate update (no stale values)
```

Changes Summary

Location	Change
Firmware: `spo2Task`	Added `lastRetryMs`, `lastHealthCheckMs` for hot-plug detection
Firmware: `spo2Task` recovery	Retry `maxSensor.begin()` every 5s when `!max3010xPresent`
Firmware: `spo2Task` health check	Periodic `maxSensor.check()` every 5s (runs even during normal operation)
Firmware: `spo2Task` disconnection	Timeout detection (100 retries) + **vitals invalidation**
Firmware: vitals invalidation	Set `spo2_u16 = 0xFFFF`, `hr_x10_u16 = 0xFFFF`, `flags = 0` on disconnect
Android: `decodeVitals()`	Extract SpO2, HR, battery from vitals frame
Android: `decodeVitals()`	Check validity flags before displaying
Android: `decodeVitals()`	Display "N/A" when flags are clear or values are 0xFFFF

Overhead Analysis

When SpO2 sensor missing:

```
I2C transactions: 1 per 5s (~200µs each)
Task wakeups: Every 1s (minimal CPU)
Total overhead: <0.01% CPU
```

When SpO2 sensor present:

```
Detection overhead: Zero (recovery logic skipped)
Normal operation: 25 Hz sampling, computation every ~30s
```

Design Consistency

Both IMU and SpO2 now follow the same hot-plug pattern:

Sensor	Presence Flag	Recovery Interval	Disconnection Detection	Vitals Handling
ICM-20948 (IMU)	`imuPresent`	5s	Per-sample I2C status check	N/A (no vitals)
MAX30105 (SpO2)	`max3010xPresent`	5s	Timeout (100 retries)	**Invalidate on disconnect**
MAX17048 (Battery)	`batteryAvailable`	N/A (no recovery)	N/A (assumed stable)	Report N/A if unavailable

Impact Analysis

What changed:

- SpO2 initialization: single attempt (unchanged)
- `spo2Task`: hot-plug detection when sensor missing (new)
- `spo2Task`: vitals invalidation on disconnection (new)
- Android `decodeVitals()`: extract and display SpO2/HR (new)

What didn't change:

- Protocol format (no version bump needed)
- Vitals frame structure (11 bytes, unchanged)
- EMG/IMU/battery operation (completely independent)
- Ring buffer sizing, task priorities, synchronization

No host-side decoder changes required (Python `btCentral.py` already handles vitals frames correctly).

2026 — Session 18c: Fix — IMU Disconnection Detection When Paused (Periodic Health Check)

Problem

After implementing hot-plug recovery (Session 18) and fixing the timer callback bug (Session 18b), disconnections were still not detected in one critical scenario:

When the IMU was disconnected BEFORE any BLE connection or BEFORE the host sent the first PING, the system continued showing `(IMU:OK)` indefinitely.

Root Cause: State-Dependent Detection

The disconnection detection code was only executed during active sampling:

```
// Only runs when NOT paused
if (!getSamplingPaused() && getImuTicks() > 0) {
  // ... read sensor
  if (myICM.status != ICM_20948_Stat_Ok) {
    imuPresent = false;  // ← Disconnection detected
  }
}
```

The problem: When `samplingPaused = true` (waiting for BLE connection or host PING), this code never runs, so disconnections go undetected.

Timeline of the bug:

1. System boots with IMU connected → `imuPresent = true`, `samplingPaused = true`
2. User disconnects IMU physically
3. No BLE connection yet → `samplingPaused` stays `true`
4. Disconnection detection code never runs → `imuPresent` stays `true`
5. Health report keeps showing `(IMU:OK)` even though sensor is gone

Fix: Periodic Health Check Independent of Sampling State

Added a periodic health check that runs **every 5 seconds regardless of `samplingPaused` state**:

```
void imuTask(void* /*param*/) {
  static uint32_t lastHealthCheckMs = 0;
  static constexpr uint32_t HEALTH_CHECK_INTERVAL_MS = 5000;

  for (;;) {
    // ... recovery logic when !imuPresent

    // NEW: Periodic health check (runs even when paused)
    uint32_t now = millis();
    if (now - lastHealthCheckMs >= HEALTH_CHECK_INTERVAL_MS) {
      lastHealthCheckMs = now;

      xSemaphoreTake(wireMutex, portMAX_DELAY);
      myICM.getAGMT();  // Try to read sensor
      bool sensorOk = (myICM.status == ICM_20948_Stat_Ok);
      xSemaphoreGive(wireMutex);

      if (!sensorOk) {
        imuPresent = false;
        Serial.println("[IMU] Disconnected! (health check).");
      }
    }

    // Normal sampling (only when not paused)
    if (!getSamplingPaused() && getImuTicks() > 0) {
      // ... existing code
    }
  }
}
```

Three-Layer Detection Strategy (Complete)

Layer	When	Interval	Purpose

Layer	When	Interval	Purpose
Boot detection	`setup()`	10 retries × 500ms	Non-blocking boot without IMU
Recovery detection	When `!imuPresent`	Every 5s	Auto-reconnect when sensor returns
Disconnection (sampling)	When actively sampling	Every 5ms (200 Hz)	Immediate detection during use
Disconnection (paused) ← NEW	When `samplingPaused`	Every 5s	Detection before/between sessions

Complete Test Matrix

Scenario	Detection Method	Latency	Status
Boot without IMU	Boot timeout	<5s	✅ Session 18
Disconnect before BLE connect	**Periodic health check**	**<5s**	✅ **Session 18c (NEW)**
Disconnect while paused (waiting for PING)	**Periodic health check**	**<5s**	✅ **Session 18c (NEW)**
Disconnect during active sampling	Per-sample check	<5ms	✅ Session 18b
Reconnect anytime	Recovery retry	<5s	✅ Session 18

Overhead Analysis

When paused (before connection or waiting for PING):

```
Health check: 1 I2C transaction per 5s (~200µs)
CPU overhead: <0.01%
Impact: Negligible
```

When actively sampling:

```
Health check: Still runs every 5s (redundant but harmless)
Per-sample check: Runs at 200 Hz (primary detection)
Total overhead: <0.02%
```

Why 5 Seconds?

Interval	Pros	Cons	Use Case
1 second	Fast detection	5× more I2C traffic	Development/testing
5 seconds ← chosen	Good balance	Slight delay	**Production**
10 seconds	Lowest overhead	Slow detection	Battery-constrained

Decision: 5 seconds matches the recovery retry interval, providing consistent behavior across all hot-plug scenarios.

Lessons Learned: State-Dependent Logic Pitfalls

This bug required **three iterations** to fix completely:

Session 18 (Initial): Implemented recovery when `!imuPresent`

- ❌ **Missed:** Disconnection detection when `imuPresent = true`

Session 18b (First fix): Added disconnection check during sampling

- ❌ **Missed:** Only runs when `!getSamplingPaused()`

Session 18c (Final fix): Added periodic health check independent of state

- ✅ **Complete:** Works in all states

Root Cause of Multiple Iterations

1. Incomplete State Analysis

- Initial implementation only considered the "sensor missing" state
- Didn't analyze all possible states: `{imuPresent, samplingPaused}` = 4 combinations
- Only tested 2 of 4 states during development

2. Conditional Logic Nesting

```
// Deeply nested conditions hide edge cases
if (imuPresent) {
  if (!getSamplingPaused()) {
    if (getImuTicks() > 0) {
      // Disconnection detection buried here
    }
  }
}
```

3. Testing Bias

- Tested "happy path": boot → connect → sample → disconnect → recover
- Didn't test "edge path": boot → disconnect → wait → connect

Design Principles for Robust State Machines

1. Enumerate All States Explicitly

```
State space: {imuPresent} × {samplingPaused} × {isConnected}
= 2 × 2 × 2 = 8 possible states

Test matrix: 8 states × 3 transitions (connect/disconnect/pause)
= 24 test cases minimum
```

2. Separate Concerns

```
// BAD: Detection logic depends on sampling state
if (!samplingPaused && imuPresent) {
  checkSensor();  // Only runs when sampling
}

// GOOD: Detection logic independent of sampling state
periodicHealthCheck();  // Always runs
if (!samplingPaused && imuPresent) {
  normalSampling();
}
```

3. Redundant Detection is Acceptable

- Health check runs every 5s even during active sampling
- Per-sample check runs every 5ms during sampling
- Redundancy ensures no edge case is missed
- Overhead is negligible (<0.02% CPU)

4. Test State Transitions, Not Just States

```
Test: Boot → Disconnect → Connect → Sample
Not just: Boot → Connect → Sample → Disconnect
```

5. Document State Dependencies

```
// BEFORE (implicit dependency):
if (getImuTicks() > 0) {
  // Disconnection check here
}

// AFTER (explicit documentation):
// Periodic health check (runs even when paused)
if (now - lastHealthCheckMs >= HEALTH_CHECK_INTERVAL_MS) {
  // Disconnection check here
}
```

Impact on System Reliability

Before Session 18c:

- Disconnections before BLE connection: **Not detected** (infinite stale state)
- User experience: Confusing (shows OK but no data)
- Workaround: Reboot device

After Session 18c:

- All disconnections: **Detected within 5 seconds**
- User experience: Clear status (`IMU:N/A`)
- Auto-recovery: Seamless when reconnected

Changes Summary

Location	Change
`imuTask`	Added `lastHealthCheckMs` and `HEALTH_CHECK_INTERVAL_MS`
`imuTask` main loop	Added periodic health check before sampling check
Health check	Calls `myICM.getAGMT()` and checks `myICM.status`
Health check	Sets `imuPresent = false` on I2C error
Health check	Runs **independently** of `samplingPaused` state

2026 — Session 18b: Fix — IMU Recovery Bug (Timer Callback Gating Issue)

Problem

After implementing hot-plug recovery in Session 18, the IMU sensor was detected successfully but **no IMU samples were being captured**. The health report showed:

```
[Health] ... IMUavail=0 (IMU:OK) ...
```

This meant:

- `imuPresent = true` ✅ (sensor detected and FSR configured)
- `IMUavail = 0` ❌ (zero samples in ring buffer)

Root Cause: Timer Callback Gating Logic

The IMU timer callback was checking `samplingPaused` and returning early without incrementing ticks:

```
// Before (buggy):
static void imu_timer_cb(void* /*arg*/) {
  if (getSamplingPaused()) return;  // ← Bug: no ticks when paused
  incrementImuTicks();
}
```

The problem: When `samplingPaused` is true (waiting for host PING), the timer generates **zero ticks**. Even after the IMU recovers (`imuPresent = true`), `imuTask` never gets any ticks to process, so it can't read the sensor!

Why this happened:

1. System boots → `samplingPaused = true` (waiting for host)
2. IMU recovery detects sensor → `imuPresent = true`
3. Host sends PING → `samplingPaused = false`
4. BUT: Timer callback was gating tick generation based on `samplingPaused`
5. Result: `imuTask` checks `getImuTicks() > 0` but always sees 0

Fix: Move Sampling Check from Timer to Task

Changed timer callback to always generate ticks:

```
// After (fixed):
static void imu_timer_cb(void* /*arg*/) {
  // Always increment ticks - imuTask will check samplingPaused
  incrementImuTicks();
}
```

Changed imuTask to check samplingPaused before consuming ticks:

```
// Before:
if (getImuTicks() > 0) {
  decrementImuTicks();
  // ... read IMU sensor
}

// After:
if (!getSamplingPaused() && getImuTicks() > 0) {
  decrementImuTicks();
  // ... read IMU sensor
}
```

Why This Fix Is Correct

Timer callback (200 Hz, Core 0 esp_timer task):

- Always generates ticks at 200 Hz
- No conditional logic
- Minimal overhead (~1 µs per tick)

imuTask (Core 1, priority 2):

- Checks `samplingPaused` before processing ticks
- When paused: ticks accumulate but are not consumed
- When resumed: immediately starts processing accumulated ticks

Benefits:

1. ✅ IMU recovery works immediately when sampling resumes
2. ✅ No lost ticks during pause (they accumulate harmlessly)
3. ✅ Consistent with EMG behavior (ADC DMA runs independently, `emgDrainTask` checks `samplingPaused`)
4. ✅ Simpler logic (timer just counts, task decides when to act)

Expected Behavior After Fix

Before fix (broken recovery):

```
[Health] ... IMUavail=0 (IMU:OK) ...  ← Sensor detected but not sampling
```

After fix (working recovery):

```
[IMU] Recovered! Set FSR: acc=+/- 4g, gyro=+/- 1000dps
[Health] ... IMUavail=42 (IMU:OK) ...  ← Samples flowing!
```

Changes Summary

Location	Before	After
`imu_timer_cb()`	`if (getSamplingPaused()) return;`	Removed check — always increment ticks
`imuTask` tick processing	`if (getImuTicks() > 0)`	`if (!getSamplingPaused() && getImuTicks() > 0)`

Impact Analysis

What changed:

- Timer callback: always generates ticks (was conditional)
- imuTask: checks `samplingPaused` before consuming ticks (was unchecked)

What didn't change:

- Tick generation rate: still 200 Hz
- IMU sampling rate: still 200 Hz when active
- Ring buffer, protocol, BLE transmission: unchanged
- Hot-plug detection logic: unchanged

Overhead when paused:

- Timer callback: ~1 µs per tick × 200 Hz = 0.02% CPU (negligible)
- Accumulated ticks: cleared on resume via `clearImuTicks()` in `loop()`

Lesson Learned

Design principle: Timers should generate events unconditionally. Tasks should decide whether to act on those events based on system state.

Why this is better:

- Separates concerns (timing vs. control flow)
- Avoids state-dependent timer behavior
- Makes recovery scenarios simpler (no need to "restart" the timer)
- Consistent with DMA-based EMG sampling (hardware runs independently)

2026 — Session 18: Feature — IMU Graceful Degradation + Hot-Plug Auto-Recovery

Problem

The firmware blocked indefinitely at startup if the ICM-20948 IMU sensor was missing or disconnected:

```
// Before (infinite retry loop):
while (myICM.status != ICM_20948_Stat_Ok) {
  myICM.begin(Wire, AD0_VAL);
  delay(500);
}
```

This prevented the system from booting when:

- IMU sensor physically disconnected (loose cable, hardware failure)
- I2C address conflict or bus error
- Sensor not yet powered on during development/testing

Impact: System unusable without IMU, even though EMG/SpO2/battery could still function.

Solution: Graceful Degradation with Hot-Plug Support

Implemented a three-part strategy:

1. Timeout-Based Initialization (Non-Blocking Boot)

```
// After (10 retries × 500ms = 5 seconds max):
int imuRetries = 10;
while (imuRetries > 0) {
  myICM.begin(Wire, AD0_VAL);
  if (myICM.status == ICM_20948_Stat_Ok) {
    imuPresent = true;
    break;
  }
  imuRetries--;
  if (imuRetries > 0) delay(500);
}
if (!imuPresent) {
  Serial.println("[WARN] IMU not found; continuing without motion data.");
}
```

Benefits:

- System boots in <10 seconds even with missing IMU
- Clear diagnostic message for troubleshooting
- Other sensors (EMG, SpO2, battery) remain operational

2. Hot-Plug Detection & Auto-Recovery

```
void imuTask(void* /*param*/) {
  static uint32_t lastRetryMs = 0;
  static constexpr uint32_t RETRY_INTERVAL_MS = 5000;  // Retry every 5 seconds

  for (;;) {
    if (!imuPresent) {
      uint32_t now = millis();
      if (now - lastRetryMs >= RETRY_INTERVAL_MS) {
        lastRetryMs = now;

        xSemaphoreTake(wireMutex, portMAX_DELAY);
        myICM.begin(Wire, AD0_VAL);
        bool recovered = (myICM.status == ICM_20948_Stat_Ok);
        xSemaphoreGive(wireMutex);

        if (recovered) {
          // Configure FSR on recovery
          imuPresent = true;
          Serial.printf("[IMU] Recovered! Set FSR: acc=+/- %ug, gyro=+/- %udps\n",
                        IMU_ACC_FSR_G, IMU_GYRO_FSR_DPS);
        }
      }
      vTaskDelay(1000 / portTICK_PERIOD_MS);
      continue;
    }

    // Normal 200 Hz operation when IMU present...
  }
}
```

Recovery Characteristics:

- **Detection interval:** 5 seconds (configurable via `RETRY_INTERVAL_MS`)
- **Overhead when missing:** <0.01% CPU (1 I2C transaction per 5s)
- **Overhead when present:** Zero (no retry logic executes)
- **Seamless recovery:** No reboot or manual intervention required

3. Conditional Data Transmission

```
// Only send IMU frames if sensor present
if (imuPresent) {
  static uint32_t lastImuSendMs = 0;
  if (nowMs - lastImuSendMs >= 20 && emg_available() < EMG_BUF_SIZE * 3 / 4) {
    lastImuSendMs = nowMs;
    sent |= send_imu_frame(maxNotifyPayload);
  }
}
```

Benefits:

- No bandwidth waste on dummy data
- No protocol changes needed
- Host decoder already handles missing TLV types gracefully

Design Options Considered

Option 1: Skip Missing Sensor Data (Implemented)

```
if (imuPresent) {
  sent |= send_imu_frame(maxNotifyPayload);
}
```

Pros:

- ✅ No bandwidth waste on dummy data
- ✅ No protocol changes needed
- ✅ Host decoder already handles missing TLV types
- ✅ Clear signal to host (missing TLV = sensor unavailable)

Cons:

- ⚠️ Host must handle variable data streams

Option 2: Send Zero/Stale Values (Not Implemented)

```
ImuSample lastGood = {0};
if (!imuPresent) {
  s = lastGood;  // Use stale/zero data
}
imu_push(s);
```

Pros:

- ✅ Consistent data stream (always has IMU frames)
- ✅ Easier to detect mid-session disconnections

Cons:

- ❌ Wastes bandwidth on dummy data
- ❌ Host must detect "stuck at zero" pattern
- ❌ Ambiguous (zeros could be valid data)

Option 3: Status Flag in Protocol (Not Implemented)

```
uint8_t sensorStatus = 0;
if (imuPresent) sensorStatus |= 0x01;
if (max3010xPresent) sensorStatus |= 0x02;
```

Pros:

- ✅ Explicit status reporting
- ✅ Host knows exactly what's available

Cons:

- ❌ Requires protocol version bump
- ❌ Requires decoder changes
- ❌ Unnecessary complexity for current use case

Decision Rationale: Option 1 chosen for simplicity, no host changes required, and consistency with existing SpO2/battery handling.

Status Reporting

Health Report Format:

```
// Before:
[Health] MTU=247 EMGavail=0 IMUavail=0 EMGdrop=0 IMUdrop=0 ...

// After:
[Health] MTU=247 EMGavail=0 IMUavail=0 (IMU:N/A) EMGdrop=0 IMUdrop=0 ...
[Health] MTU=247 EMGavail=128 IMUavail=42 (IMU:OK) EMGdrop=0 IMUdrop=0 ...
```

Sensor Status Indicators:

- `(IMU:OK)` - Sensor present and operational
- `(IMU:N/A)` - Sensor missing or failed initialization

Recovery Scenarios

Scenario 1: IMU Disconnected at Startup

```
[Setup] Initializing IMU...
[Setup] IMU init retry...
[Setup] [WARN] IMU not found; continuing without motion data.
[BLE] Connected. MTU=247
[Health] ... (IMU:N/A) ...
[imuTask] Retrying every 5s...
```

Scenario 2: IMU Reconnected During Session

```
[Health] ... (IMU:N/A) ...
[imuTask] Attempting recovery...
[IMU] Recovered! Set FSR: acc=+/- 4g, gyro=+/- 1000dps
[Health] ... (IMU:OK) ...
[BLE] Sending IMU frames...
```

Scenario 3: IMU Disconnected Mid-Session

- Current implementation: No detection (sensor assumed stable once initialized)
- Future enhancement: Add periodic health checks during normal operation

Changes Summary

Location	Before	After
Global	(no flag)	`static bool imuPresent = false;`
`setup()` IMU init	Infinite retry loop	10-retry timeout (5 seconds max)
`imuTask`	Assumes IMU always present	Hot-plug detection every 5s when missing
`loop()` TX	Always sends IMU frames	Conditional: `if (imuPresent)`
`[Health]` report	No IMU status	`(IMU:OK)` or `(IMU:N/A)`

Overhead Analysis

When IMU missing:

```
I2C transactions: 1 per 5s (~200µs each)
Task wakeups: Every 1s (minimal CPU)
Total overhead: <0.01% CPU
```

When IMU present:

```
Detection overhead: Zero
Normal operation: 200 Hz polling
```

Retry Interval Trade-offs

Interval	Recovery Speed	Overhead	Use Case
1 second	Fast	5× more I2C traffic	Development/testing
5 seconds ← current	Good balance	Minimal	**Production**
10 seconds	Slow	Lowest	Battery-constrained

Decision: 5 seconds chosen as good balance between recovery speed and overhead.

Consistency with Other Sensors

This implementation follows the same pattern as existing sensors:

Sensor	Presence Flag	Initialization	Behavior When Missing
ICM-20948 (IMU)	`imuPresent`	Timeout-based, hot-plug retry	Skip IMU frames
MAX30105 (SpO2)	`max3010xPresent`	Single attempt	Skip vitals frames
MAX17048 (Battery)	`batteryAvailable`	Single attempt	Report N/A in vitals

Future Enhancements

1. **Configurable retry intervals** - Allow user to tune recovery speed vs overhead
2. **Mid-session health checks** - Detect sensor disconnections during operation
3. **Exponential backoff** - Reduce retry frequency after prolonged failures
4. **Event-driven detection** - Use I2C bus interrupts instead of polling

Impact Analysis

What changed:

- IMU initialization: timeout-based instead of infinite retry
- `imuTask`: hot-plug detection when sensor missing
- BLE TX: conditional IMU frame transmission
- Health report: IMU status indicator

What didn't change:

- Protocol format (no version bump needed)
- Host decoder (already handles missing TLV types)
- EMG/SpO2/battery operation (completely independent)
- Ring buffer sizing, task priorities, synchronization

No host-side changes required.

2026 — Session 17: Fix — ADC Continuous Minimum Frequency Violation (Oversampling + Decimation)

Problem

The firmware aborted at startup with:

```
E (66921) adc_continuous: adc_continuous_config(477): ADC sampling frequency out of range
ESP_ERR_INVALID_ARG at void emg_adc_init()
```

The ESP32 ADC continuous driver (IDF 5.x) enforces a **minimum `sample_freq_hz` of ~20,000 Hz**. The previous configuration used:

```
static constexpr uint32_t ADC_CONV_FREQ_HZ = EMG_RATE_HZ * 2;  // 4000 conv/s
```

4,000 Hz is far below the hardware floor, causing an unconditional abort inside `adc_continuous_config()` every time `emg_adc_init()` was called (i.e. on every host PING after BLE connect).

Root Cause

The IDF 5.x ADC continuous driver requires the total conversion frequency to be at least ~20 kHz regardless of the number of channels. This limit is not enforced at compile time — it only fires at runtime inside `adc_continuous_config()`, which is why it was not caught during earlier sessions that did not exercise the host-PING → `emg_adc_init()` path.

Fix: Oversampling + Decimation

Raised `ADC_CONV_FREQ_HZ` to 40,000 Hz (20 kHz per channel × 2 channels) by introducing an `ADC_OVERSAMPLE` factor of 10:

```
// Before (aborts at runtime):
static constexpr uint32_t ADC_CONV_FREQ_HZ = EMG_RATE_HZ * 2;  // 4000 — below minimum!

// After:
static constexpr uint32_t ADC_OVERSAMPLE   = 10;
static constexpr uint32_t ADC_CONV_FREQ_HZ = EMG_RATE_HZ * 2 * ADC_OVERSAMPLE; // 40000
```

`emgDrainTask` was updated to accumulate `ADC_OVERSAMPLE` (10) raw readings per channel into running sums (`envAcc`, `rawAcc`), then divide and emit one `EmgSample` when both accumulators are full:

```
ADC DMA: 40,000 conv/s total
  → 20,000 conv/s per channel (ENV, RAW)
  → accumulate 10 readings per channel
  → emit 1 decimated sample per channel pair
  → output: 2,000 EmgSamples/s  ✓  (EMG_RATE_HZ unchanged)
```

Side Effect: Noise Reduction

Averaging 10 raw ADC readings reduces quantization noise by $\sqrt{10} \approx 3.16\times$, gaining approximately 1.5 effective bits of resolution at no extra cost.

Removed: `emgChOrderViolations`

The old pairing logic required strict ENV/RAW alternation and counted violations when two consecutive same-channel results arrived. The new accumulator approach counts each channel independently — strict ordering is no longer required — so the violation counter was removed entirely:

- `static volatile uint32_t emgChOrderViolations` — deleted
- Reset in `onConnect()` under `emgMux` — removed
- `EMGchViol=N` field in `[Health]` report — removed

Changes Summary

Location	Before	After
`ADC_CONV_FREQ_HZ`	`EMG_RATE_HZ * 2 = 4000`	`EMG_RATE_HZ * 2 * 10 = 40000`
`ADC_OVERSAMPLE`	(not present)	`10`
`emgDrainTask` accumulators	`envValid/rawValid` bool pair	`envAcc/rawAcc` uint32 sums + `envCount/rawCount`
`emgDrainTask` emit condition	both bools true (one reading each)	both counts ≥ `ADC_OVERSAMPLE`
`emgChOrderViolations`	present, printed in `[Health]`	removed
`[Health]` report	`EMGchViol=N` field	field removed
DMA frame coverage	~16 ms at 4 kHz	~1.6 ms at 40 kHz
Effective ADC resolution	12-bit raw	~13.5-bit (1.5 bits gained via averaging)

Verification

- `ADC_CONV_FREQ_HZ = 40000` is well above the ~20 kHz minimum floor
- Output rate: 40000 / 2 channels / 10 oversample = **2000 Hz** = `EMG_RATE_HZ` ✓
- `ADC_FRAME_SIZE = 256` bytes = 64 results; at 40 kHz this covers 1.6 ms per frame (down from 16 ms at 4 kHz) — also reduces timestamp back-calculation error
- No protocol changes; `EmgSample` struct, ring buffer, and `send_emg_frame()` unchanged

Impact Analysis — What Changed vs. What Didn't

EMG output rate: still exactly 2000 Hz. The oversampling is entirely internal to `emgDrainTask`.

Layer	Before	After
ADC hardware clock	4,000 conv/s total	40,000 conv/s total
Per-channel ADC rate	2,000 raw readings/s	20,000 raw readings/s
`emgDrainTask` emit rate	1 pair per ENV+RAW	1 averaged pair per 10 ENV + 10 RAW
`EmgSample` output rate	2,000/s	**2,000/s** ← unchanged
`EmgSample.env` / `.raw` values	single 12-bit ADC reading	mean of 10 readings (still fits `uint16_t`, same 0–4095 range)

Completely unaffected:

- `EMG_RATE_HZ = 2000` — unchanged; still transmitted in every `TLV_EMG_BATCH` frame as the `rate` field
- `send_emg_frame()` — unchanged; still batches `EmgSample` structs and writes `EMG_RATE_HZ` into the wire format
- Protocol / decoder — `btCentral.py` reads `emg_rate_hz` from the frame, gets 2000, nothing changes
- Ring buffer sizing (`EMG_BUF_SIZE = 2048`) — sized for 2000 Hz output, still correct
- Backlog threshold (`EMG_BACKLOG_PAUSE_THRESH = 1800`) — still ~0.9 s of output samples, still correct
- `EMG_PERIOD_US` — was only used by the old software timer (removed in Session 1), not present in current code
- Timestamp back-calculation — `US_PER_CONV = 1e6 / ADC_CONV_FREQ_HZ` is now `25 µs` instead of `250 µs`, which is **more accurate** (smaller per-result age correction)

One subtle behavioural change — sample values are now averages: The `env` and `raw` fields in each `EmgSample` are the **mean of 10 ADC readings** rather than a single reading. Values remain `uint16_t` in the 0–4095 range. The Python decoder, CSV format, and all downstream analysis are unaffected — they treat these as raw ADC counts regardless.

Nothing outside the firmware needs to change.

2026 — Session 16: IMU FSR raised — gyro 250→1000 dps, acc 2→4 g (anti-saturation)

Problem

Tennis swings saturated both IMU axes at the previous FSR settings:

Axis	FSR	Saturation limit	Observed median	Status
Gyro	250 dps	±32767 LSB = ±250 dps	Clipped on every hard swing	❌ Saturated
Acc	2 g	±32767 LSB = ±2 g	`imu_peak_acc_dyn` median = 2.464g	❌ Saturated

Gyro saturation clipped `gx/gy/gz` at ±32767 on every hard swing, making gyro-based swing detection unreliable. The `peak_mag` and `swing_acc_drop_pct` fatigue indicators were computed from clipped data.

Acc saturation caused `imu_peak_acc_dyn` to hit the 2g ceiling on most swings, preventing meaningful per-swing force tracking.

Fix

```
// Before (saturated):
static constexpr uint8_t  IMU_ACC_FSR_G     = 2;    // saturated at 2g
static constexpr uint16_t IMU_GYRO_FSR_DPS  = 250;  // saturated on every hard swing

// After:
static constexpr uint8_t  IMU_ACC_FSR_G     = 4;    // covers 2-4g tennis swing range
static constexpr uint16_t IMU_GYRO_FSR_DPS  = 1000; // covers 500-1000 dps tennis swing range
```

Why these values:

- Gyro 1000 dps: tennis swings peak at ~500–1000 dps. Stays in linear range. Resolution: 32.8 LSB/dps (vs 131.0 at 250 dps) — still more than sufficient.
- Acc 4g: doubles the range from 2g. Resolution: 8192 LSB/g (vs 16384 at 2g). `imu_mean_acc_dyn` (mean `|acc_mag - 1g|`) will no longer saturate.

Self-Describing Protocol — No Decoder Changes Needed

Both FSR codes are transmitted in every IMU meta frame (`FLAG_IMU_META_V2`):

```
*p++ = accFsrToCode(IMU_ACC_FSR_G);   // 1 = 4g
*p++ = gyroFsrToCode(IMU_GYRO_FSR_DPS); // 2 = 1000 dps
```

`btCentral.py` and `btcentral_offline_decode.py` decode these codes and write `acc_fsr_g=4`, `gyro_fsr_dps=1000` per row in the CSV. `capture_loader.py` reads per-row FSR for physical-unit conversion. No decoder changes needed.

Companion Changes (Python side)

Fallback defaults updated to match new firmware (used for old captures without FSR meta):

- `btCentral.py`: `cur_acc_fsr_g = 4`, `cur_gyro_fsr_dps = 1000`
- `emg_util/capture_loader.py`: `acc_fsr_default_g=4.0`, `gyro_fsr_default_dps=1000.0`
- `emg_util/config.yaml`, `config_fast.yaml`: same
- `emg_util/tennis_analysis_cloud.ipynb` CLOUD_CONFIG: same

IMU FSR Lookup Table (Reference)

Code	Acc FSR	LSB/g	Gyro FSR	LSB/dps
0	2g	16384	250 dps	131.0
1	**4g** ← new	**8192**	500 dps	65.5
2	8g	4096	**1000 dps** ← new	**32.8**
3	16g	2048	2000 dps	16.4

2025 — Session 15: Fix — Inconsistent `samplingPaused` Write in `onConnect()`

Problem

The comment on line 489 in `onConnect()` was incorrect:

```
samplingPaused = true;  // direct assign OK here — BLE callback runs before tasks start
```

The comment is wrong because:

- `onConnect()` is called when a BLE client connects **AFTER** `setup()` completes
- Tasks (`emgDrainTask`, `imuTask`, `spo2Task`) are already running at this point
- `emgDrainTask` on Core 1 is actively reading `samplingPaused` via `getSamplingPaused()`

The inconsistency:

- `onDisconnect()` line 498 uses `setSamplingPaused(true)` (atomic with memory barrier)
- `onConnect()` line 489 uses direct assign `samplingPaused = true` (no memory barrier)

Why it hasn't caused a visible bug:

- `onConnect()` sets `samplingPaused = true` (pausing), which is the safe direction
- The ADC DMA hasn't been started yet (it starts only after the first PING in `loop()`)
- `emgDrainTask` checks `getSamplingPaused()` first thing in its loop, and if true, it just sleeps for 5ms
- So even if Core 1 sees a stale `false` value briefly, it will just do one extra iteration before seeing the updated `true`

But it's still wrong — it violates the documented pattern and could theoretically cause a race.

Fix

Changed `onConnect()` line 489 to use `setSamplingPaused(true)` (atomic write with memory barrier), matching the pattern used in `onDisconnect()` and all other cross-core writes to `samplingPaused`.

```
// Before:
samplingPaused = true;  // direct assign OK here — BLE callback runs before tasks start

// After:
setSamplingPaused(true);  // atomic write — emgDrainTask on Core 1 reads this
```

This ensures consistent use of atomic accessors for all cross-core access to `samplingPaused`.

Verification of Other Cross-Core Variables

All other cross-core accesses were reviewed and confirmed correct:

Variable	Writer	Reader	Protection	Status
`samplingPaused`	Core 0 (`loop`, BLE callbacks)	Core 1 (`emgDrainTask`, `imuTask`)	`setSamplingPaused()` / `getSamplingPaused()` (atomic)	✅ Fixed
`imu_ticks`	Core 0 (`imu_timer_cb` task)	Core 1 (`imuTask`)	`volatile` + 32-bit atomic writes	✅ Acceptable (lost ticks OK)
`ledBrightness`	Core 1 (`spo2Task`)	Core 0 (`send_vitals_frame`)	8-bit atomic reads/writes	✅ Acceptable (non-critical display value)
`lastBatteryPct` / `lastBatteryVoltage`	Core 0 (`readBattery`)	Core 0 (`printBatteryStatus`, LED check)	Same core	✅ No issue
`lastBatteryReadMs` / `batteryInitialReadDone`	Core 0 (`send_vitals_frame`)	Core 0 (`printBatteryStatus`)	Same core	✅ No issue
`isConnected`	Core 0 (BLE callbacks)	Core 0 (`loop`)	Same core	✅ No issue
`negotiatedMTU` / `maxNotifyPayload`	Core 0 (`onConnect`)	Core 0 (`loop`)	Same core	✅ No issue
`frameSeq`	Core 0 (`loop`)	Core 0 (`loop`)	Same core	✅ No issue
`emgSeq` / `imuSeq` / `emgDropped` / `imuDropped`	Core 0 (`onConnect`) / Core 1 (tasks)	Both cores	`emgMux` / `imuMux` spinlocks	✅ Correct (Session 5)
`emgChOrderViolations`	~~removed in Session 17~~	—	—	✅ N/A (oversampling accumulator does not require strict channel ordering)

2025 — Session 14: Analysis — `getSamplingPaused()` in `imu_timer_cb` (Safe from ESP32 `esp_timer` Task Context)

Concern Raised

> `imu_timer_cb` is an `esp_timer` callback. Is it safe to call `getSamplingPaused()` (which uses `__atomic_load_n`) from this context?

Analysis: Safe — `esp_timer` Callbacks Run in Task Context, Not Hardware ISR

The relevant code:

```
// Line 447-450
static void imu_timer_cb(void* /*arg*/) {
  if (getSamplingPaused()) return;
  imu_ticks++;
}

static inline bool getSamplingPaused() {
  return __atomic_load_n(&samplingPaused, __ATOMIC_ACQUIRE);
}
```

Key fact: On ESP32, `esp_timer` callbacks are **not hardware ISRs**. They run in a dedicated FreeRTOS task (`esp_timer` task) at priority 22 (configurable). This is explicitly configured in `setup()` line 1210:

```
esp_timer_create_args_t imuArgs = {
  .callback = &imu_timer_cb,
  .arg = nullptr,
  .dispatch_method = ESP_TIMER_TASK,  // ← Runs in task context
  .name = "imu_timer"
};
```

The `ESP_TIMER_TASK` dispatch method guarantees the callback runs in the `esp_timer` task, not in a hardware interrupt. This means:

1. **`__atomic_load_n` is safe** — GCC atomic built-ins are safe from any context (task or ISR)
2. **`__ATOMIC_ACQUIRE` memory ordering is correct** — ensures cross-core visibility of `samplingPaused` writes from Core 0 to reads on Core 1
3. **`imu_ticks++` is safe** — 32-bit aligned writes are atomic on Xtensa LX6; `volatile` prevents compiler reordering

What Would Be Unsafe (If This Were a Hardware ISR)

If `esp_timer` callbacks were hardware ISRs (they're not), the following would be unsafe:

Operation	Safe in hardware ISR?	Safe in `esp_timer` task?
`xSemaphoreTake()`	❌ No — would crash	✅ Yes
`portENTER_CRITICAL()`	⚠️ Only with `_ISR` variant	✅ Yes
`__atomic_load_n()`	✅ Yes	✅ Yes
`vTaskDelay()`	❌ No — would crash	✅ Yes

But since `esp_timer` callbacks run in task context, all FreeRTOS APIs are safe to use (within reason — long-running operations would delay other timer callbacks).

Conclusion

No code change required. `getSamplingPaused()` is safe to call from `imu_timer_cb` because:

1. `esp_timer` callbacks run in the `esp_timer` FreeRTOS task, not a hardware ISR
2. `__atomic_load_n` is safe from any context (task or ISR)
3. The `__ATOMIC_ACQUIRE` memory ordering ensures cross-core visibility of `samplingPaused`

The current implementation is correct.

2025 — Session 13: Analysis — `adcMutex` Held for 10 ms During `adc_continuous_read()` (Not a Bug)

Concern Raised

> `emgDrainTask` holds `adcMutex` for the full duration of `adc_continuous_read()`, which has a 10 ms timeout. Does this block `emg_adc_deinit()` for too long?

Analysis: 10 ms Hold Is Bounded, Intentional, and Acceptable

The relevant code:

```
// emgDrainTask (Core 1)
esp_err_t ret = adc_continuous_read(adcHandle, dmaBuf, ADC_FRAME_SIZE, &bytesRead, 10);
xSemaphoreGive(adcMutex);  // release immediately after read

// emg_adc_deinit() (Core 0)
xSemaphoreTake(adcMutex, portMAX_DELAY);  // waits up to 10 ms
adc_continuous_stop(adcHandle);
adc_continuous_deinit(adcHandle);
adcHandle = nullptr;
xSemaphoreGive(adcMutex);
```

Maximum blocking time for `emg_adc_deinit()`: 10 ms (one `adc_continuous_read` timeout).

All three `emg_adc_deinit()` call sites:

Call site	Context	10 ms delay acceptable?
`onDisconnect()` line 509	BLE callback, Core 0	✅ Yes — disconnect is not time-critical
`loop()` disconnect branch line 1264	Core 0 task	✅ Yes — `loop()` runs at ~1 kHz, 10 ms is one iteration
`loop()` host-absent branch line 1274	Core 0 task	✅ Yes — triggered after 5 s silence, 10 ms is negligible

None of the deinit call sites have a hard real-time deadline. A 10 ms wait is indistinguishable from normal `loop()` jitter in all three cases.

Why `portMAX_DELAY` in `emg_adc_deinit()` Is Correct

Using `portMAX_DELAY` in `deinit` (rather than a timeout) is intentional:

- `deinit` **must** complete — a partial deinit leaving `adcHandle` non-null would cause `emg_adc_init()` to skip re-initialisation on the next resume.
- The maximum wait is bounded at 10 ms by the `adc_continuous_read` timeout in `emgDrainTask`, so `portMAX_DELAY` never actually waits indefinitely.

Why the Mutex Is Held Across the Full `adc_continuous_read()` Call

Releasing the mutex before `adc_continuous_read()` returns would create a window where `emg_adc_deinit()` could free `adcHandle` while `adc_continuous_read()` is still using it — the exact crash scenario Session 2 was designed to prevent. The 10 ms hold is the minimum necessary to close that window.

Conclusion

No code change required. The 10 ms mutex hold is bounded, intentional, and acceptable at all call sites. `portMAX_DELAY` in `deinit` is safe because the maximum wait is bounded by the `adc_continuous_read` timeout.

Concern Raised

> `spo2Task` (priority 0) holds `wireMutex` during I2C reads. `imuTask` (priority 2) blocks waiting for it. Classic priority inversion — is this handled?

Analysis: FreeRTOS Priority Inheritance Covers This

`wireMutex` is created with `xSemaphoreCreateMutex()` (line 1210), which is the FreeRTOS **mutex with priority inheritance** — not `xSemaphoreCreateBinary()` (no inheritance) or `xSemaphoreCreateRecursiveMutex()` (recursive, different semantics).

When `imuTask` (priority 2) blocks on `wireMutex` held by `spo2Task` (priority 0), FreeRTOS automatically raises `spo2Task`'s effective priority to 2 for the duration of the lock hold. This ensures `spo2Task` is scheduled promptly to release the mutex, preventing `imuTask` from being indefinitely delayed by any lower-priority task.

```
Normal case (no contention):
  spo2Task (pri 0) holds wireMutex → runs at pri 0
  imuTask  (pri 2) not blocked     → preempts freely

Priority inversion window:
  spo2Task (pri 0) holds wireMutex
  imuTask  (pri 2) blocks on wireMutex
  FreeRTOS: spo2Task temporarily raised to pri 2
  spo2Task completes I2C, releases wireMutex
  FreeRTOS: spo2Task restored to pri 0
  imuTask  (pri 2) acquires wireMutex, proceeds
```

Worst-Case Blocking Time for `imuTask`

`spo2Task` holds `wireMutex` for one I2C transaction at a time:

- `maxSensor.check()` — one I2C read, ~100–400 µs at 400 kHz
- `maxSensor.getRed/getIR/nextSample()` — one batch, ~200–500 µs
- `configureMax3010x()` — multi-register write, ~500–800 µs (rare)

`imuTask` budget per tick: 5 ms (200 Hz). Worst-case I2C hold ~800 µs. Blocking time is well within the 5 ms budget even without priority inheritance.

Why `adcMutex` Does Not Have This Issue

`emgDrainTask` (priority 2) holds `adcMutex` only during `adc_continuous_read()`, which is called with a 10 ms timeout. `loop()` (Core 0) calls `emg_adc_deinit()` which takes `adcMutex` — but `loop()` and `emgDrainTask` are on **different cores**, so this is cross-core mutex contention, not priority inversion (different scheduler domains on ESP32 dual-core).

Conclusion

No code change required. `xSemaphoreCreateMutex()` provides priority inheritance. Worst-case blocking time for `imuTask` is ~800 µs, well within the 5 ms tick budget.

Concern Raised

> `readBattery()` uses `if (wireMutex) xSemaphoreTake(...)` — is the conditional guard necessary, and could it mask a real bug?

Analysis: Guard Is Defensive Dead-Code, Correct As-Is

`readBattery()` is called from exactly **one** site:

Call site	Context	`wireMutex` state
`send_vitals_frame()` line 952	`loop()` task, Core 0	Always non-null (created in `setup()` before tasks start)

The two other historical call sites no longer exist:

- `printBatteryStatus()` — rewritten in Session 9 to use cached values; no longer calls `readBattery()`
- `setup()` initial read — calls `lipo.getSOC()` / `lipo.getVoltage()` **directly**, not through `readBattery()`

The `setup()` direct calls are correct: they run before `wireMutex` is created and before any tasks start, so there is no contention and no mutex is needed.

`readBattery()` itself is only reachable after `setup()` completes (via `loop()`), at which point `wireMutex` is guaranteed non-null. The `if (wireMutex)` guard is therefore defensive dead-code — it can never be false in practice.

Why Keep the Guard

It costs nothing (one pointer comparison). It prevents a hard fault if `readBattery()` is ever called from a new code path before `setup()` completes — e.g. during future refactoring. It is consistent with the comment on `emg_adc_init()` which has the same pattern (`if (!adcMutex) return`).

Conclusion

No code change required. The guard is correct and intentional.

Concern Raised

> `wireMutex` is created after `BLEDevice::startAdvertising()`. Could a BLE callback fire before `wireMutex` exists and try to take it?

Analysis: Order Is Correct

The `setup()` sequence is:

```
Wire.begin() + sensor inits     ← single-threaded, no mutex needed
BLEDevice::init / startAdvertising  ← BLE stack starts here
adcMutex  = xSemaphoreCreateMutex() ← created
wireMutex = xSemaphoreCreateMutex() ← created
configASSERT(both)              ← verified non-null
esp_timer_create/start          ← imu_timer_cb only touches imu_ticks, no mutex
xTaskCreatePinnedToCore × 3    ← tasks start AFTER mutexes exist
```

`BLEDevice::startAdvertising()` does start the BLE stack before the mutexes are created. However, the BLE callbacks that use `wireMutex` are:

- `onConnect()` — uses `emgMux` / `imuMux` spinlocks only, **not** `wireMutex`
- `onDisconnect()` — calls `emg_adc_deinit()`, uses `adcMutex` only
- `onWrite()` (RxCallbacks) — uses `hostMux` spinlock only

`wireMutex` is only taken in:

- `readBattery()` — called from `send_vitals_frame()` in `loop()` (Core 0 task)
- `imuTask` — FreeRTOS task
- `spo2Task` — FreeRTOS task

All three are FreeRTOS tasks created **after** `wireMutex` exists. No BLE callback ever calls `xSemaphoreTake(wireMutex, ...)`, so there is no window where a BLE callback could race against `wireMutex` being null.

`readBattery()` has an explicit null guard: `if (wireMutex) xSemaphoreTake(...)` — this would safely skip the lock if somehow called before init, but that path does not exist in practice.

Conclusion

No code change required. Mutex creation order is correct and safe.

Problem

`printBatteryStatus()` called `readBattery()` unconditionally on every call, which is invoked from the `[Health]` debug report every 1 second. `readBattery()` performs 4 live I2C transactions (`getSOC`, `getVoltage`, `getChangeRate`, `isLow`) — ~400 µs of I2C bus time added to `loop()` every second, and an unnecessary contention point on `wireMutex` shared with `imuTask` and `spo2Task`.

The cached values `lastBatteryPct` and `lastBatteryVoltage` are already maintained by `send_vitals_frame()` (refreshed every `BATTERY_READ_INTERVAL_MS` = 10 s) and by `setup()` (initial read). They are always available for a serial debug print.

Fix

Rewritten `printBatteryStatus()` to use `lastBatteryPct` / `lastBatteryVoltage` directly. No I2C. No `wireMutex`. Added `age=Ns` field showing seconds since last real read, so the output remains honest about data freshness.

```
// Before (every 1 s):
[Battery] 87.3% (3.92V) +0.1%/hr
  └─ 4 live I2C reads, ~400 µs, wireMutex contention

// After (every 1 s):
[Battery] 87.3% (3.92V) age=3s
  └─ 2 RAM reads, ~0 µs, no I2C
```

`readBattery()` is now called **only** from `send_vitals_frame()` on the 10-second interval.

Concern Raised

> If `emg_adc_init()` is called while `emg_adc_deinit()` hasn't set `adcHandle = nullptr` yet, `adc_continuous_new_handle()` could be called while the old handle is still being deinitialized.

Analysis: Already Covered by `adcMutex` (Session 2)

Both `emg_adc_init()` and `emg_adc_deinit()` take `adcMutex` with `portMAX_DELAY` as their first operation. The mutex serialises them completely:

```
emg_adc_deinit() (Core 0)          emg_adc_init() (Core 0)
─────────────────────────          ─────────────────────────
xSemaphoreTake(adcMutex) LOCKED
adc_continuous_stop()
adc_continuous_deinit()
adcHandle = nullptr
xSemaphoreGive(adcMutex) UNLOCKED
                                   xSemaphoreTake(adcMutex)  ← now acquires
                                   adcHandle == nullptr ✓
                                   adc_continuous_new_handle()
                                   xSemaphoreGive(adcMutex)
```

`emg_adc_init()` cannot observe a partially-deinitialized handle because it cannot acquire the mutex until `emg_adc_deinit()` has completed **and** set `adcHandle = nullptr`.

Scenario	Result
`init` called while `deinit` holds mutex	Blocks at `xSemaphoreTake` until `deinit` finishes

Scenario	Result
`init` called twice concurrently	Second caller blocks, then sees `adcHandle != nullptr` and returns
`emgDrainTask` reading while `deinit` runs	10 ms timeout — skips cycle if mutex unavailable

Conclusion

No code change required. The concern was valid before Session 2. `adcMutex` is the fix.

Problem

The DMA delivers ADC results in round-robin order: ENV, RAW, ENV, RAW, … If the ADC arbiter skips a conversion (e.g. due to BLE radio interference on ESP32), two consecutive same-channel results can arrive: ENV, ENV, RAW, RAW.

The previous code silently overwrote `envVal / rawVal` with no record of the event. The resulting pair used the second ENV with the next RAW — a one-sample mismatch.

Fix

Added `static volatile uint32_t emgChOrderViolations` counter:

- **Incremented** inside `emgMux` spinlock when a same-channel overwrite is detected (ENV arriving while `envValid` is already set, or RAW while `rawValid` is already set)
- **Reset** to 0 under `emgMux` in `onConnect()` alongside `emgDropped / emgSeq`
- **Printed** in the `[Health]` report every second as `EMGchViol=N`

The pairing behaviour is unchanged — overwrite-and-continue is still correct (the newer value is more recent and more useful). The counter provides diagnostic visibility to detect ADC arbiter issues in the field.

Health Report Format Change

```
// Before:
[Health] ... EMGdrop=N IMUdrop=N Frames/s=N ...
// After:
[Health] ... EMGdrop=N IMUdrop=N EMGchViol=N Frames/s=N ...
```

Problem

`imuTask` and `spo2Task` were both priority 1 on Core 1. `spo2Task` collects 100 samples over ~4 seconds, calling `maxSensor.check()` in a loop with `vTaskDelay(1)` between polls. If `maxSensor.check()` (I2C) takes longer than expected (e.g. bus contention, timeout), `spo2Task` holds the CPU and `imuTask` misses its 200 Hz timer ticks — dropping IMU samples.

`spo2Task` has no real-time requirement: it computes SpO2/HR once every ~30 seconds. `imuTask` is real-time: it must respond to 200 Hz `esp_timer` ticks within 5 ms.

Fix

Adjusted task priorities on Core 1:

Task	Before	After	Reason
`emgDrainTask`	2	2	Unchanged — real-time DMA drain at 2 kHz
`imuTask`	1	**2**	Raised — real-time 200 Hz, must not be starved
`spo2Task`	1	**0**	Lowered — background, no real-time requirement

`emgDrainTask` and `imuTask` are now equal priority 2. The FreeRTOS scheduler time-slices between equal-priority tasks, so neither starves the other. `spo2Task` at priority 0 only runs when both priority-2 tasks are blocked (waiting on DMA data or `vTaskDelay`).

Problem

`emgSeq`, `imuSeq`, `emgDropped`, `imuDropped` are `volatile uint32_t` accessed from two cores without synchronisation:

Variable	Reset (Core 0)	Increment (Core 1)
`emgSeq`	`onConnect()` line 498	`emgDrainTask` — `emgSeq++` outside `emgMux`
`imuSeq`	`onConnect()` line 499	`imuTask` — `imuSeq++` outside `imuMux`
`emgDropped`	`onConnect()` line 496	`emg_push()` inside `emgMux`

Variable	Reset (Core 0)	Increment (Core 1)
`imuDropped`	`onConnect()` line 497	`imu_push()` inside `imuMux`

Two distinct races:

1. `onConnect()` resets `emgSeq = 0` while `emgDrainTask` is mid `emgSeq++` — torn write.
2. `emgSeq++` in `emgDrainTask` was **outside** `emgMux`, so it was not protected by the same lock used to reset it in `onConnect()`.

Fix

1. Move `emgSeq++ / imuSeq++` inside the existing critical sections in `emg_push / imu_push`:

```
// emg_push: seq now assigned atomically with the ring buffer write
else { emgBuf[emgHead] = s; emgBuf[emgHead].seq = emgSeq++; emgHead = next; }
```

The call sites set `s.seq = 0` as a placeholder — the real value is assigned under the lock.

2. Reset all four counters under their respective spinlocks in `onConnect()`:

```
portENTER_CRITICAL(&emgMux);
emgDropped = 0;  emgSeq = 0;
portEXIT_CRITICAL(&emgMux);

portENTER_CRITICAL(&imuMux);
imuDropped = 0;  imuSeq = 0;
portEXIT_CRITICAL(&imuMux);
```

Why `portMUX` (spinlock) and not FreeRTOS mutex here

`emg_push()` is called from `emgDrainTask` (a FreeRTOS task) but `emgMux` is a `portMUX_TYPE` spinlock, not a FreeRTOS mutex. `portENTER_CRITICAL` / `portEXIT_CRITICAL` disable interrupts on the calling core and are safe to use from task context for very short critical sections. `onConnect()` runs on Core 0 in the BLE task context — also safe to use `portENTER_CRITICAL`.

Problem 1: EMG Sample Timestamps Late by Up to One DMA Frame (~16 ms)

`s.t_us = micros()` was called when a pair was formed in `emgDrainTask`, not when the ADC actually captured the signal. The DMA frame is 256 bytes = 64 results = 32 ENV+RAW pairs. At 2000 pairs/s, one frame covers 16 ms. `adc_continuous_read()` blocks up to 10 ms. So `s.t_us` could be up to ~16 ms later than the actual sample time — a systematic offset that would misalign EMG and IMU signals during swing detection.

Fix 1: Back-Calculate Actual ADC Capture Time

Capture `frameEndUs = micros()` immediately after `adc_continuous_read()` returns. For each result slot `i` in the frame, the actual capture time is:

```
actual_t_us = frameEndUs - (numResults - 1 - i) * (1 000 000 / ADC_CONV_FREQ_HZ)
```

At 4000 conv/s, `US_PER_CONV = 250 µs`. The oldest result in a 64-result frame was captured 63 × 250 = 15 750 µs before the newest. This corrects the systematic offset down to the residual jitter of `micros()` itself (~1 µs).

	Before	After
Timestamp source	`micros()` at pair-emit time	Back-calculated from frame-end time
Max timestamp error	~16 ms (one full frame)	~1 µs (micros() resolution)
IMU-EMG alignment	Systematic 16 ms offset	Accurate

Problem 2: Regression — `setSamplingPaused(true)` + `emg_adc_deinit()` Missing from `loop()` Pause Branches

During Session 3 refactoring, the disconnect and host-absent branches in `loop()` lost their `setSamplingPaused(true)` and `emg_adc_deinit()` calls. The DMA would keep running after the host disconnected or went silent.

Fix 2: Restore Missing Calls

Both pause branches in `loop()` now correctly call:

```
setSamplingPaused(true);
emg_adc_deinit();
```

before `rb_flush_all()` and `imu_ticks = 0`, matching the original intended behaviour.

Problem 1: I2C Bus Shared Without Mutex

Three execution contexts used the `Wire` I2C bus concurrently without synchronisation:

- `imuTask` (Core 1): `myICM.dataReady()` + `myICM.getAGMT()`
- `spo2Task` (Core 1): `maxSensor.check()` + `maxSensor.getRed()` + `maxSensor.getIR()`
- `loop()` / `readBattery()` (Core 0): `lipo.getSOC()` + `lipo.getVoltage()` (every 1 s health report + every 30 s vitals frame)

Arduino `Wire` on ESP32 is **not thread-safe**. Concurrent transactions corrupt I2C bus state, causing garbled sensor readings or SDA/SCL stuck-low bus lockups.

Fix 1

Added `static SemaphoreHandle_t wireMutex` protecting every I2C call site:

Call site	Context	Protection added
`lipo.getSOC/getVoltage/getChangeRate/isLow`	`readBattery()` → Core 0	`wireMutex` take/give
`myICM.dataReady()` + `myICM.getAGMT()`	`imuTask` → Core 1	`wireMutex` take/give
`maxSensor.check()` + `available()`	`spo2Task` → Core 1	`wireMutex` take/give
`maxSensor.getRed/getIR/nextSample()`	`spo2Task` → Core 1	`wireMutex` take/give
`configureMax3010x()` (brightness adjust)	`spo2Task` → Core 1	`wireMutex` take/give

Note: `Wire.begin()`, `myICM.begin()`, `maxSensor.begin()`, `lipo.begin()` in `setup()` are **not** wrapped — they run before any tasks start, so no contention is possible.

Problem 2: `samplingPaused` Cross-Core Visibility

`samplingPaused` is a `volatile bool` written on Core 0 and read on Core 1. On ESP32 Xtensa LX6, `volatile` prevents compiler reordering but does **not** insert a hardware memory barrier. The L1 data cache is not coherent between cores for DRAM without explicit barriers — reads on Core 1 may see stale values under high load.

Fix 2

Added atomic accessor functions using GCC built-ins:

```
static inline void setSamplingPaused(bool v) {
  __atomic_store_n(&samplingPaused, v, __ATOMIC_RELEASE);
}
static inline bool getSamplingPaused() {
  return __atomic_load_n(&samplingPaused, __ATOMIC_ACQUIRE);
}
```

All read/write sites replaced with `getSamplingPaused()` / `setSamplingPaused()`. Two exceptions use direct assign with comments: `setup()` end and `onConnect()` — both run before tasks start, so no cross-core visibility issue exists there.

Problem Identified

`adcHandle` was accessed from two cores without synchronisation:

- **Core 0** (`loop()`): calls `emg_adc_deinit()` → frees handle, sets `adcHandle = nullptr`
- **Core 1** (`emgDrainTask`): checks `adcHandle == nullptr`, then calls `adc_continuous_read(adcHandle, ...)`

The check and the read were not atomic, leaving a race window:

```
Core 1 (emgDrainTask)          Core 0 (loop)
─────────────────────          ─────────────
check: adcHandle != nullptr ✓
                               samplingPaused = true
                               emg_adc_deinit()
                                 → adc_continuous_deinit()
                                 → adcHandle = nullptr   ← freed!
adc_continuous_read(adcHandle) ← called with freed handle → CRASH
```

`samplingPaused = true` being set first does not help because there is no memory barrier guaranteeing Core 1 sees the updated value before it proceeds past its check.

Fix

Added a **FreeRTOS mutex** (`SemaphoreHandle_t adcMutex`) protecting all access to `adcHandle`.

- `portMUX_TYPE` spinlock was **not** used — it is ISR-safe but not suitable for blocking across cores in a task context (would busy-spin and starve the scheduler).
- A FreeRTOS mutex is correct here because both callers (`loop()` and `emgDrainTask`) are tasks.

Changes

Location	Change
Global	Added `static SemaphoreHandle_t adcMutex = nullptr;`
`setup()`	`adcMutex = xSemaphoreCreateMutex()` + `configASSERT` before tasks start
`emg_adc_init()`	Takes mutex for entire init sequence; releases after `adc_continuous_start()`
`emg_adc_deinit()`	Takes mutex for entire deinit sequence; releases after `adcHandle = nullptr`
`emgDrainTask`	Takes mutex with 10 ms timeout before using `adcHandle`; re-checks `adcHandle == nullptr` after acquiring; releases immediately after `adc_continuous_read()`

Mutex Timeout in `emgDrainTask`

A 10 ms timeout (not `portMAX_DELAY`) is used so the drain task never blocks indefinitely if `emg_adc_deinit()` is slow. On timeout, the task skips the cycle and retries next iteration.

2025 — Session 1: ADC DMA Migration + Bug Fixes

Problem Identified

`analogRead()` was being called inside an `esp_timer` ISR at 2000 Hz (every 500 µs).
On ESP32, `analogRead()` is **not ISR-safe** — it uses the ADC arbiter which can conflict with the BLE/WiFi radio. Each call blocks for ~50–100 µs, consuming 20–40% of a CPU core.

Solution

Replaced software-timer + `analogRead()` with **ESP32 ADC Continuous (DMA) mode** (`esp_adc/adc_continuous.h`, IDF 5.x / Arduino core 3.3.5).
DMA fills the buffer autonomously at hardware-clocked 4000 conv/s (2000 Hz per channel).
A new `emgDrainTask` (FreeRTOS, Core 1, priority 2) drains the DMA buffer and pushes paired `EmgSample` entries into the existing ring buffer.

Fixes Applied

#	Category	Issue	Fix
1	🔴 ISR safety	`analogRead()` called in `esp_timer` ISR at 2 kHz	Replaced with ADC DMA + `emgDrainTask`
2	🔴 Crash	`adc_continuous_read()` called before `adcHandle == nullptr` guard	Guard moved **before** the read call
3	🔴 Wrong API	`ADC_DIGI_OUTPUT_FORMAT_TYPE2` is S2/S3 only	Corrected to `ADC_DIGI_OUTPUT_FORMAT_TYPE1` for original ESP32
4	🟡 Compile	`ADC_CONV_FREQ_HZ` used `EMG_RATE_HZ` before it was defined	Moved ADC config block **after** `EMG_RATE_HZ` definition
5	🟡 Compile	`{ .flush_pool = 0 }` nested designated initializer warning in C++	Replaced with zero-init `= {}`
6	🟡 Compile	`SOC_ADC_DIGI_RESULT_BYTES` removed in IDF 5.x	Replaced with `sizeof(adc_digi_output_data_t)`
7	🟡 Compile	`r->type2.channel` / `r->type2.data` union removed in IDF 5.x	Replaced with `r->val` bit extraction (`>> 12` / `& 0x0FFF`)
8	🟡 Dead code	`emgTimer` handle created but never started; `emg_timer_cb` was empty no-op	Both removed entirely
9	🟡 Performance	`readBattery()` (I2C, ~100 µs) called on every `loop()` iteration (~1 kHz) for LED check	Replaced with cached `lastBatteryPct` (pure RAM read); I2C refresh unchanged at 10 s via `send_vitals_frame()`

Architecture After Changes

```
Before:
  esp_timer ISR (500 µs) → analogRead() x2 (blocking, ~100 µs each) → emg_push()

After:
  ADC DMA hardware (4000 conv/s, autonomous)
       ↓
  emgDrainTask (Core 1, priority 2)
       → drains DMA frame
       → demux ENV (ch3) / RAW (ch4) by channel tag
       → pairs into EmgSample
       → emg_push()
```

ADC DMA Configuration

Parameter	Value	Notes
Channels	ADC1*CH3 (PIN 39), ADC1*CH4 (PIN 32)	ENV and RAW
Attenuation	`ADC_ATTEN_DB_12`	~0–3.3 V range
Bit width	12-bit	Same as before
Format	`ADC_DIGI_OUTPUT_FORMAT_TYPE1`	Only valid format on original ESP32
Total conv rate	40000 conv/s	Round-robin: 20000 Hz per channel; decimated 10× to 2000 Hz output
DMA frame size	256 bytes	64 results per frame
Internal buffer	1024 bytes (4× frame)	

ADC DMA Lifecycle

Event	Action
Host heartbeat received (resume)	`emg_adc_init()` — start DMA
Host heartbeat lost (pause)	`emg_adc_deinit()` — stop DMA
BLE disconnect	`emg_adc_deinit()` — stop DMA
BLE connect	DMA stays stopped until first host PING

What Was NOT Changed

- Ring buffers, `EmgSample` / `ImuSample` structs
- All BLE, IMU, SpO2, battery, watchdog logic
- Protocol framing (`send_emg_frame`, `send_imu_frame`, `send_vitals_frame`)
- LED state machine patterns
- `samplingPaused` gate behaviour

Target Platform

- Board: ESP32 WROOM-32E
- Arduino ESP32 core: **3.3.5** (ESP-IDF 5.3.x)

Add new sessions above this line, newest first.