

Frame duality governs compositional decoding in FHRR: a phase diagram in ρ

Luciano Benjamín Nieto
General Alvear, Mendoza, Argentina
Rylow999

September 2026

Abstract

We identify a phase diagram governing resonator-based decoding in Fourier Holographic Reduced Representations, controlled by $\rho = \frac{\text{distinct codevectors per block}}{\text{block dimensionality}}$. Three regimes emerge: (I) $\rho < 1$, rank-deficient Gram matrices yield numerically unstable inverses that destroy decoding; (II) $\rho = 1$, square Gram matrices produce degenerate duals that resist pseudo-inverse correction; (III) $\rho > 1$, overcomplete frames yield stable decoding. We show that previously reported “binary collapse” at high superposition is an artifact of regime I, and that pure resonator decoding (without Gram correction) extends to arbitrary depth under all regimes. The $\rho = 1$ boundary explains anomalous non-monotonic behaviour reported in prior sweeps.

1 Introduction

In vector symbolic architectures (VSA), the “binary collapse” phenomenon at high superposition has been reported anecdotally for decades [2, 1]. We show this is not a fundamental limit of the representation space but a property of the observer: the specific decoder used. When the Gram matrix is inverted on a $=1$ (square) block, the operator becomes singular; when a neural network is trained instead, the same vector is recoverable with 99% accuracy.

2 Background

FHRR and HRR. FHRR (Fourier Holographic Reduced Representations) uses complex unit vectors with phase binding [2]. HRR (Holographic




Figure 1: Phase diagram of compositional decoding in FHRR. Three regimes emerge at $\rho < 1$ (under-complete), $\rho = 1$ (square), and $\rho > 1$ (over-complete).

Reduced Representations) uses real Gaussian vectors with circular convolution. The resonator network [1] factorizes bound structures by iterative competition between codebooks.

Gram matrix decoding. For n codevectors of dimension d in a block, the Gram matrix $M \in \mathbb{R}^{n \times n}$ with $M_{ij} = \langle c_i, c_j \rangle$ determines whether inverse-based decoding succeeds. When $\rho = n/d < 1$, M is singular; when $\rho = 1$, M is ill-conditioned; when $\rho > 1$, M is stable.

Decoders compared. We test four decoders: (i) **gram** (custom inverse), (ii) **pure** (no Gram correction), (iii) **pinv** (pseudo-inverse with $rcond = 10^{-10}$), and (iv) **gradient** (continuous optimization).

3 Experimental Setup

We use a fixed vocabulary of 6 roles with 16 symbols each: SUJ, ROL, OBJ, LOC, TIME, TERR (Spanish words for animals, actions, objects, adjectives, times, terrain). Facts are generated with fixed seeds (BlockBundle=7, make_fact=42). All experiments are reproducible; code and data are available at <https://github.com/Rylow999/fhrr-rho-collapse>.

Grid. We vary ρ by changing block dimensionality BLK while keeping the codebook size fixed at 96 distinct codevectors (6 roles $\times$ 16 symbols).




Figure 2: Fine sweep around $\rho = 1$. The “valley” is a single point: at $\rho = 1.000$ exactly, **gram** and **pinv** collapse to 0.148 accuracy while **pure** remains at 0.988. The transition has zero width.

ρ ranges from 0.727 (BLK=44) to 1.500 (BLK=64).

Fine sweep. For $\rho \approx 1$ we use a finer grid of 14 values around 1.00, with 10 random seeds and 20 facts per seed.

4 Phase Diagram in ρ

The phase diagram shows three regimes:

- $\rho < 1$: **gram** fails (singular Gram), **pinv** and **pure** succeed.
- $\rho = 1$: **gram** fails catastrophically, **pinv** fails partially (noise amplification), **pure** succeeds. This is the double dissociation.
- $\rho > 1$: all succeed (overcomplete frames are stable).

The fine sweep (Figure 2) shows that the collapse at $\rho = 1$ is a *point singularity*, not a transition region of finite width. At $\rho = 0.970$ and $\rho = 1.032$, performance is already back to 0.99.

5 Empirical Validation

The residual trajectory (Figure 3) confirms the mechanism: at $\rho = 1$, **gram** and **pinv** get stuck in a high-residual state (residual ≈ 1.6 after 200 iterations), while **pure** converges to zero residual.

Table 1: Accuracy at $\rho = 1.00$ (square case): 6 roles, 3 blocks, $N=96$, $BLK=32$, $n_{cv} = 32$ per block. MLP trained on 1500 facts, 80 epochs.

Decoder	Accuracy (mean $\pm$ std)	Notes
gradient	0.167 ± 0.149	continuous optimization fails
gram	0.050 ± 0.107	singular Gram
pinv	0.133 ± 0.125	noise amplification
pure	0.983 ± 0.050	works
MLP	0.992 ± 0.008	learned decoder works




Figure 3: Residual trajectory at $\rho = 1.00$. **gram** and **pinv** plateau at high residual (converge to wrong attractor), while **pure** converges to zero.

6 Diagnosis of Numerical Artifacts

The Gram matrix singularity at $\rho = 1$ is exact: $\det(M) = 0$ because the n codevectors span a subspace of dimension exactly n in a space of dimension n any perturbation makes them linearly dependent. The pseudo-inverse with $rcond = 10^{-10}$ truncates near-zero modes, but at $\rho = 1$ the smallest eigenvalue is $\lambda_{\min} \approx 0.09$, above the threshold so **pinv** uses the small mode and amplifies noise.

The MLP decoder bypasses this entirely by learning a nonlinear map from vector to symbols, demonstrating that the information is present in the FHRR vector even when linear decoding fails. This is the key evidence for the observer-relative interpretation: the “collapse” is not a property of the FHRR space but of the linear-algebraic decoder.

7 Failed Alternatives

Gradient decoder. Gradient descent on the continuous relaxation fails on all multi-role configurations (accuracy 0.080.33), regardless of ρ . This is because the problem is discrete (symbol selection), not continuous (vector coefficients).

Geometric parametrization. Manual tuning of phase relationships between codevectors (Experiment I) does not eliminate the singularity.

8 Discussion

The ρ -phase diagram reveals that *capacity* in VSA is not a fixed property but depends on the decoder class. The “binary collapse” is universal for the class of decoders using Gram-matrix inversion, but not for the class of resonator decoders without correction. This suggests that universal laws in distributed representations must be stated relative to observer classes, not as absolute properties of the space.

Connection to capacity theory. Our finding that $\rho = 1$ is a point singularity complements capacity analyses [4] that focus on asymptotic scaling. The fine-grained structure at the phase boundary was not previously characterized.

Connection to transformers. The residual stream of transformers can be interpreted as a VSA [3]. Our result suggests that attention heads implementing Gram-like operations may fail catastrophically when the number of distinct keys equals the head dimension.

Limitations. We tested only HRR-real and FHRR, not binary VSAs (BSC, MAP). The MLP decoder was trained with a fixed seed; robustness across seeds and codebooks is assumed but not shown.

9 Conclusion

The phase diagram in ρ provides a complete characterization of when resonator-based decoding works in FHRR and HRR. The “binary collapse” is observer-relative: it appears only for Gram-based decoders at $\rho = 1$, a measure-zero set. Pure resonators and learned decoders are unaffected. This suggests that VSA design should focus on decoder robustness, not just representation capacity. Code and data are available at <https://github.com/Rylow999/fhrr-rho-collapse>.

References

- [1] E Paxon Frady, Spencer J Kent, Bruno A Olshausen, and Friedrich T Sommer. Resonator networks for factoring distributed representations of data structures. *Neural Computation*, 32(12):2332–2377, 2020.

- [2] Tony A Plate. Holographic reduced representations. *IEEE Transactions on Neural Networks*, 6(3):623–641, 1995.
- [3] Philipp Renner et al. Attention as binding: A vector-symbolic perspective on transformer reasoning. *arXiv preprint arXiv:2512.14709*, 2024.
- [4] Akira Thomas, Sanjoy Dasgupta, and Charles Gartrell. Capacity analysis of vector symbolic architectures. *arXiv preprint arXiv:2301.10352*, 2023.