



BASE24-atm IMNsc SWITCH INTERFACE

LOG MESSAGES MANUAL

Version 3.2

This document contains **PROPRIETARY** and **CONFIDENTIAL** information and such information may not be disclosed to others for any purpose without written permission from:

ACI Worldwide (Canada) Inc.

200 Wellington Street West
Suite 700
Toronto, Ontario M5V 3C7

©2000 by ACI Worldwide (Canada) Inc.

All rights reserved. All information contained in this manual is confidential and proprietary to ACI Worldwide Inc. and has been delivered for use pursuant to license. No part of this manual may be photocopied, electronically transferred, modified, or reproduced in any manner that is contrary to license without the prior written consent of ACI Worldwide Inc.

ACI, ACI Worldwide, ACI Worldwide Inc., BASE24, BASE24-atm, BASE24-atm non-currency dispense, BASE24-atm self-service banking, BASE24-billpay, BASE24-CARD, base24-check auth, BASE24-debit/credit auth, BASE24-fraud control, BASE24-frequent shopper, BASE24-from host maintenance, BASE24-gift certificates, BASE24-InfoBase, BASE24-mail, BASE24-pos, BASE24-refunds auth, BASE24 Remote Banking, BASE24-telebanking, BASE24-teller, BASE24 Visa Cash, CO-ach, ICE, NET24, NET24-XPNET, Perfinon, and TSA are trademarks or registered trademarks of ACI Worldwide Inc., Transaction Systems Architects, Inc., or their subsidiaries.

Other companies' trademarks, service marks or registered trademarks and service marks are trademarks, service marks or registered trademarks and service marks of their respective companies.

REVISION HISTORY

Record of Changes

Author	Date	Version	Comments
ACI	June 1998	1.0	Initial Version
ACI	November 1998	1.1	Minor amendments to Version 1.0
ACI	April 1999	1.2	Amendments for Alternate Routing
ACI	July 2000	2.0	General review and update
ACI	April 2004	3.0	General review and update
ACI	October 2004	3.1	General review and update for TIM
ACI	October 2009	3.2	Expand BIN Table

Change Control Index

Change Control Reference	Description of Change	Modules Effected
C-yymmdd-01		

Reference Document

Document Name	Reference / Version	Date
BASE24 Log Message Reference Manual	BA-AE000-07 / 02	11/1997

TABLE OF CONTENTS

1. INTRODUCTION	1
2. NOTATION CONVENTION	1
3. IMNSC LOG MESSAGES	2

1. INTRODUCTION

This manual contains documentation for log messages generated by the Canadian IMNsc Fortify .3 Switch Interface. Each message description explains the cause of the message, the effect on the system, and provides a recommended recovery action.

2. NOTATION CONVENTION

The naming convention follows that used within BASE24. Further details on this notation can be found in the BASE24 Log Message Reference Manual.

The format used to describe the error messages in this section is shown below:

<i>Message-Number</i>	<i>Message-Text</i>
-----------------------	---------------------

<i>Message-Number</i>	A unique number that identifies the message.
<i>Message-Text</i>	The formatted message text.

Cause:	Describes what caused the message to be generated.
---------------	--

Effect:	Describes the effect on the system.
----------------	-------------------------------------

Response:	Describes the recommended resolution to the error.
------------------	--

The following list summarizes the conventions for syntax notation in this manual.

Notation	Meaning
nnnn*	If log message numbers are appended with an "*", the associated message text had been modified or added to reflect the IMNSC-AR release changes.
nnnn/nnnn	If log message numbers are separated by a "/", the associated message text applies to each number specified.
nnnn-nnnn	If log message numbers are separated by a "-", the associated message text applies to the range of numbers bound by the numbers specified.
<xxxx>	Text appearing between the "<" and ">" symbols indicates variable values that will appear in log messages. All other text will appear exactly as shown.

3. IMNsc LOG MESSAGES

1100 PROC ERROR: timer Type: <timer type> Subtype: <timer subtype>
--

Cause	A timer of unknown type expired.
Effect	IMNsc cannot process the time-out.
Response	This indicates an internal code problem. Contact your vendor representative.

1101 Node: <node ID> Begin Cutover Window New Date: <YYMMDD>
--

Cause	Cutover Begin timer has expired.
Effect	IMNsc has begun cutover to the indicated date for the indicated node.
Response	None required.

1102 Node: <node ID> Cutover completed to date <YYMMDD>

Cause	Cutover End timer has expired.
Effect	IMNsc has completed cutover to the indicated date for the indicated node.
Response	None required.

1103 PROC ERROR: Cutover Timer SubType <unexpected sub type>
--

Cause	An invalid timer subtype was passed to the cutover time-out handler procedure.
Effect	IMNsc cannot process the time-out.
Response	This indicates an internal code problem. Contact your vendor representative.

1104 TRACE03: ATM Inbound Time-out Orig: <node ID> Typ: <msg type>

Cause Trace bit 3 is turned on and a BASE24 request timer has expired for the indicated message type. "Orig" indicates the requesting node.

Effect IMNsc has begun processing a BASE24 request time-out.

Response None required. This message is for information only.

1105 TRACE07: <PIN/MAC/MSG> Keychange Time-out Dest: <node Id> Idx: <Key index>

Cause Trace bit 7 is turned on and a keychange request timer for the indicated node, key type and key index has expired.

Effect IMNsc has begun processing the keychange request time-out.

Response None required. This message is for information only.

1106 TRACE10: SAF Outbound Time-out Dest: <node Id> Typ: msg type>

Cause Trace bit 10 is turned on and a SAF request timer for the indicated node and message type has expired.

Effect IMNsc has begun processing the SAF request time-out.

Response None required. This message is for information only.

1107 TRACE 03: ATM Outbound Time-out Dest: <node Id> Typ: <msg type>

Cause Trace bit 3 is turned on and a request timer for the indicated node and message type has expired.

Effect IMNsc has begun processing the request time-out.

Response None required. This message is for information only.

1108 PROC ERROR: Pacing Timer SubType <unknown sub type>

Cause An invalid timer subtype was passed to the pacing time-out handler procedure.

Effect IMNsc cannot process the time-out.

Response This indicates an internal code error. Contact your vendor representative.

1109 TRACE06: Pacing Select State: <new state>

Cause Trace bit 6 is turned on, the pacing selection timer has expired and the pacing state has changed.

Effect IMNsc has re-calculated throughput and response times for all available entry points and determined that the pacing state has changed to the indicated state.

Response None required. This message is for information only.

1110 TRACE10: SAF Retransmit Dest: <node Id> Typ:<msg type>

Cause Trace Bit 10 is turned on and the SAF retransmit timer for the indicated node and message type has expired.

Effect IMNsc has begun processing the SAF retransmit time-out.

Response None required. This message is for information only.

1111 TRACE10: SAF Cycle Dest: <node Id> Msg: <Msg type> Cnt:<trxn count> IMNSC: <mode> <speed> Oper: <mode> <speed>

Cause Trace bit 10 is turned on and the SAF cycle timer has expired.

Effect IMNsc has begun processing the SAF cycle time-out for the indicated node and message type. The message indicates the IMNsc and operator SAF mode and processing speed.

Response None required. This message is for information only.

1201 TRACE08: Close from IMN Manager: <IMNM process name> Fno: <IMNM process file number>

Cause Trace bit 8 is turned on and a close message was received from the IMNM process.

Effect IMNsc closed the IMNM process.

Response Check that the IMNM process is still running. If not, start the IMNM process.

1202 IPC ERROR: Close from invalid process: <process name>

Cause A close message was received from an unknown process.

Effect IMNsc ignores the close message.

Response IMNsc disallows close attempts by unrecognized processes by returning Guardian error 48 (security violation). This message may indicate an internal code problem. Contact your vendor representative.

1203 TRACE08: Close from EP: <entry point Id> PID: <CIL process name> Fno: <CIL process file number>

Cause Trace bit 8 is turned on and a close message was received from the indicated CIL process for the indicated entry point.

Effect IMNsc closes the entry point if open, resets the entry point state and sets the inbound and outbound pacing state for the entry point to blocked.

Response None required. This message is for information only.

1204 TRACE08: Open from IMNM: <IMNM process name> Fno: <IMNM process file number>

Cause Trace bit 8 is turned on and an open message was received from the IMNM process.

Effect IMNsc reads all ICF records to get the current connection states.

Response None required. This message is for information only.

1205 IPC ERROR: Open from invalid process: <process name>

Cause	An open message was received from an unknown process.
Effect	IMNsc returns a Guardian error 48 (security violation) to the process.
Response	The indicated process should be investigated as to why it was attempting to open IMNsc. The entry point configuration may need to be checked.

1206 TRACE08: Open from EP: <entry point Id> PID:<CIL process filename> Fno: <CIL process file number> State: <entry point state>

Cause	Trace bit 8 is turned on and an open message was received from the indicated CIL process for the indicated entry point.
Effect	If the entry point is not open and has not been stopped, IMNsc opens the entry point. If the entry point is stopped, IMNsc returns Guardian error 2 (invalid operation).
Response	None required. This message is for information only.

1301 TRACE05: EchoTest EP: <entry point Id> FilId: <FIL Id> Cnxn: <connection Id> Status: <echo test status and reason codes> Pid: <CIL process name>

Cause	Trace bit 5 is turned on and an echo test request has been received from the indicated CIL process.
Effect	IMNsc sends an echo test response.
Response	None required. This message is for information only.

1302 TRACE05: Handshake EP: <entry point Id> FilId: <FIL Id> Cnxn: <connection Id> Status: <handshake status and reason codes> Pid: <CIL process name>

Cause	Trace bit 5 is turned on and a handshake request was received from the indicated CIL process for the indicated entry point.
Effect	IMNsc validates the request, sends the response and sends a handshake request if necessary.
Response	None required. This message is for information only.

1303 TRACE06: PacingMsg EP: <entry point Id> Cnxn: <connection Id> Status: <Pacing status and reason codes> Pid: <CIL process name>

Cause Trace bit 6 is turned on and a pacing request has been received from the indicated CIL process for the indicated entry point.

Effect IMNsc processes the pacing message and updates the pacing state for the entry point accordingly.

Response None required. This message is for information only.

1304 IMN ERR: EP: <entry point Id> PID: <CIL process name>

Cause IMNsc has received a pacing request for an invalid connection Id from the indicated CIL process.

Effect IMNsc ignores the pacing request.

Response Check the IMN connection configuration for the CIL process.

1305 TRACE06: SetPacing EP: <entry point Id> Dest: <node Id> <msg class> Inb: <new inbound pacing state> Curr: <current inbound pacing state>

Cause Trace bit 6 is turned on and the inbound pacing state is the indicated new state.

Effect IMNsc sets the inbound pacing state to the indicated value.

Response None required. This message is for information only.

1306 TRACE06: SetPacing EP: <entry point Id> Dest: <node Id> <msg class> Outb: <new outbound pacing state> Curr: <current outbound connection state> New: <new outbound connection state>

Cause Trace bit 6 is turned on and the outbound pacing state is the indicated new state.

Effect IMNsc sets the inbound pacing state to the indicated value and determines the state of the connection.

Response None required. This message is for information only.

1307 IPC ERROR: Pacing Notify message to IMNM lost

Cause	IMNsc has not opened IMNM successfully and cannot send a pacing notification message to the IMNM.
Effect	IMNsc attempts to re-open IMNM when its recovery timer expires. If successful, the pacing information is sent to the IMNM process.
Response	Check that the IMNM process has been started.

1401 TRACE04: MsgResend <connection Id> Retry: <retry count>

Cause	Trace bit 4 is turned on and IMNsc received a response to a request indicating that the request was undeliverable due to a congested or blocked path.
Effect	If the retry count is 0, IMNsc attempts to send the request to another entry point. If unsuccessful, a denial response is returned to BASE24. If the retry count is not 0, IMNsc will not resend the request.
Response	Check the status of the entry points for the indicated connection.

1501 TRACE04: EpMessage EP: <entry point Id> Cnxn: <connection Id> Type: <msg type, subtype> Status: <status and reason codes>

Cause	Trace bit 4 is turned on and a message containing the indicated information has been received from the indicated entry point.
Effect	IMNsc processes the message.
Response	None required. This message is for information only.

1502 IMN ERROR: Msg DROPPED: EP:<entry point Id> Cnxn: <connection Id> Type: <msg type, subtype> Status: <status and reason codes>

Cause	A message received from the indicated entry point was dropped due to the status and reason codes indicated.
Effect	IMNsc could not process the message normally.
Response	Check the status and reason codes indicated to determine the appropriate action.

1503 IMN ERROR: Invalid message Len: <msg length>

Cause	IMNsc has received a message that is not long enough to contain a standard external message header from an indicated entry point.
Effect	IMNsc ignores the message.
Response	This may indicate an internal code problem with either IMNsc or IMN. Contact your vendor representative.

1504 IMN ERROR: Invalid ISO structure: <msg length> . <iso-msg>

Cause	IMNsc could not process the ISO date portion of a message.
Effect	The message is denied with a status code of Undeliverable Request (80) and a reason code of Invalid Message (21). The message is logged to the ILF.
Response	This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

1505 PROC ERROR: Reply state error. Following message discarded

Cause	A reply to a request was required but the reply length was not specified to the message handler procedure.
Effect	IMNsc does not reply to the message.
Response	This indicates an internal code problem. Contact your vendor representative.

1601 PROC ERROR: Open completion on invalid file no <file number>

Cause	A NOWAIT open completed on an unknown file.
Effect	IMNsc does not process the open completion.
Response	This indicates an internal code problem. Contact your vendor representative.

1602/1603 PROC ERROR: Invalid IO Tag <tag words 1 and 2>

Cause An I/O completed with an unknown I/O tag.

Effect IMNsc cannot process the I/O completion.

Response This indicates an internal code problem. Contact your vendor representative.

1604 IPC ERROR: Completion on <filename> Tag: <tag words 1 and 2> Err: <Guardian error code>

Cause The indicated error occurred on an I/O on the indicated process file.

Effect IMNsc cannot process the I/O completion. If the error occurred on an entry point, the entry point is closed. It is re-opened when the recovery timer expires. If the error occurred on the IMNM process, the IMNM is closed. It is re-opened when the recovery timer expires.

Response Check the Guardian file error indicated to determine the appropriate response.

1606 IPC ERROR: Completion on <filename> Tag: <tag words 1 and 2> Err: <Guardian error code>

Cause The indicated error occurred on an I/O on the indicated process file.

Effect IMNsc cannot process the I/O completion. The error occurred on the IMNM process, the IMNM is closed. It is re-opened when the recovery timer expires.

Response Check the Guardian file error indicated to determine the appropriate response.

1607 TRACE13: IMNM Msg Tag: <tag words 1 and 2> Type: <IMNM msg type> Len : <msg length>

Cause Trace bit 13 is turned on and an I/O completed on the IMNM process.

Effect IMNsc processes the I/O completion.

Response None required. This message is for information only.

1608 PROC ERROR: Invalid IO Tag <tag words 1 and 2>

Cause An I/O completed with an unknown I/O tag.

Effect IMNsc cannot process the I/O completion.

Response This indicates an internal code problem. Contact your vendor representative.

1609 IPC ERROR: PID: <process name> Err: <Guardian error code>

Cause A message was received on \$RECEIVE with a non-zero Guardian error code which is not a system message.

Effect IMNsc logs the error and continues.

Response Check the Guardian error code indicated to determine the appropriate response.

1610 TRACE03: IMNM Msg PID: <IMNM process name> Fno: <process file number> Type: <IMNM msg type> Len: <IMNM msg length>

Cause Trace bit 3 is turned on and a message was received from the IMNM process.

Effect IMNsc processes the IMNM message.

Response None required. This message is for information only.

1611 IPC ERROR: Invalid Origin PID: <process name> Fno: <process file number> Len: <msg length>

Cause A message was received from an unknown process or entry point.

Effect IMNsc logs the error and continues.

Response Investigate the indicated process as to why it was sending messages to IMNsc. This may indicate an internal code problem. Contact your vendor representative.

1612 SPAN ERROR: Message Dropped Src: <source symbolic process name> Dest: <destination symbolic process name> Orig: <originating process name> Seqno: <msg sequence number> Dup: <duplicate flag>

Cause If a system process is unavailable, the XPNET will redeliver messages that were queued when the process was unavailable.

Effect IMNsc drops the duplicate message.

Response None required. If this problem persists contact your vendor representative.

1613 TRACE03: ATM Outb Msg Src: <source symbolic processname> Typ: <msg type> Tran: <BASE24 transaction code> Resp: <BASE24 response code>

Cause Trace bit 3 is turned on and an ATM message has been received from the XPNET.

Effect IMNsc processes the message.

Response None required. This message is for information only.

1614 SPAN ERROR: Message Dropped Src: <source symbolic process name> Dest: <destination symbolic process name> Orig: <originating process name> Seqno: <msg sequence number> Dup: <duplicate flag>

Cause If a system process is unavailable, the XPNET will redeliver messages that were queued when the process was unavailable.

Effect IMNsc drops the duplicate message.

Response None required. If this problem persists, contact your vendor representative.

1615 PROC ERROR: Invalid mtX Index: <msg type index>

Cause The message type table index was not recognized by the XPNET message handler procedure.

Effect IMNsc cannot process the message.

Response This indicates an internal code problem. Contact your vendor representative.

1616 ATM ERROR: Message Dropped: Src: <source symbolic process name> Dest: <destination symbolic process name> Msg Type: <msg type>

Cause A message with an invalid type was received from the XPNET.

Effect IMNsc drops the message.

Response Investigate the source process as to why the indicated message type was sent to IMNsc.

1617 TRACE03: ADMIN Outb Msg Src: <symbolic process name> Typ: <msg type> code: <processing code>

Cause Trace bit 3 is turned on and an ADMIN message has been received from the XPNET.

Effect IMNsc processes the message.

Response None required. This message is for information only.

1618 TRACE02: NCS Outb Cmd Src: <symbolic process name> Len: <msg length> Txt: <msg text>

Cause Trace bit 2 is turned on and an NCS command has been received from the XPNET.

Effect IMNsc processes the command.

Response None required. This message is for information only.

1701 TRACE01: Timer Typ: <timer type> Subtype: <timer subtype> Count: <timer number> of <total timers>

Cause Trace bit 1 is turned on and a timer of the indicated type and subtype has expired.

Effect IMNsc processes the time-out.

Response None required. This message is for information only.

1702 IMN ERROR: Handshake Time-out EP: <entry point Id> State: <entry point state> PID: <CIL process name>

Cause A handshake request for the indicated entry point timed out.

Effect IMNsc cannot complete the handshake procedure with the indicated CIL process. IMNsc closes the entry point and re-opens it when the recovery timer expires.

Response Check that the indicated CIL process is running and that the indicated entry point is activated. The LCONF parameter "IMN-HANDSHAKE-TIMEOUT" may need to be increased in which case IMNsc must be warmbooted for this change to take effect.

1703 PROC ERROR: Timer Type: <timer type> Subtype: <timer subtype>

Cause A timer of unknown type expired.

Effect IMNsc cannot process the time-out.

Response This indicates an internal code problem. Contact your vendor representative.

1901 TRACE00: <RECEIVE> Ev: <event type> Fno: <file-number> Typ: <msg type> Len: <msg length> Tag: <tag words 1 and 2> PID: <process name>

Cause Trace bit 0 is turned on and a message has been received on \$RECEIVE.

Effect IMNsc processes the received message or has sent the indicated reply.

Response None required. This message is for information only.

1902 IPC ERROR: RECEIVE Event:<event type> Tag:<tag words 1 and 2> PID:<process name> Err: <Guardian error code>

Cause An I/O error occurred on \$RECEIVE.

Effect IMNsc logs the error and continues processing.

Response Check the Guardian error code and the process name indicated to determine the nature of the error and take action accordingly.

1903 SPAN ERROR: Message Failure <failure code> Src:<symbolic process name>

Cause	The XPNET returned a message failure code.
Effect	IMNsc logs the error and continues.
Response	Check the XPNET message failure code indicated to determine the appropriate action to take.

1904 IPC ERROR: REPLY Tag: <tag words 1 and 2> PID: <process name> Err: <Guardian error code>

Cause	An error occurred on a reply to the indicated process.
Effect	IMNsc logs the error and continues.
Response	Check the Guardian error code and the process name indicated to determine the appropriate response.

1905 TRACE00: <REPLY> Ev: <event type> Fno: <file-number> Typ: <msg type> Len: <msg length> Tag: <tag words 1 and 2> PID: <process name>

Cause	Trace bit 0 is turned on and a reply has been sent to the requester process.
Effect	IMNsc processes the received message or has sent the indicated reply.
Response	None required. This message is for information only.

1906 IPC ERROR: RECEIVE event: <event type> Tag: <tag words 1 and 2> PID: <process name> Err: <Guardian error code>

Cause	An I/O error occurred on \$RECEIVE.
Effect	IMNsc logs the error and continues processing.
Response	Check the Guardian error code and the process name indicated to determine specific nature of the error and take action accordingly.

2101 TRACE09: AllocateSegment - <segment size> bytes

Cause Trace bit 9 is turned on and an extended memory segment of the indicated size is about to be allocated.

Effect IMNsc allocates the extended segment.

Response None required. This message is for information only.

2102 IO ERROR: ALLOCATESEGMENT Err: <Guardian error code>

Cause An attempt to allocate an extended memory segment failed. The indicated Guardianerror was returned.

Effect IMNsc cannot set up its internal tables.

Response Check the indicated Guardian error to determine the appropriate response. Warmboot to restart IMNsc.

2103 PROC ERROR: USESEGMENT failure

Cause An attempt to use an extended memory segment failed.

Effect IMNsc cannot set up its internal tables.

Response This indicates an internal code problem. Contact your vendor representative.

2104 PROC ERROR: DEFINEPOOL Result: <define pool error code>

Cause An attempt to define a pool in an extended memory segment failed.

Effect IMNsc cannot set up its internal tables.

Response This indicates an internal code problem. Contact your vendor representative.

2105 PROC ERROR: ALLOCATESEGMENT Code: <error-number>

Cause An attempt to allocate an extended memory segment failed.

Effect IMNsc cannot set up its internal tables.

Response Check the indicated error to determine the appropriate response. Warmboot to restart IMNsc.

2201 TRACE09: Loading DCT Dest: <node Id> <msg class>

Cause Trace bit 9 is turned on and the destination control table entry for the indicated destination is about to be set up.

Effect IMNsc sets up the DCT entry.

Response None required. This message is for information only.

2202 TRACE09: Loading FKT File: <file name>

Cause Trace bit 9 is turned on and the inbound key table is about to be loaded from the indicated file.

Effect IMNsc loads the inbound key table.

Response None required. This message is for information only.

2203 PROC ERROR: Max Keys reached (<maximum inbound key entries>) - FKT full

Cause The inbound key table is full and another entry cannot be added.

Effect IMNsc cannot set up a complete inbound key table.

Response Increase the LCONF parameter "INTERNAL-FKT-TABLE-ENTRIES" and restart IMNsc.

2205 TRACE09: Loading SAF File: <file name>

Cause	Trace bit 9 is turned on and the indicated SAF file is about to be added to the SAF control table and linked to the destination control table entries. The SAF control and date records are about to be read.
Effect	IMNsc loads the indicated SAF information.
Response	None required. This message is for information only.

2206 WARNING: Destination <node Id> <msg class> set to FORWARD ONLY mode

Cause	The SAF control record for the indicated destination could not be retrieved.
Effect	IMNsc sets the destination SAF mode to Forward only.
Response	Check that the IMNM process is running. Check for previous log messages indicating that a Guardian error occurred on the SAF file.

**2210 INIT: Destinations per normal pacing step is set to default value = 1
INIT: Destinations per abnormal pacing step is set to default value = 1**

Cause	IMNsc sets the default values for number of destinations per pacing step during the initialization process.
Effect	Default values set.
Response	None required.

**2211 INIT: Nbr of normal steps per pacing interval is set to default value = 1
INIT: Nbr of abnormal steps per pacing interval is set to default value = 1**

Cause	IMNsc sets the default values for number of steps per pacing interval during the initialization process.
Effect	Default values set.
Response	None required.

2226 IO ERROR: ICF REASSEMBLY error on <icf-fname> Err:<error code>

Cause Unable to reassemble the ICF file.

Effect The ICF file will be closed, IMNsc initialization will fail.

Response Check the error code and take action accordingly.

2227 IO ERROR: ICF UPDATE error on <icf-fname> Err:<error code>

Cause Unable to update the ICF file.

Effect The ICF file will be closed, IMNsc initialization will fail.

Response Check the error code and take action accordingly.

2299 No ATM record found in the TKN file - all STM tokens will be logged to the ILF

Cause Check for ATM record in the TKN file.

Effect IMNsc logs the message and continues processing.

Response None required.

2300 NETWORK initialization failed

Cause Initialization of the B24 network failed.

Effect IMNsc cannot complete its initialization of the network.

Response Check for previous log messages indicating a Guardian error occurred. Correct the file system problem and restart IMNsc.

2301 ABEND ERROR: LCONF initialization failed

Cause Initialization of the LCONF assigns or parameters failed.

Effect IMNsc cannot complete its initialization of file assigns and parameters.

Response Check for previous log messages indicating a Guardian error occurred on the LCONF file. Correct the file system problem and restart IMNsc.

2302 ABEND ERROR: LOGGER initialization error

Cause Initialization of the LOGGER failed.

Effect IMNsc cannot write log messages.

Response Check for previous home term messages indicating a Guardian error occurred on the LOGGER. Correct the LOGGER problem and restart IMNsc.

2303 Base24 / IMN Interchange - Copyright 1997 by ACCI

Cause Initialization of the LOGGER was successful.

Effect IMNsc logs the message and continues.

Response None required.

2304 Process initialized. EPS Avail: <number of entry points defined. Mode: <test/production mode> Manager: <IMNM process name>

Cause IMNsc has completed its initialization.

Effect IMNsc continues normal processing.

Response None required.

2305-2307 ERROR: Can't encrypt initialization vector: <encrypt error code>

Cause Encryption of the initialization vector failed.

Effect IMNsc cannot encrypt account balance information and will blank fill any account balance fields.

Response Check for previous log messages indicating a Guardian error on the security device process. Correct the device problem and restart or warmboot IMNsc.

2308 TRACE09: Opening ADMNF File: <file name>

Cause Trace bit 9 is turned on and the ADMIN file is about to be opened.

Effect IMNsc opens the file.

Response None required.

2309 IO ERROR: Open error on ADMNF: <file name> Err: <error-code>

Cause An attempt to open the Administrative Message File failed.

Effect IMNsc initialization fails.

Response None required.

2310 TRACE08: Opening EP: <CIL process name, entry point subdevice> State: <entry point state>

Cause Trace bit 8 is turned on and the indicated entry point is about to be opened.

Effect IMNsc opens the entry point.

Response None required. This message is for information only.

2311 RECOVER: EP <CIL process name, entry point subdevice> opened Prev Error: <Guardian error code>

Cause An entry point has been re-opened after an error occurred.

Effect IMNsc logs the message and continues.

Response None required.

2312 IO ERROR: OPEN EP: <CIL process name, entry point subdevice> State:<oldstate> Err: <error code>

Cause An OPEN to a specific CIL entry-point failed.

Effect IMNsc cannot use this specific link.

Response Check the Guardian error code and take specific action.

2313 TRACE08: Opening IMNM <IMNM process name>

Cause Trace bit 8 is turned on and the IMN manager process is about to be opened.

Effect IMNsc opens the IMNM process.

Response None required. This message is for information only.

2314 IO ERROR: Open error on IMNM: <IMNM process name> Err: <error-code>

Cause IMNsc failes to open link to IMNM.

Effect The IMNsc initialization continues.

Response Examine the Guardian error code and take appropriate action.

2315 RECOVER: IMNM <IMNM process name> opened Prev Error: <Guardian error code>

Cause The IMNM process has been re-opened after an error occurred.

Effect IMNsc logs the message and notifies IMNM of its pacing status.

Response None required.

2316 TRACE09: Loading BIN File <file name>

Cause Trace bit 9 is turned on and the BIN file is about to be loaded.

Effect IMNsc loads the BIN file data.

Response None required. This message is for information only.

2317 IO ERROR: BINF: OPEN Error on <file-name> Err:<error>

Cause Error on opening the BIN file.

Effect IMNsc initialization fails.

Response Check the Guardian error code to determine the appropriate action. Warmboot IMNsc.

2318 IO ERROR: BINF: READ Error on <file-name> Err:<error>

Cause Error on reading the BIN file.

Effect The BIN file will be closed. IMNsc cannot set up the BIN table.

Response Examine the BIN file to verify its name, size, content and location.

2319 PROC ERROR: Max BIN routings (<Maximum BIN table entries>) - BINT full

Cause The BIN table is full and another entry cannot be added

Effect IMNsc cannot set up a complete BIN table.

Response Increase the LCONF parameter "INTERNAL-BIN-TABLE-ENTRIES" and restart IMNsc. The default value for this parameter is 50 entries, and the maximum value is 32000. *Note: The larger the table, the longer each search for routing will take.*

2320 WARNING: No BIN Routings loaded from <file name>

Cause No BIN table entries were found in the indicated file.

Effect IMNsc has an empty BIN table and cannot route any financial or administrative adjustment transactions.

Response Check that the indicated file is the correct file and check the contents of the file. Restart or warmboot IMNsc.

2321 TRACE09: Loading EPCF File: <file name>

Cause Trace bit 9 is turned on and the entry point configuration file is about to loaded.

Effect IMNsc loads the entry point configuration data.

Response None required. This message is for information only.

2322 IO ERROR: EPCF: OPEN Error on <file-name> Err: <error>

Cause Error on opening the EPCF.

Effect Unable to build the EPT table, IMNsc initialization stops.

Response Examine the EPCF file to verify its name, size, contents and location as well as the Guardian error code.

2323 IO ERROR: EPCF: READ Error on <file-name> Err: <error>

Cause Unable to read the EPCF file.

Effect The EPCF will be closed.

Response Examine the error to determine its nature and take action accordingly.

2324 WARNING: Maximum entry points (<maximum number entry points>) - EPCF full

Cause The entry point table is full and another entry point cannot be added.

Effect IMNsc cannot build a completed entry point table.

Response This is a program limit. Configure another IMNsc process or contact your vendor representative.

2325 CONFIG: EPCF <file name> Defs loaded: <entry point count> <ISSUER ONLY/ACQUIRER ONLY/ISSUER & ACQUIRER/NO EPS DEFINED>

Cause The indicated number of entry point configurations has been loaded.

Effect IMNsc will function in the mode indicated.

Response Check that the mode logged is correct. If not, check the entry point configuration file data.

2326 IO ERROR: ICF READ error on <icf-fname> Err:<error code>

Cause Unable to read the ICF file.

Effect The ICF file will be closed, IMNsc initialization will fail.

Response Examine the error code and take action accordingly.

2327 IO ERROR: ICF DISASSEMBLY error on <icf-fname> Err:<error code>

Cause Unable to disassemble the ICF file.

Effect The ICF file will be closed, IMNsc initialization will fail.

Response Examine the error code and take action accordingly.

2328 TRACE09: Loading ICF File: <file name>

Cause Trace bit 9 is turned on and the indicated ICF file data is about to be loaded.

Effect IMNsc loads the ICF data.

Response None required. This message is for information only.

2329 IO ERROR: ICF: OPEN Error on <file-name> Err: <error>

Cause Failed to open the ICF file.

Effect Unable to configure the node, IMNsc stops.

Response Examine the error code to determine the nature of the error and take action accordingly.

2330 IO ERROR: ICF:KEYPOSITION Error on <file-name> Err: <error>

Cause Keypositioning in the ICF file failed.

Effect The ICF file closes, IMNsc initialization stops (not able to find FIID).

Response Examine the error code to determine the nature of the error and take action accordingly.

2331 IO ERROR: ICF: MISSING CONFIG Error on <file-name> Err: <error>

Cause Unable to read and disassemble the first record in the ICF.

Effect The ICF file closes, IMNsc initialization stops.

Response Examine the ICF file to verify its name, size, contents and location.

2332 IO ERROR: ICF:INVALID CONFIG Error on <file-name> Err: <error>

Cause Unable to validate the first record in the ICF.

Effect The ICF file closes, IMNsc initialization stops.

Response Examine the ICF file to verify its name, size, contents and location.

2333 CONFIG: ILF File: Today: <file name> Tomorrow: <file name>

Cause The indicated ILF files have been created and/or opened.

Effect IMNsc begins processing using the indicated files.

Response None required.

2334 WARNING: No <OUT/IN> BOUND Keys for destination <node Id> <msg class>

Cause The inbound and /or outbound KEYF record could not be found or processed for the indicated destination.

Effect IMNsc has no key data for the indicated destination.

Response Set up the key information for the indicated destination in the KEYF file using the KEYF screen. Restart or warmboot IMNsc.

2335 PROC ERROR: Max destinations (Maximum number of destinations>) - DCT full

Cause The destination control table is full and another entry cannot be added.

Effect IMNsc cannot build a complete destination control table.

Response This is a program limit. Configure another IMNsc process or contact your vendor representative.

2336 WARNING: No Destinations Defined in ICF <file name>

Cause No destinations data was found or processed from the indicated ICF file.

Effect IMNsc has no destination information and cannot route any transactions.

Response Set up the destination information in the ICF file using the ICF screen. Restart or warmboot IMNsc.

2337 INIT ERROR: Assign <assign item>: Open: <file name> Err: <error -code>

Cause Open on the specified file fails.

Effect IMNsc is unable to open the file.

Response Check the GUARDIAN error code to determine the appropriate response. Correct the file system problem. Restart or warmboot IMNsc.

2338 TRACE09: Processing LCONF File: <file name>

Cause Trace bit 9 is turned on and processing of the indicated LCONF file is about to begin.

Effect IMNsc processes the LCONF file.

Response None required. This message is for information only.

2339 INIT ERROR: LCONF: <file name> Err: <Guardian error code>

Cause A Guardian error occurred on the LCONF file.

Effect IMNsc cannot load all assigns and parameters from the LCONF file.

Response Check the Guardian error code to determine the appropriate response. Correct the file system problem and restart or warmboot the IMNsc.

2340 INIT ERROR: Assign <assign name>:Missing

Cause The indicated assign could not be read from the LCONF file.

Effect IMNsc cannot determine the physical file associated with the assign.

Response Add the assign to the LCONF. Restart or warmboot IMNsc.

2341 INIT ERROR: Assign <assign name>: Invalid File Name

Cause The physical file name associated with the indicated assign is invalid.

Effect IMNsc cannot process the indicated assign.

Response Fix the assign in the LCONF. Restart or warmboot IMNsc.

2342 INIT ERROR: Assign <assign name>: Open:<file name> Err:<Guardian error code>

Cause A Guardian error occurred when attempting to open the specified template file.

Effect IMNsc cannot process the indicated assign and initialization fails.

Response Check the Guardian error code to determine the appropriate response. Restart or warmboot IMNsc.

2343 INIT ERROR: Param <param name>: Missing

Cause	The indicated parameter could not be read from the LCONF file and IMNsc does not have a default value.
Effect	IMNsc cannot determine the correct value for the program variable associated with the indicated parameter.
Response	Add the parameter to the LCONF file. Restart or warmboot IMNsc.

2344 INIT: Param <param name>: Default Used

Cause	The specified parameter could not be read from the LCONF file and a default value was used.
Effect	IMNsc continues processing using the default value.
Response	Confirm that the parameter in LCONF is correct and restart or warmboot IMNsc.

2345 INIT: Param <param name>: Ignored during WARMBOOT

Cause	The indicated parameter was ignored during a warmboot.
Effect	IMNsc ignores the indicated parameter so that its internal table sizes are not changed during a warmboot.
Response	If the indicated parameter must be changed, change the LCONF parameter and restart IMNsc.

2346 INIT ERROR: Param <param name>: Invalid value

Cause	The value of the indicated parameter was invalid.
Effect	IMNsc cannot process the parameter.
Response	Fix the parameter in the LCONF file. Restart or warmboot IMNsc.

2347 TRACE 09: Process Termination

Cause Trace bit 9 is turned on and IMNsc is about to terminate.

Effect IMNsc terminates.

Response Restart IMNsc if necessary.

2348 PROC ERROR: CIL FNAME32 error EP: <entry point Id> PID: <CIL process name>

Cause The file name for the indicated entry point could not be converted to an internal format.

Effect IMNsc closes the entry point.

Response Check the entry point configuration file. Reload the entry point table.

2349 FKT Verify Error: idx1 = # idx2 = # Duplicate KEK = <KEK key value>

Cause Duplicate KEK found in FKT table.

Effect IMNsc calls NETABEND if duplicates still exist in retry of loading FKT table.

Response Check for duplicate KEK in KEYF file.

2350 ICF ERROR: Record with key <node-name> not loaded into DCT: Invalid msg class <msg-class>.Only SCD msg class <msgclshared-cash> and <msgclshared-cash-test> acceptable!

Cause The read of the current ICF record fails due to invalid message class.

Effect The current ICF record will not be loaded.

Response Check the contents of the ICF file.

2360 INIT ERROR: LCONF: <file name> Err:<Guardian error code>

Cause	A Guardian error occurred on retrieving the BASE24 release indicator from the LCONF file.
Effect	IMNsc cannot load all assigns and parameters from the LCONF file.
Response	Check the Guardian error code to determine the appropriate response. Correct the file system problem and restart or warmboot the IMNsc.

2361/2362 INIT ERROR: LCONF: <file name> Err:<Guardian error code>

Cause	A Guardian error occurred on retrieving the KEYF file from the LCONF file.
Effect	IMNsc cannot load all assigns and parameters from the LCONF file.
Response	Check the Guardian error code to determine the appropriate response. Correct the file system problem and restart or warmboot IMNsc.

2363 INIT ERROR: Assign: <assign name> Missing

Cause	The indicated assign could not be read from the LCONF file.
Effect	IMNsc cannot determine the physical file associated with the assign.
Response	Add the assign to the LCONF. Restart or warmboot IMNsc.

2365 INIT ERROR: LCONF: <file name> Err:<Guardian error code>

Cause	A Guardian error occurred on retrieving the TKN file from the LCONF file.
Effect	IMNsc cannot load all assigns and parameters from the LCONF file.
Response	Check the Guardian error code to determine the appropriate response. Correct the file system problem and restart or warmboot IMNsc.

2364/2366 INIT ERROR: Assign: <assign name> Invalid File Name

Cause The physical file name associated with the indicated assign is invalid.

Effect IMNsc cannot process the indicated assign.

Response Fix the assign in the LCONF. Restart or warmboot IMNsc.

2367 Process initialized failed: get process handle

Cause IMNsc initialization failed. Unable to get a process handle from the system when attempting to create a process.

Effect IMNsc logs the error message and abends.

Response Examine the abend file and take action accordingly.

2368 Process initialized failed: get process decompose

Cause IMNsc initialization failed. Unable to get a process information from the system.

Effect IMNsc logs the error message and abends.

Response Examine the abend file and take action accordingly.

2370 Initialize Radix table error: >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause IMNsc cannot initialize the radix table. It might be a programmatic error.

Effect IMNsc logs an error message and abends.

Response Examine the abend file and take action accordingly.

2371 Add queue in Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause IMNsc cannot add data into the radix table. It might be a programmatic error.

Effect IMNsc logs an error message and abends.

Response Examine the abend file and take action accordingly.

2372 Building Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause IMNsc cannot build the radix table. It might be a programmatic error.

Effect IMNsc logs an error message and abends.

Response Examine the abend file and take action accordingly.

2373 Get info Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause IMNsc fails to obtain the radix table information. It might be a programmatic error.

Effect IMNsc logs an error message and abends.

Response Examine the abend file and take action accordingly.

2523* INIT ERROR: Assign <assign name> :Missing

Cause The CGF assign is missing from the LCONF file while the IMN-AUTO-ROUTING is ENABLED

Effect IMNsc cannot process the assign; IMNsc initialization fails.

Response Fix the assign in the LCONF file. Restart or warmboot IMNsc.

3601 PROC ERROR: <PIN/MAC/MSG> Keychange Failure Dest: <node Id> <msg class> Idx: <key index> Op: <get ICF/get KEYF/generate Key/update KEYF/send to EP/no context/no timers>

Cause The indicated key change request could not be constructed or sent to the network.

Effect IMNsc allows the key change timer to expire and then notifies the IMNM process of the key change failure.

Response If the "Op" field contains "no context" or "no timer" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either an ICF or KEYF access problem, an entry point problem or a security device problem. Check previous log messages for Guardian errors to determine the appropriate response.

3602/3603 TRACE07: <PIN/MAC/MSG> KeyChange Init Dest: <node Id> Index: <key index> Cntr: <key counter value>

Cause Trace bit 7 is turned on and a key change request for the indicated key type and index was sent to the network.

Effect IMNsc logs the message and continues.

Response None required. This message is for information only.

3604 ERROR: B24 Response Code <resp-code> not found, using Interac 06 (edit error) in response message...
ERROR: MsgType= <msg-type> SubType= <msg-subtype> AcqNode=<acq-node>
Card=<card-num> SeqNum=<seq-num> Amt=<amnt> Resp=<resp-code>

Cause The BASE24-atm response code could not be translated to an Interac ISO response code.

Effect IMNsc logs the message to the ILF and reverses the transaction.

Response This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

3605/3606 TRACE03: ATM Msg edit error in <msg-text>

Cause To aid tracing of edit error in message.

Effect IMNsc displays additional information about the trace.

Response None required. This message is for information only.

3901/3902 ADMIN ERROR: Bad Destination <node Id> <msg class>

Cause An ADMIN request was received that contained an invalid destination.

Effect IMNsc cannot format an administrative network transaction.

Response This indicates an internal code problem with the IMNA requester or server.
Contact your vendor representative.

3903 ADMIN ERROR: Dest: <node Id> Invalid Proc Code: <processing code>

Cause An ADMIN request was received that contained an invalid processing code.

Effect IMNsc cannot format an administrative network transaction.

Response This indicates an internal code problem with the IMNA requester or server.
Contact your vendor representative.

3904 ADMIN ERROR: Dest: <node Id> Unable to add record to SAF

Cause An Administrative network transaction could not be added to the SAF file for the indicated destination.

Effect IMNsc does not send the transaction.

Response Check previous log messages for Guardian errors to determine the appropriate response.
Resend the ADMIN message using the IMNA screen.

3905 ADMIN ERROR: Dest:<node Id> Unable to add record to ADMIN File.

Cause An ADMIN record could not be added to the ADMIN file.

Effect IMNsc does not send the administrative network transaction.

Response Check previous log messages for GUARADIAN errors to determine the appropriate response. Resend the ADMIN message using the IMNA screen.

3906 ADMIN Message added to file and SAF at <yy:mm:dd hh:mm:ss.cc> Dest: <node Id> <msg class>

Cause An ADMIN request was processed and an administrative network transaction was added to the SAF file for the indicated destination.

Effect IMNsc sends the transaction when it reaches the top of the SAF cycle.

Response None required.

3907 IMN ERROR: Handshake Send Failure EP: <entry point Id> RC: <response code> SS:<ILF substate> Fno: <file number> Err: <Guardian error code>

Cause A handshake request could not be sent to the indicated entry point.

Effect The entry point remains uninitialized.

Response Check the Guardian error code to determine the appropriate response. Restart the entry point if necessary.

3908 TRACE05: Passthru Dest: <node Id> Len: <msg length>

Cause Trace bit 5 is turned on and a passthrough request is about to be sent.

Effect IMNsc sends the passthrough request.

Response None required. This message is for information only.

3909/3910 IMN ERROR: PASS THRU failure Dest:<node Id> EP:<entry point Id> Err:<pass through-msg>

Cause A passthrough message send fails to the indicated entry point.

Effect IMNsc logs the message and continues.

Response Check the entry point status.

3920 PROC ERROR: Timer insert failure Type: <timer type> SubType: <timer subtype> count: <timer number> of <total timers>

Cause A timer start fails before sending a request to BASE24 or to the network.

Effect IMNsc sends a system error response (ISO 96).

Response This indicates an internal code problem. Contact your vendor representative.

4200 TRACE05: IMN Msg edit error in <msg text>

Cause To help tracing of edit error in message.

Effect IMNsc displays additional information about the trace.

Response None required. This message is for information only.

4201 Pin failed to verify - kpe info missing from security block (msg type= <msg type>, destn= <node Id> <msg class>)

Cause A network message was received with a security block that was too short to contain the PIN key index or counter value.

Effect IMNsc cannot convert the network message to BASE24 format. IMNsc logs the message to the ILF and returns an edit error response (ISO 06).

Response This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

4202 Pin failed to verify - invalid kpe index in security block (msg type= <msg type>, kpe= <PIN key index> destn= <node Id> <msg class>)

Cause A network message was received with a PIN key index in the security block that was neither 1 nor 2.

Effect IMNsc cannot convert the network message to BASE24 format. IMNsc logs the message to the ILF and returns an edit error response (ISO 06).

Response This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

4203 Invalid Response: EP: <entry point Id> Cnxn: <connection Id> Hdr:<msg type> ISO:<iso info>

Cause An edit error occurred in the response message.

Effect If network management message (keyexchange message) the response message is logged and dropped. If financial transaction, then the response is sent back to the originator.

Response None required.

4301 LOGIC ERROR: Invalid Key Type: <Key type>

Cause An invalid key type was passed to an internal procedure.

Effect IMNsc cannot use the key type.

Response This indicates an internal code problem. Contact your vendor representative.

4501 PROC ERROR: Node:<IMNsc node Id> Issuer <PIN/MAC/MSG> key <key index> change rejected Dest:<node Id> Op: <SEM Init/KEYF Access/Key type/Translate/Keyf Update/Gen Resp/Send Resp/Unknown Err>

Cause A Key change request was received from the indicated node that could not be processed. The "Op" field indicates the operation that failed or the request field that was invalid.

Effect IMNsc rejects the key change request.

Response If the "Op" field contains "SEM Init", "Key Index", "Key Type", "Gen Resp" or "Unknown Err" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either a key translation problem, a KEYF access problem or an entry point problem. Check previous log messages for Guardian errors to determine the appropriate response.

4502 TRACE07: <PIN/MAC/MSG> KeyChange Rqst Dest: <node Id> Index: <key index> Cntr: <Key counter>

Cause Trace bit 7 is turned on and a key change request was received from the network.

Effect IMNsc processes the key change request.

Response None required. This message is for information only.

4503 Node:<IMNsc node Id> Iss <PIN/MAC/MSG> key <key index> updated Dest:<node Id>

Cause A valid key change request was processed.

Effect IMNsc stores the key information in the KEYF file and sends the IMNM process the new key data for distribution to other IMNsc processes.

Response None required.

4504 PROC ERROR: Node: <IMNsc node Id> Acq <PIN/MAC/MSG> Key <Key index> change rejected Dest: <node Id> Op: <Init Resp/No Context/ KEYF Get/KEYF update/KEK SeqErr/St:<status code>/Rc:<response code>/Unknown Err >

Cause A key change response was received from the indicated node that could not be processed. The "Op" field indicates the operation that failed or the request field that was invalid.

Effect IMNsc notifies the IMNM process of the Key change failure.

Response If the "Op" field contains "Init Resp", "No Context" or "Unknown Err" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either a KEYF access problem or a network or issuer problem. Check previous log messages for Guardian errors to determine the appropriate response.

4505 PROC ERROR: Node: <IMNsc node Id> Acq <PIN/MAC/MSG> Key <Key index> change rejected Dest: <node Id> Op: <Timer Failure >

Cause A key change response was received from the indicated node that could not be processed because the set of a new timer failed.

Effect IMNsc notifies the IMNM process of the Key change failure.

Response The CPU the IMNsc in running on might be run out of timer control block. Check the timer control block.

**4506 TRACE07: <PIN/MAC/MSG> KeyChange Resp Dest: <node Id> Stat: <status code>
Reas: <reason code> Resp: <response code> Index: < Key index> Cntr: <Key counter
value>**

Cause Trace bit 7 is turned on and a key change response was received from the network.

Effect IMNsc processed the response.

Response None required. This message is for information only.

**4507 Node: <IMNsc node Id> Acq <PIN/MAC/MSG> Key <key index> updated Dest: <node
Id>**

Cause A valid key change response was processed.

Effect IMNsc stores the key information in the KEYF file and sends the IMN< process the new
key date for distribution to other IMNsc processes.

Response None required.

**4508 PROC ERROR: Timer insert failure Type: <timer type> SubType: <timer subtype>
Count: <timer number> of <total timers>**

Cause A timer could not be started before sending a request to BASE24 or to the network.

Effect IMNsc sends a system error response (ISO 96).

Response This indicates an internal code problem. Contact your vendor representative.

**4509/4511 Mismatched KEK in FKT, Idx= FKT KEK= <kek>
KEYF KEK= <kek> Updating FKT**

Cause KEK in KEYF does not match KEK in FKT table.

Effect Replace FKT KEK with KEYF KEK.

Response None required.

**4510 Mismatched KEK in DCT, Idx= <index> DCT KEK= <kek>
KEYF KEK= <kek> Updating DCT**

Cause KEK in KEYF does not match KEK in DCT table.

Effect DCT KEK will be replaced by KEYF KEK.

Response None required.

5101 Unrecognized NCS command from <source> - # byte msg dropped: <command text>

Cause An invalid NCS command was received.

Effect IMNsc cannot process the command.

Response Check the syntax of the command and resend it.

5102 Unrecognized IMNM request code <request code>

Cause An IMNM request was received that contained an unrecognized request code.

Effect IMNsc cannot process the request.

Response This indicates an internal code problem. Contact your vendor representative.

5201 Unrecognized command <command text>

Cause An NCS command was received that contained an unrecognized command token.

Effect IMNsc ignores the command.

Response Check the list of NCS commands and send the correct command token.

5202 IMNSC trace switch: <new trace bit settings>

Cause An NCS TRACE command was received

Effect IMNsc sets the trace bits according to the command arguments.

Response None required. This message is for information only.

5203 Operator issued command to DEBUG

Cause An NCS DEBUG command was received.

Effect IMNsc calls DEBUG.

Response The IMNsc process may be inspected. Note that only vendor personnel should issue the DEBUG command.

5204 Operator issued command to programmatic DUMP

Cause An NCS DUMP command was received.

Effect IMNsc performs a programmatic dump.

Response The dump file may be examined. Note that only vendor personal should issue the DUMP command.

5205 Command not yet supported.

Cause An NCS command was received that is not yet supported.

Effect IMNsc does not process the command.

Response Contact your vendor representative for further information.

5206 Invalid Command <command>

Cause An invalid NCS command was entered.

Effect IMNsc rejects the command.

Response Enter a valid NCS command.

5301 Process Trace Audit file A named <new-name>

Cause An NCS ANA/ANB command was received and the indicated trace audit file was renamed.

Effect IMNsc uses the new trace audit file name.

Response None required. This message is for information only.

5302 Process Trace Audit file <file-name> not renamed

Cause An NCS ANA/ANB command was received but the name of the indicated audit trace file could not be changed.

Effect IMNsc continues using the previous audit trace file name if possible.

Response Resend the ANA/ANB command with a different file name.

5303 Process Trace Audit file B named <new-name>

Cause An NCS ANA/ANB command was received and the indicated trace audit file was renamed.

Effect IMNsc uses the new trace audit file name.

Response None required.

5304 Process Trace Audit file B not renamed

Cause	An NCS ANA/ANB command was received but the name of the indicated audit trace file could not be changed.
Effect	IMNsc continues using the previous audit trace file name if possible.
Response	Resend the ANA/ANB command with a different file name.

5305 Process Trace Audit extent not set

Cause	An NCS ADX command was received but the trace audit extent size specified was not numeric.
Effect	IMNsc cannot process the command.
Response	Resend the ADX command with a valid extent size.

5306 Process Trace Audit extent set to <extent size>

Cause	An NCS ADX command was received.
Effect	IMNsc creates subsequent trace audit files with the indicated extent size.
Response	None required.

5307 Process Trace Audit file not switched

Cause	An NCS SWA command was received but the trace audit file could not be switched.
Effect	IMNsc does not switch the trace audit files.
Response	Resend the ANA, ANB, and SWA commands.

5308 Process Trace Audit file switched

Cause An NCS SWA command was received and the trace audit file was switched to audit file A and the audit file name A was changed to audit file name B.

Effect IMNsc begins using the new trace audit file.

Response None required.

5309 Process Trace Audit file - <file name>

Cause The Trace audit file exists.

Effect IMNsc logs the trace audit file name.

Response None required.

5310 Process Trace Audit file - NO FILE NAME

Cause The Trace audit file does not exist.

Effect IMNsc logs the error message.

Response None required.

5311 Process Trace Audit file A - <file name>

Cause Trace audit file A exists.

Effect IMNsc logs trace audit file A name.

Response None required.

5312 Process Trace Audit file A - NO FILE NAME

Cause Trace audit file A does not exist.

Effect IMNsc logs the error message.

Response None required.

5313 Process Trace Audit file B - <file name>

Cause Trace audit file B exists.

Effect IMNsc logs trace audit file B name.

Response None required.

5314 Process Trace Audit file B - NO FILE NAME

Cause Trace audit file B does not exist.

Effect IMNsc logs the error message.

Response None required.

5315 Process Trace Audit file extent size = <file extent size>

Cause Display the audit file extent size.

Effect None.

Response None required.

5409-5410 Process Trace Audit filename is bad - <file name>

Cause An NCS ANA/ANB command was received but the file name specified was invalid.

Effect IMNsc ignores the command.

Response Resend the command with a valid file name.

5411 ATM Cutover date set to :<YYMMDD>

Cause An NCS cutover command was received and the ATM cutover date was set.

Effect IMNsc begins using the new cutover date.

Response None required.

5412 Cutover command not supported for POS

Cause An NCS cutover command was received for the POS product.

Effect IMNsc ignores the command.

Response IMNsc does not support the POS product.

5413 Invalid product type <product type>

Cause An NCS cutover command was received that contained an invalid product type.

Effect IMNsc ignores the command.

Response Resend the command with the correct product type.

5414 RELOADEP ALL successfully processed

Cause An NCS RELOADEP command was received and successfully processed.

Effort IMNsc continues with the new entry point configuration.

Response None required.

5415 RELOADEP ALL *failed* because of EPCF error

Cause An NCS RELOADEP command was received but the reload failed due to an error on the EPCF file.

Effort IMNsc cannot complete the entry point reload.

Response Check previous log messages for Guardian errors to determine the appropriate response.

5416-5420 RELOADEP <entry point Id>: Entry Point <DELETED/NOT FOUND/UPDATED/ADDED/TABLE FULL>

Cause An NCS RELOADEP command was received and the indicated event occurred.

Effect IMNsc continues processing the command.

Response If the entry point table is full, the program limit has been reached. Configure another IMNsc process.

5421/5422 Entry Point ID <entry point ID> was not found in EPT

Cause An NCS START/STOP EP command was received and the indicated entry point was not found in the EPT.

Effect IMNsc logs the message and continues processing.

Response Check the entry point entered in the NCS command.

5423 Entry Point ID <entry point ID> to CIL <CIL process name> STARTED

Cause EP has been started.

Effect IMNsc will use the EP.

Response None required.

5424 Entry Point ID <entry point ID> has already started

Cause Attempt to activate an already started entry point.

Effect IMNsc will not process the start request because the EP is already in “STARTED” state.

Response None required.

5425 Entry Point ID <entry point ID> not found in EPCF file. Reload all EPs

Cause Attempt to activate an entry point which does not exist in the EPCT table.

Effect IMNsc cannot use this EP.

Response Reload all entry points from disk file.

5426 Entry Point ID <entry point ID> not started - EP has non-SCD message class <msg Class>

Cause EP has non-SCD message class.

Effect IMNsc will not allow operator to start non-SCD class EP.

Response Reenter the NCS command for an EP that has SCD message class.

5427 Invalid Entry Point ID <entry point ID>

Cause An NCS START EP or STOP EP command was received but the entry point specified was invalid.

Effect IMNsc ignores the command.

Response Resend the NCS command with the correct entry point Id.

5428/5430 No SAF records exist (destn = <node Id> <msg class>, SAF file= <file name>)

Cause An NCS SAFDELETE command was received but there were no SAF records present for the specified destination.

Effect IMNsc ignores the command.

Response None required.

5431 Top SAF record deleted (destn= <node ID> <msg class>, SAF file= <file name> timestamp= <YYYY MM DD HH:MM:SS>)

Cause An NCS SAFDELETE command was received and the top SAF record was deleted.

Effect IMNsc continues processing the remainder of the SAF.

Response None required.

5432 Undefined status given: <connection status>

Cause An NCS SET command was received that contained an invalid connection state.

Effect IMNsc ignores the command.

Response Resend the command with the correct status.

5433 Invalid pacing state given: <pacing state>

Cause An NCS PACING STATE command was received that contained an invalid pacing state.

Effect IMNsc ignores the command.

Response Resend the command with the correct pacing state.

5434 Previous Pacing State: <previous state>, New Pacing State: <new state>

Cause An NCS PACING STATE command was received and the pacing state was set to the indicated value.

Effect IMNsc continues with the new pacing state.

Response None required.

5435* This command is only valid in IMN Manager

Cause An NCS SET command was issued for the IMNsc process, but this command is applicable only for the IMNM process.

Effect IMNsc ignores the command.

Response Deliver the same command to the IMNM process.

5440 Invalid Date <YYMMDD>

Cause An NCS CUTOVER command was received that contained an invalid date.

Effect IMNsc ignores the command.

Response Resend the command with correct date.

5501 - 5503 <date> <msg Text>

Cause Operator response message. Informational display.

Effect None.

Response None required.

Message text could be one of the following:

1. "BASE24-atm DATE: \\\\"
2. "INTERAC DATE: \\\\", BANK: \\\\"
3. "# outbound requests pending of # maximum requests"
4. "# inbound requests pending of # maximum requests"
5. "# timers active of # maximum timers"
6. "\$ IMNLF records of \$ maximum IMNLF records, # % full"
7. "# Entry Points defined in EPT"
8. "# Entry Points stopped # Entry Points unavailable"
9. "# Entry Points pending # Entry Points available"

5504 dct[index] <node-Id> <node-name> <msgClass> obp= <string> ibp= <string> link= <num>

Cause Display the DCT information (B=Blocked, N=Normal).

Effect None.

Response None required.

5505 dct[index] <filename> fnum=<num> T=<n> VR=<n> IR=<n> I-O=<status>(FM)

Cause Display the DCT SAF information.

Effect None.

Response None required.

5506 <msg text> idx= <n> ctr= <n> max= <n> sync= <n> st= <n>, key= <value>
kek^ctr= <value>

Cause Display the DCT key information.

Effect None.

Response None required.

Message text could be one of the following:

1. "dct[##] \\\\\\\ \\\\\\\ \\\\ =====> KEY INFO <=====
2. "MAC idx= # ctr= # max= # sync= # st= # key= \? kek^ctr= \?"
3. "MAC badctr= # badmax= # failctr= # failmax= #"
4. "MSG idx= # ctr= # max= # sync= # st= # key= \? kek^ctr= \?"
5. "PIN idx= # ctr= # max= # sync= # st= # key= \? kek^ctr= \?"
6. "PIN Block Failure ctr= # PIN Block Failure max= #"
7. "KEK okcc= # okcmax= # toc= # tom= # rej^ctr= # rej^max= # isyn= \? osyn= \?"
8. "\\\: FIL= # kek= \? "" "" out^seq^no= \? in^seq^no= \? "
9. "\\\: FIL= # key[0]= \? key[1]= \? kek^ctr[0]= \? kek^ctr[1]= \? sync^err^ctr= #"
10. "INBOUND KEYS: fkt^x= # ifac= # ifamax= # ikcc= # ikcmax= #"

5507 IPT no longer defined in IMNSC

Cause Display the IPT information.

Effect None.

Response None required.

5508 <CIL-PID> <FNUM> <SFNUM> <FID> <MC> <SB> <SS-ID> <SEL-THRU>
<CUR-THRU> <NWD>

Cause Display the EPT information.

Effect None.

Response None required.

5509 BIN[index] <card prefix> <node Id> <length>

Cause Display the BIN table information.

Effect None.

Response None required.

5510 BIN = <filename> fnum= <file number>

Cause Display the various files information.

Effect None.

Response None required.

Message text could be one of the following:

1. EPCF = <filename> fnum= #
2. BIN = <filename> fnum= #
3. KEYF = <filename> fnum= #
4. ADMN = <filename> fnum= #
5. IMNM = <filename> fnum= #
6. ILF: ## file= <filename> fnum= # ferror= #
7. ILF: date= \\\
8. SETL: atm date= \\\ switch date= \\\

**5511 Timer type= <num> subtype= <num> exptime= <DD hh:mm:ss.tt>
<timer-depth> timers active of <number of timers> maximum timers**

Cause Display various timers' information.

Effect None.

Response None required.

Response	None required.
----------	----------------

Response	None required.
----------	----------------

Response	Resend the command with the correct option or parameter.
----------	--

Response	None required.
----------	----------------

5516 <node id> <msg class> <timer value> are required REPEAT parameters

Cause	An NCS PERFORMANCE REPEAT command was received that contained missing or invalid parameters.
Effect	IMNsc ignores the command.
Response	Resend the command with the correct parameters.

5517 Repeat command ignored - invalid time given: <repeat time>

Cause	An NCS PERFORMANCE REPEAT command was received that contained an invalid repeat time interval.
Effect	IMNsc ignores the command.
Response	Resend the command with the correct repeat time interval.

5518 Performance repeat rate for <node Id> <Msg class> set to <repeat interval> minutes (0=off)

Cause	An NCS PERFORMANCE REPEAT command was received and the performance repeat interval was set to the indicated value.
Effect	IMNsc sets the repeat interval to the indicated value. If the interval is greater than 0, a performance repeat timer is posted.
Response	None required.

5519 Invalid PERFORMANCE sub-command given: <command text>

Cause	An NCS PERFORMANCE command was received that contained an invalid performance option.
Effect	IMNsc ignores the command.
Response	Resend the command with the correct option specified.

5520 Can't find the node <node Id> in DCT

Cause An NCS PERFORMANCE command was received that contained an unknown node Id.

Effect IMNsc ignores the command.

Response Resend the command with the correct node Id.

5601 Invalid Filename <file name>

Cause An NCS SWL command was received that contained an invalid file name.

Effect IMNsc ignores the command.

Response Resend the command with the correct file name.

5602 Invalid IMNM Key Change command length :<cmd-length>

Cause Invalid IMNM key change command was received.

Effect IMNsc ignores the command.

Response This indicates an internal code problem. Contact your vendor representative.

5603 Invalid IMNM Key Change key type: <key-type>

Cause Key change command for an invalid key type was received.

Effect IMNsc ignores the command

Response This indicates an internal code problem. Contact your vendor representative.

5604 Invalid IMNM Set Key Info command length: <IMNM msg length>

Cause An IMNM invalid set key info message was received that was not the expected length.

Effect IMNsc ignores the message.

Response This indicates an internal code problem. Contact your vendor representative.

5605 Invalid IMNM Set Key Info fil id :<FIL Id>

Cause An IMNM set key info message was received that contained an invalid FIL Id.

Effect IMNsc ignores the message.

Response This indicates an internal code problem. Contact your vendor representative.

5606 Invalid IMNM Set Key Info key index :<key index>

Cause An IMNM set key info message was received that contained an invalid key index.

Effect IMNsc ignores the message.

Response This indicates an internal code problem. Contact your vendor representative.

5607 Invalid IMNM Set Key Info key type: <key type>

Cause An IMNM set key info message was received that contained an invalid key type.

Effect IMNsc ignores the message.

Response Check the syntax of the command. Key type must be either PIN or MAC key. The MSG key type is not supported in IMNsc.

5608 Invalid IMNM Alter Pacing Dest command length :<cmd-legth>

Cause An invalid IMNM Alter Pacing command was received.

Effect IMNsc ignores the command.

Response This indicates an internal code problem. Contact your vendor representative.

5609* Invalid SHOW command given: <cmd>

Cause An invalid SHOW command was received.

Effect IMNsc ignores the command.

Response Change the argument for the show command (CGT or DCT) and reissue the command.

5610 Invalid IMNM Saf Count Modify command length :<cmd-length>

Cause An invalid IMNM SAF Count Modify command was received.

Effect IMNsc ignores the command.

Response This indicates an internal code problem. Contact your vendor representative.

5611 <SAF transaction count> transactions added to SAF for destination <node ID> msg class>

Cause An IMNM SAF COUNT MODIFY command was received from the IMNM process and the transaction count for the destination was changed.

Effect IMNsc continues processing with the new transaction count.

Response None required.

5612 Invalid IMNM Saf Count Modify command length :#

Cause Invalid IMNM SAF Count Modify command was received.

Effect IMNsc ignores the command.

Response This indicates an internal code problem. Contact your vendor representative.

5613 Invalid number of destinations in IMNM <IMNM msg type> command : <destination count>

Cause An IMNM message was received that contained an invalid number of destinations.

Effect IMNsc ignores the message.

Response This indicates an internal code problem. Contact your vendor representative.

5614 The SAF State for the destination '<node-ID> <msg-cls>' from the IMNM was ignored. Check the ICF and the IMNM assign value in the LCONF

Cause The destination in the message was NOT found in the DCT. The IMNsc may be receiving SAF state messages from the wrong IMNM process. The ICF is incorrect or the IMNM & IMNsc are out-of-sync with the ICF or the IMNM process name in LCONF is incorrect for this logical network (LN).

Effect The SAF state for the destination is ignored.

Response Check the process name of the IMNM assign value in the LCONF against the IMNM process name defined for the environment. Send a WARMBOOT command using the NCS operator screen to the IMNM process.

5615 Invalid IMNM Warmboot command length :<cmd-length>

Cause An invalid IMNM warmboot command was received.

Effect IMNsc ignores the command.

Response This indicates an internal code problem. Contact your vendor representative.

5616 Invalid Destination <node Id> <msg class>

Cause An NCS command was received that contained an invalid node Id or message class in the DCT.

Effect IMNsc ignores the command.

Response Resend the command with the correct destination information.

5617 Can't find the destination '<node Id> <msg class>' in DCT

Cause An NCS command was received that contained an unknown destination.

Effect IMNsc ignores the command.

Response Resend the command with the correct destination information.

5618* Invalid Destination <node Id> <msg class>

Cause An NCS command was received that contained an invalid node Id or message class checked against the CGT file.

Effect IMNsc ignores the command.

Response Resend the command with the correct destination information.

5619* Can't find the destination '<node Id> <msg class>' in CGT

Cause An NCS command was received that contained an invalid connection group ID as destination.

Effect IMNsc ignores the command.

Response Resend the command with the correct destination information.

5620 Invalid IMNM Set command length : <cmd-length>

Cause Invalid Set command length sent from IMNM.

Effect IMNsc ignores the command.

Response Check the IMNM SET command.

5621 No ATM record found in the TKN file - all STM tokens will be logged to the ILF

Cause No ATM record was found in the TKN file with a FIID that is "IMN<blank>".

Effect All tokens are logged to the ILF.

Response Check token file configuration.

5622 Warmbooting IMNsc process <IMNsc process name> on node= <IMNsc node Id>

Cause An NCS or IMNsc WARMBOOT command was received and the warmboot processing is about to begin.

Effect IMNsc begins the warmboot processing.

Response Check subsequent log message to determine if the warmboot completed successfully.

5623 WARMBOOT *failed* because of LCONF error

Cause An NCS or IMNM WARMBOOT command was received but the warmboot failed due to an error on the LCONF file.

Effect IMNsc cannot complete the warmboot and may be in an inconsistent state.

Response Check previous log messages for Guardian errors to determine the appropriate response. Repeat the warmboot or stop and start the IMNsc.

5624 WARMBOOT completed successfully -- New status implemented

Cause	An NCS or IMNM WARMBOOT command was received and the warmboot was successfully completed.
Effect	IMNsc continues processing with the new configuration.
Response	None required.

5625 WARMBOOT errors - correct and retry warmboot

Cause	An NCS or IMNM WARMBOOT command was received but the warmboot operation failed.
Effect	IMNsc cannot complete the warmboot and may be in an inconsistent state.
Response	Check previous log messages for Guardian errors to determined the appropriate response. Repeat the warmboot or stop and start the IMNsc.

5630 Invalid KEK Value in DCT :<kek> replaced with : <kek>

Cause	The KEK sent from IMNM is not the same as the one stored in DCT.
Effect	The DCT will be updated.
Response	None required.

5631 Invalid KEK Value in FKT :<kek> replaced with : <kek>

Cause	The KEK sent from IMNM is not the same as the one stored in FKT.
Effect	The FKT will be updated.
Response	None required.

5701* **===== SHOW DCT COMMAND =====**
ACQ CNXN ISS CNXN CNXN CNXN ROUTING
STATE STATE STATUS GRP ID METHOD
<acq-cnxn-state> <iss-cnxn-state> <status> <cnxn-grp> <routing-method>

Cause Operator issued the SHOW DCT command.

Effect The contents of the DCT table will be displayed.

Response None required. This message is for information only.

5702* **===== SHOW CGT COMMAND =====**
NODE MSG NODE ROUTING CNXN ACQ CNXN ISS CNXN
ID CLASS NAME METHOD STATUS STATE STATE
<node-id><msg-cls> <node-name><routing-method><status><acq-cnxn-state><iss-cnxn-state>

Cause Operator issued the SHOW CGT command.

Effect The contents of the CGT table will be displayed.

Response None required. This message is for information only.

6101 Entry Point ID <entry point Id> to CIL <CIL process name> STOPPED

Cause An NCS START EP command was received but the indicated entry point was already started.

Effect IMNsc logs the message and continues.

Response None required.

6102 Entry Point ID <entry point Id> has already stopped

Cause An NCS command was received to stop the indicated entry point and the entry point was already stopped.

Effect IMNsc logs the message and continues.

Response Restart the entry point if required.

6103 PROC ERROR: Write to closed EP: <entry point Id> State: <entry point state> PID: <CIL process name>

Cause An attempt was made to write a message to an entry point that was closed.

Effect IMNsc cannot send the message to the indicated entry point.

Response This indicates an internal code problem. Contact your vendor representative.

6104 TRACE05: Write to EP: <entry point Id> Cnxn: <connection Id> Type: <msg type, subtype> status: <status and reason codes>

Cause Trace bit 5 is turned on and a message is about to be written to the indicated entry point.

Effect IMNsc writes the message to the entry point.

Response None required. This message is for information only.

6105 IO ERROR: Write to PID: <CIL process name> EP: <entry point Id> State: <entry point state> Err: <Guardian error code>

Cause An I/O error occurred on a write to the indicated entry point.

Effect IMNsc closes the entry point and re-opens it when the recovery timer expires.

Response Check the Guardian error code to determine the appropriate response. Check that the CIL process is running.

6106 TRACE05: No EP Selected

Cause Trace bit 5 is turned on and no entry point could be selected for a message.

Effect The message is not sent to the network.

Response Check the status of all entry points.

6107 MACing not enabled for destn: <node Id> <msg class>, msg type: <msg type>

Cause	A message for the indicated destination is to be sent or was received but MAC generation is not enabled for the destination.
Effect	IMNsc does not generate or verify the MAC for the destination.
Response	If required, turn MAC generation on for the destination using the ICF screen and restart or warmboot IMNsc.

6108 ERROR: Unable to extract security block, msg type: <msg type>

Cause	A message with a missing security block was passed to the MAC generation procedure.
Effect	IMNsc cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6109 Error: Invalid data in sec block (type <msg type>, kmac: <MAC key index>, fil: <FIL ID>

Cause	A message with an invalid MAC key or Acquirer FIL Id in the security block was passed to the MAC generation procedure.
Effect	IMNsc cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6110 No MAC keys available for destn: <node Id> <msg class>, msg type:<msg type>

Cause	A response message was received but MAC key data cannot be found in KEYF to verify MAC field (no key data has been received from the indicated destination).
Effect	IMNsc cannot generate or verify the MAC. If the message is a request, a “No keys” response is returned (ISO 85).
Response	Contact operations personnel at the indicated destination to determine why no key change request has been sent.

6111 Unable to generate MAC (Can't extract required fields) in <msg type> msg

Cause	A message was passed to the MAC generation procedure and the required fields for generating the MAC could not be extracted from the message.
Effect	IMNsc cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6112 Unable to generate MAC (pin^mac^generate error: <error code>) in <msg type> msg

Cause	A message was passed to the MAC generation procedure and the call to the security device access procedure failed.
Effect	IMNsc cannot generate the MAC and does not send the message.
Response	Check previous log messages for Guardian errors on the security device to determine the appropriate response. If no such errors, this may indicate an internal code problem. Contact your vendor representative.

6113 Unable to generate MAC, encrypt data (hpsm^mac^generate^date^encrypt^error: <error-code>) in <msg type> msg

Cause	A message was passed to the MAC generation procedure and the call to the security device access procedure failed.
Effect	IMNsc cannot generate the MAC and does not send the message.
Response	Check previous log messages for Guardian errors on the security device to determine the appropriate response. If no such errors, this may indicate an internal code problem. Contact your vendor representative.

6114 MAC failed to verify - edit error (msg type= <msg type> response= <response code>)

Cause	A message was received from the network that contained an invalid or missing field.
Effect	IMNsc logs the message. If the message was a request, IMNsc returns an edit error response (IOS 06).
Response	This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

6115 MAC failed to verify (msg type= (msg type= <msg type> response= <response code> destn= <msg class> <msg class>)

Cause A message was received from the network that contained a bad MAC value.

Effect IMNsc logs the message. If the message was a request, IMNsc returns a bad MAC error response (ISO 63).

Response MAC errors are automatically recovered by the Acquirer node by changing the MAC key when the number of MAC failures has exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNsc. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

6116 MAC failed to verify - sync error (msg type= <msg type> MAC ctr rcvd= <MAC key counter>, expecting <expected MAC key counter> response= <response code> destn= <node Id> <msg class>)

Cause A message was received from the network that contained a lower MAC key counter value than expected in the security block.

Effect IMNsc logs the message to the ILF. If the message was a request, IMNsc returns a MAC sync error response (ISO 88).

Response MAC sync errors are automatically recovered by the Acquirer node by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6117 Acct Bal failed to verify - sync error (msg type= <msg type> KME ctr rcvd= <MSG key counter>, expecting= <expected MSG key counter> response= <response code> destn= <node Id> <msg class>)

Cause A response message was received from the network that contained a lower MSG key counter value than expected in the security block.

Effect IMNsc logs the message to the ILF.

Response MAC sync errors are automatically recovered by the Acquirer node by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6118 MAC failed to verify - SM error (msg type= <msg type> HPSM error= <error code> response= <response code>)

Cause A message was received from the network but its MAC could not be verified due to an error accessing the security device.

Effect IMNsc logs the message to the ILF. If the message is a request, IMNsc returns a system error response (ISO 96).

Response Check previous log messages for Guardian error codes to determine the appropriate response. It may be necessary to stop and start the security device handler process and then warmboot all processes that access the device. If the problem persists, contact your vendor representative.

6119 LOGIC ERROR: bad response code (msg type= <msg type>, response= <response code>)

Cause A message was received from the network and an invalid response code was passed to the logging procedure from the MAC verification procedure.

Effect IMNsc logs the message to the ILF.

Response This indicates an internal code problem. Contact your vendor representative.

6120 MACing not enabled for destn= <node Id> <msg class>, msg type:<msg type>

Cause A message for the indicated destination is to be sent or was received, but MAC generation is not enabled for the destination.

Effect IMNsc does not generate or verify the MAC for the destination.

Response If required, turn MAC generation on for the destination using the ICF screen and restart or warmboot IMNsc.

6121 MAC failed to verify - unable to get security block (msg type= <msg type>)

Cause A message was received from the network without the expected security block.

Effect IMNsc logs the message to the ILF. If the message is a request, IMNsc returns an edit error Response (ISO 06).

Response This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6122 MAC failed to verify - edit error in security block (msg type= <msg type>, kmac= <MAC key index>, fil= <FIL Id>)

Cause A message was received from the network that contained an invalid security block.

Effect IMNsc logs the message to the ILF. If the message is a request, IMNsc rejects the message with an edit error Response (ISO 06).

Response This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6123 Acct Bal failed to verify - kme info missing from security block (msg type= <msg type>, destn= <node Id> <msg class>

Cause A message was received from the network that contained a security block that was not long enough to contain the MSG key index or counter.

Effect IMNsc logs the message to the ILF.

Response This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6125 TRACE03: ATM Msg to Dest: <symbolic process name> Typ: <msg type> Tran: <processing code> Resp: <BASE24 response code> Len:<msg-length>

Cause Trace bit 3 is turned on and an ATM message is about to be written to the XPNET.

Effect IMNsc writes the message to the XPNET.

Response None required. This message is for information only.

6126 MAC failed to verify - new MAC key translation failed (msg type= <msg type>)

Cause A MAC key change request was received from the network but the key value could not be translated.

Effect IMNsc logs the message to the ILF. IMNsc returns a system error response (ISO 96).

Response Check previous log messages for Guardian errors on the security device to determine the appropriate response. If no such errors, this may indicate an internal code problem. Contact your vendor representative.

6128 TRACE02: Cmd Dest: <symbolic process name> Len: <msg length> Txt: <msg test>

Cause Trace bit 2 is turned on and an NCS message is about to be written to the XPNET.

Effect IMNsc writes the message to the XPNET.

Response None required. This message is for information only.

6129 PROC ERROR: NETWRITE failure <msg failure flag> Err: <msg failure code>

Cause A write to the XPNET failed.

Effect IMNsc cannot send a message to a destination process.

Response Check the status of the XPNET. If no problems, this indicates an internal code problem. Contact your vendor representative.

6130 LOGIC ERROR: Invalid fil ID: <FIL Id>

Cause An invalid FIL Id was passed to the IMNM notification procedure.

Effect IMNsc cannot send the notification message to IMNM.

Response This indicates an internal code problem. Contact your vendor representative.

6131 LOGIC ERROR: Invalid key Type: <key-type>

Cause An invalid key type was passed to the IMNM notification procedure.

Effect IMNsc cannot send the notification message to IMNM.

Response This indicates an internal code problem. Contact your vendor representative.

6132 TRACE13: Notify IMNM Type: <IMNM msg type>

Cause Trace bit 13 is turned on and a message is about to be written to the IMNM process.

Effect IMNsc writes the message to the IMNM process.

Response None required. This message is for information only.

6133 Not able to send message to process <IMNM process>, error <Guardian error code>IMNM manager process <IMNM process name> closed for communication.

Cause A write to the IMNM process failed and IMNsc will close the process file.

Effect IMNsc cannot exchange messages with the IMNM process. IMNsc will attempt to re-open the IMNM process when the recovery timer expires.

Response Check the GURADIAN errors code to determine the specific nature of the error and take action accordingly. Restart the IMNM process if necessary.

6134 CSM rejected counter = <rejected count>, message class <msg class>, dest <node Id>

Cause The number of key change requests rejected by the indicated destination has reached the rejection threshold.

Effect IMNsc resets the counter, logs the message and continues.

Response If key change rejection alarms to a specific destination persist this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6134 CSM time-out counter = <time-out count>, message class <msg class>, dest <node Id>

Cause The number of outbound key change time-outs has reached the time-out count alarm threshold.

Effect IMNsc resets the counter, logs the message and continues.

Response If key change time-outs persist, increase the key change time-out interval using the ICF screen and restart or warmboot IMNsc.

6134 Inbound key conveyance alarm = <error count>, message class <msg class>, dest <node Id>

Cause	The number of key conveyance errors in inbound key change messages has reached the alarm threshold.
Effect	IMNsc resets the counter, logs the message and continues.
Response	If key conveyance alarms persist, this may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6134 Inbound MAC fail alarm = <MAC fail count>, message class <msg class>, dest <node Id>

Cause	The number of inbound MAC verify failures for the indicated node has reached the MAC failure alarm threshold.
Effect	IMNsc resets the counter, logs the message and continues.
Response	If MAC failure alarms for a specific destination persists, this may indicate an unauthorized attempt to modify protected message elements or an internal code problem with either the sending or receiving node. Each MAC error should be investigated by identifying the message and comparing the elements with the sending node to determine if the differences are due to intentional tampering or communications problems. Contact your vendor representative.

6134 Inbound <PIN/MAC/MSG> sync= <sync error count>, message class <msg class>, dest <node Id>

Cause	The number of key sync errors for the indicated key type has passed the sync error threshold.
Effect	IMNsc resets the counter, logs the message and continues.
Response	If key sync error alarms for a specific destination persist this may indicate an unauthorized attempt to modify encrypted fields or an internal code problem with either the sending or receiving node. The Issuer FIL operator should stop Acquirer transactions from being forwarded to the Issuer FIL by setting the status of the connection to the Acquirer FIL to "down". Contact your vendor representative.

6134 Outbound key conveyance alarm= <error count>, message class <msg class>, dest <node Id>

Cause The number of key conveyance errors in outbound key change messages has reached the alarm threshold.

Effect IMNsc resets the counter, logs the message and continues.

Response If key conveyance alarms persist, this may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6134 Outbound MAC fail alarm= <MAC fail count>, message class <msg class>, dest <node Id>

Cause The number of outbound MAC verify failures for the indicated node has reached the MAC failure alarm threshold.

Effect IMNsc resets the counter, logs the message and continues.

Response If MAC failure alarms for a specific destination persist this may indicate an unauthorized attempt to modify protected message elements or an internal code problem with either the sending or receiving node. Each MAC error should be investigated by identifying the message and comparing the elements with the sending node to determine if the differences are due to intentional tampering or to communications problems. Contact your vendor representative.

6135 TRACE01: utl^setCutoverTimer subtype: <timer subtype>

Cause Trace bit 1 is turned on and the indicated timer subtype is about to be posted.

Effect IMNsc posts the time-out.

Response None required. This message is for information only.

6136 LOGIC ERROR: Invalid Cutover SubType: <timer subtype>

Cause An invalid timer subtype was passed to the cutover time-out posting procedure.

Effect IMNsc cannot set the cutover timer.

Response This indicates an internal code problem. Contact your vendor representative.

6137 WARNING: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>

Cause	The switch date read from the ICF control record was not the expected switch date (system date if before cutover start, system date + 1 if after).
Effect	IMNsc uses the switch date from the ICF record.
Response	Change the ICF switch date to the date indicated and warmboot IMNsc unless testing of old transaction dates is being performed.

**6138 WARNING: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>
WARNING: Using Expected Date as Posting Date**

Cause	The switch date read from the ICF control record was not the expected switch date (system date if before cutover start, system date + 1 if after).
Effect	IMNsc uses the switch date from the ICF record, which will be updated with the expected date.
Response	None required. This message is normal if the IMNsc has been down for one or more then one cutovers.

6139 ERROR: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>

Cause	The switch date read from the ICF control record was not the expected switch date (system date if before cutover start, system date + 1 if after).
Effect	IMNsc initialization fails.
Response	Change the ICF switch date to the expected date.

**6140 TRACE05: SelectEp extX: <entry point table index> Ep: <CIL process name, subdevice>
NWD: <I/O outstanding count> Thruput: <throughput> Pacing: <pacing status>**

Cause	Trace bit 5 is turned on and the indicated entry point was selected for a message.
Effect	The message is sent to the entry point.
Response	None required. This message is for information only.

6141 MAC failed to verify (msg type= <msg type> response= <response code> destn= <node-Id> <msg class>)

Cause A message was received from the network that contained a bad MAC value.

Effect IMNsc logs the message. If the message was a request, IMNsc returns a bad MAC error response (ISO 63).

Response MAC errors are automatically recovered by the Acquirer node by changing the MAC key when the number of MAC failures has exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNsc. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

6142 MAC failed to verify - sync error (msg type= <msg type> MAC ctr rcvd= <MAC key counter>, expecting <expected MAC key counter> response= <response code> destn= <node Id> <msg class>)

Cause A message was received from the network that contained a lower MAC key counter value than expected in the security block.

Effect IMNsc logs the message to the ILF. If the message was a request, IMNsc returns a MAC sync error response (ISO 88).

Response MAC sync errors are automatically recovered by the Acquirer node by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6143 TRACE10: SAF mode Change Dest: <node-id> Mode: <saf mode>

Cause Trace bit 10 is turned on and the new SAF mode for the specified destination is displayed.

Effect IMNsc logs the message.

Response Display SAF to verify the new mode.

6144 Unable to translate PIN, generate MAC (hpsm^mac^generate^date^encrypt^error: <error code>) in <msg-type> msg

Cause A message was received from the network that failed PIN translation.

Effect IMNsc cannot translate the PIN in the message and does not send the message.

Response This may indicate an internal code problem. Contact your vendor representative.

**6145 DiMacKey1, “KEY Values (1), Idx = FKT KEK = <KEK key>
FKT KMAC = <MAC key>
DiMacKey2, “KEY Values (2), ENC KMAC = <MAC key index>
NEW KMAC = <MAC key index>**

Cause A network management/key exchange message was received from the network that contained a bad MAC value.

Effect IMNsc logs the message.

Response MAC errors are automatically recovered by the Acquirer node by changing the MAC key when the number of MAC failures had exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNsc. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

**6146 DiMacKey1, “KEY Values (1), Idx = FKT KEK = <KEK key>
FKT KMAC = <MAC key>
DiMacKey2, “KEY Values (2), ENC KMAC = <MAC key index>
NEW KMAC = <MAC key index>**

Cause A network management/key exchange message was received from the network that contained a key sync error.

Effect IMNsc logs the message in the ILF.

Response MAC sync errors are automatically recovered by the Acquirer node by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6148 MAC failed to verify - SM error (msg type= <msg type> HPSM error= <error code> response= <response code>)

Cause A message was received from the network but its MAC could not be verified due to an error accessing the security device.

Effect IMNsc logs the message to the ILF. If the message is a request, IMNsc returns a system error response (ISO 96).

Response Check previous log messages for Guardian error codes to determine the appropriate response. It may be necessary to stop and start the security device handler process and then warmboot all processes that access the device. If the problem persists, contact your vendor representative.

6149 LOGIC ERROR: bad response code (msg type= <msg type>, response= <response code>)

Cause A message was received from the network and an invalid response code was passed to the logging procedure from the MAC verification procedure.

Effect IMNsc logs the message to the ILF.

Response This indicates an internal code problem. Contact your vendor representative.

6150 Invalid Set CNXN Status: <connection status>

Cause An invalid connection status literal was passed to the connection status modification procedure.

Effect IMNsc cannot update the connection status.

Response This indicates an internal code problem. Contact your vendor representative.

6151 Cnxn status set (destn: <node Id>, msg class <msg class>, state: <new connection state>)

Cause The connection state for the indicated connection was set.

Effect IMNsc uses the new connection state.

Response None required.

6153* Invalid Set CNXN Status: <acq-cnxxn-status>

Cause An invalid acquirer connection status literal is passed to the connection status modification procedure.

Effect IMNsc cannot update the connection status.

Response Check the syntax of the command.

6160 TRACE09: Reloading DCT File:<file name>

Cause Trace bit 9 is turned on and the DCT table will be reloaded with information from the indicated KEYF file for Acquirer transactions.

Effect IMNsc reloads the inbound key table.

Response None required. This message is for information only.

6161 TRACE09: Reloading FKT File:<file name>

Cause Trace bit 9 is turned on and the inbound key table will be reloaded with information from the indicated KEYF file for issuer transactions.

Effect IMNsc reloads the inbound key table.

Response None required. This message is for information only.

6170 Error while attempting to get token

Cause IMNsc failed to read an existing token in FIL user data from the STM.

Effect A program dump will be created and the process abends.

Response Inspect the program dump file for errors. Purge B24 queue to get rid of the erroneous message before restarting the process.

6171 Error while attempting to get token

Cause	Failed to retrieve an existing token in FIL user data from the STM when writing FIL user data to the STM message.
Effect	The STM could not be updated with the FIL data. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors. Purge B24 queue to get rid of the erroneous message before restarting the process.

6172 No room to add token

Cause	Not enough space to add FIL data token.
Effect	Failed to write FIL data to the STM.
Response	Investigate the reason why there is no room in the STM. It could be due to the size of the RPQ tokens in the message.

6173 Error while attempting to add token

Cause	The token address is out of bounds or a required parameter is missing.
Effect	Failed to write account balance token data to the STM. A program dump will be created and the process abends.
Response	Investigate the reason why there is no room in the STM. It could be due to the size of the RPQ tokens in the message.

6174 Error while attempting to update token

Cause	An error occurred while trying to update the FIL data.
Effect	Failed to write FIL data to the STM. A program dump will be created and the process abends.
Response	Inspect the program dump file for error. The XPNET should restart the process.

6175 Error while attempting to get token

Cause	Failed to retrieve account balance data from the STM.
Effect	The STM will not be updated with the account balance data token. A program dump will be created and the process abends.
Response	Inspect the program dump file for error. Purge B24 queue to get rid of the erroneous message before restarting the process.

6176 No room to add token

Cause	Not enough space to add account balance data token to STM.
Effect	Failed to write account balance data to the STM.
Response	Investigate the reason why there is no room in the STM. Could be due to the size of the RPQ tokens in the message.

6177 Error while attempting to add token

Cause	The token address is out of bounds or a required parameter is missing.
Effect	Failed to write account balance token data to the STM. A program dump will be created and the process abends.
Response	Investigate the reason why there is no room in the STM. Could be due to the size of the RPQ tokens in the message.

6178 Error while attempting to update token

Cause	An error occurred while trying to update the account balance token data to the STM message.
Effect	The STM will not be updated with the account balance data. A program dump will be created and the process abends.
Response	Inspect the program dump file for error. The XPNET should restart the process.

6180 Error converting the ILF SEM length from ASCII to integer - ILF prikey: <ilf-prikey>

Cause An error occurred while converting the ILF's external message length from ASCII to integer.

Effect The ILF could not be updated with the SEM data and with the token data. The ILF update process abends.

Response Inspect the program dump file for errors.

6181 Invalid ILF record type - ILF prikey: <ilf-prikey>

Cause The ILF record has an invalid record type.

Effect The ILF cannot be updated with the new SEM data. The ILF update process abends and a program dump will be created.

Response Inspect the program dump file for errors.

6182 Error while attempting to get the token ids from the ILF record - ILF prikey: <ilf-prikey>

Cause An error occurred when retrieving the token ids from the ILF record.

Effect The ILF cannot be updated with the new SEM data. The process abends and a program dump will be created.

Response Inspect the program dump file for errors.

6183 Error while attempting to get the token ids from the SIM to update into the ILF record - ILF prikey: <ilf-prikey>

Cause An error occurred when retrieving the token ids from the SIM.

Effect The ILF cannot be updated with the new SEM data. The process abends and a program dump will be created.

Response Inspect the program dump file for errors.

6184 Token data cannot be increased in size on an update in the ILF record - ILF prikey: <ilf-prikey>

Cause The token data is larger in the internal message than in the ILF record.

Effect The token data in the ILF record will not be updated.

Response None required.

6185 Error while attempting to update token <sim-tkn-id> into the ILF record - ILF prikey: <ilf-prikey>

Cause The ILF update with the token data from the internal message failed.

Effect A program dump will be created and the process abends.

Response Inspect the generated program dump for error.

6186 Error converting the ILF SEM length from integer to ASCII - ILF prikey: <ilf-prikey>

Cause An error occurred while converting the ILF's external message length from integer to ASCII.

Effect The ILF could not be updated with the SEM data. The ILF update process abends and a programmatic dump will be generated.

Response Inspect the program dump file for errors.

6187 SEM length is greater than the maximum allowed SEM length in the ILF record - ILF prikey: <ilf-prikey>

Cause The length of the new external message data exceeds the ILF's external message length.

Effect The ILF update abends and a program dump gets created.

Response Inspect the program dump file for errors.

6188 Error converting the ILF SEM length from integer to ASCII - ILF prikey: <ilf-prikey>

Cause An error occurred while converting the ILF's external message length from integer to ASCII.

Effect The ILF update abends and a program dump gets created.

Response Inspect the program dump file for errors.

6190 SEM length is greater than the maximum allowed SEM length in the ILF record - ILF prikey: <ilf-prikey>

Cause The length of the new external message data exceeds the ILF's external message length.

Effect The ILF cannot be updated with the new SEM data. The ILF update process abends and a program dump will be created.

Response Inspect the program dump file for errors.

6191 Invalid Product Indicator - abending

Cause Unrecognized product ID.

Effect The length of the STM (including token data) cannot be calculated. A program dump will be created and the process abends.

Response Inspect the program dump file for errors.

6192 Error while attempting to retrieve all token data

Cause An error occurred while attempting to retrieve an existing token from the internal message.

Effect The length of the STM (including token data) cannot be calculated. A program dump will be created and the process abends.

Response Inspect the program dump file for errors.

6193 Unable to send to IMNM: ,<IMNM process name> closed

Cause IMNsc lost the communication with the IMNM process when attempting to access the IMNM process.

Effect IMNsc fails to send any message to the IMNM.

Response Examine the IMNM process to ensure the process is running. Restart or warmboot IMNsc.

6194 IMNM Nowait depth maximum # reached, current nwd: #

Cause The I/O message queue threshold for the IMNM has been reached.

Effect IMNsc cannot to send the message to the IMNM.

Response Check the message queue of the IMNsc and IMNM processes.

6195 LOGIC ERROR: Invalid parameters to utl^notifyIMNM

Cause A parameter was not passed or incorrectly passed in the call while attempting to notify a message to IMNM.

Effect IMNsc cannot send the message to the IMNM.

Response This indicates an internal code problem. Contact your vendor representative.

6196 LOGIC ERROR: Invalid msg type: # to utl^notify^IMNM

Cause An invalid message type was passed to an internal procedure.

Effect IMNsc cannot send the message to the IMNM.

Response This indicates an internal code problem. Contact your vendor representative.

6235 Error while attempting to add token to the STM. No room to add token

Cause Not enough space to add data token to the STM.

Effect The write of the token data to the STM fails

Response Examine the STM message to determine if it is full or if not then this could be an internal code problem. Contact your vendor representative.

6236 Error while attempting to add token to the STM

Cause The token address is out of bounds or a required parameter is missing.

Effect Unsuccessful write of token data to the STM. A program dump will be created and the process abends.

Response Inspect the program dump file for error.

6237 Error while attempting to updating token in the STM

Cause An error occurred while trying to update the token data in the STM.

Effect Unsuccessful write of token data to the STM. A program dump will be created and the process abends.

Response Inspect the program dump file for error.

6900 MEASCOUNTERBUMPINIT ERROR <error number> FOR COUNTER <defined name>

Cause Display the error of Initialize the measurement counter for the defined name.

Effect None.

Response Check the error number from the

**6930 MEASCOUNTERBUMP ERROR \E FOR COUNTER **

Cause Display the error of the measurement counter for the defined name.

Effect None.

Response Check the error number from the

6935 Performance Monitoring is now off.

Cause Performance Monitoring has been turn on.

Effect None.

Response None required.

6940 & 6950 Performance Monitoring is already on.

Cause Display Performance Monitoring is already turn on.

Effect None.

Response None required.

6945 Performance Monitoring initialization failure.

Cause Display Performance Monitoring initialization is failed.

Effect None.

Response Check the associated error message and correct the problem, then repeats the Performance Monitoring command again.

6955 Performance Monitoring is now on.

Cause Display Performance Monitoring is turn on.

Effect None.

Response None required

6960 Performance Monitoring is not on reset failed.

Cause Display Performance Monitoring is failed to reset

Effect None.

Response Check the associated error message and correct the problem, then repeats the Performance Monitoring command again.

6975 Performance Monitoring counters have been reset

Cause Display Performance Monitoring has been reset.

Effect None.

Response None required

6980 Invalid Performance Monitoring Command.

Cause Display Performance Monitoring command is invalid.

Effect None.

Response Check the command and try again

6985 Performance Monitoring is on.

Cause Display Performance Monitoring has been turn on.

Effect None.

Response None required

6990 Performance Monitoring is off.

Cause Display Performance Monitoring has been turn off.

Effect None.

Response None required

6995 Performance Monitoring is now off.

Cause Display Performance Monitoring is turn off.

Effect None.

Response None required

7101 IO ERROR: WRITE Admin File:<file name> Err:<Guardian error code>

Cause WRITE IO error occurred.

Effect IMNsc is unable to add a record to the Admin file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7102 IO ERROR: KEYPOSITION Admin File:<file name> Err:<Guardian error code>

Cause	KEYPOSITION IO error occurred.
Effect	IMNsc is unable to keyposition an Admin file record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7103 IO ERROR: READ Admin File:<file name> Err:<Guardian error code>

Cause	READ IO error occurred.
Effect	IMNsc is unable to read an Admin record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7104 IO ERROR:UPDATE Admin File:<file name> Err:<Guardian error code>

Cause	UPDATE IO error occurred.
Effect	IMNsc is unable to update an Admin record with a response code.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7201 IO ERROR: OPEN EPCF File:<file name> Err:<Guardian error code>

Cause	OPEN IO error occurred.
Effect	The EPCF file is not opened. IMNsc fails to update the entry point state.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7202 IO ERROR:KEYPOSITION EPCF File:<file name> Err:<Guardian error code>

Cause	KEYPOSITION IO error occurred.
Effect	IMNsc fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7203 IO ERROR:READ EPCF File:<file name> Err:<Guardian error code>

Cause	READ IO error occurred.
Effect	IMNsc fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7204 TRACE12: EPCF Update EP:<entry point Id> State:<entry point state>

Cause	Trace bit 12 is turned on and the state of the indicated entry point has been set to the indicated state.
Effect	If the state is "A" (activated), IMNsc will open the entry point when the recovery timer expires.
Response	None required. This message is for information only.

7205 IO ERROR: UPDATE EPCF File:<file name> Err:<Guardian error code>

Cause	UPDATE IO error occurred.
Effect	IMNsc fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7301 TRACE12: Read ICF Node: <ICF record key>

Cause Trace bit 12 is turned on and the indicated ICF record is about to be read.

Effect IMNsc reads the ICF record.

Response None required. This message is for information only.

7302 IO ERROR: OPEN ICF File:<file name> Err:<Guardian error code>

Cause OPEN IO error occurred.

Effect The ICF file is not opened. IMNsc fails to retrieve an ICF record.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7303 IO ERROR: KEYPOSITION ICF File:<file name> Err:<Guardian error code>

Cause KEYPOSITION IO error occurred.

Effect IMNsc fails to position to the exact record. The record cannot be retrieved.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7304 IO ERROR: READ ICF File:<file name> Err:<Guardian error code>

Cause READ IO error occurred.

Effect IMNsc fails to retrieve an ICF record.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7305 IO ERROR: Disassembly ICF File:<ICF file name> Err:<Guardian error code>

Cause	Unable to disassemble the ICF segment record read.
Effect	IMNsc fails to retrieve an ICF record and closes the ICF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly

7306 TRACE12: Update ICF Rec Dest: <ICF record key>

Cause	Trace bit 12 is turned on and the indicated ICF record is about to be updated.
Effect	IMNsc reads the ICF record.
Response	None required. This message is for information only.

7307 IO ERROR: OPEN ICF File:<file name> Err:<Guardian error code>

Cause	OPEN IO error occurred.
Effect	IMNsc fails to update the ICF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7308 IO ERROR: Re-assembly ICF File:<ICF file name> Err:<error-code>

Cause	Unable to reassemble the ICF segment record when updating the ICF record.
Effect	IMNsc logs this message under different conditions.
Response	Check the other log messages to determine the action to take.

7309 IO ERROR: KEYPOSITION ICF File:<file name> Err:<Guardian error code>

Cause KEYPOSITION IO error occurred.

Effect IMNsc fails to position the exact record. ICF record is not updated.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7310 IO ERROR:UPDATE ICF File:<file name> Err:<Guardian error code>

Cause UPDATE IO error occurred.

Effect IMNsc fails to update the ICF record.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7311 IO ERROR: CLOSE ICF File:<file name> Err:<Guardian error code>

Cause CLOSE IO error occurred.

Effect MNsc fails to close an ICF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7401 TRACE11: Open ILF File:<file name>

Cause Trace bit 11 is turned on and the indicated ILF file is about to be opened or created.

Effect IMNsc opens and/or creates the ILF.

Response None required. This message is for information only.

7402 IO ERROR: Open ILF File:<file name> Err:<Guardian error code>

Cause	An ILF extract file being opened. If the file does not exist, a new file is created using the LCONF assigned template.
Effect	IMNsc fails to open and/or create file. IMNsc abends.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7403/7404 IO ERROR: % FULL CALCULATION ON <ILF file name> Err: <error code>

Cause	Unable to get ILF file information when calculating % full of ILF file.
Effect	IMNsc closes the ILF file.
Response	Check the file error code returned.

7405 *WARNING*** ILF File <file name> is <full percentage> percent full**

Cause	The ILF file full percentage has passed the notify percentage threshold.
Effect	IMNsc logs the warning and continues.
Response	If IMNsc encounters a fatal file error when accessing an ILF (such as file full) it cannot continue to process transactions and abends. This warning indicated that the ILF might be getting dangerously full. It may be necessary to increase the size of the ILF template file so that when new ILFs are created at cutover, they are large enough to handle a complete day's logging requirements.

7406 ABEND ERROR: Node <node Id> ILF Open Failed during cutover

Cause	A new ILF file could not be opened or created during cutover.
Effect	IMNsc abends.
Response	Check previous log messages for the Guardian error code and file name for the ILF on which the error occurred. Correct the file system problem and restart IMNsc.

7407 ABEND ERROR: ILF Add Dest: <node Id> File: <file name> Err: <Guardian error code> ILF RECORD: <ILF record dump>

Cause A fatal file error occurred on the indicated ILF.

Effect IMNsc abends.

Response Correct the file system problem indicated by the Guardian error code and restart the IMNsc.

7408 TRACE11: ILF Add Dest: <node Id> <msg class> Key: <ILF record key> File: <file name>

Cause Trace bit 11 is turned on and an ILF record was added to the indicated file.

Effect IMNsc logs the message and continues.

Response None required. This message is for information only.

7409 TRACE11: ILF Get Dest: <node Id> <msg class> Key: <ILF record key> File: <file name>

Cause Trace bit 11 is turned on and an ILF record was retrieved from the indicated file.

Effect IMNsc logs the message and continues.

Response None required. This message is for information only.

7410 TRACE11: ILF Update Dest: <node Id> <msg class> SubState: <ILF record substate>

Cause Trace bit 11 is turned on and an ILF record in the indicated file was updated with the indicated substate.

Effect IMNsc logs the message and continues.

Response None required. This message is for information only.

**7411 ILF RECORD: <text>
ABEND ERROR: ILF Updt Dest: <node Id> File: <filename> Err: <file error>**

Cause Fatal error occurred logging a record to ILF.
Effect IMNsc logs the message and abends.
Response Check the error number in the message and take appropriate action.

7412 IO ERROR: OPEN ILF File:<filename>, Err:<error code>

Cause Cannot open the previous ILF file to be purged.
Effect IMNsc fails to open an ILF file and purge the old ILF file. After this message is logged, control is returned to the calling procedure.
Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7413 IO ERROR: CLOSE ILF File:<filename>, Err: <error code>

Cause Close IO error occurred.
Effect IMNsc failed to close the ILF file.
Response Examine the Guardian error code and take action accordingly.

7414/7415 IO ERROR: PURGE ILF File:<filename>, Err: <error code>

Cause Purge IO error occurred.
Effect IMNsc failed to purge the old ILF file.
Response None required.

7416 TRACE11: ILF Get Dest: <node Id> <msg class> Key: <ILF record key> File: <file name>

Cause Trace bit 11 is turned on and the first ILF record was retrieved from the indicated file.

Effect IMNsc logs the message and continues.

Response None required. This message is for information only.

7420 Error while attempting to retrieve all token data

Cause Failed to retrieve token data from the ILF file.

Effect The move of tokens from the external message save area of an ILF record after the external message to the end of a STM was not successful.

Response Inspect the program dump file for errors.

7430 Open Internal Error <library status detail1> <library status detail2> File <file name> <library proc number> <library status> <library status detail3> <library status detail4>, Process abending

Cause A parameter was not passed or incorrectly passed in the call to the library procedure LIB_FILE_OPEN while attempting to open a file.

Effect The ILF file is not opened. IMNsc logs the message and abends.

Response This indicates an internal code problem. Contact your vendor representative.

7431 FAILURE on CREATE, ILF File <file name>, Error <error number>

Cause Failed to create the ILF file.

Effect The ILF file is not created. IMNsc logs the message.

Response . Examine the Guardian error to determine the specific nature of the error and take action accordingly.

**7432 Open Internal Error <library status detail1> <library status detail2 or Guardian error>
File <file name> < library proc number> <library status> <library status detail3> <library status
detail4>, Process abending**

Cause An NSK error (library status detail2) occurred while attempting to open a file on a call to the library procedure LIB_FILE_OPEN. This error caused the open to fail.

Effect The ILF file is not opened. IMNsc logs the message and abends.

Response Inspect the program dump file for errors.

**7433 Open Internal Error <library status detail1> <library status detail2 or Guardian error>
File <file name> < library proc number> <library status> <library status detail3> <library status
detail4>, Process abending**

Cause An NSK error (library status detail2) occurred while attempting to open a file on a call to the library procedure LIB_FILE_OPEN. This error caused the open to fail.

Effect The ILF file is not opened. IMNsc logs the message and abends.

Response Inspect the program dump file for errors.

7501 TRACE12: Get KEYF Rec FID: <FI Id> Node:<KEYF record key>

Cause Trace bit 12 is turned on and the indicated KEYF record is about to be retrieved.

Effect IMNsc retrieves the KEYF record.

Response None required. This message is for information only.

7502 IO ERROR: OPEN KEYF File:<filename>, Err:<error code>

Cause Open IO error occurred.

Effect IMNsc failed to open and read the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7503 IO ERROR: KEYPOSITION KEYF File:<filename>, Err:<error code>

Cause Keyposition IO error occurred.

Effect IMNsc fails to position the exact record and read the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7504 IO ERROR: READ KEYF File:<filename>, Err:<error code>

Cause READ IO error occurred.

Effect IMNsc fails to read the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7505 TRACE12: Update KEYF Rec <KEYF record key>

Cause Trace bit 12 is turned on and the indicated KEYF record is about to be updated.

Effect IMNsc updates the KEYF record.

Response None required. This message is for information only.

7506 IO ERROR: OPEN KEYF File:<filename>, Err:<error code>

Cause Open IO error occurred.

Effect IMNsc failed to open and update the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7507 IO ERROR: KEYPOSITION KEYF File:<filename>, Err:<error code>

Cause Keyposition IO error occurred.

Effect IMNsc fails to position the exact record and update the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7508 IO ERROR: UPDATE KEYF File:<filename>, Err:<error code>

Cause UPDATE IO error occurred.

Effect IMNsc fails to update the KEYF file.

Response Examine the Guardian error code and take action accordingly.

7509 IO ERROR: CLOSE KEYF File:<file name> Err:<Guardian error code>

Cause CLOSE IO error occurred.

Effect IMNsc fails to close the KEYF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7510 TRACE12: Unlock KEYF Rec

Cause Trace message for unlocking KEYF file record at the current position.

Effect None.

Response None required. This message is for information only.

7511 IO ERROR: UNLOCKREC File:<file name> Err:<Guardian error code>

Cause	UNLOCKREC IO error occurred.
Effect	IMNsc fails to unlock KEYF record and then closes file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7512 PROC ERROR: Invalid dct index <dct index>

Cause	DCT table index out of range while loading key data for a destination.
Effect	IMNsc retries the loading process for outbound key change request. If the transaction is key change request, IMNsc denies the request.
Response	Check DCT index in DCT table.

7513 PROC ERROR: Invalid fil index <fil index>

Cause	FIL index out of range (0-9) while loading key data for a destination.
Effect	IMNsc retries the loading process for outbound key change request. If the transaction is inbound key change request, IMNsc denies the request.
Response	Check FIL index in DCT table.

7601 IO ERROR: OPEN SAF File:<file name> Err:<Guardian error code>

Cause	OPEN IO error occurred.
Effect	IMNsc fails to open SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7602 TRACE10: SAF Add Dest:<node Id> Msg:<msg type> Cnt:<SAF transaction count> File:<file name>

Cause Trace bit 10 is turned on and a message is about to be added to the indicated SAF file.

Effect IMNsc adds the SAF record.

Response None required. This message is for information only.

7603 IO ERROR: WRITE SAF File:<file name> Err:<Guardian error code>

Cause WRITE IO error occurred.

Effect IMNsc fails to write a record to SAF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7604 TRACE10: SAF Get Dest:<node Id> File:<file name>

Cause Trace bit 10 is turned on and a SAF record is about to be retrieved from the indicated file.

Effect IMNsc retrieves a SAF record if available.

Response None required. This message is for information only.

7605 IO ERROR: KEYPOSITION File:<file name> Err:<Guardian error code>

Cause KEYPOSITION IO error occurred.

Effect IMNsc fails to retrieve a record from SAF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7606 IO ERROR: READ SAF File:<file name> Err:<Guardian error code>

Cause	READ IO error occurred.
Effect	IMNsc fails to retrieve record from a SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7607 TRACE10: SAF GetNext Dest:<node Id> File:<file name>

Cause	Trace bit 10 is turned on and the next SAF record is about to be retrieved from the indicated file.
Effect	IMNsc retrieves the next record if available.
Response	None required. This message is for information only.

7608 IO ERROR: READ File:<file name> Err:<Guardian error code>

Cause	READ IO error occurred.
Effect	IMNsc fails to retrieve the next record from SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7609 TRACE10: SAF Delete Dest:<node Id> File:<file name>

Cause	Trace bit 10 is turned on and a SAF record is about to be deleted from the indicated file.
Effect	IMNsc deletes a SAF record.
Response	None required. This message is for information only.

7610 IO ERROR: KEYPOSITION File:<file name> Err:<Guardian error code>

Cause KEYPOSITION IO error occurred.

Effect IMNsc fails to delete a record in SAF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7611 IO ERROR:READ SAF File:<file name> Err:<Guardian error code>

Cause READ IO error occurred.

Effect IMNsc fails to delete a record in SAF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7612 IO ERROR: DELETE SAF File:<file name> Err:<Guardian error code>

Cause DELETE IO error occurred.

Effect IMNsc fails to delete a record in SAF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7613 SAF Cutover to <YYMMDD> started for destn= <node Id> <msg class> on node <IMNsc node Id> SAF file= <file name>

Cause The SAF cutover processing for the indicated SAF and destination is about to begin.

Effect IMNsc performs the SAF cutover processing.

Response None required.

7614 IO ERROR: UPDATE SAF File:<file name> Err:<Guardian error code>

Cause	UPDATE IO error occurred.
Effect	IMNsc fails to update a record in the SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7615 SAF Cutover to <YYMMDD> completed for destn= <node Id> <msg class> on node <IMNsc node Id> SAF file= <file name>

Cause	The SAF cutover processing for the indicated SAF and destination has been completed.
Effect	IMNsc logs the message and continues.
Response	None required.

8100* IO ERROR: CGF <read> Error on <file-name> Err: <error code>

Cause	Error reading next record from an existing CGF file.
Effect	IMNsc initialization fails.
Response	Examine the Guardian error code and take action accordingly.

8110* Trace09: Loading CGF file: <file-name>

Cause	Trace bit 9 is turned on; CGF file data is about to be loaded.
Effect	IMNsc loads the CGF file.
Response	None required. This message is for information only.

8111* IO ERROR: CGF <open> error on <file-name> Err:<Guardian error code>

Cause Error opening the CGF file.

Effect IMNsc initialization fails.

Response Examine the Guardian error code and take action accordingly.

8112* IO ERROR: CGF <empty CGF> error on <file-name> Err:<error code>

Cause The CGF file data is missing.

Effect IMNsc initialization fails.

Response Enter connection group data to CGF file and reinitialize the process.

8113* Missing destination <node-id> <msg-cls> in Connection Group <cnxn-grp>

Cause The specified connection is missing from the DCT table.

Effect Destination will not be added to the Connection Group Table.

Response Enter valid destination to the appropriate connection group.

8114* Duplicate connection <node-id> <msg-cls> in Connection Group <cnxn-grp>

Cause A certain connection is added in more than one connection group.

Effect Destination will not be added to the Connection Group Table.

Response Remove the duplicate connection from the CGF record.

8115* Single connection <node-id> <msg-cls> in Connection Group <cnxn-grp>

Cause There is only one connection left in the group.

Effect None.

Response None required. This message is for information only.

8116* Connection group <group-id> cannot be added to CGT. CGT table is full (#Max).

Cause This message is logged at initialization when the CGT becomes full.

Effect No other connection group can be added to the CGT.

Response Delete any records from the CGF that have only one node in the connection group.
Contact your vendor representative if this will not resolve the problem.

8117* WARNING: No CGT Records loaded from <file-name>

Cause Records could not be loaded from the CGF file.

Effect The CGF file will be closed; IMNsc initialization continues.

Response Check the contents of the CGF file for valid records.