



BASE24-pos IMNi SWITCH INTERFACE

LOG MESSAGES MANUAL

Version 1.8

This document contains **PROPRIETARY** and **CONFIDENTIAL** information and such information may not be disclosed to others for any purpose without written permission from:

ACI Worldwide (Canada) Inc.

200 Wellington Street West
Suite 700
Toronto, Ontario M5V 3C7

©2000 by ACI Worldwide (Canada) Inc.

All rights reserved. All information contained in this manual is confidential and proprietary to ACI Worldwide Inc. and has been delivered for use pursuant to license. No part of this manual may be photocopied, electronically transferred, modified, or reproduced in any manner that is contrary to license without the prior written consent of ACI Worldwide Inc.

ACI, ACI Worldwide, ACI Worldwide Inc., BASE24, BASE24-atm, BASE24-atm non-currency dispense, BASE24-atm self-service banking, BASE24-billpay, BASE24-CARD, base24-check auth, BASE24-debit/credit auth, BASE24-fraud control, BASE24-frequent shopper, BASE24-from host maintenance, BASE24-gift certificates, BASE24-InfoBase, BASE24-mail, BASE24-pos, BASE24-refunds auth, BASE24 Remote Banking, BASE24-telebanking, BASE24-teller, BASE24 Visa Cash, CO-ach, ICE, NET24, NET24-XPNET, Perfinon, and TSA are trademarks or registered trademarks of ACI Worldwide Inc., Transaction Systems Architects, Inc., or their subsidiaries.

Other companies' trademarks, service marks or registered trademarks and service marks are trademarks, service marks or registered trademarks and service marks of their respective companies.

REVISION HISTORY

Record of Changes

Author	Date	Version	Comments
ACI	1994	1.0	Initial version
KM	March 1999	1.4	Amendments for Alternate Routing
ON	April 2000	1.5	General review and update
NR	April, 2004	1.6	General review and update for 6.0
II	October, 2004	1.7	General review and update for TIM
ACI	October 2009	1.8	Expand BIN Table

Change Control Index

Change Control Reference	Description of Change	Modules Effected
C-yymmdd-01		

Reference Document

Document Name	Reference / Version	Date
BASE24 Log Message Reference Manual	BA-AE000-07 / 02	11/1997
Interac IMNi Interface External Design	3.0	01/1991

TABLE OF CONTENTS

<u>1.</u>	<u>INTRODUCTION</u>	1
<u>2.</u>	<u>NOTATION CONVENTION</u>	1
<u>3.</u>	<u>IMNI LOG MESSAGES</u>	2

1. INTRODUCTION

This manual contains documentation for log messages generated by the Canadian IMNi 6.0 Switch Interface. Each message description explains the cause of the message, the effect on the system, and provides a recommended recovery action.

2. NOTATION CONVENTION

The naming convention follows that used within BASE24. Further details on this notation can be found in the BASE24 Log Message Reference Manual.

The format used to describe the error messages in this section is shown below:

<i>Message-Number</i>	<i>Message-Text</i>
-----------------------	---------------------

<i>Message-Number</i>	A unique number that identifies the message.
<i>Message-Text</i>	The formatted message text.

Cause:	Describes what caused the message to be generated.
---------------	--

Effect:	Describes the effect on the system.
----------------	-------------------------------------

Response:	Describes the recommended resolution to the error.
------------------	--

The following list summarizes the conventions for syntax notation in this manual.

Notation	Meaning
nnnn*	If log message numbers are appended with an "*", the associated message text had been modified or added to reflect the IMNi-AR release changes.
nnnn/nnnn	If log message numbers are separated by a "/", the associated message text applies to each number specified.
nnnn-nnnn	If log message numbers are separated by a "-", the associated message text applies to the range of numbers bound by the numbers specified.
<xxxx>	Text appearing between the "<" and ">" symbols indicates variable values that will appear in log messages. All other text will appear exactly as shown.

3. IMNi LOG MESSAGES

1100	PROC ERROR: timer Type:<timer type> Subtype:<timer subtype>
-------------	--

Cause	A timeout of unknown type expired.
Effect	IMNi cannot process the timeout.
Response	This indicates an internal code problem. Contact your vendor representative.

1101	Node: <node ID> Begin Cutover Window New Date: <YYMMDD>
-------------	--

Cause	Cutover Begin timeout has expired.
Effect	IMNi has begun cutover to the indicated date for the indicated node.
Response	None required.

1102	Node: <node ID> Cutover completed to date <YYMMDD>
-------------	---

Cause	Cutover End timeout has expired.
Effect	IMNi has completed cutover to the indicated date for the indicated node.
Response	None required.

1103	PROC ERROR: Cutover Timer SubType < unexpected sub type>
-------------	---

Cause	An invalid timer subtype is passed to the cutover timeout handler procedure.
Effect	IMNi cannot process the timeout.
Response	This indicates an internal code problem. Contact your vendor representative.

1104	TRACE03: POS Inbound Timeout Orig: <node ID> Typ: <msg type>
-------------	---

Cause	Trace bit 3 is turned on and a BASE24 request timeout has expired for the indicated message type. "Orig" indicates the requesting node.
Effect	IMNi is processing a BASE24 request timeout.
Response	None required.

1105	TRACE07: <PIN/MAC/MSG> Keychange Timeout Dest: <node Id> Idx:<Key index>
-------------	---

Cause	Trace bit 7 is turned on. A key exchange request for the mentioned key type and key index for the node in the message has expired.
Effect	IMNi is processing the key exchange request timeout.
Response	None required.

1106	TRACE10: SAF Outbound Timeout Dest: <node Id> Typ: <msg type>
-------------	--

Cause	Trace bit 10 is turned on and a SAF request timeout for the indicated node and message type has expired.
Effect	IMNi is processing the key exchange request timeout.
Response	None required.

1107	TRACE03: POS Outbound Timeout Dest: <node Id> Typ:<msg type>
-------------	---

Cause	Trace bit 3 is turned on and a request timeout for the indicated node and message type has expired.
Effect	IMNi is processing the request time-out.
Response	None required

1108	PROC ERROR: Pacing Timer SubType <unknown sub type>
-------------	--

Cause An invalid timer subtype is passed to the pacing timeout handler procedure.

Effect IMNi cannot process the timeout.

Response None required.

1109	TRACE06: Pacing Select State:<new state>
-------------	---

Cause Trace bit 6 is turned on, the pacing selection timeout has expired and the pacing state has changed.

Effect IMNi has re-calculated throughput and response times for all available entry points and determined that the pacing state has changed to the indicated state.

Response None required.

1110	TRACE10: SAF Retransmit Dest: <node Id> Typ:<msg type>
-------------	---

Cause Trace Bit 10 is turned on and the SAF retransmit timeout for the indicated node and message type has expired.

Effect IMNi is processing the SAF retransmit timeout.

Response None required.

1111	TRACE10: SAF Cycle Dest:<node Id> Msg: <msg type> Cnt:<txn count> Out: # Imni:<mode> <speed> Oper: <mode> <speed>
-------------	--

Cause Trace bit 10 is turned on and the SAF cycle timeout has expired.

Effect IMNi has begun processing the SAF cycle timeout for the indicated node and message type. The message indicates the IMNi and operator SAF mode and processing speed.

Response None required.

1201	TRACE08: Close from IMN Manager: <IMNM process name> Fno: <IMNM process file number>
-------------	---

Cause Trace bit 8 is turned on and a close message is received from the IMNM process.

Effect IMNi closes the IMNM process.

Response None required.

1202	IPC ERROR: Close from invalid process: <process name>
-------------	--

Cause A close message is received from an unknown process.

Effect IMNi ignores the close message.

Response IMNi rejects the close attempt by unrecognized processes by returning GUARDIAN error 48 (security violation). This message may indicate an internal code problem. Contact your vendor representative.

1203	TRACE08: Close from EP:<entry point Id> PID:<CIL process name> FNO:<CIL process file number>
-------------	---

Cause Trace bit 8 is turned on and a close message is received from the indicated CIL process for the indicated entry point.

Effect IMNi closes the entry point if open, resets the entry point state and sets the inbound and outbound pacing state for the entry point to blocked.

Response None required.

1204	TRACE08: Open from IMNM: <IMNM process name> Fno: <IMNM process file number>
-------------	---

Cause	Trace bit 8 is turned on and an open message is received from the IMNM process.
Effect	IMNi reads all ICF records to get the current connection states.
Response	None required.

1205	IPC ERROR: Open from invalid process: < process name>
-------------	--

Cause	An open message is received from an unknown process.
Effect	IMNi returns a GUARDIAN error 48 (security violation) to the process.
Response	Check for valid process name in the Entry Point Table.

1206	TRACE08: Open from EP:<entry point Id> PID:CIL process filename> Fno:<CIL process file number> State:<entry point state>
-------------	--

Cause	Trace bit 8 is turned on.
Effect	If the entry point is not open and has not been stopped, IMNi opens the entry point. If the entry point is stopped, IMNi returns GUARDIAN error 2 (invalid operation).
Response	None required.

1301	TRACE05: EchoTest EP:<entry point Id> FilId: <FIL Id> Cnxn: <Connection Id> Status: <Echo Test status and reason codes> Pid: <CIL process name>
-------------	--

Cause	Trace bit 5 is turned on and an echo test request has been received from the indicated CIL process.
Effect	IMNi sends an echo test response.
Response	None required.

1302	TRACE05: Handshake EP:<entry point Id> FilId: <FIL Id> Cnxn:<connection Id> Status:<handshake status and reason codes> Pid: <CIL process name>
-------------	---

Cause	Trace bit 5 is turned on and a handshake request is received from the CIL process for the indicated entry point.
Effect	IMNi validates the request, sends the response and handshake request if necessary.
Response	None required.

1303	Trace06: PacingMsg EP: <entry point ID> Cnxn: <connection Id> Status: <Pacing status and reason codes> Pid: <CIL process name>
-------------	---

Cause	Trace bit 6 is turned on and a pacing request has been received from the CIL process for the indicated entry point.
Effect	IMNi processes the pacing message and updates the pacing state for the entry point accordingly.
Response	None required.

1304	IMN ERR: EP:<entry point Id> PID:<CIL process name>
-------------	--

Cause	IMNi has received a pacing request for an invalid connection Id from the indicated CIL process.
Effect	IMNi ignores the pacing request.
Response	Check the IMN connection configuration for the CIL process.

1305	TRACE06: SetPacing EP:<entry point Id> Dest:<node Id><msg class> Inb:<new inbound pacing state> Curr:<current inbound pacing state>
-------------	--

Cause Trace bit 6 is turned on and the inbound pacing state is the indicated new state.

Effect IMNi sets the inbound pacing state to the indicated value.

Response None required.

1306	TRACE06: SetPacing EP:<entry point Id> Dest:<node Id><msg class> Outb:<new outbound pacing state> Curr:<current outbound connection state> New:<new outbound connection state>
-------------	---

Cause Trace bit 6 is turned on and the outbound pacing state is the indicated new state.

Effect IMNi sets the outbound pacing state to the indicated value.

Response None required.

1307	IPC ERROR: Pacing Notify message to IMNM lost
-------------	--

Cause IMNi has not opened IMNM successfully and cannot send a pacing notification message to the IMNM.

Effect IMNi attempts to re-open IMNM when its recovery timeout expires. If successful, the pacing information is sent to the IMNM process.

Response Check that the IMNM process has been started.

1401	TRACE04: MsgResend <connection Id> Retry: <retry count>
-------------	--

Cause	IMNi has not opened IMNM successfully and cannot send a pacing notification message to the IMNM.
Effect	If the retry count is 0, IMNi attempts to send the request to another entry point. If not successful, a denial response is returned to BASE24.
Response	Check the status of the entry points for the indicated connection.

1501	TRACE04: EpMessage EP:<entry point Id> Cnxn:<connection Id> Type:<msg type, subtype> Status:<status and reason codes>
-------------	--

Cause	IMNi has not opened IMNM successfully and cannot send a pacing notification message to the IMNM.
Effect	Trace bit 4 is turned on and a message containing the indicated entry point is logged.
Response	None required.

1502	IMN ERROR: Msg DROPPED: EP:<entry point Id> Cnxn:<connection Id> Type:<msg type, subtype> Status:<status and reason codes>
-------------	---

Cause	A message received from the indicated entry point is dropped due to the status and reason codes indicated.
Effect	IMNi cannot process the message.
Response	Check the status and reason codes indicated to determine the appropriated response action

1503	IMN ERROR: Invalid message Len: <msg length> Message dropped
-------------	---

Cause	IMNi has received a message that is not long enough to contain a standard external message header from an indicated entry point.
Effect	IMNi ignores the message.
Response	This may indicate an internal code problem with either IMNi or IMN. Contact your vendor representative.

1504	IMN ERROR: Invalid ISO structure: <msg length>
-------------	---

Cause	IMNi cannot process the ISO date portion of a message.
Effect	If the message is a request, it is denied with a status code of Undeliverable Request (80) and a reason code of Invalid Message (21). The message is logged to the ILF.
Response	This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

1505	PROC ERROR: Reply state error. Following message discarded
-------------	---

Cause	A reply to a request is required, but the reply length is not specified to the message handler procedure.
Effect	IMNi cannot reply to the message.
Response	This indicates an internal code problem. Contact your vendor representative.

1601	PROC ERROR: Open completion on invalid file no <file number>
-------------	---

Cause	A NOWAIT open completed on an unknown file.
Effect	IMNi cannot process the open completion.
Response	This indicates an internal code problem. Contact your vendor representative.

1602/1603 PROC ERROR: Invalid IO tag <tag words 1 and 2>

Cause An I/O is completed with an unknown I/O tag.

Effect IMNi cannot process the I/O completion.

Response This indicates an internal code problem. Contact your vendor representative.

1604 IPC ERROR: Completion on <filename> Tag: <tag words 1 and 2> Err: <GUARDIAN error code>

Cause The indicated error occurred on an I/O on the indicated process file.

Effect IMNi cannot process the I/O completion. If the error occurs on an entry point, the entry point is closed. It is re-opened when the recovery timeout expires. If the error occurs on the IMNM process, the IMNM is closed. It is re-opened when the recovery timeout expires.

Response Check the GUARDIAN file error indicated to determine the appropriate response.

1606 IPC ERROR: Completion on <filename> Tag: <tag words 1 and 2> Err: <GUARDIAN error code>

Cause The indicated error occurred for an I/O on the specified process file.

Effect IMNi cannot process the I/O completion. If the error occurs on an entry point, the entry point is closed. It is re-opened when the recovery timeout expires. If the error occurs on the IMNM process, the IMNM is closed. It is re-opened when the recovery timeout expires.

Response Check the GUARDIAN file error indicated to determine the appropriate response.

1607	TRACE13: IMNM Cmp Tag: <tag words 1 and 2> Len :<msg length> Out: #
-------------	--

Cause	Trace bit 13 is turned on and an I/O completed on the IMNM process.
Effect	IMNi processes the I/O completion.
Response	None required.

1608	PROC ERROR: Invalid IO Tag <tag words 1 and 2>
-------------	---

Cause	An I/O completed with an unknown I/O tag.
Effect	IMNi cannot process the I/O completion.
Response	This indicates an internal code problem. Contact your vendor representative.

1609	IPC ERROR: PID:<process name> Err:<GUARDIAN error code>
-------------	--

Cause	A message is received on \$RECEIVE with a non-zero GUARDIAN error code that is not a system message.
Effect	IMNi processes the I/O completion.
Response	None required.

1610	Trace13: IMNM Msg PID: <IMNM process name> Fno: <process file number> Type:<msg-type> Len:<IMNM msg length>
-------------	--

Cause	IMNi processes the IMNM message.
Effect	None.
Response	None required.

1611	IPC ERROR: Invalid Origin PID:<process name> Fno:<process file number> Len:<msg length>
-------------	---

Cause	A message is received from an unknown process or entry point.
Effect	IMNi logs the error and continues.
Response	Investigate the indicated process as to why it is sending messages to IMNi. This may indicate an internal code problem. Contact your vendor representative.

1612	SPAN ERROR: Message Dropped Src:<source symbolic process name> Dest:<destination symbolic process name> Orig:<originating process name> Seqno:<msg sequence number> Dup:>duplicate flag>
-------------	---

Cause	If a system process is unavailable, the nucleus will redeliver messages that are queued when the process is unavailable.
Effect	IMNi drops the duplicate message.
Response	None required. If this problem persists contact your vendor representative.

1613	TRACE03: POS Outb Msg SrcL<source symbolic processname> Typ:<msg type> Tran:<BASE24 transaction code> Resp:<BASE24 response code>
-------------	---

Cause	Trace bit 3 is turned on and a POS message has been received from the nucleus.
Effect	IMNi processes the message.
Response	None required.

1614	SPAN ERROR: Message Dropped Src:<source symbolic process name> Dest:<destination symbolic process name> Orig:<originating process name> Seqno:<msg sequence number> Dup:<duplicate flag>
-------------	---

Cause	If a system process is unavailable, the nucleus will redeliver messages that had been queued while the process was unavailable.
-------	---

Effect	IMNi drops the duplicate message.
--------	-----------------------------------

Response	None required. If this problem persists contact your vendor representative.
----------	---

1615	PROC ERROR: Invalid mtX Index: <msg type index>
-------------	--

Cause	The message type table index is not recognized by the nucleus message handler procedure.
-------	--

Effect	IMNi cannot process the message.
--------	----------------------------------

Response	This indicates an internal code problem. Contact your vendor representative.
----------	--

1616	POS ERROR: Message Dropped: Src: <source symbolic process name> Dest:<destination symbolic process name> Msg Type:<msg type>
-------------	---

Cause	A message with an invalid type is received from the nucleus.
-------	--

Effect	IMNi drops the message.
--------	-------------------------

Response	Investigate the source process as to why the indicated message type is sent to IMNi.
----------	--

1617	TRACE03: ADMIN Outb Msg Src:<symbolic process name> SubTyp: <msg-type> Code: <processing code>
-------------	---

Cause	Trace bit 3 is turned on and an ADMIN message has been received from the nucleus.
-------	---

Effect	IMNi processes the message.
--------	-----------------------------

Response	None required.
----------	----------------

1618	TRACE02: NCS Outb Cmd SrcL<symbolic process name> Len:<msg length> Txt:<msg text>
-------------	--

Cause	Trace bit 2 is turned on and an NCS command has been received from the nucleus.
Effect	IMNi processes the command.
Response	None required.

1701	TRACE01: Timer Typ:<timer type> Subtype:<timer subtype> Count:<timer number> of total timers>
-------------	---

Cause	Trace bit 1 is turned on and a timeout of the indicated type and subtype has expired.
Effect	IMNi processes the timeout.
Response	None required.

1702	IMN ERROR: Handshake Timeout EP:<entry point Id> State:<entry point state> PID:<CIL process name>
-------------	--

Cause	A handshake request for the indicated entry point times out.
Effect	IMNi cannot complete the handshake procedure with the indicated CIL process. IMNi closes the entry point and re-opens it when the recovery timeout expires.
Response	None required.

1703	PROC ERROR: timer Type:<timer type> Subtype:<timer subtype>
-------------	--

Cause	A timeout of unknown type expired.
Effect	IMNi cannot process the timeout.
Response	This indicates an internal code problem. Contact your vendor representative.

1901	TRACE00: <RECEIVE> Ev:<event type> Fno:<file-number> Typ:<msg type> Len:<msg length> Tag:<tag words 1 and 2> PID:<process name> Err: <err-code>
-------------	--

Cause	Trace bit 0 is turned on and the message has been received.
Effect	IMNi processes the received message or has sent the indicated reply.
Response	None required.

1902	IPC ERROR: RECEIVE Event:<event type> Tag:<tag words 1 and 2> PID:<process name> Err GUARDIAN error code>
-------------	---

Cause	An I/O error occurred on \$RECEIVE.
Effect	IMNi logs the error and continues processing.
Response	Check the GUARDIAN error code and the specified process name to determine the nature of the error and take action accordingly.

1903	SPAN ERROR: Message Failure <failure code> Src:<symbolic process name>
-------------	---

Cause	The nucleus returns a message failure code.
Effect	IMNi logs the error and continues processing.
Response	Check the nucleus message failure code indicated to determine the appropriate response.

1904	IPC ERROR: REPLY Tag:<tag words 1 and 2> PID:>process name> Err:<GUARDIAN error code>
-------------	--

Cause	An error occurred on a reply to the indicated process.
Effect	IMNi logs the error and continues processing.
Response	Check the GUARDIAN error code and the specified process name to determine the appropriate response.

1905	TRACE00: <REPLY> Ev:<event type> Fno:<file-number> Typ:<msg type> Len:<msg length> Tag:<tag words 1 and 2> PID:<process name>
-------------	--

Cause	Trace bit 0 is turned on and the reply has been sent.
Effect	IMNi processes the received message or sends the indicated reply.
Response	None required.

1906	IPC ERROR: RECEIVE event:<event type> Tag:<tag words 1 and 2> PID:<process name> Err:<GUARDIAN error code>
-------------	---

Cause	An I/O error occurred on \$RECEIVE.
Effect	IMNi logs the error and continues processing.
Response	Check the GUARDIAN error code and the process name indicated to determine the nature of the error and take action accordingly.

2101	TRACE09: AllocateSegment - <segment size> bytes
-------------	--

Cause	Trace bit 9 is turned on and an extended memory segment of the indicated size is about to be allocated.
Effect	IMNi allocates the extended segment.
Response	None required.

2102	PROC ERROR: ALLOCATESEGMENT Code: <error code>
-------------	---

Cause	The process that allocates an extended memory segment fails. The indicated GUARDIAN error is returned.
Effect	IMNi cannot set up its internal tables.
Response	Check the indicated GUARDIAN error to determine the appropriate response. Warmboot to restart IMNi.

2103	PROC ERROR: USESEGMENT failure
-------------	---------------------------------------

Cause	An attempt to use an extended memory segment failed.
Effect	IMNi cannot set up its internal tables.
Response	This indicates an internal code problem. Contact your vendor representative.

2104	PROC ERROR: DEFINEPOOL Result:<define pool error code>
-------------	---

Cause	An attempt to define a pool in an extended memory segment failed.
Effect	IMNi cannot set up its internal tables.
Response	This indicates an internal code problem. Contact your vendor representative.

2110	IO ERROR: ALLOCATESEGMENT Err:<GUARDIAN error code>
-------------	--

Cause	An attempt to allocate an extended memory segment failed. The indicated GUARDIAN error is returned.
Effect	IMNi cannot set up its internal tables.
Response	Check the indicated GUARDIAN error to determine the appropriate response. Warmboot to restart IMNi.

2201	TRACE09: Loading DCT Dest:<node Id> <msg class>
-------------	--

Cause	Trace bit 9 is turned on and the destination control table entry for the indicated destination is about to be set up.
Effect	IMNi sets up the DCT entry.
Response	None required.

2202	TRACE09: Loading FKT File:<file name>
-------------	--

Cause	Trace bit 9 is turned on and the inbound key table is about to be loaded from the indicated file.
Effect	IMNi loads the inbound key table.
Response	None required.

2203	PROC ERROR: Max Keys reached (<maximum inbound key entries>) - FKT full
-------------	--

Cause	The inbound key table is full and another entry cannot be added.
Effect	IMNi cannot set up a completed inbound key table.
Response	Increase the LCONF parameter "INTERNAL-FKT-TABLE-ENTRIES" and restart the IMNi.

2205	TRACE09: Loading SAF File:<file name>
-------------	--

Cause	Trace bit 9 is turned on and the indicated SAF file is about to be added to the SAF control table and linked to the destination control table entries. The SAF control and date records are about to be read.
Effect	IMNi loads the indicated SAF information.
Response	None required.

2206	WARNING: Destination <node Id> <msg class> set to FORWARD ONLY mode
-------------	--

Cause	The SAF control record for the indicated destination cannot be retrieved.
Effect	IMNi sets the destination SAF mode to Forward only.
Response	Check if the IMNM process is running. Check for previous log messages indicating that a GUARDIAN error occurred on the SAF file.

2210	IO ERROR: SAF <msg text> Error File: <saf-file> Err: <error>
-------------	---

Cause	The SAF control record for the indicated destination cannot be retrieved.
Effect	IMNi sets the destination SAF mode to Forward only.
Response	Check that the IMNM process is running. Check the GUARDIAN error.

2211	INIT: Destinations per normal pacing step is set to default value = 1 INIT: Destinations per abnormal pacing step is set to default value = 1
-------------	--

Cause	Set the default values for number of destinations per pacing step during initialization process.
Effect	None.
Response	None required.

2212	INIT: Nbr of normal steps per pacing interval is set to default value = 1 INIT: Nbr of abnormal steps per pacing interval is set to default value = 1
-------------	--

Cause	Set the default values for number of steps per pacing interval during initialization process.
Effect	None.
Response	None required.

2299	No POS record found in the TKN file - all PSTM tokens will be logged to the ILF
-------------	--

Cause	Check for POS record in the TKN file.
Effect	IMNi logs the message and continues processing.
Response	None required.

2300	NETWORK initialization failed
-------------	--------------------------------------

Cause	Unable to initialize network.
Effect	IMNi logs error message and abends.
Response	Check the saveabend file for error.

2301	ABEND ERROR: LCONF initialization failed
-------------	---

Cause	Unable to Obtain assigns/parameters from LCONF file.
Effect	IMNi logs error message and abends.
Response	Correct assigns/parameters in LCONF file and restart IMNi.

2302	ABEND ERROR: LOGGER initialization error
-------------	---

Cause	Initialization of the LOGGER failed.
Effect	IMNi cannot write log messages.
Response	Check for previous home terminal messages indicating that a GUARDIAN error occurred on the LCONF file. Correct the file LOGGER problem and restart IMNi.

2303	Base24 / IMN Interchange - Copyright 2002 by Applied Communications Inc.
-------------	---

Cause	Initialization of the LOGGER is successful.
Effect	IMNi logs the message and continues.
Response	None required.

2304	Process initialized. EPS Avail:<number of entry points defined. Mode:<test/production mode> Manager:<IMNM process name>
-------------	---

Cause IMNi has completed its initialization.

Effect IMNi continues normal processing.

Response None required.

2305-2307	ERROR: Can't encrypt initialization vector: <encrypt error code>
------------------	---

Cause Encryption of the initialization vector failed.

Effect IMNi cannot encrypt account balance information and fills with blanks any account balance fields.

Response Check for previous log messages indicating a GUARDIAN error on the security device process. Correct the device problem and restart or warmboot IMNi.

2308	TRACE09: Opening ADMNF File: <file name>
-------------	---

Cause Trace bit 9 is turned on and the ADMIN file is about to be opened.

Effect IMNi opens the file.

Response None required.

2309	IO ERROR: Open error on ADMNF: <file name> Err: <error-code>
-------------	---

Cause An attempt to open the Administrative Message File failed.

Effect IMNi initialization will fail.

Response Check the Guardian error to determine the appropriate response. Warmboot IMNi.

2310	TRACE08: Opening EP: <CIL process name, entry point subdevice> State:<entry point state>
-------------	---

Cause	Trace bit 8 is turned on and the indicated entry point is about to be opened.
Effect	IMNi opens the entry point.
Response	None required.

2311	RECOVER: EP <CIL process name, entry point subdevice> opened Prev Error:<GUARDIAN error code>
-------------	--

Cause	An entry point has been re-opened after an error occurred.
Effect	IMNi logs the message and continues.
Response	None required.

2312	IO ERROR: OPEN EP: <CIL process name, entry point subdevice> State:<oldstate> Err: <error code>
-------------	--

Cause	An OPEN to a specific CIL entry-point failed.
Effect	IMNi cannot use this specific link.
Response	Check the Guardian error code and take specific action.

2313	TRACE08: Opening IMNM <IMNM process name>
-------------	--

Cause	Trace bit 8 is turned on and the IMN manager process is about to be opened.
Effect	IMNi opens the IMNM process.
Response	None required.

2314	IO ERROR: Open error on IMNM: <IMNM process name> Err: <error-code>
-------------	--

Cause	IMNi fails to open link to IMNM.
Effect	The IMNi initialization will continue.
Response	Examine the Guardian error code and take appropriate action.

2315	RECOVER: IMNM <IMNM process name> opened. Prev Error: <GUARDIAN error code>
-------------	--

Cause	The IMNM process is re-opened after an error occurred.
Effect	IMNi logs the message and notifies IMNM of its pacing status.
Response	None required.

2316	TRACE09: Loading BIN File <file name>
-------------	--

Cause	Trace bit 9 is turned on and the BIN file is about to be loaded.
Effect	IMNi loads the BIN file data.
Response	None required.

2317	IO ERROR: BINF: OPEN Error on <file-name> Err:<error>
-------------	--

Cause	Error on opening the BIN file.
Effect	IMNi initialization fails.
Response	Check Guardian error code to determine the appropriate response. Warmboot IMNi.

2318	IO ERROR: BINF: READ Error on <file-name> Err: <error>
-------------	---

Cause	Error on reading the BIN file.
Effect	The BIN file will be closed. IMNi cannot set up the BIN table.
Response	Examine the BIN file to verify its name, size, content and location.

2319	PROC ERROR : Max BIN routings <Maximum BIN table entries> - BINT fill
-------------	--

Cause	The BIN is full and another entry cannot be added.
Effect	IMNi cannot set up a complete BIN table.
Response	Increase the LCONF parameter "INTERNAL-BIN-TABLE-ENTRIES" and restart IMNi. The default value for this parameter is 50 entries, and the maximum value is 32000. The larger the table, the longer each search for routing will take.

2320	WARNING: No BIN Routings from <file name> WARNING: No BIN Routings from <file name>
-------------	--

Cause	No BIN table entries are found in the indicated file.
Effect	IMNi has an empty BIN table and cannot route any financial or administrative transactions.
Response	Check that the indicated file is the correct file and check the contents of the file. Restart or warmboot IMNi.

2321	TRACE09: Loading EPCF File: <file name>
-------------	--

Cause	Trace bit 9 is turned on and the entry point configuration file is about to be loaded.
Effect	IMNi loads the entry point configuration data.
Response	None required.

2322	IO ERROR: EPCF: OPEN Error on <file-name> Err: <error>
-------------	---

Cause	Error on opening the EPCF.
Effect	Unable to build the EPT table, IMNi initialization stops.
Response	Examine the EPCF file to verify its name, size, contents and location as well as the Guardian error code.

2323	IO ERROR: EPCF: READ Error on <file-name> Err: <error>
-------------	---

Cause	Unable to read the EPCF file.
Effect	The EPCF will be closed.
Response	Examine the error to determine its nature and take action accordingly.

2324	WARNING: Maximum entry points (<maximum number entry points>) - EPCF full
-------------	--

Cause	The entry point table is full and another entry point cannot be added.
Effect	IMNi cannot build a completed entry point table.
Response	This is a program limit. Configure another IMNi process or contact your vendor representative.

2325	CONFIG: EPCF <file name> Defs loads:<entry point count><ISSUER ONLY/ACQUIRER ONLY/ISSUER & ACQUIRER/NO EPS DEFINED>
-------------	--

Cause	The indicated number of entry point configurations has been loaded.
Effect	IMNi will function in the mode indicated.
Response	Check that the mode is correct. If not, check the entry point configuration file data.

2326	IO ERROR: ICF: READ Error on <file-name> Err: <error>
-------------	--

Cause	Unable to read the ICF file.
Effect	The ICF file will be closed, IMNi initialization stops.
Response	Examine the error code and take action accordingly.

2327	IO ERROR: ICF: DISASSEMBLY Error on <file-name> Err: <error>
-------------	---

Cause	Unable to disassemble the ICF file.
Effect	The ICF file will be closed, IMNi initialization stops.
Response	Examine the error code and take action accordingly.

2328	TRACE09: Loading ICF File: <file name>
-------------	---

Cause	Trace bit 9 is turned on and the indicated ICF file data is about to be loaded.
Effect	IMNi loads the ICF data.
Response	None required.

2329	IO ERROR: ICF: OPEN Error on <file-name> Err: <error>
-------------	--

Cause	Failed to open the ICF file.
Effect	Unable to configure the node, IMNi stops itself.
Response	Examine the error code to determine the nature of the error and take action accordingly.

2330	IO ERROR: ICF:KEYPOSITION Error on <file-name> Err: <error>
-------------	--

Cause	Keypositioning in the ICF file failed.
Effect	The ICF file closes, IMNi initialization stops (not able to find FIID).
Response	Examine the error code to determine the nature of the error and take action accordingly.

2331	IO ERROR: ICF: MISSING CONFIG Error on <file-name> Err: <error>
-------------	--

Cause	Unable to read and disassemble the first record in the ICF.
Effect	The ICF file closes, IMNi initialization stops.
Response	Examine the ICF file to verify its name, size, contents and location.

2332	IO ERROR: ICF:INVALID CONFIG Error on <file-name> Err: <error>
-------------	---

Cause	Unable to validate the first record in the ICF.
Effect	The ICF file closes, IMNi initialization stops.
Response	Examine the ICF file to verify its name, size, contents and location.

2333	CONFIG: ILF File: Today:<file name> Tomorrow: <file name>
-------------	--

Cause	The indicated ILF files have been created and/or opened.
Effect	IMNi begins processing using the indicated files.
Response	None required.

2334 WARNING: No <OUT/IN> BOUND Keys for destination <node Id> <msg class>

Cause	The inbound and /or outbound KEYF record cannot be found or processed for the indicated destination.
Effect	IMNi has no key data for the indicated destination.
Response	Set up the key information for the indicated destination in the KEYF file using the KEYF screen. Restart or warmboot the IMNi.

2335 PROC ERROR: Max destinations (Maximum number of destinations>) - DCT full

Cause	The destination control table is full and another entry cannot be added.
Effect	IMNi cannot build a complete destination control table.
Response	This is a program limit. Configure another IMNi process or contact your vendor representative.

2336 WARNING: No Destinations Defined in ICF <file name>

Cause	No destination data is found or processed from the indicated ICF file.
Effect	IMNi has no destination information and cannot route any transactions.
Response	Set up the destination information in the ICF file using the ICF screen. Restart or warmboot the IMNi.

2337 INIT ERROR: Assign <assign item>: Open: <file name> Err: <error -code>

Cause	Open on the specified file fails.
Effect	IMNi is unable to open the file.
Response	Check the GUARDIAN error code to determine the appropriate response. Correct the file system problem and restart or warmboot the IMNi.

2338	TRACE09: Processing LCONF File: <file name>
-------------	--

Cause	Trace bit 9 is turned on and processing of the indicated LCONF file is about to begin.
Effect	IMNi processes the LCONF file.
Response	None required.

2339	INIT ERROR: LCONF: <file name> Err:<GUARDIAN error code>
-------------	---

Cause	A GUARDIAN error occurred on the LCONF file.
Effect	IMNi cannot load all assigns and parameters from the LCONF file.
Response	Check the GUARDIAN error code to determine the appropriate response. Correct the file system problem and restart or warmboot the IMNi.

2340	INIT ERROR: Assign <assign name>:Missing
-------------	---

Cause	The indicated assign cannot be read from the LCONF file.
Effect	IMNi cannot determine the physical file associated with the assign.
Response	Add the assign to the LCONF. Restart or warmboot the IMNi.

2341	INIT ERROR: Assign <assign name>: Invalid File Name
-------------	--

Cause	The physical file name associated with the indicated assign is invalid.
Effect	IMNi cannot process the indicated assign.
Response	Fix the assign in the LCONF. Restart or warmboot the IMNi.

2342	INIT ERROR: Assign <assign name>: Open:<file name> Err:<GUARDIAN error code>
-------------	---

Cause	A GUARDIAN error occurred when attempting to open the specified template file.
Effect	IMNi cannot process the indicated assign and initialization fails.
Response	Check the GUARDIAN error code to determine the appropriate response. Restart or warmboot the IMNi.

2343	INIT ERROR: Param <param name> : Missing
-------------	---

Cause	The indicated parameter could not be read from the LCONF file and IMNi does not have a default value.
Effect	IMNi cannot determine the correct value for the program variable associated with the indicated parameter.
Response	Add the parameter to the LCONF file. Restart or warmboot the IMNi.

2344	INIT ERROR: Param <param name> : Default used
-------------	--

Cause	The specified parameter could not be read from the LCONF file and a default value is used.
Effect	IMNi continues processing using the default value.
Response	Confirm that the parameter in the LCONF is correct and restart or warmboot the IMNi.

2345	INIT: Param <param name> : Ignored during WARMBOOT
-------------	---

Cause	The indicated parameter is ignored during warmboot.
Effect	IMNi ignores the indicated parameter so that its internal table sizes are not changed during a warmboot.
Response	If the indicated parameter must be changed, change the LCONF parameter and restart IMNi.

2346	INIT ERROR: Param <param name> : Invalid value
-------------	---

Cause	The value of the indicated parameter is invalid.
Effect	IMNi cannot process the parameter.
Response	Fix the parameter in the LCONF file. Restart or warmboot IMNi.

2347	TRACE 09: Process Termination
-------------	--------------------------------------

Cause	Trace bit 9 is turned on and IMNi is about to terminate.
Effect	IMNi stops.
Response	Restart the IMNi if necessary.

2348	PROC ERROR: CIL FNAME32 error EP:<entry point id> PID:<process id>
-------------	---

Cause	Unable to convert a CIL process ID and EP ID from the 32 character format used by the Distributed Name Service (DNS) to the Guardian file name format when attempting to load the Entry Point information from the EPCF file to the internal table.
Effect	IMNi issues this warning and continues processing.
Response	Check the EPCF file. Restart or warmboot IMNi.

2349	FKT Verify Error: idx1 = # idx2 = # Duplicate KEK = <KEK key value>
-------------	--

Cause	Duplicate KEK found in FKT table.
Effect	IMNi will call NETABEND if duplicates still exist in retry of loading FKT table.
Response	Check for duplicate KEK in KEYF file.

2350	IO ERROR: ICF: REASSEMBLY Error on <file-name> Err: <error>
-------------	--

Cause	Unable to reassemble the ICF file.
Effect	The ICF file closes, IMNi initialization stops.
Response	Examine the error code and take action accordingly.

2351	IO ERROR: ICF: UPDATE Error on <file-name> Err: <error>
-------------	--

Cause	Unable to update the ICF file.
Effect	The ICF file closes, IMNi initialization stops.
Response	Examine the error code and take action accordingly.

2367	Process initialized failed: get process handle
-------------	---

Cause	IMNi initialization failed. Unable to get a process handle from the system when attempting to create a process.
Effect	IMNi logs the error message and abends.
Response	Examine theabend file and take action accordingly.

2368	Process initialized failed: get process decompose
-------------	--

Cause	IMNI initialization failed. Unable to get a process information from the system.
Effect	IMNi logs the error message and abends.
Response	Examine the abend file and take action accordingly.

2370	Initialize Radix table error: >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending
-------------	--

Cause	IMNi cannot initialize the radix table. It might be a programmatic error.
Effect	IMNi logs an error message and abends.
Response	Examine the abend file and take action accordingly.

2371 Add queue in Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause	IMNi cannot add data into the radix table. It might be a programmatic error.
Effect	IMNi logs an error message and abends.
Response	Examine the abend file and take action accordingly.

2372 Building Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause	IMNi cannot build the radix table. It might be a programmatic error.
Effect	IMNi logs an error message and abends.
Response	Examine the abend file and take action accordingly.

2373 Get info Radix Table error:< Library status >, cde1=< Library error code detail-1>, cde2=< Library error code detail-2>, File<File name>. Process abending

Cause	IMNi fails to obtain the radix table information. It might be a programmatic error.
Effect	IMNsc logs an error message and abends.
Response	Examine the abend file and take action accordingly

2523 INIT ERROR: Assign <CGF>:Missing

Cause The indicated assign Coonection Group File (CGF) cannot be read from the LCONF file.

Effect IMNi cannot determine the physical file associated with the assign.

Response Add the assign to the LCONF. Restart or warmboot IMNi.

3601 PROC ERROR: <PIN/MAC/MSG> Keychange Failure Dest:<node Id <msg class> Idx:<key index> Op:<get ICF/get KEYF/generate Key/update KEYF/send to EP/no context/no timers>

Cause The indicated key exchange request could not be constructed or sent to the network.

Effect IMNi allows the key exchange timeout to expire and then notifies the IMNM process of the key exchange failure.

Response If the "Op" field contains "no context" or "no timer" this indicates an internal code problem. Contact your TXN representative. The other "Op" field values indicate either an ICF or KEYF access problem, an entry point problem or a security device problem. Check previous log messages for GUARDIAN errors to determine the appropriate response.

3602/3603 TRACE07: <PIN/MAC/MSG> KeyChange Init Dest:<node Id> Index:<Key index> Cntr:<Key counter value>

Cause Trace bit 7 is turned on and a key exchange request for the indicated key type and index is sent to the network.

Effect IMNi logs the message and continues.

Response None required.

3901/3902 ADMIN ERROR: Bad Destination <node Id> <msg class>

Cause	An ADMIN request is received that contains an invalid destination.
Effect	IMNi cannot format an administrative network transaction.
Response	This indicates an internal code problem with the IMNA requester or server. Contact your vendor representative.

3903 ADMIN ERROR: Dest:<node Id> Invalid Proc Code: <processing code>

Cause	An ADMIN request is received that contains an invalid processing code.
Effect	IMNi cannot format an administrative network transaction.
Response	This indicates an internal code problem with the IMNA requester or server. Contact your vendor representative.

3904 ADMIN ERROR: Dest:<node Id> Unable to add record to SAF

Cause	An administrative network transaction cannot be added to the SAF file for the indicated destination.
Effect	IMNi cannot send the transaction.
Response	Check previous log messages for GUARDIAN errors to determine the appropriate response. Resend the ADMIN message using the IMNA screen.

3905 ADMIN ERROR: Dest:<node Id> Unable to add record to ADMIN file.

Cause	An Administrative record cannot be added to the ADMIN file.
Effect	IMNi cannot send the administrative network transaction.
Response	Check previous log messages for GUARDIAN errors to determine the appropriate response. Resend the ADMIN message using the IMNA screen.

3906	ADMIN Message added to SAF. Dest:<node Id> <msg class>
-------------	---

Cause	An Administrative request is processed and an administrative network transaction is added to the SAF file for the indicated destination.
Effect	IMNi sends the transaction when it reaches the top of the SAF cycle.
Response	None required.

3907	IMN ERROR: Handshake Send Failure EP:<entry point Id> RC:<response code> SS:<ILF substate> Fno:<file number> ERR:<GUARDIAN error code>
-------------	---

Cause	A handshake request to the indicated entry point fails.
Effect	The entry point remains uninitialized.
Response	Check the GUARDIAN error code to determine the appropriate response. Restart the entry point if necessary.

3908	TRACE05: Passthru Dest: <node Id> Len:<msg length>
-------------	---

Cause	Trace bit 5 is turned on and a passthrough request is about to be sent.
Effect	IMNi sends the passthrough request.
Response	None required.

3909/3910	IMN ERROR: PASS THRU failure Dest:<node Id> EP:<entry point Id> Err:<pass through msg>
------------------	---

Cause	A passthrough message could not be sent to the indicated entry point.
Effect	IMNi logs the message and continues.
Response	Check the entry point status.

3920	PROC ERROR: Timer insert failure Type<timer type> SubType:<timer subtype> count:<timer number> of <total timers>
-------------	---

Cause	A timer could not be started before sending a request to BASE24 or to the network.
Effect	IMNi sends a system error response (ISO 96).
Response	This indicates an internal code problem. Contact your vendor representative.

4201	Pin failed to verify - kpe info missing from security block (msg type= <msg type>, destn=<node Id> <msg class>)
-------------	--

Cause	A network message is received which contains a security block that is too short to contain the PIN key index or counter value.
Effect	IMNi cannot covert the network message to BASE24 format. IMNi logs the message to the ILF and returns an edit error response (ISO 06).
Response	This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

4202	Pin failed to verify - invalid kpe index in security block (msg type= <msg type>, kpe= <PIN key index, destn=<node Id> <msg class>)
-------------	---

Cause	A network message is received which contains a PIN key index in the security block that is neither 1 nor 2.
Effect	IMNi cannot convert the network message to BASE24 format. IMNi logs the message to the ILF and returns an edit error response (ISO 06).
Response	This may indicate an internal code problem with either the sending or receiving node. Contact your vendor representative.

4203	Invalid Response: EP: <entry point> Cnxn: <node-id> <msg-class> <node-id> Hdr: <msg-type> <transaction code> <response code> ISO: <iso msg-type> <process code> <response code>
-------------	--

Cause Response fails edit checking.

Effect IMNi continues processing.

Response None required.

4301	LOGIC ERROR: Invalid Key Type: <Key type>
-------------	--

Cause An invalid key type is passed to an internal procedure.

Effect IMNi cannot use the key type.

Response This indicates an internal code problem. Contact your vendor representative.

4501 *	PROC ERROR: Node: < IMNi node Id> Issuer <PIN/MAC/MSG> key <key index> change rejected Dest:<node Id> Op: <SEM Init/KEYF Access/Key type/Translate/Keyf Update/Gen Resp/Send Resp/Unknown Err>
---------------	---

Cause A key exchange request is received from the indicated node that could not be processed. The "Op" field indicates the failed operation or the invalid request field.

Effect IMNi rejects the key exchange request.

Response If the "Op" field contains "SEM Init", "Key Index", "Key Type", "Gen Resp" or "unknown Err" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either a key translation problem, a KEYF access problem or an entry point problem. Check previous log messages for GUARDIAN errors to determine the appropriate responses.

4502	TRACE07: <PIN/MAC/MSG> KeyChange Rqst Dest:<node Id> Index:<key index> Cntr: <Key counter>
-------------	---

Cause Trace bit 7 is turned on and a key exchange request is received from the network.

Effect IMNi processes the key exchange request.

Response None required.

4503*	Node:<IMNi node Id> Iss <PIN/MAC/MSG> key <key index> updated Dest:<node Id>
--------------	---

Cause A valid key exchange request is processed.

Effect IMNi stores the key information in the KEYF file and sends the IMNM process the new key date for distribution to other IMNi processes.

Response None required.

4504*	PROC ERROR: Node:<IMNi node Id> Acq <PIN/MAC/MSG> Key <Key index> change rejected Dest:node Id> Op: <Init Resp/No Context/ KEYF Get/KEYF update/KEK SeqErr/St:<status code>/Rc:<response code>/Unknown Err>
--------------	---

Cause A key exchange response is received from the indicated node that cannot be processed. The "Op" field indicates the operation that failed or the request field that is invalid.

Effect IMNi notifies the IMNM process of the Key exchange failure.

Response If the "Op" field contains "Init Resp", "No Context", "Unknown Err" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either a KEYF access problem or a network or issuer problem. Check previous log messages for GUARDIAN errors to determine the appropriate response.

4505* PROC ERROR: Node:<IMNi node Id> Acq <PIN/MAC/MSG> Key <Key index> change rejected Dest:node Id> Op: <Init Resp/No Context/ KEYF Get/KEYF update/KEK SeqErr/St:<status code>/Rc:<response code>/Unknown Err>

Cause A key exchange response is received from the indicated node that cannot be processed. The "Op" field indicates the operation that failed or the request field that is invalid.

Effect IMNi notifies the IMNM process of the Key exchange failure.

Response If the "Op" field contains "Init Resp", "No Context", "Unknown Err" this indicates an internal code problem. Contact your vendor representative. The other "Op" field values indicate either a KEYF access problem or a network or issuer problem. Check previous log messages for GUARDIAN errors to determine the appropriate response.

4506 TRACE07: <PIN/MAC/MSG> KeyChange Resp Dest:<node Id> Stat:<status code> Reas:<reason code> Resp:<response code> Index:< Key index> Cntr:<Key counter value>

Cause Trace bit 7 is turned on and a key exchange response is received from the network.

Effect IMNi processes the response.

Response None required.

4507* Node:<IMNi node Id> Acq <PIN/MAC/MSG> Key <key index> updated Dest:<node Id>

Cause A valid key exchange response is preceded.

Effect IMNi stores the key information in the KEYF file and sends the IMN process the new key date for distribution to other IMNi processes.

Response None required.

4508	PROC ERROR: Timer insert failure Type:<timer type> SubType:<timer subtype> Count:<timer number> of <total timers>
-------------	--

Cause	A timer cannot be started before sending a request to BASE24 or to the network.
Effect	IMNi sends a system error response (ISO 96).
Response	This indicates an internal code problem. Contact your vendor representative.

4509	Mismatched KEK in FKT, Idx= # FKT KEK= <KEK> KEYF KEK = <KEK> Updating FKT
-------------	---

Cause	KEK in KEYF does not match KEK in FKT table.
Effect	Replace FKT KEK with KEYF KEK.
Response	None required.

4510	Mismatched KEK in FKT, Idx= # FKT KEK= <KEK> KEYF KEK = <KEK> Updating FKT
-------------	---

Cause	KEK in KEYF does not match KEK in DCT table.
Effect	Replace DCT KEK with KEYF KEK.
Response	None required.

4511	Mismatched KEK in FKT, Idx= # FKT KEK= <KEK> KEYF KEK = <KEK> Updating FKT
-------------	---

Cause	KEK in KEYF does not match KEK in FKT table.
Effect	Replace FKT KEK with KEYF KEK.
Response	None required.

5101	Invalid command <command text>
-------------	---

Cause	An invalid NCS command received.
Effect	IMNi cannot process the command.
Response	Check the syntax of the command and resent it.

5102	Unrecognized IMNM request code <request code>
-------------	--

Cause	An IMNM request is received that contains an unrecognized request code.
Effect	IMNi cannot process the request.
Response	This indicates an internal code problem. Contact your vendor representative.

5108	Invalid KEK Value in DCT :<KEK> replaced with :<IMNM KEK>
-------------	--

Cause	KEK sent from IMNM is different from the one stored in DCT table.
Effect	Replace KEK exchange key in DCT table with KEK sent from IMNM.
Response	None required.

5109	Invalid KEK Value in FKT : <KEK> replaced with :<IMN KEK>
-------------	--

Cause	KEK sent from IMNM is different from the one stored in DCT table.
Effect	Replace KEK exchange key in FKT table with KEK sent from IMNM.
Response	None required.

5201	Unrecognized command <command text>
-------------	--

Cause	An NCS command is received that contains an unrecognized command token.
Effect	IMNi ignores the command.
Response	Check the list of NCS commands and send the correct command token.

5202	IMNi trace switch: <new tract bit settings>
-------------	--

Cause	An NCS TRACE command received.
Effect	IMNi sets the trace bits according to the command arguments.
Response	None required.

5203	Operator issued command to DEBUG
-------------	---

Cause	An NCS DEBUG command received.
Effect	IMNi calls DEBUG.
Response	The IMNi process may be inspected. Note that only TXN personnel should issue the DEBUG command.

5204	Operator issued command to programmatic DUMP
-------------	---

Cause	An NCS DEBUG command received.
Effect	IMNi calls DEBUG.
Response	The IMNi process may be inspected. Note that only vendor personnel should issue the DEBUG command.

5205	Command not yet supported
-------------	----------------------------------

Cause	An NCS command is received that is not yet supported.
Effect	IMNi does not process the command.
Response	Contact your vendor representative for further information.

5206	Invalid Command <command>
-------------	--

Cause	An invalid NCS command entered.
Effect	IMNi rejects the command.
Response	Enter a valid NCS command.

5301	Process Trace Audit file A named <new-name>
-------------	--

Cause	An NCS ANA/ANB command is received and the indicated trace audit file is renamed.
Effect	IMNi uses the new trace audit file name.
Response	None required.

5302	Process Trace Audit file <file-name> not renamed
-------------	---

Cause	An NCS ANA/ANB command is received, but the name of the indicated audit trace file cannot be changed.
Effect	IMNi continues using the previous audit trace file name if possible.
Response	Resend the ANA/ANB command with a different file name.

5303	Process Trace Audit file B named <new-name>
-------------	--

Cause	An NCS ANA/ANB command is received and the indicated audit trace file is renamed.
Effect	IMNi uses the new trace audit file name.
Response	None required.

5304	Process Trace Audit file B not renamed
-------------	---

Cause	An NCS ANA/ANB command is received, but the name of the indicated audit trace file cannot be changed.
Effect	IMNi continues using the previous audit trace file name if possible.
Response	Resend the ANA/ANB command with a different file name.

5305	Process Trace Audit extent not set
-------------	---

Cause	An NCS change audit file extent command is received, but the extent indicated for the audit trace file is not valid.
Effect	IMNi continues using the previous audit trace file extents if possible.
Response	Resend the change audit file extent command with a different file extent.

5306	Process Trace Audit extent set to <extent size>
-------------	--

Cause	An NCS ADX command is received.
Effect	IMNi creates subsequent trace audit files with the indicated extent size.
Response	None required.

5307	Process Trace Audit file not switched
-------------	--

Cause	An NCS ADX command is received, but the trace audit file could not be switched.
Effect	IMNi does not switch the trace audit files.
Response	Resend the ANA, ANB, and SWA commands.

5308	Process Trace Audit file switched
-------------	--

Cause	An NCS ADX command is received and the trace audit file is switched to audit file A and audit file name A is changed to audit file name B.
Effect	IMNi begins using the new trace audit file.
Response	None required.

5309	Process Trace Audit file - <file name>
-------------	---

Cause	Trace audit file exists.
Effect	IMNi logs trace audit file name.
Response	None required.

5310	Process Trace Audit file - NO FILE NAME
-------------	--

Cause	Trace audit file not exists.
Effect	IMNi logs the error message.
Response	None required.

5311	Process Trace Audit file A - <file name>
-------------	---

Cause	Trace audit file A exists.
Effect	IMNi logs trace audit file A name.
Response	None required.

5312	Process Trace Audit file A - NO FILE NAME
-------------	--

Cause	Trace audit file A does not exist.
Effect	IMNi logs no file name message.
Response	None required.

5313	Process Trace Audit file B - <file name>
-------------	---

Cause	Trace audit file B exists.
Effect	IMNi logs trace audit file B name.
Response	None required.

5314	Process Trace Audit file B - NO FILE NAME
-------------	--

Cause	Trace audit file B does not exist.
Effect	IMNi logs no file name message.
Response	None required.

5315	Process Trace Audit file extent size = <file extent size>
-------------	--

Cause Display the audit file extent size.

Effect None.

Response None required.

5401-5410	Process Trace Audit filename is bad - <file name>
------------------	--

Cause An NCS ANA/ANB command is received, but the file name specified is invalid.

Effect IMNi ignores the command.

Response Resend the command with a valid file name.

5411	POS cutover date set to: <YYMMDD>
-------------	--

Cause An NCS cutover command is received and the POS cutover date is set.

Effect IMNi begins using the new cutover date.

Response None required.

5412	Cutover command not supported for ATM
-------------	--

Cause An NCS cutover command is received for the ATM product.

Effect IMNi ignores the command.

Response IMNi does not yet support ATM.

5413	Invalid product type <product type>
-------------	--

Cause	An NCS cutover command is received that contained an invalid product type.
Effect	IMNi ignores the command.
Response	Resend the command with the correct product type.

5414	Invalid Date <YYMMDD>
-------------	------------------------------------

Cause	An NCS CUTOVER command is received that contains an invalid date.
Effect	IMNi ignores the command.
Response	Resend the command with the correct date.

5415	RELOADEP ALL successfully processed
-------------	--

Cause	An NCS RELOADEP command is received and successfully processed.
Effect	IMNi continues with the new entry point configuration.
Response	None required.

5440	RELOADEP ALL *failed* because of EPCF error
-------------	--

Cause	An NCS RELOADEP command is received and failed.
Effect	Entry Point Table cannot be reloaded.
Response	Check EPCF for abnormalities.

5416-5420 RELOADEP <entry point Id>: Entry Point <DELETED/NOT FOUND/UPDATED/ADDED/TABLE FULL>

Cause	An NCS RELOADEP command is received and the indicated event occurred.
Effect	IMNi continues processing the command.
Response	If the entry point table is full, the program limit has been reached. Configure another IMNi process.

5421-5422 Entry Point ID <entry point Id> was not found in EPT

Cause	An NCS START/STOP EP command is received and the indicated entry point is not found.
Effect	IMNi logs the message and continues processing.
Response	Check the entry point entered in the NCS command.

5423 Entry Point ID <entry point id> to CIL <CIL process name> STARTED

Cause	Activate an entry point successfully.
Effect	None.
Response	None required.

5424 Entry Point ID <entry point id> has already started

Cause	Attempt to activate an already started entry point.
Effect	None.
Response	None required.

5425	Entry Point ID <entry point id> not found in EPCF file. Reload all EPs
-------------	---

Cause Attempt to activate an entry point.

Effect None.

Response None required.

5427	Invalid Entry Point ID <entry point Id>
-------------	--

Cause An NCS START UP or STOP EP command is received, but the specified entry point is invalid.

Effect IMNi ignores the command.

Response Resend the command with the correct entry point Id.

5428	No SAF records exist (destn = <node Id> <msg class>, SAF file= <file name>)
-------------	--

Cause An NCS SAFDELETE command is received, but there are no SAF records present for the specified destination.

Effect IMNi ignores the command.

Response None required.

5429	No SAF records exist (destn = <node-id> <msg-class>, SAF file = <file name>)
-------------	---

Cause No SAF records to be deleted from destination.

Effect None.

Response None required.

5430	No SAF records exist (destn = <node-id> <msg-class>, SAF file= <file name>)
-------------	--

Cause No SAF records to be deleted from destination.

Effect None.

Response None required.

5431	Top SAF record deleted (destn= <node ID> <msg class>, SAF file= <file name> timestamp= <YYYY MM DD HH:MM:SS>)
-------------	--

Cause An NCS SAFDELETE command is received and the top SAF record is deleted.

Effect IMNi continues processing the remainder of the SAF.

Response None required.

5432	Undefined status given: <connection status>
-------------	--

Cause An NCS SET command is received that contains an invalid connection state.

Effect IMNi ignores the command.

Response Resend the command with the correct status.

5433	Invalid pacing state given: <pacing state>
-------------	---

Cause An NCS PACING STATE command is received that contained an invalid pacing state.

Effect IMNi ignores the command.

Response Resend the command with the correct pacing state.

5434 **Previous Pacing State: <previous state>, New Pacing State: <new state>**

Cause An NCS PACING STATE command is received and the pacing state is set to the indicated value.

Effect IMNi continues with the new pacing state.

Response None required.

5435* **This command is only valid in IMN Manager**

Cause The operator issued an invalid SET command to the IMNi.

Effect The command will be ignored.

Response Deliver the SET command to the IMNM.

5501 **<IMNi name> STATUS COMMAND - RELEASE 1.2 -**
ENTRY CIL PID ENTRY POINT PACING QUEUE
POINT ID STATUS STATUS SIZE
<entry point> <cil id> <entry point status> <pacing status> <io count>
BASE24-pos DATE: <yymmdd>
INTERAC DATE: <yymmdd>, BANK: <fil id>
outbound requests pending of # maximum requests
inbound requests pending of # maximum requests
timers active of # maximum timers
\$ IMNLF records of \$ maximum IMNLF records, # % full
Entry Points defined in EPT
Entry Points stopped # Entry Points unavailable
Entry Points pending # Entry Points available

Cause Display entry point status.

Effect None.

Response None required.

5502

===== BASE-24 POS PACING STATUS =====

CURRENT RECENT STATUS WEIGHT	TOTAL RESPONSE TIME	CURRENT TRXNS COUNT	AVERAGE RESPONSE TIME	CONGESTED THRESHOLD FACTOR	BLOCKED THRESHOLD %
<state>	<time>	<count>	<time>	<no.>	<no.>

Cause Display BASE24 POS pacing status.

Effect None.

Response None required.

5503

===== CONNECTION STATUS COMMAND =====

MSG NODE ID	NODE CLASS	CNXN NAME	STATUS STATE	OUTBOUND EP PACING STATUS	INBOUND EP PACING STATUS
<node-id>	<msg-cls>	<name>	<state>	<state>	<state>

Cause Display connection status.

Effect None.

Response None required.

5504

dct[<index>] <node name> <node id> <msg-class> obp= <pacing status> ibp= <pacing status> link= <link state>

Cause Display DCT information.

Effect None.

Response None required.

5505	dct[<index>] <saf filename> fnum=<fileno> T=<counter> VR=<response> IR=<response> I-O=<forward mode>(FM)
-------------	---

Cause Display the DCT SAF info.

Effect None.

Response None required.

5506	MAC idx= # ctr= # max= # sync= # st= # key= <key value> kek^ctr= <counter> MAC badctr= # badmax= # failctr= # failmax= # MSG idx= # ctr= # max= # sync= # st= # key= <key value> kek^ctr= <counter> PIN idx= # ctr= # max= # sync= # st= # key= <key value> kek^ctr= <counter> PIN Block Failure ctr= # PIN Block Failure max= # KEK okcc= # okcmax= # toc= # tom= # rej^ctr= # rej^max= # isyn=<key value> osyn= # INBOUND KEYS: fkt^x= # ifac= # ifamax= # ikcc= # ikcmax= # PIN: FIL=<index>key[0]= <key> key[1]= <key> kek^ctr[0]= # kek^ctr[1]= #sync^err^ctr= # KEK: FIL= <index> kek= <KEK key> ', ' out^seq^no= <seq.no> in^seq^no= <seq.no>)
-------------	---

Cause Display the DCT key info.

Effect None.

Response None required.

5507	IPT no longer defined in IMNi
-------------	--------------------------------------

Cause IPT table is no longer in IMNi.

Effect None.

Response None required.

5508	CIL-PID FNUM SFNUM FID MC SB SS-ID SEL-THRU CUR-THRU NWD
	<process name> <fileno> <send. process no> <fil id> <msg-class> <subsystem id> <security byte> <thru put> <thru put> <io count>

Cause Display the entry point table.

Effect None.

Response None required.

5509	BIN[<index>] <card prefix> <node id> <compare length>
-------------	--

Cause Display the BIN table.

Effect None.

Response None required.

5510	BIN = <file name> fnum= <file number> KEYF = <file name> fnum= <file number> ADMN = <file name> fnum= <file number> IMNM = <file name> fnum= <file number> ILF: <index> file= <file name> fnum= <file number> ferror= <file error number> ILF: date= <yymmdd> SETL: pos date= <yymmdd> switch date= <yymmdd>
-------------	---

Cause Display file information.

Effect None.

Response None required.

5511	Timer type= <timer-type> subtype= <timer-subtype> exptime= ## ##:##:##.## # timers active of # maximum timers
-------------	--

Cause Display timer information.

Effect None.

Response None required.

5512	Trace Bit settings: <trace bits>
-------------	---

Cause Display trace bit settings.

Effect None.

Response None required.

5513	===== DISPLAY =====
-------------	----------------------------

Cause Header line for Display command.

Effect None.

Response None required.

5514	Invalid DISPLAY command given: <command text> Commands: DCT SAF, DCT KEYS, BIN FILES, IPT, TIMERS, EPT, TRACEBITS
-------------	--

Cause An NCS DISPLAY command is received that contains an invalid display option or
parameter.

Effect IMNi ignores the command.

Response Resend the command with the correct option or parameter.

5515 **<IMNi name> Command - Release 1.2 -**
Destination Node: <node id> Msg Class: <msg-class>
Destination : inbound, BASE24-pos Msg Class:<msg-class>
Destination : inbound, BASE24-atm Msg Class:<msg-class>
Period requests timeouts AVG RESP percent
Time Approvals
##:##:## <outb request> <outb request> ##.## # %

Can't find the node <node Id> in DCT

Cause An NCS PERFORMANCE command is received that contains an unknown node Id.

Effect IMNi ignores the command.

Response Resend the command with the correct node Id.

5516 <node id> <msg class> <timer value> are required REPEAT parameters

Cause An NCS PERFORMANCE REPEAT command is received that contains missing or invalid parameters.

Effect IMNi ignores the command.

Response Resend the command with the correct parameters.

5517 Repeat command ignored - invalid time given: <repeat time>

Cause An NCS PERFORMANCE REPEAT command is received that contains an invalid repeat time interval.

Effect IMNi ignores the command.

Response Resend the command with the correct repeat time interval.

5518	Performance repeat rate for <node Id> <msg class> set to <repeat interval> minutes (0=off)
-------------	---

Cause	An NCS PERFORMANCE REPEAT command is received and the performance repeat interval is set to the indicated value.
Effect	IMNi sets the repeat interval to the indicated value. If the interval is greater than 0, a performance repeat timeout is posted.
Response	None required.

5519	Invalid PERFORMANCE sub-command given: <command text>
-------------	--

Cause	An NCS PERFORMANCE command is received that contains an invalid performance option.
Effect	IMNi ignores the command.
Response	Resend the command with the correct option.

5601	Invalid Filename <file name>
-------------	---

Cause	An NCS SWL command is received that contains an invalid file name.
Effect	IMNi ignores the command.
Response	Resend the command with the correct file name.

5602	Invalid IMNM Key Change command length: #
-------------	--

Cause	Invalid key exchange command length sent from IMNM.
Effect	IMNi logs the error message and continues processing.
Response	Check the IMNM key exchange command.

5603	Invalid IMNM <IMNM msg type> fil id :<FIL Id>
-------------	--

Cause	An IMNM message is received that contains an invalid FIL ID.
Effect	IMNi ignores the message.
Response	This indicates an internal code problem. Contact your vendor representative.

5604	Invalid IMNM <IMNM msg type> command length: <IMNM msg length>
-------------	---

Cause	An IMNM message is received with an unexpected length.
Effect	IMNi ignores the message.
Response	This indicates an internal code problem. Contact your vendor representative.

5605	Invalid IMNM Set Key Info fil id:<fil id>
-------------	--

Cause	Invalid FIL id in Set Key Info command sent from IMNM.
Effect	IMNi logs the error message and continues processing.
Response	Check the IMNM Set Key Info command.

5606	Invalid IMNM <IMNM msg type> key index :<key index>
-------------	--

Cause	An IMNM message is received that contained an invalid key index.
Effect	IMNi ignores the message.
Response	This indicates an internal code problem. Contact your vendor representative.

5607	Invalid IMNM <IMNM msg type> key type: <key type>
-------------	--

Cause	An IMNM message is received that contains an invalid key type.
Effect	IMNi ignores the message.
Response	This indicates an internal code problem. Contact your vendor representative.

5608	Invalid IMNM Alter Pacing Dest command length : #
-------------	--

Cause	Invalid Alter Pacing Destination command length sent from IMNM.
Effect	IMNi logs the error message and continues processing.
Response	Check the IMNM Alter Pacing Destination command.

5609*	Invalid SHOW command given: <command-text>
--------------	---

Cause	The operator issued an invalid SHOW command to the IMNi.
Effect	The command will be ignored.
Response	Check for correct syntax and re-issue command.

5610	Invalid IMNM Saf Count Modify command length : #
-------------	---

Cause	Invalid IMNM SAF COUNT MODIFY command length sent from IMNM.
Effect	IMNi logs the error message and continues processing.
Response	Check the IMNM SAF COUNT MODIFY command.

5611	<SAF transaction count> transactions added to SAF for destination <node Id> <msg class>
-------------	--

Cause An IMNM SAF COUNT MODIFY command is received from the IMNM process and the transaction count for the destination is changed.

Effect IMNi continues processing with the new transaction count.

Response None required.

5612	Invalid IMNM Saf State command length : #
-------------	--

Cause Invalid SAF state message length sent from IMNM.

Effect IMNi logs the error message and continues processing.

Response Check the IMNM SAF state message.

5613	Invalid number of destinations in IMNM <IMNM msg type> command :<destination count>
-------------	--

Cause An IMNM message is received that contains an invalid number of destinations.

Effect IMNi ignores the message.

Response This indicates an internal code problem. Contact your vendor representative.

5614	Invalid IMNM Set command length : #
-------------	--

Cause Invalid Set command length sent from IMNM.

Effect IMNi logs the error message and continues processing.

Response Check the IMNM SET command.

5615	Invalid IMNM Warmboot command length : #
-------------	---

Cause	Invalid Warmboot command length sent from IMNM.
Effect	IMNi logs the error message and continues processing.
Response	Check the IMNM Warmboot command.

5616	Invalid Destination <node Id> <msg class>
-------------	--

Cause	An NCS command is received that contains an invalid node Id or message class.
Effect	IMNi ignores the command.
Response	Resend the command with the correct destination information.

5617	Can't find the destination '<node Id> <msg class>' in DCT
-------------	--

Cause	An NCS command is received that contains an unknown destination.
Effect	IMNi ignores the command.
Response	Resend the command with the correct destination information.

5618*	Invalid destination <command-text>
--------------	---

Cause	Invalid destination is specified.
Effect	Command will be ignored.
Response	Input a valid destination.

5619* Can't find the destination <node-id> <msg-cls> in CGT

Cause Invalid connection group id is specified.

Effect Command will be ignored.

Response Input a valid connection in the group.

5622 Warmbooting IMNi process = <IMNi process name> on node = <IMNi node Id>

Cause An NCS or IMNi WARMBOOT command is received and the warmboot processing is about to begin.

Effect IMNi begins the warmboot processing.

Response Check subsequent log message to determine if the warmboot completed successfully.

5623 WARMBOOT *failed* because of LCONF error

Cause An NCS or IMNM WARMBOOT command is received, but the warmboot fails due to an error on the LCONF file.

Effect IMNi cannot complete the warmboot and may be in an inconsistent state.

Response Check previous log messages for GUARDIAN errors to determine the appropriate response. Repeat the warmboot or restart the IMNi.

5624 WARMBOOT completed successfully -- New status implemented

Cause An NCS or IMNM WARMBOOT command is received and the warmboot is successfully completed.

Effect IMNi continues processing with the new configuration.

Response None required.

5625 WARMBOOT errors - correct and retry warmboot

Cause	An NCS or IMNM WARMBOOT command is received, but the warmboot operation fails
Effect	IMNi cannot complete the warmboot and may be in an inconsistent state.
Response	Check previous log messages for GUARDIAN errors to determine the appropriate response. Repeat the warmboot or restart the IMNi.

5626 No POS record found in the TKN file - all PSTM tokens will be logged to the ILF

Cause	Check for POS record in the TKN file.
Effect	IMNi logs the message and continues processing.
Response	None required.

5701* **===== SHOW DCT COMMAND =====**
ACQ CNXN ISS CNXN CNXN CNXN ROUTING
STATE STATE STATUS GRP ID METHOD
<acq-cnxn-state> <iss-cnxn-state> <status> <cnxn-grp> <routing-method>

Cause	Operator issued the SHOW DCT command.
Effect	The contents of the DCT table will be displayed.
Response	None required.

5702*

```
===== SHOW CGT COMMAND =====  
NODE MSG NODE ROUTING CNXN ACQ CNXN ISS CNXN  
ID CLASS NAME METHOD STATUS STATE STATE  
<node-id> <msg-cls> <node-name> <routing-method> <status> <acq-cnxn-state> <iss-cnxn-  
state>
```

Cause Operator issued the SHOW CGT command.

Effect The contents of the CGT table will be displayed.

Response None required.

6101 Entry Point ID <entry point Id> to CIL <CIL process name> STOPPED

Cause An NCS START EP command is received, but the indicated entry point is already started.

Effect IMNi logs the message and continues.

Response None required.

6102 Entry Point ID <entry point Id> has already stopped

Cause An NCS command is received to stop an entry point that is already stopped.

Effect IMNi logs the message and continues.

Response Restart the entry point if required.

6103 PROC ERROR: Write to closed or unopened EP:<entry point Id> State:<entry point state> PID:CIL process name>

Cause An attempt is made to write a message to an entry point that is closed.

Effect IMNi cannot send the message to the indicated entry point.

Response This indicates an internal code problem. Contact your vendor representative.

6104	TRACE04: Write to EP: <entry point Id> Cnxn: <connection Id> Type: <msg type, subtype> status: <status and reason codes>
-------------	---

Cause	Trace bit 4 is turned on and a message is about to be written to the indicated entry point.
Effect	IMNi writes the message to the entry point.
Response	None required.

6105	IO ERROR: Write to PID: <CIL process name> EP:<entry point Id> State:<entry point state> Err:<GUARDIAN error code>
-------------	---

Cause	An I/O error occurred on a write to the indicated entry point.
Effect	IMNi closes the entry point and re-opens it when the recovery timeout expires.
Response	Check the GUARDIAN error code to determine the appropriated response. Check that the CIL process is running.

6106	TRACE05: No EP Selected
-------------	--------------------------------

Cause	Trace bit 5 is turned on and no entry point can be selected for a message.
Effect	The message is not sent to the network.
Response	Check the status of all entry points.

6107	MACing not enabled for destn: <node Id> <msg class>, msg type:<msg type>
-------------	---

Cause	A message for the indicated destination is to be sent or received, but MAC generation is not enabled for the destination.
Effect	IMNi does not generate or verify the MAC for the destination.
Response	If required, turn MAC generation on for the destination using the ICF screen and restart or warmboot IMNi.

6108	ERROR: Unable to extract security block, msg type: <msg type>
-------------	--

Cause	A message with a missing security block is passed to the MAC generation procedure.
Effect	IMNi cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6109	ERROR: Invalid data in sec block (type <msg type>, Kmac:<MAC key index>, fil: <FIL ID>
-------------	---

Cause	A message with an invalid MAC key or Acquirer FIL Id in the security block is passed to the MAC generation procedure.
Effect	IMNi cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6110	No MAC keys available for destn: <node Id> <msg class>, msg type:<msg type>
-------------	--

Cause	A response message is passed to the MAC generation procedure. A message other than a key exchange is received from the network and no key data has been received from the indicated destination.
Effect	IMNi cannot generate or verify the MAC. If the message is a request, a 'No keys' response is returned (ISO 85).
Response	Contact operations personnel at the indicated destination to determine why no key exchange requests have been sent.

6111	Unable to generate MAC (Can't extract required fields) in <msg type> msg
-------------	--

Cause	A message is passed to the MAC generation procedure and the required fields for generating the MAC cannot be extracted from the message.
Effect	IMNi cannot generate the MAC and does not send the message.
Response	This indicates an internal code problem. Contact your vendor representative.

6112	Unable to generate MAC (pin^mac^generate error: <error code>) in <msg type> msg
-------------	--

Cause	A message is passed to the MAC generation procedure and the call to the security device access procedure fails.
Effect	IMNi cannot generate the MAC and does not send the message.
Response	Check previous log messages for GUARDIAN errors on the security device to determine the appropriate response. If no such errors, this may indicate an internal code problem. Contact your vendor representative.

6113	Unable to generate MAC, encrypt data (hpsm^mac^generate^date^encrypt^error: #) in <msg type> msg
-------------	---

Cause	A message is passed to the MAC generation procedure and the message encryption fails.
Effect	IMNi cannot generate the MAC and does not send the message.
Response	This may indicate an internal code problem. Contact your vendor representation.

6114	Unable to translate PIN, generate MAC (hpsm^mac^generate^date^encrypt^error: #) in <msg-type> msg
-------------	--

Cause	A message is received from the network that failed pin translation.
Effect	IMNi cannot translate the PIN from the message.
Response	This may indicate an internal code problem. Contact your vendor representative.

6115 MAC failed to verify (msg type = <msg type> response = <response code> destn = <msg class> <msg class>)

Cause	A message is received from the network that contains a bad MAC value.
Effect	IMNi logs the message. If the message is a request, IMNi returns a bad MAC error response (ISO 63).
Response	The acquirer node automatically recovers from MAC errors by changing the MAC key when the number of MAC failures had exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNi. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communication problems.

6116 MAC failed to verify - sync error (msg type = <msg type> MAC ctr rcvd = <key counter> , expecting = <kek key counter> response = <response code> destn = <node Id> <msg class>)

Cause	A message is received from the network that contains a lower MAC key counter value than expected in the security block.
Effect	IMNi logs the message to the ILF. If the message is a request, IMNi returns a MAC sync error response (ISO 88).
Response	The acquirer node automatically recovers MAC sync errors by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6117	Acct Bal failed to verify - sync error (msg type= <msg type> KME ctr revd= <MSG key counter>, expecting= <expected MSG key counter> response= <response code> destn= <node Id> <msg class>)
-------------	---

Cause	A response message is received from the network that contains a lower MSG key counter value than expected in the security block.
Effect	IMNi logs the message to the ILF.
Response	The acquirer node automatically recovers MAC sync errors by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6118	MAC failed to verify - SM error (msg type= <msg type> HPSM error = <error code> response = <response code>)
-------------	---

Cause	A message is received from the network, but its MAC cannot be verified due to an error accessing the security device.
Effect	IMNi logs the message to the ILF. If the message is a request, IMNi returns a system error response (ISO 96).
Response	Check previous log messages for GUARDIAN error codes to determine the appropriate response. It may be necessary to stop and start the security device handler process and then warmboot all processes that access the device. If the problem persists, contact your vendor representative.

6119	LOGIC ERROR: bad response code (msg type = <msg type>, response = <response code>
-------------	--

Cause	A message received from the network and an invalid response code is passed to the logging procedure from the MAC verification procedure.
Effect	IMNi logs the message to the ILF.
Response	This indicates an internal code problem. Contact your vendor representative.

6120	MACing not enabled for destn = <node Id> <msg class>, msg type:<msg type>
-------------	--

Cause	A message for the indicated destination is to be sent or is received, but MAC generation is not enabled for the destination.
Effect	IMNi does not generate or verify the MAC for the destination.
Response	If required, turn MAC generation on for the destination using the ICF screen and restart or warmboot IMNi.

6121	MAC failed to verify - unable to get security block (msg type= <msg type>)
-------------	--

Cause	A message is received from the network that does not contain an expected security block.
Effect	IMNi logs the message to the ILF. If the message is a request, IMNi returns an edit error response (ISO 06).
Response	This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6122	MAC failed to verify - edit error in security block (msg type = <msg type>, kmac = <MAC key index>, fil = <FIL Id>)
-------------	---

Cause	A message is received from the network that contains an invalid security block.
Effect	IMNi logs the message to the ILF. If the message is a request, IMNi rejects the message with an edit error response (ISO 06).
Response	This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6123	No MAC keys available for destn: <node-id> <msg-class> , msg type: <msg type>
-------------	--

Cause	A system generated issuer reversal message is received from the IMNi network, but no MAC key value exists for that destination.
Effect	IMNi returns a system error response (ISO 85).
Response	Contact operations personnel at the indicated destination to determine why no key exchange requests have been sent.

6124	Acct Bal failed to verify - invalid kme info in the security block (msg type = <msg type>, kme < MSG key index >, destn = < node Id > < msg class >)
-------------	---

Cause	A message is received from the network that contained an invalid MSG key in the security block.
Effect	IMNi logs the message to the ILF.
Response	This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6125	Error # translating acct bal field (msg type = <msg-type>)
-------------	---

Cause	A response message is received containing an account balance field, but the account balance cannot be translated from CBC encoding the ECB encoding.
Effect	IMNi cannot process the response message.
Response	Check previous log messages for GUARDIAN errors on the security device to determine the appropriate response. This may also indicate a bad format in the account balance field. IMNi is expecting a "C" or "D" followed by 15 digits.

6126	Acct Bal failed to verify - new MAC key translation failed (msg type = <msg type>)
-------------	---

Cause	A MAC key exchange request is received from the network, but the key value cannot be translated.
Effect	IMNi logs the message to the ILF. IMNi returns a system error response (ISO 96).
Response	Check previous log messages for GUARDIAN errors on the security device to determine the appropriate response. If no such errors, this may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6128	TRACE02: Cmd Dest:<symbolic process name> Len:<msg length> Txt:<msg test>
-------------	--

Cause	Trace bit 2 is turned on and an NCS message is about to be written to the nucleus.
Effect	IMNi writes the message to the nucleus.
Response	None required.

6129	PROC ERROR: NETWRITE failure <msg failure flag> Err: <msg failure code>
-------------	--

Cause	A write to the nucleus failed.
Effect	IMNi cannot send a message to a destination process.
Response	Check the status of the nucleus. If no errors, this may indicate an internal code problem. Contact your vendor representative.

6130	LOGIC ERROR: Invalid fil ID: <FIL Id>
-------------	--

Cause	An invalid FIL Id is passed to the IMNM notification procedure.
Effect	IMNi cannot send a notification message to IMNM.
Response	This indicates an internal code problem. Contact your vendor representative.

6132	TRACE13: Notify IMNM Type: < IMNM msg type > Out : # PN: # #
-------------	---

Cause	Trace bit 13 is turned on and a message is about to be written to the IMNM process.
Effect	IMNi writes the message to the IMNM process.
Response	None required.

6133	TRACE10: SAF mode Change Dest: <node-id> Mode: <saf mode>
-------------	--

Cause	Trace bit 10 is turned on and the new SAF mode for the specified destination is displayed.
Effect	IMNi logs the message.
Response	Display SAF to verify the new mode.

6134	CSM rejected counter = <rejected count>, message class <msg class>, dest <node Id>
-------------	---

Cause	The number of key exchange requests rejected by the indicated destination has reached the rejection threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If key exchange rejection alarms to a specific destination persist this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6134	CSM timeout counter = < timeout count >, message class <msg class>, dest <node Id>
-------------	---

Cause	The number of outbound key exchange timeouts has reached the timeout count alarm threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If key exchange timeouts persist, increase the key exchange timeout interval using the ICF screen then restart or warmboot.

6134 Inbound key conveyance alarm = <error count>, message class <msg class>, dest <node Id>

Cause The number of key conveyance errors in inbound key exchange messages has reached the alarm threshold.

Effect IMNi resets the counter, logs the message and continues.

Response If key conveyance alarms persist, this may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6134 Inbound MAC fail alarm = <MAC fail cont>, message class <msg class>, dest <node Id>

Cause The number of inbound MAC verify failures for the indicate node has reached the MAC failure alarm threshold.

Effect IMNi resets the counter, logs the message and continues.

Response If a MAC failure alarm for a specific destination persists, this may indicate an unauthorized attempt to modify protected message elements or an internal code problem with either the sending or receiving node. Each MAC error should be investigated by identifying the message and comparing the elements with the sending node to determine if the differences are due to intentional tampering or to communications problems. Contact your vendor representative.

6134 Inbound <PIN/MAC/MSG> sync - <sync error count>, message class <msg class>, dest <node Id>

Cause The number of key sync errors for the indicated key type has passed the sync error threshold.

Effect IMNi resets the counter, logs the message and continues.

Response If key sync error alarms for a specific destination persist this may indicate an unauthorized attempt to modify encrypted fields or an internal code problem with either the sending or receiving node. The Issuer FIL operator should stop Acquirer transactions from being forwarded to the Issuer FIL by setting the status of the connection to the Acquirer FIL to "down". Contact your vendor representative.

6134	Inbound <PIN/MAC/MSG> sync - <sync error count>, message class <msg class>, dest <node Id>
-------------	---

Cause	The number of key sync errors for the indicated key type has passed the sync error threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If key sync error alarms for a specific destination persist this may indicate an unauthorized attempt to modify encrypted fields or an internal code problem with either the sending or receiving node. The Issuer FIL operator should stop Acquirer transactions from being forwarded to the Issuer FIL by setting the status of the connection to the Acquirer FIL to "down". Contact your vendor representative.

6134	Outbound <PIN/MAC/MSG> sync - <sync error count>, message class <msg class>, dest <node Id>
-------------	--

Cause	The number of key sync errors for the indicated key type has passed the sync error threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If key sync error alarms for a specific destination persist this may indicate an unauthorized attempt to modify encrypted fields or an internal code problem with either the sending or receiving node. The Issuer FIL operator should stop Acquirer transactions from being forwarded to the Issuer FIL by setting the status of the connection to the Acquirer FIL to "down". Contact your vendor representative.

6134	Outbound key conveyance alarm = <error count>, message class <msg class>, dest <node Id>
-------------	---

Cause	The number of key conveyance errors in outbound key exchange messages has reached the alarm threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If key conveyance alarms persist, this may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6134	Outbound MAC fail alarm = <MAC fail count>, message class <msg class>< dest <node Id>
-------------	---

Cause	The number of outbound MAC verifies failures for the indicated node has reached the MAC failure alarm threshold.
Effect	IMNi resets the counter, logs the message and continues.
Response	If MAC failure alarms for a specific destination persist this may indicate an unauthorized attempt to modify protected message elements or an internal code problem with either the sending or receiving node. Each MAC error should be investigated by identifying the message and comparing the elements with the sending node to determine if the differences are due to intentional tampering or to communications problems. Contact your vendor representative.

6135	TRACE01: utl^setCutoverTimer subtype: <timer subtype>
-------------	--

Cause	Trace bit 1 is turned on and the indicated timer subtype is about to be posted.
Effect	IMNi posts the timeout.
Response	None required.

6136	LOGIC ERROR: Invalid Cutover SubType: <timer subtype>
-------------	--

Cause	An invalid timer subtype is passed to the cutover timeout posting procedure.
Effect	IMNi cannot post procedure.
Response	This indicates an internal code problem. Contact your vendor representative.

6137 WARNING: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>

Cause The switch date read from the ICF control record is not the expected switch date (system date before cutover start, system date + 1 after cutover).

Effect IMNi uses the switch date from the ICF record.

Response Change the ICF switch date to the date indicated and warmboot IMNi unless testing of old transaction dates is being performed.

**6138 WARNING: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>
WARNING: Using Expected Date as Posting Date**

Cause The switch date read from the ICF control record is not the expected switch date (system date before cutover start, system date + 1 after cutover).

Effect IMNi uses the switch date from the ICF record that will be updated with the expected date.

Response Warmboot IMNi unless testing of old transaction dates is being performed.

6139 ERROR: ICF Switch Posting Date is <YYMMDD>, expected <YYMMDD>

Cause The switch date read from the ICF control record is not the expected switch date (system date before cutover start, system date + 1 after cutover).

Effect IMNi initialization failed.

Response Change the ICF switch date to the expected date.

6150* Invalid Set CNXN Status: <iss-cnxxn-status>

Cause An invalid issuer connection status literal is passed to the connection status modification procedure.

Effect IMNi cannot update the connection status.

Response Check the syntax of the command.

6151* **Cnxn status set (destn: <node Id>, msg class <msg class>, state: <iss-cnxxn-state>)**

Cause The issuer connection state for the indicated connection is set.

Effect IMNi uses the new connection state.

Response None required.

6152* **Cnxn status set (destn: <node Id>, msg class <msg class>, state: <acq-cnxxn-state>)**

Cause The acquirer connection state for the indicated connection is set.

Effect IMNi uses the new connection state.

Response None required.

6153* **Invalid Set CNXXN Status: <acq-cnxxn-status>**

Cause An invalid acquirer connection status literal is passed to the connection status modification procedure.

Effect IMNi cannot update the connection status.

Response Check the syntax of the command.

6160 **TRACE05: SelectEp extX:<entry point table index> Ep:<CIL process name, subdevice> NWD:<I/O outstanding count> Thruput:<throughput> pacing:< pacing status>**

Cause Trace bit 5 is turned on and the indicated entry point is selected for a message.

Effect The message is sent to the entry point.

Response None required.

6161	MAC failed to verify - edit error (msg type= <msg type> response= <response code>)
-------------	---

Cause	A message is received from the network that contains an invalid or missing field.
Effect	IMNi logs the message. If the message is a request, IMNi returns an edit error response (ISO 06).
Response	This may indicate an internal code problem. Contact your vendor representative.

6162	MAC failed to verify (msg type = <msg type> response = <response code> destn = <msg class> <msg class>)
-------------	---

Cause	A message is received from the network that contains a bad MAC value.
Effect	IMNi logs the message. If the message is a request, IMNi returns a bad MAC error response (ISO 63).
Response	The acquirer node automatically recovers from MAC errors by changing the MAC key when the number of MAC failures had exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNi. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

6163	DiMacKey1, "KEY Values (1), Idx = FKT KEK = <KEK key> FKT KMAC = <MAC key>
-------------	---

Cause	A network management/key exchange message is received from the network that contains a bad MAC value.
Effect	IMNi logs the message.
Response	The acquirer node automatically recovers from MAC errors by changing the MAC key when the number of MAC failures had exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNi. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

6164	DiMacKey2, “KEY Values (2), ENC KMAC = <MAC key index> NEW KMAC = <MAC key index>
-------------	--

Cause	A network management/key exchange message is received from the network that contains a bad MAC value.
Effect	IMNi logs the message.
Response	The acquirer node automatically recovers from MAC errors by changing the MAC key when the number of MAC failures had exceeded the MAC failure threshold. If MAC errors persist, decrease the MAC failure threshold for the destination using the ICF screen and restart or warmboot the IMNi. MAC failures may also indicate an unauthorized attempt to modify protected message elements. Messages with MAC errors should be identified and compared by the Acquirer and Issuer institutions to determine if tampering has taken place or if the errors may be explained by communications problems.

6165	MAC failed to verify - sync error (msg type = <msg type> MAC ctr rcvd = <key counter> , expecting = <kek key counter> response = <response code> destn = <node Id> <msg class>)
-------------	---

Cause	A message is received from the network that contains a lower MAC key counter value than expected in the security block.
Effect	IMNi logs the message to the ILF. If the message is a request, IMNi returns a MAC sync error response (ISO 88).
Response	The acquirer node automatically recovers MAC sync errors by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6166 **DiMacKey1, “KEY Values (1), Idx = FKT KEK = <KEK key value>
FKT KMAC = <MAC key value>**

Cause A network management/key exchange message is received from the network that contains a key sync error.

Effect IMNi logs the message to the ILF.

Response The acquirer node automatically recovers MAC sync errors by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6167 **DiMacKey2, “KEY Values (2), ENC KMAC = <MAC key value>
NEW KMAC = <Mac key value>**

Cause A network management/key exchange message is received from the network that contains a key sync error.

Effect IMNi logs the message to the ILF.

Response The acquirer node automatically recovers MAC sync errors by switching to the other MAC key index and changing the key for which the sync error occurred. If MAC sync errors persist, this may indicate an internal code problem, with either the sending or receiving node. Contact your vendor representative.

6168 **MAC failed to verify - SM error (msg type= <msg type> HPSM error = <error
code> response = <response code>)**

Cause A message is received from the network, but its MAC cannot be verified due to an error accessing the security device.

Effect IMNi logs the message to the ILF. If the message is a request, IMNi returns a system error response (ISO 96).

Response Check previous log messages for GUARDIAN error codes to determine the appropriate response. It may be necessary to stop and start the security device handler process and then warmboot all processes that access the device. If the problem persists, contact your vendor representative.

6169	LOGIC ERROR: bad response code (msg type = <msg type>, response = <response code>)
-------------	---

Cause	A message is received from the network and an invalid response code is passed to the logging procedure from the MAC verification procedure.
Effect	IMNi logs the message to the ILF.
Response	This indicates an internal code problem. Contact your vendor representative.

6170	No MAC keys available for destn: <node-id> <msg-class> , msg type: <msg type>
-------------	--

Cause	A system generates issuer reversal message is received from the IMNi network, but no MAC key value exists for that destination.
Effect	IMNi returns a system error response (ISO 85).
Response	Contact operations personnel at the indicated destination to determine why no key exchange requests have been sent.

6171	Acct Bal failed to verify - kme info missing from security block (msg type = <msg type>, destn = <node Id> <msg class>)
-------------	---

Cause	A message is received from the network that contained a security block that is not long enough to contain the MSG key index or counter.
Effect	IMNi logs the message to the ILF.
Response	This may indicate an internal code problem in either the sending or receiving node. Contact your vendor representative.

6172	Error # translating acct bal field (msg type = <msg type>)
-------------	--

Cause	A response message is received containing an account balance field, but the account balance could not be translated.
Effect	IMNi cannot process the response message.
Response	None required.

6180	TRACE03: POS Msg Dest:<symbolic process name> Typ:<msg type> Tran:<processing code> Resp:<BASE24 response code>
-------------	--

Cause	Trace bit 3 is turned on and a POS message is about to be written to the nucleus.
Effect	IMNi writes the message to the nucleus.
Response	None required.

6190	Not able to sent message to process <IMNM process>, error <GUARDIAN error code>
-------------	--

Cause	A write to the IMNM process failed and IMNi will close the process file.
Effect	IMNi cannot exchange messages with the IMNM process. IMNi will attempt to re-open the IMNM process when the recovery timeout expires.
Response	Check the GURADIAN error code to determine the specific nature of the error and take action accordingly. Restart the IMNM process if necessary.

6191	IMNM manager process <filename> closed for communication
-------------	---

Cause	A write to the IMNM process failed and IMNi will close the process file.
Effect	IMNi cannot exchange messages with the IMNM process. IMNi will attempt to re-open the IMNM process when the recovery timeout expires.
Response	Check the GURADIAN error code to determine the specific nature of the error and take action accordingly. Restart the IMNM process if necessary.

6201	TRACE09: Reloading DCT File:<file name>
-------------	--

Cause	Trace bit 9 is turned on and the DCT table will be reloaded with information from the indicated KEYF file for acquirer transactions.
Effect	IMNi reloads the inbound key table.
Response	None required.

6211	TRACE09: Reloading FKT File:<file name>
-------------	--

Cause	Trace bit 9 is turned on and the inbound key table will be reloaded with information from the indicated KEYF file for issuer transactions.
Effect	IMNi reloads the inbound key table.
Response	None required.

6220	Error while attempting to get token
-------------	--

Cause	IMNi failed to read an existing token in FIL user data from the PSTM.
Effect	A program dump will be created and the process abends.
Response	Inspect the program dump file for error.

6221	Error while attempting to get token
-------------	--

Cause	Failed to retrieve an existing PSTM's Acct Balance token.
Effect	A program dump will be created and the process abends.
Response	Inspect the program dump file for error.

6230	Error while attempting to get token
-------------	--

Cause	The retrieve of an existing token in FIL user data from the PSTM when writing FIL user data to the PSTM message fails.
Effect	The PSTM cannot be updated with the FIL data. A program dump will be created and the process abends.
Response	Inspect the program dump file for error.

6231	No room to add token
-------------	-----------------------------

Cause	Not enough space to add FIL data token.
Effect	The write of the FIL data to the PSTM fails.
Response	Examine the PSTM message to determine if it is full or if not then this could be an internal code problem. Contact your vendor representative.

6232	Error while attempting to add token
-------------	--

Cause	The token address is out of bounds or a required parameter is missing.
Effect	Unsuccessful write of FIL data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for error.

6233	Error while attempting to update token
-------------	---

Cause	An error occurred while trying to update the FIL data.
Effect	Unsuccessful write of FIL data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for error.

6240	Error converting the ILF SEM length from ascii to integer - ILF prikey: <ilf-prikey>
-------------	---

Cause	An error occurred while converting the ILF's external message length from ASCII to integer.
Effect	The ILF cannot be updated with the SEM data and with the token data. The ILF update process abends and a program dump will be created.
Response	Inspect the program dump file for error.

6241	SEM length is greater than the maximum allowed SEM length in the ILF record - ILF prikey: <ilf-prikey>
-------------	---

Cause	The length of the new external message data exceeds the ILF's external message length.
Effect	The ILF cannot be updated with the new SEM data. The ILF update process abends and a program dump will be created.
Response	Inspect the program dump file.

6242	Invalid ILF record type - ILF prikey: <ilf-prikey>
-------------	---

Cause	The ILF record has invalid record type.
Effect	The ILF cannot be updated with the new SEM data. The ILF update process abends and a program dump will be created.
Response	Inspect the program dump file.

6243	Error while attempting to get the token ids from the ILF record - ILF prikey: <ilf-prikey>
-------------	---

Cause	An error occurred when retrieving the token ids from the ILF record.
Effect	The ILF cannot be updated with the new SEM data. Process abends and a program dump will be created.
Response	Inspect the program dump file for the error.

6244	Error while attempting to get the token ids from the SIM to update into the ILF record - ILF prikey: <ilf-prikey>
-------------	--

Cause	An error occurred when retrieving the token ids from the SIM.
Effect	The ILF cannot be updated with the new SEM data. Process abends and a program dump will be created.
Response	Inspect the program dump file for the error.

6245	Token data cannot be increased in size on an update in the ILF record - ILF prikey: <ilf-prikey>
-------------	---

Cause	The token data is larger in the internal message than in the ILF record.
Effect	The token data in the ILF record will not be updated.
Response	None required.

6246	Error while attempting to update token <sim-tn-id> into the ILF record - ILF prikey: <ilf-prikey>
-------------	--

Cause	The ILF update with the token data from the internal message failed.
Effect	A program dump will be created and the process abends.
Response	Inspect the generated program dump for error.

6247	Error converting the ILF SEM length from integer to ascii - ILF prikey: <ilf-prikey>
-------------	---

Cause	An error occurred while converting the ILF's external message length from integer to ASCII.
Effect	The ILF cannot be updated with the SEM data. The ILF update process abends and a programmatic dump will be generated.
Response	Inspect the program dump file for errors.

6248	SEM length is greater than the maximum allowed SEM length in the ILF record - ILF prikey: <ilf-prikey>
-------------	---

Cause	The length of the new external message data exceeds the ILF's external message length.
Effect	The update of ILF abends and a program dump gets created.
Response	Inspect the program dump file for errors.

6249	Error converting the ILF SEM length from integer to ascii - ILF prikey: <ilf-prikey>
-------------	---

Cause	An error occurred while converting the ILF's external message length from integer to ASCII.
Effect	The ILF update abends and a program dump get created.
Response	Inspect the program dump file for errors.

6250	Error while attempting to retrieve all token data
-------------	--

Cause	An error occurred while attempting to retrieve an existing token from the internal message.
Effect	The length of the PSTM (including token data) cannot be calculated. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6251	Error while attempting to add token
-------------	--

Cause	The token address is out of bound or a required parameter is missing.
Effect	Unsuccessful write of the token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6260	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the POS balance token from the PSTM.
Effect	The POS balance cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6270	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the encrypted balance token from the PSTM.
Effect	The encrypted balance token cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6271	No room to add token
-------------	-----------------------------

Cause	Not enough space to add encrypted balance data token to the PSTM.
Effect	Unsuccessful write of the encrypted balance data to the PSTM.
Response	Examine the PSTM message to determine whether it is full or not. If not, it could be an internal code problem. Contact your vendor representative.

6272	Error while attempting to add token
-------------	--

Cause	An error occurred while attempting to add encrypted balance data token to the PSTM.
Effect	Unsuccessful write of the encrypted balance token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6273	Error while attempting to update token
-------------	---

Cause	An error occurred while attempting to update the encrypted balance token in the PSTM.
Effect	The PSTM will not be updated with the encrypted balance data. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6274	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the data encrypted key token from the PSTM.
Effect	The data encrypted key token cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6275	No room to add token
-------------	-----------------------------

Cause	Not enough space to add data encrypted key token to the PSTM.
Effect	Unsuccessful write of the data encrypted key token data to the PSTM.
Response	Examine the PSTM message to determine whether it is full or not. If not, it could be an internal code problem. Contact your vendor representative.

6276	Error while attempting to add token
-------------	--

Cause	An error occurred while attempting to add data encrypted key token to the PSTM
Effect	Unsuccessful write of the data encrypted key token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6277	Error while attempting to update token
-------------	---

Cause	An error occurred while attempting to update the data encrypted key token in the PSTM.
Effect	The PSTM will not be updated with the data encrypted key token. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6278	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the TSS index token from the PSTM.
Effect	The TSS index token cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6279	No room to add token
-------------	-----------------------------

Cause	Not enough space to add TSS index token to the PSTM.
Effect	Unsuccessful write of the TSS index token data to the PSTM.
Response	Examine the PSTM message to determine whether it is full or not. If not, it could be an internal code problem. Contact your vendor representative.

6280	Error while attempting to add token
-------------	--

Cause	An error occurred while attempting to add the TSS index token to the PSTM.
Effect	Unsuccessful write of the TSS index token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6281	Error while attempting to update token
-------------	---

Cause	An error occurred while attempting to update the TSS index token to the PSTM.
Effect	The PSTM will not be updated with the TSS index token. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6290	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the POS merchant token from the PSTM.
Effect	The POS merchant token cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6291	No room to add token
-------------	-----------------------------

Cause	Not enough space to add POS merchant token to the PSTM.
Effect	Unsuccessful write of the POS merchant token data to the PSTM.
Response	Examine the PSTM message to determine whether it is full or not. If not, it could be an internal code problem. Contact your vendor representative.

6292	Error while attempting to add token
-------------	--

Cause	An error occurred while attempting to add the POS merchant token to the PSTM.
Effect	Unsuccessful write of the POS merchant token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6293	Error while attempting to update token
-------------	---

Cause	An error occurred while attempting to update the POS merchant token to the PSTM.
Effect	The PSTM will not be updated with the POS merchant token. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6300	Error while attempting to get token
-------------	--

Cause	An error occurred while attempting to retrieve the POS merchant token from the PSTM.
Effect	The POS merchant token cannot be retrieved from the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6301	No room to add token
-------------	-----------------------------

Cause	Not enough space to add POS merchant token to the PSTM.
Effect	Unsuccessful write of the POS merchant token data to the PSTM.
Response	Examine the PSTM message to determine whether it is full or not. If not, it could be an internal code problem. Contact your vendor representative.

6302	Error while attempting to add token
-------------	--

Cause	An error occurred while attempting to add the POS merchant token to the PSTM.
Effect	Unsuccessful write of the POS merchant token data to the PSTM. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6303	Error while attempting to update token
-------------	---

Cause	An error occurred while attempting to update the POS merchant token to the PSTM.
Effect	The PSTM will not be updated with the POS merchant token. A program dump will be created and the process abends.
Response	Inspect the program dump file for errors.

6900	MEASCOUNTERBUMPINIT ERROR <error number> FOR COUNTER <defined name>
-------------	--

Cause Display the error of Initialize the measurement counter for the defined name.

Effect None.

Response Check the error number from the

6930	MEASCOUNTERBUMP ERROR \E FOR COUNTER \
-------------	---

Cause Display the error of the measurement counter for the defined name.

Effect None.

Response Check the error number from the

6935	Performance Monitoring is now off.
-------------	---

Cause Performance Monitoring has been turn on.

Effect None.

Response None required.

6940 6950	Performance Monitoring is already on.
----------------------------	--

Cause Display Performance Monitoring is already turn on.

Effect None.

Response None required.

6945	Performance Monitoring initialization failure.
-------------	---

Cause	Display Performance Monitoring initialization is failed.
Effect	None.
Response	Check the associated error message and correct the problem, then repeats the Performance Monitoring command again.

6955	Performance Monitoring is now on.
-------------	--

Cause	Display Performance Monitoring is turn on.
Effect	None.
Response	None required

6960	Performance Monitoring is not on reset failed.
-------------	---

Cause	Display Performance Monitoring is failed to reset
Effect	None.
Response	Check the associated error message and correct the problem, then repeats the Performance Monitoring command again.

6975	Performance Monitoring counters have been reset
-------------	--

Cause	Display Performance Monitoring has been reset.
Effect	None.
Response	None required

6980	Invalid Performance Monitoring Command.
-------------	--

Cause	Display Performance Monitoring command is invalid.
Effect	None.
Response	Check the command and try again

6985	Performance Monitoring is on.
-------------	--------------------------------------

Cause	Display Performance Monitoring has been turn on.
Effect	None.
Response	None required

6990	Performance Monitoring is off.
-------------	---------------------------------------

Cause	Display Performance Monitoring has been turn off.
Effect	None.
Response	None required

6995	Performance Monitoring is now off.
-------------	---

Cause	Display Performance Monitoring is turn off.
Effect	None.
Response	None required

7101	IO ERROR: WRITE Admin File:<file name> Err:<Guardian error code>
-------------	---

Cause	WRITE IO error occurred.
Effect	IMNi is unable to add record to the Admin file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7102	IO ERROR: KEYPOSITION Admin File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi is unable to keyposition an Admin file record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7103	IO ERROR: READ Admin File:<file name> Err:<Guardian error code>
-------------	--

Cause	READ IO error occurred.
Effect	IMNi is unable to read an Admin record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7104	IO ERROR:UPDATE Admin File:<file name> Err:<Guardian error code>
-------------	---

Cause	UPDATE IO error occurred.
Effect	IMNi is unable to update an Admin record with a response code.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7201	IO ERROR: OPEN EPCF File:<file name> Err:<Guardian error code>
-------------	---

Cause	OPEN IO error occurred.
Effect	The EPCF file is not open. IMNi failed to update the entry point state.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7202	IO ERROR:KEYPOSITION EPCF File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7203	IO ERROR:READ EPCF File:<file name> Err:<Guardian error code>
-------------	--

Cause	READ IO error occurred.
Effect	IMNi fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7204	TRACE12: EPCF Update EP:<entry point Id> State:<entry point state>
-------------	---

Cause	Trace bit 12 is turned on and the state of the indicated entry point has been set to the indicated state.
Effect	If the state is "A" (activated), IMNi will open the entry point when the recovery timeout expires.
Response	None required.

7205	IO ERROR: UPDATE EPCF File:<file name> Err:<Guardian error code>
-------------	---

Cause	UPDATE IO error occurred.
Effect	IMNi fails to update the entry point state in EPCF.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7301	TRACE12: Read ICF Node: <ICF record key>
-------------	---

Cause	Trace bit 12 is turned on and the indicated ICF record is about to be read.
Effect	IMNi reads the ICF record.
Response	None required.

7302	IO ERROR: OPEN ICF File:<file name> Err:<Guardian error code>
-------------	--

Cause	OPEN IO error occurred.
Effect	The ICF file is not opened. IMNi fails to retrieve an ICF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7303	IO ERROR: KEYPOSITION ICF File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to position the exact record. Record cannot be retrieved.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7304	IO ERROR: READ ICF File:<file name> Err:<Guardian error code>
-------------	--

Cause	READ IO error occurred.
Effect	IMNi fails to retrieve an ICF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7305	IO ERROR: Disassembly ICF File:<ICF file name> Err:<error code>
-------------	--

Cause	Unable to disassemble the ICF segment record read.
Effect	IMNi logs this message under different conditions.
Response	Check other log message to determine the action to take.

<u>7306</u>	<u>TRACE12: Update ICF Rec Dest: <ICF record key></u>
--------------------	--

Cause	Trace bit 12 is turned on and the indicated ICF record is about to be updated.
Effect	IMNi reads the ICF record.
Response	None required.

7307	IO ERROR: OPEN ICF File:<file name> Err:<Guardian error code>
-------------	--

Cause	OPEN IO error occurred.
Effect	IMNi fails to update the ICF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7308	IO ERROR: Re-assembly ICF File: <ICF file name> Err: <error-code>
-------------	--

Cause Unable to reassemble the ICF segment record when updating the ICF record.

Effect IMNi logs this message under different conditions.

Response Check the other log messages to determine the action to take.

7309	IO ERROR: KEYPOSITION ICF File:<file name> Err:<Guardian error code>
-------------	---

Cause KEYPOSITION IO error occurred.

Effect IMNi fails to position the exact record. ICF record is not updated.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7310	IO ERROR:UPDATE ICF File:<file name> Err:<Guardian error code>
-------------	---

Cause UPDATE IO error occurred.

Effect IMNi fails to update the ICF record.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7401	TRACE11: Open ILF File:<file name>
-------------	---

Cause Trace bit 11 is turned on and the indicated ILF file is about to be opened or created.

Effect IMNi opens or creates and opened the ILF.

Response None required.

7402	IO ERROR: Open ILF File:<file name> Err:<Guardian error code>
-------------	--

Cause	An ILF extract file being opened. If the file does not exist, a new file is created using the LCONF assigned template.
Effect	IMNi fails to open and/or create file. IMNi abends.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7403	IO ERROR: % FULL CALCULATION ON <ILF file name> Err: <error code>
-------------	--

Cause	Unable to get ILF file information when calculating % full of ILF file.
Effect	IMNi closes the ILF file.
Response	Check the file error code returned.

7404	IO ERROR: % FULL CALCULATION ON File:<file name> Err:<Guardian error code>
-------------	---

Cause	Unable to get ILF file record information when calculating % full of ILF file.
Effect	IMNi closes the ILF file.
Response	Check the file error code returned.

7405	***WARNING*** ILF File <file name> is <full percentage> percent full
-------------	---

Cause	The ILF file full percentage has passed the notify percentage threshold.
Effect	IMNi logs the warning and continues.
Response	If IMNi encounters a fatal file error when accessing an ILF (such as file full) it cannot continue to process transactions and abends. This warning indicates that the ILF might be getting dangerously full. It may be necessary to increase the size of the ILF template file so that when new ILFs are created at cutover, they are large enough to handle a complete day's logging requirements.

7406	ABEND ERROR: Node <node Id> ILF Open Failed during cutover
-------------	---

Cause	A new ILF file could not be opened or created during cutover.
Effect	IMNi abends.
Response	Check previous log messages for the GUARDIAN error code and file name for the ILF on which the error occurred. Correct the file system problem and restart IMNi.

7407	ABEND ERROR: ILF Add Dest:<node Id> File:<file name> Err:<GUARDIAN error code> ILF RECORD: <ILF record dump>
-------------	---

Cause	A fatal file error occurred on the indicated ILF.
Effect	IMNi abends.
Response	Correct the file system problem indicated by the GUARDIAN error code and restart the IMNi.

7408	TRACE11: ILD Add Dest:<node Id> <msg class> Key:<ILF record key> File:<file name>
-------------	--

Cause	Trace bit 11 is turned on and an ILF record is added to the indicated file.
Effect	IMNi logs the message and continues.
Response	None required.

7409	TRACE11: ILF Get Dest:<node Id> <msg class> Key: <ILF record key> File:<file name>
-------------	---

Cause	Trace bit 11 is turned on and an ILF record is retrieved from the indicated file.
Effect	IMNi logs the message and continues.
Response	None required.

7410	TRACE11: ILF Update Dest:<node Id> <msg class> SubState:<ILF record substate>
-------------	--

Cause	Trace bit 11 is turned on and an ILF record in the indicated file is updated with the indicated substate.
Effect	IMNi logs the message and continues.
Response	None required.

7411	ABEND ERROR: UPDATE ILF Add Dest: <node ID> File: <file name> Err: <Guardian error code> ILF RECORD
-------------	--

Cause	UPDATE IO error occurred.
Effect	IMNi fails to update an ILF record. IMNi abends.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7412	IO ERROR: OPEN ILF File:<file name> Err:<Guardian error code>
-------------	--

Cause	OPEN IO error occurred.
Effect	IMNi fails to open an ILF file and purge the old ILF file. After this message is logged, control is returned to the calling procedure.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7413	IO ERROR: CLOSE ICF File:<file name> Err:<Guardian error code>
-------------	---

Cause	CLOSE IO error occurred.
Effect	IMNi fails to close an ICF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7414/7415 IO ERROR: PURGE ILF File:<file name> Err:<Guardian error code>

Cause PURGE IO error occurred.

Effect IMNi fails to purge the old ILF file.

Response None required.

7421 IO ERROR: CLOSE ILF File:<file name> Err:<Guardian error code>

Cause CLOSE IO error occurred.

Effect IMNi fails to close an ILF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7430 Open Internal Error <library status detail1> <library status detail2> File <file name> < library proc number> <library status> <library status detail3> <library status detail4>, Process abending

Cause A parameter was not passed or incorrectly passed in the call to the library procedure LIB_FILE_OPEN while attempting to open a file.

Effect The ILF file is not opened. IMNi logs the message and abends.

Response This indicates an internal code problem. Contact your vendor representative.

7431 FAILURE on CREATE, ILF File <file name>, Error <error number>

Cause Failed to create the ILF file.

Effect The ILF file is not created. IMNi logs the message.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7432	Open Internal Error <library status detail1> <library status detail2 or Guardian error> File <file name> < library proc number> <library status> <library status detail3> <library status detail4>, Process abending
-------------	---

Cause An NSK error (library status detail2) occurred while attempting to open a file on a call to the library procedure LIB_FILE_OPEN. This error caused the open to fail.

Effect The ILF file is not opened. IMNi logs the message and abends.

Response Inspect the program dump file for errors.

7433	Open Internal Error <library status detail1> <library status detail2 or Guardian error> File <file name> < library proc number> <library status> <library status detail3> <library status detail4>, Process abending
-------------	---

Cause An NSK error (library status detail2) occurred while attempting to open a file on a call to the library procedure LIB_FILE_OPEN. This error caused the open to fail

Effect The ILF file is not opened. IMNi logs the message and abends.

Response Inspect the program dump file for errors.

7501	TRACE12: Get KEYF Rec FID: <FI Id> Node:<KEYF record key>
-------------	--

Cause Trace bit 12 is turned on and the indicated KEYF record is about to be retrieved.

Effect IMNi retrieves the KEYF record.

Response None required.

7502	IO ERROR: OPEN KEYF File:<file name> Err:<Guardian error code>
-------------	---

Cause OPEN IO error occurred.

Effect IMNi fails to open and read the KEYF file.

Response Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7503	IO ERROR: KEYPOSITION KEYF File:<file name> Err:<Guardian error code>
-------------	--

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to position the exact record and read the KEYF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7504	IO ERROR: READ KEYF File:<file name> Err:<Guardian error code>
-------------	---

Cause	READ IO error occurred.
Effect	IMNi fails to read the KEYF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7505	TRACE12: Update KEYF Rec <KEYF record key>
-------------	---

Cause	Trace bit 12 is turned on and the indicated KEYF record is about to be updated.
Effect	IMNi updates the KEYF record.
Response	None required.

7506	IO ERROR: <I/O Operation> [<file type>] <file name> Err:<GUARDIAN error code>
-------------	--

Cause	A GUARDIAN error occurred on the indicated file for the indicated I/O operation.
Effect	IMNi logs the error and continues.
Response	Check the GUARDIAN error code indicated to determine the appropriate response. If the error occurred during startup or warmbooting, the operation must be repeated.

7507	IO ERROR: KEYPOSITION File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to update the KEYF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7508	IO ERROR: UPDATE File:<file name> Err:<Guardian error code>
-------------	--

Cause	UPDATE IO error occurred.
Effect	IMNi fails to update the KEYF record.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7510	TRACE12: Unlock KEYF Rec
-------------	---------------------------------

Cause	Trace message for unlocking KEYF file record at the current position.
Effect	None.
Response	None required.

7511	IO ERROR: UNLOCKREC File:<file name> Err:<Guardian error code>
-------------	---

Cause	UNLOCKREC IO error occurred.
Effect	IMNi fails to unlock KEYF record and then closes file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7520	PROC ERROR: Invalid dct index <dct index>
-------------	--

Cause	DCT table index out of range while loading key data for a destination.
Effect	IMNi retries the loading process for outbound key exchange request. If the transaction is key exchange request, IMNi denies the request.
Response	Check DCT index in DCT table.

7521	PROC ERROR: Invalid fil index <fil index>
-------------	--

Cause	FIL index out of range (0-9) while loading key data for a destination.
Effect	IMNi retries the loading process for outbound key exchange request. If the transaction is inbound key exchange request, IMNi denies the request.
Response	Check FIL index in DCT table.

7601	IO ERROR: OPEN SAF File:<file name> Err:<Guardian error code>
-------------	--

Cause	OPEN IO error occurred.
Effect	IMNi fails to open SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7602	TRACE10: SAF Add Dest:<node Id> Msg:<msg type> Cnt:<SAF transaction count> File:<file name>
-------------	--

Cause	Trace bit 10 is turned on and a message is about to be added to the indicated SAF file.
Effect	IMNi adds the SAF record.
Response	None required.

7603	IO ERROR: WRITE SAF File:<file name> Err:<Guardian error code>
-------------	---

Cause	WRITE IO error occurred.
Effect	IMNi fails to write a record to SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7604	TRACE10: SAF Get Dest:<node Id> File:<file name>
-------------	---

Cause	Trace bit 10 is turned on and a SAF record is about to be retrieved from the indicated file.
Effect	IMNi retrieves SAF record if available.
Response	None required.

7605	IO ERROR: KEYPOSITION File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to retrieve record from SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7606	IO ERROR: READ SAF File:<file name> Err:<Guardian error code>
-------------	--

Cause	READ IO error occurred.
Effect	IMNi fails to retrieve record from a SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7607	TRACE10: SAF GetNext Dest:<node Id> File:<file name>
-------------	---

Cause	Trace bit 10 is turned on and the next SAF record is about to be retrieved from the indicated file.
Effect	IMNi retrieves the next record if available.
Response	None required.

7608	IO ERROR: READ File:<file name> Err:<Guardian error code>
-------------	--

Cause	READ IO error occurred.
Effect	IMNi fails to retrieve the next record from SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7609	TRACE10: SAF Delete Dest:<node Id> File:<file name>
-------------	--

Cause	Trace bit 10 is turned on and a SAF record is about to be deleted from the indicated file.
Effect	IMNi deletes the SAF record.
Response	None required.

7610	IO ERROR: KEYPOSITION File:<file name> Err:<Guardian error code>
-------------	---

Cause	KEYPOSITION IO error occurred.
Effect	IMNi fails to delete a record from the SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7611	IO ERROR:READ SAF File:<file name> Err:<Guardian error code>
-------------	---

Cause	READ IO error occurred.
Effect	IMNi fails to delete a record from the SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7612	IO ERROR: DELETE SAF File:<file name> Err:<Guardian error code>
-------------	--

Cause	DELETE IO error occurred.
Effect	IMNi fails to delete a record from the SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7613	SAF Cutover to <YYMMDD> started for destn= <node Id> <msg class> on node <IMNi node Id> SAF file= <file name>
-------------	--

Cause	The SAF cutover processing for the indicated SAF and destination is about to begin.
Effect	IMNi performs the SAF cutover processing.
Response	None required.

7614	IO ERROR: UPDATE SAF File:<file name> Err:<Guardian error code>
-------------	--

Cause	UPDATE IO error occurred.
Effect	IMNi fails to update a record in the SAF file.
Response	Examine the Guardian error code to determine the specific nature of the error and take action accordingly.

7615	SAF Cutover to <YYMMDD> completed for destn= <node Id> <msg class> on node <IMNi node Id> SAF file= <file name>
-------------	--

Cause	The SAF cutover processing for the indicated SAF and destination has been completed.
Effect	IMNi logs the message and continues.
Response	None required.

7616	REVERSAL ERROR: REVERSAL ERROR: Invalid transaction Rsp Cde 55 threshold reached. Occurrences: <counter>
-------------	---

Cause	IMNi receives a reversal request with an invalid transaction format.
Effect	IMNi logs the message and continues.
Response	Examine the origin of the invalid reversal request and take action accordingly. Correct the problem and warmboot to restart IMNi.

8100*	IO ERROR: CGF <read> Error on <file-name> Err: <error code>
--------------	--

Cause	Error reading next record from an existing CGF file.
Effect	IMNi initialization fails.
Response	Examine the Guardian error code and take action accordingly.

8110*	Trace09: Loading CGF file: <file-name>
--------------	---

Cause	Trace bit 9 is turned on; CGF file data is about to be loaded.
Effect	IMNi loads the CGF file.
Response	None required.

8111*	IO ERROR: CGF <open> error on <file-name> Err:<Guardian error code>
--------------	--

Cause	Error opening the CGF files.
Effect	IMNi initialization fails.
Response	Examine the Guardian error code and take appropriate measures.

8112*	IO ERROR: CGF <empty CGF> error on <file-name> Err:<error>
--------------	---

Cause	The CGF file data is missing.
Effect	IMNi initialization fails.
Response	Enter connection group data to CGF file.

8113*	Missing destination <node-id> <msg-cls> in Connection Group <cnxn-grp>
--------------	---

Cause	The specified connection is missing from the DCT table.
Effect	Destination will not be added to the Connection Group Table.
Response	Enter valid destination to the appropriate connection group.

8114*	Duplicate connection <node-id> <msg-cls> in Connection Group <cnxn-grp>
--------------	--

Cause	A certain connection is added in more than one connection group.
Effect	Destination will not be added to the Connection Group Table.
Response	Remove the duplicate connection from the CGF record.

8115*	Single connection <node-id> <msg-cls> in Connection Group <cnxn-grp>
--------------	---

Cause There is only one connection left in the group.

Effect None.

Response None required.

8116*	Connection group <group-id> cannot be added to CGT. CGT table is full (#Max)
--------------	---

Cause This message is logged at initialization when the CGT becomes full.

Effect No other connection group can be added to the CGT.

Response Do not exceed the maximum number of connection groups.

8117*	WARNING: No CGT Records loaded from <file-name>
--------------	--

Cause Records could not be loaded from the CGF file.

Effect The CGF file will be closed, IMNi initialization continues.

Response Check the contents of the CGF file for valid records.