

A Major Project Report
on
**“SIMULATION AND HARDWARE IMPLEMENTATION OF
BATTERY MANAGEMENT SYSTEM”**
Submitted in partial fulfilment of the requirement for the award of the degree of
BACHELOR OF TECHNOLOGY
IN
ELECTRICAL AND ELECTRONICS ENGINEERING

by

Katkozu Sathwika Sindhu	20251A0260
Farheen Fathima	20251A0253
Rudrarapu Nehanjali	20251A0270
Kotagiri Deekshitha	21255A0221
Chitrala Hari Sahithi	20251A0278

Under the Guidance of
Mrs. K. Priyamvada
(Assistant Professor, EEE)



Department of Electrical and Electronics Engineering
G. NARAYANAMMA INSTITUTE OF TECHNOLOGY AND SCIENCE
(For Women)
(NBA & NAAC Accredited Institution)
(Affiliated to JNTUH, Hyderabad)
Hyderabad-500104, TS, India
April-2024

G. NARAYANAMMA INSTITUTE OF TECHNOLOGY & SCIENCE
(for women)
Shaikpet, Hyderabad-500104.



CERTIFICATE

This is to certify that the project report on, **“SIMULATION AND
HARDWARE IMPLEMENTATION OF BATTERY MANAGEMENT
SYSTEM”** that is being submitted by

Katkozu Sathwika Sindhu	20251A0260
Farheen Fathima	20251A0253
Rudrarapu Nehanjali	20251A0270
Kotagiri Deekshitha	21255A0221
Chitrula Hari Sahithi	20251A0278

in partial fulfillment for the award of degree **BACHELOR OF TECHNOLOGY in
ELECTRICAL AND ELECTRONICS ENGINEERING** from **G. Narayanamma Institute
of Technology and Science (AUTONOMOUS)** is a record of Bona-fide work carried out by
the students under our guidance and supervision in the academic year 2023-24.

Mr. K. Priyamvada
Assistant professor, Dept. of EEE
Major Project Guide

Dr. P. Ramakrishna Reddy
Head of the Department
Dept. of EEE

External Examiner

ACKNOWLEDGEMENT

The completion of any project brings with it a sense of satisfaction, but it is not complete without thanking people who made it possible. It gives us immense pleasure to express our deep sense of gratitude to our guide, **Mrs. K. Priyamvada**, Assistant Professor, Department of Electrical and Electronics Engineering, for his valuable suggestions, constant encouragement, cooperation and keen interest evinced throughout the course of our project. Our sincere thanks and gratitude to **Dr. P. Ramakrishna Reddy**, HOD, Department of EEE, for extending his support. We would like to express our sincere thanks to **Dr. K. Ramesh Reddy**, Principal, GNITS for providing the working facilities in the college. We owe thanks to our institution, our teaching and non-teaching faculty and our friends without whom this project would have been a distant reality.

ABSTRACT

Battery Management Systems (BMS) are crucial components in electric vehicles (EVs), ensuring optimal battery performance, safety, and longevity. BMS actively monitors and balances cell voltages, estimates State of Charge (SOC) and State of Health (SOH), and manages thermal conditions. Accurate SOC estimation reduces range anxiety for drivers, manages thermal conditions. Accurate SOC estimation reduces range anxiety for drivers, against overheating, enhancing battery safety and longevity. BMS also facilitates real-time communication with the vehicle's central control unit, optimizing overall system intelligence. Ongoing research focuses on improving BMS for higher energy density, faster charging, and integration with emerging technologies, shaping the future of electronics.

CONTENTS

ABSTRACT.....	iv
LIST OF FIGURES.....	vii
LIST OF TABLES.....	viii
CHAPTER-1.....	1
1.INTRODUCTION	1
Objective of the project	2
CHAPTER-2.....	3
LITERATURE SURVEY.....	3
Literature Reviews.....	3
CHAPTER-3.....	5
SIMULATION	5
3.1 CELL BALANCING	5
Fig 3.1 Basic circuit of Battery management system.....	5
3.2 ACTIVE CELL BALANCING.....	5
Fig 3.2.1 Battery management system by active cell balancing.....	6
Fig 3.2.2 MATLAB function code	6
OUTPUT.....	7
Fig 3.2.3 output characteristics of cell balancing.....	7
3.3 WORKING.....	7
3.4 COMPONENTS DESCRIPTION	9
CHAPTER-4.....	10
4.1 BMS CONNECTION	10
Fig 4.1 BMS Module	10
Fig 4.2 BMS Module Hardware Connections	11
4.1.1 DW01-A: Battery Protection IC	11

4.1.2 Electrical Characteristics of DW01-A.....	12
Table 4.1.1 characteristics of DWO1-A	12
4.2 PROTECTION CIRCUIT	12
Fig 4.2.1 protection circuit of battery pack	12
Table 4.2.1 Characteristic code and other function options	13
Fig 4.2.2 N-channel BMS connection	14
4.3 6S 12A BMS CIRCUIT DIAGRAM	14
4.4 MULTIPLE MOSFETs CONNECTION	14
4.5 CONTROLLING THE MOSFETs	15
4.6 COMPONENTS USED IN 6S 12A BMS MODULE	16
Table 4.6.1 Markings on the BMS & Connection with the BMS	16
Table 4.6.2-BMS Specifications	17
4.7 PROTECTION FEATURES OF 6S 12A BMS MODULE	17
Overcharge Condition	17
Fig 4.7.1 Overcharge condition graph	18
Over Discharge Condition.....	18
Fig 4.7.2 Overcharge condition.....	18
Over Current Protection	19
CHAPTER-5.....	21
5.1 ADVANTEGES.....	21
5.2 DISADVANTAGES.....	22
5.3 APPLICATIONS	23
CONCLUSION	24
REFERENCES.....	25

LIST OF FIGURES

Fig 3.1 Basic circuit of Battery management system.....	5
Fig 3.2.1 Battery management system by active cell balancing.....	6
Fig 3.2.2 MATLAB function code.....	6
Fig 3.2.3 Output characteristics of cell balancing.....	7
Fig 4.1 BMS Module.....	10
Fig 4.2. BMS Hardware.....	11
Fig 4.2.1 Protection circuit of Battery pack.....	13
Fig 4.2.2 N-Channel BMS Connection.....	14
Fig 4.7.1 Overcharge condition graph.....	18
Fig 4.7.2 Overcharge condition.....	19
Fig 4.7.3 Overcurrent protection graph	20

LIST OF TABLES

Table 4.1.1 characteristics of DWO1-A.....	12
Table 4.2.1 Characteristic code and other function options.....	14
Table 4.6.1 Markings on BMS and connections with BMS	16
Table 4.6.2 BMS Specifications	17

CHAPTER-1

1.INTRODUCTION

Rechargeable battery is an electrochemical device which converts electrical energy to chemical energy during charging and converts chemical energy to electrical energy during discharging. Rechargeable battery plays important role in future technology since it is potentially to be applied as energy storage element in green technology applications, such as electric vehicle (EV) and photovoltaic (PV) system. The renewable energy source can be stored in battery packs and thus help to reduce the reliance on fossil fuels. In the aspect of technology, the rechargeable battery is improved from Lead acid battery to Nickel-based battery and from Nickel- based battery to Lithium-ion (Li-ion) battery.

The development of BMS involves two critical phases: simulation and hardware implementation. Simulation serves as a fundamental tool for conceptualizing, refining, and validating BMS designs in a virtual environment. Through simulation, engineers can model battery behavior under various conditions, optimize control algorithms, and predict system performance without the need for physical prototypes.

On the other hand, hardware implementation translates theoretical BMS designs into tangible systems ready for real-world deployment. This phase involves selecting appropriate components, designing electronic circuits, and integrating control algorithms into physical prototypes. Hardware testing allows for validation, refinement, and optimization of BMS functionalities, ensuring robustness and reliability in practical applications.

Lithium-ion battery has higher terminal voltage, higher power density and higher energy density compared to the other rechargeable batteries. Nowadays, Li-ion battery is widely adopted in portable electronic devices, such as laptop computers, smart phones and digital cameras. Accurate battery information such as state-of-charge (SOC), current and voltage are vital for circuit designer to manage the energy consumption of battery- powered system. Moreover, handling on battery is necessary to avoid battery from overcharging or over-discharging. MATLAB/Simulink is a powerful simulation tools for circuit and system designs. It provides a lot of simple, powerful and user-friendly toolboxes or simulation blocks.

Objective of the project

This project is to develop and implement an advanced Battery Management System (BMS) that integrates cutting-edge monitoring, control, and safety functionalities for rechargeable battery packs. The primary aim is to create accurate simulation models that represent lithium-ion battery behavior under diverse operating conditions. These models will facilitate the development and optimization of essential BMS algorithms, including state-of-charge (SOC) estimation, thermal management strategies, and cell balancing techniques.

Furthermore, the project seeks to refine and optimize BMS algorithms using simulation tools, ensuring robustness and efficiency for real-time implementation. This optimization process will enhance the overall performance and reliability of the BMS in managing battery health and performance.

The project's objective is to contribute to the advancement of energy storage technologies by developing an innovative BMS solution that prioritizes safety, efficiency, and reliability in electric vehicles, renewable energy systems, and other applications requiring rechargeable battery packs.

CHAPTER-2

LITERATURE SURVEY

Battery Management Systems (BMS) have garnered significant interest in recent years due to their crucial role in optimizing the performance, safety, and longevity of rechargeable batteries used in various applications. A literature survey reveals a wealth of research and advancements in BMS design, simulation, implementation, and optimization. This survey aims to provide insights into key research trends, challenges, and emerging technologies in the field of BMS.

Literature Reviews

Battery Management Systems (BMS) have emerged as crucial components in various industries reliant on rechargeable batteries, such as electric vehicles (EVs), renewable energy systems, and portable electronics. A comprehensive literature review illuminates key advancements and trends in BMS research, covering simulation, control algorithms, hardware implementation, safety features, and practical applications.

One significant area of focus is the simulation and modelling of battery behaviour. Researchers have explored diverse modelling techniques, including physics-based models, equivalent circuit models, and empirical approaches. These models are instrumental in BMS design for accurately estimating state-of-charge (SOC), predicting thermal behaviour, and anticipating battery aging dynamics. The literature emphasizes the importance of sophisticated battery models in optimizing BMS performance and ensuring effective battery management.

In terms of control strategies and algorithms, recent literature underscores the evolution of BMS control techniques. Advanced algorithms for battery balancing, charge/discharge optimization, and real-time fault detection have been investigated.

Hardware implementation and system integration have also been extensively reviewed, particularly concerning BMS architectures for electric vehicles. Studies delve into sensor selection, microcontroller configurations, and communication protocols critical for reliable battery monitoring and management.

Robust hardware design is paramount in realizing the full potential of BMS technologies in practical applications.

Safety and reliability enhancement remain focal points in BMS literature, with an emphasis on mitigating risks associated with lithium-ion batteries. Furthermore, BMS applications in renewable energy systems have been explored in depth.

Finally, literature reviews identify key challenges and future directions in BMS development. Issues such as cost-effectiveness, scalability, standardization, and interoperability are discussed. The reviews envision integrating BMS with emerging battery technologies like solid-state batteries and advancing predictive maintenance strategies to address these challenges and drive innovation in the field.

Collectively, these literature reviews contribute valuable insights into the multifaceted landscape of BMS research, shedding light on advancements, challenges, and opportunities for enhancing battery performance and accelerating the adoption of clean energy technologies.

CHAPTER-3

SIMULATION

3.1 CELL BALANCING

Battery Cell Balancing also means battery charge redistribution to improve the overall potential of the battery pack and emphasize each cell's longevity. Cell Balancing enhances the State of Charge (SOC) of your battery.

An imbalance is created when every cell in the connected series of the battery pack depicts a different SOC. Such an imbalance results in the overall battery capacity equal to the weakest cell in the battery pack.

However, to optimize the battery life, we must ensure that we bring a cell balancing to equalize the overall battery of each cell in the pack.

In the domain of Battery Management Systems (BMS), there are two types of Cells Balancing techniques available. Let's get on them one by one.




Fig 3.1 Basic circuit of Battery management system

3.2 ACTIVE CELL BALANCING

In an active cell balancer, energy transfers from a higher voltage to a lower voltage cell within the battery. In other words, the cell with higher SOC transfers energy to a lower SOC cell. Thus, the active cell balancing technique avoids dissipating heat energy and rather uses shuttling or converters to balance out the energy levels of the highest voltage cell and the lowest.

Battery Management System (BMS) is a collection of interconnected batteries that store electrical energy to power the vehicle. The BMS monitors and manages the battery pack's performance, ensuring optimal charging and discharging.

It oversees individual cell health, temperature, and voltage, preventing issues like overcharging or over-discharging that could harm the battery. The BMS plays a crucial role in enhancing battery life, safety, and overall EV efficiency by balancing cell capacities and maintaining optimal operating conditions for the entire battery pack.




Fig 3.2.1 Battery management system by active cell balancing

```

MATLAB Function
1  function [s1,s2] = fcn(SOC1,SOC2,PWM)
2
3
4  if SOC2<SOC1
5      s1=PWM
6      s2=0
7  elseif SOC1<SOC2
8      s1=0
9      s2=PWM
10 else
11     s1=0
12     s2=0
13 end
14

```

Fig 3.2.2 MATLAB function code

OUTPUT




Fig 3.2.3 output characteristics of cell balancing

3.3 WORKING

Active cell balancing is a technique used in Battery Management Systems (BMS) to equalize the state-of-charge (SOC) of individual cells within a battery pack to maximize performance, improve longevity, and ensure safety. The working principle of active cell balancing involves monitoring each cell's SOC and transferring charge between cells to maintain uniform SOC levels across the battery pack. Here's a step-by-step explanation of how active cell balancing typically works:

Cell Monitoring: The BMS continuously monitors the voltage (and possibly other parameters like temperature or current) of each cell within the battery pack. This monitoring provides real-time data on the state-of-charge (SOC) of individual cells.

SOC Calculation: Based on the voltage measurements, the BMS calculates the SOC of each cell. SOC estimation algorithms use the voltage characteristics of the battery cells to determine their charge levels.

SOC Comparison: The BMS compares the SOC of each cell against a predefined threshold or target SOC. Cells with SOC levels significantly higher or lower than the target are identified as candidates for balancing.

Balancing Decision: If the SOC difference between cells exceeds a specified threshold, the BMS initiates a balancing decision. Cells with higher SOC (overcharged) will need to transfer charge to cells with lower SOC (undercharged) to achieve SOC equilibrium.

Balancing Action: Depending on the balancing technique used, the BMS activates appropriate balancing circuitry to transfer charge between cells:

Resistive Dissipation: In this method, excess charge from higher SOC cells is dissipated as heat through resistors.

Switched Capacitor Balancing: Charge is transferred between cells using capacitors and switches to equalize SOC.

DC-DC Converter Balancing: More advanced method using DC-DC converters to efficiently transfer charge between cells without significant energy loss.

Control Algorithm Execution: Balancing control algorithms implemented in the BMS dictate when and how charge transfer occurs based on SOC measurements. These algorithms optimize the balancing process to minimize energy loss and ensure safe operation.

Monitoring and Feedback: Throughout the balancing process, the BMS continues to monitor cell voltages and SOC levels. Feedback from the monitoring system allows the BMS to adjust balancing actions dynamically based on changing battery conditions.

Completion and Verification: Once the SOC of all cells reaches a balanced state within predefined tolerance limits, the balancing process is completed. The BMS verifies SOC uniformity and transitions to regular monitoring and maintenance routines.

Overall, active cell balancing is an iterative process performed continuously during battery operation to maintain optimal battery performance and health. By equalizing SOC levels across battery cells, active cell balancing helps maximize energy utilization, extend battery life, and enhance the overall efficiency and reliability of battery-powered systems.

3.4 COMPONENTS DESCRIPTION

Ideal switch: The Ideal Switch block does not correspond to a particular physical device. When used with appropriate switching logic, it can be used to model simplified semiconductor devices such as a GTO or a MOSFET, or even a power circuit breaker with current chopping.

Bus Selector: The Bus Selector block extracts the elements you select by name from the input bus hierarchy. The block can output the selected elements separately or in a new virtual bus. When the block outputs the selected elements separately, each selected element corresponds to an output port.

Goto: The Goto block passes its input to its corresponding from blocks. The input can be a real- or complex-valued signal or vector of any data type. From and Goto blocks allow you to pass a signal from one block to another without actually connecting them.

Voltage measurement: The Voltage measurement block measures the instantaneous voltage between two electric nodes.

Current measurement: The Current Measurement block measures the instantaneous current flowing in any electrical block or connection line.

Diode: The diode is a semiconductor device that is controlled by its own voltage V_{ak} and current I_{ak} . When a diode is forward biased ($V_{ak} > 0$), it starts to conduct with a small forward voltage V_{ak} across it. It turns off when the current flow into the device becomes 0. When the diode is reverse biased ($V_{ak} < 0$), it stays in the off state.

PWM: The PWM Generator block implements a PWM generator. The pulse width modulation technique controls power transfer from one electrical component to another by quickly switching between full power transfer and no power transfer.

POWERGUI: The power Gui block allows you to choose one of these methods to solve your circuit. Continuous, which uses a variable-step solver from Simulink. Discretization of the electrical system for a solution at fixed time steps. Continuous or discrete phasor solution.

CHAPTER-4

4.1 BMS CONNECTION

The BMS module has a neat layout with markings for connecting the BMS with different points in the battery pack. The image below shows how we need to connect the cell with BMS.

The BMS acts like 4 separate modules for 4 separate cells and then these 4 modules are very smartly integrated together with transistors and passive components to make a complete BMS that is able to deliver current up to 40A and protect individual cell's parameters.

The BMS has 2 ICs, DW01, and BB3A; some variants of this BMS may have the same ICs or similar ICs from different manufacturers. But all the ICs will have the same pinouts and functioning. I will be discussing the 2 ICs later. The figure below shows the parts of BMS responsible for different operations.




Fig 4.1 BMS Module




Fig 4.2 BMS Module Hardware Connections

4.1.1 DW01-A: Battery Protection IC

DW01-A is a 1 cell Li-ion/ Polymer battery protection IC. It is responsible for all the protection features of the BMS. Each individual cell has 1 DW01-A connected which monitors the health of the particular cell. It comes in a 6 pins sot-23-6 package. You can refer to the IC's datasheet to see the functional diagram and other data. It has an internal voltage divider circuit that is responsible for measuring the undervoltage and overvoltage of the cell. The short circuit and overcurrent are detected by the comparators which compare the voltage between CS pin input and VSS.

4.1.2 Electrical Characteristics of DW01-A

The working of any Integrated circuit depends on how it has been designed, which is given by the manufacturer, the electrical characteristics of DW01 is given in the table below:

PARAMETER	TEST CONDITIONS	SYMBOL	Min	Typ	Max	UNIT
Supply Current	V _{CC} =3.9V	I _{CC}		3.0	6.0	μA
Power-Down Current	V _{CC} =2.0V	I _{PD}			0.1	μA
Overcharge Protection Voltage	DW01 Plus	V _{OC} P	4.25	4.30	4.35	V
Overcharge Release Voltage		V _{OC} R	4.05	4.10	4.15	V
Overdischarge Protection Voltage		V _{OD} P	2.30	2.40	2.50	V
Overdischarge Release Voltage		V _{OD} R	2.90	3.00	3.10	V
Overcurrent Protection Voltage		V _{OIP} (V _{OI1})	120	150	180	mV
Short Current Protection Voltage	V _{CC} =3.6V	V _{SIP} (V _{OI2})	1.25	1.35	1.45	V

Table 4.1.1 characteristics of DW01-A

4.2 PROTECTION CIRCUIT

The protection circuit of this battery pack is shown here. Here, the Batt+ and S3 denote the positive and negative terminals of the cell respectively. The IC measures the voltage of the cell using an internal voltage divider circuit between V_{CC} and ground pin and based on the electrical characteristics table shown above control the Over-discharge (OD) and Overcharge (OC) pin thus controlling the transistors Q2 and Q3 in the figure below.

The DW01-A constantly monitors the overcurrent or short-circuit by measuring the voltage at the current sense pin. In the case of a short circuit the voltage exceeds V_{SIP}, and the fault, i.e. the short circuit is inhibited by turning off the discharge control MOSFET.




Fig 4.2.1 protection circuit of battery pack

In the above figure, you can observe that the VSS pin is connected to the positive terminal of the cell with a resistor R24 and VSS and VDD have a capacitor C1 parallel to them. The capacitor and resistor are essential for suppressing the ripples and disturbance from the charger.

HY2212 BB3A: Cell Balancing IC

Coming to the cell balancer circuit, the heart of this circuit is HY2212 BB3A, 1 cell Li-ion/polymer battery charger balance IC.

This IC is capable of active balancing of a cell by electrical level monitoring and it comprises a very high-accuracy voltage detection circuit and delay circuit.

The series of HY2212 is created for a single-cell lithium-ion or can also be used for multi-cell battery packs with individual cells. It features charge balance control, electrical level monitoring ICs and it also comprises a high-accuracy voltage detection circuit and delay circuit. The functional block diagram of the IC is given below, as you can see, the IC has a voltage divider circuit connected to the input VSS and VDD which is being fed to the overcharge detection comparator, which is used for controlling the enhancement MOSFET. You can refer to the datasheet of the IC to see the internal block diagram of this IC. It has a very simple circuit that just measures the voltage using a voltage detection comparator and gives an output. The output is used to control the gate of a MOSFET. Either P-type or N-type MOSFET can be used and the effective operation of both MOSFET are given in the table below.

Characteristic Code	Out Effective Operation
A	N-MOSFET balance control; OUT output status L→H effective
B	P-MOSFET balance control; OUT output status H→L effective

Table 4.2.1 Characteristic code and other function options

In this BMS an N-channel BMS is being used which is then connected to a Resistor of 480 ohm, the circuit used in the BMS is shown in the image below:




Fig 4.2.2 N-channel BMS connection

In the above circuit, the MOSFET used with this IC is A2SHB which is an N-channel Enhancement MOSFET. When the out pin from pin 6 of BB3A gives a high signal to the gate of this enhancement type MOSFET, the MOSFET connects a low resistance path through this 480-ohm resistance which acts as a load resistor and starts depleting the battery.

The rate of discharge can easily be found by Ohm's law. $V=IR$

4.3 6S 12A BMS CIRCUIT DIAGRAM

The above image shows the complete circuit diagram of the BMS circuit, as discussed above the circuit can be divided into smaller modules for balancing and monitoring every single cell.

As shown in the image below, we can see that the Balancer IC is connected in parallel with the cell. Similarly, the Battery charging IC, DW01 is also connected in parallel to the cell.

As explained above the VSS and VDD of DW01 are connected with the negative and positive of the cell respectively, and pin 2 which is the current sense pin is connected to the negative rail. According to the received input from the current sense pin, the Overcharge and Over-discharge transistors are controlled.

4.4 MULTIPLE MOSFETs CONNECTION

Since the BMS is designed for drills motor operations, the starting current is generally higher than the rated current. Starting current of motors can be as high as 4-8 times its rated current.

The current reduces and comes back to its rated speed as the motor accelerates and reaches its synchronous or base speed. So, even though it is rated for 40A if a 500Watt motor that consumes around 40A is connected the surge current can be higher than 240 Amps for a very small time, hence multiple MOSFETs are connected in parallel.

Note: When placing the MOSFETs in parallel, make sure that all the MOSFETs have very close actual values of $V_{GS(TS)}$ since you want all the parallel-connected MOSFETs to turn on at the same time so as to avoid damages to the MOSFET.

The above image shows the flow of current when all the MOSFETs are in the On State. The current from the battery flows through the battery pack and from the series-parallel connection of MOSFET AOD 472s.

4.5 CONTROLLING THE MOSFETs

The MOSFETs are controlled by controlling the overcharge and over discharge pins of the DW01 IC. The source on the left side MOSFETs is connected to the ground, the current sense pin of DW01 is connected with the source, hence when there is a short circuit or an overcurrent is detected by the DW01 IC it turns on Q9 which turns on the transistor pair giving a signal to the gate terminal thus turning the MOSFETs off.

The Gate of the right pair of MOSFETs which are responsible for protecting the battery pack from overcharging is connected to the positive terminal of the battery pack. When the battery is overcharged, the DW01 IC will sense the overcharge condition using the internal potential divider circuit and will turn on the OD transistor.

Taking the IC 1 in this condition, it will turn on transistor Q2, the flow of the current will turn on Q21 connecting the gate of the combination of parallel MOSFETs responsible for overcharge protection with the ground thus turning it off and hence disconnecting the whole circuit. The below graph shows us the working of the DW01 IC during the charge condition.

4.6 COMPONENTS USED IN 6S 12A BMS MODULE

Coming to the components of the BMS, the BMS has 2 ICs, DW01-A which is a battery protection IC and a BB3A which is a cell balancing IC.

Markings on the BMS	Connection with the BMS
-	Negative Terminal Connection for the battery pack for charging and connecting the load.
+	Positive Terminal Connection for the battery pack for charging and connecting the load
0	Negative terminal of the 1 st cell
3.7	Positive terminal of the 1 st cell
7.4	Positive terminal of the 2 nd cell
11.1	Positive terminal of the 3 rd cell
14.8	Positive terminal of the 4 th cell
18.5	Positive terminal of the 5 th cell

Table 4.6.1 Markings on the BMS & Connection with the BMS

Parameter	Values
Model	6S BMS 12A
Charging Voltage	22 V
Charging Current	12 A (Max)
Operating Temperature	-40°C - 85°C
Maximum lamp shift discharge current	12 A
Overcharge detection voltage	4.25 V $\pm$ 0.05 V
Over-discharge detection voltage	2.50 V $\pm$ 0.08V
Overcurrent Protection	50 A

Table 4.6.2-BMS Specifications

4.7 PROTECTION FEATURES OF 6S 12A BMS MODULE

As discussed above, the BMS module has all the necessary features to protect the battery pack, it provides overcharge protection, over discharge protection, short circuit protection along cell balancing. More details about the protection features are given below.

Overcharge Condition

When the cell is charged beyond a safe charging voltage, the cell's health is affected and the lifecycle of the cell is reduced. To protect the cell from overcharging, this BMS employs the overcharge protection mechanism which disconnects the battery pack from the charger. The working of the overcharge protection is shown in the graph below.




Fig 4.7.1 Overcharge condition graph

Over Discharge Condition

When the cell voltage goes below a safe operating voltage, the cell's health is affected and the lifecycle of the cell is reduced. To protect the cell from over discharge, this BMS employs over discharge protection.




Fig 4.7.2 Overcharge condition

From the above graph, you can see that when the load is connected, the battery voltage continues to decrease and as soon as it goes under VODP (Over-discharge protection voltage) it waits for the TOD(over discharge delay time) and open the over discharge protection transistor thus switching off the over-discharge protection MOSFETs. Hence no current flows through the BMS. And till the time the battery is not recharged and the voltage of the cell does not cross beyond the VODR (Over-discharge release voltage), the BMS doesn't allow the usage of the battery pack, thus increasing the life of our battery pack. The above image shows the flow of current during over discharge conditions. As you can see the transistors are connected in parallel because when the transistors are connected in parallel, they act as a single big transistor that can handle a higher amount of current.

Over Current Protection

Over current protection in a BMS is necessary to safeguard the battery systems from overcurrent or short circuit when a short circuit fault occurs or there's a surge in current from the load which is higher than the battery packs' specification. This condition can affect the cell's health or even cause damage to the cell leading to fires. To protect the cell from over current, this BMS employs overcurrent protection.




Fig 4.7.3 Overcurrent protection graph

In normal conditions, the CS pin monitors the discharge current by constantly monitoring the voltage of CS pin. When there is a surge in current demand from the cell and the voltage in CS pin exceeds the VOIP (Over-current protection voltage) for longer than TOI1(Over-current delay time) the overcurrent protection circuit operates and turns off the OC MOSFET thus disconnecting the circuit. The overcurrent discharged protection is released only when the load is released or the impedance of the battery between the positive and negative terminal becomes greater than 500k ohm.

CHAPTER-5

5.1 ADVANTEGES

1. **Safety:** One of the primary advantages of a BMS is safety. It monitors and manages the battery's temperature, voltage, and current to prevent overcharging, over-discharging, and overheating, which can lead to safety hazards such as fire or explosion.
2. **Prolonged battery life:** The BMS helps optimize the charging and discharging processes, preventing conditions that can degrade the battery over time. This can lead to a longer overall battery life.
3. **Efficiency:** BMS helps improve the efficiency of the battery system by ensuring that energy is used and stored optimally. This can result in better overall performance and longer run times for battery-powered devices.
4. **Cell Balancing:** In multi-cell battery packs, individual cells may have different capacities or states of charge. The BMS helps balance these cells by redistributing energy, ensuring that each cell operates within its safe operating range.
5. **Fault Detection and Diagnostics:** BMS monitors the battery system for faults and issues, providing diagnostics that can be used to identify and address problems promptly. This proactive approach can prevent catastrophic failures and downtime.
6. **Communication and Control:** BMS often includes communication capabilities, allowing it to interface with external systems and controllers. This enables remote monitoring, control, and data logging, which is crucial for many applications.

5.2 DISADVANTAGES

1. **Cost:** Implementing a sophisticated BMS can add to the overall cost of a battery system. This cost may be a significant factor, especially in applications where minimizing expenses is crucial.
2. **Complexity:** BMS can be complex, especially in large and advanced battery systems. The complexity can lead to challenges in design, installation, and maintenance, requiring skilled personnel for proper implementation.
3. **Energy Loss:** Some BMS functions, such as balancing cells, can result in energy losses. While necessary for the health of the battery, these losses can reduce the overall efficiency of the system.
4. **Limited Standards:** There is a lack of universal standards for BMS, and different manufacturers may implement different protocols and specifications. This can lead to compatibility issues when integrating batteries and BMS components from different sources.
5. **Weight and Size:** In some applications, especially those with stringent size and weight requirements (e.g., electric vehicles), the additional components and wiring associated with a BMS can be a drawback. There is a loss of energy (10-20%) while transferring energy amongst cells. Only one-way flow of energy from higher to lower. It has a complex control algorithm and expensive production cost as it needs a power electronics interface.

5.3 APPLICATIONS

1. Electric Vehicles (EVs)

Simulation: Simulating a BMS in the context of electric vehicles can help optimize battery performance, extend battery life, and ensure safe charging and discharging.

Hardware Implementation: Implementing the BMS in actual electric vehicles ensures the reliable operation of the battery pack, protects against overcharging and over-discharging, and enhances overall safety.

2. Renewable Energy Systems

Simulation: Simulating a BMS for energy storage systems allows for efficient management of batteries connected to renewable energy sources, such as solar or wind, optimizing energy utilization and storage.

Hardware Implementation: Implementing the BMS in real energy storage systems ensures the reliability and longevity of the battery storage, providing a stable power supply.

3. Portable Electronics

Simulation: Simulating BMS for devices like laptops, smartphones, and wearables helps optimize battery usage, considering factors like charging cycles, temperature, and load conditions.

Hardware Implementation: Implementing BMS in consumer electronics ensures the safe and efficient operation of batteries, preventing issues like overheating and overcharging.

4. Grid-Scale Energy Storage and Microgrids

Simulation: Simulating a BMS for grid-scale energy storage systems helps manage large battery arrays, optimizing performance and ensuring the stability of the electrical grid.

Hardware Implementation: Implementing the BMS in grid energy storage systems enhances the reliability and efficiency of the stored energy, contributing to grid stability.

5. Research and Development

Simulation: Researchers can use the simulated BMS to test and validate new algorithms, control strategies, or protocols for battery management.

Hardware Implementation: Implementing the BMS in real-world scenarios provides practical insights, allowing researchers to validate their simulations.

CONCLUSION

MATLAB is a standard software package that engineering students learn to use as part of their degree programme. Simulink provides a graphical editor, customizable block libraries, and solvers for modelling and simulating dynamic systems. We used MATLAB Simulink to build circuit diagram of BMS for a battery pack of 22V and to know performance characteristics i.e. SOC of individual batteries i.e. the balanced voltage when connected as in circuit diagram.

Battery Management Systems (BMS) serve as critical components in modern energy storage and utilization, offering sophisticated monitoring, control, and optimization capabilities for rechargeable battery packs. The widespread adoption of BMS technology has significantly improved the performance, safety, and longevity of batteries across diverse applications. By integrating precise monitoring of key parameters such as state-of-charge (SOC), voltage, temperature, and current, BMS ensures efficient energy utilization and enhances overall system reliability.

REFERENCES

1. R.-J. Wai, R.-Y. Duan, and K.-H. Jheng, "High-efficiency bidirectional dc–dc converter with high-voltage gain," *IET Power Electron.*, vol. 5, no. 2, pp. 173– 184, Apr. 2012.
2. W. Na and B. Guo, "Analysis and control of bidirectional dc/dc converter for PEM fuel cell applications" .
3. K. Jin, X. Ruan, M. Yang, and M. Xu, "Power management for fuelcell power system cold tart," *IEEE Trans. Power Electron.*, vol. 24, no. 10, pp. 2391– 2395, Oct. 2009.
4. J. Park and S. Choi, "Design and control of a bidirectional resonant dc– dc converter for automotive engine/battery hybrid power generators," *IEEE Trans. Power Electron.*, vol. 29, no. 7, pp. 3748–3757, Jul. 2014.
5. D. Kim, S. Choi, S. Kim, and B. Choi, "MATLAB-based digital design of current mode control for multi-module bidirectional battery charging/dischargingconverters," in *Proc. 2011 IEEE 8th Int. Conf. on Power Electronics and ECCE Asia*, pp. 2256– 2260.
6. S.-i. Hamasaki, R. Mukai, and M. Tsuji , "Control of power leveling unit with super capacitor using bidirectional buck/boost dc/dc converter," in *Proc. 2012 IEEE Int. Conf. on Renewable Energy Research and*

