

EEE4114F: Digital Signal Processing

Class Test

11 March 2024

Please do not put your name or student number anywhere on this script.

Peoplesoft ID:

Information

- The test is closed-book.
 - This test has *four* questions, totalling 20 marks.
 - Answer *all* the questions.
 - You have 60 minutes.
 - An information sheet is attached.
-

1. (5 marks) A system is governed by the input-output relation

$$y[n] = \max_{-\infty < k \leq n} |x[k]|,$$

where $x[n]$ is the input and $y[n]$ is the output. The "max" operator returns the maximum value of the argument over the specified range, so in other words

$$\max_{-\infty < k \leq n} |x[k]| = \max\{\dots, |x[n-2]|, |x[n-1]|, |x[n]|\}.$$

- (a) Find the response $y_1[n]$ of the system to the input $x_1[n] = \delta[n]$.
- (b) Is the system linear? Why?
- (c) Is the system time invariant? Why?

2. (5 marks) Suppose the signal

$$x[n] = \sum_{k=-\infty}^{\infty} (-1)^k \delta[n - 2k]$$

is provided as input to an LTI system with impulse response

$$h[n] = \delta[n] + \delta[n - 2].$$

- (a) Sketch $x[n]$ over the range $-6 \leq n \leq 6$.
- (b) Find and sketch the output $y[n]$.

3. (5 marks) Answer the following:

(a) Find the DTFT of the following sequence:

$$f[n] = e^{-3n} \cos(3n)u[n].$$

(b) Find the inverse DTFT of the following:

$$X(e^{j\omega}) = \frac{e^{-j2\omega} - 1}{e^{-j2\omega} - 4}.$$

(c) (Bonus 2 marks) If $X(e^{j\omega}) = \text{DTFT}\{x[n]\}$ then Parseval's theorem states that

$$\sum_{n=-\infty}^{\infty} |x[n]|^2 = \frac{1}{2\pi} \int_0^{2\pi} |X(e^{j\omega})|^2 d\omega.$$

Find the energy in the signal having DTFT

$$Y(e^{j\omega}) = \frac{1 - ae^{-j\omega}}{a - e^{-j\omega}}$$

where $-1 < a < 1$. Hint: the magnitude of the DTFT has a particularly simple form.

4. (5 marks) Consider the difference equation

$$6y[n] - y[n-1] - y[n-2] = x[n-1],$$

where $x[n]$ is the input and $y[n]$ is the output. What are the impulse response $h[n]$ and the frequency response $H(z)$ for the causal LTI system satisfying this difference equation?

Transforms

$$X(j\Omega) = \int_{-\infty}^{\infty} x(t)e^{-j\Omega t} dt \quad \Longleftrightarrow \quad x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(j\Omega)e^{j\Omega t} d\Omega$$

(CTFT)

$$X(e^{j\omega}) = \sum_{n=-\infty}^{\infty} x[n]e^{-j\omega n} \quad \Longleftrightarrow \quad x[n] = \frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\omega})e^{j\omega n} d\omega$$

(DTFT)

$$X(z) = \sum_{n=-\infty}^{\infty} x[n]z^{-n} \quad \Longleftrightarrow \quad x[n] = \frac{1}{2\pi j} \oint_C X(z)z^{n-1} dz$$

(ZT)

$$X[k] = \sum_{n=0}^{N-1} x[n]W_N^{kn} \quad \Longleftrightarrow \quad x[n] = \frac{1}{N} \sum_{k=0}^{N-1} X[k]W_N^{-kn} \quad \text{with} \quad W_N = e^{-j\frac{2\pi}{N}}$$

(DFT)

Discrete-time Fourier transform properties

Sequences $x[n], y[n]$	Transforms $X(e^{j\omega}), Y(e^{j\omega})$	Property
$ax[n] + by[n]$	$aX(e^{j\omega}) + bY(e^{j\omega})$	Linearity
$x[n - n_d]$	$e^{-j\omega n_d} X(e^{j\omega})$	Time shift
$e^{j\omega_0 n} x[n]$	$X(e^{j(\omega - \omega_0)})$	Frequency shift
$x[-n]$	$X(e^{-j\omega})$	Time reversal
$nx[n]$	$j \frac{dX(e^{j\omega})}{d\omega}$	Frequency diff.
$x[n] * y[n]$	$X(e^{j\omega})Y(e^{j\omega})$	Convolution
$x[n]y[n]$	$\frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\theta})Y(e^{j(\omega - \theta)}) d\theta$	Modulation

Common discrete-time Fourier transform pairs

Sequence	Fourier transform
$\delta[n]$	1
$\delta[n - n_0]$	$e^{-j\omega n_0}$
1 $(-\infty < n < \infty)$	$\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega + 2\pi k)$
$a^n u[n] \quad (a < 1)$	$\frac{1}{1 - ae^{-j\omega}}$
$u[n]$	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{\infty} \pi\delta(\omega + 2\pi k)$
$(n + 1)a^n u[n] \quad (a < 1)$	$\frac{1}{(1 - ae^{-j\omega})^2}$
$\frac{\sin(\omega_c n)}{\pi n}$	$X(e^{j\omega}) = \begin{cases} 1 & \omega < \omega_c \\ 0 & \omega_c < \omega \leq \pi \end{cases}$
$x[n] = \begin{cases} 1 & 0 \leq n \leq M \\ 0 & \text{otherwise} \end{cases}$	$\frac{\sin[\omega(M+1)/2]}{\sin(\omega/2)} e^{-j\omega M/2}$
$e^{j\omega_0 n}$	$\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega - \omega_0 + 2\pi k)$

Z-transform properties

Sequences $x[n], y[n]$	Transforms $X(z), Y(z)$	ROC	Property
$ax[n] + by[n]$	$aX(z) + bY(z)$	ROC contains $R_x \cap R_y$	Linearity
$x[n - n_d]$	$z^{-n_d} X(z)$	ROC = R_x	Time shift
$z_0^n x[n]$	$X(z/z_0)$	ROC = $ z_0 R_x$	Frequency scale
$x^*[-n]$	$X^*(1/z^*)$	ROC = $\frac{1}{R_x}$	Time reversal
$nx[n]$	$-z \frac{dX(z)}{dz}$	ROC = R_x	Frequency diff.
$x[n] * y[n]$	$X(z)Y(z)$	ROC contains $R_x \cap R_y$	Convolution
$x^*[n]$	$X^*(z^*)$	ROC = R_x	Conjugation

Common z-transform pairs

Sequence	Transform	ROC
$\delta[n]$	1	All z
$u[n]$	$\frac{1}{1-z^{-1}}$	$ z > 1$
$-u[-n-1]$	$\frac{1}{1-z^{-1}}$	$ z < 1$
$\delta[n-m]$	z^{-m}	All z except 0 or ∞
$a^n u[n]$	$\frac{1}{1-az^{-1}}$	$ z > a $
$-a^n u[-n-1]$	$\frac{1}{1-az^{-1}}$	$ z < a $
$na^n u[n]$	$\frac{az^{-1}}{(1-az^{-1})^2}$	$ z > a $
$-na^n u[-n-1]$	$\frac{az^{-1}}{(1-az^{-1})^2}$	$ z < a $
$\begin{cases} a^n & 0 \leq n \leq N-1, \\ 0 & \text{otherwise} \end{cases}$	$\frac{1-a^N z^{-N}}{1-az^{-1}}$	$ z > 0$
$\cos(\omega_0 n) u[n]$	$\frac{1-\cos(\omega_0)z^{-1}}{1-2\cos(\omega_0)z^{-1}+z^{-2}}$	$ z > 1$
$r^n \cos(\omega_0 n) u[n]$	$\frac{1-r\cos(\omega_0)z^{-1}}{1-2r\cos(\omega_0)z^{-1}+r^2 z^{-2}}$	$ z > r $

Other

$$\sum_{n=0}^{N-1} a^n = \frac{1-a^N}{1-a} \quad \text{for } a \neq 1.$$