



**WITS**  
UNIVERSITY



SCHOOL OF  
**ELECTRICAL AND  
INFORMATION  
ENGINEERING**

## ELEN4011: DESIGN II

---

### DESIGN OF A ROBUST CODEC FOR A FADING CHANNEL.

---

Author

ELIAS SEPURU - 1427726

Supervisor

PROF. FAMBIRAI TAKAWIRA

School of Electrical and Information Engineering, University of the Witwatersrand,  
Johannesburg 2050, South Africa

25 October 2019

## **Abstract**

# Contents

1	Introduction . . . . .	2
2	Design Overview . . . . .	2
	2.1 The Transmitter . . . . .	2
	2.2 The Channel . . . . .	3
	2.3 The Receiver . . . . .	3
3	Channel Encoding . . . . .	3
	3.1 Convolutional Codes . . . . .	4

# 1 Introduction

The aim of modern and next-generation wireless communication systems is to provide communication services with high data rates and low probability of error, this also helps in catering for numerous requests from various applications and devices [1, 2, 3]. The reliability of such communication systems is often hindered by strong shadowing, intersymbol interference (ISI) and attenuation due to the destructive addition of multipaths propagation in the transmission channel [1, 4]. Such a channel is often accurately modeled using a Rayleigh model known as the Rayleigh Fading Channel (RFC) [4]. To combat the effect of fading and scattering due to RFC, several methods have been proposed. Methods such as Selection Diversity, Equal Gain Combining and Maximal Ratio Combining were proposed. However the methods proved to be inefficient and ineffective in dealing with the requirement of high data rates as per modern communication needs [5]. This lead to the development of Multiple-Input Multiple-Output (MIMO) systems. MIMO leverages off the multipath characteristic of the Rayleigh Fading Channel. It transmits data over the multiple paths, therefore increasing the amount of information the communication system carries [6]. MIMO uses multiple transmit and receive antennas to significantly increase the data throughput and link range without additional bandwidth or transmit power [7]. However MIMO cannot achieve all this without robust Forward Error Correction (FEC) and modem schemes.

This paper presents the design of a robust codec for a fading channel. The codec is to operate at a rate of at least 2 bits/Hz over a Rayleigh Fading Channel. The design of the codec focuses mainly on FEC, modulation and MIMO. The codec input data input is expected to be at 10 Mbps. The design assumes that the data stream has already been converted from analog to digital, hence source encoding is neglected. Encryption is also left out as it does not affect the Bit Error Rate (BER) and spectral efficiency. The below sections present the mathematical description of the designed codec together with testing, results and analysis. All simulations and computations are carried out in MATLAB.

## 2 Design Overview

A typical digital communication system constitutes of three main components, those components being the transmitter, the channel and the receiver. Figure 1 illustrates a typical communication system consisting of MIMO architecture.

From figure 1, it can be seen that the receiver mirrors the transmitter in most of the sub-components.

### 2.1 The Transmitter

On the transmitter side, the source encoder takes in a raw message signal and converts it into a sequence of bits. This is done to compress the raw message data and to remove redundancy. The end result of source encoding is digital information bits with lesser bandwidth and just enough information to reconstruct the original message [8]. After source encoding, the information bits are sent to the channel encoder. The channel encoder uses FEC codes to add redundancy to the information bits. This is done to facilitate error detection and correction on the receiver side after channel transmission. The next step is modulation, the modulator takes in the coded bits from the channel encoder and maps them to a signal to be transmitted over the channel. This is done to conserve power and bandwidth. The MIMO transmitter takes in the symbols and transmits them over the channel using its multiple antennas. The MIMO transmitter uses



Figure 1: System block diagram of a typical communication system with MIMO architecture

multiple antennas to boost bandwidth and to improve signal range as mentioned earlier.

## 2.2 The Channel

The steps mentioned in section 2.1 are taken so as to prepare the original message to prevail in the channel and so that it is sent as efficiently as possible. The channel can be any medium, wireless or physical, into which the transmitted signal propagates. The channel distorts and adds noise to the transmitted signal, and in some instances interference occurs [8].

## 2.3 The Receiver

The mirrored side of the transmitter, which is the receiver, performs the opposite of all the steps mentioned in section 2.1 respectively. This is done in order to recover the original sent message to the highest accuracy possible.

This paper only focuses on the part of the communication system highlighted in red on figure 1.

## 3 Channel Encoding

As mentioned earlier, transmitting data over a noisy channel often leads to the information being corrupted. To minimise the occurrence of errors during transmission the information has to somehow be protected. This protection is achieved through either the use of FEC codes or Automatic Repeat Requests (ARQ). ARQ requires retransmission of bits if they are in error. This leads to delays in communication, wasteful retransmissions that require additional power and bandwidth and also interference with other users [9]. All these make ARQ not suitable for real-time applications especially in interactive media applications [10]. FEC on the other hand uses error correcting codes to correct errors that occur during transmission. It does this by adding redundant bits on the information bits, this helps to detect and correct errors as

mentioned earlier. For this design FEC is chosen due to the fact that it offers improved BER, higher throughput and minimal delays compared to its counterpart [10, 11].

FEC codes are split up into two categories: Convolutional Codes and Linear Block Codes. Error correcting capability and/or performance of an FEC coding scheme is measured by its code rate  $r$ . The code rate represented by equation 1 below.

$$r = \frac{k}{n} \tag{1}$$

The code rate presents the proportion of the data stream that is useful to the one that has redundancy, represented by  $k$  and  $n$  respectively in equation 1.

### 3.1 Convolutional Codes

Convolutional Codes are mostly used in applications that require real time error correction. They are generated by combining the input data stream bits in a series manner. The input bits are stored in a fixed length shift register and are combined with the use of modulo-2 adders [?]. The output of the convolutional encoder at any point is a combination of the previous bits in the shift register.

One type of a Convolutional Codes are Turbo codes. Turbo codes are known to perform extremely well compared to any other FEC code. They achieve within a fraction of a dB of the Shannon Capacity in certain channels [9]. The major disadvantage of Convolutional Codes is their complexity. The complexity curve steepens even further when trying to decode them [9]. The simplest decoder which is the Viterbi also increase in complexity and it gets much difficult to implement for large codewords [?].

# References

- [1] A. S. Behbahani, R. Merched, and A. M. Eltawil, "Optimizations of a mimo relay network," *IEEE Transactions on Signal Processing*, vol. 56, no. 10, pp. 5062–5073, 2008.
- [2] A. M. Alsahlany, M. J. Alhasan, and Q. Jalil, "Performance investigation of interleaving and bch code in mimo system," *International Journal of Innovative Research in Science, Engineering and Technology*, vol. 7, no. 6, pp. 6883–6891, 2018.
- [3] S. S. Sarnin, N. F. Nairn, and W. N. S. W. Muhamad, "Performance evaluation of phase shift keying modulation technique using bch code, cyclic code and hamming code through awgn channel model in communication system," in *The 3rd International Conference on Information Sciences and Interaction Sciences*. IEEE, 2010, pp. 60–65.
- [4] V. Tarokh, H. Jafarkhani, and A. R. Calderbank, "Space-time block coding for wireless communications: performance results," *IEEE Journal on selected areas in communications*, vol. 17, no. 3, pp. 451–460, 1999.
- [5] B. Kumbhani and R. S. Kshetrimayum, *MIMO wireless communications over generalized fading channels*. CRC Press, 2017.
- [6] G. Lawton, "Is mimo the future of wireless communications?" *computer*, vol. 37, no. 7, pp. 20–22, 2004.
- [7] D. Tse and P. Viswanath, *Fundamentals of wireless communication*. Cambridge university press, 2005.
- [8] U. Madhow, *Introduction to Communication Systems*. Cambridge University Press, 2014.
- [9] J. Walrand and P. P. Varaiya, *High-performance communication networks*. Morgan Kaufmann, 2000.
- [10] M. Sugano, D. Eom, M. Murata, and H. Miyahara, "A combination scheme of arq and fec for error correction of wireless atm networks," 07 1997.
- [11] D. Barman, I. Matta, E. Altman, and R. El Azouzi, "Tcp optimization through fec, arq, and transmission power tradeoffs," in *International Conference on Wired/Wireless Internet Communications*. Springer, 2004, pp. 87–98.