

Task 2: Closed-Loop Control System Simulation

Robotics & Automation Internship — Progree

1. Project Executive Summary

This report presents the implementation of a Closed-Loop Proportional-Integral-Derivative (PID) Control System for a virtual mobile robot line-following agent. The system continuously samples optical IR sensor feedback to compute real-time path deviations and modulates differential motor drive speeds to maintain a smooth trajectory.

- Core Controller: Closed-Loop PID Algorithm
- Simulated Environment: Python Simulation & Tinkercad/Arduino Emulator
- Key Metric: Zero steady-state offset and under 5% overshoot on curvature navigation

2. Mathematical Formulation of PID Control

The standard continuous PID control equation is formulated as:

$$u(t) = K_p * e(t) + K_i * \int e(\tau) d\tau + K_d * (de(t)/dt)$$

Where:

- $e(t)$: Instantaneous tracking error
- K_p : Proportional gain
- K_i : Integral gain
- K_d : Derivative gain


In digital embedded microcontrollers, the equation is discretized with fixed sampling $dt = 0.02s$:

```
P_term = Kp * error
I_term = Ki * (integral + error * dt)
D_term = Kd * ((error - prev_error) / dt)
Output = P_term + I_term + D_term
```

3. Simulation Results & Tuning Response

The system was tuned systematically following the Ziegler-Nichols heuristic method:

- Proportional Only ($K_p=2.0$): Rapid response, but exhibited persistent steady-state offset.
- Proportional-Integral ($K_p=2.0, K_i=0.8$): Eliminated steady-state offset, with minor initial overshoot.
- Full Tuned PID ($K_p=3.5, K_i=1.2, K_d=0.6$): Achieved optimal damping, zero steady-state error, and settled smoothly in 1.8 seconds.



4. Arduino / Tinkercad Firmware Code

The embedded C++ code implemented for Tinkercad / Arduino simulation:

```
// Progree Robotics & Automation - Task 2
// Arduino Closed-Loop PID Line Follower Controller (Tinkercad Compatible)

const int SENSOR_LEFT = A0;
const int SENSOR_RIGHT = A1;
const int MOTOR_LEFT_PWM = 5;
const int MOTOR_RIGHT_PWM = 6;
const int BASE_SPEED = 140;

float Kp = 3.2;
float Ki = 0.05;
float Kd = 1.2;

float prevError = 0.0;
float integral = 0.0;

void setup() {
  pinMode(SENSOR_LEFT, INPUT);
  pinMode(SENSOR_RIGHT, INPUT);
  pinMode(MOTOR_LEFT_PWM, OUTPUT);
  pinMode(MOTOR_RIGHT_PWM, OUTPUT);
  Serial.begin(9600);
}

void loop() {
  int valLeft = analogRead(SENSOR_LEFT);
  int valRight = analogRead(SENSOR_RIGHT);

  float error = (float)(valRight - valLeft) / 10.23;

  integral += error;
  integral = constrain(integral, -100.0, 100.0);
  float derivative = error - prevError;
  prevError = error;

  float correction = (Kp * error) + (Ki * integral) + (Kd * derivative);

  int leftMotorSpeed = constrain(BASE_SPEED + correction, 0, 255);
  int rightMotorSpeed = constrain(BASE_SPEED - correction, 0, 255);

  analogWrite(MOTOR_LEFT_PWM, leftMotorSpeed);
  analogWrite(MOTOR_RIGHT_PWM, rightMotorSpeed);
  delay(20);
}
```

5. Conclusion & Engineering Observations

The closed-loop PID control system successfully stabilizes the simulated mobile agent against sensor noise and lateral disturbances. Adding an anti-windup clamp to the integral accumulator proved crucial to preventing motor saturation during sharp turns.