SDK Document

Time	Version	Author	Modified contents
2019-02-28	v3.0 beta	Jinming Chen	Initial publish
2019-03-05	v3.0 beta2	Jinming Chen	Add section of shared memory
2019-03-06	v3.0 beta3	Jinming Chen	Add section of video data and range data
2019-03-07	v3.0 beta4	Jinming Chen	Add new project and open project
2019-03-11	v3.0 beta5	Jinming Chen	Add save project and start/end/cancel scanning
2019-03-12	v3.0 beta6	Jinming Chen	Add mesh, export data and manual align
2019-03-21	v3.0 beta7	Jinming Chen	Add enter cali & exit cali
2019-04-15	v3.1.0 Release	Weijian Lin	Add post data process
2019-05-20	v3.1.1 Release	Weijian Lin	Add incremental point cloud handle

- Device events
- Enter calibration
- Exit calibration
- Calibration time
- Snap enabled
- Calibration type
- Calibration group
- Calibration distance
- Calibration distance states
- Scan type
- Scan sub-type
- Path of last saved project
- Path of current project
- Has turnable
- Scan with texture
- Point distance range
- Predefined resolution values
- Framerate
- Point count
- Marker count
- Triangle count in fix mode
- Triangle count of wrapped mesh
- Frame memory
- Camera position
- Scan with global markers
- Current brightness
- Brightness range
- Point count in wrapped mesh
- HDR
- Use discovery
- Has light box
- Light box open
- Has mesh data
- Scan alignment type
- Scan status
- Scan distance

- Rapid mode of EP
- Rapid save of EP
- Enter scan
- Exit scan
- Create new project
- Open project
- Control scanning (pre/start/pause/resume)
- End scanning
- Cancel scanning
- No markers detected
- Too flat
- Track lost
- Manual align
- Last mesh type
- Mesh/Wrap the point cloud
- Last degree of mesh detail
- Last simplification params
- Last resize params for saving
- Save mesh to disk
- Export sharable data
- Update Firmware
- Mesh Data Has Marker
- Is Mesh Data Water Tight
- Smooth
- Sharp
- Zoom
- Edit Fill Hole
- Apply Fill Hole
- Load Model
- Get All Hole Info
- Request Data
- Read Data End
- Enter Post Data Process
- Exit Data Post Process
- Clear Mesh Data
- Rebuild Texture Map

Overview

This is the official SDK that helps third party developers to write apps to manipulate 3D cameras of Shining3D's 2X series.

It runs as a standalone executable and communicates with 3rd apps via ZMQ. The interfaces try to keep consistent with the latest EXScan Pro®, the official controlling software of 2X series cameras.

Installation

The SDK consists of only two files:

- Sn3DPlatform.exe: the main executable of the SDK.
- platform.ini: the configuration file.

The executable cannot run alone. It has dependencies of the controlling software. Therefore, these two files have to be put into the root directory of EXScan Pro installation path, i.e. in the same directory of EXScanPro.exe.

Configuration & run

Currently there are only two parameters in platform.ini in version v1.0:

- `Pub`: the publish url of ZMQ. Default is `tcp://*:11398`.
- `Rep`: the request url of ZMQ. Default is `tcp://*:11399`.

Normally you only need to change the ports if you want.

Double click Sn3DPlatform.exe and then the SDK is ready to talk to you via ZMQ interfaces.

Interfaces

Each message between Sn3DPlatform.exe and your app consists of two frames:

- Envelop: An ASCII string with a maximum length of 255. It contains two parts:
    - Version: the version of this message. Currently only `"v1.0"` is supported.
    - Commands: the actual commands of this message. The commands may have several parts, who are joined by character `/`.
- Payload: A byte array with a maximum length of 1024. It could be an integer, a string, or a JSON object, depending on the certain command.

The heartbeat message is a special message publishing from the SDK. It has only the evelop. Third party app should pay attention if they receive a message with such envelop.

There are three types of interfaces:

- **Publish**: The publish messages are published automatically by SDK when the corresponding properties are changed.
- **Request Get**: Third apps use this interface to get certain value from the device with a REQ/REP pattern.
- **Request Set**: Third apps use this interface to set certain value on the device with a REQ/REP pattern.

To receive all the publish messages, you should connect to the `Pub` url. To do Req/Rep communication to the SDK, you should connect and send/receive data to the `Rep` url.

The payload has different types:

- **Int Bool**: integar with 4 bytes, 0 means `false`, 1 measn `true;
- **Int**: signed integar with 4 bytes;
- **Int LL**: signed longlong integar with 8 bytes;
- **String**: C-style string;
- **JSON**: JSON object.

Heartbeat

This is a publish message broadcasted by the SDK repeatedly to indicate the main SDK process is still alive.

Type	Envelop	Payload
Publish	v1.0/hb	None

The interval of heartbeat is 1 seconds currently. Third app who cares about the aliveness of SDK could moniter the heartbeat. If no heartbeat comes any more, the main SDK process should be dead and needs relaunching.

Asynchronous actions

Many actions on the device take time to perform. To inform the third party apps the current status of the actions, the SDK broadcasts three messages/signals:

- **The beginning messages**: indicating that the action has begun.
- **The progress messages**: telling how far the action has gone. The progress value is between 0 and 100. It is ideal for developers to bind the value to a visual progress bar. Note: some actions don't have this kind of messages.
- **The finishing messages**: signaling that the action has finished.

Type	Envelop	Payload
Publish	v1.0/beginAsyncAction	JSON
Publish	v1.0/progress	Int
Publish	v1.0/finishAsyncAction	JSON

All the asynchronous actions are listed below:

- `"AAT_CHECK_DEVICE"`: Check the device.
- `"AAT_ENTER_CALI"`: Enter the calibration state.
- `"AAT_CHANGE_CALI_TYPE"`: Change the calibration type.

- `"AAT_EXIT_CALI"`: Exit the calibration state.
- `"AAT_COMPUTE_CALI"`: Compute the calibration.
- `"AAT_NEW_PROJECT"`: Create a new project.
- `"AAT_OPEN_PROJECT"`: Open the specified project.
- `"AAT_ENTER_SCAN"`: Enter the scanning state.
- `"AAT_EXIT_SCAN"`: Exit the scanning state.
- `"AAT_CANCEL_SCAN"`: Cancel the current scanning.
- `"AAT_END_SCAN"`: Finish the current scanning.
- `"AAT_SCAN"`: Start scanning.
- `"AAT_WHITE_BAL"`: Compute the white balancing.
- `"AAT_MANUAL_ALIGN"`: Start manual alignment for multiple point clouds.
- `"AAT_MESH"`: Start warping/meshing the point cloud.
- `"AAT_SIMPLIFY"`: Simplify the current scanned model.
- `"AAT_EDIT"`: Edit the current model.
- `"AAT_EDIT_LIST"`: Edit the data list for the current scanning project.
- `"AAT_DEL_POINT_CLOUD"`: Delete certain point cloud.
- `"AAT_SAVE"`: Save the current scanned model to the project.
- `"AAT_FIX_SINGLE_EDIT"`: Edit a single patch of point cloud in fix scan mode.
- `"AAT_AXIS_VERIFY"`: Compute & adjust the turnable axis.
- `"AAT_FIX_SCAN"`: Broadcast current state in fix scan mode.
- `"AAT_FIX_REMOVE_DATA"`: Remove data in fix scan mode.
- `"AAT_FIX_UPDATE_DATA_RT"`: Update the RT matrix in fix scan mode.
- `"AAT_EXPORT_SHARE_DATA"`: Export shared data.
- `"AAT_LOAD_MODEL"`: Only Support Load .obj or .stl Mode.
- `"AAT_ENTER_POSTDATAPROCESS"`: Enter post data process.
- `"AAT_EXIT_POSTDATAPROCESS"`: Exit post data process.
- `"AAT_ENTER_FILL_HOLE_MODE"`: Enter fill hole mode.
- `"AAT_APPLAY_FILLHOLE"`: Apply hole mode.
- `"AAT_FILLING_HOLE"`: Filling hole mode.
- `"AAT_SMOOTH"`: Broadcast current state in smoothing the mesh data.
- `"AAT_SHARP"`: Broadcast current state in sharping the mesh data.
- `"AAT_ZOOM"`: Broadcast current state in zooming the mesh data.
- `"AAT_REBUILDTEXTURE"`: Rebuild texture map.
- `"AAT_RESTORE_RAW_MESH"`: Restore raw mesh data.
- `"AAT_CANCEL_ALIGEN"`: Cancle manual alignment.

The beginning JSON format is below:

```
{
    "type": "AAT_CHECK_DEVICE",
    "props": {}
}
```

The `props` differs between different actions. It will be explained in detail under the corresponding action interface later.

The finishing JSON format is below:

```
{
    "type": "AAT_CHECK_DEVICE",
    "result":{
        "success": false,
        "error": 2,
        "detail": "Cannot connect to the device."
    },
    "props": {}
}
```

The `props` differs between different actions. It will be explained in detail under the corresponding action interface later.

Shared memory

Messages through ZMQ are commands, signals or small data. It is not feasible to transfer large data through ZMQ since it involves redundant copying. We use shared memories to transfer large data.

There are 6 different types of large data transferring via shared memories currently:

- `"MT_POINT_CLOUD"`: Point cloud captured by the device and sent to apps.
- `"MT_DELETE_POINTS"`: Indices of points that need deleting. It is sent from apps to the device.
- `"MT_MARKERS"`: The positions information of markers captured by the device and sent to apps.
- `"MT_TRI_MESH"`: Triangle mesh information sent from the device to apps.
- `"MT_VIDEO_DATA"`: Video streaming sent from the device to apps.
- `"MT_RANGE_DATA"`: Single frame data with depth information sent from device to apps in fix mode only.

To receive shared memories, you need to do the following steps:

1. Setup a new `ZMQ_REQ` type ZMQ socket, and bind to a url.
2. Register to the SDK by calling `v1.0/scan/register` and send the url. It should be done before the scanning, otherwise data might be lost.
3. Wait for requesting from the SDK with the key and type of the shared memory.
4. Open the shared memory using language-specific manner and analyzing the data.
5. Reply the SDK with Int Bool `true` if you sucessfully handle the data, `false` otherwise.
6. Finish analyzing. Return to Step 3, waiting for the next large data.

Related interfaces are:

Type	Envelop	Payload
Request	v1.0/scan/register	String
Request	v1.0/scan/unregister	String

The message sent from SDK to the app contains JSON with the information (key and type) of the shared memory. It has no envelop. The JSON definition is below:

```
{
    "type": "MT_POINT_CLOUD",   // The data type
    "key": "qtipc_XXXXXXXXXX",  // The native shared memory key
    "name": "currentPointCloud",// The name of current data
    "offset": 100,              // The offset from the beginning of the data (bytes)
    "props":{}                  // type-specific parameters
}
```

Open from other languages

The key is a native mapped file descriptor on Windows. You can use corresponding functions in your favorite language to open and manipulate it. For example, in Python, the shared memory can be opend like this:

```
import mmap
shm = mmap.mmap(0, 512, 'qtipc_XXXXXXXXXX')
```

Then you can use member functions of `mmap` to read/write the shared memory.

In C#, the same thing can be done like this:

```
using System.IO.MemoryMappedFiles;
MemoryMappedFile mm = MemoryMappedFile.OpenExisting(@"qtipc_XXXXXXXXXX",
                                                    MemoryMappedFileRights.ReadWrite);
using(var accessor = mm.CreateViewAccessor(0, 512)){
    // read/write using accessor
}
```

Properties and structures on the shared memory

Different data types have different props and structures.

Point cloud related data

For `MT_POINT_CLOUD`, `MT_MARKERS`, `MT_RANGE_DATA` and `MT_TRI_MESH`, the props definition is:

```
{
    "pointCount": 1000,     // The number of points
    "hasTexture": false,    // Whether there is texture attribute for each point
    "hasNormal": true,      // Whether there is normal attribute for each point
    "incremental": true,    // Whether this data is incremental to the last data
    "hasMarkers": true,     // Whether this data contains markers
    "haveUsed": false,      // [Todo]
    "hasTexturePicture": false,// [Todo]
    "faceCount": 500,       // The number of triangles
    "textureImgWidth": 512, // The width of texture image
    "textureImgHeight": 512,// The height of texture image
    "textureUVCount": 1000, // [Todo]
    "hasFaceNormal": true,  // Whether there is normal attribute for each triangle
    "packID": 0,            // Current package index, used for data segmentation
    "totalPacks": 10        // Total package count, used for data segmentation
}
```

There are 8 different named shared memories currently:

- `"currentPointCloud"`: Current frame of point cloud.
- `"currentMarker"`: Current frame of markers.
- `"wholePointCloud"`: The whole point cloud.
- `"failedPointCloud"`: Current frame of point cloud that cannot be aligned to existing points.
- `"frameMarkerPoint"`: Global marker file information.
- `"wholeMarkerPoint"`: The whole markers information.
- `"meshData"`: The triangle mesh data.
- `"rangeData"`: One frame of point cloud data in fix mode.

For `currentPointCloud`, `failedPointCloud` and `wholePointCloud`, the structures on the shared memory starting at offset `offset` are:



If `hasNormal` is `false`, then the normal part will be missing. If `hasTexture` is false, then the color part will be missing. If `incremental` is false, the id part will be missing.

The id is integer with 4 bytes, and the others are all float with 8 bytes.

For non-incremental `wholePointCloud` (the `incremental` property is `false` of its props), the complete data may be divided into `totalPacks` packages, and `packID` denotes the current package index. Developers should gather all the packages before processing the whole data.

For incremental `wholePointCloud` (the `incremental` property is `true` of its props), you should update point cloud data according to the value of ID. When you receive the `incremental` wholePointCloud data, you can iterate the point cloud data to get the value of IDs which are the indice of data array. If the ID is smaller then the size of the whole point cloud, it means it is an *old* point, and you should update the origin position, normal and color using received data through the new inex of id; If the ID is equal to or larger than the size of the whole point cloud, it means it is a *new* point, and you need to append this point to the whole point cloud (effectively expanding the whole point cloud).

As mentioned above, the whole points are updated in an incremental manner while the current point cloud is updated in the same manner as the first frame. So from the 2nd frame and so on, the whole point data should be different from the current point cloud.

These two point clouds share the same memory type of `MT_POINT_CLOUD`, however, the names of memory are different, i.e. the name for current point is `currentPointCloud` and the whole point name is `wholePointCloud`. You should distinguish them by the memory names and handle them accordingly.

For `currentMarker`, `frameMarkerPoint` and `wholeMarkerPoint`, the structures on the shared memory starting at offset `offset` are:



For `meshData`, since the data is too large, it is sent via 4 sequential units, each of which may consist of several packages (`totalPacks` is larger than 1):

Unit 1: Vertices unit.

If `pointCount` is non-zero, this unit delivers the vertices. The structures on the shared memory starting at offset `offset` are almost the same as point cloud except the absence of `id`:



If `hasNormal` is `false`, then the normal part will be missing. If `hasTexture` is false, then the color part will be missing. If `incremental` is false, the id part will be missing.

Unit 2: Texture image unit.

If `hasTexturePicture` is `true`, this unit delivers the texture image. The image has `textureImgWidth * textureImgHeight` pixels, each of which is 3 bytes of RGB.

Unit 3: Triangles unit.

If `faceCount` is non-zero, this unit delivers the indexed triangles. The structures on the shared memory starting at offset `offset` are:



If `hasTexturePicture` is false, then the part of texture uv index will be absent.

Unit 4: Texture UV unit.

If `textureUVCount` is non-zero, this unit delivers the texture UV coordinates. The structures on the shared memory starting at offset `offset` are:



After receving the 4 units, developers can put them togather and analyze/render the triangle mesh.

For `rangeData`, the structures on the shared memory starting at offset `offset` are:



If `hasNormal` is `false`, then the normal part will be missing. If `hasTexture` is false, then the color part will be missing. If `incremental` is false, the id part will be missing.

`rotation` is a 3x3 column-major matrix, and `translation` is a 3-element vector.

Video data

For `MT_VIDEO_DATA`, the props definition is:

```
{
    "width": 512,  // Image width
    "height": 512, // Image height
    "rotation": 90,// The rotation angle (in degree)
    "channel": 1   // The channel number for each pixel
}
```

If `channel` is 1, it means that it is a grey image; if `channel` is 3, it means that it is a colorful image coming from the texture camera, and each pixel contains RGB 3 bytes.

There are 4 different named shared memories currently:

- `"cam0"`: The 1st camera.
- `"cam1"`: The 2nd camera.
- `"cam2"`: The 3rd camera.
- `"cam3"`: The 4th camera.

To render the images correctly, developers should rotate the images counterclockwise with the degree of `rotation`.

Device type

The type of your connected camera. For 2X Series, there three types:

- 2X.
- 2X Plus.
- EP.

Type	Envelop	Payload
Publish	v1.0/device/type	String
Request Get	v1.0/device/type	REQ: None REP: String

Device check

Check the hardware environment to determine whether the GPU and USB are good for the camera.

Type	Envelop	Payload
Request Get	v1.0/device/check	REQ: None REP: Int Bool

The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` is empty.

The finishing `props` has the following definition:

```
{
    "GPU": true,// true: OK false: error
    "USB": true // true: OK false: error
}
```

There is no `progress` signal.

Infrared radiation

Whether the device has infrared radiation camera.

Type	Envelop	Payload
Publish	v1.0/device/hasIr	Int Bool
Request Get	v1.0/device/hasIr	REQ: None REP: Int Bool

Texture/Color camera

Whether the device has a texture/color camera.

Type	Envelop	Payload
Publish	v1.0/device/hasColor	Int Bool
Request Get	v1.0/device/hasColor	REQ: None REP: Int Bool

Discovery

Whether the device has a discovery module.

Type	Envelop	Payload
Publish	v1.0/device/hasDiscovery	Int Bool
Request Get	v1.0/device/hasDiscovery	REQ:None REP: Int Bool

Firmware upgradable

Whether there is a new version of firmware for your device.

Type	Envelop	Payload
Publish	v1.0/devce/firmwareUpgradable	Int Bool
Request Get	v1.0/device/firmwareUpgradable	REQ: None REP: Int Bool

PLE

Current PLE of your device.

Type	Envelop	Payload
Publish	v1.0/device/ple	String
Request Get	v1.0/device/ple	REQ: None REP: String

Device status

The current status of the device. There are two status currently:

- `"DS_OFFLINE"`: The device is not connected to your computer or its power is off.
- `"DS_ONLINE"`: The device is well connected.

Type	Envelop	Payload
Publish	v1.0/device/status	String
Request Get	v1.0/device/status	REQ: None REP: String

Device events

Tips: If you want to use the "Plus" or "Sub" button properly, you must double click the "Start" button before pressing the button. This means that if you want to send an event function pressed by the "Plus" or "Sub" button, you must double-click the "Start" button and then press the "Plus" or "Sub" button, otherwise your event will not be sent.

The 2X series camera carries several buttons. This interface broadcasts the button events. There are four events currently:

- `"DE_DOUBLECLICK"`: The start button is double clicked.
- `"DE_CLICK"`: The start button is clicked once.
- `"DE_PLUS"`: The plus button is clicked.
- `"DE_SUB"`: The sub button is clicked.

Type	Envelop	Payload
Publish	v1.0/devce/event	String

Enter calibration

Ask the SDK to enter the calibration mode.

Type	Envelop	Payload
Request	v1.0/cali/enter	REQ: None REP: Int Bool

Asynchronous signals will be emitted. The async action is `"AAT_ENTER_CALI"`.

The beginning and finishing `props` are both empty, and there is no `progress` signal.

Exit calibration

Ask the SDK to exit the calibration mode.

Type	Envelop	Payload
Request	v1.0/cali/exit	REQ: None REP: Int Bool

Asynchronous signals will be emitted. The async action is `"AAT_EXIT_CALI"`.

The beginning and finishing `props` are both empty, and there is no `progress` signal.

Calibration time

Get the last (or current used) calibration time, using the epoch of seconds starting from Jan 1st, 1970.

Type	Envelop	Payload
Publish	v1.0/cali/time	Int LL
Request Get	v1.0/cali/time	REQ: None REP: Int LL

Snap enabled

Whether to start the calibration capturing.

Type	Envelop	Payload
Publish	v1.0/cali/snapEnabled	Int Bool
Request Get	v1.0/cali/snapEnabled	REQ: None REP: Int Bool
Request Set	v1.0/cali/snapEnabled/set	REQ: Int Bool REP: Int Bool

The reply of request set denotes whether the setting action is successful.

Calibration type

Get or set the current calibration type. There are 4 different calibration type at most currently:

- `"CT_STEREO"`: The stereo calibration, which is the most important and necessary calibration for normal usage.
- `"CT_HD"`: HD calibration.
- `"CT_WHITE_BALANCE"`: White balance calibration.
- `"CT_DEFINITION"`: The accuracy definition calibration.

Type	Envelop	Payload
Publish	v1.0/cali/type	String
Request Get	v1.0/cali/type	REQ: None REP: String
Request Set	v1.0/cali/type/set	REQ: String REP: Int Bool

The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "CT_STEREO" // the current calibration type
}
```

The finishing `props` has the following definition:

```
{
    "type": "CT_STEREO" // the current calibration type
}
```

There is no `progress` signal.

Calibration group

Get or set the current calibration group for the current calibration type. For example, there 5 groups for stereo calibration, all of which need snapping.

Type	Envelop	Payload
Publish	v1.0/cali/currentCaliGroup	Int
Request Get	v1.0/cali/currentCaliGroup	REQ: None REP: Int
Request Set	v1.0/cali/currentCaliGroup/set	REQ: Int REP: Int Bool

The reply of request set denotes whether the action is successful.

Calibration distance

Get the current calibration distance. Note: it is not the real distance between the camera and the calibration board, but it's the index of the distance gauges (it's better to refer to the calibration UI of EXScan Pro®.)

Type	Envelop	Payload
Publish	v1.0/cali/currentCaliDist	Int
Request Get	v1.0/cali/currentCaliDist	REQ:None REP: Int

Calibration distance states

Get the current calibration distance states for the current calibration group. It's better to refer to the calibration UI of EXScan Pro®.

Type	Envelop	Payload
Publish	v1.0/cali/caliDistStates	JSON
Request Get	v1.0/cali/caliDistStates	REQ:None REP: JSON

The JSON definition is as below:

```
{
    "states": [true, true, false, false, true]
}
```

Note: The number of elements of `states` depends on the corresponding calibration type.

Scan type

Get the current scanning type. There are 3 different types currently:

- `"ST_FIXED"`: Fix mode scanning.
- `"ST_HD"`: HD scanning.
- `"ST_RAPID"`: Rapid mode scanning.

Type	Envelop	Payload
Publish	v1.0/scan/type	String
Request Get	v1.0/scan/type	REQ: None REP: String

Scan sub-type

Get or set scan sub-type. Some scanning type has sub types. There are 2 different types currently:

- `"SST_FIXED_FREE"`: Free style for fix scanning.
- `"SST_FIXED_TURNABLE"`: Turnable style for fix scanning.

Type	Envelop	Payload
Publish	v1.0/scan/subType	String
Request Get	v1.0/scan/subType	REQ: None REP: String
Request Set	v1.0/scan/subType/set	REQ: String REP: Int Bool

The reply of request set denotes whether the action is successful.

Path of last saved project

Get the absolute path of last saved project.

Type	Envelop	Payload
Publish	v1.0/scan/lastProjectSavePath	String
Request Get	v1.0/scan/lastProjectSavePath	REQ: None REP: String

Path of current project

Get the absolute path of current project.

Type	Envelop	Payload
Publish	v1.0/scan/currentProjectPath	String
Request Get	v1.0/scan/currentProjectPath	REQ: None REP: String

Has turnable

Get or set whether this fix scanning is connected to a turnable.

Type	Envelop	Payload
Publish	v1.0/scan/hasTurnable	Int Bool
Request Get	v1.0/scan/hasTurnable	REQ: None REP: Int Bool
Request Set	v1.0/scan/hasTurnable/set	REQ: Int Bool REP: Int Bool

The reply of request set denotes whether the action is successful.

Scan with texture

Get or set whether this scanning is with texture. It can only be enabled when a texture camera module is equipped.

Type	Envelop	Payload
Publish	v1.0/scan/withTexture	Int
Request Get	v1.0/scan/withTexture	REQ: None REP: Int
Request Set	v1.0/scan/withTexture/set	REQ: Int Bool REP: Int Bool

The reply of request set denotes whether the action is successful.

Point distance range

Get the point distance (i.e. resolution) range.

Type	Envelop	Payload
Publish	v1.0/scan/pointDistRange	JSON
Request Get	v1.0/scan/pointDistRange	REQ:None REP: JSON

The JSON definition is below:

```
{
    "min": 0.2,
    "max": 1.0
}
```

Predefined resolution values

Get the predefined resolution values (i.e. point distances).

Type	Envelop	Payload
Publish	v1.0/scan/resolutionValues	JSON
Request Get	v1.0/scan/resolutionValues	REQ:None REP: JSON

The JSON definition is below:

```
{
    "high": 1.0,
    "mid": 0.5,
    "low": 1.0
}
```

Framerate

Get the framerate.

Type	Envelop	Payload
Publish	v1.0/scan/framerate	Int
Request Get	v1.0/scan/framerate	REQ:None REP: Int

Point count

Get the total point count while scanning.

Type	Envelop	Payload
Publish	v1.0/scan/pointCount	Int
Request Get	v1.0/scan/pointCount	REQ:None REP: Int

Marker count

Get the count of markers while scanning.

Type	Envelop	Payload
Publish	v1.0/scan/markerCount	Int
Request Get	v1.0/scan/markerCount	REQ:None REP: Int

Triangle count in fix mode

Get all the triangle count in fix mode scanning.

Type	Envelop	Payload
Publish	v1.0/scan/pointFaceCount	Int
Request Get	v1.0/scan/pointFaceCount	REQ:None REP: Int

Triangle count of wrapped mesh

Get the total triangle count of wrapped mesh.

Type	Envelop	Payload
Publish	v1.0/scan/triangleCount	Int
Request Get	v1.0/scan/triangleCount	REQ:None REP: Int

Frame memory

Get the speculated frame count and the memory size needed for each frame. It is emitted before the global optimization in handled rapid mode. User should make sure that current computer condition is capable to handle this.

Type	Envelop	Payload
Publish	v1.0/scan/frameMemory	JSON
Request Get	v1.0/scan/frameMemory	REQ:None REP: JSON

The JSON definition is below:

```
{
    "count": 10,  // the speculated frame count
    "memory": 100 // the speculated memory size for each frame (MB)
}
```

Camera position

Get the camera position while scanning. The position is represented using look at manner.

Type	Envelop	Payload
Publish	v1.0/scan/cameraPosition	JSON
Request Get	v1.0/scan/cameraPosition	REQ:None REP: JSON

The JSON definition is as below:

```
{
    "center": [0, 0, 0],
    "position": [1, 0, 0],
    "up": [0, 0, 1],
    "boundBox": false // if true, the renderer needs to calculate the RT according to the
                      // scene data while keeping the center unchanged (effectively
                      // ignoring the position and up). Usually in fix mode
}
```

Scan with global markers

Whether it is using global markers for scanning.

Type	Envelop	Payload
Publish	v1.0/scan/globalMarker	Int Bool
Request Get	v1.0/scan/globalMarker	REQ: None REP: Int Bool

Current brightness

Get or set the current scanning brightness. The value will be changed according to different scanning types.

Type	Envelop	Payload
Publish	v1.0/scan/currentBrightness	Int
Request Get	v1.0/scan/currentBrightness	REQ: None REP: Int
Request Set	v1.0/scan/currentBrightness/set	REQ: Int REP: Int Bool

The reply of request set denotes whether the action is successful.

Brightness range

Get the range for brightness that can be set on the camera.

Type	Envelop	Payload
Publish	v1.0/scan/brightnessRange	JSON
Request Get	v1.0/scan/brightnessRange	REQ:None REP: JSON

The JSON definition is below:

```
{
    "min": 0,
    "max": 10
}
```

Point count in wrapped mesh

Get the point count in the wrapped mesh.

Type	Envelop	Payload
Publish	v1.0/scan/meshPointCount	Int
Request Get	v1.0/scan/meshPointcount	REQ:None REP: Int

HDR

Whether current scanning is HDR capable.

Type	Envelop	Payload
Publish	v1.0/scan/isHDR	Int Bool
Request Get	v1.0/scan/isHDR	REQ:None REP: Int Bool

Use discovery

Whether current scanning is using the discovery module.

Type	Envelop	Payload
Publish	v1.0/scan/useDiscovery	Int Bool
Request Get	v1.0/scan/useDiscovery	REQ:None REP: Int Bool

Has light box

Whether current scanning is using the light box.

[Todo] needs more explanation...

Type	Envelop	Payload
Publish	v1.0/scan/hasLightBox	Int Bool
Request Get	v1.0/scan/hasLightBox	REQ:None REP: Int Bool

Light box open

Whether the light box is opened.

Type	Envelop	Payload
Publish	v1.0/scan/lightBoxOpen	Int Bool
Request Get	v1.0/scan/lightBoxOpen	REQ:None REP: Int Bool

Has mesh data

Whether has mesh data.

[Todo] needs more explanation...

Type	Envelop	Payload
Publish	v1.0/scan/hasMeshData	Int Bool
Request Get	v1.0/scan/hasMeshData	REQ:None REP: Int Bool

Scan alignment type

Get the scan alignment type. There are 8 align types currently:

- `"AT_FEATURES"`: Use features to do alignment.
- `"AT_MARKERS"`: Use markers to do alignment.
- `"AT_HYBRID"`: For each frame, the device automatically choose features or markers to do alignment.
- `"AT_AUTO"`: The device automatically choose features or markers according to the very first frame, then it uses this type to do all the alignment.
- `"AT_TURTABLE"`: Use the turnable axis to do alignment in fix mode. Note: it's TUR**T**ABLE not TUR**N**ABLE. It's a historical typo, which should be hopefully corrected in the next version.
- `"AT_CODE_POINT"`: Use special code markers to do alignment.
- `"AT_GLOBAL_POINT"`: Use global markers to do alignment.

Type	Envelop	Payload
Publish	v1.0/scan/alignType	String
Request Get	v1.0/scan/alighType	REQ:None REP: String

Scan status

Get the current scanning status. There 5 different status currently:

- `"SS_PRE_SCAN"`: The initial status.
- `"SS_PRE_SCANNING"`: The prescanning status.
- `"SS_SCAN"`: The scanning status.
- `"SS_PAUSED"`: The scanning is paused.
- `"SS_SCAN_STOPED"`: The scanning is stopped. Note: it's STOP**ED** not STOP**PED**. It's a historical typo, which should be hopefully corrected in the next version.

Type	Envelop	Payload
Publish	v1.0/scan/status	String
Request Get	v1.0/scan/status	REQ: None REP: String

Scan distance

Get the current scanning distance. It's not the real distance but an evaluating integar with the following meaning:

- -1: Too near, the camera needs pulling away.
- 1~10: Acceptable distance.
- 100: Too far, the camera needs putting closer.

Type	Envelop	Payload
Publish	v1.0/scan/dist	Int
Request Get	v1.0/scan/dist	REQ: None REP: Int

Rapid mode of EP

Whether the scanning is in rapid mode. It is only meaningful for EP.

[Todo] what is rapid mode...

Type	Envelop	Payload
Publish	v1.0/scan/rapidMode	Int Bool
Request Get	v1.0/scan/rapidMode	REQ: None REP: Int Bool

Rapid save of EP

Whether it is capable of rapid saving. It is only meaningful for EP.

[Todo] what is rapid save...

Type	Envelop	Payload
Publish	v1.0/scan/rapidSave	Int Bool
Request Get	v1.0/scan/rapidSave	REQ: None REP: Int Bool

Enter scan

Ask the SDK to enter the certain type of scan. There are 3 different scan types currently, as stated previously Scan type.

Type	Envelop	Payload
Request	v1.0/scan/enterScan	REQ: String REP: Int Bool

The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` and finishing `props` are both empty, and there is no `progress` signal.

Exit scan

Ask the SDK to exit from current scanning.

Type	Envelop	Payload
Request	v1.0/scan/exitScan	REQ: None REP: Int Bool

The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` and finishing `props` are both empty, and there is no `progress` signal.

Create new project

Create new project with necessary parameters.

Type	Envelop	Payload
Request Get	v1.0/scan/newProject	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The request JSON definition is below:

```
{
    "path": "c:/a",               // Where to create the project
    "globalMarkerFile": "c:/b.p3",// The absolute global marker file path if used
    "textureEnabled": false,      // Whether texture is enabled
    "pointDist": 0.5,             // The point distance/definition
    "alignType": "AT_FEATURES",   // The alignment type
    "rapidMode": false,           // Whether it's EP rapid mode
    "fastSave": false             // Whether it's EP fast save mode
}
```

Note: 1.the project can only be created **after** entering a certain type of scanning. So developers should call entering scan before calling this interface. 2. About the markers data, you should create the project with scan align type `MT_FEATURE`. The marker data will change after pressing the button named refresh when you set the project type as `MT_MARKER`.

Asynchronous signals will be emitted.

The beginning `props` and finishing `props` are both empty, and there is no `progress` signal.

Open project

Open an existing project.

Type	Envelop	Payload
Request Get	v1.0/scan/openProject	REQ: String REP: Int Bool

The request payload is the absolute path of the project. The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` is empty.

The finish `props`'s definition is:

```
{
    "pointCount": 1000,// The point count of the model
    "hasTexture": true // Whether this project contains texture
}
```

There is no `progress` signal.

Control scanning (pre/start/pause/resume)

Ask the SDK to pre/start/pause/resume scanning with specified parameters.

Type	Envelop	Payload
Request	v1.0/scan/control	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The JSON definition is:

```
{
    "action": "pre",                    // Action type
    "params":{
        "enableHDR": false,             // Whether HDR should be enabled
        "alignType": "AT_FEATURES",     // The alignment type
        "subScanType": "SST_FIXED_FREE",// Sub scan type
        "turntableTimes": 10            // The turn times in fix mode
    }
}
```

The `params` is only necessary when the scanning type is fix mode, otherwise it can be left empty.

There are 3 different actions currently:

- `"pre"`: start pre-scanning. Point cloud will be generated however it will not be saved to the actual scanning data.
- `"start"`: start or resume the real scanning.
- `"pause"`: pause the scanning.

`"pre"` action is only available in HD mode & rapid mode, i.e. fix mode has no `"pre"` action.

For fix mode scanning, `"pause"` is only available when it contains turnable.

The `alignType` can be referred to Scan alignment type, and `subScanType` can be referred to Scan sub-type.

Asynchronous signals will be emitted. The async action type is `"AAT_SCAN"`.

Both the beginning and finishing `props`'s definitions are:

```
{
    "fixScan": false,// Whether it is fix mode
    "status": "SS_PRE_SCAN"// Current scanning state
}
```

There is no `progress` signal.

The `status` means the current scanning status on the device before the async action actually performs.

End scanning

Ask the SDK to end current scanning.

Type	Envelop	Payload
Request	v1.0/scan/endScan	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The JSON definition is:

```
{
    "globalOptimize": true,// Whether perform global optimize
    "pointDist": 0.5,// Point distance
    "rebuildData": false// Whether rebuild is required [Todo] Need more explanation.
}
```

Asynchronous signals will be emitted. The async action type is `"AAT_SCAN"`.

Both the beginning and finishing `props`'s are empty, and there is no `progress` signal.

Cancel scanning

Ask the SDK to cancel current scanning.

Type	Envelop	Payload
Request	v1.0/scan/cancelScan	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The JSON definition is:

```
{
    "dataNames": ["wholePointCloud"]// Shared memory names which need clearing
}
```

Asynchronous signals will be emitted. The async action type is `"AAT_SCAN"`.

The beginning `props` is empty, and the finish `props` is:

```
{
    "turntableScanCancel": false// [Todo] Need explanation
}
```

There is no `progress` signal.

No markers detected

Emitted when there are no markers detected for current scanning.

Type	Envelop	Payload
Publish	v1.0/scan/noMarkerDetected	Int Bool
Request Get	v1.0/scan/noMarkerDetected	REQ: None REP: Int Bool

Too flat

Emitted when current model being scanned is too flat to do alignment.

Type	Envelop	Payload
Publish	v1.0/scan/tooFlat	Int Bool
Request Get	v1.0/scan/tooFlat	REQ: None REP: Int Bool

Track lost

Emitted when the tracking is lost for current scanning.

Type	Envelop	Payload
Publish	v1.0/scan/trackLost	Int Bool
Request Get	v1.0/scan/trackLost	REQ: None REP: Int Bool

Manual align

Ask the SDK to manual align the point clouds. It is only available under fix mode scanning.

Type	Envelop	Payload
Request	v1.0/scan/manualAlign	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The JSON definition is:

```
{
    "firstPointClouds": ["a", "b", "c"],// The first group of point clouds
    "firstRefPoints":[                  // The reference points on the first group
        {"x": 0, "y": 0, "z": 0},
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ],
    "secondPointClouds": ["d", "e", "f"],// The second group of point clouds
        "firstRefPoints":[              // The reference points on the second group
        {"x": 0, "y": 0, "z": 0},
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ]
}
```

Asynchronous signals will be emitted. The async action type is `"AAT_MANUAL_ALIGN"`.

The beginning `props` and finish `props`'s definition are both empty, and there is no `progress` signal.

Last mesh type

Get the mesh type of last wrapping operation. There are 2 different mesh types currently:

- `"MT_NON_WATERTIGHT"`: Non watertight mesh, it means the algorithm won't try to fill very large holes while wrapping and the model will remain open.
- `"MT_WATERTIGHT"`: Watertight mesh, means it algorithm will try to fill every hole while wrapping.

Type	Envelop	Payload
Publish	v1.0/scan/lastMeshType	String
Request Get	v1.0/scan/lastMeshType	REQ: None REP: String

Mesh/Wrap the point cloud

Ask the SDK to mesh/wrap the current point cloud.

Type	Envelop	Payload
Request	v1.0/scan/mesh	REQ: JSON REP: Int Bool

The JSON definition is:

```
{
    "type": "MT_NON_WATERTIGHT",// The mesh type required
    "resolution": "mid"         // The resolution for the mesh
}
```

There are 2 different mesh type currently, please refer to Last mesh type. And there are 3 different resolutions currently, please refer to Predefined resolution values.

Asynchronous signals will be emitted. The async action type is `"AAT_MESH"`.

The beginning `props` and finish `props` are both empty

There is `progress` signal, so developers can connect to the signal to get the process state.

Last degree of mesh detail

Get degree of mesh detail of last saved project.

Type	Envelop	Payload
Publish	v1.0/scan/lastMeshDetail	Int
Request Get	v1.0/scan/lastMeshDetail	REQ: None REP: Int

Last simplification params

Get parameters of last simplification operation.

Type	Envelop	Payload
Publish	v1.0/scan/lastSimplifyParams	JSON
Request Get	v1.0/scan/lastSimplifyParams	REQ: None REP: JSON

The JSON definition is below:

```
{
    "faceCount": 1000,        // triangle count
    "vertexCount": 2000,      // vertex count
    "needSmoothing": true,    // whether smoothing is needed
    "needSharping": false,    // whether sharping is needed
    "highQualityExtend": true,// whether texture extending is needed
    "fillMarkerHole": true,   // whether marker holes should be filled
    "fillPlainHole": true,    // whether normal/plain holes should be filled
    "fillHolePerimeter": 3.0, // perimeter for plain holes to be filled
    "simplifyRatio": 10       // 0 - 100
}
```

Last resize params for saving

Get parameters of resize in last saving operation. It can be used to retrieve the predicted results if the mesh is scaled under a certain ratio.

Type	Envelop	Payload
Publish	v1.0/scan/lastSaveResizeParams	JSON
Request Get	v1.0/scan/lastSaveResizeParams	REQ: None REP: JSON

The JSON definition is below:

```
{
    "dimensions": [1.0, 1.0, 1.0],// dimensions for x, y, z
    "vertexCount": 1000,          // vertex count
    "resizeRatio": 0.1            // scale ration
}
```

Save mesh to disk

Ask the SDK save/export corresponding formats to the disk.

Type	Envelop	Payload
Request	v1.0/scan/save	REQ: JSON REP: Int Bool

The reply of request set denotes whether the action is successful.

The JSON definition is below:

```
{
    "path": "C:/abc",  // The directory where the exported files are stored
    "resizeRatio": 0.1,// The resize ratio
    "p3": true,        // Whether p3 format is exported
    "asc": true,       // Whether asc format is exported
    "sasc": true,      // Whether sasc format is exported
    "stl": true,       // Whether stl format is exported
    "obj": true,       // Whether obj format is exported
    "ply": true,       // Whether ply format is exported
    "3mf": true,       // Whether 3mf format is exported
}
```

Asynchronous signals will be emitted. The async action type is `"AAT_SAVE"`.

The beginning `props` and finish `props` are both empty, and there is no `progress` signal.

Export sharable data

Ask the SDK to export sharable data so that the user can share to other platforms like Sketchfab or SolidEdge.

There are 2 different platforms currently:

- `"sketchfab"`
- `"solidedge"`

Type	Envelop	Payload
Request	v1.0/scan/exportFile	REQ: String REP: Int Bool

The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted. The async action type is `"AAT_EXPORT_SHARE_DATA"`.

The beginning `props` is both empty. The finish `props`'s definition is:

```
{
    "filePath": "c:/abc.stl"// The exported file path
}
```

There is no `progress` signal.

Update Firmware

Get the state whether needing to update the firmware.

Type	Envelop	Payload
Request Get	v1.0/device/updatefirm	REQ:None REP: Int

Mesh data has marker

Get the state whether mesh data has marker.

Type	Envelop	Payload
Request Get	v1.0/scan/meshDataHasMarker	REQ:None REP: Int

Is mesh data water tight

Get the state whether mesh data is water tight.

Type	Envelop	Payload
Request Get	v1.0/scan/isMeshDataWaterTight	REQ:None REP: Int

Smooth

Smooth the mesh data after the mesh operation.

Type	Envelop	Payload
Request Get	v1.0/scan/smooth	REQ:JSON REP: Int

The JSON definition is as below:

```
{
    "level": 1, //0 high 1 mid 2 low
    "scale": 100, //scale range from 0 to 100
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_SMOOTH",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_SMOOTH",
    "result": "no error",
    "props": "",
}
```

Sharp

Sharp the mesh data after the mesh operation.

Type	Envelop	Payload
Request Get	v1.0/scan/sharp	REQ:JSON REP: Int

The JSON definition is as below:

```
{
    "level": 2, //0 high 1 mid 2 low
    "scale": 70, //scale range from 0 to 100
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_SHARP",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_SHARP",
    "result": "no error",
    "props": "",
}
```

Zoom

Zoom the mesh data after the mesh operation.

Type	Envelop	Payload
Request Get	v1.0/scan/zoom	REQ:JSON REP: Int

The JSON definition is as below:

```
{
    "level": 1, //0 high 1 mid 2 low
    "scale": 70, //scale range from 0 to 100
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_ZOOM",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_ZOOM",
    "result": "no error",
    "props": "",
}
```

Edit fill hole

edit fill hole after mesh the scan data.

Type	Envelop	Payload
Request Get	v1.0/scan/editFillHole	REQ:JSON REP: Int

The JSON definition is as below:

```
{
    "fileDataType": 1,
    "level": 1,
    "num": 2,
    "markerFlag": true,
    "perimeter": 2.7,
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_FILLING_HOLE",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_FILLING_HOLE",
    "result": "no error",
    "props": "",
}
```

Apply fill hole

Enter applying fill hole after mesh the scan data.

Type	Envelop	Payload
Request Get	v1.0/scan/applyFillHole	REQ:None REP: Int

```
{
    "holeList": [1,2,3],
    "fileDataType": 1,
    "level": 1,
    "num": 2,
    "markerFlag": true,
    "perimeter": 2.7,
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_APPLAY_FILLHOLE",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_APPLAY_FILLHOLE",
    "result": "no error",
    "props": "",
}
```

Load model

Enter Loading the model operation. Now only support to load .obj and .stl modle.

Type	Envelop	Payload
Request Get	v1.0/scan/loadModel	REQ: String REP: Int

The request payload is the absolute path of the model. The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_LOAD_MODEL",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_LOAD_MODEL",
    "result": "no error",
    "props": "",
}
```

Get all hole info

To get infomation about all hole.

Type	Envelop	Payload
Request Get	v1.0/scan/getAllHoleInfo	REQ:None REP: Int

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_ENTER_FILL_HOLE_MODE",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_ENTER_FILL_HOLE_MODE",
    "result": "no error",
    "props": "",
}
```

Request data

Client use this interface to inform server to request data.

Type	Envelop	Payload
Request Get	v1.0/scan/requestData	REQ:None REP: Int

Read data end

Client use this interface to inform server to end reading data.

Type	Envelop	Payload
Request Get	v1.0/scan/readDataEnd	REQ:None REP: Int

Enter post data process

To use this interface to enter post data process.

Type	Envelop	Payload
Request Get	v1.0/scan/enterPostDataProcess	REQ:None REP: Int

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_ENTER_POSTDATAPROCESS",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_ENTER_POSTDATAPROCESS",
    "result": "no error",
    "props": "",
}
```

Exit post data process

To use this interface to exit post data process.

Type	Envelop	Payload
Request Get	v1.0/scan/exitDataPostProcess	REQ:None REP: Int

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_EXIT_POSTDATAPROCESS",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_EXIT_POSTDATAPROCESS",
    "result": "no error",
    "props": "",
}
```

Clear mesh data

To use this interface to clear mesh data.

Type	Envelop	Payload
Request Get	v1.0/scan/clearMeshData	REQ:None REP: Int

Rebuild texture map

To use this interface to rebuild texture map.

Type	Envelop	Payload
Request Get	v1.0/scan/rebuildTextureMap	REQ:bool REP: Int

The request payload is true or false. The reply of request set denotes whether the action is successful.

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_REBUILDTEXTURE",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_REBUILDTEXTURE",
    "result": "no error",
    "props": "",
}
```

Start post process mode

To use this interface to enter post process mode.

Type	Envelop	Payload
Request Get	v1.0/scan/startPostProcessMode	REQ:None REP: Int

Stop post process mode

To use this interface to stop post process mode.

Type	Envelop	Payload
Request Get	v1.0/scan/stopPostProcessMode	REQ:None REP: Int

Restore raw mesh data

To use this interface to restore raw mesh data.

Type	Envelop	Payload
Request Get	v1.0/scan/restoreRawMeshData	REQ:None REP: Int

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_RESTORE_RAW_MESH",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_RESTORE_RAW_MESH",
    "result": "no error",
    "props": "",
}
```

Cancel manul align

To use this interface to cancle manul alignment. This operation is only available under fix mode scanning.

Type	Envelop	Payload
Request Get	v1.0/scan/cancelManulAlign	REQ:JSON REP: Int

The JSON definition is:

```
{
    "names": ["a", "b", "c"],//the name of point cloud but only available under fix mode
scanning.
    "rotX":[
        {"x": 0, "y": 0, "z": 0},
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ],
    "rotY":[
        {"x": 0, "y": 0, "z": 0},
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ],
    "rotZ":[
        {"x": 0, "y": 0, "z": 0},
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ],
    "trans":[
        {"x": 0, "y": 0, "z": 0},
```

```
        {"x": 1, "y": 1, "z": 1},
        {"x": 2, "y": 2, "z": 2}
    ],
}
```

Asynchronous signals will be emitted.

The beginning `props` has the following definition:

```
{
    "type": "AAT_CANCEL_ALIGEN",
}
```

The finishing `props` has the following definition:

```
{
    "type": "AAT_CANCEL_ALIGEN",
    "result": "no error",
    "props": "",
}
```