SmartPot

COMPONENT TECHNICAL DOCUMENTATION

SmartPot-IoT-Python

Real Crop Firmware Engine

MicroPython firmware for ESP32 hardware and Wokwi simulation: sensor acquisition, LCD status interface, PWM actuator control, and MQTT v1 contract with TLS encryption.



DOCUMENT / DOCUMENTO
SmartPot-IoT-Python Documentation

VERSION / VERSIÓN
2.0 · November 2026

TEAM / EQUIPO
SmartPotTech

PROJECT / PROYECTO
smartpot.app

> **NOTE / NOTA**
> **Language / Idioma:** ---

Document Sheet

FIELD	VALUE
Project	SmartPot · smartpot.app
Component	SmartPot-IoT-Python
Version	2.0 · November 2026
Scope	Circuit, firmware modules, main loop, commands, telemetry and capabilities, secure connection, configuration, and tests
Platform Documentation	Technical documentation, project journey, software lifecycle, and global diagrams
Maintenance	Generated from `docs/` in this repository using `.github/docs/tools`; updated with each component change

CONTENTS · CONTENIDO

Contents / Contenido

1. Purpose
2. Component Architecture
3. Main Loop
4. Commands
5. Telemetry, Capabilities and Command Validation
6. Secure Connection
7. Configuration
8. Tests
9. Getting Started

PART I

The Component

1. Purpose

In Plain Terms

SmartPot-IoT-Python is the program running on the device of a **real crop**: an ESP32 with its sensors, actuators, and LCD display. It measures, displays, publishes readings to the SmartPot broker, and executes incoming commands while acknowledging each one. It makes no autonomous agronomic decisions—the API and the platform AI decide. The same firmware runs on a physical board or in Wokwi, and in both cases the crop is real to the platform; virtual crops, by contrast, are simulated by SmartPot-DataGenerator.

2. Component Architecture




Figure / Figura 1 · *SmartPot-IoT-Python por dentro*

COMPONENT	ESP32 PIN	REPORTED SCALE
DHT22 (air temperature and humidity)	GPIO 15	°C and %
Light sensor (potentiometer in Wokwi)	GPIO 34	0–2000 lux
pH sensor	GPIO 35	0–14
TDS sensor	GPIO 32	0–3000 ppm
Substrate moisture	GPIO 33	0–100 %
Water pump	GPIO 19	`WATER_PUMP`
UV light	GPIO 18	`UV_LIGHT`
Fan	GPIO 5	`FAN`
20×4 I2C LCD	SCL 16 · SDA 17	—

PART II

Operation

3. Main Loop




Figure / Figura 2 · *Ciclo principal del firmware*

4. Commands




Figure / Figura 3 · *Cómo atiende una orden*

5. Telemetry, Capabilities and Command Validation

- **Telemetry**: JSON v1 with six fields (`temperature`, `humidity`, `brightness`, `ph`, `tds`, `soilMoisture`). `brightness` and `tds` are integers; `ph` keeps two decimals and the rest one. Missing sensors are omitted, never sent as `null`.
- **Capabilities**: after `status=online` and before subscribing to `commands`, the client publishes a retained QoS 1 message on `.../capabilities`. It uses schema 1, declares firmware `smartpot-iot-python/2.0.0`, hardware `esp32-devkit-c-v4`, telemetry `json-v1` only, six sensors (no `atmosphere`) and three actuators (`WATER_PUMP`, `UV_LIGHT`, `FAN`). The payload stays under 2 KB; a publish failure does not block the command subscription.
- **Command ids**: `parse_command` requires `id` to be a non-empty string; null, booleans, numbers, lists and objects are rejected. `actuator` and `action` must be non-empty strings, and `durationSeconds` must be a non-negative integer or absent.
- **Deduplication**: `ActuatorBank` keeps the last 16 ids with their ACK. A QoS 1 redelivery repeats the stored ACK without toggling the pin; success and failure results are both cached.

6. Secure Connection

PARAMETER	VALUE
Broker	`mqtt.smartpot.app:8883`, MQTT over TLS 1.2 or newer
Certificate	Signed by SmartPot's internal CA; verified by the firmware using the public CA embedded in `config.json` under `BROKER["CA_CRT"]`
Username & Key	Crop ID and device key, shown once by the PWA upon creating the real crop or rotating the key
Client ID	`smartpot-<cropId>`
Status	Retained `online` upon connecting and `offline` as Last Will

> **WOKWI**
> Keep your copy of the project private: anyone who sees `config.json` can publish as your crop. If leaked, generate a new key from the Device tab.

PART III

Configuration & Testing

7. Configuration

The PWA generates `config.json` in its connection guide, containing the WiFi network (yours or `Wokwi-GUEST`), the crop's `SMARTPOT` block, and the `BROKER` block with the broker CA. `config.json` is untracked; `config.example.json` is the template, and the Rust firmware reads the same file when it is built.

KEY	PURPOSE
`WIFI.ssid`, `WIFI.password`	Network the ESP32 connects to
`SMARTPOT.crop_id`, `device_key`	MQTT credentials for the real crop
`SMARTPOT.host`, `port`, `tls`	Broker host, port, and TLS toggle
`BROKER.CA_CRT`	SmartPot public CA in PEM format used by the firmware to verify the broker certificate
`SMARTPOT.interval_seconds`	Seconds between readings (30 by default)

8. Tests

`uv run ruff check .` and `uv run pytest`: a 132-test CPython suite with simulated MicroPython modules covering the MQTT contract, integer telemetry, capabilities, strict command ids, 16-id deduplication and ACKs (with durations in seconds, minutes, or hours), timed actuator shutoff, sensor scaling, broker verification with the template CA, and TLS fallback for older MicroPython versions.

9. Getting Started

ENVIRONMENT	STEPS
Physical board	Wire the circuit, flash MicroPython 1.22.0 (1.23+ also works), copy `fs/` with `mpremote`, add your `config.json` (includes the CA), and power on
Wokwi in browser	Open the project, create `config.json` with the guide's block, and run; the `Wokwi-GUEST` network has Internet access
Local Wokwi	`uv sync`, start the simulation with `wokwi.toml`, and run `uv run python start.py`

