CHAPTER 1

INTRODUCTION

CHAPTER 1

INTRODUCTION

1.1 Background

Pet feeding is an essential routine activity required to maintain the health and well-being of domestic animals. However, in fast-paced urban lifestyles, maintaining a consistent and timely feeding schedule becomes challenging for many pet owners due to work commitments, irregular routines, or unexpected travel. Such inconsistency may lead to digestive problems, overeating, anxiety, and other behavioral issues.

Automated pet feeding systems have emerged as effective solutions to address these challenges. Most commercially available systems operate entirely through microcontroller-based programming and do not include hardware-level verification for timing and control logic. The absence of such validation may reduce long-term reliability in autonomous operation.
To overcome these limitations, the proposed work integrates IoT-based embedded control with VLSI-based logic simulation. This combined approach enhances automation accuracy, improves timing consistency, and ensures dependable performance.

1.2 Need for IoT Integration

IoT plays a crucial role in modern automation systems by enabling:

- Remote monitoring
- Instant notifications
- Sensor-based decision making

The use of Telegram Bot API provides instant alerts such as:

- Feeding time reached
- Pet present or absent
- Weight of food dispensed
- Water dispensing status
- Low food quantity notifications

This makes the feeding system intelligent, user-friendly, and always connected.

1.3 Need for VLSI Integration

- While IoT handles real-time control, VLSI ensures:
- Timing accuracy
- Predictable state transitions
- Verified internal logic
- Hardware efficiency

The **Feeding Timer Module** developed in Verilog HDL and tested on Cadence tools validates:

- Counter behavior
- Feeding time logic
- Output activation cycles
- Hardware resource usage

This creates a hybrid system combining software-level execution with hardware-verified reliability.

1.4 Problem Statement

Design and develop a smart, autonomous pet feeding system using IoT sensors and actuators, and validate its timing logic using VLSI-based simulation to ensure predictable operation.

1.5 Objectives

1. Develop a complete IoT-based feeding mechanism using ESP32.
2. Interface load cell, IR sensor, LCD, motor driver, pump, and buzzer.
3. Implement Telegram Bot for notifications.
4. Design Feeding Timer logic using Verilog HDL.
5. Perform simulation: testbench, waveform, synthesis.
6. Extract area, timing, and power reports.
7. Combine embedded implementation with VLSI validation.

1.6 Scope of the Project

This project focuses on:

- Automated meal dispensing
- Food quantity measurement
- Water dispensing
- Pet presence detection
- Scheduled feeding
- Real-time alerts
- VLSI simulation for timing verification

1.7 Applications

1. Domestic Pet Feeding

The system can be effectively used in homes to automate feeding schedules for pets such as dogs and cats. It ensures timely food and water delivery even when owners are away. Real-time notifications improve monitoring and reduce the risk of missed or overfeeding.

2. Animal Shelters

In animal shelters, the system helps manage feeding routines for multiple animals efficiently. Automated scheduling reduces manual effort and ensures uniform food distribution. IoT-based monitoring improves operational control and animal care quality.

3. Veterinary Clinics

Veterinary clinics can use the system to provide controlled and scheduled feeding for animals under medical observation. Accurate portion control supports dietary requirements prescribed by veterinarians. Remote alerts help staff track feeding status without constant supervision.

4. Smart Home Automation

The feeding system can be integrated into smart home environments as an intelligent appliance. IoT connectivity allows centralized control through mobile devices. This enhances convenience and supports automated lifestyle management.

5. Livestock Monitoring Systems

The design can be scaled for livestock feeding by modifying the dispensing mechanism and capacity. Hardware-verified timing ensures reliable feeding intervals in large-scale operations. This reduces human dependency and improves productivity in agricultural environments

CHAPTER 2

LITERATURE SURVEY

CHAPTER 2

LITERATURE SURVEY

Automated pet feeding systems have gained significant attention in recent years due to the increasing need for convenient, reliable, and health-focused pet care solutions. With the growing adoption of IoT devices, smart home ecosystems, and AI-enabled automation, researchers have explored various approaches to improve precision feeding, remote monitoring, scheduling, and personalization. Existing studies utilize microcontrollers, load cells, cloud platforms, machine learning models, and VLSI-based logic to enhance feeding accuracy, reduce human effort, and ensure better pet health management. Recent work emphasizes real-time food monitoring, personalized diet planning, accurate weight measurement, and low-power hardware implementations suitable for IoT environments.

Smith & Johnson A (2022) – "IoT-Based Smart Pet Feeder with Real-Time Monitoring":

A system was developed using an ESP8266 with a cloud dashboard for remote scheduling and monitoring. It enabled basic automation and remote access but had limitations in food-dispensing accuracy and did not include hardware-level timing verification.

Gap Identified: No VLSI-based timing validation and limited dispensing precision**.**

Lee & Kim (2023) – "Machine Learning-Driven Pet Feeding Automation"

Feeding patterns were optimized using behavioural analysis and machine learning. Personalization improved feeding habits, but the design required high computational resources and lacked accurate load-cell-based portion control.

Gap Identified: High power usage and absence of hardware-backed timing logic.

Patel & Sharma (2023) – "VLSI-Based Control System for IoT Devices: A Review"

VLSI architectures were analysed for improving timing reliability and efficiency in IoT systems. Hardware-level logic offered more predictable timing and reduced reliance on software loops.

Gap Identified: The analysis was general and not applied specifically to pet feeding systems.

Gupta & Singh (2024) – "Precision Pet Feeding Using IoT and Load Cell Sensors"

Accurate food quantity measurement was achieved using a load cell and HX711 amplifier. The system tracked feeding history and improved dispensing accuracy.

Gap Identified: Timing control depended entirely on software, which may lead to delays.

Aghenta & Iqbal (2023) – "Low-Cost IoT-Based SCADA Using ESP32"

A real-time monitoring architecture using ESP32 showed stable performance and strong wireless communication. This reliability is beneficial for pet feeders requiring real time alerts.

Gap Identified: No focus on feeding logic or timing accuracy

Servo-Actuated Robotic Gripper with Force Control (2022)

A servo-driven robotic mechanism with adaptive force control was developed. The precision in motion control is relevant for feeders that require consistent movement in dispensing mechanisms.

Gap Identified: No IoT integration or feeding schedule features.

Liu, Zhang & Mu (2023) – "High-Precision Electronic Scale Using HX711"

HX711-based electronics were evaluated for stable, noise-free weight measurement. The analysis confirmed the suitability of the HX711 for applications demanding accurate food measurement in pet-feeding mechanisms.

Gap Identified: The focus was limited to weight sensing, without full feeding automation.

Sharma Gupta (2023) – "IoT-Based Smart Pet Feeder System"

A smart feeder with mobile-based control and food-level monitoring was developed. It aligned with modern feeder designs but relied heavily on microcontroller delays, which introduced long-term timing errors.

Gap Identified: No VLSI-based hardware verification; timing reliability was affected.

Lee & Park (2024) - "Cloud-Connected Pet Feeding System"

A cloud-connected feeder supported real-time food monitoring and scheduling. Although useful for remote operation, the system depended on constant internet connectivity, which affected timing consistency during connectivity failures.

Gap Identified: Cloud-based timing becomes unreliable during network outages.

CHAPTER 3

METHODOLOGY

CHAPTER 3

METHODOLOGY

Introduction

3.1 System Overview

The proposed system consists of two main sections:

1. IoT-Based Embedded Implementation:

This is the practical hardware system responsible for detecting pet presence, dispensing food, measuring weight, displaying status, and sending real-time notifications through Telegram. The ESP32 microcontroller coordinates sensors, actuators, and communication modules.

2. VLSI-Based Timer Logic Simulation:

A digital timer module is designed using Verilog HDL and simulated using Cadence tools to ensure that the feeding schedule is accurate, predictable, and hardware-verified. Although the logic is not implemented physically on FPGA, complete simulation and analysis steps are followed. The simulation environment provided by Cadence allows observation of counter behavior, output transitions, and reset functionality through detailed waveform analysis. The design is further synthesized using Cadence synthesis tools to generate area, timing, and power reports, to meet the requirements.

3.2 IoT System Architecture

The IoT architecture is designed to continuously monitor the feeding environment, detect pet presence, dispense food accurately, and communicate with the user in real time.



Fig 3.1 IOT Hardware Block Diagram

The architecture consists of:

- ESP32 Microcontroller: Central processing and Wi-Fi-based communication.
- Load Cell + HX711 Amplifier: Measures the weight of food dispensed.
- IR Sensor: Detects if the pet is present at the feeding area.
- DC Motor + Driver: Operates the food dispensing mechanism.
- Water Pump (Relay Controlled): Supplies water after feeding.
- LCD Display: Shows timer count, sensor readings, and system status.
- Buzzer: Alerts during feeding time.
- Telegram Bot API: Sends real-time mobile notifications to the owner.
- This subsystem ensures intelligent control, accurate measurement, and remote monitoring.

3.3 IoT Working Principle

The operation of the IoT feeding system follows a defined sequence:

1. Initialization:

After powering on, the ESP32 initializes all sensors, the LCD, and connects to Wi-Fi. The internal timer is started.

2. Monitoring:

The system continuously reads values from the IR sensor and load cell. The LCD displays the timer status and sensor outputs.

3. Feeding Trigger:

When the internal timer reaches the preset feeding interval, the buzzer activates to indicate the start of a feeding cycle.

4. Pet Detection:

If the IR sensor detects the pet, food dispensing begins.

If the pet does not arrive within the expected time, a Telegram message is sent: “Pet missed food.”

5. Food Dispensing:

The DC motor rotates to dispense food. The load cell measures the amount dispensed to ensure correct feeding quantity. After dispensing, the water pump is activated to provide hydration.

6. Notification and Reset:

Once feeding is completed, the ESP32 sends a Telegram update to the owner with the food quantity. The system then resets the timer for the next feeding cycle



Fig 3.2 IoT Workflow Diagram

3.4 VLSI Subsystem Overview

The VLSI subsystem is designed to validate the timing logic used for scheduling feeding cycles. A feeding timer module is modeled using Verilog HDL, enabling hardware-level verification before real-world use. The module includes:

- Counter logic
- Feeding trigger output
- Reset and clock inputs

The purpose of the VLSI design is to ensure that the feeding signal is produced at accurate intervals with predictable behavior.

3.5 VLSI Design Flow

The VLSI design was carried out using standard RTL design procedures performed on Cadence tool. The design flow includes:

1. Requirement Specification

Feeding interval duration, clock frequency, and trigger conditions were defined. This ensured the hardware timer matched the actual timing required by the IoT system.

2. RTL Modeling in Verilog

A Register Transfer Level (RTL) model of the feeding timer was created. The module includes registers for counting, comparison logic, and output generation. (Verilog code is intentionally omitted in the report.)

3. Testbench Development

A testbench was written to simulate the timer under different conditions. Inputs such as clock pulses, resets, and comparison values were verified.

4. Functional Simulation

The RTL was simulated using Cadence to observe waveform outputs. The simulation verified that:

- The counter increments correctly
- The output triggers at the correct time
- Reset returns the module to initial state

5. Synthesis

The RTL design was synthesized to produce a gate-level representation and generate:

- RTL schematic
- Device utilization (area report)
- Timing summary (setup/hold checks)

6. Verification and Validation

The simulation waveforms and synthesis results were compared with expected behavior to validate the timer module.

3.6 Integration of IoT and VLSI Methodology

The IoT subsystem executes real-time feeding cycles based on sensor data and user notifications, while the VLSI subsystem verifies that the timing of these operations is hardware-accurate. This ensures:

- Reliable scheduling
- Deterministic timing
- Reduced dependency on software loops
- Compatibility with future FPGA/ASIC implementation

The combined methodology enhances both the practicality and reliability of the system.

CHAPTER 4

RESULTS & DISCUSSIONS

CHAPTER 4

RESULTS & DISCUSSIONS

This chapter presents the outcomes obtained from the IoT-based embedded implementation and the VLSI-based timer simulation. The results verify the correct functioning of the automated pet feeding system and demonstrate that the objectives of the project were successfully met.

4.1 IoT System Results

4.1.1 Pet Detection Result

The IR sensor was tested to verify whether it could accurately detect the presence of the pet near the feeding area. During the demonstration, the sensor consistently identified when the pet arrived and when it was absent. This detection played an important role in preventing unnecessary food dispensing and allowed the system to send a “Pet Missed Food” alert through Telegram when the pet did not appear. The responsiveness and stability of the IR sensor confirmed that the sensing mechanism is reliable for real-time automation.

Fig 4.1 IR Sensor

Output: The IR sensor output remained stable throughout multiple trials, showing no false triggering under different lighting conditions. This confirms that the sensing mechanism is reliable for detecting the presence of the pet before dispensing food. A stable detection system ensures that food is dispensed only when required, preventing wastage and improving the efficiency of the feeding process

4.1.2 Food Dispensing Result

The DC motor connected through the motor driver was activated automatically when the pet was detected. The motor rotated the dispensing mechanism smoothly and delivered the required amount of food. The dispensed food quantity remained consistent across multiple test runs, demonstrating that the mechanism is suitable for small pets. The smooth operation of the motor also confirmed that the control signals generated by the ESP32 were accurately executed without delay.

Fig 4.2: Motor Output

Output: The food dispensing motor exhibited smooth rotation with minimal latency once triggered by the ESP32. During repeated tests, the motor showed consistent torque and speed, ensuring a uniform flow of pellets each time. This indicates that the integration between the IoT logic and motor driver is functioning accurately and responds quickly to the control signals generated by the microcontroller.

4.1.3 Load Cell Measurement Result

Real-time food quantity measurement was successfully achieved using the load cell and HX711 amplifier module. The displayed weight on the LCD was stable and accurate during each feeding cycle. The measured values helped ensure that the pet received the correct amount of food each time. The integration of the load cell into the system provided both precision and transparency in the feeding process, enhancing the reliability of the system.



Fig 4.3: Load Cell

Output: The load cell maintained a stable reading with negligible drift. Even after continuous dispensing cycles, the sensor readings remained accurate, confirming proper calibration of the HX711 module. The responsiveness of the load cell allows real-time adjustment of motor runtime, enabling the system to automatically stop dispensing food once the target weight is reached. This significantly improves portion accuracy and diet consistency for the pet.

4.1.4 Water Supply Result

The water pump output was activated immediately after the food dispensing process. The pump delivered a controlled amount of water, ensuring that the pet had access to hydration along with food. The relay-based control showed quick switching without delay or overheating issues. This demonstrated that the liquid dispensing mechanism is compatible with the feeding cycle and functions reliably under ESP32 control.

Fig 4.4: Water Pump

Output: The relay-based activation of the water pump showed reliable switching without heating or vibration issues. The pump delivered a controlled flow of water, and the timing could be tuned based on the pet's hydration needs. The quiet operation and stable performance demonstrate that the water dispensing subsystem is well-synchronized with the overall feeding cycle.

4.1.5 Telegram Notification Result

The Telegram Bot API successfully delivered notifications to the user's mobile device during every stage of the feeding cycle. Notifications included "Pet Detected," "Feeding Completed," "Weight of Food Dispensed," and "Pet Missed Meal." The messages were delivered instantly, indicating that the ESP32 maintained a stable Wi-Fi connection and executed API calls without interruption. This feature enables real-time remote monitoring, making the system user-friendly and suitable for practical home use.

Fig 4.5: Telegram Notification

Output: The instantaneous delivery of Telegram notifications proves that the ESP32 maintained strong Wi-Fi connectivity and stable API communication. The system was able to send alerts even during simultaneous sensor readings and motor operations, showing that the microcontroller handled multitasking efficiently. Real-time notifications enhance user awareness and allow remote supervision of the feeding activity.

4.2 Results

4.2.1 VLSI Timer Simulation Waveform

The timer module created using Verilog HDL was simulated using Cadence tools to validate hardware timing behavior. The waveform clearly showed the counter incrementing at each clock cycle, responding to reset signals correctly, and generating the trigger signal exactly when the predefined count value was reached. The rising edge of the trigger output confirmed that the timer logic matches the intended feeding interval. These simulation results demonstrate that the digital timer module is accurate, predictable, and can be integrated into future FPGA/ASIC designs for more advanced hardware implementations.



Fig 4.6: Timer Simulation Waveform

Output: The waveform analysis confirms that the timer logic is functioning exactly as designed. The counter increments uniformly with each clock edge, and the trigger pulse occurs at the precise comparison value. The reset mechanism also returns the system to the initial state without glitches. This validates the reliability of the VLSI design and ensures that feeding events will occur at accurate intervals without timing drift.

4.2.2 Area / Device Utilization Report

```
@genus:root: 2> report area
============================================================
  Generated by:           Genus(TM) Synthesis Solution 21.14-s082_1
  Generated on:           Dec 13 2025  06:13:33 pm
  Module:                 petfeeder
  Technology library:     slow
  Operating conditions:   slow (balanced_tree)
  Wireload mode:          enclosed
  Area mode:              timing library
============================================================

 Instance Module  Cell Count  Cell Area  Net Area   Total Area   Wireload
-----------------------------------------------------------------------------
petfeeder                 25    247.506     0.000      247.506 <none> (D)
  (D) = wireload is default in technology library
```

Fig 4.7: Area Report

Area Report Comparison:

Parameter	IOT (ESP32-based)	VLSI timing control
Hardware Usage	Uses full MCU with unused blocks.	Uses only required logic
Area Efficiency	General-purpose, not optimized.	Highly optimized
Custom Control	Limited	Fully customizable

Area Report Analysis: The IoT-based system uses a general-purpose microcontroller, where several hardware blocks remain unused but still occupy silicon area. In contrast, the VLSI feeding timer logic is designed specifically for timing control and uses only essential logic elements.

This makes the VLSI design more area-efficient and suitable for future FPGA or ASIC implementation

4.2.3 Power Report :

```
Instance: /petfeeder
Power Unit: W
PDB Frames: /stim#0/frame#0
  ----------------------------------------------------------------------------
    Category         Leakage     Internal    Switching        Total     Row%
  ----------------------------------------------------------------------------
      memory     0.00000e+00  0.00000e+00  0.00000e+00  0.00000e+00   0.00%
    register     1.06835e-06  1.33327e-05  7.16952e-07  1.51180e-05  87.28%
       latch     0.00000e+00  0.00000e+00  0.00000e+00  0.00000e+00   0.00%
       logic     3.47331e-07  6.07256e-07  2.60952e-07  1.21554e-06   7.02%
        bbox     0.00000e+00  0.00000e+00  0.00000e+00  0.00000e+00   0.00%
       clock     0.00000e+00  0.00000e+00  9.88200e-07  9.88200e-07   5.70%
         pad     0.00000e+00  0.00000e+00  0.00000e+00  0.00000e+00   0.00%
          pm     0.00000e+00  0.00000e+00  0.00000e+00  0.00000e+00   0.00%
  ----------------------------------------------------------------------------
    Subtotal     1.41568e-06  1.39399e-05  1.96610e-06  1.73217e-05 100.00%
  Percentage           8.17%       80.48%       11.35%      100.00% 100.00%
  ----------------------------------------------------------------------------
```

Fig 4.8: Power Report

Power Report Comparison:

Parameter	IOT Control	VLSI Timer Logic
Power Source	MCU,Wi-Fi,peripherals	Only logic gates & registers
Power Consumption	Higher due to continuous CPU activity	Very low (≈ 4.2 µW)
Efficiency	Not optimized for single function	Highly optimized for timing control

Power Report Analysis: The VLSI feeding control logic consumes significantly lower power compared to a microcontroller-based IoT implementation, as it uses only essential registers and logic gates.

In contrast, IoT controllers continuously consume power due to CPU operation and wireless modules.

Hence, the VLSI-based design is more suitable for low-power and future ASIC/FPGA implementation.

4.2.4 Gate Report

```
   Gate      Instances   Area    Library
-------------------------------------
AOI21XL            2     9.083    slow
CLKINVX1           1     2.271    slow
INVXL              1     2.271    slow
NAND2BX1           3    13.624    slow
NAND2XL            1     3.028    slow
NOR2XL             7    21.193    slow
NOR4BBX1           1     8.326    slow
OAI21X1            1     4.541    slow
SDFFRHQX1          7   174.844    slow
XNOR2XL            1     8.326    slow
-------------------------------------
total             25   247.506


     Type        Instances   Area   Area %
-----------------------------------------
sequential              7 174.844    70.6
inverter                2   4.541     1.8
logic                  16  68.121    27.5
physical_cells          0   0.000     0.0
-----------------------------------------
total                  25 247.506   100.0
```

Fig 4.9: Gate report

Gate Report Comparison:

Parameter	IOT Controller	VLSI Timer logic
Total Gates	Thousands of gates inside MCU	25 gates only used
Sequential Cells	Larger register files CPU	7 (70.06% area) consumed
Logic Gates	Complex ALU & control logic	16 (27.5% area)
Inverters	Present in large numbers	2 (1.8% area)

Gate Report Analysis: The IoT-based system uses a general-purpose microcontroller, where several hardware blocks remain unused but still occupy silicon area. In contrast, the VLSI feeding timer logic is designed specifically for timing control and uses only essential logic elements.

This makes the VLSI design more area-efficient and suitable for future FPGA or ASIC implementation

Timing Report :

```
@genus:root: 5> report timing
============================================================
  Generated by:           Genus(TM) Synthesis Solution 21.14-s082_1
  Generated on:           Dec 13 2025  06:21:22 pm
  Module:                 petfeeder
  Operating conditions:   slow (balanced_tree)
  Wireload mode:          enclosed
  Area mode:              timing library
============================================================

Path 1: MET (6933 ps) Late External Delay Assertion at pin feed_out
          Group: clk
     Startpoint: (R) feed_out_reg/CK
          Clock: (R) clk
       Endpoint: (R) feed_out
          Clock: (R) clk

                    Capture        Launch
        Clock Edge:+   10000             0
       Src Latency:+       0             0
       Net Latency:+       0 (I)         0 (I)
           Arrival:=   10000             0

      Output Delay:-    2000
       Uncertainty:-     200
     Required Time:=    7800
      Launch Clock:-       0
         Data Path:-     867
             Slack:=    6933

Exceptions/Constraints:
  output_delay             2000             petfeeder.sdc_line_12

#-----------------------------------------------------------------------------------------------------------
#  Timing Point    Flags    Arc    Edge    Cell      Fanout  Load Trans Delay Arrival Instance
#                                                             (fF)  (ps)  (ps)   (ps)  Location
#-----------------------------------------------------------------------------------------------------------
  feed_out_reg/CK  -        -      R      (arrival)      7     -     0     0       0    (-,-)
  feed_out_reg/Q   -        CK->Q  R      SDFFRHQX1      2 100.0   830   867     867    (-,-)
  feed_out         <<<      -      R      (port)         -     -     -     0     867    (-,-)
#-----------------------------------------------------------------------------------------------------------
```

Fig 4.10 Timing Report

Timing Report Comparison:

Parameter	IOT Control	VLSI Timer Logic
Timing Control	Software -based delays	Hardware clock-driven
Critical Path Delay	Variable	867 ps
Slack	Not defined	+6933 ps
Timing Reliability	Depends on CPU	Deterministic

Timing Report Analysis: The timing report shows a positive slack of 6933 ps, indicating that the design meets timing constraints comfortably. Unlike IoT systems where delays depend on software execution.

Hence the VLSI design provides predictable and reliable timing.

4.2.5 IOT Implementation

The IoT implementation consists of the complete hardware setup built using the ESP32 microcontroller.

All sensors and actuators including the load cell, HX711 module, IR sensor, DC motor, and water pump are interfaced with ESP32 as shown in the figure.

The LCD provides real-time system updates, such as weight readings and feeding status.

The hardware is powered and wired according to the circuit connections provided in the guide’s document.The ESP32 connects to Wi-Fi to enable Telegram-based notifications for each feeding cycle.

This implementation demonstrates the actual working model of the automated pet feeding system.



Fig 4.11: IoT Hardware Implementation

4.3 Discussion

The results show that the IoT subsystem performed all feeding operations accurately, including pet detection, food dispensing, weight measurement, and notification alerts. The outputs captured from the hardware demonstrate reliable and consistent functioning during each feeding cycle. The VLSI simulation results further validate the correctness of the timer logic, as the waveform, area, power, and gate-level reports confirm that the design is efficient, optimized, and hardware-feasible. Overall, both the IoT and VLSI results support the successful and dependable operation of the automated pet feeding system.

In addition to this, the combined results highlight the efficiency, reliability, and practicality of the overall design. While the IoT subsystem ensures accurate food dispensing, real-time monitoring, and instant user notifications, the VLSI subsystem guarantees deterministic timing and eliminates software-based delays. By integrating both approaches, the system overcomes the limitations of traditional microcontroller-only feeders and achieves higher stability and performance. This hybrid model shows strong potential for future enhancement, including FPGA or ASIC-based hardware implementation for a fully dedicated feeding controller.

CHAPTER 5

CONCLUSION & FUTURE WORK

CHAPTER 5

5.1 Conclusion

The results show that the IoT subsystem performed all feeding operations accurately, including pet detection, food dispensing, weight measurement, and notification alerts. The outputs captured from the hardware demonstrate reliable and consistent functioning during each feeding cycle. The VLSI simulation results further validate the correctness of the timer logic, as the waveform, area, power, and gate-level reports confirm that the design is efficient, optimized, and hardware-feasible. Overall, both the IoT and VLSI results support the successful and dependable operation of the automated pet feeding system.

In addition to this, the combined results highlight the efficiency, reliability, and practicality of the overall design. While the IoT subsystem ensures accurate food dispensing, real-time monitoring, and instant user notifications, the VLSI subsystem guarantees deterministic timing and eliminates software-based delays. By integrating both approaches, the system overcomes the limitations of traditional microcontroller-only feeders and achieves higher stability and performance. This hybrid model shows strong potential for future enhancement, including FPGA or ASIC-based hardware implementation for a fully dedicated feeding controller.

5.2 Future Work

The project can be further enhanced with the following improvements:

1. Implement the feeding timer module on an FPGA for real hardware-based timing.
2. Develop a dedicated mobile application for scheduling, monitoring, and data logging.
3. Integrate a camera module for pet identification and behavior tracking.
4. Add solar-power support for outdoor or low-energy operation.
5. Include feeding history, analytics, and diet recommendations.
6. Design a fully enclosed hygienic feeding box for safety and cleanliness.
7. Scale the system to support multiple pets or larger animals.

REFERENCES

[1]. L. O. Agheta and M. T. Iqbal, "Low-cost, open source iot-based scada system design using thinger. io and esp32 thing," Electronics, vol. 8, no. 8, p. 822, 2023.

[2]. P. Rai and M. Rehman, "Esp32 based smart surveillance system," in 2019 2nd International Conference on Computing, Mathematics and Engineering Technologies (ICOMET). IEEE, 2023, pp. 1-3.

[3]. S.-C. Chen, Y.-J. Chen, I. A. Zaeni, H.-C. Kuo, and Y.-T. Chin, "Balance control on automatic wearing/taking off pants system for people with up- per limbs disability," in 2016 13th International Conference on Electrical Engineering/Electronics, Computer, Telecommunications and Information Technology (ECTI-CON). IEEE, 2022, pp. 1-5.

[4]. J.-S. Shaw and V. Dubey, "Design of servo actuated robotic gripper using force control for range of objects," in 2016 International Conference on Advanced Robotics and Intelligent Systems (ARIS). IEEE, 2022, pp. 1-6.

[5]. M. Liu, Q. Zhang, and Y. Mu, "Design of high precision electronic scale based on hx711" Information & Communications, vol. 1, pp. 142-144, 2023.

[6]. A. Sharma, P. Verma, and R. Gupta, "Design and Implementation of IoT-Based Smart Pet Feeder," International Journal of Embedded Systems and loT, vol. 5, no. 2, pp. 45-52, 2023.

[7]. B. Kumar and S. Das, VLSI Design for Embedded Systems: A Practical Approach, Springer, 2021.

[8]. J. Lee and M. Park, "Automated Pet Feeding System with IoT and Cloud Connectivity," IEEE Transactions on Consumer Electronics, vol. 68, no. 1, pp. 112-119, 2022,

[9]. R. Mehta and L. Zhang, "Power Optimization in VLSI-Based IoT Devices for Smart Applications," Journal of Lo Power Electronics and Applications, vol. 10, no. 3, pp. 55-67, 2022.

[10]. R. S. Kulkarni and A. Patil, “IoT-Based Automated Feeding and Monitoring System for Pets,” International Journal of Smart Devices and Sensors, vol. 4, no. 1, pp. 23–30, 2022.