CLASS: T.E. E &TC **SUBJECT: MC**

ROLL NUMBER-32440

EXPT 7: LCD Interfacing with PIC18F4550

```
#include <p18f4550.h>
#include "vector_relocate.h"

//Declarations
#define LCD_DATA    PORTD                    //LCD data port to PORTD
#define ctrl        PORTE                    //LCD control port to PORTE
#define rs          PORTEbits.RE0    //register select signal to RE0
#define rw          PORTEbits.RE1    //read/write signal to RE1
#define en          PORTEbits.RE2    //enable signal to RE2

//Function Prototypes
void init_LCD(void);                         //Function to initialise the LCD
void LCD_command(unsigned char cmd);         //Function to pass command to the LCD
void LCD_data(unsigned char data);           //Function to write character to the LCD
void LCD_write_string(static char *str);//Function to write string to the LCD
void msdelay (unsigned int time);            //Function to generate delay

//Start of Main Program
void main(void)
{
    char var1[] = "BHANU";//Declare message to be displayed
    char var2[] = "aaaaaa";

    ADCON1 = 0x0F;                  //Configuring the PORTE pins as digital I/O
    TRISD = 0x00;              //Configuring PORTD as output
    TRISE = 0x00;                   //Configuring PORTE as output

    init_LCD();                 // call function to initialise of LCD
    msdelay(50);        // delay of 50 mili seconds
```

```
    LCD_write_string(var1);//Display message on first line
    msdelay(15);

    LCD_command(0xC0);            // initiate cursor to second line
    LCD_write_string(var2);//Display message on second line

    while (1);                    //Loop here
}                                                    //End of Main

//Function Definitions
void msdelay (unsigned int time) //Function to generate delay
{
unsigned int i, j;
  for (i = 0; i < time; i++)
          for (j = 0; j < 710; j++);//Calibrated for a 1 ms delay in MPLAB
}


void init_LCD(void)           // Function to initialise the LCD
{
   LCD_command(0x38);      // initialization of 16X2 LCD in 8bit mode
   msdelay(15);
   LCD_command(0x01);      // clear LCD
   msdelay(15);
   LCD_command(0x0C);      // cursor off
   msdelay(15);
   LCD_command(0x80);      // go to first line and 0th position
   msdelay(15);
}

void LCD_command(unsigned char cmd) //Function to pass command to the LCD
{
```

```
   LCD_DATA = cmd;              //Send data on LCD data bus
   rs = 0;                      //RS = 0 since command to LCD
   rw = 0;                      //RW = 0 since writing to LCD
   en = 1;                      //Generate High to low pulse on EN
   msdelay(15);
   en = 0;
}

void LCD_data(unsigned char data)//Function to write data to the LCD
{
   LCD_DATA = data;        //Send data on LCD data bus
   rs = 1;                      //RS = 1 since data to LCD
   rw = 0;                      //RW = 0 since writing to LCD
   en = 1;                      //Generate High to low pulse on EN
        msdelay(15);
   en = 0;
}
//Function to write string to LCD
void LCD_write_string(static char *str)
{
   int i = 0;
   while (str[i] != 0)
   {
      LCD_data(str[i]);      // sending data on LCD byte by byte
      msdelay(15);
      i++;
   }
}
```