Ajax Relay (Jeweller)

Wireless dry-contact relay for Ajax systems

STOCK CODE

1938204-19-NC1

Small wireless relay that lets the Ajax app switch gates, lights, locks and valves — on demand, on a schedule or on alarm.



1 km	7–24 V	13 A	2 yr
radio range	DC supply	@ 230 V~	warranty

BEST FOR

- ✔ Opening gates or garage doors from the Ajax app
- ✔ Switching lights on when the alarm triggers
- ✔ Controlling maglocks, valves, irrigation
- ✔ Existing Ajax hub customers
- ✔ Tight spaces (39 × 33 mm)

NOT FOR

- ✖ Non-Ajax alarm systems
- ✖ Outdoor/wet mounting (IP20)
- ✖ DIY mains wiring — installer only

WHY CUSTOMERS CHOOSE IT

- **Dry (volt-free) contacts** — switch low-voltage or mains loads
- **Pulse (0.5–255 s) or on/off** mode
- Automation by alarm, schedule or button press
- Voltage and temperature protection
- Reports supply voltage to the app

KEY SPECS

Supply	**7 – 24 VDC (12 or 24 V recommended)**
Max load	**5 A @ 24 VDC · 13 A @ 230 VAC**
Inductive load	**3 A @ 24 VDC · 8 A @ 230 VAC**
Radio	**Jeweller 868 MHz, up to 1,000 m**
Size / weight	**39 × 33 × 18 mm · 25 g**
Operating temp	**−20 to +64 °C · IP20**

COUNTER QUICK ANSWERS

Needs a hub? Yes — any Ajax hub or range extender.

Gate motor? Yes — use pulse mode to simulate the gate button.

Power? Needs a 7–24 V DC supply (not mains powered).