
Sherlotronics RX4-500 Receiver

4-channel code-hopping receiver · 500 m

STOCK CODE

14SHRX4-500

Long-range 4-relay receiver — gate, pedestrian, garage and lights from one unit.



No product photo in the datasheet

4	500 m	64	12 V / 24 VAC
relay channels	line of sight	remotes / channel	supply

WHY CUSTOMERS CHOOSE IT

- **500 m** line-of-sight range
- **4 independent relays**
- Code-hopping encryption
- Latch, timed or on/off relay modes

BEST FOR

- ✔ Large properties needing long range
- ✔ Controlling 4 devices (gate, garage, lights, alarm)
- ✔ Estates and complexes with many remotes
- ✔ Panic remotes into the alarm

NOT FOR

- ✖ Small single-gate jobs (RX1/RX2 is cheaper)
- ✖ Other brands' remotes

KEY SPECS

Frequency	**403 MHz (local) / 433 MHz (export)**
Supply	**12 VDC / 24 VAC**
Current	**~22 mA standby · ~126 mA all on**
Memory	**64 remotes per channel**
Size	**145 × 66 × 40 mm · 135 g**
Operating temp	**−3 to +49 °C**

FAMILY — PICK THE RIGHT ONE

RX2-150	**2 channels, 150 m**
RX4-500	**4 channels, 500 m — this unit**
S4	**4-channel transmitter (pairs with this)**

COUNTER QUICK ANSWERS

Range test? Always do a range test on site before handover.

How many remotes? 64 per channel.

24 V gate motor supply? Yes — runs on 24 VAC.

Source: Sherlotronics RX4-500 installation instructions.

Internal counter reference