
Sherlotronics S4 4-Channel Transmitter

Stand-alone wired-input transmitter · 1500 m

STOCK CODE

14SHS4

Turns wired inputs (alarm outputs, buttons, sensors) into radio signals for Sherlo receivers — up to 1.5 km.



4	1500 m	12 V	60 min
input channels	line of sight	10–16 VDC	supervision

WHY CUSTOMERS CHOOSE IT

- **4 wired inputs** → 4 radio channels
- **Up to 1500 m** line of sight
- On/off mode to latch & unlatch receiver relays
- Supervision signal every 60 minutes
- Triple-send option for reliability

BEST FOR

- ✔ Linking an alarm output to a gate or siren wirelessly
- ✔ Sending signals between buildings
- ✔ Remote panic or trigger points
- ✔ Pairing with Sherlo RX receivers

NOT FOR

- ✖ Handheld use — it's a box transmitter
- ✖ Non-Sherlotronics receivers

KEY SPECS

Frequency	**403 MHz (local) / 433 MHz (export)**
Voltage	**10 – 16 VDC**
Current	**< 20 mA standby · < 110 mA transmitting**
Size	**145 × 66 × 40 mm · 135 g**
Operating temp	**−3 to +49 °C**

FAMILY — PICK THE RIGHT ONE

Receivers	**RX1-150, RX2-150, RX3-150, RX1-500, RX4-500, MB4000**

COUNTER QUICK ANSWERS

Which receivers? RX1/2/3-150, RX1-500, RX4-500, MB4000.

Power? 12 V supply (10–16 VDC).

Switch off too? Yes — use the on/off jumper.

Source: Sherlotronics S4 installation instructions.

Internal counter reference