
# Sherlotronics RX1-150 Receiver

1-channel code-hopping receiver · 150 m

STOCK CODE

**14SHRX1-150**

**Simple single-relay receiver for one gate, door or light — up to 80 remotes.**



No product photo in the datasheet

| 1 | 150 m | 80 | 12 V |
|---|---|---|---|
| relay channel | line of sight | remotes | 10–16 VDC |

## WHY CUSTOMERS CHOOSE IT

- **Code-hopping** decoding
- Relay N.O./N.C., 3 A
- Pulse 0.5 / 1 / 3 s, latch or 3 min
- Erase individual remotes

## KEY SPECS

| | |
|---|---|
| Frequency | **403 MHz (local) / 433 MHz (export)** |
| Power | **10–16 VDC · 14 mA standby, 50 mA active** |
| Relay | **3 A @ 24 VDC / 120 VAC** |
| Size | **100 × 60 × 25 mm** |
| Operating temp | **−3 to +49 °C** |

## BEST FOR

- ✔ Single gate or garage
- ✔ Switching one light or lock
- ✔ Adding remotes to an existing motor

## NOT FOR

- ✖ More than one output (RX2 / RX4)
- ✖ Over 80 remotes

## FAMILY — PICK THE RIGHT ONE

| | |
|---|---|
| **RX1-150** | **1 channel — this unit** |
| **RX2-150** | **2 channel** |
| **RX4-500** | **4 channel, 500 m** |

## COUNTER QUICK ANSWERS

**How many remotes?** Up to 80.

**Latching?** Yes — set by jumpers.

**Indoors range?** About 60 m.

Source: Sherlotronics RX1-150 installation instructions.