# Sherlotronics 6.4 A Backup Power Supply

12 V 6.4 A battery-backup power supply / charger

STOCK CODE

**14SH6.4AMP (W)**

**Keeps alarms, CCTV, maglocks and door controllers running when the power goes off.**



| 6.4 A | 70 W | 13–14.4 V | 12 mo |
|---|---|---|---|
| output | max power | adjustable | warranty |

## BEST FOR

- ✔ CCTV camera power with battery backup
- ✔ Maglocks & access control doors
- ✔ Alarm panel backup supply
- ✔ Load-shedding protection for 12 V systems

## NOT FOR

- ✖ Loads above 6.4 A / 70 W
- ✖ Outdoor mounting without protection
- ✖ 24 V equipment

## WHY CUSTOMERS CHOOSE IT

- **Microprocessor-controlled** battery charging
- **Low-battery cut-out** at 10 V protects the battery
- Buzzer warns on low battery & mains failure
- AC fail output to signal the alarm panel
- Resettable fuse on output, fused mains input

## KEY SPECS

| | |
|---|---|
| Input | **110 – 230 VAC 50 Hz** |
| Output | **13 – 14.4 VDC adjustable, 6.4 A** |
| Relay contact | **10 A** |
| AC fail output | **140 mA positive switching** |
| Size / weight | **275 × 225 × 97 mm · 1.13 kg** |
| Operating temp | **−3 to +60 °C** |

## COUNTER QUICK ANSWERS

**Battery included?** Check stock — add a 12 V 7 Ah (06AS12-7) or larger.

**How many cameras?** Add up each device's current — keep the total under 6.4 A.

**Tells the alarm power failed?** Yes — via the AC fail output.

Source: Sherlotronics 6.4A Battery Backup Power-Supply datasheet.

Internal counter reference