
Sherlotronics RX2-150 Receiver

2-channel code-hopping receiver · 150 m

STOCK CODE

14SHRX2-150

Two-relay remote receiver for gates, garages and lights — 40 remotes per relay.



No product photo in the datasheet

2	150 m	40	12 V
relay channels	line of sight	remotes / relay	10–16 VDC

WHY CUSTOMERS CHOOSE IT

- **Code-hopping** encryption
- **2 relays**, N/O or N/C, 3 A
- Relay times: 0.5 s to 3 min, latch, or on/off
- Erase single remotes without resetting

KEY SPECS

Frequency	**403 MHz (local) / 433 MHz (export)**
Voltage	**10 – 16 VDC**
Current	**~14 mA standby · ~65 mA all on**
Relay rating	**3 A @ 24 VDC / 120 VAC**
Size	**100 × 60 × 25 mm · 78 g**
Operating temp	**−3 to +49 °C**

BEST FOR

- ✔ Gate motor + pedestrian or garage on one receiver
- ✔ Switching lights or pumps (latch / on-off modes)
- ✔ Sherlotronics code-hopping remotes

NOT FOR

- ✖ More than 40 remotes per channel
- ✖ 24 V-only supplies (10–16 VDC)
- ✖ Other brands' remotes

COUNTER QUICK ANSWERS

How many remotes? 40 per relay.

Can it switch a light on/off? Yes — on/off or latch mode.

Warranty? 2 years from manufacture.

Source: Sherlotronics RX2-150 installation instructions.

Internal counter reference