Centurion NOVA HELIX Receiver

NOVA HELIX code-hopping 433 MHz receiver (single channel)

STOCK CODE

24RX1NHV3433

Ultra-secure code-hopping receiver for gates and garages — works with all NOVA remotes.

⚠ Stock code read as the single-channel NOVA HELIX receiver — confirm 1- vs multi-channel before quoting.



433 MHz	62	12–24 V	Hopping
frequency	buttons (1-ch)	DC supply	anti-clone code

WHY CUSTOMERS CHOOSE IT

- **Code-hopping** — every press sends a new code, can't be cloned
- **Timed Autolearn** — learns remotes for a set time
- **Sticky latch** — outputs keep their state after a power cut
- SmartSwitch II support — control up to 15 devices
- Backward compatible with NOVA remotes

BEST FOR

- ✔ Gate motors, garage doors, booms
- ✔ Upgrading to a more secure receiver
- ✔ Sites using CENTURION NOVA remotes
- ✔ Timed auto-learn for many remotes

NOT FOR

- ✖ Non-NOVA remotes
- ✖ Controlling several devices — choose a multichannel receiver
- ✖ AC-only supplies

KEY SPECS

Frequency	**433.92 MHz**
Supply	**12 – 24 VDC**
Current	**11 mA quiet · 40 mA max @ 12 V**
Memory	**62 buttons (1-ch) · 250 (multi-ch)**
Operating temp	**−15 to +50 °C · UV-stable ABS**

FAMILY — PICK THE RIGHT ONE

1-channel	62-button memory — **this unit**
2 / 4-channel	250-button memory
NOVA remotes	1, 2, 3 or 4 button (GP23 12 V battery)

COUNTER QUICK ANSWERS

Which remotes? CENTURION NOVA code-hopping remotes.

Remote battery? GP23 12 V.

Power cut? Sticky latch keeps outputs as they were.