

VOICE CONTROL & TELEGRAM BOT GUIDE

SUPERNOVA SMARTHOME

Hands-free browser voice commands | Full Telegram Bot setup & reference

Table of Contents

Part 1 — Voice Control

- 1.1 Overview
- 1.2 Requirements & Enabling Voice Control
- 1.3 How Voice Commands Work
- 1.4 Command Reference & Examples
- 1.5 Feedback & Status Messages
- 1.6 Troubleshooting

Part 2 — Telegram Bot

- 2.1 Overview
- 2.2 Creating Your Bot
- 2.3 Configuring the Bot in the Web UI
- 2.4 Security & Access Control
- 2.5 Command Reference
- 2.6 Inline Switch Panel (/menu)
- 2.7 Scheduling via Telegram
- 2.8 Notifications & Alerts
- 2.9 Troubleshooting

Part 1 — Voice Control

1.1 Overview

SUPERNOVA SMARTHOME includes hands-free voice control built directly into the web dashboard, using your browser's built-in Web Speech API. No app, server, or internet speech service is required beyond what your browser already provides — spoken commands are converted to text locally in the browser and sent to the device exactly like a button tap.

1.2 Requirements & Enabling Voice Control

- A browser that supports the Web Speech API — **Google Chrome** is recommended and officially supported (Chrome on desktop or Android).
- The device must be in **Station (STA) mode**, i.e. connected to your home WiFi. The Voice button is hidden while the device is in Access Point mode.
- Microphone permission must be granted to the page when prompted by the browser.

To start: tap the **"Voice OFF"** button on the dashboard (it turns into **"Voice ON"** and a status bar appears). Tap it again at any time to stop listening.

If your browser does not support voice recognition, an alert will prompt you to use Google Chrome instead.

1.3 How Voice Commands Work

Once listening is active, the dashboard continuously listens and matches your speech against a set of recognized phrases. Recognition automatically restarts if it pauses (e.g. after a period of silence), and pauses automatically while the browser tab is hidden, resuming when you return to it.

Each switch can be addressed by its **custom name**, or generically by number using any of these forms:

Form	Example (Switch 3)
Custom switch name	the exact name you gave it, e.g. "living room light"
"switch <number>"	"switch 3"
"switch <number word>"	"switch three"
"light <number/word>"	"light 3" / "light three"
"device <number/word>"	"device 3" / "device three"

1.4 Command Reference & Examples

Say...	Action
"all on" / "turn on all" / "master on" / "everything on"	Turns every switch ON
"all off" / "turn off all" / "master off" / "everything off"	Turns every switch OFF
"turn on switch 2" / "switch on switch 2" / "switch 2 on"	Turns switch 2 ON
"turn off switch 2" / "switch off switch 2" / "switch 2 off"	Turns switch 2 OFF
"toggle switch 2"	Flips switch 2 to the opposite of its current state

Say...	Action
"turn on living room light" (custom name)	Turns the switch named "living room light" ON

Matching is flexible about word order and surrounding words — the key words (on / off / toggle, plus a switch reference) just need to appear somewhere in what you say.

1.5 Feedback & Status Messages

The status bar below the Voice button shows live feedback:

Status shown	Meaning
"Listening... Say a command"	Actively listening for speech
"Heard: '...'"	Shows exactly what was transcribed
"[Switch] turned ON / OFF / toggled"	Command recognized and executed
"Not recognized: '...'"	Speech was heard but matched no known command
"Mic access denied. Allow mic in browser."	Microphone permission was blocked
"Paused (tab hidden). Resume when visible."	Recognition auto-pauses on a hidden tab

A short tap-confirmation sound and a phone vibration also play when a switch is toggled by voice, using the same sound/haptic settings as the rest of the dashboard.

1.6 Troubleshooting

- **Voice button is missing** — confirm the device is in Station mode, not Access Point mode.
- **"Not recognized"** for a switch name — try the generic "switch <number>" form instead, or check the name for unusual punctuation.
- **Nothing happens when I speak** — check the browser's microphone permission for the page, and confirm you are using Chrome.
- **Recognition keeps stopping** — this is expected behavior on silence; it automatically restarts within half a second.

Part 2 — Telegram Bot

2.1 Overview

The built-in Telegram Bot lets you control every switch, view status, and manage schedules from anywhere, directly from Telegram — no port forwarding or public IP required, since the device connects out to Telegram's servers over a secure connection.

2.2 Creating Your Bot

- Open Telegram and search for **@BotFather**.
- Send `/newbot` and follow the prompts to name your bot.
- BotFather will reply with a **Bot Token** — a long string like `123456789:AAH...`. Keep this private.
- Find your own numeric **Chat ID** by messaging **@userinfobot** (or a similar utility bot) — it will reply with your ID.

The Bot Token grants full control of your bot to whoever holds it. Never share it publicly (e.g. in a GitHub repo, screenshot, or forum post).

2.3 Configuring the Bot in the Web UI

- Log in to the SUPERNOVA SMARTHOME dashboard and open Settings → Telegram.
- Paste your Bot Token into the Token field.
- Enter your Chat ID (and up to 2 more, for additional authorized users/admins) into the Chat ID fields.
- Toggle Telegram Bot to ON and save. The device restarts to apply the new settings.
- Message your bot on Telegram with `/start` or `/help` to confirm it responds.

2.4 Security & Access Control

Only messages from the up-to-3 configured Chat IDs are accepted as commands. If someone else messages the bot, they receive an "Unauthorized User" reply, and an alert is automatically sent to all configured (authorized) Chat IDs so you know an unrecognized user tried to access the system.

You can remotely disable the bot at any time with the `/botoff` command below, or from the Web UI — useful if you ever suspect the token has been compromised.

2.5 Command Reference

Command	Description
<code>/start, /help</code>	Welcome message / list all available commands
<code>/menu</code>	Interactive inline switch control panel (see 2.6)
<code>/status</code>	Current ON/OFF state of every switch
<code>/on <n></code>	Turn switch n ON
<code>/off <n></code>	Turn switch n OFF
<code>/allon</code>	Turn all switches ON
<code>/alloff</code>	Turn all switches OFF
<code><Switch Name> on / off</code>	Control a switch by its custom name, e.g. "Living Room on"

Command	Description
/timeron <n> <YYYY-MM-DD HH:MM>	Schedule switch n to turn ON at a date/time
/timeroff <n> <YYYY-MM-DD HH:MM>	Schedule switch n to turn OFF at a date/time
/cancelon <n>	Cancel switch n's scheduled ON timer
/canceloff <n>	Cancel switch n's scheduled OFF timer
/timers	List all currently active timers
/uptime	Show how long the device has been running
/restart	Restart the device remotely
/botoff	Disable the Telegram bot (re-enable from the Web UI)

2.6 Inline Switch Panel (/menu)

Sending /menu opens a tappable button panel directly inside the chat — one button per switch, showing its current state. Tapping a button toggles that switch instantly and the panel updates in place, so you don't need to remember any command syntax for everyday use.

2.7 Scheduling via Telegram

Timers set via /timeron / /timeroff use the same underlying schedule engine as the Web Dashboard: they survive power cuts, and setting a new timer for a switch cancels any conflicting timer already active on it. Use /timers at any time to review everything currently scheduled.

Date/time format is strictly YYYY-MM-DD HH:MM in 24-hour time, for example:
 /timeron 1 2026-08-15 21:30

2.8 Notifications & Alerts

When enabled, the bot proactively sends messages to all configured Chat IDs for events such as switches being turned on/off in bulk and unauthorized access attempts (the unauthorized-access alert is always sent regardless of the notification toggle, as a security measure).

2.9 Troubleshooting

The bot does not reply to anything.

Confirm the Bot Token was copied correctly (no extra spaces), the bot is enabled in Settings, and the device has internet access (Station mode connected to your router).

I get "Unauthorized User".

Your Telegram Chat ID does not match any of the 3 configured IDs. Double-check the numeric ID from @userinfobot and re-enter it exactly in Settings.

Commands work but /menu buttons do nothing.

Ensure only one instance of the bot is polling for updates (avoid running the same token in two places), and that the device has not lost WiFi connectivity.

I forgot to save my Bot Token somewhere safe and lost it.

Message @BotFather with /mybots, select your bot, and choose "API Token" to view or regenerate it.