MAGNETIC TAPE CONTROLLER REGISTERS

BIT	COMMAND	STATUS	DIAGNOSTIC
0	DRIVE 1	DATA OUT FULL	SPARE
1	DRIVE 2	DATA IN FULL	"
2	DRIVE 3	END OF TAPE	"
3	DRIVE 4	BEGINNING OF TAPE	"
4	SPARE	WRITE PROTECTED	"
5	TAPE	TAPE	"
6	FILE	FILE	"
7	BLOCK	BLOCK	"
8	BACKWARD	BACKWARD	"
9	FORWARD	FORWARD	REVERSE
10	FEED	FEED	FORWARD
11	ERASE	ERASE	ENABLE LRC
12	READ	READ	DISABLE WRITE
13	WRITE	WRITE	WRITE ENABLED
14	SPARE	ACTIVE	ERASE ENABLED
15	"	TAPE MARK	PARITY INTO QUEUE
16	SET LOCAL	TERMINATED	PARITY FROM QUEUE
17	GENERAL RESET (TAPE)	DATA FAULT	READ/WRITE PARITY
18	SPARE	DATA OVERRUN	LRC CHECK
19	RESTART	TAPE NOT TENSIONED	TAPE MARK GAP
20	STOP	STOPPED	* GAP IN PROGRESS
21	CONTROL GENERAL RESET	OFF LINE	* TAPE NOT TENSIONED
22	SET OUT OF SERVICE	OUT OF SERVICE	* END OF TAPE
23	SPARE	POWER FAULT	* BEGINNING OF TAPE

(* CAN BE FORCED. REMAINDER ONLY MONITORED)

SERIAL-PARALLEL ADAPTOR REGISTERS

BIT	COMMAND	STATUS	DIAGNOSTIC
0	SPARE	SPARE	ACTX
1	"	"	DATX
2	"	"	TIMX
3	MICRO STEP	DIAGNOSTIC REGISTER IN USE	ACTY
4	ENABLE MICRO STEP	MICRO STEP ENABLED	DATY
5	STEP	STEP IN PROGRESS	TIMY
6	ENABLE STEP	STEP ENABLED	SM TEST
7	SPARE	INCOMING PARITY FAIL	SPA TEST
8	"	SERIAL OUTPUT DATA FULL	FORWARD PARITY INVERSION
9	"	SERIAL OUTPUT ADDRESS FULL	SPARE
10	"	SERIAL INPUT DATA FULL	"
11	"	SERIAL INPUT ADDRESS FULL	"
12	"	OUTPUT DATA REGISTER FULL	"
13	"	OUTPUT ADDRESS REGISTER FULL	"
14	"	INPUT TIMESTAMP REGISTER FULL	"
15	"	INPUT DATA REGISTER FULL	"
16	"	INPUT ADDRESS REGISTER FULL	"
17	"	OVERRUN	"
18	RESET O/G ERROR	OUTGOING ERROR	"
19	RESET I/C TIMEOUT	INCOMING TIMEOUT	"
20	STOP OUTPUT	OUTPUT STOPPED	"
21	STOP INPUT	INPUT STOPPED	"
22	GENERAL RESET	OFFLINE	"
23	SET OUT OF SERVICE	OUT OF SERVICE	"

DISC CONTROLLER REGISTERS

BIT	COMMAND	STATUS	TRANSFER CAPABILITY *	
			START ADDRESS	TRANSFER SIZE
0	SPARE	SPARE	0	24
1	"	DATA PARITY ERROR		
2	"	SPARE		
3	"	"		NUMBER OF SECTORS TO BE TRANSFERRED
4	"	"		
5	"	"		
6	"	DATA OUT FULL		
7	"	DATA IN FULL	ABSOLUTE SECTOR ADDRESS	
8	"	SPARE		
9	"	"		
10	INHIBIT DATA CHECK	DATA CHECK INHIBIT		34
11	DISC READ	DISC READ		35
12	DISC WRITE	DISC WRITE		SPARE
13	SPARE	ACTIVE		
14	"	TERMINATED		
15	"	DATA OVERRUN	15	
16	"	DATA CHECK FAILED	16	40
17	"	ROUTINING ERROR		41 WRITE PROTECT
18	"	ACCESS FAULT		42 F
19	"	STORAGE UNIT FAULT	WIRED DISC IDENTITY	E
20	RESTART	WRITE PROTECT LOCK		D CHECK CODE
21	STOP	STOPPED		C
22	GENERAL RESET	OFF LINE		B
23	SET OUT OF SERVICE	OUT OF SERVICE	23	A 47

* 256 TRACK DISC.

PARALLEL TELETYPE CONTROLLER REGISTERS

BIT	COMMAND	STATUS
0	SPARE	SPARE
1	"	"
2	"	"
3	"	"
4	"	"
5	"	"
6	"	"
7	"	"
8	"	"
9	"	"
10	"	"
11	"	"
12	"	"
13	"	"
14	"	"
15	"	"
16	ECHO	ECHO
17	SPARE	DATA OUT REGISTER EMPTY
18	"	DATA IN REGISTER FULL
19	FAULT RESET	SPARE
20	GENERAL RESET	OVERRUN
21	STOP	STOPPED
22	SPARE	OFF LINE
23	SET OUT OF SERVICE	OUT OF SERVICE

LINE PRINTER CONTROLLER REGISTERS

BIT	COMMAND	STATUS
0	SPARE	SPARE
1	"	"
2	"	"
3	"	"
4	"	"
5	"	"
6	"	"
7	"	"
8	"	"
9	"	"
10	"	"
11	"	"
12	"	"
13	"	DATA OUT FULL
14	"	SPARE
15	"	DOUBLE SPACE
16	"	POWER FAULT
17	"	PARITY FAULT
18	"	PAPER OUT
19	"	MOTOR OFF
20	FAULT RESET	ALARM
21	STOP	STOPPED
22	GENERAL RESET	OFF-LINE
23	SET OUT OF SERVICE	OUT OF SERVICE

SERIAL TELETYPE CONTROLLER REGISTERS

BIT	COMMAND	STATUS
0	RESET	DATA OUT FULL
1		DATA IN FULL
2		SPARE
3		"
4		"
5		DATA TERMINAL NOT READY
6		DATA OVERRUN
7		OFF-LINE

SERIAL READER CONTROLLER REGISTERS

BIT	COMMAND	STATUS
0	RESET	DATA IN FULL
1	READ	SPARE
2		STOPPED
3		SPARE
4		END OF TAPE
5		SPARE
6		POWER OFF
7		OFFLINE

SERIAL PUNCH CONTROLLER REGISTERS

BIT	COMMAND	STATUS
0	RESET	DATA OUT FULL
1		SPARE
2		"
3		TAPE LOW
4		SPARE
5		TAPE TIGHT/BROKEN
6		POWER OFF
7		OFF-LINE