

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250278130

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

WANG; Yong et al.

MANAGEMENT OF NEAR FIELD COMMUNICATIONS USING A LOW POWER EXPRESS MODE OF AN ELECTRONIC DEVICE

Abstract

Systems, methods, and computer-readable media for managing near field communications during a low power express mode of an electronic device are provided that may make credentials of a near field communication (“NFC”) component appropriately secure and appropriately accessible while also limiting the power consumption of the NFC component and of other components of the electronic device.

Inventors: WANG; Yong (Sunnyvale, CA), SCOTT; Gordon Y. (Cupertino, CA), CHANG; Andrew C. (Sunnyvale, CA), WILLIAMS; Scott A. (San Jose, CA)

Applicant: Apple Inc. (Cupertino, CA)

Family ID: 68693463

Appl. No.: 19/048844

Filed: February 07, 2025

Related U.S. Application Data

parent US continuation 17399031 20210810 parent-grant-document US 12222794 child US 19048844

Publication Classification

Int. Cl.: G06F1/3287 (20190101); G06F1/3212 (20190101); H04L43/062 (20220101); H04L43/0829 (20220101); H04L43/087 (20220101); H04L65/75 (20220101); H04L65/80 (20220101); H04W4/80 (20180101); H04W24/08 (20090101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) [0001] This application a continuation of prior filed U.S. patent application Ser. No. 17/399,031, filed Aug. 10, 2021, now U.S. Pat. No. 12,222,794, with an issue date of Feb. 11, 2025, which is a continuation of prior filed U.S. patent application Ser. No. 16/128,206, filed Sep. 11, 2018, now U.S. Pat. No. 11,086,387, with an issue date of Aug. 10, 2021, which claims the benefit of prior filed U.S. Provisional Patent Application No. 62/679,909, filed Jun. 3, 2018, each of which is hereby incorporated by reference herein in its entirety.

TECHNICAL FIELD

[0002] This disclosure relates to the management of near field communications and, more particularly, to the management of near field communications using a low power express mode of an electronic device.

BACKGROUND OF THE DISCLOSURE

[0003] Portable electronic devices (e.g., cellular telephones) may be provided with near field communication (“NFC”) components for enabling contactless proximity-based communications with another entity. Often times, these communications are associated with currency transactions or other secure data transactions that users rely on every day, such as credit card payments and public transportation ticketing. However, due to the limited amount of power available to battery operated devices, the NFC capabilities of such devices are often compromised or rendered unusable when their available power drops below certain thresholds.

SUMMARY OF THE DISCLOSURE

[0004] This document describes systems, methods, and computer-readable media for managing power usage in a device that is capable of near field communications and/or other wireless communications technologies.

[0005] As an example, a method for operating an electronic device that includes a near field communication component may be provided that includes, while the electronic device is operating in a normal power mode of the electronic device, during which the near field communication component is operating in a full power mode of the near field communication component, detecting a low power mode initiation event with the electronic device, and, in response to the detecting, determining a status of a low power mode flag (LPMF) of the electronic device, and transitioning the electronic device from operating in the normal power mode of the electronic device to operating in a low power mode of the electronic device, wherein the transitioning the electronic device includes disabling a plurality of subsystems of the electronic device, transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in a low power mode of the near field communication component when the determined status of the LPMF is a first status, and transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in an off mode of the near field communication component when the determined status of the LPMF is a second status that is different than the first status, wherein the near field communication component uses less power when operating in the off mode of the near field communication component than when operating in the low power mode of the near field communication component.

[0006] As another example, a method for operating an electronic device that includes a

communication component and a power supply may be provided that includes detecting a low power mode initiation event with the electronic device and, in response to the detecting, disabling at least one of a power management unit of the electronic device or an operating system of the electronic device, when at least one express mode credential is available on the electronic device, providing power from the power supply to the communication component for enabling the communication component to communicate data from the at least one express mode credential to a remote terminal, and, when no express mode credential is available on the electronic device, preventing the communication component from receiving any power from the power supply.

[0007] As yet another example, a method for operating an electronic device that includes a communication component, a memory register, and a battery may be provided that includes detecting that a charge of the battery is below a predetermined threshold and, in response to the detecting, disabling a plurality of subsystems of the electronic device, when the status of the memory register is a first status, providing power from the battery to the communication component for enabling the communication component to communicate data with a remote terminal, and, when the status of the memory register is a second status that is different than the first status, preventing the communication component from receiving any power from the battery.

[0008] This Summary is provided only to summarize some example embodiments, so as to provide a basic understanding of some aspects of the subject matter described in this document. Accordingly, it will be appreciated that the features described in this Summary are only examples and should not be construed to narrow the scope or spirit of the subject matter described herein in any way. Unless otherwise stated, features described in the context of one example may be combined or used with features described in the context of one or more other examples. Other features, aspects, and advantages of the subject matter described herein will become apparent from the following Detailed Description, Figures, and Claims.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] The discussion below makes reference to the following drawings, in which like reference characters may refer to like parts throughout, and in which:

[0010] FIG. 1 is a schematic view of an illustrative system that includes an electronic device for managing near field communications;

[0011] FIG. 1A is an exemplary battery chart detailing various battery state-of-charge thresholds of an exemplary battery of the electronic device of FIG. 1;

[0012] FIG. 2 is a front view of an illustrative example of the electronic device of FIG. 1;

[0013] FIGS. 2A and 2B are front views of exemplary screens of a graphical user interface of the electronic device of FIGS. 1 and 2 illustrating processes for managing near field communications;

[0014] FIG. 3 is a schematic view of an illustrative portion of the electronic device of FIGS. 1-2B;

[0015] FIG. 4 is an exemplary state diagram of various power states of portions of the electronic device of FIGS. 1-3;

[0016] FIG. 5 is an exemplary state diagram of various configurations of portions of the electronic device of FIGS. 1-3; and

[0017] FIGS. 6-8 are flowcharts of illustrative processes for managing communications.

DETAILED DESCRIPTION OF THE DISCLOSURE

[0018] Systems, methods, and computer-readable media may be provided for managing near field communications. Near field communications may be managed differently according to different power management modes of an electronic device. In certain low power management modes, certain components of an electronic device may be at least partially disabled or shut down to conserve power. When an electronic device operates in these modes, credentials (e.g., payment

credentials) of an NFC component in the device may be appropriately secure and/or appropriately accessible, while power consumption of the NFC component is limited or reduced. For example, while in a low powered operating state at which both a system power management unit (“PMU”) and any device operating system may be off or disabled or inactive, an electronic device may be operative to carry out one or more NFC transactions using one or more specific credentials (e.g., credentials previously designated as express mode cards) and provide any suitable output that may be operative to indicate such an attempted or completed transaction to a user of the device. Various transitions between power management states may be accomplished using a system PMU and a boot loader application of the electronic device but not a full operating system application, such that significant power savings may be realized, while certain actions within a state, such as an NFC transaction within a low power management state, which may include generating a haptic or other user detectable output, may be accomplished without even using a system PMU or loading any application for realizing additional power savings while also securely enabling certain NFC transactions for improving user convenience.

[0019] FIG. 1 is a schematic view of an illustrative communications system 1 that may include a terminal 10 and an electronic device 100 for managing near field communications 55 with terminal 10 in accordance with some embodiments. Electronic device 100 can include, but is not limited to, a music player (e.g., an iPod™ available by Apple Inc. of Cupertino, California), video player, still image player, game player, other media player, music recorder, movie or video camera or recorder, still camera, other media recorder, radio, medical equipment, domestic appliance, transportation vehicle instrument, musical instrument, calculator, cellular telephone (e.g., an iPhone™ available by Apple Inc.), other wireless communication device, personal digital assistant, remote control, pager, computer (e.g., a desktop, laptop, tablet (e.g., an iPad™ available by Apple Inc.), server, etc.), monitor, television, stereo equipment, set up box, set-top box, boom box, modem, router, printer, or any combination thereof. In some embodiments, electronic device 100 may perform a single function (e.g., a device dedicated to managing near field communications) and, in other embodiments, electronic device 100 may perform multiple functions (e.g., a device that manages near field communications, plays music, and receives and transmits telephone calls).

[0020] Electronic device 100 may be any portable, mobile, hand-held, or miniature electronic device that may be configured to manage near field communications wherever a user travels. Some miniature electronic devices may have a form factor that is smaller than that of hand-held electronic devices, such as an iPod™. Illustrative miniature electronic devices can be integrated into various objects that may include, but are not limited to, watches (e.g., an Apple Watch™ available by Apple Inc.), rings, necklaces, belts, accessories for belts, headsets, accessories for shoes, virtual reality devices, glasses, other wearable electronics, accessories for sporting equipment, accessories for fitness equipment, key chains, or any combination thereof. Alternatively, electronic device 100 may not be portable at all, but may instead be generally stationary.

[0021] As shown in FIG. 1, for example, electronic device 100 may include a processor 102, memory 104, communications component 106, power supply 108, input component 110, output component 112, antenna 116, and near field communication (“NFC”) component 120. Electronic device 100 may also include a bus 118 that may provide one or more wired or wireless communication links or paths for transferring data and/or power to, from, or between various other components of device 100. In some embodiments, one or more components of electronic device 100 may be combined or omitted. Moreover, electronic device 100 may include other components not combined or included in FIG. 1. For example, electronic device 100 may include motion-sensing circuitry, a compass, any other suitable components, or several instances of the components shown in FIG. 1. For the sake of simplicity, only one of each of the components is shown in FIG. 1.

[0022] Memory 104 may include one or more storage mediums, including for example, a hard-drive, flash memory, permanent memory such as read-only memory (“ROM”), semi-permanent

memory such as random access memory (“RAM”), any other suitable type of storage component, or any combination thereof. Memory **104** may include cache memory, which may be one or more different types of memory used for temporarily storing data for electronic device applications. Memory **104** may be fixedly embedded within electronic device **100** or may be incorporated onto one or more suitable types of cards that may be repeatedly inserted into and removed from electronic device **100** (e.g., a subscriber identity module (“SIM”) card or secure digital (“SD”) memory card). Memory **104** may store media data (e.g., music and image files), software (e.g., for implementing functions on device **100**), firmware, preference information (e.g., media playback preferences), lifestyle information (e.g., food preferences), exercise information (e.g., information obtained by exercise monitoring equipment), transaction information (e.g., information such as credit card information), wireless connection information (e.g., information that may enable device **100** to establish a wireless connection), subscription information (e.g., information that keeps track of podcasts or television shows or other media a user subscribes to), contact information (e.g., telephone numbers and e-mail addresses), calendar information, any other suitable data, or any combination thereof.

[0023] Communications component **106** may be provided to allow device **100** to communicate with one or more other electronic devices or servers using any suitable communications protocol. For example, communications component **106** may support Wi-Fi (e.g., an 802.11 protocol), ZigBee (e.g., an 802.15.4 protocol), WiDi™, Ethernet, Bluetooth™, Bluetooth™ Low Energy (“BLE”), high frequency systems (e.g., 900 MHz, 2.4 GHz, and 5.6 GHz communication systems), infrared, transmission control protocol/internet protocol (“TCP/IP”) (e.g., any of the protocols used in each of the TCP/IP layers), Stream Control Transmission Protocol (“SCTP”), Dynamic Host Configuration Protocol (“DHCP”), hypertext transfer protocol (“HTTP”), BitTorrent™, file transfer protocol (“FTP”), real-time transport protocol (“RTP”), real-time streaming protocol (“RTSP”), real-time control protocol (“RTCP”), Remote Audio Output Protocol (“RAOP”), Real Data Transport Protocol™ (“RDTP”), User Datagram Protocol (“UDP”), secure shell protocol (“SSH”), wireless distribution system (“WDS”) bridging, any communications protocol that may be used by wireless and cellular telephones and personal e-mail devices (e.g., Global System for Mobile Communications (“GSM”), GSM plus Enhanced Data rates for GSM Evolution (“EDGE”), Code Division Multiple Access (“CDMA”), Orthogonal Frequency-Division Multiple Access (“OFDMA”), high speed packet access (“HSPA”), multi-band, etc.), any communications protocol that may be used by a low power Wireless Personal Area Network (“6LoWPAN”) module, any suitable cellular communications protocol (e.g., broadband cellular network technologies (e.g., 3G, 4G, 5G, etc.)), any other communications protocol, or any combination thereof. Communications component **106** may also include or be electrically coupled to any suitable transceiver circuitry (e.g., transceiver circuitry or antenna **116** via bus **118**) that can enable device **100** to be communicatively coupled to another device (e.g., a host computer or an accessory device) and communicate with that other device wirelessly, or via a wired connection (e.g., using a connector port). Communications component **106** may be configured to determine a geographical position of electronic device **100**. For example, communications component **106** may utilize the global positioning system (“GPS”) or a regional or site-wide positioning system that may use cell tower positioning technology or Wi-Fi technology.

[0024] Power supply **108** can include any suitable circuitry for receiving and/or generating power, and for providing such power to one or more of the other components of electronic device **100**. For example, power supply **108** can be coupled to a power grid (e.g., when device **100** is not acting as a portable device or when a battery of the device is being charged at an electrical outlet with power generated by an electrical power plant). As another example, power supply **108** can be configured to generate power from a natural source (e.g., solar power using solar cells). As another example, power supply **108** can include one or more batteries for providing power (e.g., when device **100** is acting as a portable device). For example, power supply **108** can include one or more of a battery

(e.g., a gel, nickel metal hydride, nickel cadmium, nickel hydrogen, lead acid, or lithium-ion battery), an uninterruptible or continuous power supply (“UPS” or “CPS”), and circuitry for processing power received from a power generation source (e.g., power generated by an electrical power plant and delivered to the user via an electrical socket or otherwise). The power can be provided by power supply **108** as alternating current or direct current, and may be processed to transform power or limit received power to particular characteristics. For example, the power can be transformed to or from direct current, and constrained to one or more values of average power, effective power, peak power, energy per pulse, voltage, current (e.g., measured in amperes), or any other characteristic of received power. Power supply **108** can be operative to request or provide particular amounts of power at different times, for example, based on the needs or requirements of electronic device **100** or periphery devices that may be coupled to electronic device **100** (e.g., to request more power when charging a battery than when the battery is already charged).

[0025] One or more input components **110** may be provided to permit a user to interact or interface with device **100**. For example, input component **110** can take a variety of forms, including, but not limited to, a touch pad, dial, click wheel, scroll wheel, touch screen, one or more buttons (e.g., a keyboard), mouse, joy stick, track ball, microphone, camera, scanner (e.g., a bar code scanner or any other suitable scanner that may obtain product identifying information from a code, such as a bar code, a QR code, or the like), proximity sensor, light detector, motion sensor, biometric sensor (e.g., a fingerprint reader or other feature recognition sensor, which may operate in conjunction with a feature-processing application that may be accessible to electronic device **100** for authenticating a user), and combinations thereof. Each input component **110** can be configured to provide one or more dedicated control functions for making selections or issuing commands associated with operating device **100**.

[0026] Electronic device **100** may also include one or more output components **112** that may present information (e.g., graphical, audible, and/or tactile information) to a user of device **100**. For example, output component **112** of electronic device **100** may take various forms, including, but not limited to, audio speakers, headphones, audio line-outs, visual displays, antennas, infrared ports, rumblers, vibrators, any other suitable haptic elements, or combinations thereof.

[0027] As a specific example, electronic device **100** may include a display output component as an output component **112**. Such a display output component may include any suitable type of display or interface for presenting visual data to a user. A display output component may include a display embedded in device **100** or coupled to device **100** (e.g., a removable display). A display output component may include, for example, a liquid crystal display (“LCD”), a light emitting diode (“LED”) display, an organic light-emitting diode (“OLED”) display, a surface-conduction electron-emitter display (“SED”), a carbon nanotube display, a nanocrystal display, any other suitable type of display, or combination thereof. Alternatively, a display output component can include a movable display or a projecting system for providing a display of content on a surface remote from electronic device **100**, such as, for example, a video projector, a head-up display, or a three-dimensional (e.g., holographic) display. As another example, a display output component may include a digital or mechanical viewfinder, such as a viewfinder of the type found in compact digital cameras, reflex cameras, or any other suitable still or video camera. A display output component may include display driver circuitry, circuitry for driving display drivers, or both, and such a display output component can be operative to display content (e.g., media playback information, application screens for applications implemented on electronic device **100**, information regarding ongoing communications operations, information regarding incoming communications requests, device operation screens, etc.) that may be under the direction of processor **102**.

[0028] It should be noted that one or more input components and one or more output components may sometimes be referred to collectively herein as an input/output (“I/O”) component or I/O interface (e.g., input component **110** and output component **112** as I/O component or I/O interface

114). For example, input component **110** and output component **112** may sometimes be a single I/O component **114**, such as a touch screen, that may receive input information through a user's touch of a display screen and that may also provide visual information to a user via that same display screen.

[0029] Processor **102** of electronic device **100** may include any processing circuitry that may be operative to control the operations and performance of one or more components of electronic device **100**. For example, processor **102** may receive input signals from input component **110** and/or drive output signals through output component **112**. As shown in FIG. 1, processor **102** may be used to run one or more applications, such as an application **103**. Application **103** may include, but is not limited to, one or more operating system applications, firmware applications, media playback applications, media editing applications, NFC low power mode applications, biometric feature-processing applications, or any other suitable applications. For example, processor **102** may load application **103** as a user interface program to determine how instructions or data received via an input component **110** or other component of device **100** may manipulate the way in which information may be stored and/or provided to the user via an output component **112**. Application **103** may be accessed by processor **102** from any suitable source, such as from memory **104** (e.g., via bus **118**) or from another device or server (e.g., via communications component **106**). Processor **102** may include a single processor or multiple processors. For example, processor **102** may include at least one “general purpose” microprocessor, a combination of general and special purpose microprocessors, instruction set processors, graphics processors, video processors, and/or related chips sets, and/or special purpose microprocessors. Processor **102** also may include on board memory for caching purposes.

[0030] Electronic device **100** may also include near field communication (“NFC”) component **120**. NFC component **120** may be any suitable proximity-based communication mechanism that may enable contact-less transactions or communications **55** between electronic device **100** and terminal **10** (e.g., a payment terminal). NFC component **120** may allow for close range communication at relatively low data rates (e.g., 424 kbps), and may comply with any suitable standards, such as ISO/IEC 7816, ISO/IEC 18092, ECMA-340, ISO/IEC 21481, ECMA-352, ISO 14443, and/or ISO 15693. Alternatively or additionally, NFC component **120** may allow for close range communication at relatively high data rates (e.g., 560 Mbps), and may comply with any suitable standards, such as the TransferJet™ protocol. Communication between NFC component **120** and terminal **10** may occur within any suitable close range distance *D* between device **100** and terminal **10**, such as a range of approximately 2 to 4 centimeters (or any other distance greater than 4 centimeters or less than 2 centimeters), and may operate at any suitable frequency (e.g., 13.56 MHz). For example, such close range communication of NFC component **120** may take place via magnetic field induction, which may allow NFC component **120** to communicate with other NFC devices and/or to retrieve information from tags having radio frequency identification (“RFID”) circuitry. NFC component **120** may provide a manner of acquiring merchandise information, transferring payment information, and otherwise communicating with an external device (e.g., terminal **10**).

[0031] NFC component **120** may include any suitable modules for enabling contactless proximity-based communication **55** between electronic device **100** and terminal **10**. As shown in FIG. 1, for example, NFC component **120** may include an NFC device module **130**, an NFC controller module **140**, and an NFC memory module **150**.

[0032] NFC device module **130** may include an NFC data module **132**, an NFC antenna **134**, and an NFC booster **136**. NFC data module **132** may be configured to contain, route, or otherwise provide any suitable data that may be transmitted by NFC component **120** to terminal **10** as part of a contactless proximity-based or NFC communication **55**. Additionally or alternatively, NFC data module **132** may be configured to contain, route, or otherwise receive any suitable data that may be received by NFC component **120** from terminal **10** as part of a contactless proximity-based

communication 55.

[0033] NFC transceiver or NFC antenna 134 may be any suitable antenna or other suitable transceiver circuitry that may generally enable communication of communication 55 from NFC data module 132 to terminal 10 and/or to NFC data module 132 from terminal 10. Therefore, NFC antenna 134 (e.g., a loop antenna) may be provided specifically for enabling the contactless proximity-based communication capabilities of NFC component 120.

[0034] Alternatively or additionally, NFC component 120 may utilize the same transceiver circuitry or antenna (e.g., antenna 116) that another communication component of electronic device 100 (e.g., communication component 106) may utilize. For example, communication component 106 may leverage antenna 116 to enable Wi-Fi, Bluetooth™, or GPS communication between electronic device 100 and another remote entity, while NFC component 120 may leverage antenna 116 to enable contactless proximity-based or NFC communication 55 between NFC data module 132 of NFC device module 130 and another entity (e.g., terminal 10). In such embodiments, NFC device module 130 may include NFC booster 136, which may be configured to provide appropriate signal amplification for data of NFC component 120 (e.g., data within NFC data module 132) so that such data may be appropriately transmitted by shared antenna 116 as communication 55 to terminal 10. For example, shared antenna 116 may require amplification from booster 136 before antenna 116 (e.g., a non-loop antenna) may be properly enabled for communicating contactless proximity-based or NFC communication 55 between electronic device 100 and terminal 10 (e.g., more power may be needed to transmit NFC data using antenna 116 than may be needed to transmit other types of data using antenna 116).

[0035] NFC controller module 140 may include at least one NFC processor module 142. NFC processor module 142 may operate in conjunction with NFC device module 130 to enable, activate, allow, and/or otherwise control NFC component 120 for communicating NFC communication 55 between electronic device 100 and terminal 10. NFC processor module 142 may exist as a separate component, may be integrated into another chipset, or may be integrated with processor 102, for example, as part of a system on a chip (“SoC”). As shown in FIG. 1, NFC processor module 142 of NFC controller module 140 may be used to run one or more applications, such as an NFC low power mode or wallet application 143 that may help dictate the function of NFC component 120. Application 143 may include, but is not limited to, one or more operating system applications, firmware applications, NFC low power applications, or any other suitable applications that may be accessible to NFC component 120 (e.g., application 103). NFC controller module 140 may include one or more protocols, such as the Near Field Communication Interface and Protocols (“NFCIP-1”), for communicating with another NFC device (e.g., terminal 10). The protocols may be used to adapt the communication speed and to designate one of the connected devices as the initiator device that controls the near field communication.

[0036] NFC controller module 140 may control the near field communication mode of NFC component 120. For example, NFC processor module 142 may be configured to switch NFC device module 130 between a reader/writer mode for reading information (e.g., communication 55) from NFC tags (e.g., from terminal 10) to NFC data module 132, a peer-to-peer mode for exchanging data (e.g., communication 55) with another NFC enabled device (e.g., terminal 10), and a card emulation mode for allowing another NFC enabled device (e.g., terminal 10) to read information (e.g., communication 55) from NFC data module 132. NFC controller module 140 also may be configured to switch NFC component 120 between active and passive modes. For example, NFC processor module 142 may be configured to switch NFC device module 130 (e.g., in conjunction with NFC antenna 134 or shared antenna 116) between an active mode where NFC device module 130 may generate its own RF field and a passive mode where NFC device module 130 may use load modulation to transfer data to another device generating an RF field (e.g., terminal 10). Operation in such a passive mode may prolong the battery life of electronic device 100 compared to operation in such an active mode. The modes of NFC device module 130 may be

controlled based on preferences of a user and/or based on preferences of a manufacturer of device **100**, which may be defined or otherwise dictated by an application running on device **100** (e.g., application **103** and/or application **143**).

[0037] NFC memory module **150** may operate in conjunction with NFC device module **130** and/or NFC controller module **140** to allow for NFC communication **55** between electronic device **100** and terminal **10**. NFC memory module **150** may be embedded within NFC device hardware or within an NFC integrated circuit (“IC”). NFC memory module **150** may be tamper resistant and may include at least a portion of a secure element. For example, NFC memory module **150** may store one or more applications relating to NFC communications (e.g., application **143**) that may be accessed by NFC controller module **140**. For example, such applications may include financial payment applications, secure access system applications, loyalty card applications, and other applications, which may be encrypted. In some embodiments, NFC controller module **140** and NFC memory module **150** may independently or in combination provide a dedicated microprocessor system that may contain an operating system, memory, application environment, and security protocols intended to be used to store and execute sensitive applications on electronic device **100**. NFC memory module **150** may be a portion of memory **106** or at least one dedicated chip specific to NFC component **120**. NFC memory module **150** may reside on a SIM, a dedicated chip on a motherboard of electronic device **100**, or as an external plug in memory card. NFC memory module **150** may be completely independent from NFC controller module **140** and may be provided by different components of device **100** and/or provided to electronic device **100** by different removable subsystems.

[0038] NFC memory module **150** may include one or more of an issuer security domain (“ISD”) **152** and a supplemental security domain (“SSD”) **154** (e.g., a service provider security domain (“SPSD”), a trusted service manager security domain (“TSMSSD”), etc.), which may be defined and managed by an NFC specification standard (e.g., GlobalPlatform). For example, ISD **152** may be a portion of NFC memory module **150** in which a trusted service manager (“TSM”) or issuing financial institution may store keys and/or other suitable information for creating or otherwise provisioning one or more credentials (e.g., credentials associated with various credit cards, bank cards, gift cards, access cards, transit passes, etc.) on electronic device **100** (e.g., via communications component **106**), for credential content management, and/or security domain management. A specific supplemental security domain (“SSD”) **154** (e.g., one of SSDs **154-154b**) may be associated with a specific credential (e.g., a specific credit card credential or a specific public transit card credential or a specific space (e.g., building) access card credential) that may provide specific privileges or payment rights to electronic device **100**. Each SSD **154** may have its own manager key **155** for its own application or applet **153** that may need to be activated to enable a specific credential of that SSD **154** for use by NFC device module **130** as an NFC communication **55**. For example, a particular SSD **154** may be associated with a particular credit card credential. However, that particular credential may only be communicated as an NFC communication **55** to terminal **10** by NFC component **120** (e.g., that particular credential may only be accessible by NFC data module **132**) when a particular applet **153** of that particular SSD **154** has been enabled or otherwise activated or unlocked for such use. Security features may be provided for enabling use of NFC component **120** that may be particularly useful when transmitting payment information, such as credit card information or bank account information to terminal **10**. Such security features also may include a secure storage area that may have restricted access. For example, user authentication via personal identification number (“PIN”) entry or via user interaction with a biometric sensor may need to be provided to access the secure storage area. In certain embodiments, some or all of the security features may be stored within NFC memory module **150**. Further, security information, such as an authentication key, for communicating with terminal **10** may be stored within NFC memory module **150**. In certain embodiments, NFC memory module **150** may include a microcontroller embedded within electronic device **100**.

[0039] Terminal **10** may include a reader for detecting, reading, or otherwise receiving NFC communication **55** from electronic device **100** (e.g., when electronic device **100** comes within a certain distance or proximity **D** of terminal **10**). Accordingly, it is noted that NFC communication **55** between terminal **10** and electronic device **100** may occur wirelessly and, as such, may not require a clear “line of sight” between the respective devices. As mentioned, NFC device module **130** may be passive or active. When passive, NFC device module **130** may only be activated when within a response range **D** of a suitable reader of terminal **10**. For instance, a reader of terminal **10** may emit a relatively low-power radio wave field that may be used to power an antenna utilized by NFC device module **130** (e.g., shared antenna **116** or NFC-specific antenna **134**) and, thereby, enable that antenna to transmit suitable NFC communication information (e.g., transit card credential information) from NFC data module **132**, via antenna **116** or antenna **134**, to terminal **10** as NFC communication **55**. When active, NFC device module **130** may incorporate or otherwise have access to a power source local to electronic device **100** (e.g., power supply **108**) that may enable shared antenna **116** or NFC-specific antenna **134** to actively transmit NFC communication information (e.g., transit card credential information) from NFC data module **132**, via antenna **116** or antenna **134**, to terminal **10** as NFC communication **55**, rather than reflect radio frequency signals, as in the case of a passive NFC device module **130**.

[0040] While NFC component **120** has been described with respect to near field communication, it is to be understood that component **120** may be configured to provide any suitable contactless proximity-based mobile payment or any other suitable type of contactless proximity-based communication **55** between electronic device **100** and terminal **10**. For example, NFC component **120** may be configured to provide any suitable short-range communication, such as those involving electromagnetic/electrostatic coupling technologies.

[0041] Electronic device **100** may also be provided with a housing **101** that may at least partially enclose one or more of the components of device **100** for protection from debris and other degrading forces external to device **100**. In some embodiments, one or more of the components may be provided within its own housing (e.g., input component **110** may be an independent keyboard or mouse within its own housing that may wirelessly or through a wire communicate with processor **102**, which may be provided within its own housing).

[0042] FIG. **1A** illustrates an exemplary battery chart **108a** detailing various potential state-of-charge thresholds of an exemplary power supply **108** (e.g., an exemplary battery) of electronic device **100**. Specifically, FIG. **1A** illustrates how different operating modes of device **100** may be enabled based on the amount of energy that may be remaining in power supply **108**, as battery chart **108a** may represent the actual energy left in a battery of power supply **108**, where chart **108a** may detail various possible levels and thresholds that device **100** may incorporate into its operation. For example, as shown, battery chart **108a** may include a first or full operating charge level range **162** that may be any charge level between a maximum threshold charge level **161** and a first switching threshold or software threshold or low power express mode (“LPEM”)-on threshold charge level **163**, a second or high battery trap or LPEM operating charge level range **164** that may be any charge level between LPEM-on threshold charge level **163** and a second switching threshold or low power or LPEM-off threshold charge level **165**, a third or low battery trap operating charge level range **166** that may be any charge level between LPEM-off threshold charge level **165** and a third switching threshold or over-discharge lockout (“ODL”) threshold charge level **167**, and a fourth or disconnect operating charge level range **168** that may be any charge level between ODL threshold charge level **167** and a minimum threshold charge level **169**.

[0043] When the charge level of power supply **108** is in full operating charge level range **162**, device **100** may usually be configured to operate in a full or normal operating mode, which may allow device **100** to perform functions such as place telephone calls, connect to Wi-Fi, play media files, and/or any other suitable functions that may be a normal functionality of device **100** (e.g., by configuring NFC component **120** to be in an NFC full power mode). LPEM-on threshold charge

level **163** may be provided in order to limit the current output of power supply **108** once the battery charge has dropped to or below that threshold charge level **163**. Upon the battery charge decreasing to at least that threshold charge level **163** and to no less than ODL threshold charge level **167**, such that the charge level of power supply **108** is in LPEM operating charge level range **164** or in low battery trap operating charge level range **166**, device **100** may usually be configured to operate in a battery trap operating mode, which may allow device **100** to perform limited functions by providing power to only certain components for limited purposes (e.g., to perform emergency or high priority functionalities) while preventing certain power intensive functionalities, such as by disabling one, some, or all input components, output components, communications components, applications, and/or the like (e.g., to mitigate discharge of the battery (e.g., to prevent battery swell, loss of capacity, etc.)). For example, while operating in the battery trap operating mode, which may also be referred to herein as a normal off operating mode, device **100** may be configured to require an external power supply to assist device **100** in harvesting power when starting up again but may be able to start up or power up immediately in response to being charged by an external power supply in a way that provides full functionality of device **100**. The charge remaining during the battery trap operating mode may be any charge level of power supply **108** that is in LPEM operating charge level range **164** or in low battery trap operating charge level range **166**. However, should the charge level of power supply **108** fall below ODL threshold charge level **167**, device **100** may not be able to start up or power up immediately in response to being charged by an external power supply in a way that provides full functionality of device **100**, but instead may first require receiving a significant amount of such external power supply before being able to start up in a way that provides full functionality to device **100**. For example, fast universal serial bus (“USB”) charging may be enabled immediately if the charge level of power supply **108** is not below ODL threshold charge level **167**, yet fast USB charging may be delayed until after a certain amount of external power has charged power supply **108** up above the charge level of ODL threshold charge level **167**. Unlike in the full or normal operating mode of charge level range **162**, where there may be sufficient energy remaining in power supply **108** to power up all of the components of device **100** (e.g., at their normal operating frequencies), in the battery trap operating mode(s) of charge level(s) **164** and/or **166** there may not be sufficient energy remaining in power supply **108** to power up all of the sub-components of device **100** (e.g., at their normal operating frequencies), but there may be enough energy remaining in power supply **108** to run a subset of the components (e.g., a processor, a communications component (e.g., NFC component **120**), an output component (e.g., a display and/or a haptic component), an input component (e.g., a mechanical button), etc.) of device **100** (e.g., at their reduced operating frequencies) for a limited amount of time.

[0044] Upon the battery charge decreasing to at least LPEM-on threshold charge level **163** and to no less than LPEM-off threshold charge level **165**, such that the charge level of power supply **108** is in LPEM operating charge level range **164**, device **100** may be configured to operate in a high battery trap or LPE operating mode, which may allow device **100** to perform limited functions with NFC communication component **120** by situationally providing power to NFC communication component **120** and configuring NFC communication component **120** to carry out certain actions while device **100** is operating in the LPE operating mode (e.g., by configuring NFC component **120** to be in an NFC low power mode or NFC low power express mode in which NFC component **120** may be enabled to carry out one or more LPEM NFC transactions). However, upon the battery charge decreasing to at least LPEM-off threshold charge level **165** and to no less than ODL threshold charge level **167**, such that the charge level of power supply **108** is in low battery trap operating charge level range **166**, device **100** may be configured to operate in a low battery trap operating mode, which may allow device **100** to perform certain limited functions but without providing power to NFC communication component **120** (e.g., by configuring NFC component **120** to be in an NFC OFF mode in which NFC component **120** may not be enabled to carry out any

NFC transactions). Starting up a limited subset of components in a battery trap operating mode (e.g., of charge level **164** and/or of charge level **166**) may cause spikes in the current drawn from the PMU and power supply. As the power supply charge level decreases, its ability to cope with those surges may decrease to the point where turning on a component may cause the voltage being supplied to the device to fall below the level at which the device can operate, thereby causing it to crash or behave erratically. LPEM-off threshold charge level **165** may be defined to avoid this with respect to turning on NFC component **120** (e.g., the limiting factor may be the ability to power NFC component **120** sufficiently so that it can communicate with terminal **10**). ODL threshold charge level **167** may be provided in order to terminate the current output of power supply **108** once the battery charge has dropped to or below that threshold charge level **167**. Upon the battery charge decreasing to at least that threshold charge level **167**, such that the charge level of power supply **108** is in disconnect operating charge level range **168**, device **100** may be configured to disconnect power supply **108** from any or all non-required internal discharge components to prevent any further discharge (e.g., to prevent over discharge) of the battery of power supply **108** (e.g., to operate in a power disconnect operating mode). As mentioned, starting up a limited subset of components in a battery trap operating mode (e.g., of charge level **164** and/or of charge level **166**) may cause spikes in the current drawn from the PMU and power supply. As the power supply charge level decreases, its ability to cope with those surges may decrease to the point where turning on a component may cause the voltage being supplied to the device to fall below the level at which the device can operate, thereby causing it to crash or behave erratically. ODL threshold charge level **167** may be defined to avoid this with respect to turning on any device component (e.g., the limiting factor may be the ability to power any component other than already disabled NFC component **120** (e.g., the display to present a UI and/or a mechanical button to receive a user input and/or a haptic output component to provide a haptic output and/or the like)).

[0045] For example, LPEM-on threshold charge level **163** (e.g., for defining the initial threshold for enabling an NFC low power mode in which NFC component **120** may be enabled to carry out one or more LPEM NFC transactions) may be set by a manufacturer of device **100** to be unchanged throughout the entire period of ownership of device **100**. Alternatively, LPEM-on threshold charge level **163** can be dynamic or adaptive, such that the system can set LPEM-on threshold charge level **163** to be larger or smaller (e.g., through user selection or adjustment or through use of any suitable heuristics or historical device use). In some embodiments, LPEM-on threshold charge level **163** can use a predictive engine of device **100** to determine how often the user conducts LPEM NFC transactions (e.g., NFC transactions in an LPE operating mode) and/or NFC transactions generally (e.g., NFC transactions in any device operating mode), and thereafter increase LPEM-on threshold charge level **163** if the user begins to use NFC transactions more, or decrease LPEM-on threshold charge level **163** if the user begins to use NFC transactions less. As just one example, maximum threshold charge level **161** may have a magnitude of about 4.35 Volts or may have a magnitude in a range of about 4.00 Volts to 4.70 Volts, while LPEM-on threshold charge level **163** may have a magnitude of about 3.20 Volts or may have a magnitude in a range of about 2.85 Volts to 3.55 Volts, while LPEM-off threshold charge level **165** may have a magnitude of about 2.95 Volts or may have a magnitude in a range of about 2.60 Volts to 3.30 Volts, while ODL threshold charge level **167** may have a magnitude of about 2.45 Volts or may have a magnitude in a range of about 2.10 Volts to 2.80 Volts. One, some, or each of the power management and threshold features described herein may be opted-into and/or opted-out of by a user of the device (e.g., rather than being set as an automatic or default feature), such that the user may have control over how its device's power supply may operate.

[0046] While various NFC transactions may be described herein as being enabled due to NFC communication component **120** being powered by power supply **108** of device **100** while device **100** is operating either in the normal operating mode of full operating charge level range **162** (e.g., when NFC communication component **120** may be in an NFC full power mode state **401** of FIG. 4)

or in the LPE operating mode of LPEM operating charge level range **164** (e.g., when NFC communication component **120** may be in an NFC low power mode state **451** of FIG. **4**), in some embodiments, NFC communication component **120** of device **100** can be used as a passive transaction device regardless of the level of charge of power supply **108** being provided to NFC component **120** (e.g., even when the battery charge is below LPEM-off threshold charge level **165** or even below ODL threshold charge level **167**). While being used as a passive transaction device, one or more portions of device **100** (e.g., one or more portions of NFC communication component **120**) can be powered by an external electromagnetic field or carrier field that may be associated with a person, business, or system with which a user of device **100** may intend to conduct contactless proximity-based communication **55**. For example, a user of device **100** could be at a public subway station, bus station, or any other suitable transportation facility that may use passive transaction cards in order to provide a person with access to the respective mode of transportation. By placing device **100** near a carrier field source of terminal **10**, device **100** can be provided power for the subsystem(s) of device **100** that may be configured for passive transactions and thereafter conduct a transaction, thereby allowing the user to access the transportation provided. Of course, for credential security, such passive transactions may only be enabled if an authenticated user has indicated that a particular card may be utilized in such a passive transaction.

[0047] As shown in FIG. **2**, one specific example of electronic device **100** may be a handheld electronic device, such as an iPhone™, where housing **101** may allow access to various input components **110a-110i**, various output components **112a-112c**, and various I/O components **114a-114d** through which device **100** and a user and/or an ambient environment may interface with each other. Input component **110a** may include a button that, when pressed, may cause a “home” screen or menu of a currently running application to be displayed by device **100**. Input component **110b** may be a top or side button for toggling electronic device **100** between a sleep mode and a wake mode or between any other suitable modes. Input component **110c** may include a two-position slider that may disable one or more output components **112** in certain modes of electronic device **100**. Input components **110d** and **110e** may include buttons for increasing and decreasing the volume output or any other characteristic output of an output component **112** of electronic device **100**. Each one of input components **110a-110i** may be a mechanical input component, such as a button supported by a dome switch, a sliding switch, a control pad, a key, a knob, a scroll wheel, or any other suitable form.

[0048] An output component **112a** may be a display that can be used to display a visual or graphic user interface (“GUI”) **180**, which may allow a user to interact with electronic device **100**. GUI **180** may include various layers, windows, screens, templates, elements, menus, and/or other components of a currently running application (e.g., application **103** and/or application **143**) that may be displayed in all or some of the areas of display output component **112a**. One or more of user input components **110a-110i** may be used to navigate through GUI **180** (e.g., from GUI screen **190** of FIG. **2**). For example, one user input component **110** may include a scroll wheel that may allow a user to select one or more graphical elements **182** of GUI **180**. Icons **182** may also be selected via a touch screen I/O component **114a** that may include display output component **112a** and an associated touch input component **110f**. Such a touch screen I/O component **114a** may employ any suitable type of touch screen input technology, such as, but not limited to, resistive, capacitive, infrared, surface acoustic wave, electromagnetic, or near field imaging. Furthermore, touch screen I/O component **114a** may employ single point or multi-point (e.g., multi-touch) input sensing.

[0049] Icons **182** may represent various layers, windows, screens, templates, elements, and/or other components that may be displayed in some or all of the areas of display component **112a** upon selection by the user. Furthermore, selection of a specific icon **182** may lead to a hierarchical navigation process. For example, selection of a specific icon **182** may lead to a new screen of GUI **180** that may include one or more additional icons or other GUI elements of the same application

or of a new application associated with that icon **182**. Textual indicators **181** may be displayed on or near each icon **182** to facilitate user interpretation of each graphical element icon **182**. It is to be appreciated that GUI **180** may include various components arranged in hierarchical and/or non-hierarchical structures. When a specific icon **182** is selected, device **100** may be configured to open a new application associated with that icon **182** and display a corresponding screen of GUI **180** associated with that application. For example, when the specific icon **182** labeled with an NFC LOW POWER MODE textual indicator **181** (i.e., specific icon **183**) is selected, device **100** may launch or otherwise access a specific NFC low power mode or wallet mode application (e.g., application **143**) and may display screens of a specific user interface that may include one or more tools or features for interacting with NFC component **120** in a specific manner (e.g., one or more user interfaces for enabling an authenticated user to select one or more credentials that may later be utilized to carry out an LPEM NFC transaction when NFC component **120** is operating in an NFC low power mode (e.g., for enabling a user to select or provision a credential on device **100** as an “express mode card”) (e.g., as described with respect to state diagram **500** of FIG. 5) and/or for enabling an authenticated user to define one or more particular rules for the use of such a credential (e.g., for enabling a user to determine one or more ways in which an identified “express mode card” may be used in an LPEM NFC transaction (e.g., define a maximum number of times that an express mode card may be used during a particular NFC low power mode and/or define a maximum duration of time after a most recent user authentication event that an express mode card may be used in an LPEM NFC transaction))). For each application, screens may be displayed on display output component **112a** and may include various user interface elements. Additionally or alternatively, for each application, various other types of non-visual information may be provided to a user via various other output components **112** of device **100**. For example, device **100** may be configured to let a user select one or more credentials of a first type but not a second type to be available as an express mode card, where the first type (e.g., simple transit system credentials, such as for the subway, etc.) may be a type of credential that may not warrant as high a level of security as the second type (e.g., credit card credentials, high security access credentials, etc.).

[0050] Electronic device **100** also may include various other I/O components **114** that may allow for communication between device **100** and other devices. I/O component **114b** may be a connection port that may be configured for transmitting and receiving data files, such as media files or customer order files, from a remote data source and/or power from an external power source. For example, I/O component **114b** may be a proprietary port, such as a Lightning™ connector or a 30-pin dock connector from Apple Inc. of Cupertino, California. I/O component **114c** may be a connection slot for receiving a SIM card or any other type of removable component. I/O component **114d** may be a headphone jack for connecting audio headphones that may or may not include a microphone component. Electronic device **100** may also include at least one audio input component **110g**, such as a microphone, and at least one audio output component **112b**, such as an audio speaker.

[0051] Electronic device **100** may also include at least one tactile or haptic output component **112c** (e.g., a rumbler or any other suitable subsystem operative to provide haptic or tactile feedback to a user), a camera and/or scanner input component **110h** (e.g., a video or still camera, and/or a bar code scanner or any other suitable scanner that may obtain product identifying information from a code, such as a bar code, a QR code, or the like), and a biometric input component **110i** (e.g., a fingerprint reader or other feature recognition sensor, which may operate in conjunction with a feature-processing application that may be accessible to electronic device **100** for authenticating a user). As shown in FIG. 2, at least a portion of biometric input component **110i** may be incorporated under or otherwise combined with input component **110a** or any other suitable I/O component of device **100**. For example, biometric input component **110i** may be a fingerprint reader that may be configured to scan the fingerprint of a user's finger as the user interacts with mechanical input component **110a** by pressing input component **110a** with that finger. As another

example, biometric input component **110i** may be a fingerprint reader that may be combined with touch input component **110f** of touch screen I/O component **114a**, such that biometric input component **110i** may be configured to scan the fingerprint of a user's finger as the user interacts with touch screen input component **110f** by pressing or sliding along touch screen input component **110f** with that finger. Moreover, as mentioned, electronic device **100** may further include NFC component **120**, which may be communicatively accessible to terminal **10** via antenna **116** and/or antenna **134** (not shown in FIG. 2). NFC component **120** may be located at least partially within housing **101**, and a mark or symbol **121** can be provided on the exterior of housing **101** that may identify the general location of one or more of the antennas associated with NFC component **120** (e.g., the general location of antenna **116** and/or antenna **134**).

[0052] To facilitate the following discussion regarding the operation of electronic device **100** in managing near field communications (e.g., communications **55** with terminal **10**) during an NFC low power express mode of operation, reference is made to a schematic diagram of a power management subsystem **301** of electronic device **100** (e.g., as shown in FIG. 3), an exemplary state diagram of various power states of portions of electronic device **100** (e.g., as shown in FIG. 4), an exemplary state diagram of various configurations of portions of electronic device **100** (e.g., as shown in FIG. 5), and front views of screens **200a** and **200b** that may be representative of a graphical user interface of electronic device **100** during such near field communication management (e.g., as shown in FIGS. 2A and 2B). The operation described may be achieved with a wide variety of graphical elements and visual schemes. Therefore, the embodiments of FIGS. 2A and 2B are not intended to be limited to the precise user interface conventions adopted herein. Rather, embodiments may include a wide variety of user interface styles.

[0053] FIG. 3 shows a schematic view of near field communication management subsystem **301** of electronic device **100** that may be provided to manage near field communications during different operating modes of electronic device **100**. For example, power management subsystem **301** may determine when to utilize an NFC low power express mode of electronic device **100** and/or how to manage NFC component **120** during such a low power express mode (e.g., how to make credentials of NFC component **120** appropriately secure and/or appropriately accessible during such a low power express mode).

[0054] Electronic device **100** can be configured to operate according to different power management modes for controlling and managing power consumption by the various components of device **100**. As shown in FIG. 3, for example, power management subsystem **301** may include a mode detection module **310** that may be configured to determine when to enter a particular one of various power management modes of electronic device **100**. For example, mode detection module **310** may be configured to determine when to enter a particular one of many possible power management modes, such as a full or normal operating mode, a high battery trap or LPE operating mode, a low battery trap operating mode, or a power disconnect operating mode of electronic device **100** (e.g., as described with respect to battery chart **108a** of FIG. 1A). In particular, mode detection module **310** can be configured to switch the operation of electronic device **100** amongst the various particular power management modes for reducing power consumption when device **100** is not connected to a remote power supply (e.g., when power supply **108** is not plugged into a wall socket). For example, operation of device **100** in a particular power management mode can prevent non-essential power intensive processes from being performed by device **100** while device **100** is being powered by a battery that has less than a certain threshold of power potential remaining.

[0055] As shown in FIG. 3, mode detection module **310** may be configured to poll for or otherwise receive power level data **307** from power supply **108**, where power level data **307** may be indicative of the amount of power remaining in power supply **108** (e.g., when power supply **108** may be a battery whose power level may diminish during use). When mode detection module **310** detects that the remaining power of power supply **108** indicated by received power level data **307** has dropped below a particular threshold (e.g., below one of threshold charge levels **163**, **165**, or

167, or any other suitable threshold), mode detection module 310 may be configured to generate a switch command 311 that may be configured to switch electronic device 100 to a particular power management operating mode based on the particular new operating charge level range entered by power supply 108 (e.g., to a full or normal operating mode when the charge level has entered range 162, to a high battery trap or LPE operating mode when the charge level has entered range 164, to a low battery trap operating mode when the charge level has entered range 166, or to a power disconnect operating mode when the charge level has entered range 162 (e.g., as described with respect to battery chart 108a of FIG. 1A)). For example, as shown in FIG. 3, when mode detection module 310 detects that received power level data 307 is indicative of a particular characteristic of power supply 108 (e.g., that power supply 108 has dropped below a particular power threshold), mode detection module 310 may be configured to generate switch command 311 and provide switch command 311 to a switch application module 320 of power management subsystem 301. [0056] As another example of an initiation event of a particular operating mode (e.g., an NFC low power express mode) that may be detectable by mode detection module 310, mode detection module 310 may be configured to receive input mode selection data 309 from an input component 110 (e.g., one or more of input components 110a-110i). Such input mode selection data 309 may be any suitable data generated by input component 110 that may be indicative of a desire to enter a particular mode. For example, input mode selection data 309 may be indicative of a user selecting "NFC LOW POWER MODE" icon 183 of GUI 180 using touch screen input component 110f of I/O component 114a of FIG. 2, and this may be recognized by mode detection module 310 as an initiation event for entering an NFC low power express mode. Thus, when mode detection module 310 receives such specific input mode selection data 309, mode detection module 310 may be configured to generate switch command 311 and provide switch command 311 to switch application module 320 of power management subsystem 301. Therefore, in addition to or as an alternative to device 100 switching to an NFC low power express mode when power supply 108 is below a certain power threshold (e.g., within LPEM operating charge level range 164 between LPEM-on threshold charge level 163 and LPEM-off threshold charge level 165), such an NFC low power express power management mode may be entered at a user's discretion or during any other suitable situation.

[0057] Regardless of why mode detection module 310 may generate switch command 311 and transmit switch command 311 to switch application module 320 (e.g., in response to a particular received power level data 307 and/or in response to a particular received input mode selection data 309), switch application module 320 may be configured to switch electronic device 100 into a particular power management operating mode (e.g., into an NFC low power express mode) in response to receipt of such a switch command 311. This switch process into a new power management operating mode can include switch application module 320 generating and transmitting one or more disabling commands to one or more components of device 100 for at least partially shutting down, removing power from, or otherwise at least partially disabling at least one function of such components (e.g., if switching to a lower power mode or if a particular component is otherwise to be at least partially disabled for the new operating mode), which may reduce the power consumption of one or more components of device 100 and/or may at least partially disable one, some, or all components of device 100 that are not necessary for at least initially operating device 100 in the new power management operating mode (e.g., one or more NFC communication component switching commands 321 for shutting down, removing power from, or otherwise at least partially disabling at least one function of NFC communication component 120, one or more output component switching commands 323 for shutting down, removing power from, or otherwise at least partially disabling at least one function of at least one output component 110, one or more input component switching commands 325 for shutting down, removing power from, or otherwise at least partially disabling at least one function of at least one output component 112, and/or one or more processor component switching commands 327 for shutting down, removing power from, or

otherwise at least partially disabling at least one function of at least one processor component **102**). Alternatively or additionally, this switch process into a new power management operating mode can include switch application module **320** generating and transmitting one or more enabling commands to one or more components of device **100** for at least partially turning on, providing power to, or otherwise at least partially enabling at least one function of such components (e.g., if switching to a higher power mode or if a particular component is otherwise to be at least partially enabled for the new operating mode), which may increase the power consumption of one or more components of device **100** and/or may at least partially enable one, some, or all components of device **100** that are may be necessary or at least utilized for at least initially operating device **100** in the new power management operating mode (e.g., one or more NFC communication component switching commands **321** for turning on, providing power to, or otherwise at least partially enabling at least one function of NFC communication component **120**, one or more output component switching commands **323** for turning on, providing power to, or otherwise at least partially enabling at least one function of at least one input component **110**, one or more input component switching commands **325** for turning on, providing power to, or otherwise at least partially enabling at least one function of at least one output component **112**, and/or one or more processor component switching commands **327** for turning on, providing power to, or otherwise at least partially enabling at least one function of at least one processor component **102**).

[0058] For example, in response to receipt of a switch command **311** operative to switch device **100** from a normal operating mode to an NFC low power express mode (e.g., in response to the charge level of power supply **108** entering into LPEM operating charge level range **164** or in response to a user input manually requesting a switch into such an NFC low power express mode (e.g., to conserve power of power supply **108**)), switch application module **320** generate and transmit an NFC disabling command **321** to NFC component **120** as part of the switching process to the NFC low power express mode. Such an NFC disabling command **321** may be configured to be received by any suitable element of NFC component **120** such that at least one credential previously enabled by NFC component **120** prior to receipt of command **321** may be disabled in response to receipt of command **321**. As one particular example, command **321** may disable NFC antenna **134** and/or booster **136** of NFC device module **130** when command **321** is received by NFC component **120**, such that no NFC communications **55** may be transmitted by NFC component **120** to terminal **10** after such disablement (e.g., if a user has not selected any credentials provisioned on device **100** for use during such a mode). As another example, command **321** may disable a first applet **153** of a first SSD **154** of NFC memory module **150** when command **321** is received by NFC component **120**, such that no NFC communications **55** associated with the credentials of that first applet **153** may be transmitted by NFC component **120** to terminal **10** after such disablement. In some embodiments, command **321** may disable every applet **153** of every SSD **154** of NFC memory module **150** when command **321** is received by NFC component **120**, such that no NFC communications **55** associated with any credential of any applet **153** of any SSD **154** may be transmitted by NFC component **120** to terminal **10** after such disablement. However, in other embodiments, command **321** may disable only some specific applets **153** of some SSDs **154** of NFC memory module **150** when command **321** is received by NFC component **120**, such that NFC communications **55** associated with the credentials of those specific applets (e.g., credit card credentials, which may warrant a high security level) may not be transmitted by NFC component **120** to terminal **10** after such disablement, but such that other NFC communications **55** that are associated with the credentials of other specific applets (e.g., simple transit system credentials, such as for the subway, which may not warrant a high security level) may be transmitted by NFC component **120** to terminal **10** after such disablement (e.g., based on default credential settings and/or based on specific user selected settings for particular individual or particular groups or types credentials provisioned on device **100**). When received by NFC component **120**, NFC disabling command **321** may be configured to shut down, remove power from, or otherwise at least partially

disable at least one function of NFC component **120**. In some embodiments, NFC component **120** may be provided with no NFC disabling command **321** but instead NFC component **120** may be operated the same as it was in a full power mode (e.g., NFC component **120** may be powered the same by power supply **108** no matter whether device **100** is in a normal operating mode or an NFC LPEM mode. In some embodiments, power management subsystem **301** may be configured to switch electronic device **100** from a normal operating mode to an NFC low power express mode by providing an NFC disabling command **321** that may prevent NFC command **120** from receiving any power from power supply **108** via power management subsystem **301** and/or by providing an NFC direct power command **321d** that may be operative to close a switch **321s** for enabling any suitable power **321p** to be directly provided from power supply **108** to NFC component **120** for powering NFC component **120** during an NFC LPEM mode of operation. In such embodiments, power management subsystem **301** may also be configured to switch electronic device **100** from an NFC low power express mode to an NFC off mode (e.g., when switching to a low battery trap operating mode or to a power disconnect operating mode) by providing another NFC direct power command **321d** that may be operative to open switch **321s** for preventing any power **321p** from being directly provided from power supply **108** to NFC component **120**.

[0059] In addition to or as an alternative to generating an NFC disabling command **321**, switch application module **320** may be configured to switch electronic device **100** from a normal operating mode to an NFC low power express mode (e.g., in response to the charge level of power supply **108** entering into LPEM operating charge level range **164** or in response to a user input requesting a manual switch into such an NFC low power express mode (e.g., to conserve power of power supply **108**)) by generating and transmitting an output component disabling command **323** to at least one output component **112** (e.g., at least one of output components **112a-112c**). When received by that output component **112**, such an output component disabling command **323** may be configured to shut down, remove power from, or otherwise at least partially disable at least one function of that output component **112**. For example, in response to display output component **112a** receiving such a disabling command **323**, display output component **112a** may be turned off (e.g., no more power may be provided to display output component **112a**). In some embodiments, power management subsystem **301** may be configured to switch electronic device **100** from a normal operating mode to an NFC low power express mode by providing an output component disabling command **323** to at least one or all output components **112** for preventing such output component(s) from receiving any power from power supply **108** via power management subsystem **301** and by also providing an output direct power command **323d** that may be operative to close a switch **323s** for enabling any suitable power **323p** to be directly provided from power supply **108** to a particular output component **112** (e.g., haptic output component **112c**) for powering that particular output component **112** during an NFC LPEM mode of operation. In such embodiments, power management subsystem **301** may also be configured to switch electronic device **100** from an NFC low power express mode to an NFC off mode (e.g., when switching to a low battery trap operating mode or to a power disconnect operating mode) by providing another output direct power command **323d** that may be operative to open switch **323s** for preventing any power **323p** from being directly provided from power supply **108** to that particular output component **112** that had been previously directly powered (e.g., haptic output component **112c**).

[0060] Similarly, switch application module **320** may be configured to switch electronic device **100** from a normal operating mode to an NFC low power express mode (e.g., in response to the charge level of power supply **108** entering into LPEM operating charge level range **164** or in response to a user input requesting a switch into such an NFC low power express mode (e.g., to conserve power of power supply **108**)) by generating and transmitting an input component disabling command **325** to at least one input component **110** (e.g., one or more of input components **110a-110i**). When received by that input component **110**, input component disabling command **325** may be configured to shut down, remove power from, or otherwise at least partially disable at least one

function of that input component **110**. In some embodiments, power management subsystem **301** may be configured to switch electronic device **100** from a normal operating mode to an NFC low power express mode by providing an input component disabling command **325** to at least one or all input components **110** for preventing such input component(s) from receiving any power from power supply **108** via power management subsystem **301** and by also providing an input direct power command **325d** that may be operative to close a switch **325s** for enabling any suitable power **325p** to be directly provided from power supply **108** to a particular input component **110** (e.g., side button input component **110b**) for powering that particular input component **110** during an NFC LPEM mode of operation. In such embodiments, power management subsystem **301** may also be configured to switch electronic device **100** from an NFC low power express mode to an NFC off mode (e.g., when switching to a low battery trap operating mode or to a power disconnect operating mode) by providing another input direct power command **325d** that may be operative to open switch **325s** for preventing any power **325p** from being directly provided from power supply **108** to that particular input component **110** that had been previously directly powered (e.g., side button input component **110b**).

[0061] Similarly, switch application module **320** may be configured to switch device **100** from a normal operating mode to an NFC low power express mode or NFC LPE power management mode (e.g., in response to the charge level of power supply **108** entering into LPEM operating charge level range **164** or in response to a user input requesting a switch into such an NFC low power express mode (e.g., to conserve power of power supply **108**)) by generating and transmitting an application disabling command **327** to processor **102**. When received by processor **102**, application disabling command **327** may be configured to shut down or otherwise at least partially disable one or more applications currently being run by processor **102** (e.g., to force quit all non-native applications and/or any non-essential applications and/or all applications that were running on device **100** prior to the generation of that application disabling command **327**). This may reduce the power consumption of processor **102** going forward with the switch to the NFC low power express mode.

[0062] Moreover, additionally or alternatively, switch application module **320** may be configured to switch device **100** from a normal operating mode to an NFC low power express mode (e.g., in response to the charge level of power supply **108** entering into LPEM operating charge level range **164** or in response to a user input requesting a switch into such an NFC low power express mode (e.g., to conserve power of power supply **108**)) by generating and transmitting one or more additional disabling commands (not shown) to at least one other component of device **100** (e.g., memory **104**, communication component **106**, antenna **116**, etc.), such that, when received by that device component, that component disabling command may be configured to shut down, remove power from, or otherwise at least partially disable at least one function of that device component.

[0063] Therefore, switch application module **320** may be configured to initiate the transition of electronic device **100** into a new power management mode by generating and transmitting one or more disabling commands and/or one or more enabling commands (e.g., commands **321**, **323**, **325**, **327**, etc.) that may be configured to shut down, remove power from, or otherwise at least partially disable one, some, or all components of device **100** that are not necessary for at least initially operating device **100** in the new power management mode and/or that may be configured to turn on, provide power to, or otherwise at least partially enable one, some, or all components of device **100** that may be utilized for at least initially operating device **100** in the new power management mode. For example, as mentioned, one or more disabling commands of switch application module **320** may be configured to at least partially turn off one or more input components **110**, one or more output components **112**, processor **102** or at least one or more applications being run by processor **102**, at least some of memory **104**, at least some or all of communications component **106**, antenna **116**, and/or some or all of NFC component **120**. When at least initially operating in such an NFC low power express mode, electronic device **100** may be configured to refrain from providing power

to or otherwise enabling particular device components that are not necessary for securely managing NFC component **120**. For example, in response to receiving one or more disabling commands from switch application module **320**, electronic device **100** can turn off a hard drive (e.g., memory **104**), dim or turn off a display (e.g., output component **112a**), place a processor (e.g., processor **102**) in a low-power “sleep” or “hibernate” or “off” mode, and/or completely or partially disable NFC component **120**. Some or all of the power management settings of power management subsystem **301** can be set automatically or by a user of device **100** (e.g., the user may define a duration and/or a condition before device **100** switches between particular power management modes and/or the components that may be at least partially disabled or turned off when switching between different power management modes, such as the NFC low power express mode). By forcing electronic device **100** to operate in such an NFC low power express mode, switch application module **320** may eventually allow electronic device **100** to securely utilize NFC component **120** for communications **55** in an efficient manner (e.g., until power supply **108** is no longer able to power electronic device **100** to operate in that mode (e.g., until a level of power supply **108** falls below threshold charge level **165**)).

[0064] Therefore, at least certain modules of power management subsystem **301** may be configured as a power management unit (“PMU”) that may be coupled to at least one source of power, such as power supply **108**. Such a PMU may include a microcontroller and can be configured to govern the power functions of device **100**. Such a PMU may include its own memory (e.g., loaded with software and/or firmware), processor with input/output functionality and timers, as well as one or more converters for measuring the power provided by power supply **108**. Moreover, additionally or alternatively, such a PMU may include a backup power source that can power components of power management subsystem **301** even when device **100** is completely shut down, such that, for example, the current time of a real-time clock (“RTC”) may be maintained. For example, an RTC **351** may be provided by subsystem **301** (e.g., by a power mode control application module **330** or otherwise), where RTC **351** may be provided as an integrated circuit (e.g., an integrated circuit with one or more general-purpose input/outputs (“GPIOs”)) and/or may include one or more registers **353** (e.g., one or more RTC counter registers and/or one or more PMU scratch pad registers). Such a PMU may be responsible for coordinating certain functions of device **100**, including, but not limited to, monitoring power connections and battery charges, controlling power provided to other components of device **100**, shutting down certain components of device **100** when they are left idle or deemed to be currently unnecessary to properly operate device **100**, regulating a real-time clock of device **100**, and controlling various power management modes of device **100**. A battery control circuit or power management stage may be connected to a battery and to the base-band/firmware processor. One or more dedicated connections from such a PMU and/or from power supply **108** to various elements of NFC component **120** (e.g., device module **130**, controller module **140**, and/or memory module **150**) may also be provided by power management subsystem **301**. These additional connections may be provided to enable a battery control circuit or power supply circuit to selectively power various components of device **100**, and especially the various components necessary to perform NFC communication with terminal **10**.

[0065] When switch application module **320** has received switch command **311** from mode detection module **310** and has thereafter generated and transmitted one or more commands (e.g., commands **321**, **323**, **325**, etc.) for at least partially adjusting one, some, or all components of device **100** for at least initially operating device **100** in the new power management mode, switch application module **320** may also be configured to generate and transmit a launching command **329** to a power mode control application module **330** of power management subsystem **301**. In response to receiving launching command **329**, control application module **330** may be configured to launch and run at least one application (e.g., application **143**) that may be specifically tailored to appropriately manage and/or otherwise control electronic device **100** in the new power management mode. Therefore, for example, operation of device **100** in an NFC LPE mode may be

based on one or more applications accessible to electronic device **100** (e.g., application **143**) and/or based on any input instructions being received by electronic device **100** (e.g., via input component **110**) that may control such an application.

[0066] As an example, when control application module **330** receives launching command **329** for managing device **100** in an NFC LPE power management mode, NFC component **120** may be initially configured by NFC command **321** and/or NFC direct power command **321d** to be in an active antenna mode (e.g., where antenna **116** and/or antenna **134** may be actively enabled for NFC communication by electronic device **100** itself (e.g., by power supply **108**)). It is to be understood that when NFC component **120** is initially configured by NFC command **321** and/or NFC direct power command **321d** to be in either the passive or active antenna modes, one or more other elements of NFC component **120** (e.g., an applet **153** of one or more SSDs **154**) may be initially disabled by NFC disabling command **321** and/or NFC direct power command **321d** to prevent a passive/active antenna from communicating a credential of NFC component **120** as communication **55** to terminal **10** (e.g., certain applets associated with certain credentials may have a particular register or flag set or not set (e.g., due to user preference) that may prevent those credentials from being used in a transaction with terminal **10** during an NFC LPE power management mode, while other certain applets associated with other certain credentials may have a particular register or flag set or not set (e.g., due to user preference) that may allow those credentials to be used in a transaction with terminal **10** during an NFC LPE power management mode). For example, one or more flags or registers in NFC component **120** (e.g., a flag or register in a particular SSD or applet associated with a particular credential) may be set (e.g., while device **100** is operating in a full or normal operating mode) to enable or not enable one or more particular credentials from being used while in an NFC LPE power management mode. Additionally or alternatively, an LPM flag (“LPMF”) may be set (e.g., to either ‘1’ or ‘0’), for example, in a PMU scratch pad register (e.g., register **353** (e.g., in non-volatile memory)) in a particular manner based on whether or not any credential has been enabled (e.g., by a user) for use when an NFC LPE mode is entered. For example, as shown in FIG. 5, an exemplary state machine **500** may be provided for illustrating various configurations of portions of electronic device **100** for determining whether an NFC LPE mode may be utilized by device **100**. Each state of state machine **500** may be possible while NFC component **120** is in an NFC full power mode of an NFC full power mode state **401** of state diagram **400** of FIG. 4. For example, at state **501** of state machine **500**, electronic device **100** may be in a state in which there is no credential provisioned on device **100** (e.g., in NFC component **120**) that has been selected (e.g., by a user or otherwise) for potential use in a communication **55** with terminal **10** during a future NFC low power express mode of operation of device **100**. In response to any suitable event **502** in which a first credential may be selected for potential use in a future NFC low power express mode (e.g., when a user selects or provisions a credential on device **100** as an “express mode card” or “express mode credential” (e.g., while device **100** is operating in a full or normal operating mode)), device **100** may be configured to transition from state **501** to a state **521** in which there is at least one credential provisioned on device **100** (e.g., in NFC component **120**) that has been selected (e.g., by a user or otherwise) for potential use in a communication **55** with terminal **10** during a future NFC low power express mode of operation of device **100**. During such a transition between state **501** and state **521**, device **100** may be configured to take one or more actions **506** (e.g., automatically) in order for device **100** to properly perform in accordance with that new state **521**. For example, as shown, action(s) **506** may include any suitable action or combination of actions, including, but not limited to, one or more of the following actions: [0067] (1) setting NFC_VEN_int=1; [0068] (2) setting NFC_GPIO2_AO=OPT_RESET_L=HIGH; [0069] (3) setting LPMF=1; [0070] (4) loading an output waveform onto a driver amplifier; [0071] (5) setting PMU_ALARM_EN=1; [0072] (6) configuring PMU_RTC_ALARM for a duration X; and/or [0073] (7) configuring a SW_Alarm for a duration X-1 (e.g., any suitable duration less (e.g., slightly less than duration X).

Similarly, in response to any suitable event **522** in which a last credential may be de-selected for potential use in a future NFC low power express mode (e.g., when a user adjusts the only credential on device **100** previously identified as an express mode card to a credential that is not to be identified as an express mode card or removes such a card altogether (e.g., while device **100** is operating in a full or normal operating mode)), device **100** may be configured to transition from state **521** to state **501** in which there is no credential provisioned on device **100** (e.g., in NFC component **120**) that has been selected (e.g., by a user or otherwise) for potential use in a communication **55** with terminal **10** during a future NFC low power express mode of operation of device **100**. During such a transition between state **521** and state **501**, device **100** may be configured to take one or more actions **526** (e.g., automatically) in order for device **100** to properly perform in accordance with that new state **501**. For example, as shown, action(s) **526** may include any suitable action or combination of actions, including, but not limited to, one or more of the following actions: [0074] (1) setting NFC_VEN_int=0; [0075] (2) setting LPMF=0; and/or [0076] (3) setting PMU_ALARM_EN=0.

Additionally or alternatively, in response to any suitable event **532** in which a SW_Alarm may clapse (e.g., be triggered) while device **100** is in state **521**, device **100** may be configured to take one or more actions **536** (e.g., automatically) in order for device **100** to properly respond to event **532**. For example, as shown, action(s) **536** may include any suitable action or combination of actions, including, but not limited to, one or more of the following actions: [0077] (1) setting PMU_ALARM_EN=1; [0078] (2) configuring PMU_RTC_ALARM for another duration X; and/or [0079] (3) configuring a SW_Alarm for duration X-1.

Each one of actions **506**, **526**, and **536** may be described in more detail with respect to FIG. **4** and operation of NFC component **120** in a low power express mode of electronic device **100**. It is understood that the various operations and conditions shown in state diagram **500** of FIG. **5** are only illustrative and that existing operations and conditions may be modified or omitted, additional operations and conditions may be added, and the order of certain operations and conditions may be altered.

[0080] Control application module **330** may be configured to receive any suitable input component command **331** from any suitable input component **110** (e.g., side button input component **110b**) that may be at least partially or at least temporarily enabled during the current power management mode (e.g., by power **325p** during a low power express mode). Additionally or alternatively, control application module **330** may be configured to provide any suitable output component command **333** to any suitable output component **112** that may be at least partially or at least temporarily enabled during the current power management mode (e.g., haptic output component **112c** by power **323p** during a low power express mode) or for waking up any suitable output component **112** that may be normally disabled during the current power management mode (e.g., display output component **112a** during a battery trap operating mode (e.g., a low power express mode)). Additionally or alternatively, control application module **330** may be configured to provide any suitable NFC component input command **339** to any suitable portion of NFC component **120** that may be at least partially or at least temporarily enabled during the current power management mode (e.g., by power **321p** during a low power express mode). Additionally or alternatively, control application module **330** may be configured to receive any suitable NFC component output command **341** from any suitable portion of NFC component **120** that may be at least partially or at least temporarily enabled during the current power management mode (e.g., by power **321p** during a low power express mode). Control application module **330** may be configured to generate any suitable one or more of commands **333** and/or **339** (and/or one or more of commands **321d**, **323d**, and/or **325d**) during the current power management mode, and/or to receive any suitable one or more of commands **331** and/or **341** during the current power management mode, for example, in accordance with any suitable power management mode application or rule set or state machine that may be specifically tailored to appropriately manage and/or otherwise control electronic device **100**.

in the current power management mode (e.g., state machine **400** of FIG. 4).

[0081] For example, as shown in FIG. 4, an exemplary state machine **400** may be provided for illustrating at least one particular manner in which power management subsystem **301** may operate for managing near field communications during a low power express mode of electronic device **100**. As shown, at an NFC full power mode (“NFC FPM”) state **401**, NFC component **120** may be powered on and may be functioning normally. For example, at state **401**, electronic device **100** may be operating in the full or normal operating mode (e.g., when a charge level of power supply **108** is within full operating charge level range **162** between threshold charge levels **161** and **163**), in which NFC component **120** and any other suitable components of device **100** (e.g., a display output component **112**, a touch screen input component **110**, an application processor **102** running any suitable operating system application and/or any suitable specific UI applications, a cellular communications component **106**, etc.) may be provided with power by power supply **108** (e.g., via power management system **301** (e.g., via a PMU)) and may be functioning normally. For example, as shown, while operating in an NFC full power mode of NFC FPM state **401**, NFC component **120** may be configured to carry out any suitable transactions or communications **55** between electronic device **100** and terminal **10** at operation **40** In using any credential of device **100** (e.g., whether or not the credential is currently designated as an express mode card). However, in response to detecting any suitable first condition **402**, the state of electronic device **100** may transition from state **401** to an NFC off power mode (“NFC OFF”) state **471**, at which NFC component **120** may be powered off (e.g., for conserving power), or, in response to detecting any suitable second condition **412**, the state of electronic device **100** may transition from state **401** to an NFC low power mode (“NFC LPM”) state **451**, at which NFC component **120** may remain powered but limited to enabling transactions for only credentials designated as an express mode card (e.g., for conserving power). For example, as shown, while operating in an NFC low power mode of NFC LPM state **451**, NFC component **120** may be configured to actively carry out any suitable transactions or communications **55** between electronic device **100** and terminal **10** at operation **451n** using any credential of device **100** that is currently designated as an express mode card. However, while operating in an NFC off power mode of NFC OFF state **471**, NFC component **120** may not be configured to actively carry out any suitable transactions or communications **55** between electronic device **100** and terminal **10** (e.g., due to NFC component **120** being not provided with any power in that state (although it is to be noted that certain passive transactions may be able to occur at NFC OFF state **471** if certain security measures are taken)).

[0082] For example, at state **471**, in which NFC component **120** may be powered off, electronic device **100** may be operating in any suitable operating mode, such as in a completely powered off mode (e.g., when device **100** has automatically shut down due to a charge level of power supply **108** falling within disconnect operating charge range **168** below threshold charge level **167** or when device **100** has any other suitable charge level but has been manually shut down by a user (e.g., a possible condition **402**)) or in a battery trap operating mode (e.g., when a charge level of power supply **108** has fallen below threshold charge level **163** and into one of ranges **164** or **166** (e.g., a possible condition **402**)). At state **471**, a system PMU of device **100** may be powered off or inactive, power may not be provided to NFC component **120** (e.g., via power management system **301** or directly through switch **321s**), and only limited functionality, if any, may be enabled for other portions of electronic device, such as a functionality for enabling a user to determine if device **100** is operating in the battery trap mode. For example, if device **100** is operating in the battery trap mode while at state **471**, a limited functionality may be enabled by device **100** for enabling the sensing of a particular user interaction with a particular input component (e.g., a user press of side button input component **110b** (e.g., detection of any suitable wake event condition **472**), where side button input component **110b** may be at least partially or at least temporarily enabled during the current power management mode (e.g., by power **325p** during the battery trap mode)) and then temporarily powering on display output component **112a** (e.g., by booting up a system PMU, then

booting up at least another portion or the rest of the system (e.g., a boot loader and potentially an operating system application)) for displaying a very specific UI screen (e.g., a “dead battery UI” screen **190b** of FIG. 2B (e.g., at an operation **482**)) in response to sensing such a particular user input component interaction, such that a user may be able to determine that device **100** is operating in the battery trap mode (e.g., to provide a user some peace of mind that device **100** is not in a power disconnect operating mode (e.g., of range **168**)). For example, while device **100** is operating in a battery trap mode (e.g., when the charge level **307** of power supply **108** is within one of ranges **164** and **166**) while NFC component is in an NFC off power mode at state **471**, in response to detection of a button press condition **472** by input component **110b** that may be powered directly by power **325p**, input component **110b** may be configured to generate and transmit any suitable input component command **331** to control application module **330**, which may be operative to wake up a system PMU such that control application module **330** may be configured to provide any suitable output component command **333** to display output component **112a** that may normally be disabled during a battery trap operating mode, where that command **333** may be operative to at least temporarily power on display output component **112a** for presenting at event **482** the “dead battery UI” screen **190b** of FIG. 2B to the user that may be indicative of the current battery trap mode of device **100** (e.g., via drained battery icon **201**) but that may not be indicative of any express mode cards being enabled in the current battery trap mode (e.g., due to NFC component **120** being in the NFC OFF power mode state of state **471**) (e.g., as compared to a “Express Mode capability UI” screen **190a** of FIG. 2A that may be presented to a user at event **455** that may be indicative of a current battery trap mode of device **100** (e.g., via drained battery icon **201**) but that may also be indicative of at least one express mode card being enabled in the current battery trap mode (e.g., due to NFC component **120** being in an NFC low power mode of state **451**) (e.g., via text **203**). As shown by a distinction line (“DL”), all operations above line DL in state diagram **400** may be carried out when a system PMU of device **100** may be powered on and/or awake and/or active (e.g., when an operating system application or a boot loader application or otherwise may be in use by device **100**), while all operations below line DL in state diagram **400** may be carried out when a system PMU of device **100** may be in an off state or powered off or inactive. For example, when a PMU is in an off state, the PMU may still not be completely turned off, as it may still support processing button presses or one or more other functionalities (e.g., a PMU may include at least one always on domain in the PMU that's still alive when the PMU is in an off state). Alternatively, a PMU may be completely off in an off state. NFC transactions and/or haptic feedback and/or other certain output feedback may be able to occur completely independent of a system PMU (e.g., a PMU can remain in an off state while an NFC component and/or an output component may operate in a low power mode (e.g., an NFC component and/or an output component may be powered on by its own by a power source without relying on any rails from the PMU, and/or may receive the same or different amounts of power when operating in a low power mode or full power mode)). It is to be understood that any suitable wake event or condition **452** and/or **472** may be configured as any suitable user interaction that is properly enabled by device **100** (e.g., raise to wake gesture, a tap on a touch-sensitive display, a voice trigger, a button press, etc.).

[0083] One or more suitable conditions **402** may be satisfied in order to transition from state **401** to state **471**, including, but not limited to, a condition in which a user manually shuts down (e.g., powers off) device **100** (e.g., by pressing and holding side button **110b** for at least a particular duration of time (e.g., 3 seconds)), or a condition in which not only is the current charge of power supply **108** below threshold charge level **163** (e.g., as may be detected by module **310** using power level data **307**) but also no credential on device **100** is currently designated as an express mode card (e.g., as may be determined when LPMF is equal to ‘0’ (e.g., as may be enforced by an action **526** of state diagram **500**)). In some particular embodiments, NFC component **120** may be configured to transition from NFC FPM state **401** to NFC OFF state **471** when a particular NFC state transition

sequencing protocol is carried out at operation **403**. For example, as shown by an NFC state transition sequencing protocol of an NFC state transition operation **403**, NFC component **120** may be configured to transition from NFC FPM state **401** to NFC OFF state **471** (e.g., after a certain order of certain operations (e.g., when a GPIO output from a system PMU to NFC component **120** (e.g., “NFC_EN”) is set to “LOW” at least a certain amount of time (e.g., buffer or margin time (e.g., 3 milliseconds)) prior to disabling a supply rail for NFC component **120** (e.g., a 1.8 Volt supply rail “PP1V8_NFC”), although any other suitable operations may transition NFC component **120** between state **401** and state **471**)).

[0084] Alternatively, one or more suitable other conditions **412** may be satisfied in order to transition from state **401** to state **451**, including, but not limited to, a condition in which at least one credential on device **100** is currently designated as an express mode card (e.g., as may be determined when LPMF is equal to ‘1’ (e.g., as may be enforced by an action **506** of state diagram **500**)) when a user manually instructs device **100** to enter an NFC low power express mode (e.g., in response to power management system receiving particular input mode selection data **309** from an input component **110**) (e.g., for conserving device power while maintaining the functionality of the at least one credential of NFC component **120** designated as an express mode card), or a condition in which at least one credential on device **100** is currently designated as an express mode card when the current charge of power supply **108** is detected to fall below threshold charge level **163** (e.g., as may be detected by module **310** using power level data **307**), or a condition in which at least one credential on device **100** is currently designated as an express mode card when an undervoltage-lockout (“UVLO”) event is detected (e.g., when a voltage of a battery of power supply **108** is detected to fall below any suitable UVLO threshold of a system PMU of device **100**). In some particular embodiments, NFC component **120** may be configured to transition from NFC FPM state **401** to NFC LPM state **451** when a particular NFC state transition sequencing protocol is carried out at operation **413**. For example, as shown by an NFC state transition sequencing protocol of an NFC state transition operation **413**, NFC component **120** may be configured to transition from NFC FPM state **401** to NFC LPM state **451** (e.g., after a certain order of certain operations (e.g., when a GPIO output from a system PMU to NFC component **120** (e.g., “NFC_EN”) is set to “LOW” within at least a certain amount of time (e.g., buffer or margin time (e.g., 3 milliseconds)) of disabling a supply rail for NFC component **120** (e.g., a 1.8 Volt supply rail “PP1V8_NFC”), although any other suitable operations may transition NFC component **120** between state **401** and state **451**)). For example, such an NFC state transition sequencing protocol may be implemented in hardware by a PMU power down sequencer of device **100**.

[0085] At NFC LPM state **451**, in which NFC component **120** may be powered (e.g., directly by power **321p** via switch **321s**) while a system PMU may be inactive, electronic device **100** may be configured to operate in an NFC low power express mode (e.g., mode in which device **100**, to conserve power, has turned off processor **102** and every communications component **106** and every output component **112** and every input component **110**, except, perhaps, a particular output component **112** (e.g., haptic output component **112c**) and/or a particular input component **110** (e.g., side button input component **110b**) to enable a user to detect that device **100** is operating in the NFC low power express mode. Therefore, at state **451**, a system PMU of device **100** may be powered off or inactive, power may be provided to NFC component **120** (e.g., directly through switch **321s**), and only limited functionality, if any, may be enabled for other portions of electronic device, such as a functionality for enabling a user to determine if device **100** is operating in the NFC low power express mode. For example, if device **100** is operating in the NFC low power express mode while at state **451**, a limited functionality may be enabled by device **100** for enabling the sensing of any suitable wake event or particular user interaction with a particular input component (e.g., a user press of side button input component **110b** (e.g., detection of any suitable wake event condition **452**), where side button input component **110b** may be at least partially or at least temporarily enabled during the current power management mode (e.g., by power **325p** during

the NFC low power express mode of a battery trap mode)) and then, in response to sensing such a particular user input component interaction and in response to a determination at operation **453** that a particular power supply condition **454** is satisfied, temporarily powering on display output component **112a** for displaying a very specific UI screen (e.g., a “Express Mode capability UI” screen **190a** of FIG. 2A (e.g., at an operation **455**)), such that a user may be able to determine that device **100** is operating in the NFC low power express mode (e.g., to provide a user some peace of mind that an express mode NFC transaction may be possible). For example, while device **100** is operating in the NFC low power express mode while NFC component is in an NFC LPM power mode at state **451**, in response to detection of any suitable wake event **452** (e.g., button press condition **452** by input component **110b** that may be powered directly by power **325p**), input component **110b** may be configured to generate and transmit any suitable input component command **331** to control application module **330**, which may be operative to wake up a system PMU such that control application module **330** may be configured to make a determination at operation **453** that particular power supply condition **454** is satisfied and then to provide any suitable output component command **333** to display output component **112a** that may normally be disabled during a NFC low power express mode of a battery trap operating mode, where that command **333** may be operative to at least temporarily power on display output component **112a** for presenting at event **455** the “Express Mode capability UI” screen **190a** of FIG. 2A to the user that may be indicative of the current battery trap mode of device **100** and that may be indicative of the fact that at least one express mode card is enabled in the current NFC low power express mode of the current battery trap mode (e.g., due to NFC component **120** being in the NFC LPM power mode state of state **451**) (e.g., as compared to a “dead battery UI” screen **190b** of FIG. 2B that may be presented to a user at event **482** that may be indicative of only a current battery trap mode of device **100** but that may not also be indicative of at least one express mode card being enabled in the current battery trap mode (e.g., due to NFC component **120** being in an NFC OFF power mode of state **471**)).

[0086] The determination at operation **453** may be any suitable determination of any suitable power supply condition. For example, in some embodiments, operation **453** may be operative to determine a condition of a “LOW_V” flag, which may be configured to be indicative of a relationship between the current charge of power supply **108** and a particular threshold charge level. As a particular example, operation **453** may generally be used to determine whether the current charge level of power supply **108** is above or below LPEM-off threshold charge level **165**, which may be useful to determine whether to keep NFC component **120** in the NFC LPM power mode of state **451** or to transition NFC component **120** from the NFC LPM power mode of state **451** to the NFC OFF power mode of state **471** (e.g., for conserving power by powering off NFC component **120** and terminating the NFC low power express mode while still remaining in a battery trap mode (e.g., a low battery trap operating mode)). In a particular example, device **100** (e.g., device firmware) may be configured to set a LOW_V flag (e.g., a flag of a register of a system PMU) to be equal to ‘1’ if each one of any suitable number of consecutive samples (e.g. 10 consecutive samples) of the current charge level of power supply **108** (e.g., using data **307**) is determined to be less than LPEM-off threshold charge level **165** and may be configured to clear or reset the LOW_V flag to be equal to ‘0’ when the current charge level of power supply **108** is determined to be at least a certain amount greater than LPEM-off threshold charge level **165** (e.g., at least 0.05 Volts greater than LPEM-off threshold charge level **165**). Therefore, device **100** may be configured to make a confident determination at operation **453** that the current charge level of power supply **108** is either greater than LPEM-off threshold charge level **165** by satisfying condition **454** (e.g., LOW_V=0) or less than LPEM-off threshold charge level **165** by satisfying condition **457** (e.g., LOW_V=1). Thus, in response to device **100** detecting button press condition **452** and then determining at operation **453** that the current charge level of power supply **108** is greater than LPEM-off threshold charge level **165** by satisfying condition **454**, device **100** may be

configured to present “Express Mode capability UI” screen **190a** of FIG. 2A at operation **455** and then return to (e.g., maintain NFC component **120** in the NFC LPM mode of) state **451** (e.g., via operation **456**, at which a PMU RTC Alarm may be set), as power supply **108** may be operating in LPEM operating charge level range **164**.

[0087] Alternatively, in response to device **100** detecting button press condition **452** and then determining at operation **453** that the current charge level of power supply **108** is less than LPEM-off threshold charge level **165** by satisfying condition **457**, device **100** may be configured to transition NFC component **120** from the NFC LPM mode of state **451** to the NFC OFF mode of state **471** (e.g., via operation **458** and either operation **474** or operations **459** and **462** via state **461**), as power supply **108** may no longer be operating in LPEM operating charge level range **164**. Instead, in order to operate in a low battery trap operating mode for conserving further power by disabling NFC component **120**, device **100** may be operative transition NFC component **120** from the NFC low power mode of NFC LPM state **451** to the NFC off power mode of NFC OFF state **471**. Device **100** may be operative to carry out such a transition by first carrying out operation **458**. At operation **458**, device **100** may be configured to set LPMF to ‘0’, which may prevent any credential on device **100** from being used as an express mode card until LPMF may be re-set back to ‘1’ (e.g., at operation **499**, where a user of device **100** may be reauthenticated (e.g., by entering a PIN to access functionality of a device operating system (e.g., to access screen **190** of FIG. 2)) once NFC component **120** has been transitioned back from the NFC off power mode of NFC OFF state **471** to the NFC full power mode of NFC FPM state **401** (e.g., via operations **492**, **494**, and **497**), which may provide a layer of security to prevent an unauthorized user from being able to use an express card if/when device **100** were to ever return to NFC LPM state **451** after arriving at NFC OFF state **471**). Additionally or alternatively, at operation **458**, device **100** may be configured to disable an alarm (e.g., a PMU_RTC_ALARM (e.g., by setting PMU_ALARM_EN to ‘0’)), such that the alarm may not timeout for initiating a routine while in NFC OFF state **471**. After operation **458**, device **100** may be configured to transition NFC component **120** from the NFC LPM mode of state **451** directly to the NFC OFF mode of state **471** when a particular NFC state transition sequencing protocol is carried out at operation **474**. Alternatively, NFC component **120** may be configured to transition from the NFC LPM mode of state **451** to the NFC OFF mode of state **471** indirectly via a quick intermediate transition from the NFC LPM mode of state **451** to the NFC FPM mode of state **461**. For example, NFC component **120** may be configured to transition from NFC LPM state **451** to NFC FPM state **461** when a particular NFC state transition sequencing protocol is carried out at operation **459** (e.g., after a certain order of certain operations (e.g., when a supply rail for NFC component **120** (e.g., a 1.8 Volt supply rail “PP1V8_NFC”) is enabled at least a certain amount of time (e.g., buffer or margin time (e.g., 3 milliseconds)) prior to setting to “HIGH” a GPIO output from a system PMU to NFC component **120** (e.g., “NFC_EN”), although any other suitable operations may transition NFC component **120** between state **451** and state **461**)), and then NFC component **120** may be configured to transition from NFC FPM state **461** to NFC OFF state **471** when a particular NFC state transition sequencing protocol is carried out at operation **462** (e.g., after a certain order of certain operations (e.g., when a GPIO output from a system PMU to NFC component **120** (e.g., “NFC_EN”) is set to “LOW” at least a certain amount of time (e.g., buffer or margin time (e.g., 3 milliseconds)) prior to disabling a supply rail for NFC component **120** (e.g., a 1.8 Volt supply rail “PPIV8_NFC”), although any other suitable operations may transition NFC component **120** between state **461** and state **471**)). Then, once NFC component **120** has been transitioned to the NFC off power mode of NFC OFF state **471**, NFC component **120** may remain in the NFC off power mode of NFC OFF state **471** until power supply **108** has been charged above a particular threshold charge level (e.g., threshold charge level **163**) for enabling the transition back to the NFC full power mode of NFC FPM state **401**. For example, as shown, when in state **471**, device **100** may be operative to carry out a device charging operation **492** (e.g., in response to any suitable charging event (e.g., a user plugging device **100** into an electrical outlet for

receiving external power generated by an electrical power plant)), during which any suitable “Charge & Display UI” screen may be presented to a user at event **494** (e.g., to enable a user to determine that the device is being properly charged). However, until operation **492** results in the charge level of power supply **108** passing above a particular threshold charge level (e.g., threshold charge level **163**) for satisfying condition **496** for enabling the transition back to the NFC full power mode of NFC FPM state **401** at operation **497**, device **100** may satisfy condition **495** and may remain in the NFC FPM state **471**. Therefore, device **100** may enable charging of power supply **108** for returning to FPM state **401** from OFF state **471**, but may not enable charging of power supply **108** for returning only to LPM state **451** from OFF state **471**. Moreover, it is to be understood that if device transitioned to OFF state **471** from ON state **401** in response to a condition **402** in which a user manually shut down (e.g., powered off) device **100**, then operation **492** may include a user attempting to manually turn back on device **100**, in which case condition **496** may be satisfied and device **100** may transition back from state **471** to state **401** without any actual charging of power supply **108**.

[0088] With further reference to state **451**, if device **100** is operating in the NFC low power express mode while at state **451**, rather than (e.g., before) detection of any button press condition **452** for initiating a user-initiated device capability check process, an alarm timeout condition **442** may be detected for initiating a silent device-initiated device capability check process, in response to which device **100** may be operative to make a determination at operation **463** about the current charge level of power supply **108** with respect to any suitable threshold charge level (e.g., threshold charge level **165**). For example, alarm timeout condition **442** may be a condition in which a PMU_RTC_ALARM is triggered, where such a condition may be triggered when an RTC counter register value of an RTC (e.g., a value of a first register **353** of RTC **351**) is greater than a defined PMU_RTC_ALARM value (e.g., a stored value in hardware of a system PMU). As shown in FIG. 5, while device **100** may be in state **521** and operating in a full power operating mode, in response to any suitable event **532** in which a SW_Alarm may elapse (e.g., be triggered), device **100** may be configured to take one or more actions **536**, including, but not limited to, one or more of the following actions: [0089] (1) setting PMU_ALARM_EN=1, which may enable an alarm of a system PMU to be enabled and/or set and/or monitored; [0090] (2) configuring PMU_RTC_ALARM for another duration X, which may reset the value of PMU_RTC_ALARM by any suitable duration X; and/or [0091] (3) configuring a SW_Alarm for X-1 minutes, which may reset the value of a software alarm by any suitable duration that may be at least slightly less than the reset duration of the PMU_RTC_ALARM, or, other embodiments, the SW_alarm may be any other suitable software alarm, which could be a part of any other periodic system wakeup event (e.g., to check for cellular signal strength, etc.).

This may enable the PMU_RTC_ALARM to be continuously reset to a duration X (e.g., 1 hour, 2 hours, 4 hours, etc.) at a periodic frequency at least slightly less than duration X while device **100** may be in the full power state **521** (e.g., state **401** when LPMF is set to ‘1’). Therefore, a hardware based PMU alarm (PMU_RTC_ALARM) may always be active when device **100** may transition from NFC FPM state **401** to NFC LPM state **451**, such that alarm timeout condition **442** ought to occur at least within duration X of the transition from state **401** to state **451**. In response to detection of a PMU alarm (PMU_RTC_ALARM) timing out at condition **442**, device **100** may be operative to (e.g., further) wake up a system PMU such that control application module **330** may be configured to make a determination at operation **463** that particular power supply condition **464** is satisfied and then to re-set the PMU alarm (PMU_RTC_ALARM) (e.g., to duration X) at operation **456** before returning to NFC LPM state **451**. Alternatively, in response to detection of a PMU alarm (PMU_RTC_ALARM) timing out at condition **442**, device **100** may be operative to (e.g., further) wake up a system PMU such that control application module **330** may be configured to make a determination at operation **463** that particular power supply condition **465** is satisfied and then to proceed to operation **458** for transitioning NFC component **120** from NFC LPM state **451** to NFC

OFF state **471**.

[0092] The determination at operation **463** may be any suitable determination of any suitable power supply condition, such as the same operation as operation **453** or an operation substantially similar to operation **453**. For example, in some embodiments, operation **463** may be operative to determine a condition of a “LOW_V” flag, which may be configured to be indicative of a relationship between the current charge of power supply **108** and a particular threshold charge level. As a particular example, operation **463** may generally be used to determine whether the current charge level of power supply **108** is above or below LPEM-off threshold charge level **165**, which may be useful to determine whether to keep NFC component **120** in the NFC LPM power mode of state **451** or to transition NFC component **120** from the NFC LPM power mode of state **451** to the NFC OFF power mode of state **471** (e.g., for conserving power by powering off NFC component **120** and terminating the NFC low power express mode while still remaining in a battery trap mode (e.g., a low battery trap operating mode)). In a particular example, device **100** (e.g., device firmware) may be configured to set a LOW_V flag (e.g., a flag of a register of a system PMU) to be equal to ‘1’ if each one of any suitable number of consecutive samples (e.g. 10 consecutive samples) of the current charge level of power supply **108** (e.g., using data **307**) is determined to be less than LPEM-off threshold charge level **165** and may be configured to clear or reset the LOW_V flag to be equal to ‘0’ when the current charge level of power supply **108** is determined to be at least a certain amount greater than LPEM-off threshold charge level **165** (e.g., at least 0.05 Volts greater than LPEM-off threshold charge level **165**). Therefore, device **100** may be configured to make a confident determination at operation **463** that the current charge level of power supply **108** is either greater than LPEM-off threshold charge level **165** by satisfying condition **464** (e.g., LOW_V=0) or less than LPEM-off threshold charge level **165** by satisfying condition **465** (e.g., LOW_V=1). Thus, in response to device **100** detecting RTC alarm timeout condition **442** and then determining at operation **463** that the current charge level of power supply **108** is greater than LPEM-off threshold charge level **165** by satisfying condition **464**, device **100** may be configured to return to (e.g., maintain NFC component **120** in the NFC LPM mode of) state **451** (e.g., via operation **456**, at which a PMU RTC Alarm may be re-set), as power supply **108** may be operating in LPEM operating charge level range **164**. Alternatively, in response to device **100** detecting RTC alarm timeout condition **442** and then determining at operation **463** that the current charge level of power supply **108** is less than LPEM-off threshold charge level **165** by satisfying condition **465**, device **100** may be configured to transition NFC component **120** from the NFC LPM mode of state **451** to the NFC OFF mode of state **471** (e.g., via operation **458** and either operation **474** or operations **459** and **462** via state **461**), as power supply **108** may no longer be operating in LPEM operating charge level range **164**. Therefore, condition **442** may enable device **100** to periodically determine whether or not to transition from state **451** to state **471** (e.g., especially in absence of any regular condition **452**).

[0093] NFC component **120** may remain in the NFC low power mode of NFC LPM state **451** until power supply **108** has been charged above a particular threshold charge level (e.g., threshold charge level **163**) for enabling the transition back to the NFC full power mode of NFC FPM state **401**. For example, as shown, when in state **451**, device **100** may be operative to carry out a device charging operation **466** (e.g., in response to any suitable charging event (e.g., a user plugging device **100** into an electrical outlet for receiving external power generated by an electrical power plant)), during which any suitable “Charge & Display UI” screen may be presented to a user at event **467** (e.g., to enable a user to determine that the device is being properly charged). However, until operation **466** results in the charge level of power supply **108** passing above a particular threshold charge level (e.g., threshold charge level **163**) for satisfying condition **468** for enabling the transition back to the NFC full power mode of NFC FPM state **401** at operation **498** (e.g., an operation that may be similar to operation **459**), device **100** may satisfy condition **469** and may remain in the NFC LPM state **451**. Therefore, device **100** may enable charging of power supply **108** for returning to FPM

state **401** from LPM state **451**, and may also enable charging of power supply **108** for returning to LPM state **451** from LPM state **451** (e.g., to remain in LPM state **451** if the charging accomplished at operation **466** is not sufficient to satisfy condition **468**). Moreover, it is to be understood that if device transitioned to LPM state **451** from ON state **401** in response to a condition **412** in which a user manually instructed such a transition, then operation **466** may include a user attempting to manually instruct a transition back from state **451** to state **401** (e.g., through any suitable interaction with an enabled input component (e.g., through a long hold of button input component **110b** or another input component interaction)), in which case condition **466** may be satisfied and device **100** may transition back from state **451** to state **401** without any actual charging of power supply **108**. It is understood that the various operations and conditions shown in state diagram **400** of FIG. **4** are only illustrative and that existing operations and conditions may be modified or omitted, additional operations and conditions may be added, and the order of certain operations and conditions may be altered.

[0094] As mentioned, while operating in an NFC low power mode of NFC LPM state **451**, NFC component **120** may be configured to carry out any suitable transactions or communications **55** between electronic device **100** and terminal **10** at operation **451n** using any credential of device **100** that is currently designated as an express mode card. At any point during even an attempt at a transaction at operation **451n** or after a transaction has been **451n**, device **100** may be configured to generate any suitable output that may be operative to indicate such an attempted or completed transaction to a user of device **100**. However, due to the fact that a majority or the entirety of all software and/or applications and/or even a system PMU may be inactive or off during such an attempt or at such a completion of operation **451n**, NFC component **120** may be operative to control the generation and transmission of an appropriate command for inciting such an output to user. For example, as shown in FIG. **3**, NFC component **120** may be configured to generate and transmit any suitable NFC activity output command **341** directly to any suitable output component **112** that may be operable during the NFC LPM mode of operation of state **451** (e.g., haptic output component **112c** that may be powered by power **323p** directly from power supply **108** during the NFC LPM mode of operation of state **451**). For example, haptic feedback output component **112c** may include a haptic driver amplifier **361** on which may be loaded a haptic waveform **363** that may be automatically played back by haptic driver amplifier **361** in response to haptic feedback output component **112c** receiving an NFC activity output command **341** from NFC component **120** while device **100** may be operating in an NFC low power mode of NFC LPM state **451**. This may enable device **100** to provide haptic feedback to a user in response to NFC component **120** at least attempting to conduct a transaction with terminal **55** using an express mode card while device **100** may be operating in an NFC low power mode of NFC LPM state **451** (e.g., without a system PMU may be inactive or off and may not be providing any power to any output component or NFC component of device **100**). As shown in FIG. **5** by an action **506** when a first express mode card is enabled on device **100**, an output waveform (e.g., waveform **363**) may be loaded onto a driver amplifier (e.g., amplifier **361**) (e.g., a haptic waveform may be loaded onto a haptic driver amplifier and/or an audio waveform may be loaded onto an audio driver amplifier), and/or a GPIO (“NFC_GPIO2_AO=OPT_RESET_L=HIGH”) may be set high as always on to enable haptic driver amplifier **361** to be triggered in an NFC low power mode, such that it may be ensured that a haptic waveform may be available for playback during an NFC low power mode. Although this output has been described as a haptic feedback output using a haptic feedback output component, it is to be understood that various other types of output information may be presented by any other suitable output component other than a haptic output component (e.g., user information may be provided audibly to a user via audio speaker output component **112b** (e.g., any suitable audio waveform may be loaded onto any suitable audio driver amplifier and used in a similar manner to any haptic waveform and/or any haptic driver amplifier described above) or visibly to a user via a visual output component (e.g., an LED)). Therefore, device **100** may be operative to carry out one

or more NFC transactions and provide any suitable output that may be operative to indicate such an attempted or completed transaction to a user of device **100** while in a low powered operating state at which both a system PMU and any device operating system may be off or disabled or inactive. Various transitions between states of state diagram **400** (e.g., above line DL) may be accomplished using a system PMU and a boot loader application of device **100** but not a full operating system application, such that significant power savings may be realized, while certain actions within a state (e.g., below line DL (e.g., action **451n**, which may include generating a haptic or other user detectable output)) may be accomplished without even using a system PMU or loading any application for realizing additional power savings while also securely enabling certain NFC transactions for improving user convenience.

[0095] Although many of the concepts described herein (e.g., with respect to one, some, or each of FIGS. 1-5) have been described with respect to managing near field communications (e.g., by NFC component **120**) during different power management modes of an electronic device, it is to be understood that various other types of communications (e.g., by any other suitable communications component or communications circuitry) and/or any other suitable device functionalities may be similarly managed. For example, any suitable first type of communications circuitry **106** (e.g., a higher powered communications circuitry, such as broadband cellular network communications circuitry or Wi-Fi, etc.) may be turned off or disabled or inactive during any suitable battery trap operating mode while any suitable second type of communications circuitry **106** (e.g., a lower powered communications circuitry, such as Bluetooth or the like) may be selectively or continuously used during any suitable battery trap operating mode. Therefore, device **100** may be operative to carry out one or more specific communication type functionalities (e.g., Bluetooth communications) and provide any suitable output that may be operative to indicate such an attempted or completed communication of that type to a user of device **100** (e.g., playing back a particular audio waveform in response to a Bluetooth communication being received by the device) while in a low powered operating state at which both a system PMU and any device operating system and/or any other communication type functionalities (e.g., cellular) may be off or disabled or inactive. Various transitions between states of state diagram **400** (e.g., above line DL) may be accomplished using a system PMU and a boot loader application of device **100** but not a full operating system application, such that significant power savings may be realized, while certain actions within a state (e.g., below line DL (e.g., action **451n**, which may include generating a haptic or other user detectable output)) may be accomplished without even using a system PMU or loading any application for realizing additional power savings while also securely enabling certain types of communications for improving user convenience (e.g., enabling Bluetooth communications to provide certain functionality to the device in the low powered operating state (e.g., communicate with other devices via Bluetooth to enable detection of the device in the low powered operating state) (e.g., the LPMF may be set to '1' if a user wishes for the Bluetooth communication component to be enabled during the low powered operating state and the LPMF may be set to '0' if a user wishes for the Bluetooth communication component not to be enabled during the low powered operating state)). Therefore, if the device's operating system is not running because the device needs to be charged, there may still be enough power in the battery to support the express mode (e.g., to support "Express Card" transactions). The device may be configured to automatically support this feature with any suitable credentials, including, but not limited to, a transit card designated as an "Express Transit" card (e.g., automatically upon provisioning or manually by a user), student ID cards with "Express Mode" turned on, and/or the like. The device may be configured such that, in response to receiving any suitable user interaction with any suitable device input component, such as a user pressing a side button, the device may display a low battery icon as well as text indicating Express Cards are available to use. The NFC controller may perform express card transactions under the same conditions as when the device's operating system is running, except that transactions may be indicated with only limited output component use (e.g.,

haptic notification, but without any visible notification being presented). This feature may not be available when a standard user initiated shutdown is performed.

[0096] FIG. 6 is a flowchart of an illustrative process **600** for operating an electronic device that includes a near field communication component. At operation **602** of process **600**, while the electronic device is operating in a normal power mode of the electronic device, during which the near field communication component is operating in a full power mode of the near field communication component, a low power mode initiation event may be detected with the electronic device (e.g., the charge of power supply **108** of device **100** may be detected to be below threshold **163**). At operation **604** of process **600**, in response to the detection of operation **602** of process **600**, a status of a low power mode flag (LPMF) of the electronic device may be determined (e.g., a status of the LPMF of device **100** may be determined). At operation **606** of process **600**, in response to the detection of operation **602** of process **600**, the electronic device may be transitioned from operating in the normal power mode of the electronic device to operating in a low power mode of the electronic device by disabling a plurality of subsystems of the electronic device, transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in a low power mode of the near field communication component when the determined status of the LPMF is a first status, and transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in an off mode of the near field communication component when the determined status of the LPMF is a second status that is different than the first status, wherein the near field communication component uses less power when operating in the off mode of the near field communication component than when operating in the low power mode of the near field communication component (e.g., device **100** may transition from a normal power mode to a low power mode by disabling a power management unit and/or a device operating system of device **100**, and by providing power from power supply **108** to NFC component **120** for enabling communication of an express mode credential when LPMF=1 (e.g., by configuring NFC component **120** in an NFC low power mode state **451**) or by providing no power from power supply **108** to NFC component **120** when LPMF=0 (e.g., by configuring NFC component **120** in an NFC off mode state **471**)).

[0097] It is understood that the operations shown in process **600** of FIG. 6 are only illustrative and that existing operations may be modified or omitted, additional operations may be added, and the order of certain operations may be altered.

[0098] FIG. 7 is a flowchart of an illustrative process **700** for operating an electronic device that includes a communication component and a power supply. At operation **702** of process **700**, a low power mode initiation event may be detected with the electronic device (e.g., the charge of power supply **108** of device **100** may be detected to be below threshold **163**). At operation **704** of process **700**, in response to the detection of operation **702** of process **700**, at least one of a power management unit of the electronic device or an operating system of the electronic device may be disabled (e.g., a power management unit and/or a device operating system of device **100** may be disabled). At operation **706** of process **700**, in response to the detection of operation **702** of process **700**, when at least one express mode credential is available on the electronic device, power may be provided from the power supply to the communication component for enabling the communication component to communicate data from the at least one express mode credential to a remote terminal (e.g., NFC component **120** may be provided with power from power supply **108** for enabling communication of an express mode credential when LPMF=1). At operation **708** of process **700**, in response to the detection of operation **702** of process **700**, when no express mode credential is available on the electronic device, the communication component may be prevented from receiving any power from the power supply (e.g., no power may be provided by power supply **108** to NFC component **120** when LPMF=0).

[0099] It is understood that the operations shown in process **700** of FIG. 7 are only illustrative and

that existing operations may be modified or omitted, additional operations may be added, and the order of certain operations may be altered.

[0100] FIG. 8 is a flowchart of an illustrative process **800** for operating an electronic device that includes a communication component, a memory register, and a battery. At operation **802** of process **800**, a charge of the battery may be detected to be below a predetermined threshold (e.g., the charge of power supply **108** of device **100** may be detected to be below threshold **163**). At operation **804** of process **800**, in response to the detection of operation **802** of process **800**, a number of subsystems of the electronic device may be disabled (e.g., a power management unit and/or a device operating system and/or a touch screen input component of device **100** may be disabled). At operation **806** of process **800**, in response to the detection of operation **802** of process **800**, when the status of the memory register is a first status, power may be provided from the battery to the communication component for enabling the communication component to communicate data with a remote terminal (e.g., NFC component **120** may be provided with power from power supply **108** for enabling communication of an express mode credential when LPMF=1). At operation **808** of process **800**, in response to the detection of operation **802** of process **800**, when the status of the memory register is a second status that is different than the first status, the communication component may be prevented from receiving any power from the battery (e.g., no power may be provided by power supply **108** to NFC component **120** when LPMF=0).

[0101] It is understood that the operations shown in process **800** of FIG. 8 are only illustrative and that existing operations may be modified or omitted, additional operations may be added, and the order of certain operations may be altered.

[0102] Moreover, one, some, or all of the processes described with respect to FIGS. 1-8 may each be implemented by software, but may also be implemented in hardware, firmware, or any combination of software, hardware, and firmware. Instructions for performing these processes may also be embodied as machine- or computer-readable code recorded on a machine- or computer-readable medium. In some embodiments, the computer-readable medium may be a non-transitory computer-readable medium. Examples of such a non-transitory computer-readable medium include but are not limited to a read-only memory, a random-access memory, a flash memory, a CD-ROM, a DVD, a magnetic tape, a removable memory card, and a data storage device (e.g., an optical data storage device, such as memory **104** and/or memory module **150** of FIG. 1). In other embodiments, the computer-readable medium may be a transitory computer-readable medium. In such embodiments, the transitory computer-readable medium can be distributed over network-coupled computer systems so that the computer-readable code is stored and executed in a distributed fashion. For example, such a transitory computer-readable medium may be communicated from one electronic device to another electronic device using any suitable communications protocol (e.g., the computer-readable medium may be communicated to electronic device **100** via communications component **106** (e.g., as at least a portion of application **103** and/or application **143**)). Such a transitory computer-readable medium may embody computer-readable code, instructions, data structures, program modules, or other data in a modulated data signal, such as a carrier wave or other transport mechanism, and may include any information delivery media. A modulated data signal may be a signal that has one or more of its characteristics set or changed in such a manner as to encode information in the signal.

[0103] It is to be understood that any or each module of either one or both of NFC component **120** and power management subsystem **301** may be provided as a software construct, firmware construct, one or more hardware components, or a combination thereof. For example, any or each module of either one or both of NFC component **120** and power management subsystem **301** may be described in the general context of computer-executable instructions, such as program modules, that may be executed by one or more computers or other devices. Generally, a program module may include one or more routines, programs, objects, components, and/or data structures that may perform one or more particular tasks or that may implement one or more particular abstract data

types. It is also to be understood that the number, configuration, functionality, and interconnection of the modules of either one or both of NFC component **120** and power management subsystem **301** are only illustrative, and that the number, configuration, functionality, and interconnection of existing modules may be modified or omitted, additional modules may be added, and the interconnection of certain modules may be altered.

[0104] At least a portion of one or more of the modules of either one or both of NFC component **120** and power management subsystem **301** may be stored in or otherwise accessible to device **100** in any suitable manner (e.g., in memory **104** of device **100** (e.g., as at least a portion of application **103** and/or application **143**)). Any or each module of either one or both of NFC component **120** and power management subsystem **301** may be implemented using any suitable technologies (e.g., as one or more integrated circuit devices), and different modules may or may not be identical in structure, capabilities, and operation. Any or all of the modules or other components of either one or both of NFC component **120** and power management subsystem **301** may be mounted on an expansion card, mounted directly on a system motherboard, or integrated into a system chipset component (e.g., into a “north bridge” chip).

[0105] Any or each module of either one or both of NFC component **120** and power management subsystem **301** may be a dedicated system implemented using one or more expansion cards adapted for various bus standards. For example, all of the modules may be mounted on different interconnected expansion cards or all of the modules may be mounted on one expansion card. With respect to NFC component **120**, by way of example only, the modules of NFC component **120** may interface with a motherboard or processor **102** of device **100** through an expansion slot (e.g., a peripheral component interconnect (“PCI”) slot or a PCI express slot). Alternatively, NFC component **120** need not be removable but may include one or more dedicated modules that may include memory (e.g., RAM) dedicated to the utilization of the module. In other embodiments, NFC component **120** may be integrated into device **100**. For example, a module of NFC component **120** may utilize a portion of device memory **104** of device **100**. Any or each module of either one or both of NFC component **120** and power management subsystem **301** may include its own processing circuitry and/or memory. Alternatively, any or each module of either one or both of NFC component **120** and power management subsystem **301** may share processing circuitry and/or memory with any other module of NFC component **120** and/or power management subsystem **301** and/or processor **102** and/or memory **104** of device **100**.

[0106] As mentioned, electronic device **100** may drive a display (e.g., display output component **112a**) with graphical data to display a graphical user interface (“GUI”) **180**. GUI **180** may be configured to receive touch input via a touch input component **110f**. Embodied as a touch screen (e.g., with display output component **112a** as I/O component **114a**), touch I/O component **110f** may display GUI **180**. Alternatively, GUI **180** may be displayed on a display (e.g., display output component **112a**) separate from touch input component **110f**. GUI **180** may include graphical elements displayed at particular locations within the interface. Graphical elements may include, but are not limited to, a variety of displayed virtual input devices, including virtual scroll wheels, a virtual keyboard, virtual knobs, virtual buttons, any virtual user interface (“UI”), and the like. A user may perform gestures at one or more particular locations on touch input component **110f**, which may be associated with the graphical elements of GUI **180**. In other embodiments, the user may perform gestures at one or more locations that are independent of the locations of graphical elements of GUI **180**. Gestures performed on a touch input component **110** may directly or indirectly manipulate, control, modify, move, actuate, initiate, or generally affect graphical elements, such as cursors, icons, media files, lists, text, all or portions of images, or the like within the GUI. For instance, in the case of a touch screen, a user may directly interact with a graphical element by performing a gesture over the graphical element on the touch screen. Alternatively, a touch pad may generally provide indirect interaction. Gestures may also affect non-displayed GUI elements (e.g., causing user interfaces to appear) or may affect other actions of device **100** (e.g.,

affect a state or mode of a GUI, application, or operating system). Gestures may or may not be performed on a touch input component **110** in conjunction with a displayed cursor. For instance, in the case in which gestures are performed on a touchpad, a cursor or pointer may be displayed on a display screen or touch screen and the cursor or pointer may be controlled via touch input on the touchpad to interact with graphical objects on the display screen. In other embodiments, in which gestures are performed directly on a touch screen, a user may interact directly with objects on the touch screen, with or without a cursor or pointer being displayed on the touch screen. Feedback may be provided to the user via bus **118** in response to or based on the touch or near touches on a touch input component **110**. Feedback may be transmitted optically, mechanically, electrically, olfactory, acoustically, or the like or any combination thereof and in a variable or non-variable manner.

[0107] While there have been described systems, methods, and computer-readable media for managing near field communications, it is to be understood that many changes may be made therein without departing from the spirit and scope of the subject matter described herein in any way. Insubstantial changes from the claimed subject matter as viewed by a person with ordinary skill in the art, now known or later devised, are expressly contemplated as being equivalently within the scope of the claims. Therefore, obvious substitutions now or later known to one with ordinary skill in the art are defined to be within the scope of the defined elements.

[0108] Therefore, those skilled in the art will appreciate that the invention can be practiced by other than the described embodiments, which are presented for purposes of illustration rather than of limitation.

Claims

1. A method for operating an electronic device that comprises a near field communication component, the method comprising: while the electronic device is operating in a normal power mode of the electronic device, during which the near field communication component is operating in a full power mode of the near field communication component, detecting a low power mode initiation event with the electronic device; and in response to the detecting: determining a status of a low power mode flag (LPMF) of the electronic device; and transitioning the electronic device from operating in the normal power mode of the electronic device to operating in a low power mode of the electronic device, wherein the transitioning the electronic device comprises: disabling a plurality of subsystems of the electronic device; transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in a low power mode of the near field communication component when the determined status of the LPMF is a first status; and transitioning the near field communication component from operating in the full power mode of the near field communication component to operating in an off mode of the near field communication component when the determined status of the LPMF is a second status that is different than the first status, wherein the near field communication component uses less power when operating in the off mode of the near field communication component than when operating in the low power mode of the near field communication component.
2. The method of claim 1, wherein: the near field communication component is operative to actively communicate data from at least one credential on the electronic device to a remote terminal while the near field communication component is operating in the low power mode of the near field communication component; and the near field communication component is not operative to actively communicate any data from any credential on the electronic device to a remote terminal while the near field communication component is operating in the off mode of the near field communication component.
3. The method of claim 1, further comprising: while the electronic device is operating in the low power mode of the electronic device, detecting a wake event; and in response to detecting the wake

event: presenting first status information via an output component of the electronic device if the near field communication component is operating in the low power mode of the near field communication component; and presenting second status information via the output component of the electronic device if the near field communication component is operating in the off mode of the near field communication component, wherein the first status information is different than the second status information.

4. The method of claim 3, wherein the first status information is indicative of: the low power mode of the electronic device; and the low power mode of the near field communication component.

5. The method of claim 4, wherein the second status information is indicative of the low power mode of the electronic device.

6. The method of claim 1, wherein the plurality of subsystems of the electronic device comprises a power management unit of the electronic device.

7. The method of claim 1, wherein the plurality of subsystems of the electronic device comprises a device operating system of the electronic device.

8. The method of claim 1, wherein the plurality of subsystems of the electronic device comprises a touch screen input component of the electronic device.

9. The method of claim 1, wherein the detecting the low power mode initiation event comprises receiving a particular user input via at least one input component of the electronic device.

10. The method of claim 1, wherein the detecting the low power mode initiation event comprises determining that a charge of a battery of the electronic device is below a predetermined threshold.

11. The method of claim 10, wherein the predetermined threshold is a minimum battery charge value for executing a device operating system of the electronic device.

12. The method of claim 1, wherein the LPMF is a register in a power management unit of the electronic device.

13. The method of claim 1, wherein the LPMF is a register in a non-volatile memory of the electronic device.

14. The method of claim 1, further comprising, prior to the detecting the low power mode initiation event with the electronic device, while the electronic device is operating in the normal power mode: designating a credential on the electronic device as an initial credential for potential use in a future low power communication mode; and in response to the designating, setting the status of the LPMF to the first status.

15. The method of claim 14, further comprising, in response to the designating, at least one of the following: loading an output waveform into an output component of the electronic device; setting a flag of a power management unit alarm register of the electronic device; configuring a duration of a power management unit alarm of the electronic device to a first duration; or configuring a duration of a software alarm of the electronic device to a second duration that is less than the first duration.

16. The method of claim 1, further comprising, prior to the detecting the low power mode initiation event with the electronic device, while the electronic device is operating in the normal power mode: removing a designation from the only credential on the electronic device that is designated for potential use in a future low power communication mode; and in response to the removing, setting the status of the LPMF to the second status.

17. The method of claim 1, wherein the status of the LPMF is the first status when at least one credential provisioned on the electronic device has been designated for potential use in a future low power communication mode.

18. The method of claim 1, wherein the status of the LPMF is the second status when there is no credential provisioned on the electronic device that has been designated for potential use in a future low power communication mode.

19. A method for operating an electronic device that comprises a communication component and a power supply, the method comprising: detecting a low power mode initiation event with the electronic device; and in response to the detecting: disabling at least one of a power management

unit of the electronic device or an operating system of the electronic device; when at least one express mode credential is available on the electronic device, providing power from the power supply to the communication component for enabling the communication component to communicate data from the at least one express mode credential to a remote terminal; and when no express mode credential is available on the electronic device, preventing the communication component from receiving any power from the power supply.

20. A method for operating an electronic device that comprises a communication component, a memory register, and a battery, the method comprising: detecting that a charge of the battery is below a predetermined threshold; and in response to the detecting: disabling a plurality of subsystems of the electronic device; when the status of the memory register is a first status, providing power from the battery to the communication component for enabling the communication component to communicate data with a remote terminal; and when the status of the memory register is a second status that is different than the first status, preventing the communication component from receiving any power from the battery.
