

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279711

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Adams; Daniel Thomas et al.

Coil Actuator

Abstract

An actuator is introduced that utilizes the forces that result from placing a current carrying coil in a magnetic field to rotate a connected object about at least one axis. In some embodiments, the introduced coil actuator includes a coil of conductor coupled to an arm or other type of structural element that extends radially from an axis of rotation. The introduced coil actuator can be utilized to provide motion control in a variety of different applications such as gimbal mechanisms. In some embodiments, the introduced coil actuator can be implemented in a gimbal mechanism for adjusting an orientation of a device such as a camera relative to a connected platform such as the body of an aerial vehicle.

Inventors: Adams; Daniel Thomas (Palo Alto, CA), Lowe; Patrick Allen (Palo Alto, CA), Thompson; Benjamin Scott (San Carlos, CA), Bachrach; Abraham Galton (Emerald Hills, CA), Bry; Adam Parker (Redwood City, CA)

Applicant: Skydio, Inc. (San Mateo, CA)

Family ID: 68763646

Assignee: Skydio, Inc. (San Mateo, CA)

Appl. No.: 19/085410

Filed: March 20, 2025

Related U.S. Application Data

parent US continuation 17874879 20220727 parent-grant-document US 12261498 child US 19085410

parent US continuation 17015248 20200909 parent-grant-document US 11418102 child US 17874879

parent US continuation 16439646 20190612 parent-grant-document US 10784761 child US 17015248

us-provisional-application US 62683996 20180612

Publication Classification

Int. Cl.: H02K41/035 (20060101); B64U20/87 (20230101); B64U101/30 (20230101); G03B15/00 (20210101); G03B17/56 (20210101)

U.S. Cl.:

CPC H02K41/0358 (20130101); B64U20/87 (20230101); G03B15/006 (20130101); G03B17/561 (20130101); B64U2101/30 (20230101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) [0001] This application is a continuation of U.S. patent application Ser. No. 17/874,879, titled “COIL ACTUATOR,” filed Jul. 27, 2022; which is a continuation of U.S. patent application Ser. No. 17/015,248, titled “COIL ACTUATOR,” filed Sep. 9, 2020, and issued as U.S. Pat. No. 11,418,102 on Aug. 16, 2022; which is a continuation of U.S. patent application Ser. No. 16/439,646, titled “COIL ACTUATOR,” filed Jun. 12, 2019, and issued as U.S. Pat. No. 10,784,761 on Sep. 22, 2020; which is entitled to the benefit and/or right of priority of U.S. Provisional Patent Application No. 62/683,996, titled, “VOICE COIL ACTUATOR FOR CAMERA GIMBAL,” filed Jun. 12, 2018, the contents of each of which are hereby incorporated by reference in their entirety for all purposes. This application is therefore entitled to a priority date of Jun. 12, 2018.

TECHNICAL FIELD

[0002] The present disclosure generally relates to electromechanical actuators, specifically electromechanical actuators that drive mechanical motion by applying current to a coil in a magnetic field.

BACKGROUND

[0003] Actuators are components in a machine or other device that are responsible for moving or otherwise controlling a component of the machine or device. For example, an actuator can be used in a gimbal mechanism to enable controllable reorientation of an object such as a camera relative to a frame of reference. Examples of actuators include hydraulic actuators, pneumatic actuators, and electromechanical actuators. A rotary electromechanical actuator converts electrical energy into mechanical energy, such as torque or force. A commonly used rotary electromechanical actuator is a brushless direct current (DC) electric motor (or “BLDC” motor). A BLDC motor is powered by DC electricity via an inverter to produce an alternating current (AC) to drive each phase of the motor. A controller provides pulses to motor windings that cause the rotation of a motor axle. In a gimbal mechanism, a BLDC motor can be mounted at an axis and can apply torque to actively rotate the structural elements about the axis relative to each other.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] Various features of the technology will become more apparent to those skilled in the art from a study of the Detailed Description in conjunction with the drawings. Embodiments of the technology are illustrated by way of example and not limitation in the drawings, in which like references may indicate similar elements.

[0005] FIG. 1A shows a side view of an example coil actuator.

[0006] FIG. 1B shows a top view of the example coil actuator of FIG. 1A in a first position.

[0007] FIG. 1C shows a top view of the example coil actuator of FIG. 1A in a second position.

[0008] FIG. 1D shows a diagram that illustrates an electromagnetic force response to a current applied in a first direction to the example coil actuator of FIG. 1A.

[0009] FIG. 1E shows a diagram that illustrates an electromagnetic force response to a current applied in a second direction to the example coil actuator of FIG. 1A.

[0010] FIG. 2 shows a perspective view of another example coil actuator in which the coil is oriented perpendicular to a path of motion of the actuator.

[0011] FIG. 3A shows a perspective view of an example linear coil actuator.

[0012] FIG. 3B shows a side view of the example linear coil actuator of FIG. 3A.

[0013] FIG. 3C shows a front view of the example linear coil actuator of FIG. 3A.

[0014] FIG. 4A shows a side view of an example coil actuator that includes stacked magnets.

[0015] FIG. 4B shows a front view of the example coil actuator of FIG. 4A.

[0016] FIG. 4C shows a side view of another example coil actuator that includes stacked magnets.

[0017] FIG. 4D shows a front view of the example coil actuator of FIG. 4C.

[0018] FIG. 5A shows a side view of an example coil actuator that includes a concave-shaped magnet.

[0019] FIG. 5B shows a front view of the example coil actuator of FIG. 5A.

[0020] FIG. 5C shows a side view of an example coil actuator that includes a convex-shaped magnet.

[0021] FIG. 5D shows a front view of the example coil actuator of FIG. 5C.

[0022] FIG. 6A shows a side view of an example coil actuator with multiple coils and multiple magnets.

[0023] FIG. 6B shows a top view of the example coil actuator of FIG. 6A in a first position.

[0024] FIG. 6C shows a top view of the example coil actuator of FIG. 6A in a second position.

[0025] FIG. 7A shows a top view of an example coil actuator that can be implemented in a mechanical linkage.

[0026] FIG. 7B shows a top view of an example mechanical linkage including the coil actuator of FIG. 7A in a first position.

[0027] FIG. 7C shows a top view of an example mechanical linkage including the coil actuator of FIG. 7A in a second position.

[0028] FIG. 8 shows a top view of an example coil actuator that is configured to rotate an attached payload about an axis of rotation.

[0029] FIG. 9 shows a side view of an example coil actuator that includes an electromagnet.

[0030] FIG. 10A shows a top view of an example coil actuator configured for two-dimensional (2D) motion.

[0031] FIG. 10B shows a top view of the example coil actuator of FIG. 10A in a first position.

[0032] FIG. 10C shows a top view of the example coil actuator of FIG. 10A in a second position.

[0033] FIG. 11A shows a top view of another example coil actuator configured for 2D motion.

[0034] FIG. 11B shows a top view of the example coil actuator of FIG. 11A in a first position.

[0035] FIG. 11C shows a top view of the example coil actuator of FIG. 11A in a second position.

[0036] FIG. 12 shows a top view of an example coil actuator that includes spring and damper components.

[0037] FIG. 13A shows a side view of an example adjustable coil-based spring mechanism.

[0038] FIG. 13B shows a side view of the example adjustable coil-based spring mechanism of FIG. 13A in a first position.

[0039] FIG. 13C shows a side view of the example adjustable coil-based spring mechanism of FIG. 13A in a second position.

[0040] FIG. 14 shows an example aerial vehicle in the form of an unmanned aerial vehicle (UAV) in which the introduced coil actuator can be impended.

[0041] FIG. 15 shows a side view of an example image capture assembly that includes a motorized gimbal mechanism for adjusting an orientation of a mounted camera.

[0042] FIG. 16A shows a perspective view of an example coil actuator configured to adjust a yaw of a camera.

[0043] FIG. 16B shows a perspective view of the example coil actuator of FIG. 16A with a camera attached.

[0044] FIG. 17A show a top view of an example coil and magnet of a coil actuator similar to the coil actuator of FIG. 16A.

[0045] FIG. 17B shows a perspective view of the coil and magnet of FIG. 17A with a flux guide.

[0046] FIG. 18A shows a perspective view of an example coil actuator with one or more magnets arranged above and below a coil.

[0047] FIG. 18B shows a perspective view of an example coil actuator with multiple magnets arranged above a coil.

[0048] FIG. 19 shows a conceptual diagram of a mechanical linkage system that includes different types of actuators.

[0049] FIG. 20A shows a perspective view of an example gimbal mechanism that uses a coil actuator for yaw control and rotatory motors roll and pitch control.

[0050] FIG. 20B shows a top view of the example gimbal mechanism of FIG. 20A.

[0051] FIG. 21 shows a schematic diagram of an example circuit for a gimbal mechanism.

[0052] FIG. 22A shows a perspective view of an example coil-based isolator.

[0053] FIG. 22B shows a side view of the example coil-based isolator of FIG. 22A.

[0054] FIG. 22C shows a section view of the example coil-based isolator of FIG. 22A.

[0055] FIG. 23A shows a cross section of an example unmanned aerial vehicle (UAV) in a first position that includes a camera suspensions system that includes coil-based isolators.

[0056] FIG. 23B shows a cross section of the example UAV of FIG. 23A in a second position.

[0057] FIG. 23C shows a cross section of the example UAV of FIG. 23A in a third position.

[0058] FIG. 24 shows a block diagram that illustrates an example control system that may be implemented to control a coil actuator.

[0059] FIG. 25 shows a block diagram illustrating an example processing system which may be implemented to control a coil actuator.

DETAILED DESCRIPTION

Overview

[0060] An actuator is introduced that utilizes the forces that result from placing a current carrying coil in a magnetic field to rotate a connected object about at least one axis. In some embodiments, the introduced coil actuator includes a coil of conductor coupled to an arm or other type of structural element that extends radially from an axis of rotation.

[0061] The introduced coil actuator can be utilized to provide motion control in a variety of different applications such as gimbal mechanisms. In typical gimbal mechanisms, each axis of rotation is actuated using a standard BLDC motor mounted at an axis. While effective in providing necessary ranges of motion to reorient a connected object, such motors have a relatively large displacement and therefore consume volume around each axis. This can be impractical in certain applications, particularly where space is limited such as small unmanned aerial vehicles (UAVs). The introduced coil actuator addresses these challenges and provides several benefits over existing actuators such as increased performance-per-weight, decreased electrical power required for comparable mechanical output, and the ability to directly drive the axis of rotation with no backlash. Further, the hardware needed to implement a coil actuator can involve fewer moving parts and can be arranged off of the drive axis. In some embodiments, the introduced coil actuator can be implemented in a gimbal mechanism for adjusting an orientation of a device such as a camera, relative to a connected platform such as the body of an aerial vehicle.

[0062] The introduced coil actuator can be implemented using what is sometimes referred to as a

“voice-coil.” The term “voice-coil” refers to a coil of conductive wire that can be utilized to drive a cone of a loudspeaker in response to applied signal current. The term “voice-coil” may be used herein for illustrative simplicity; however, the term shall not be construed to limit the introduced actuator to coils that are capable of such audio applications. Accordingly, as used herein, the term “voice-coil” shall be understood to refer to any type of coil of conductive material that can be used for any purpose.

Coil Actuator

[0063] FIGS. **1A-1C** illustrate, at a high level, operation of an example actuator that includes a coil or “voice-coil”, according to some embodiments. Specifically, FIG. **1A** shows a side view of an example actuator assembly **100** and FIGS. **1B** and **1C** show top views of the example actuator assembly **100** of FIG. **1A** in a first position and second position (respectively).

[0064] As shown in FIG. **1A**, the example actuator assembly **100** includes a coil **110** suspended from or otherwise structurally coupled to an arm **120** that extends radially from an axis of rotation **150**. In an example configuration for yaw actuation, the arm **120** is arranged horizontally such that the axis of rotation **150** is vertical. The coil **110** (and associated arm **120**) pass through a magnetic field generated by a magnet assembly **130** coupled to a static structure **140**. By applying varying current (e.g., varying DC) in the coil **110** in proximity to the magnet assembly **130**, a tangential electromagnetic force is applied to the arm **120** supporting the coil **110**. The direction of the force can be reversed by reversing polarity. The force, acting on the arm **120** some radial distance from the axis of rotation **150**, causes torque that drives a rotation of the arm **120** and associated coil **110** about the axis **150** relative to the static structure **140**. In other words, as a result of applying current to the coil **110**, the arm **120** rotates about axis **150** relative to the static structure **140**. For example, FIG. **1B** shows the arm **120** and associated coil **110** in a first position. In response to applying current to the coil **110**, the arm **120** may rotate about axis **150** to arrive at a second position shown in FIG. **1C**.

[0065] Opposing legs of a given coil can be arranged in different portions of a magnetic field. This allows current applied to the coil to cause a tangential force (and resulting torque) in a particular direction based on the direction of the current flow. FIGS. **1D** and **1E** show details of an example force response to a current applied to coil **110** of example actuator **100**. Specifically, FIG. **1D** shows a force response to a current applied to coil **110** in a first direction and FIG. **1E** shows a force response to a current applied in a second direction opposite the first.

[0066] As shown in FIGS. **1D** and **1E**, the example actuator **100** is configured such that a first leg **110a** of the coil passes through a first portion **132a** of a magnetic field and a second leg **110b** that is opposite the first leg **110a** passes through a second portion **132b** of the magnetic field caused by magnet assembly. In the illustrated example, the first portion **132a** includes magnetic field lines pointed out of the page (indicated by the multiple circles with dots) and the second portion **132b** includes magnetic field lines pointing into the page (indicated by the multiple circles with crosses). A person having ordinary skill in the art will recognize that the direction of electromagnetic force (or “Lorentz force”) applied to a given charged particle is dependent on the direction of a magnetic field and the direction of motion of that charged particle through the magnetic field. Accordingly, the direction of tangential force **F** applied will depend on the direction of current **C** applied. FIG. **1D** shows the applied force **F** in a first tangential direction based on the current **C** in a first direction. Conversely, FIG. **1E** shows the applied force **F** in a second tangential direction (opposite the first tangential direction) based on the current applied in the second direction (opposite the first direction). Note that the magnetic field lines are depicted in FIGS. **1D** and **1E** in a simplified form for illustrative clarity. The actual shape of a magnetic field for a given magnet assembly will depend on a number of factors (e.g., type of magnet, physical shape of magnet, proximity to other magnets, proximity to flux guides, etc.) and may, in practice, be more complex than is depicted in FIGS. **1E** and **1D**.

[0067] Notably, the first leg **110a** and second leg **110b** of coil **110** do not pass through the same

portions of the magnetic field caused by the magnet assembly. This is to avoid the resulting electromagnetic forces opposing each other due to the opposing directions of current flow in the two legs of the coil **110**. In any case, the arrangement of the coil **110** relative to the magnet assembly **130** depicted in FIGS. **1A-1D** is an example provided for illustrative purposes and is not intended to limit the present disclosure to any particular shape or size of the associated components. For example, the magnet assembly **130** is depicted in FIGS. **1A-1D** as a single component. In such an embodiment, the different portions **132a** and **132b** of the resulting magnetic field may be caused by opposing poles of single magnet (e.g., in a dipole magnet). Alternatively, this variation can also be accomplished by splitting the magnet assembly **130** into multiple magnets or otherwise varying the magnetism across the magnet assembly. A person having ordinary skill in the art will recognize that the operation of a coil actuator consistent with the present disclosure can be adjusted by varying the geometry of the coil **110** and/or magnet assembly, adding multiple magnetic poles and/or coils, and/or by commutating the drive current to the coil(s) based on position.

[0068] In some embodiments, actuation is controlled with open loop current application. Alternatively, or in addition, actuation can be controlled using closed-loop control with feedback from a sensor output. In some embodiments, actuation is controlled using closed-loop control with feedback from a dedicated position sensor such as a shaft encoder, resolver, hall-effect sensor, gyro or accelerometer, magnetometer, proximity detector, etc. In some embodiments, an actuation controller can use digital electronics and software or can be implemented using an analog control circuit. While the coil **110** is depicted as a single element in FIGS. **1A-1C**, in some embodiments, the coil **110** may comprise multiple coils of conducting wire that are driven independently.

[0069] Note that structural element **140** is referred to as a “static structure” in this example embodiment to convey a frame of reference relative to the motion of the arm **120**; however, the structural element **140** need not be static or stationary in all embodiments. For example, in some embodiments, the actuator assembly **100** may be implemented as a rotatable link in a mechanical linkage involving multiple actuators configured to impart rotation about different axes. In such an embodiment, the structural element **140**, although static from the point of view of the arm **120**, may actually be in motion relative to different frame of reference such as a mounting platform at the end of the mechanical linkage chain.

[0070] Further, the example actuator assembly **100** depicted in FIGS. **1A-1C**, show the coil **110** mounted to a “dynamic” element (i.e., arm **120**) and the magnet assembly **130** mounted to a “static” element (i.e., static structure **140**). In other embodiments, this may be reversed. In other words, the coil **110** may instead be mounted to the static structure **140** and the magnet assembly **130** may be mounted to the dynamic arm **120**. Such an embodiment may be beneficial in some cases because it allows for wiring to the coil **110** to be mounted to a static structure **140**, thereby eliminating the need for a service loop of conductors crossing the relative motion between the static structure **140** and dynamic arm **120**.

[0071] The two structural elements of the example actuator assembly **100** of FIGS. **1A-1C** (arm **120** and structure **140**) are depicted at a high level of generality to illustrate the concept underlying a coil actuator. In an example embodiment, the arm **120** may serve as a payload frame for mounting any type of object or device such as a camera and the static structure may be part of a mounting platform such as the body of a vehicle and or element in a mechanical linkage.

[0072] A coil actuator, such as the example actuator assembly **100** depicted in FIGS. **1A-1C**, is particularly beneficial in certain applications that require relatively small yaw compensation (e.g., +/-10 to 15 degrees) such as in a gimbal mounted camera on an aerial vehicle. Such an arrangement has the potential for lower-inertia and higher torque-per weight. Although the angular range of motion is relatively small, such an actuator may be beneficial over other types of actuators for a number of reasons such as increased performance-per-weight, decreased electrical power required for comparable mechanical output, and the ability to directly drives the axis of rotation

with no backlash. Further, the hardware needed to implement a coil actuator can involve fewer moving parts (increasing reliability and decreasing cost) and can be arranged off of the drive axis. Note, despite the relatively small range of motion indicated in FIGS. 1A-1C, a coil actuator based on the same concept can be expanded to cover a larger angle of motion either by extending coil and magnet assembly geometry, or by adding multiple magnetic poles and/or coils, and by commutating the drive current to the coil(s) based on position.

[0073] As mentioned, the coil actuator assembly **100** depicted in FIGS. 1A-1C is an example provided for illustrative purposes and is not to be construed as limiting. A coil actuator may be configured differently to satisfy the requirements of a given embodiment while remaining within the scope of the present disclosure. FIGS. 2-13C depict some alternative embodiments of coil actuators that illustrate various configurations that can be implemented. The various configurations depicted in the embodiments of FIGS. 2-13C are also provided for illustrative purposes and are not intended to be limiting or exhaustive. Further, various features and conditions described with respect to the example coil actuator of FIGS. 1A-1C may similarly apply to any one or more of the example coil actuators of FIGS. 2-13C even if not expressly stated as such.

[0074] In some embodiments, the coil component of a coil actuator may be arranged perpendicular to a path of motion of the actuator. FIG. 2 depicts an example actuator assembly **200** that includes such a coil arrangement. As shown in FIG. 2, actuator assembly **200** includes a coil **210** that is arranged about a magnet assembly **230**. As with actuator assembly **100**, coil **210** is structurally coupled to an arm **220** that extends radially from an axis of rotation **250**. The coil **210** (and associated arm **220**) pass through a magnetic field generated by the magnet assembly **230** coupled to some static structure (not depicted in FIG. 2 for illustrative clarity). By applying varying current (e.g., varying DC) in the coil **210** in proximity to the magnet assembly **230**, a tangential electromagnetic force is applied to the arm **220** supporting the coil **210**. The force, acting on the arm **220** some radial distance from the axis of rotation **250**, causes torque that drives a rotation of the arm **220** and associated coil **210** about the axis **250** relative to the static structure. In other words, as a result of applying current to the coil **210**, the arm **120** rotates about axis **250** relative to the static structure.

[0075] The arrangement of actuator assembly **200** depicted in FIG. 2 may have certain benefits over the example arrangement of actuator **100** depicted in FIGS. 1A-1C. For example, since the coil currents run in opposite direction on opposite sides of the magnet a coil actuator **200** may not experience the same restrictions in angular range as coil actuator **100** since the pole structure can be the same for the entire length of the magnet ark.

[0076] In some embodiments, a coil actuator may be configured for linear actuation instead of rotational actuation. FIGS. 3A, 3B, and 3C show a perspective view, side view, and front view (respectively) of an example linear coil actuator **300**. As shown, for example, in FIG. 3A, the linear coil actuator **300** includes a coil **310** arranged about or in proximity to a magnet assembly **330**. Due to the geometric configuration of the magnet assembly **330** and resulting magnetic field, a current applied to the coil **310** causes a force in one of two directions along the magnet assembly **330**. This causes the coil **310** to move forward or backward (i.e., linearly) along a straight line. As depicted in FIG. 3B, the coil **310** may move along an axis from any nominal position in a positive or negative direction depending on the polarity of the applied current. An example nominal position is indicated in FIG. 3B by the "0" marker; however, this is just an example position provided for illustrative purposes and is not to be construed as limiting.

[0077] In some embodiments, the magnet assembly in a coil actuator may include a stack of individual magnets that are arranged so as to cause a variation in the magnetic field over the path of motion of the coil. This variation in the magnetic field can be used to change the force response for a given current applied to the coil.

[0078] FIGS. 4A and 4B show a side view and front view (respectively) of a first example coil actuator **400a** with a magnet stack. As illustrated in FIG. 4A, the magnet assembly **430a** of coil

actuator **400a** actually include five separate magnet components. The magnet assembly **430a** includes a single central magnet proximate to the nominal position (indicated by the “0” marker) of a coil **410a** and double stacked magnets at opposite ends of the central magnet in a positive and negative direction along an x-axis. The double stacked magnets at opposite ends may cause a stronger magnetic field than the single central magnet located proximate to the nominal position of the coil. In this example, the force (and/or torque) applied by the actuator **400a** would be stronger when the coil **410a** is in a position proximate to the double stacked magnets than when the coil **410a** is at its nominal position. Such an arrangement may be beneficial in certain applications that require additional force applied as the distance from the nominal position increases. An example might include a flap on an aircraft wing. As the flap is extended from its nominal position to a fully extended position, the force due to air-resistance increases. A strong opposing force by the actuator is therefore required to keep the flap in the extended position.

[0079] The magnet stack can be configured in an opposite arrangement as well. FIGS. **4C** and **4D** show a side view and front view (respectively) of a second example coil actuator **400b** with a magnet stack **430b** that includes more magnets proximate to the nominal position of a coil **410b**. In contrast with the example actuator **400a** depicted in FIGS. **4A-4B**, the example actuator **400b** would cause a greater force to be applied when the coil **410b** is closer to the nominal position.

[0080] In some embodiments, instead of stacking multiple discrete magnets, a magnet assembly of an actuator can be shaped to cause a variation in the magnetic field over the path of motion of the coil. In other embodiments, the magnetic field over the path of the coil can be varied by varying the magnetization of the magnet assembly even if the magnet assembly has a uniform physical shape over the path of the coil.

[0081] While the coils **410a** and **410b** are depicted as single elements in FIGS. **4A-4C**, in some embodiments, each of the coils **410a** and/or **410b** may comprise multiple coils of conducting wire that are driven independently. For example, two different legs of a coil **410a** may be driven against each other to center the actuator **400a** and keep it at a known angular position without requiring any sensors or feedback control.

[0082] FIGS. **5A** and **5B** show a side view and front view (respectively) of an example coil actuator **500a** with a concave-shaped magnet assembly **530a**. As shown in FIG. **5A**, the concave-shaped magnet assembly **530a** is thinner at the nominal position (indicated by the “0” marker) of the coil **510a** and gradually widens along an x-axis. Similar to example coil actuator **400a** of FIGS. **4A-4B**, example actuator **500a** would apply a stronger force (and/or torque) when the coil **510a** is further from the nominal position than when the coil **510a** is proximate to the nominal position.

[0083] Conversely, FIGS. **5C** and **5D** show a side view and front view (respectively) of an example coil actuator **500b** with a convex-shaped magnet assembly **530b**. As shown in FIG. **5C**, the concave-shaped magnet assembly **530b** is thicker at the nominal position (indicated by the “0” marker) of the coil **510b** and gradually tapers off along an x-axis. Similar to example coil actuator **400b** of FIGS. **4C-4D**, example actuator **500b** would apply a stronger force (and/or torque) when the coil **510a** is proximate to the nominal position than when the coil **510b** is further from the nominal position.

[0084] While the coils **510a** and **510b** are depicted as single elements in FIGS. **5A-5C**, in some embodiments, each of the coils **510a** and/or **510b** may comprise multiple coils of conducting wire that are driven independently. For example, two different legs of a coil **510a** may be driven against each other to center the actuator **500a** and keep it at a known angular position without requiring any sensors or feedback control.

[0085] In some embodiments, a coil actuator can include two or more coil and/or magnet assemblies. FIGS. **6A-6C** illustrate, at a high level, operation of an example actuator that includes two coils and two magnet assemblies. Specifically, FIG. **6A** shows a side view of an example actuator assembly **600** and FIGS. **6B** and **6C** show top views of the example actuator assembly **600** of FIG. **6A** in a first position and second position (respectively).

[0086] As shown in FIG. 6A, the example actuator assembly **600** includes a first coil **610a** and a second coil **610b** that are both suspended from or otherwise structurally coupled to an arm **620** that extends radially from an axis of rotation **650**. Each of the coils **610a** and **610b** are arranged proximate to a corresponding magnet assembly **630a** and **630b** (respectively). As with example actuator **100** described with respect to FIGS. 1A-1C, the coils **610a-b** of actuator **600** pass through magnetic fields generated by the corresponding magnet assemblies **630a-b** that coupled to a static structure **640**. By applying varying current (e.g., varying DC) in the coils **610a-b** in proximity to the magnet assemblies **630a-b**, a tangential electromagnetic force is applied to the arm **620** supporting the coils **610a-b**. The direction of the force can be reversed by reversing polarity. The force, acting on the arm **620** some radial distance from the axis of rotation **650**, causes torque that drives a rotation of the arm **620** and associated coils **610a-b** about the axis **650** relative to the static structure **640**. In other words, as a result of applying current to the coil **610a** and/or **610b**, the arm **620** rotates about axis **650** relative to the static structure **640**. For example, FIG. 6B shows the arm **620** and associated coils **610a-b** in a first position (e.g., a nominal position indicated by axis **660**). In response to applying current to coils **610a** and/or **610b**, the arm **620** may rotate about axis **650** to arrive at a second position shown in FIG. 6C.

[0087] Notably, the two magnet assemblies **630a-b** of actuator **600** are configured such that only one of the coils is in proximity to a corresponding magnet when the arm **620** is not in the nominal position. For example, as depicted in FIG. 6C, when the arm **620** is rotated a particular angle off the nominal position axis **660**, the first coil **610a** is not in proximity to the first magnet assembly **630a**. Despite this, the second coil **610b** is still in proximity to the corresponding second magnet assembly **630b**. In this position, current applied to the first coil **610a** would not cause a corresponding magnetic force (or the force would be greatly diminished) since the coil **610a** is not located proximate to magnet assembly **630a**. However, when the arm **620** is at or closer to nominal position (as depicted in FIG. 6B) current applied to both coils **610a-b** would cause corresponding magnetic forces.

[0088] Use of two or more coil and/or magnet assemblies in an actuator can be implemented, for example, to vary the forces and/or torques applied by the actuator at different positions. For example, the forces and/or torques applied by actuator **600** at or near nominal position (e.g., as depicted in FIG. 6B) would be greater than the forces and/or torques applied at a particular angle off the nominal position (e.g., as depicted in FIG. 6C) due to the proximity of the multiple coils **610a-b** to the multiple magnet assemblies **630a-b**.

[0089] The actuator **600** depicted in FIGS. 6A-6C is just an example provided to illustrate how multiple coils and/or magnets can be implemented in a coil actuator and is not to be construed as limiting. In other embodiments, more than two coils and/or magnet assemblies may be implemented. Further, the multiple coils and/or magnet assemblies may be arranged differently than as depicted in FIGS. 6A-6B.

[0090] Although not depicted in FIGS. 6A-6C, in some embodiments, multiple coils may be arranged to pass through the same magnetic field. For example, multiple independently-driven coils, each having different geometry, may pass through a magnetic field produced by a single magnet assembly. Such an arrangement may enable a higher resolution drive, faster response, and greater peak torque, depending on the drive scheme.

[0091] In some embodiments, multiple coil actuators can be combined to form a mechanical linkage with multiple degrees of freedom. For example, FIGS. 7A-7C show how multiple actuators **700a-c** can be linked to each other to form an adjustable mechanical linkage **790**. Specifically, FIG. 7A shows a top view of an example coil actuator **700** configured to rotate structural components about a point of rotation **750**. Similar to actuator **100** described with respect to FIGS. 1A-1C, actuator **700** includes a coil **710** and a magnet assembly **730**. The coil **710** is coupled to a first arm **720** and the magnet assembly is coupled to a second arm **740**. By applying varying current (e.g., varying DC) in coil **710**, a tangential electromagnetic force is applied to the first arm **720**

supporting the coil **710**. The direction of the force can be reversed by reversing polarity. The force, acting on the first arm **720** some radial distance from the axis of rotation **750**, causes torque that drives a rotation of the arm **720** and associated coil **710** about the axis **750** relative to the second arm **640**. In other words, as a result of applying current to the coil **710**, the first arm **720** rotates about axis **750** relative to the second arm **740**.

[0092] FIGS. 7B and 7C show top views of an example mechanical linkage **790** in a first position and a second position (respectively). Each of the arms of **700a**, **700b**, and **700c** of the mechanical linkage **790** may, together with an adjacent arm, comprise a coil actuator similar to actuator **700** in FIG. 7A. Current applied to the coils at the various coil actuators in the mechanical linkage **790** will cause torque to be applied at one or more of the rotation joints in the mechanical linkage thereby causing the mechanical linkage to actuate, for example, as depicted in FIG. 7C.

[0093] The mechanical linkage **790** depicted in FIGS. 7B and 7C is an example provided to illustrate how multiple coil actuators can be linked mechanically and is not to be construed as limiting. Other mechanical linkages may be arranged differently than as depicted in FIGS. 7B and 7C. For example, other embodiments may include more coil actuators, may orient the coil actuators differently, may include non-coil actuators in the linkage, etc.

[0094] In some embodiments, the coil actuator can be configured to rotate a payload about axis of rotation. FIG. 8 shows a top view of an example coil actuator **800** that is configured to rotate an attached payload **860** about an axis of rotation **850**. The payload **860** in this example may include a camera or some other sensor although other payload types may similarly be attached. The payload **860** is coupled to an arm **820** that extends radially from the payload to an attached coil **810** that is located proximate to a magnet assembly **830**. The magnet assembly is coupled to a stationary structure **840**. When actuator **800** is configured such that when current is applied to coil **810** a tangential magnetic force is applied to arm **820**, that causes the arm **820** with attached payload **860** to rotate about the axis of rotation **850**, as shown in FIG. 8. Notably, the axis of rotation **850** may not represent a joint or other physical connection to another structure. In other words, in the example actuator **800** depicted in FIG. 8, the arm **820** extends out from the stationary structure **840** to a point in space where the payload **860** is attached. The arm **820** may travel along a rail or some other type of structure that guides the path of motion of the coil **810** relative to the magnet assembly **830**, for example, as depicted by the dotted line in FIG. 8. The motion of the arm **820** causes the attached payload **860** to rotate about the axis of rotation **850** without (or with limited) linear displacement.

[0095] A coil actuator similar to actuator **900** depicted in FIG. 8 may be particularly beneficial in a gimbal mechanism with an attached camera to avoid components of the mechanism obfuscating a field of view of the camera at certain deflection angles. For example, the payload **860** may represent a camera facing outward away from the arm **820**. Actuating the arm **820** causes the camera **860** to rotate about axis **850**; however, the structural components of the actuator **800** never enter the field of view of the camera **860** even at a maximum deflection angle.

[0096] In the previously described embodiments, the magnetic assembly is depicted as including one or more permanent magnets. Such permanent magnets may include a formed portion of a material such as ceramic, ferrite, alnico, samarium cobalt, neodymium iron boron, or some combination thereof. Alternatively, in some embodiments, the magnet assembly may comprise an electromagnet. An electromagnet may itself comprise a coil of conductor which induces a magnetic field when current is applied. An electromagnet may be beneficial over a permanent magnet in certain embodiments that necessitate controlling the strength and/or polarity of the magnetic field and/or turning off the magnetic field. For example, it may be desirable in certain embodiments to include a magnet assembly in a coil actuator that can be toggled on and off to prevent accumulation of errant metallic particles on the magnet during operation.

[0097] FIG. 9 shows a side view of an example coil actuator **900** that includes a controllable electromagnet as the magnet assembly. Specifically, the magnet assembly of actuator **900** includes

a first coil **930** that is arranged relative to a flux guide **932**. A magnetic field can be induced by applying a current to the first coil **930**. This magnetic field can be shaped using the flux guide **932**. A second coil **910** is free to travel through the magnetic field induced by the current in the first coil **930**. The second coil **910** in this example is analogous, for example, to coil **110** in example actuator **100** described with respect to FIGS. **1A-1C**. Applying a second current to the second coil **910** causes a force to be applied relative to two coils **910** and **930**.

[0098] The coil actuator **900** depicted in FIG. **9** is just an example of how a coil-based electromagnet may be implemented. Some embodiments may not include a flux guide. Some embodiments may include different coil configurations for the electromagnet such as a Hemholtz coil or a Maxwell coil. Further, a person having ordinary skill in the art will recognize that any such type of electromagnet can be implemented to replace a permanent magnet in any one or more of the example coil actuators described in this disclosure.

[0099] In some embodiments, a coil actuator can be configured for two-dimensional (2D) actuation. FIGS. **10A-10C** illustrate, at a high level, operation of an example actuator **1000** that is configured for 2D actuation. Specifically, FIG. **10A** shows a side view of an example 2D actuator **1000** and FIGS. **10B** and **10C** show top views of the example 2D actuator **1000** of FIG. **10A** in a first position and second position (respectively).

[0100] As shown in FIG. **10A**, the example actuator assembly **1000** includes a coil **1010** and multiple corresponding magnets **1030a**, **1030b**, **1030c**, and **1030d**. The coil **1010** and multiple magnets **1030a-d** are configured and arranged such that an applied current causes forces that cause the coil **1010** (and any attached structural element) to move along an x and/or y-axis relative to the magnets **1030a-d** (and any attached structural element). For example, FIG. **10B** shows the motion of the actuator along an x-axis and FIG. **10C** shows the motion of the actuator along a y-axis.

[0101] Although the coil **1010** associated with actuator **1000** is depicted in FIG. **10** as a single component, in some embodiments it may comprise multiple coils on different circuits. For example, the coil **1010** may comprise a first coil and a second coil. In such an embodiment, current applied to a first coil may cause a first force (e.g., due to interaction with the magnetic fields of magnets **1030a** and **1030d**) that causes motion along a y-axis. Similarly, current applied to the second coil may cause a second force (e.g., due to interaction with the magnetic fields of magnets **1030b** and **1030c**) that causes motion along an x-axis. In such a configuration, the two coils can be arranged such that one coil interacts with the magnetic field of a first set of magnets (e.g., magnets **1030a** and **1030d**) and a second coil interacts with a second set of magnets (e.g., magnets **1030b** and **1030c**).

[0102] In some embodiments, the magnets **1030a-d** may be electromagnets that can be driven independently or as pairs to cause motion along the x-axis or y-axis. For example, magnets **1030a** and **1030d** may comprise a first pair of electromagnets on a first circuit and magnets **1030c** and **1030b** may comprise a second pair of electromagnets on a second circuit. In such an embodiment, Driving the first pair of electromagnets **1030a** and **1030d** may cause motion along the y-axis. Conversely, driving the second pair of electromagnets **1030b** and **1030c** may cause motion along the x-axis.

[0103] FIGS. **11A-11C** illustrate, at a high level, operation of another example actuator **1100** that is also configured for 2D actuation. Specifically, FIG. **11A** shows a top view of an example 2D actuator **1100** and FIGS. **11B** and **11C** show top views of the example 2D actuator **1100** of FIG. **11A** in a first position and second position (respectively). The example actuator **1100** depicted in FIGS. **11A-11C** includes a coil **1110** and a magnet assembly **1130**. The magnet assembly **1130** includes multiple shaped magnets that are arranged into a ring shape. The coil **1110** and multiple magnets of assembly **1130** are configured and arranged such that an applied current causes forces that cause the coil **1110** (and any attached structural element) to move along an x-axis and/or y-axis relative to the magnet assembly **1130** (and any attached structural element). Notably, the configuration of example actuator **1100** allows for arbitrary motion in two dimensions (i.e., not just

along an x-axis and y-axis) that may not be possible with the example actuator **1000** of FIGS. **10A-10C**. For example, FIG. **11B** shows the motion of the actuator **1100** diagonally in a first direction and FIG. **10C** shows the motion of the actuator diagonally in a second direction opposite the first direction.

[0104] While the coil **1110** is depicted as a single element in FIGS. **11A-11C**, in some embodiments, coil **1110** may comprise multiple coils of conducting wire that are driven independently. Further, the magnetic fields created by the magnet assembly **1130** can be variably controlled, for example through the use of electromagnets, to enable the 2D translation in arbitrary directions as depicted in FIGS. **11A-11C**. In some embodiments, a coil actuator may include additional mechanical components that impact the behavior of the actuator. FIG. **12** shows a conceptual diagram of a mechanical system **1200** including a coil actuator and other mechanical components such as a spring and a damper. As shown in FIG. **12**, the coil actuator includes a coil **1210** coupled to an arm **1220**. The coil **1210** is arranged proximate to a magnet assembly **1230** such that when current is applied to coil **1210** a tangential force is applied to the arm **1220** at a radial distance from an axis of rotation **1250** which applies a torque to cause the arm **1220** to rotate about the axis **1250**.

[0105] The mechanical system **1200** further includes a spring **1260** coupled to one side of the arm **1220** and to a structural component **1280a**. The spring **1260** applies an opposing force to the arm **1220** as the arm **1220** gets closer to the structural component **1280a** which impacts the behavioral response of the coil actuator.

[0106] The mechanical system **1200** also includes a damper **1270** coupled to an opposite side of the arm **1220** and to a second structural component **1280b**. In some embodiments, components **1280a** and **1280b** may be structurally coupled to each other. The damper **1280** applies an opposing force to the arm **1220** regardless of the direction of motion of the arm **1220**.

[0107] The mechanical system depicted in FIG. **12** is just an example provided to illustrate how other types of mechanical components can be implemented in conjunction with a coil actuator and is not to be construed as limiting. Other configurations can be implemented to address the requirements of a given embodiment.

[0108] Previous embodiments have described example implementations of coil-based actuators; however, the underlying principles can be applied to implement other types of components. FIGS. **13A-13C** show several views of an example coil-based adjustable spring **1300**. Specifically, FIG. **13A** shows a side view of the coil-based adjustable spring **1300** in a first nominal position (as indicated by the “0” marker), FIG. **13B** shows the coil-based adjustable spring **1300** in a second position, and FIG. **13C** shows the coil-based adjustable spring **1300** in a third position. The coil-based adjustable spring **1300** includes a dipolar magnet **1330** and a coil **1310** arranged about the dipolar magnet **1310**. Current applied to the coil **1310** may cause a magnetic force that is axial to the coil **310** and that increases or decreases based on the current applied to the coil **310**. For example, FIG. **13B** shows an upward force applied when the coil **1310** is proximate to the south pole of the magnet and FIG. **13C** shows a downward facing force when the coil is proximate to the north pole of the magnet. The magnitude of the force applied may be proportional to the current applied to the coil **1310**. The result is a mechanism that acts as a spring to return to the nominal position at any given time.

[0109] A coil-based spring **1300** has certain advantages over a more traditional mechanical springs such as helical compression springs. First, the spring strength can be adjusted at any given time by varying the current applied to the coil **1310**. An increased current causes greater magnetic forces resulting in a stiffer spring (i.e., a higher spring constant). Conversely, a decreased current reduces the magnetic forces resulting in a less stiff spring (i.e., lower spring constant). This arrangement can be applied to configure a spring that can adjust automatically and/or in response to user commands to accommodate changing conditions.

Implementation of Coil Actuators in an Aerial Vehicle

[0110] Coil actuators such as those described with respect to FIGS. 1-13C can be used in a variety of different applications where motion of an object is required such as vehicles, robots, gimbals, industrial machinery, and many other types of technologies. As alluded to earlier, such coil actuators may be particularly suited for use in aerial vehicles such as UAVs that have strict space and weight constraints; however, similar coil actuators can similarly be implemented in manned vehicles as well. As will be described, coil actuators can be implemented, for example, as part of an onboard camera gimbal mechanism or as part of a camera stabilization system.

[0111] FIG. 14 shows an example configuration of a UAV 1400 in which the introduced coil actuator can be implemented. The example UAV 1400 is depicted in FIG. 14 as a rotor-based aircraft (e.g., a “quadcopter”); however, this is not intended to be limiting. The example UAV 1400 may include one or more sensors such as proximity sensors, range sensors, audio sensors, optical sensors, etc., for use in autonomous navigation and flight control. For example, the UAV 1400 may include one or more image capture devices such as a camera 1415 for capturing images of the surrounding physical environment while in flight. “Images,” in this context, include both still images and capture video. The UAV 1400 may also include systems such as Wi-Fi, Bluetooth, etc., for communicating with other devices (e.g., a mobile device 1404) via a wireless communication channel 1416.

[0112] In the example depicted in FIG. 14, the camera 1415 is depicted capturing an object 1402 in the physical environment that happens to be a person. In some cases, the camera may be configured to capture images for display to users (e.g., as an aerial video platform) and/or, as described above, may also be configured for capturing images for use in autonomous navigation. In other words, the UAV 1400 may autonomously (i.e., without direct human control) navigate the physical environment, for example, by processing images captured by one or more cameras. While in autonomous flight, UAV 1400 can also capture images that can be displayed in real time and/or recorded for later display at other devices (e.g., mobile device 1404).

[0113] In some embodiments, the camera 1415 is coupled to the body of the UAV 1400 via an adjustable mechanism that allows for one or more degrees of freedom of motion relative to a body of the UAV 1400. The UAV 1400 may be configured to automatically adjust an orientation of the camera 1415 so as to track image capture of an object (e.g., human subject 1402) as both the UAV 1400 and object are in motion through the physical environment and/or to compensate for motion of the UAV 1400. In some embodiments, this adjustable mechanism may include a mechanical gimbal mechanism that rotates an attached camera about one or more axes. The gimbal mechanism can include any of the aforementioned coil actuators and/or other types of actuators such as BLDC motors.

[0114] FIG. 15 shows a side view of an example image capture assembly 1515 that includes a motorized gimbal mechanism for actively stabilizing a mounted camera 1415. In general, a motorized gimbal mechanism may include multiple link arms coupled at one or more motorized rotation joints. The link arms and rotation joints form a mechanical linkage coupling the camera 1415 to a platform 1530 such as the body of an aerial vehicle such as UAV 1400. In an example embodiment, in response to the detected motion (e.g., using accelerometers or other motion sensors) actuators (e.g., DC motors, coil actuators, etc.) at the rotation joints actuate the link arms about the axes of rotation of the rotation joints to counter the detected motion(s). The combined effect of this actuation by the motors is to stabilize the mounted camera 1415 relative to a particular frame of reference (e.g., the surface of the Earth) and/or to reorient to track an object in the physical environment. Alternatively, or in addition, actuators at the rotation joints may actuate the link arms to change an orientation of the attached camera 1415 so as to keep a particular object in view regardless of the motion of the platform 1530. For example, actuators in a motorized gimbal mechanism may adjust an orientation of the camera 1415 to keep a tracked subject 1402 in a field of view of the camera 1415 while the UAV 1400 maneuvers through the environment. These are just example uses for a gimbal mechanism onboard an aerial vehicle. Other uses include rotating a

sensor from a landscape to a portrait orientation, improving the coverage of a sensor with a narrow FOV by scanning back and forth, for tilting a camera during turns to suggest more aggressive motion for cinematic appeal, etc.

[0115] FIG. **15** shows an example embodiment of a motorized gimbal mechanism that is rotatable about two axes using two gimbal motors **1542** and **1544**. As shown in FIG. **15**, camera **1415** can be pitched up and down about axis **1554** by actuating motor **1544** and rotated about axis **1552** by actuating motor **1542**. Although motors **1542** and **1544** are depicted as BLDC motors (due to the cylindrical appearance), alternative actuators such as coil actuators may similarly be implemented. In some embodiments, such a two-axis gimbal system may be implemented as part of a hybrid mechanical-digital gimbal system. This two-axis configuration is described for illustrative purposes and is not to be construed as limiting. In some embodiments image capture assembly **1515** may include a motorized gimbal providing more or fewer degrees of freedom of motion for a mounted camera **1415**.

[0116] When implemented as part of a gimbal mechanism in a vehicle (e.g., UAV **1400**), a coil actuator can be arranged at any angle relative to the vehicle. Further, the actuator can be located at any height within a gimbal mechanism and at any distance away from the axis of rotation. This allows the actuator to be located in a volume of space that is most available within a gimbal mechanism. This is in contrast to a brushless motor that requires a cylindrical volume of space in line with an axis of rotation.

[0117] FIG. **16A** shows an example implementation of a coil actuator **1600** configured to apply yaw rotation to a payload such as a camera. As shown in FIG. **16A**, the example coil actuator includes a payload frame **1620**, a coil **1610** coupled to the payload frame **1620** and arranged within or proximate to a magnet assembly **1630** that is coupled to another structure **1640**. In the example depicted in FIG. **16A**, the other structure **1640** may be part of or coupled to the body of a vehicle such as a UAV. Alternatively, the other structure **1640** may be part of a multi-arm gimbal mechanism that is coupled to the body of a vehicle.

[0118] The payload frame **1620** of actuator **1600** is analogous to arm **120** of example coil actuator **100** in that it includes an arm that extends radially from the axis of rotation **1650**. Similarly, the coil **1610** is analogous to coil **110** in that it is arranged at a distal end of the arm of the payload frame and passes through a magnetic field generated by the magnet assembly **1630**. Note that the magnet assembly **1630** depicted in FIGS. **16A-16B** also includes a flux guide (the “C” shaped structure) to direct and/or focus the magnetic field through which the coil **1610** passes. In the example actuator **1600**, magnet assembly **1630** includes one or more permanent magnets arranged along a top interior surface of the flux guide. The arm of the payload structure **1620** and the associated coil **1610** pass through under the one or more permanent magnets of the magnet assembly **1630**.

[0119] By applying varying current (e.g., varying DC) in the coil **1610** in proximity to the magnet assembly **1630**, a tangential electromagnetic force is applied to the payload structure **1620** supporting the coil **1610**. The direction of the force can be reversed by reversing polarity. The force, acting on a distal end of the arm of the payload structure **1620** a radial distance from the axis of rotation **1650**, causes torque that drives a rotation of the payload structure **1620** and associated coil **1610** about the axis **1650** relative to the other structure **1640**. In other words, as a result of applying current to the coil **1610**, the payload structure **1620** (and any coupled payload such as a camera **1615**) rotates about axis **1650** relative to structure **1640**. FIG. **16B** depicts a camera **1615** coupled to the payload frame **1620**. Accordingly, the camera **1615** can be rotated about axis **1650** by applying current to the coil **1610**.

[0120] FIG. **17A** shows a top view of an example actuator assembly **1700a** including a coil **1710** and corresponding magnet **1732**. The coil **1710** may be comprised of a coil of any type of material (e.g., copper) capable of conducting electricity. FIG. **17B** shows an example actuator assembly **1700b** similar to that depicted in FIG. **17A**, but with an added flux guide **1734** coupled (or arranged proximate) to the magnet **1732**. As mentioned, a flux guide **1734** can be implemented to direct

and/or focus the magnetic field of the magnet **1732** to suit the requirements of the actuator.

[0121] The magnet **1732** can be configured as a single arc with two poles, for example, as depicted in FIG. **17A** or as multiple discrete magnets, for example, as depicted in FIG. **18B**. In an example embodiment specifically configured to handle yaw rotation (of approximate ± 10 degrees) of a camera coupled to an aerial vehicle, the coil **1710** may comprise approximately 60 turns of 35 AWG copper wire. The magnet **1732** may be shaped as an arc, for example, as depicted in FIG. **17A**, with an arc radius of approximately 15 millimeters. As shown, the coil **1710** may comprise a single coil with each pole of the magnet covering the sweep areas of one side of the coil such that the current in each side of the coil loop generates a force in the same direction.

[0122] Depending on specifics, such a configuration should be able to achieve a target peak torque sufficient to rotate a camera (e.g., approximately 0.003Nm) by applying a peak current of approximately 0.6A. However, a person having ordinary skill in the relevant art will recognize that the coil **1710** and/or magnet **1732** may be configured differently depending on application (e.g., camera gimbal, flight control actuator, etc.), operational requirements (e.g., range of motion, torque, etc.), geometry and arrangement of structural elements of the actuator assembly, and other considerations. In one embodiment, a coil of 156 turns of 38AWG wire may be constructed to have 5 mm of conductor length in a magnetic field of 0.57 Telsa. With a pivot radius of 17 mm to the center of the coil, a resulting torque constant of 0.015 Newton/amp can be achieved. For a coil actuator of this type, the resulting torque around a pivot can be calculated by taking the product of: the number of conductors in the magnetic field and normal to the direction of coil motion, length of the conductors within the magnetic field and normal to the direction of motion, the magnitude of the magnetic field, the magnitude of electrical current flowing through the conductors, and the radial distance from pivot to the midpoint of the conductor length within the magnetic field.

[0123] In some embodiments, the current applied to a given coil in a coil actuator may be limited based on the thermal capacity of the coil to avoid damaging the coil. In such embodiments, a process can be performed to limit the peak current applied to the coil based on a measured or predicted temperature of the coil. Specifically, a computer system that is electrically and/or communicatively coupled to the coil actuator may execute instructions for determining a maximum current to be applied to a coil based on a measured or predicted temperature of the coil. The temperature of the coil can be measured, for example, using temperature sensors in proximity to the coil. The temperature of the coil can also be estimated or predicted by measuring the coil voltage and temperature, calculating resistance based on Ohm's Law, and then using the thermal coefficient of resistance for the material forming the coil (e.g., Copper) to calculate a coil temperature. In some embodiments, a thermal model of the system can be generated based on observed conditions. Measured values (e.g., for voltage and/or current) can then be input into the thermal model to estimate or predict the temperature of the coil.

[0124] In any case, a maximum current can be determined based on a measured, estimated, or predicted temperature of a coil. This determined maximum can be used to limit peak current that can be applied to the coil at any time. In some embodiments, the determined maximum current dynamically changes over time as the coil temperature changes.

[0125] In some embodiments, the coil **1710** and/or magnet **1732** can be manufactured separately and affixed (e.g., using an adhesive, clip, tie, screw, etc.) to either a dynamic arm or static structure. Alternatively, or in addition, the coil **1710** and/or magnet **1732** may be co-molded into such structures. In some embodiments, the coil **1710** may be integrated into a flex circuit or rigid printed circuit board assembly (PCBA).

[0126] In some embodiments, magnets can be used above and below the coil to direct and/or focus the magnetic field (with or without a flux guide). FIG. **18A** shows an example magnet assembly that include one or more magnets **1832** arranged above and below a coil **1810**. In such an embodiment, the one or more magnets **1832** can be coupled to opposing interior surfaces of a magnet assembly housing or a flux guide **1834**, for example as depicted in FIG. **18A**.

[0127] In some embodiments, magnets can be used on only one side above or below the coil with a magnetically conducting yoke (i.e., flux guide) to direct and/or focus the magnetic field. For example, the previously described FIG. 17B shows an example magnet assembly that includes a single magnet **1732** coupled to a top interior surface of a flux guide **1734** so as to be arranged above the coil **1710**, while in use. Conversely, FIG. 18B shows an example magnet assembly that includes multiple discrete magnets **1836** coupled to a top interior surface of the flux guide **1838** so as to be arranged above a coil **1812**, while in use. Although not depicted in the figures, the magnets may similarly be arranged on bottom interior surfaces of assembly housings or flux guides so as to be arranged below the coil **1812**, while in use. Further, in some embodiments, a multiple-pole magnet assembly with multiple phase coils may be implemented with any type of commutation used to energize the coils as necessary to control the torque at a current position.

[0128] As previously discussed, a gimbal mechanism can be configured to adjust an orientation of a payload such as a camera about multiple axes. For example, a 3-axis gimbal can include multiple actuators to adjust a pitch, roll, and yaw of an attached payload. In some embodiments, different type of actuators may be utilized to control rotation about different axes. For example, FIG. 19 shows a conceptual diagram that represents a mechanical linkage system **1900** that may be part of a gimbal mechanism. Such a gimbal mechanism may be on board a UAV and configured to adjust an orientation of an attached payload such as a camera. As shown in FIG. 19, the example mechanical linkage system **1900** includes different types of actuators to control different ranges of motion. Specifically, the example mechanical linkage system **1900** includes rotatory motors (e.g., BLDC motors) **1902** and **1906** to adjust the pitch and roll (respectively) of an attached payload and a coil actuator **1904** (e.g., as previously described) to adjust the yaw of an attached payload. This is just an example configuration for a mechanical linkage system in a gimbal mechanism that includes a coil actuator. Other embodiments may include additional coil actuators and/or may use coil actuators to control different motion (e.g., pitch and/or roll).

[0129] The example mechanical linkage system **1900** described with respect to FIG. 19 utilizes different types of actuators to drive motion on different axes (i.e., pitch vs. yaw vs. roll); however, in some embodiments, multiple different actuators may be connected in series to drive varying degrees of motion on the same axis. For example, the coil actuator may be connected in series with a rotary motor to control rotation about a single axis (e.g., yaw). In such a configuration, the coil actuator may control fine tuning and error correction while a rotary motor controls directional pointing. A coil actuator driving fine tuning and error correction (i.e., small ranges of motion) would allow for a system with lower inertia and higher frequency response.

[0130] FIGS. 20A-20B show a perspective view and a top view (respectively) of an example gimbal mechanism **2000** that uses a coil actuator for yaw control and rotatory motors (e.g., BLDC motors) for large-angle roll and pitch control, similar to the example mechanical linkage system **1900** described with respect to FIG. 19. In the example depicted in FIGS. 7A-7B, a camera **2015** is coupled to a first rotary motor **2040** configured to provide pitch control of the camera **2015**. For example, as shown in FIGS. 20A-20B, operation of the first rotary motor causes the attached camera **2015** to rotate about axis **2090x**. The combined assembly of the camera **2015** and first rotary motor **2040** is coupled to a coil actuator **2030** (e.g., similar to that depicted in FIG. 16A) configured to provide yaw control of the camera **2015**. For example, as shown in FIGS. 20A-20B, operation of the coil actuator **2030** causes the combined assembly of the camera **2015** and first rotary motor **2040** to rotate about axis **2090y**. The combined assembly of the camera **2015**, first rotary motor **2040**, and coil actuator **2030** is coupled to a platform **2080** (e.g., the body of a UAV) via a second rotary motor **2050** configured to provide roll control of the camera **2015**. For example, as shown in FIGS. 20A-20B, operation of the second rotary motor **2050** causes the combined assembly of the camera **2015**, first rotary motor **2040**, and coil actuator **2030** to rotate about axis **2090z**.

[0131] FIG. 21 shows a schematic diagram of an example circuit **2100** for a gimbal mechanism.

Specifically, FIG. 8 shows an example schematic for a gimbal mechanism that includes two rotary motors and a coil motor, for example, similar to the gimbal mechanism depicted in FIGS. 20A-20B. Typically, in order to drive a 3-phase BLDC motor, the voltages for each phase must have a fixed offset. However, the offset between a given phase for each rotary motor can be chosen arbitrarily without affecting the function of the motor (relative voltage between those phases). By adding a voltage offset to each set of the 3 phases, a given voltage between phase 1 of the first rotary motor and phase 2 of the second rotary motor can be achieved. This voltage offset can therefore be used to control the coil actuator without adding any additional driving circuitry. [0132] Coil actuators can be used in other ways on board an aerial vehicle. For example, as previously discussed with respect to FIGS. 13A-13B, the underlying concept can be applied to implement an adjustable coil-based spring mechanism. Such coil-based springs can be implemented as part of system for stabilizing a camera (or other components) on board an aerial vehicle.

[0133] FIGS. 22A-22C show a series of views of an example isolator 2234 that may be implemented as part of a stabilization system on an aerial vehicle. As will be described, such an isolator 2234 may act as a spring damper to isolate certain components from rotational and/or translational motion in one or more directions by the body of an aerial vehicle such as UAV 1400. Specifically, FIG. 22A shows an isometric view of isolator 2234, FIG. 22B shows a side view of isolator 2234, and FIG. 22C shows a cross section (as indicated by cross section label 22C in FIG. 22A) of isolator 2234.

[0134] As shown in FIGS. 22A-22C, isolator 2234 includes one or more side walls 2235 that are arranged in a generally cylindrical shape that is hollow along an axis 2236. The walls 2235 of the isolator 2234 may be made of one or more elastomer materials such as natural and/or synthetic rubbers. The walls 2235 are depicted in FIGS. 22A-22C as having a specific geometry; however, this is not to be construed as limiting. The geometry implemented will depend on the materials used as well as the desired compression stiffness, tensile stiffness, and/or shear stiffness.

[0135] Certain spring and/or dampening characteristics of such an isolator 2234 can be made dynamically adjustable through the introduction of a coil-based spring mechanism, for example, similar to as discussed with respect to FIGS. 13A-13B. As shown in the cross section at FIG. 22C, a coil 2210 can be arranged within or along the walls 2235 of the isolator 2234. When in use, this coil 2210 may pass through a magnetic field generated by a magnet such as the dipolar magnet 2230 that is arranged along the axis 2236. As explained with reference to FIGS. 13A-13B, application of a current to coil 2210 will cause a magnetic force that is axial to the coil 2210 to be applied. The amount of force applied will depend on the amount of current applied to the coil 2210. For example, as external forces are applied (e.g., due to motion of the body of an aerial vehicle), the elastomer in the walls 2235 of the isolator 2234 will deform thereby causing the coil 2210 to move relative to the magnet 2230. Assuming a current is applied to the coil 2210, the change in position between the coil 2210 and magnet 2230 will apply a countering electromagnetic force.

[0136] The electromagnetic forces, along with the inter-molecular return forces of the elastomer material of the walls 2235, will cause the isolator 2234 to exhibit spring/damping characteristics. Further, the spring/damping characteristics of the isolator 2234 can be adjusted by adjusting the current applied to the coil 2210. Higher current applied to coil 2210 may increase stiffness while lower current applied to coil 2210 may decrease stiffness, at least in the direction of axis 2236.

[0137] FIGS. 23A-22C show a series of cross sections of a body of an aerial vehicle such as a UAV that illustrate how isolators such as isolator 2234 described in FIGS. 22A-C can be implemented as part of a stabilization system (e.g., for a camera) on board an aerial vehicle. The implementation depicted in FIGS. 23A-C is just an example provided for illustrative purposes and is not to be construed as limiting. A person having ordinary skill in the art will recognize that isolators such as isolator 2234 may be implemented in other ways than is depicted in FIGS. 23A-C.

[0138] FIG. 23A shows a first cross section of an example UAV 2300. As shown in FIG. 23A, the

example UAV **2300** includes a housing **2310** with one or more walls that substantially surround an interior space **2318**. The interior space **2318** has an opening **2320** at a “front end” of the housing **2310** through which an image capture assembly **2340** protrudes and is defined by the interior surfaces of one or more of the walls of the housing **2310**. For example, as shown in FIG. **23A**, the interior space **2318** is defined by an interior top surface **2314**, an interior bottom surface **2316** opposite the interior top surface **2314**, and an interior back surface **2312** opposite the opening **2320** and located towards the “back end” **2322** of the housing **2310**.

[0139] As further shown in FIG. **23A**, the image capture assembly **2340** is structurally coupled to a stabilization assembly that includes an elongated arm **2332**, a mounting assembly **2336**, and one or more isolators **2234**. The image capture assembly **2340** may include one or more components related to image capture systems such as a camera and one or more active systems such as a mechanical gimbal. For example, the image capture assembly **2340** may comprise the multi-axis gimbal mechanism **2000** described with respect to FIGS. **20A-20B**.

[0140] In the depicted embodiment, the elongated arm **2332** has a proximal end and a distal end and is arranged within the interior space **2318** to extend from the interior back surface **2312** towards the opening **2320** at the front end of the housing **2310**. The distal end of the elongated arm **2332** is dynamically coupled to the interior back surface **2312** via one or more isolators **2234** and the proximal end is coupled to the mounting assembly **2336** which is in turn mounted to any of the interior top surface **2314** or interior bottom surface **2316** (not depicted in FIG. **23A**) via one or more isolators **2234**. The image capture assembly **2340** is structurally coupled to the mounting assembly **2336** of the stabilization assembly. Accordingly, the stabilization assembly (i.e., including components **2234**, **2332**, and **2336**) and image capture assembly **2340** form a structural unit that is dynamically coupled to the housing **2310**.

[0141] Further, the elongated arm **2332** forms a counter balance to the mass of the components in the image capture assembly **2340**. The image capture assembly **2340** is thereby stabilized by a counter-balanced suspension system, for example, as depicted in FIG. **23A** which shows the dynamic components (i.e., the stabilization assembly and image stabilization assembly **2340**) in mechanical equilibrium. For example, the dynamic components supported or suspended via isolators **2234** may have a center of mass at point **2360**. FIGS. **23B-23C** show the stabilization of the image assembly **2340** in response to movement of example UAV **2300**. For example, FIGS. **23B-23C** illustrate stabilization of image assembly **2340** in response to the rotational and/or translational motion by example UAV **2300**.

[0142] Since the isolators **2234** supporting the image capture assembly **2340** include coil-based spring mechanisms, the spring/damping response of the suspension system can be adjusted by adjusting the current applied to the coils. In some embodiments, the current to the coils in one or more of the isolators **2234** can be adjusted in response to a command from a user of the UAV **2300**. The user may input such a command via a remote device such as a mobile device **1404**.

[0143] Alternatively, or in addition, the current to the coils of one or more of the isolators can be adjusted automatically by a control system on board the UAV **2300**, for example, in response to changing conditions. As an illustrative example, an on-board control system associated with the UAV **2300** may sense or predict a maneuver by the UAV **2300** that will cause the body **2310** of the UAV **2300** to rapidly change position and/or orientation. To counter the motion of the body **2310**, the control system may increase an applied current in the coils of any of the isolators **2234** thereby stiffening the suspension system, at least momentarily during the maneuver. In such an embodiment, the control system may selectively adjust current in the coils of one or more of the isolators based on the characteristics of the maneuver. For example, if a maneuver involves (or will involve) motion in a forward direction, the control system may increase current in the coil of the isolator **2234** connecting the elongated arm **2332** to the interior back surface **2312** to increase stiffness of the isolator **2234** to counter the inertia of the image capture assembly **2340**. Similarly, if the maneuver involves (or will involve) motion in an upward or downward direction, the control

system may increase current in the coil of the isolator **2234** connecting the mounting assembly **2360** to the interior top surface **2314** to counter the inertia of the image capture assembly **2340**. [0144] Note that the arrangement of elements comprising example UAV **2300** are depicted in FIGS. **23A-C** in a simplified form to clearly illustrate the concept of stabilization of a mounted image capture assembly **2340** through the use of a counter-balanced suspension system that includes coil-based isolators. For example, housing **2310** is depicted in a simplified rectangular form, but depending on the specific implementation, housing **2310** may have any shape of any dimension. Further, the walls forming the housing **2310** are depicted in a simplified form and are not to be construed as limiting with regard to arrangement or dimension.

Actuator Control System

[0145] FIG. **24** is a block diagram that illustrates an example control system **2420** that may be implemented to control any one or more of previously discussed actuators. The control system **2420** may include any combination of hardware and/or software. For example, in some embodiments, the control system **2420** and any associated subsystems may be implemented as instructions stored in memory that are executable by one or more processors. In some embodiments, the control system **2420** may include one or more components of the computer processing system **2500** described with respect to FIG. **25**.

[0146] As shown in FIG. **24**, the example control system **2420** may receive inputs in the form of control inputs **2470** and/or sensor data **2412**. Control inputs **2470** may include inputs from other control system (e.g., an autonomous navigation system onboard a UAV **1400**) or may include inputs based on user commands, for example, received by an associated user device such as a mobile device **1404**. Sensor data **2412** may be received from one or more sensor devices that are communicatively coupled to the control system **2420**. Such sensor devices may include optical sensors (e.g., cameras), audio sensors, proximity sensors, motion sensors, etc.

[0147] The control system **2420** processes the received control inputs **2470** and/or sensor data **2412** to generate control signals, control commands, etc. for controlling one or more actuators **2410**. The one or more actuators **2410** may include any of the example coil actuators as well as non-coil actuators such as BLDC motors. In some embodiments, the control system **2420** controls the one or more actuators **2410** by varying current applied to the actuators **2410**, for example, in response to control inputs **2470**. In some embodiments, the control system **2420** controls the actuators **2410** by communicating signals to one or more specialty controllers **2460** that are associated with the actuators **2410**. For example, the control system **2420** may be part of a central control and/or autonomous navigation system onboard an aerial vehicle such as UAV **1400** that includes a gimbal mounted camera. The gimbal mechanism used to adjust the rotation of the mounted camera may include one or more actuators **2410** (e.g., as described with respect to FIGS. **20A-20B**) as well as one or more controllers **2460** that are specially adapted to receiving control signals from the control system **2420** and varying a current applied to the actuators **2410**, for example, to cause the actuators **2410** to rotate. The actuators **2410** and associated controllers **2460** may similarly be part of a stabilization system, for example, as described with respect to FIGS. **23A-23C**.

[0148] In some embodiments, the control system **2420** and/or the controller **2460** may comprise an integrated electronic controller (e.g., an electronic speed controller) specifically adapted to controlling electronic actuators based on input electrical signals. Such an electronic speed controller may include a voltage regulator, a processor, and one or more switches such as field effect transistors (FETs). In example embodiment, the processor receives inputs (e.g., control inputs **2470** and/or control signals from a separate control system **2420**), processes the received inputs, and switches the one or more FETs based on the processing to regulate the current applied to the one or more actuators **2410** coupled to the controller **2460**.

[0149] In some embodiments, the control system **2420** may be configured to receive higher level control inputs (e.g., control inputs **2470**) and translate those higher-level control inputs into lower-level control inputs that are usable by controllers **2460** associated actuators **2410**. For example,

control system **2420** may be configured to control an image capture subsystem of a UAV **1400** that includes a gimbal-mounted camera **1415**. The control system **2460** may receive a high-level input such as an objective input to cause the camera to track the motion of a particular subject (e.g., subject **1402**) in the physical environment. Using sensor data **2412** (e.g., images from cameras onboard the UAV **1400**) the control system **2420** may continually estimate a position and/or orientation of the UAV **1400** and a position and/or orientation of the tracked subject. Based on these estimations, the control system **2420** may generate control signal that are sent to separate controllers **2460** to cause the actuators **2410** of a multi-axis gimbal mechanism to adjust the orientation of the attached camera **1415** to track the relative motion of the subject (i.e., keep the subject within a field of view of the camera **1415**).

Computer Processing System

[0150] FIG. **25** is a block diagram illustrating an example of a processing system **2500** which may be implemented to control any one or more of the aforementioned actuators. For example, some components of the processing system **2500** may be part of a computing device onboard a UAV **1400** and/or such as mobile device **1404**.

[0151] The processing system **2500** may include one or more processing units (“processors”) **2502**, main memory **2506**, non-volatile memory **2510**, network adapter **2512** (also referred to as a network interface), video display **2518**, input/output devices **2520**, control device **2522** (e.g., keyboard and pointing devices), drive unit **2524** including a storage medium **2526**, and signal generation device **2530** that are communicatively connected to a bus **2516**. The bus **2516** is illustrated as an abstraction that represents one or more physical buses and/or point-to-point connections that are connected by appropriate bridges, adapters, or controllers. The bus **2516**, therefore, can include a system bus, a Peripheral Component Interconnect (PCI) bus or PCI-Express bus, a HyperTransport or industry standard architecture (ISA) bus, a small computer system interface (SCSI) bus, a universal serial bus (USB), IIC (I2C) bus, or an Institute of Electrical and Electronics Engineers (IEEE) standard **1394** bus (also referred to as “Firewire”).

[0152] The processors **2502** may include combinations of general-purpose programmable microprocessors such as central processing units (CPUs), special-purpose programmable microprocessors such as graphical processing units (GPU), special-purpose hardwired (i.e., non-programmable) circuitry, or combinations of such forms. Some special-purpose circuitry may be in the form of one or more application-specific integrated circuits (ASICs), programmable logic devices (PLDs), field-programmable gate arrays (FPGAs), etc.

[0153] The processing system **2500** may share a similar computer processor architecture as that of a desktop computer, tablet computer, personal digital assistant (PDA), mobile phone, game console, music player, wearable electronic device (e.g., a watch or fitness tracker), network-connected (“smart”) device (e.g., a television or home assistant device), virtual/augmented reality systems (e.g., a head-mounted display), or another electronic device capable of executing a set of instructions (sequential or otherwise) that specify action(s) to be taken by the processing system **2500**.

[0154] While the main memory **2506**, non-volatile memory **2510**, and storage medium **2526** (also called a “machine-readable medium”) are shown to be a single medium, the term “machine-readable medium” and “storage medium” should be taken to include a single medium or multiple media (e.g., a centralized/distributed database and/or associated caches and servers) that store one or more sets of instructions **2528**. The term “machine-readable medium” and “storage medium” shall also be taken to include any medium that is capable of storing, encoding, or carrying a set of instructions for execution by the processing system **2500**.

[0155] In general, the routines executed to implement the embodiments of the disclosure may be implemented as part of an operating system or a specific application, component, program, object, module, or sequence of instructions (collectively referred to as “computer programs”). The computer programs typically comprise one or more instructions (e.g., instructions **2504**, **2508**,

2528) set at various times in various memory and storage devices in a computing device. When read and executed by the one or more processors **2502**, the instruction(s) cause the processing system **2500** to perform operations to execute elements involving the various aspects of the disclosure.

[0156] Moreover, while embodiments have been described in the context of fully functioning computing devices, those skilled in the art will appreciate that the various embodiments are capable of being distributed as a program product in a variety of forms. The disclosure applies regardless of the particular type of machine or computer-readable media used to actually effect the distribution.

[0157] Further examples of machine-readable storage media, machine-readable media, or computer-readable media include recordable-type media such as volatile and non-volatile memory devices **2510**, floppy and other removable disks, hard disk drives, optical discs (e.g., Compact Disc Read-Only Memory (CD-ROMS), Digital Versatile Discs (DVDs)), and transmission-type media such as digital and analog communication links.

[0158] The network adapter **2512** enables the processing system **2500** to mediate data in a network **2514** with an entity that is external to the processing system **2500** through any communication protocol supported by the processing system **2500** and the external entity. The network adapter **2512** can include a network adaptor card, a wireless network interface card, a router, an access point, a wireless router, a switch, a multilayer switch, a protocol converter, a gateway, a bridge, a bridge router, a hub, a digital media receiver, and/or a repeater.

[0159] The network adapter **2512** may include a firewall that governs and/or manages permission to access/proxy data in a computer network, as well as tracks varying levels of trust between different machines and/or applications. The firewall can be any number of modules having any combination of hardware and/or software components able to enforce a predetermined set of access rights between a particular set of machines and applications, machines and machines, and/or applications and applications (e.g., to regulate the flow of traffic and resource sharing between these entities). The firewall may additionally manage and/or have access to an access control list that details permissions including the access and operation rights of an object by an individual, a machine, and/or an application, and the circumstances under which the permission rights stand.

Claims

1-30. (canceled)

31. An actuator assembly comprising: a first structural element including a magnet assembly; a second structural element rotatably coupled to the first structural element about a rotation axis, the second structural element including a coil arranged relative to the magnet assembly such that current applied to the coil causes the second structural element to rotate about the rotation axis; a position sensor configured to sense a relative angular position of the second structural element with respect to the first structural element; and a controller configured to adjust a current applied to the coil based on an output of the position sensor to control a position of the second structural element.

32. The actuator assembly of claim 31, wherein the coil is a voice coil comprising copper windings formed on a flexible circuit.

33. The actuator assembly of claim 31, wherein the magnet assembly includes an arc-shaped permanent magnet.

34. The actuator assembly of claim 31, wherein the position sensor comprises a hall-effect sensor or a magnetometer.

35. The actuator assembly of claim 31, wherein the controller is configured to implement a proportional-integral-derivative (PID) control loop to regulate the current.

36. The actuator assembly of claim 31, wherein the controller is configured to limit the current applied to the coil based on a measured or predicted temperature of the coil.

37. The actuator assembly of claim 31, wherein the coil is arranged at a distal end of an arm that

extends radially from the rotation axis.

38. The actuator assembly of claim 31, wherein the position sensor comprises an optical encoder.

39. A method comprising: sensing, by a position sensor, a relative angular position of a second structural element rotatably coupled to a first structural element about a rotation axis, the second structural element including a coil arranged relative to a magnet assembly of the first structural element; generating, by a controller, a control signal based on the sensed angular position; and applying a current to the coil based on the control signal such that the second structural element rotates about the rotation axis.

40. The method of claim 39, wherein the sensing comprises generating position feedback using a gyro or an encoder mounted to the second structural element.

41. The method of claim 39, further comprising: determining a temperature of the coil and limiting the applied current based on the determined temperature.

42. The method of claim 39, wherein the control signal is generated using a closed-loop controller that includes filtering of the position signal.

43. The method of claim 39, wherein the controller limits a rate of change of the applied current to reduce overshoot.

44. An aerial vehicle comprising: a body; a payload; an actuator assembly coupling the payload to the body, the actuator assembly including: a first structural element coupled to the body and including a magnet assembly; a second structural element rotatably coupled to the first structural element and including a coil; a position sensor configured to sense a relative angular position of the second structural element with respect to the first structural element; and a controller configured to apply a current to the coil based on the sensed angular position to adjust an orientation of the payload relative to the body.

45. The aerial vehicle of claim 44, wherein the payload is a camera and the actuator assembly is configured to rotate the camera about a yaw axis.

46. The aerial vehicle of claim 44, wherein the actuator assembly is part of a gimbal mechanism that further includes at least one rotary motor configured to rotate the payload about a different axis.

47. The aerial vehicle of claim 44, wherein the position sensor comprises a hall-effect sensor mounted to the second structural element and aligned with a magnetic target coupled to the first structural element.

48. The aerial vehicle of claim 44, wherein the controller comprises an onboard processor configured to execute software for controlling orientation of the payload based on motion data and position feedback.

49. The aerial vehicle of claim 44, wherein the coil is mounted on a printed circuit board.

50. The aerial vehicle of claim 44, wherein the controller is configured to apply a correction signal to the coil in response to a deviation from a reference orientation.
