

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407323
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Nishizawa; Ryuta et al.

Vibrator device

Abstract

A vibrator device includes: a base including a semiconductor substrate having an integrated circuit disposed at a first surface; a vibration element electrically coupled to the integrated circuit; and a lid having an end surface of a side wall bonded to the first surface at a bonding portion. A first circuit of the integrated circuit includes a first circuit element disposed in a first region overlapping the bonding portion in a plan view. The first circuit element is a passive element or a transistor, and $\theta < 90^\circ$ is satisfied, θ being an angle formed by the first surface and an inner side surface of the side wall.

Inventors:	Nishizawa; Ryuta (Nagano, JP), Takeuchi; Junichi (Chino, JP)
Applicant:	SEIKO EPSON CORPORATION (Tokyo, JP)
Family ID:	91962771
Assignee:	SEIKO EPSON CORPORATION (Tokyo, JP)
Appl. No.:	18/427344
Filed:	January 30, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240258988 A1	Aug. 01, 2024

Foreign Application Priority Data

JP	2023-012739	Jan. 31, 2023
----	-------------	---------------

Publication Classification

Int. Cl.: H03H9/05 (20060101); H03B5/04 (20060101); H03B5/32 (20060101); H03H9/02 (20060101); H03H9/19 (20060101)

U.S. Cl.:

CPC H03H9/0547 (20130101); H03B5/04 (20130101); H03B5/32 (20130101); H03H9/02102 (20130101); H03H9/19 (20130101)

Field of Classification Search

CPC: H03H (9/0547); H03H (9/02102); H03H (9/19); H03B (5/04); H03B (5/32)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2015/0349746	12/2014	Yamazaki et al.	N/A	N/A
2016/0164490	12/2015	Kamijo	29/25.35	H03H 9/0509
2022/0173715	12/2021	Takeuchi et al.	N/A	N/A
2022/0239275	12/2021	Itasaka	N/A	N/A
2022/0286107	12/2021	Kitahara	N/A	N/A
2022/0311414	12/2021	Nomura	N/A	H03H 9/08

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2007180885	12/2006	JP	H03B 5/32
2015-226242	12/2014	JP	N/A
2021-57755	12/2020	JP	N/A
2022-85834	12/2021	JP	N/A
2022-114779	12/2021	JP	N/A
2022-134787	12/2021	JP	N/A

OTHER PUBLICATIONS

Machine translation of JP2007-180885 (Year: 2007). cited by examiner
Machine translation of JP2007180885. cited by examiner

Primary Examiner: Shin; Jeffrey M
Attorney, Agent or Firm: Rankin, Hill & Clark LLP

Background/Summary

(1) The present application is based on, and claims priority from JP Application Serial Number 2023-012739, filed Jan. 31, 2023, the disclosure of which is hereby incorporated by reference herein in its entirety.
BACKGROUND
1. Technical Field
(2) The present disclosure relates to a vibrator device.

2. Related Art

(3) A vibrator device such as an oscillator is known as a device using a vibration element. As such a vibrator device, for example, an oscillator is known in which a vibration element is accommodated in a first recess of a package having an H-shaped cross section, and an integrated circuit (IC) chip including an oscillation circuit and the like is accommodated in a second recess thereof. On the other hand, JP-A-2021-57755 discloses a wafer level packaging (WLP) type vibrator device including: a base having an integrated circuit disposed at one surface side thereof, the one surface side being an upper surface side; a lid bonded to the one surface side of the base; and a vibration element accommodated between the base and the lid.

(4) JP-A-2021-57755 is an example of the related art.

(5) It has been found that in such a WLP type vibrator device, when a stress is applied to the integrated circuit disposed at the one surface side that is the upper surface side of the base, circuit characteristics of the integrated circuit may be affected. For example, in order to bond the base and the lid, it is necessary to apply a pressure so as to have the lid and the base sandwiched. A stress generated in the base at this time affects the circuit characteristics of the integrated circuit formed at the one surface side of the base, and characteristics of the vibrator device may deteriorate.

SUMMARY

(6) An aspect of the disclosure relates to a vibrator device including: a base including a semiconductor substrate that has a first surface and a second surface in a front and back relationship with the first surface and that has an integrated circuit disposed at the first surface; a vibration element electrically coupled to the integrated circuit; and a lid provided with a recess for accommodating the vibration element, including a side wall around the recess, and having an end surface of the side wall bonded to the first surface at a bonding portion. The integrated circuit includes a first circuit, the first circuit includes a first circuit element disposed in a first region of the first surface, the first region overlapping the bonding portion in a plan view orthogonal to the first surface, the first circuit element is a passive element or a transistor, and $\theta < 90^\circ$ is satisfied, θ being an angle formed by the first surface and an inner side surface of the side wall.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a cross-sectional view illustrating a configuration example of a vibrator device according to an embodiment.

(2) FIG. 2 is a diagram illustrating an example of a manufacturing process of the vibrator device.

(3) FIG. 3 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(4) FIG. 4 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(5) FIG. 5 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(6) FIG. 6 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(7) FIG. 7 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(8) FIG. 8 is a diagram illustrating an example of the manufacturing process of the vibrator device.

(9) FIG. 9 is an explanatory diagram explaining an inclination of a side wall of a lid in the embodiment.

(10) FIG. 10 is an explanatory diagram explaining arrangement of circuit elements and circuits in an integrated circuit.

(11) FIG. 11 is an explanatory diagram explaining arrangement of a first circuit element and a first circuit.

(12) FIG. 12 is an explanatory diagram explaining arrangement of a second circuit element and a second circuit

(13) FIG. 13 is an explanatory graph explaining a relationship between an inclination angle α and

an angle θ and a stress.

(14) FIG. **14** is an explanatory graph explaining a relationship between an inclination angle α and an angle θ and a stress.

(15) FIG. **15** is an explanatory diagram explaining a stress at each position of a base.

(16) FIG. **16** is a graph illustrating a stress ratio at each position of the base.

(17) FIG. **17** is a graph illustrating a stress ratio at each position of the base.

(18) FIG. **18** is an explanatory diagram explaining an arrangement method of circuit elements according to the embodiment.

(19) FIG. **19** is a diagram illustrating a configuration example of the integrated circuit.

(20) FIG. **20** is a diagram illustrating another configuration example of the integrated circuit.

(21) FIG. **21** is an explanatory diagram explaining an arrangement method of the first circuit, the second circuit, the first circuit element, and the second circuit element.

(22) FIG. **22** illustrates a configuration example of a reference voltage generation circuit.

(23) FIG. **23** illustrates a configuration example of a regulator circuit.

(24) FIG. **24** illustrates a configuration example of a temperature sensor circuit.

(25) FIG. **25** illustrates a configuration example of a temperature sensor circuit.

(26) FIG. **26** illustrates a configuration example of an oscillation circuit.

(27) FIG. **27** illustrates a configuration example of a temperature compensation circuit.

(28) FIG. **28** illustrates a configuration example of a function current generation circuit of the temperature compensation circuit.

(29) FIG. **29** illustrates a layout arrangement example of the integrated circuit.

(30) FIG. **30** illustrates a layout arrangement example of the integrated circuit.

DESCRIPTION OF EMBODIMENTS

(31) Hereinafter, an embodiment will be described. The embodiment to be described below does not unduly limit the scope of the claims. Further, not all configurations described in the embodiment are necessarily essential components. In the following drawings, some components may be omitted for convenience of description. In the drawings, for easy understanding, a dimensional ratio of the components is different from an actual dimensional ratio thereof.

(32) 1. Vibrator Device

(33) FIG. **1** is a cross-sectional view illustrating a configuration example of a vibrator device **1** according to the embodiment. As illustrated in FIG. **1**, the vibrator device **1** according to the embodiment includes a base **2**, a lid **3**, and a vibration element **5**. The vibrator device **1** may include external coupling terminals **91** and **92**. In the drawings described in the embodiment, an X-axis, a Y-axis, and a Z-axis are illustrated as three axes orthogonal to one another. A direction along the X-axis is referred to as an X-axis direction or a first direction DR1, a direction along the Y-axis is referred to as a Y-axis direction or a second direction DR2, and a direction along the Z-axis is referred to as a Z-axis direction or a third direction DR3. In each axial direction, a tip end side of an arrow is referred to as a “plus side”, and a base end side is referred to as a “minus side”. A plus side in the Z-axis direction is referred to as “upper”, and a minus side in the Z-axis direction is referred to as “lower”. For example, the Z-axis direction is along a vertical direction, and an XY plane is along a horizontal plane. FIG. **1** is a cross-sectional view of the vibrator device **1** as viewed in the second direction DR2 that is the Y-axis direction.

(34) The vibrator device **1** is, for example, an oscillator. Specifically, the vibrator device **1** is, for example, an oscillator such as a temperature compensated crystal oscillator (TCXO), an oven controlled crystal oscillator (OCXO), a voltage-controlled crystal oscillator (VCXO), a simple packaged crystal oscillator (SPXO) as a crystal oscillator having no temperature compensation function, a surface acoustic wave (SAW) oscillator, a voltage-controlled SAW oscillator, or a micro electro mechanical system (MEMS) oscillator. The MEMS oscillator can be implemented by a vibration element of MEMS in which a piezoelectric film and an electrode are disposed at a substrate such as a silicon substrate. The vibrator device **1** may be an inertial sensor such as an

acceleration sensor or an angular velocity sensor, a force sensor such as an inclination sensor, or the like.

(35) The base **2** includes a semiconductor substrate **20**. The semiconductor substrate **20** is, for example, a silicon substrate. The semiconductor substrate **20** has a first surface **21** and a second surface **22** having a front and back relationship with the first surface **21**. The first surface **21** is, for example, an upper surface of the semiconductor substrate **20**, and the second surface **22** is, for example, a lower surface of the semiconductor substrate **20**. The first surface **21** and the second surface **22** of the semiconductor substrate **20** are also a first surface and a second surface of the base **2**. The first surface **21** and the second surface **22** of the semiconductor substrate **20** are surfaces along the XY plane and are surfaces orthogonal to the Z-axis. That is, the first surface **21** and the second surface **22** are surfaces along the first direction DR1 and the second direction DR2, and are surfaces orthogonal to the third direction DR3. Note that “being orthogonal” includes not only a case of intersecting at 90° but also a case of intersecting at an angle slightly deviated from 90°.

(36) The base **2** includes an integrated circuit **10**. The integrated circuit **10**, which is a semiconductor circuit, is formed at the first surface **21** of the semiconductor substrate **20**. The integrated circuit **10** includes a plurality of circuit elements. The circuit element is, for example, an active element such as a transistor or a diode, or a passive element such as a capacitive element, a resistive element, or an inductor element. The transistor is a CMOS transistor, a bipolar transistor or the like. Specifically, the integrated circuit **10** includes a plurality of circuit blocks each including a plurality of circuit elements. A first circuit and a second circuit of the integrated circuit **10** are one of the circuit blocks. The integrated circuit **10** includes a diffusion region that is an impurity region formed by doping the semiconductor substrate **20** with an impurity, and a wiring region in which a metal layer and an insulating layer are stacked. A source region and a drain region of a transistor that is a circuit element of the integrated circuit **10** are formed in the diffusion region, and a wiring that couples the circuit elements is formed in the wiring region. The coupling in the embodiment is electrical coupling. The electrical coupling is coupling in which an electrical signal can be transmitted and information can be transmitted through the electrical signal. The electrical coupling may be coupling via a passive element or the like.

(37) The base **2** includes a through electrode **40**. The through electrode **40** is made of a conductive material penetrating the semiconductor substrate **20**. For example, a through hole is formed in the semiconductor substrate **20**, and the through electrode **40** is formed by filling the through hole with a conductive material. The conductive material may be a metal such as copper or conductive polysilicon. The conductive polysilicon refers to polysilicon doped with an impurity of phosphorus (P), boron (B), or arsenic (As) to provide conductivity. When polysilicon is used as the conductive material, the through electrode **40** having sufficient resistance to heat received in a forming process of the integrated circuit **10** can be implemented.

(38) The through electrode **40** has one end electrically coupled to the integrated circuit **10** and the other end electrically coupled to the external coupling terminals **91** and **92**. Specifically, the one end of the through electrode **40** is coupled to a circuit element of the integrated circuit **10** via a contact pad formed at the integrated circuit **10**. The external coupling terminals **91** and **92** are provided at the second surface **22** side of the semiconductor substrate **20** via an insulating layer or the like. In this way, the integrated circuit **10** and the external coupling terminals **91** and **92** can be electrically coupled via the through electrode **40**. The external coupling terminals **91** and **92** of the vibrator device **1** are coupled to a terminal or wiring of a circuit board or the like on which the vibrator device **1** is mounted, so that the vibrator device **1** can be incorporated into an electronic apparatus.

(39) The lid **3** is bonded to the base **2** at bonding portions **36** and **37**. The base **2** is implemented by a semiconductor substrate such as a silicon substrate. Specifically, the lid **3** is provided with a recess **30** that accommodates the vibration element **5**, and includes side walls **32** and **33** around the

recess **30**. The side walls **32** and **33** are, for example, walls provided around the recess **30** in a plan view viewed in the third direction DR**3** that is the Z-axis direction. End surfaces **34** and **35** of the side walls **32** and **33** are bonded to the first surface **21** of the base **2** at the bonding portions **36** and **37**. The bonding portions **36** and **37** are implemented by a metal film of gold, copper or the like. The base **2** and the lid **3** are bonded to each other by applying a pressure to the bonding portions **36** and **37**, which are metal films of gold or the like, by a load described later. A method of bonding the base **2** and the lid **3** by the bonding portions **36** and **37** is not limited thereto, and various bonding methods such as direct bonding are conceivable. An airtight accommodation space SP is defined by the base **2** and the lid **3** as a lid body, and the vibration element **5** is accommodated in the accommodation space SP. The accommodation space SP corresponds to the recess **30** of the lid **3**. The accommodation space SP is hermetically sealed, and the accommodation space SP is, for example, in a depressurized state. Accordingly, the vibration element **5** can be stably driven. A state of the accommodation space SP is not limited to the depressurized state, and for example, the accommodating space SP may have an inert gas atmosphere.

(40) In the embodiment, the base **2** and the lid **3** are both implemented by a semiconductor substrate such as a silicon substrate. Accordingly, thermal expansion coefficients of the base **2** and the lid **3** can be made equal to each other, generation of a thermal stress due to thermal expansion can be prevented, and the vibrator device **1** having excellent characteristics can be implemented. In addition, since the vibrator device **1** can be formed by a semiconductor process, the vibrator device **1** can be manufactured accurately and efficiently, and a reduction in size of the vibrator device **1** can be achieved. The semiconductor substrate constituting the base **2** and the lid **3** is not limited to a silicon substrate, and may be a semiconductor substrate of Ge, GaP, GaAs, InP, or the like.

(41) The vibration element **5** is an element that generates mechanical vibration in response to an electrical signal. The vibration element **5** is electrically coupled to the integrated circuit **10**. For example, the vibration element **5** is disposed at the first surface **21** side of the semiconductor substrate **20**. Specifically, the vibration element **5** is disposed at a position spaced apart from the first surface **21** of the semiconductor substrate **20** by a given clearance. More specifically, the vibration element **5** is fixed at the first surface **21** of the semiconductor substrate **20** via, for example, a conductive bonding portion **60**.

(42) For example, the vibration element **5** includes a vibration substrate and an electrode disposed at a front surface of the vibration substrate. The vibration substrate has a thickness-shear vibration mode, and is formed of, for example, an AT-cut quartz crystal substrate. Since the AT-cut quartz crystal substrate has frequency-temperature characteristics showing a cubic curve, the vibration element **5** presents excellent temperature characteristics. In addition, the electrode includes an excitation electrode disposed at an upper surface of the vibration substrate and an excitation electrode disposed at a lower surface so as to face the excitation electrode.

(43) The configuration of the vibration element **5** is not limited to the above configuration. For example, the vibration element **5** may be of a mesa type in which a vibration region sandwiched between the two excitation electrodes protrudes from a periphery thereof, or may be of an inverted mesa type in which the vibration region is recessed from the periphery thereof. In addition, bevel machining in which a periphery of the vibration substrate is ground or convex machining in which the upper surface and the lower surface are made into convex surfaces may be performed. The vibration element **5** is not limited to a vibration element that vibrates in the thickness-shear vibration mode. For example, the vibration element **5** may be a tuning fork type vibration element in which a plurality of vibrating arms perform flexural vibration in an in-plane direction, a tuning fork type vibration element in which a plurality of vibrating arms perform flexural vibration in an out-of-plane direction, a gyro sensor element, or an acceleration sensor element. The gyro sensor element includes a driving arm performing drive vibration and a detection arm performing detection vibration, and detects an angular velocity. The acceleration sensor element includes a detection unit configured to detect an acceleration. The vibration substrate is not limited to the one

formed of the AT-cut quartz crystal substrate, and may be formed of a quartz crystal substrate other than the AT-cut quartz crystal substrate, for example, an X-cut quartz crystal substrate, a Y-cut quartz crystal substrate, a Z-cut quartz crystal substrate, a BT-cut quartz crystal substrate, an SC-cut quartz crystal substrate, or an ST-cut quartz crystal substrate. Although the vibration substrate is made of quartz crystal in the embodiment, the invention is not limited thereto. For example, the vibration substrate may be made of a piezoelectric single crystal body of lithium niobate, lithium tantalate, lithium tetraborate, potassium niobate, or gallium phosphate, or may be made of a piezoelectric single crystal body other than those described above. The vibration element **5** is not limited to a piezoelectric drive type vibration element, and may be an electrostatic drive type vibration element using an electrostatic force.

(44) The vibration element **5** is electrically coupled to the integrated circuit **10**. For example, a mount electrode **62** made of metal or the like is provided at the first surface **21** side of the semiconductor substrate **20**, and the conductive bonding portion **60** is provided on the mount electrode **62**. Accordingly, the vibration element **5** is electrically coupled to the integrated circuit **10** via the bonding portion **60** and the mount electrode **62**. For example, an insulating layer is formed at the first surface **21** of the semiconductor substrate **20**, and the mount electrode **62** is formed on the insulating layer. The mount electrode **62** is coupled to a circuit element of the integrated circuit **10** via a wiring **64** provided in the insulating layer and a contact pad (not shown) of the integrated circuit **10**. The conductive bonding portion **60** is implemented by a bump or the like. The bump is a conductive bonding member, and is specifically, a gold bump, a silver bump, a copper bump, a solder bump, a resin core bump, or the like. As the conductive bonding portion **60**, a conductive adhesive obtained by dispersing a conductive filler such as a silver filler in an adhesive such as a polyimide-based adhesive, an epoxy-based adhesive, a silicone-based adhesive, or an acrylic adhesive may be used.

(45) As described above, the vibrator device **1** of the embodiment includes the base **2** including the semiconductor substrate **20**, and the vibration element **5** electrically coupled to the integrated circuit **10**. The semiconductor substrate **20** has the first surface **21** and the second surface **22**, and the integrated circuit **10** is disposed, for example, at the first surface **21** of the semiconductor substrate **20**. In addition, the vibrator device **1** includes the lid **3** that includes the side walls **32** and **33** around the recess **30** accommodating the vibration element **5**, and the end surfaces **34** and **35** of the side walls **32** and **33** are bonded to the first surface **21** at the bonding portions **36** and **37**. In FIG. **1**, since the integrated circuit **10** is formed at the first surface **21** of the semiconductor substrate **20**, which is the lid **3** side, the integrated circuit **10** can be disposed in the accommodation space SP, and the integrated circuit **10** can be protected from an external environment.

(46) Next, an example of a manufacturing flow of the vibrator device **1** will be described with reference to FIGS. **2** to **8**. First, as illustrated in FIG. **2**, external coupling terminals **91** and **92** are formed on a first semiconductor wafer **120**. Then, as illustrated in FIG. **3**, the first semiconductor wafer **120** is ground and polished from the first surface **21** side to a thickness of, for example, about 60 μm to 80 μm . Next, as illustrated in FIG. **4**, the through hole **41** such as a through silicon via (TSV) is formed in the first semiconductor wafer **120**, and an insulating film **42** of silicon oxide (SiO₂) or the like is formed at an inner surface of the through hole **41**. As illustrated in FIG. **5**, the through electrode **40** is formed in the through hole **41**, and the integrated circuit **10** is formed at the first surface **21** of the semiconductor substrate **20**.

(47) Next, as illustrated in FIG. **6**, the vibration element **5** is coupled to the bonding portion **60**. Accordingly, the vibration element **5** and the integrated circuit **10** are electrically coupled. Further, a second semiconductor wafer **130** for forming the lid **3** is prepared, and a metal film **132**, which is a bonding film made of a material such as gold, is formed at a surface of the second semiconductor wafer **130** on a recess side.

(48) Next, as illustrated in FIG. **7**, the second semiconductor wafer **130** forming the lid **3** is bonded, via the bonding portions **36** and **37** by stress application, to the first semiconductor wafer **120**

forming the base **2**. This bonding is performed, for example, under a vacuum atmosphere. The bonding portions **36** and **37** are bonding portions formed of the metal film **132** made of gold or the like illustrated in FIG. **6**. A force applied by a load when bonding the second semiconductor wafer **130** to the first semiconductor wafer **120** is, for example, 10 ton or more, and is, for example, about 20 ton.

(49) Next, as illustrated in FIG. **8**, after grinding, a dicing saw or the like is used to perform dicing to separate the vibrator device **1**. Thus, a large number of vibrator devices **1** can be separated from the first semiconductor wafer **120** and the second semiconductor wafer **130**. A length of a long side of the vibrator device **1** in a plan view is about 1.0 mm to 1.2 mm as an example, and a length of a short side is about 0.8 mm to 1.0 mm as an example. A width of a dicing blade is, for example, about 20 μm , and a width of the bonding portions **36** and **37** of the vibrator device **1** is, for example, about 30 μm to 100 μm , and is, for example, about 60 μm .

(50) 2. Vibrator Device of WLP Type

(51) In a vibrator device in the related art, an IC chip and a quartz crystal vibration element are built in a ceramic package. In contrast, in the vibrator device **1** of a WLP type illustrated in FIGS. **1** to **8**, since the IC itself is packaged, an area of the integrated circuit **10** that is the IC can be maximized, and a small-sized and highly functional oscillator or the like can be implemented. For example, in the vibrator device of a ceramic package type, an area of the IC in a plan view is, for example, 50% to 60% or less of an area of the package of the vibrator device. In contrast, according to the vibrator device **1** of a WLP type, the area of the integrated circuit **10** can be made larger than, for example, 50% to 60% of an area of the base **2**. Accordingly, it is possible to provide the integrated circuit **10** with a circuit for making the vibrator device **1** more highly functional.

(52) However, in the vibrator device **1** of a WLP type, as illustrated in FIG. **7**, when the first semiconductor wafer **120** forming the base **2** and the second semiconductor wafer **130** forming the lid **3** are bonded to each other by a load, a large stress is generated in the bonding portions **36** and **37**, and this stress is also applied to the integrated circuit **10**. In this case, circuit characteristics of the integrated circuit **10** may change due to a residual stress or the like.

(53) For example, in the vibrator device disclosed in JP-A-2021-57755, a side wall is formed perpendicularly to a main surface of a semiconductor substrate at an angle of 90°. Accordingly, the accommodation space for the vibration element can be made wider and a size of the vibration element can be maximized, contributing to improvement of vibration characteristics of the vibration element. However, since a load in a vertical direction generated when a first semiconductor wafer forming the base and a second semiconductor wafer forming the lid are bonded to each other is vertically transmitted to a bonding portion, a large stress is easily generated in the vicinity of the bonding portion of the lid and the base. In order to achieve both size reduction and high functionality of the vibrator device, it is required to arrange the circuit elements of the integrated circuit in a wide range with a high degree of integration. Therefore, it is desirable to arrange circuit elements also in a region overlapping the bonding portion of the lid and the base in a plan view. However, when the circuit elements are arranged in the region overlapping the bonding portion, circuit characteristics of the circuit elements and a circuit including the circuit elements may deteriorate due to the stress caused by the load at the time of bonding, and thus there may be a restriction on a region where the circuit elements can be arranged.

(54) Therefore, in the embodiment, as illustrated in FIG. **9** and FIG. **1**, inner side surfaces **38** and **39** of the side walls **32** and **33** of the lid **3** are inclined with respect to the first surface **21** of the semiconductor substrate **20** of the base **2**. That is, the inner side surfaces **38** and **39** of the side walls **32** and **33** are not formed to be perpendicular to the first surface **21**, but are formed to be inclined with respect to the first surface **21**. As described, by inclining the inner side surface **38** and **39** of the side walls **32** and **33** of the lid **3**, rigidity of the lid **3** can be enhanced, and a stress caused by a load when pressed in the vertical direction can be reduced. That is, since the inner side surfaces **38** and **39** of the side walls **32** and **33** of the lid **3** are inclined, a load generation direction and a stress

generation direction when the lid **3** is pressed in the vertical direction are inclined, and the stress is dispersed in regions including an inner region of the bonding portions **36** and **37**. Accordingly, a maximum value of the stress generated in the vicinity of the bonding portions **36** and **37** can be reduced, and a stress generated in an active surface of the integrated circuit **10** can be reduced. Since a large stress is less likely to be applied to the integrated circuit **10**, a characteristics variation of the circuit element can be reduced, and the vibrator device **1** characteristic in high accuracy can be implemented. In addition, it is possible to reduce a region where the stress is large in the integrated circuit **10**, and it is possible to enlarge an area of the integrated circuit **10** allowing mounting of the circuit elements. Accordingly, the small-sized and highly functional vibrator device **1** can be implemented.

(55) FIG. **10** is an explanatory diagram explaining arrangement of circuit elements and circuits in an integrated circuit. As illustrated in FIG. **10**, the base **2** has a first side SD**1**, a second side SD**2** that is an opposite side of the first side SD**1**, a third side SD**3**, and a fourth side SD**4** that is an opposite side of the third side SD**3** in a plan view viewed in a direction orthogonal to the first surface **21**. The base **2** has, for example, a rectangular shape in the plan view. In addition to an oblong shape, the rectangular shape also includes a square shape and a shape similar to a rectangular shape or a square shape. Examples of the shapes similar to a rectangular shape or a square shape include a quadrangle having an interior angle deviated from 90° and a quadrangle having chamfered or rounded corners. A direction from the first side SD**1** toward the second side SD**2** is defined as the first direction DR**1**, and a direction from the third side SD**3** toward the fourth side SD**4** is defined as the second direction DR**2**. The first direction DR**1** is, for example, the X-axis direction, and the second direction DR**2** is, for example, the Y-axis direction. A plan view direction that is a direction orthogonal to the first surface **21** is a direction orthogonal to the first direction DR**1** and the second direction DR**2**, and is, for example, the Z-axis direction.

(56) The integrated circuit **10** includes a first circuit and a second circuit. Each of the first circuit and the second circuit is a circuit including at least one of an active element and a passive element, and is, for example, a circuit block or a macro block including a plurality of circuit elements in order to implement a specific function. Here, the first circuit includes, for example, a first circuit element, and the second circuit includes, for example, a second circuit element. As illustrated in FIG. **10**, among a first region ARA and a second region ARB of the first surface **21** of the base **2**, the first circuit element of the first circuit of the integrated circuit **10** is disposed in the first region ARA. The first surface **21** of the base **2** is also the first surface of the semiconductor substrate **20**. Specifically, the first region ARA is a region overlapping the bonding portions **36** and **37** in the plan view orthogonal to the first surface **21**. On the other hand, the second region ARB is a region on an inner side of the first region ARA. For example, the second region ARB is a region including a center point CP of the base **2**, and the first region ARA is a region surrounding the second region ARB in the plan view orthogonal to the first surface **21**. For example, a region on the inner side of the first region ARA excluding the second region ARB is the first region ARA. The first circuit element of the first circuit of the integrated circuit **10** is disposed in the first region ARA, and the second circuit element of the second circuit of the integrated circuit **10** is disposed in the second region ARB on the inner side of the first region ARA. The first region ARA and the second region ARB are regions defined to set an arrangement region of the circuit element according to stress distribution, and it does not mean that such regions actually exist in the integrated circuit **10**. The arrangement region of the integrated circuit **10** in the embodiment is, for example, a region on an inner side of a guard ring, and does not include a scribe region on an outer side of the guard ring.

(57) As described, the first region ARA is a region overlapping the bonding portions **36** and **37** in a plan view, for example. The plan view is a plan view in the direction orthogonal to the first direction DR**1** and the second direction DR**2**, and is a plan view in the third direction DR**3**. A region between a dotted line indicated by E**1** in FIG. **10** and ends of the base **2** corresponds to a region of the bonding portions **36** and **37** in the plan view. The first region ARA overlaps the

bonding portions **36** and **37** in a region AOV in the plan view. In this way, for example, the first circuit element in the first region ARA can be disposed also in a region corresponding to the bonding portions **36** and **37** in the plan view. Accordingly, the first circuit element can be disposed by effectively utilizing the region corresponding to the bonding portions **36** and **37**, and an arrangement area of the integrated circuit **10** can be enlarged.

(58) Here, as illustrated in FIG. **11**, as long as the first circuit element of the first circuit is disposed in the first region ARA, for example, another portion of the first circuit may be disposed in the second region ARB. That is, it is sufficient that at least the first circuit element of the first circuit is disposed in the first region ARA. As illustrated in FIG. **12**, as long as the second circuit element of the second circuit is disposed in the second region ARB, for example, another portion of the second circuit may be disposed in the first region ARA. That is, it is sufficient that at least the second circuit element of the second circuit is disposed in the second region ARB.

(59) The first circuit element disposed in the first region ARA is a passive element or a transistor. The passive element is, for example, a capacitive element, a resistive element, or an inductor element, and the transistor is, for example, a CMOS transistor or a bipolar transistor. In the embodiment, as illustrated in FIG. **9**, a relationship of $\theta < 90^\circ$ is satisfied, θ being an angle formed by the first surface **21** of the base **2**, which is the first surface of the semiconductor substrate **20**, and the inner side surface **38** of the side wall **32** of the lid **3**.

(60) An angle formed by the first surface **21** and the inner side surface **39** of the side wall **33** of the lid **3** also satisfies the relationship of $\theta < 90^\circ$. In the following description, for simplification, the side wall **32** and the inner side surface **38** of the lid **3** will be mainly described as an example, and a detailed description regarding the side wall **33** and inner side surface **39** will be omitted. For example, in the following description, the side wall **32** is described as a representative of the side wall **32** and the side wall **33**, and the inner side surface **38** is described as a representative of the inner side surface **38** and the inner side surface **39**.

(61) For example, in FIG. **9**, a bonding boundary of the bonding portion **36** is defined as BL. The bonding boundary BL is an inner boundary of the bonding portion **36** and is a boundary along the direction orthogonal to the first surface **21**. That is, the bonding boundary BL is a boundary along the third direction DR3 orthogonal to the first direction DR1 and the second direction DR2, for example, a boundary along the Z-axis direction. The inner side of the bonding portion **36** indicates a direction from the bonding portion **36** toward a central portion of the base **2**. In this case, an inclination angle α of the side wall **32** corresponds to an angle formed by a direction along the inner side surface **38** of the side wall **32** and the bonding boundary BL. The angle θ formed by the first surface **21** and the inner side surface **38** of the side wall **32** can be expressed as $\theta = 90^\circ - \alpha$. For example, $\theta < 90^\circ$ corresponds to the inclination angle $\alpha > 0$, and means that the inner side surface **38** of the side wall **32** is inclined in a positive direction from the direction orthogonal to the first surface **21**. For example, when the inner side surface **38** is inclined in an inward direction that is a direction from the bonding boundary BL toward the central portion of the base **2**, the inclination of the inner side surface **38** is an inclination in a positive direction, and the inclination angle α has a positive value. When the inner side surface **38** is inclined in the outward direction of the base **2** from the bonding boundary BL, the inclination of the inner side surface **38** is an inclination in the negative direction, and the inclination angle α has a negative value. The inclination in the positive direction presents, for example, a forward taper that is a taper in a forward direction, and the inclination in the negative direction presents, for example, a reverse taper that is a taper in a reverse direction.

(62) As described above, in the embodiment, the inner side surface **38** of the side wall **32** of the lid **3** is inclined such that $\theta < 90^\circ$. As described, by inclining the inner side surface **38** of the side wall **32**, a stress caused by a load when bonding the first semiconductor wafer **120** and the second semiconductor wafer **130** illustrated in FIG. **7** can be dispersed in an entire region including an inner region of the bonding portion **36**. Accordingly, it is possible to reduce a stress in a region

where the stress has a maximum value. For example, by dispersing the stress caused by the load in an inward direction or the like from the bonding boundary BL of the bonding portion **36**, a stress in a region in the vicinity of the bonding portion **36** where the stress has the maximum value is reduced.

(63) As illustrated in FIG. **10**, the first region ARA in which the first circuit element is disposed is a region overlapping the bonding portion **36** in the plan view, and is a region in the vicinity of the bonding portion **36**. Therefore, in the first region ARA, there is a region in which the stress is larger than in the other regions and has the maximum value. Accordingly, by inclining the inner side surface **38** of the side wall **32** of the lid **3** such that $\theta < 90^\circ$, a stress generated in the first region ARA can be dispersed to a region on the inner side of the bonding portion **36**, and thus a stress applied to the first circuit element disposed in the first region ARA can be reduced. In this way, it is possible to prevent deterioration of a circuit characteristic of the first circuit element or deterioration of a circuit characteristic of the first circuit including the first circuit element due to the stress caused by the load when bonding the semiconductor wafers. Accordingly, it is possible to implement the small-sized and highly functional vibrator device **1**, and it is possible to effectively prevent the deterioration of the characteristics of the vibrator device **1** caused by the stress.

(64) Next, a relationship between the inclination angle α and the angle θ of the inner side surface **38** of the side wall **32** and the stress will be described in detail. FIG. **13** is a graph illustrating a relationship between the inclination angle α and the angle θ and a stress at a position M20 in FIG. **9**. The stress represented by a vertical axis indicates a normalized stress value. The position M20 is a position on an outer side of the bonding boundary BL by a distance of 20 μm . For example, when the first region ARA in FIG. **10** is expanded and a boundary of the first region ARA on an outer side is brought close to the ends of the base **2**, the position M20 is located in the first region ARA. In FIG. **9**, “+” is assigned to a distance from the bonding boundary BL to an inner position, and “-” is assigned to a distance from the bonding boundary BL to an outer position.

(65) As illustrated in FIG. **13**, in the embodiment, the inner side surface **38** of the side wall **32** is inclined and the inclination angle thereof satisfies $\alpha > 0^\circ$. That is, by setting the angle $\theta = 90^\circ - \alpha$, which is formed by the inner side surface **38** and the first surface **21**, to $\theta < 90^\circ$, the stress at the position M20 in the vicinity of the bonding portion **36** is reduced. For example, in ranges RN1, RN2 and RN3 in FIG. **13** where the angle $\theta < 90^\circ$, the stress at the position M20 is reduced as compared to a case where $\theta = 90^\circ$. Accordingly, it is possible to effectively prevent the deterioration, caused by the stress, in the circuit characteristic of the first circuit element or the first circuit including the first circuit element disposed in the first region ARA that is a region in the vicinity of the bonding portion **36**.

(66) That is, in a case where the side wall **32** is formed to be perpendicular to the first surface **21** at an angle of $\theta = 90^\circ$, when a load pressing the lid **3** in the vertical direction is applied as illustrated in FIG. **7**, a stress caused by the load in the vertical direction is not dispersed, and thus a stress at the position M20 in the region in the vicinity of the bonding portion **36** is large. In contrast, by setting $\theta < 90^\circ$ to incline the inner side surface **38** of the side wall **32**, the stress caused by the load in the vertical direction is dispersed. Accordingly, a maximum value of the stress at the position M20 in the region in the vicinity of the bonding portion **36** can be reduced, and the stress applied to the first circuit element in the first region ARA can be reduced.

(67) FIG. **14** illustrates a relationship between the inclination angle α and the angle θ and a stress at a position P30, a position P110, and a position P180 in FIG. **9**. The position P30, the position P110, and the position P180 are located on the inner side of the bonding boundary BL by distances of 30 μm , 110 μm , and 180 μm , respectively. The stress represented by a vertical axis in FIG. **14** is normalized so that a value of a stress at a position where the stress is maximum is 1.0.

(68) As illustrated in FIG. **14**, at the position P30, the position P110 and the position P180 on the inner side of the bonding boundary BL, when the inclination is provided such that $\theta < 90^\circ$, the stress increases. That is, when $\theta < 90^\circ$, the stress caused by the load in the vertical direction is dispersed,

and thus the stresses at the position P30, the position P110 and the position P180 on the inner side of the bonding portion 36 increase. In this case, an increase amount of the stress when $\theta < 90^\circ$ increases as the position is farther away from the bonding boundary BL. By setting $\theta < 90^\circ$ in this way, when the stress caused by the load in the vertical direction is dispersed and the stresses at the position P30, the position P110 and the position P180 on the inner side of the bonding boundary BL increase, the stress at the position M20 on the outer side of the bonding boundary BL decreases by an amount corresponding to the increase in the stress. For example, the position M20 is a position where the stress has the maximum value with respect to the other positions P30, P110 and P180, and the stress at the position M20 decreases when $\theta < 90^\circ$. Accordingly, the stress applied to the first circuit element disposed in the first region ARA is reduced.

(69) As described above, in the embodiment, in the vibrator device 1 including the base 2 having the integrated circuit 10 disposed at the first surface 21, the vibration element 5 coupled to the integrated circuit 10, and the lid 3 bonded to the base 2, the first circuit element of the first circuit of the integrated circuit 10 is disposed in the first region ARA overlapping the bonding portion 36 in the plan view as illustrated in FIG. 10. The inner side surface 38 of the side wall 32 of the lid 3 is inclined such that $\theta < 90^\circ$, θ being the angle formed by the first surface 21 of the base 2 and the inner side surface 38 of the side wall 32.

(70) By inclining the inner side surface 38 of the side wall 32, a load generation direction and a stress generation direction when the lid 3 is pressed in the vertical direction can be inclined. Accordingly, the maximum value of the stress generated in the region in the vicinity of the bonding portion 36 can be reduced, a maximum value of the stress generated in the active surface of the integrated circuit 10 can be reduced, and the vibrator device 1 with high accuracy and a small characteristics variation can be implemented. In addition, a region where a stress in the integrated circuit 10 is large can be reduced, and the area of the integrated circuit 10 allowing mounting of the circuit elements can be increased. Accordingly, the small-sized and highly functional vibrator device 1 can be implemented. Further, by enhancing resistance to the load at the time of bonding, it is possible to improve strength against a load for holding a product of the vibrator device 1 when mounting the product. Therefore, it is possible to provide the vibrator device 1 that is small-sized, highly functional and durable.

(71) In the embodiment, a relational expression of $\theta < 80^\circ$ may be satisfied, θ being the angle formed by the first surface 21 and the inner side surface 38. In this way, the stress at the position M20 in the vicinity of the bonding portion 36 is a stress in the ranges RN2 and RN3 in FIG. 13, and a stress value thereof can be further reduced compared to that of a stress in the range RN1. Accordingly, the stress applied to the first circuit element disposed in the first region ARA in the vicinity of the bonding portion 36 can be further reduced, and the deterioration in circuit characteristics of the first circuit element and the first circuit caused by stress application can be further prevented.

(72) In the embodiment, a relational expression of $\theta > 45^\circ$ may be preferably satisfied, θ being the angle formed by the first surface 21 and the inner side surface 38. In this way, it is possible to prevent a situation where a restriction is posed on an arrangement space of the vibration element 5 since the angle θ is made unnecessarily small. For example, when the angle θ is set to $\theta < 45^\circ$ and the inner side surface 38 of the side wall portion 32 is further inclined, a space on the left side of the accommodation space SP in FIG. 1 is reduced, and the arrangement space of the vibration element 5 is reduced. That is, when $\theta < 45^\circ$, a situation in which the inner side surface 38 of the side wall 32 comes into contact with the vibration element 5 occurs, and thus it is essential to reduce a size of the vibration element 5, leading to deterioration in vibration characteristics of the vibration element 5 and the like. In this regard, when a relationship of $90^\circ > \theta > 45^\circ$ is satisfied, it is possible to prevent the deterioration in the vibration characteristics of the vibration element 5 and the like due to the reduction in the arrangement space while preventing the deterioration in circuit characteristics of the first circuit element and the first circuit by reducing the maximum value of the

stress that is a stress in the region in the vicinity of the bonding portion **36**.

(73) In the embodiment, in the lid **3**, the inner side surface **38** of the side wall **32** may be along a crystal orientation $\langle 111 \rangle$ of single crystal silicon. Specifically, in FIGS. **13** and **14**, $\alpha=35.3^\circ$ and $\theta=54.7^\circ$ may be satisfied. In this way, the maximum value of the stress, which is the stress at the position **M20** in the vicinity of the bonding portion **36**, can be sufficiently reduced, and the inclination of the inner side surface **38** of the side wall **32** can be formed by effectively utilizing wet etching. For example, a cavity that is the recess **30** in FIGS. **1** and **9** can be formed by wet etching the second semiconductor wafer **130** made of single crystal silicon in FIG. **6**. For example, the single crystal silicon has a property that a $\langle 111 \rangle$ surface is lower in wet etching rate than a $\langle 100 \rangle$ surface and the like and is less likely to be etched. Accordingly, by performing wet etching on the second semiconductor wafer **130** made of single crystal silicon by crystal anisotropic etching using this property, the $\langle 111 \rangle$ surface for which the wet etching rate is low appears as the inner side surface **38** of the side wall **32**. Accordingly, the inner side surface **38** of the side wall **32** along the crystal orientation $\langle 111 \rangle$ can be easily formed. Since the inner side surface **38** of the side wall **32** is along the crystal orientation $\langle 111 \rangle$, the side wall **32** can be formed to have such an inclination that the inclination angle $\alpha=35.3^\circ$ and the angle $\theta=54.7^\circ$ that is formed by the first surface **21** and the inner side surface **38**. Accordingly, the stress at the position **M20** in the vicinity of the bonding portion **36** is reduced as illustrated in FIGS. **13** and **14**, and the deterioration in the circuit characteristics of the first circuit element and the first circuit can be prevented.

(74) Although the inclination of the inner side surface **38** of the side wall **32** is preferably formed by wet etching, the embodiment is not limited thereto, and various modifications can be made, such as forming the inclination by dry etching or forming the inclination by a combination of wet etching and dry etching.

(75) For example, in dry etching, an etching gas, which is a reactive gas, is converted into a plasma, and with a high-frequency power supply or the like, active species of the plasma are brought into contact with and react with a semiconductor substrate such as a silicon substrate on which a mask of a resist is formed, thereby etching a front surface of the semiconductor substrate. As a plasma source, a capacitively coupled plasma (CCP), an electron cyclotron resonance plasma (ECR), an inductively coupled plasma (ICP), or the like can be used.

(76) For example, in reactive ion etching (RIE) that is dry etching, in addition to positive ions and electrons, neutral active species called radicals exist in a plasma generated in a processing chamber. For example, the positive ions are accelerated by a voltage of a high-frequency power supply or the like and collide with the semiconductor substrate, so that the etching in an acceleration direction is performed on the semiconductor substrate. Accordingly, etching is performed on a bottom surface of the recess **30** of the lid **3**. On the other hand, the neutral active species react with the semiconductor substrate, the resist of the mask, and the like to generate a reaction product. When the reaction product adheres to the side wall of the etched portion, the adhered reaction product serves as a mask, and for example, a forward taper can be formed at the side wall. Accordingly, a positive inclination can be formed at the inner side surface **39** of the lid **3**.

(77) Specifically, when dry etching is used, the angle θ can be controlled by controlling a substrate temperature of the silicon substrate of the lid **3** and a pressure in the processing chamber. For example, when the substrate temperature during reactive ion etching, which is dry etching, is increased, the angle θ approaches 90° . Also, when the pressure is decreased, the angle θ approaches 90° . On the other hand, when the substrate temperature is lowered, the angle θ is smaller than 90° . Also, when the pressure is increased, the angle θ is smaller than 90° . This is because an adsorption amount of the reaction product at the inner side surface **38** of the side wall **32** where the number of ion impacts is small increases due to a decrease in the substrate temperature or an increase in the pressure, and a thick polymerized film serving as a mask is formed at the inner side surface **38**. As described, by controlling the substrate temperature and the pressure in the reactive ion etching, it is possible to control the angle θ to incline the inner side surface **38** of the side wall **32** at a desired

angle. By changing a composition ratio of the reactive gas in the reactive ion etching, the angle θ may be controlled to incline the inner side surface **38** of the side wall **32** at a desired angle.

(78) In the embodiment, as described with reference to FIG. 7 and the like, the lid **3** is formed of the second semiconductor wafer **130** that is bonded, by stress application, via the bonding portions **36** and **37** to the first semiconductor wafer **120** forming the base **2**. In this way, the first semiconductor wafer **120** and the second semiconductor wafer **130** are bonded to each other and dicing or the like is performed, whereby a large number of vibrator devices **1** can be separated. Even when a stress is applied due to bonding of the first semiconductor wafer **120** and the second semiconductor wafer **130**, since the angle formed by the first surface **21** and the inner side surface **38** satisfies the relationship of $\theta < 90^\circ$ according to the embodiment, the deterioration in the circuit characteristics of the first circuit element and the first circuit caused by stress application in the first region ARA can be prevented.

(79) 3. Arrangement of Circuit Element

(80) Next, a detailed arrangement method of circuit elements in the integrated circuit **10** according to the embodiment will be described. FIG. 15 and FIGS. 16 and 17 are a diagram and graphs for explaining the stress at each position of the base **2**.

(81) For example, in FIG. 15, a distance in the first direction DR1 from the center point CP of the base **2** to the first side SD1 and the second side SD2 is defined as WX, and a distance in the second direction DR2 from the center point CP of the base **2** to the third side SD3 and the fourth side SD4 is defined as WY. A length of the base **2** in the first direction DR1 is $2 \times WX$, and is, for example, about 1.0 mm to 1.2 mm or may be smaller or larger. The length $2 \times WX$ of the base **2** in the first direction DR1 is, for example, a length of the base **2** in a lateral direction, and is, for example, a length in a long side direction. A length of the base **2** in the second direction DR2 is $2 \times WY$, and is, for example, about 0.8 mm to 1.0 mm or may be smaller or larger. The length $2 \times WY$ of the base **2** in the second direction DR2 is, for example, a length of the base **2** in a longitudinal direction, and is, for example, a length in a short side direction.

(82) FIGS. 16 and 17 are graphs illustrating stress ratios at respective positions of the base **2**. FIG. 16 is a graph illustrating stress ratios at respective positions in the first direction DR1 that is the long side direction of the base **2**, and FIG. 17 is a graph illustrating stress ratios at respective positions in the second direction DR2 that is the short side direction of the base **2**. The stress ratio is a ratio of the stress at each position to a stress at a position where the stress is maximum, and is set so that the stress ratio at the position where the stress is maximum is 1.0. The position where the stress is maximum is, for example, a position of the end of the base **2**.

(83) In FIG. 15, a distance between a point PSX1 and the center point CP in the first direction DR1 is defined as LX. A distance between a point PSX2 and the center point CP in the first direction DR1 is also LX. A distance between a point PSY1 and the center point CP in the second direction DR2 is defined as LY. A distance between a point PSY2 and the center point CP in the second direction DR2 is also LY.

(84) In this case, in FIG. 16, a vertical axis represents the stress ratio, and a horizontal axis represents LX/WX. That is, the horizontal axis in FIG. 16 represents a distance ratio of the distance LX from the center point CP to the points PSX1 and PSX2 with respect to the WX of the base **2** in the first direction DR1. In FIG. 17, a vertical axis represents the stress ratio, and a horizontal axis represents LY/WY. That is, the horizontal axis in FIG. 17 represents a distance ratio of the distance LY from the center point CP to the points PSY1 and PSY2 with respect to the WY of the base **2** in the second direction DR2.

(85) In addition, in FIGS. 16 and 17, in a range RG1 that is a first range, the stress ratio can be set to, for example, about 0.4 or less, and the stress ratio can be made smaller than that at the end of the base **2**. The range RG1 is a range in which LX/WX and LY/WY are, for example, about 0.8 to 0.95.

(86) In a range RG2 that is a second range, the stress ratio can be made smaller than the stress ratio

in the range RG1, and can be set to, for example, about 0.1 or less. For example, in the range RG2, a change amount of the stress ratio in the range is smaller than that in the range RG1.

(87) In a range RG3 that is a third range, the stress ratio can be made smaller than the stress ratio in the range RG2, and can be set to, for example, about 0.05 or less. For example, in the range RG3, a change amount of the stress ratio in the range is smaller than that in the range RG2. Hereinafter, for simplification, the stress ratio is also referred to as the stress as appropriate.

(88) As described above, regarding the stresses at the respective positions of the base 2, there are a plurality of ranges RG1, RG2, and RG3 having different tendencies and characteristics of the stress in value, change amount and the like of the stress. On the other hand, the circuit or the circuit element provided in the integrated circuit 10 includes a circuit or a circuit element having a large change in circuit characteristic with respect to the stress and a circuit or a circuit element having a small change in circuit characteristic with respect to the stress. Therefore, in the embodiment, a method of arranging circuits or circuit elements having different changes in circuit characteristic with respect to the stress is adopted in consideration of the plurality of ranges having different tendencies and characteristics of the stress.

(89) For example, in a region corresponding to a range in which the stress is large, a circuit or a circuit element having a small change in circuit characteristic with respect to the stress is disposed. In this way, even when a stress generated due to a cause or the like illustrated in FIG. 7 is applied to the circuit or the circuit element, since a change in circuit characteristic of the circuit or the circuit element is small, it is possible to prevent bad influence exerted by deterioration in the circuit characteristic caused by the stress. Since the circuit or the circuit element can be arranged in a region close to the end of the base 2, the arrangement area of the integrated circuit 10 in the vibrator device 1 can be enlarged. Accordingly, various circuit functions can be incorporated even in the vibrator device 1 of a WLP Type having a small size.

(90) On the other hand, in a region corresponding to a range in which the stress is small, a circuit or a circuit element having a large change in circuit characteristic with respect to the stress is disposed. In this way, since a large stress is not applied to the circuit or the circuit element having a large change in circuit characteristic with respect to the stress, it is possible to prevent deterioration in the circuit characteristic caused by the stress. As described above, according to the embodiment, it is possible to enlarge the arrangement area of the integrated circuit 10 and to prevent deterioration in the circuit characteristic caused by the stress, and it is possible to implement the small-sized and highly functional vibrator device 1.

(91) Next, the arrangement method of circuit elements according to the embodiment will be specifically described with reference to FIG. 18. For example, the integrated circuit 10 according to the embodiment includes a first circuit and a second circuit. The first circuit includes a first circuit element disposed in the first region ARA, and the second circuit includes a second circuit element disposed in the second region ARB.

(92) The first circuit element or the first circuit is a circuit element or a circuit having a smaller change in circuit characteristic with respect to a stress than the second circuit element or the second circuit. For example, the first circuit element is a circuit element having a smaller change in circuit characteristic with respect to the stress than the second circuit element. Alternatively, the first circuit including the first circuit element is a circuit having a smaller change in circuit characteristic with respect to the stress than the second circuit including the second circuit element. For example, in a case where a change amount of the circuit characteristic of the first circuit element when a first stress is applied to the first circuit element is a first change amount and a change amount of the circuit characteristic of the second circuit element when the first stress is applied to the second circuit element is a second change amount, the first change amount is smaller than the second change amount. In a case where a change amount of the circuit characteristic of the first circuit when the first stress is applied to the first circuit element of the first circuit is a third change amount and a change amount of the circuit characteristic of the second circuit when the first stress

is applied to the second circuit element of the second circuit is a fourth change amount, the third change amount is smaller than the fourth change amount.

(93) The circuit element is a basic element constituting a circuit, and is, for example, a passive element or an active element. The passive element is, for example, a capacitive element, a resistive element, or an inductor element. For example, the passive element is an element that consumes, stores, or discharges supplied power. For example, the passive element is a circuit element that does not perform an active operation such as amplification or rectification of power. The active element is, for example, a transistor or a diode. The active element is a circuit element that performs an active operation such as amplification or rectification of power. For example, the active element is a circuit element having a function of amplifying, controlling, or modulating an input signal or energy and outputting the processed signal or energy. The circuit characteristic of the circuit element is, for example, a resistance, a capacitance, a resistance ratio, a capacitance ratio, an amplification factor, a threshold, a transistor size, a transistor size ratio, a forward voltage, or the like. The circuit characteristic of the circuit is a characteristic of a function implemented by the circuit. For example, in the case of a signal generation circuit, the circuit characteristic is a characteristic such as accuracy, a temperature characteristic, a frequency characteristic, a conversion characteristic, or an amplification characteristic of a generated signal. For example, in the case of a voltage generation circuit, the circuit characteristic is accuracy, a temperature characteristic or the like of a generated voltage, and in the case of a sensor circuit, the circuit characteristic is accuracy, a temperature characteristic, a frequency characteristic or the like of a detected sensor signal. In the case of a signal conversion circuit, the circuit characteristic is a signal conversion characteristic. For example, in the case of an A/D conversion circuit or a D/A conversion circuit, the circuit characteristic is an A/D conversion characteristic or a D/A conversion characteristic. In the case of a signal amplifier circuit, the circuit characteristic is an amplification characteristic or the like of a signal.

(94) In the embodiment, the first circuit element having a smaller change in circuit characteristic with respect to the stress is disposed in the first region ARA, and the second circuit element having a larger change in circuit characteristic with respect to the stress is disposed in the second region ARB. Alternatively, the first circuit element provided in the first circuit having a smaller change in circuit characteristic with respect to the stress is disposed in the first region ARA, and the second circuit element provided in the second circuit having a larger change in circuit characteristic with respect to the stress is disposed in the second region ARB. The change in circuit characteristic with respect to the stress can also be referred to as stress sensitivity, and the first circuit element or the first circuit has lower stress sensitivity than the second circuit element or the second circuit. The first circuit element having lower stress sensitivity or the first circuit element provided in the first circuit having lower stress sensitivity is disposed in the first region ARA, and the second circuit element having higher stress sensitivity or the second circuit element provided in the second circuit having higher stress sensitivity is disposed in the second region ARB.

(95) In FIG. 18, a distance in the first direction DR1 from the center point CP of the base 2 to the first side SD1 and the second side SD2 is defined as WX, and a distance in the second direction DR2 from the center point CP to the third side SD3 and the fourth side SD4 is defined as WY. A distance in the first direction DR1 between the first side SD1 and a corresponding side SA1 of the first region ARA is defined as L1A, and a distance in the first direction DR1 between the second side SD2 and a corresponding side SA2 of the first region ARA is defined as L2A. A distance in the second direction DR2 between the third side SD3 and a corresponding side SA3 of the first region ARA is defined as L3A, and a distance in the second direction DR2 between the fourth side SD4 and a corresponding side SA4 of the first region ARA is defined as L4A.

(96) A distance in the first direction DR1 between the first side SD1 and a corresponding side SB1 of the second region ARB is defined as L1B, and a distance in the first direction DR1 between the second side SD2 and a corresponding side SB2 of the second region ARB is defined as L2B. A

distance in the second direction DR2 between the third side SD3 and a corresponding side SB3 of the second region ARB is defined as L3B, and a distance in the second direction DR2 between the fourth side SD4 and a corresponding side SB4 of the second region ARB is defined as L4B. Here, the corresponding side is, for example, a facing side.

(97) In this case, the following expressions (1) and (2) are established in the embodiment.

$$\begin{array}{ll}
 \{1 - L1A / WX\} \leq 0.95 & \{1 - L1B / WX\} \leq 0.8 \\
 \{1 - L2A / WX\} \leq 0.95 & \{1 - L2B / WX\} \leq 0.8 \\
 \{1 - L3A / WY\} \leq 0.95 & \{1 - L3B / WY\} \leq 0.8 \\
 \{1 - L4A / WY\} \leq 0.95 & \{1 - L4B / WY\} \leq 0.8
 \end{array}
 \quad (1) \qquad (2)$$

(99) Expression (1) corresponds to the range RG1 in FIGS. 16 and 17, and expression (2) corresponds to the ranges RG2 and RG3. That is, when expression (1) is satisfied, a stress applied to the first circuit element in the first region ARA is a stress corresponding to the range RG1. Accordingly, it is possible to ensure that the stress applied to the first circuit element in the first region ARA is, for example, about 40% or less of the maximum stress as in the range RG1 in FIGS. 16 and 17. As described above, the first circuit element disposed in the first region ARA is a circuit element having a smaller change in circuit characteristic with respect to the stress and having lower stress sensitivity. Therefore, when the stress is 40% or less of the maximum stress, since the stress sensitivity of the first circuit element is low, deterioration in the circuit characteristic of the first circuit element or the first circuit including the first circuit element is not a problem. Since the boundary of the first region ARA, which is a circuit arrangement region, can be brought as close as possible to the end of the base 2, the arrangement area of the integrated circuit 10 can be enlarged, and the integrated circuit 10 can be made highly functional.

(100) On the other hand, expression (2) corresponds to the ranges RG2 and RG3 in FIGS. 16 and 17. That is, when expression (2) is satisfied, a stress applied to the second circuit element in the second region ARB is a stress corresponding to the ranges RG2 and RG3. Accordingly, it is possible to ensure that the stress applied to the second circuit element in the second region ARB is, for example, about 10% or less of the maximum stress as in the ranges RG2 and RG3 in FIGS. 16 and 17. In the ranges RG2 and RG3, a change amount in stress in the ranges is smaller than that in the range RG1. The second circuit element disposed in the second region ARB is a circuit element having a larger change in circuit characteristic with respect to the stress and higher stress sensitivity than the first circuit element in the first region ARA. However, if the stress is, for example, 10% or less of the maximum stress, a change in circuit characteristic of the second circuit element or in circuit characteristic of the second circuit including the second circuit element is small, and thus the deterioration in the circuit characteristic caused by the stress can be prevented.

(101) As described above, according to the embodiment, the following relationships are established for the first region ARA in which the first circuit element having a smaller change in circuit characteristic with respect to the stress is disposed.

$$\begin{array}{l}
 \{1 - L1A / WX\} \leq 0.95 \\
 \{1 - L2A / WX\} \leq 0.95 \\
 \{1 - L3A / WY\} \leq 0.95 \\
 \{1 - L4A / WY\} \leq 0.95
 \end{array}
 \quad (102)$$

(103) In this way, the boundary of the first region ARA can be brought close to the end of the base 2, and the arrangement area of the integrated circuit 10 can be enlarged. The following relationships are established for the second region ARB in which the second circuit element having a larger change in circuit characteristic with respect to the stress is disposed.

$$\begin{aligned} & \{1 - L1B / WX\} \leq 0.8 \\ & \{1 - L2B / WX\} \leq 0.8 \\ (104) \quad & \{1 - L3B / WY\} \leq 0.8 \\ & \{1 - L4B / WY\} \leq 0.8 \end{aligned}$$

(105) In this way, it is possible to prevent the deterioration in the circuit characteristic of the second circuit element or the second circuit including the second circuit element caused by the stress. As described above, according to the embodiment, the arrangement region can be divided by the circuit element having low stress sensitivity and the circuit element having high stress sensitivity, and the arrangement region of the integrated circuit **10** can be maximized. Accordingly, compared to a structure in the related art, a larger number of functions can be provided in a region having the same area, and the small-sized and highly functional vibrator device **1** can be implemented.

(106) In the embodiment, the following expression (3) may be established.

$$\begin{aligned} & \{1 - L1B / WX\} \leq 0.6 \\ (107) \quad & \{1 - L2B / WX\} \leq 0.6 \\ & \{1 - L3B / WY\} \leq 0.6 \quad (3) \\ & \{1 - L4B / WY\} \leq 0.6 \end{aligned}$$

(108) Expression (3) corresponds to the range RG3 in FIGS. **16** and **17**. That is, when expression (3) is satisfied, a stress applied to the second circuit element in the second region ARB is a stress corresponding to the range RG3. Accordingly, it is possible to ensure that the stress applied to the second circuit element in the second region ARB is, for example, about 5% or less of the maximum stress as in the range RG3 in FIGS. **16** and **17**. Accordingly, it is possible to further prevent the deterioration in the circuit characteristic of the second circuit element or the second circuit including the second circuit element caused by the stress.

(109) In the embodiment, the following expression (4) may be established.

$$(110) \quad \{1 - L1A / WX\} \leq 0.8 \{1 - L2A / WX\} \leq 0.8 \{1 - L3A / WY\} \leq 0.8 \{1 - L4A / WY\} \leq 0.8 \quad (4)$$

(111) Expression (4) corresponds to the range RG2 in FIGS. **16** and **17**. That is, when expression (4) is satisfied, a stress applied to the first circuit element in the first region ARA is a stress corresponding to the range RG2. Accordingly, it is possible to ensure that the stress applied to the first circuit element in the first region ARA is, for example, about 40% or less of the maximum stress as in the range RG2 in FIGS. **20** and **21**, and it is possible to prevent the deterioration in the circuit characteristic of the first circuit element or the first circuit including the first circuit element caused by the stress.

(112) In the embodiment, the following expression (5) may be established.

$$\begin{aligned} & 0.8 < \{1 - L1A / WX\} \leq 0.95 \\ (113) \quad & 0.8 < \{1 - L2A / WX\} \leq 0.95 \\ & 0.8 < \{1 - L3A / WY\} \leq 0.95 \quad (5) \\ & 0.8 < \{1 - L4A / WY\} \leq 0.95 \end{aligned}$$

(114) For example, $1 - L1A / WX$, $1 - L2A / WX$, $1 - L3A / WY$, and $1 - L4A / WY$ correspond to distance ratios of $WX - L1A$, $WX - L2A$, $WX - L3A$, and $WX - L4A$, which are distances from the center point CP of the base **2** to corresponding sides of the first region ARA, with respect to WX and WY. When expression (5) is established, an upper limit of the distance ratio for the first region ARA is set to 0.95, and a lower limit of the distance ratio is set to 0.8. In this way, the first circuit element can be disposed in the first region ARA where the distance ratios of the distances from the center point CP of the base **2** to the corresponding side of the first region ARA with respect to WX and WY are more than 0.8 and 0.95 or less.

(115) 4. Integrated Circuit

(116) FIG. **19** illustrates a configuration example of the integrated circuit **10** according to the embodiment. The integrated circuit **10** includes an oscillation circuit **11** and an output circuit **12**. The integrated circuit **10** may include a control circuit **13**, a power supply circuit **14**, a temperature compensation circuit **15**, a temperature sensor circuit **16**, and a memory **17**. The vibrator device **1** according to the embodiment includes the vibration element **5** and the integrated circuit **10**, and the vibration element **5** and the integrated circuit **10** are electrically coupled to each other. Configurations of the integrated circuit **10** and the vibrator device **1** are not limited to the configurations in FIG. **19** and configurations in FIG. **20** to be described later, and various modifications can be made such as omitting some of the components, adding other components, and replacing some of the components with other components.

(117) The vibrator device **1** includes terminals TCK, TOE, TVDD, and TGND. The terminal TCK is a terminal for outputting a clock signal CK, and the terminal TOE is a terminal for inputting an output enable signal OE. The TVDD is a terminal to which VDD as a power supply voltage is supplied, and the TGND is a terminal to which GND as a ground voltage is supplied. GND can also be referred to as VSS. For example, VDD corresponds to a high-potential-side power supply voltage, and GND corresponds to a low-potential-side power supply voltage. The terminals TCK, TOE, TVDD, and TGND correspond to the external coupling terminals **91** and **92** in FIG. **1**. For example, in the case of the vibrator device **1** having four terminals, four terminals are provided as the external coupling terminals **91** and **92**. The number of terminals of the vibrator device **1** is not limited to four, and may be four or more or four or less. The integrated circuit **10** includes pads PCK, POE, PVDD, PGND, PX1, and PX2. The pads are terminals of the integrated circuit **10**. The pads PCK, POE, PVDD, and PGND are electrically coupled to the terminals TCK, TOE, TVDD, and TGND of the vibrator device **1**.

(118) The oscillation circuit **11** is a circuit configured to oscillate the vibration element **5**. For example, the oscillation circuit **11** is electrically coupled to the vibration element **5** via the pads PX1 and PX2, and generates an oscillation signal by oscillating the vibration element **5**. For example, the oscillation circuit **11** can be implemented by a drive circuit for oscillation provided between the pad PX1 and the pad PX2 and a passive element such as a capacitor or a resistor. The drive circuit can be implemented by, for example, a CMOS inverter circuit or a bipolar transistor. The drive circuit is a core circuit of the oscillation circuit **11**, and the drive circuit drives the vibration element **5** by a voltage or a current to oscillate the vibration element **5**. As the oscillation circuit **11**, various types of oscillation circuits such as an inverter type, a Pierce type, a Colpitts type, or a Hartley type can be used. The oscillation circuit **11** is provided with, for example, a variable capacitance circuit **86**, and an oscillation frequency can be adjusted by adjusting a capacitance of the variable capacitance circuit **86**. The variable capacitance circuit **86** can be implemented by a variable capacitance element such as a varactor. Alternatively, the variable capacitance circuit **86** may be implemented by a capacitor array and a switch array coupled to the capacitor array. For example, the variable capacitance circuit **86** may be implemented by a capacitor array including a plurality of capacitors whose capacitance values are binarily weighted, and a switch array including a plurality of switches in which each switch turns on and off coupling between a corresponding capacitor of the capacitor array and the pad PX1 or the pad PX2.

(119) The output circuit **12** outputs the clock signal CK based on an oscillation signal. For example, the output circuit **12** buffers an oscillation clock signal based on the oscillation signal and outputs the buffered oscillation clock signal as the clock signal CK to the pad PCK. The clock signal CK is output to the outside via the terminal TCK of the vibrator device **1**. For example, the output circuit **12** outputs the clock signal CK in a single-ended CMOS signal format. For example, when the output enable signal OE received via the pad POE from the terminal TOE is active, the output circuit **12** outputs the clock signal CK under the control of the control circuit **13**. On the other hand, when the output enable signal OE is inactive, the output circuit **12** sets the clock signal

CK to a fixed voltage level such as a low level. The output circuit **12** may output a differential clock signal in a signal format such as low voltage differential signaling (LVDS), positive emitter coupled logic (PECL), high speed current steering logic (HCSL), or differential complementary MOS (CMOS). In this case, two clock terminals or pads for a positive polarity and a negative polarity of the differential clock signal may be provided, and thus the vibrator device **1** is, for example, an oscillator having six terminals.

(120) The control circuit **13** is a logic circuit and performs various types of control processing. For example, the control circuit **13** controls the entire integrated circuit **10** or controls an operation sequence of the integrated circuit **10**. The control circuit **13** may control the oscillation circuit **11**, the power supply circuit **14**, the temperature compensation circuit **15**, the memory **17** and the like. The control circuit **13** can be implemented by a circuit of an application specific integrated circuit (ASIC) based on automatic placement and wiring such as a gate array.

(121) In the power supply circuit **14**, the power supply voltage VDD is supplied via the pad PVDD from the terminal TVDD, and the ground voltage GND is supplied via the pad PGND from the terminal TGND. The power supply circuit **14** supplies power supply voltages for respective internal circuits of the integrated circuit **10** to the respective internal circuits.

(122) The power supply circuit **14** includes a reference voltage generation circuit **80**, and the reference voltage generation circuit **80** generates a reference voltage to be used in the integrated circuit **10**. The reference voltage generation circuit **80** includes a resistance division circuit **82**. The power supply circuit **14** includes a regulator circuit **81**, and the regulator circuit **81** generates a regulated voltage to be used in the integrated circuit **10**. The regulated voltage is supplied to each circuit of the integrated circuit **10** such as the oscillation circuit **11**, the output circuit **12**, and the control circuit **13**. The regulator circuit **81** includes a resistance division circuit **83**. Details of the reference voltage generation circuit **80** and the regulator circuit **81** will be described later.

(123) The temperature compensation circuit **15** performs temperature compensation for an oscillation frequency of the oscillation circuit **11**. The output circuit **12** outputs a clock signal CK based on a temperature-compensated oscillation signal. Specifically, the temperature compensation circuit **15** performs temperature compensation based on a temperature detection signal from the temperature sensor circuit **16**. For example, the temperature compensation circuit **15** generates a temperature compensation voltage based on a temperature detection voltage from the temperature sensor circuit **16**, and outputs the generated temperature compensation voltage to the oscillation circuit **11**, thereby performing temperature compensation for the oscillation frequency of the oscillation circuit **11**. For example, the temperature compensation circuit **15** outputs, to the variable capacitance circuit **86** provided in the oscillation circuit **11**, a temperature compensation voltage that is a capacitance control voltage of the variable capacitance circuit **86**. In this case, the variable capacitance circuit **86** of the oscillation circuit **11** is implemented by a variable capacitance element such as a varactor. The temperature compensation is processing of performing compensation by reducing fluctuation in the oscillation frequency caused by temperature fluctuation. For example, the temperature compensation circuit **15** performs analog temperature compensation using polynomial approximation. For example, when the temperature compensation voltage for compensating frequency-temperature characteristics of the vibration element **5** is approximated using a polynomial, the temperature compensation circuit **15** performs analog temperature compensation based on coefficient information of the polynomial. The analog temperature compensation is temperature compensation implemented by, for example, addition processing of a current signal or a voltage signal that is an analog signal. Specifically, the coefficient information of the polynomial for temperature compensation is stored in the memory **17**, and the control circuit **13** reads the coefficient information from the memory **17** and sets the coefficient information in, for example, a register of the temperature compensation circuit **15**. The temperature compensation circuit **15** performs the analog temperature compensation based on the coefficient information set in the register.

(124) Further, the temperature compensation circuit **15** may perform digital temperature compensation. In this case, the temperature compensation circuit **15** is implemented by, for example, a logic circuit. Specifically, the temperature compensation circuit **15** performs digital temperature compensation processing based on temperature detection data that is a temperature detection signal of the temperature sensor circuit **16**. For example, the temperature compensation circuit **15** obtains frequency adjustment data based on the temperature detection data. A capacitance value of the variable capacitance circuit **86** of the oscillation circuit **11** is adjusted based on the obtained frequency adjustment data, thereby implementing the temperature compensation processing for the oscillation frequency of the oscillation circuit **11**. In this case, the variable capacitance circuit **86** of the oscillation circuit **11** is implemented by a capacitor array including a plurality of binary-weighted capacitors and a switch array. The memory **17** stores a look-up table indicating correspondence between the temperature detection data and the frequency adjustment data, and the temperature compensation circuit **15** uses the look-up table read from the memory **17** by the control circuit **13** to perform temperature compensation processing of obtaining the frequency adjustment data based on the temperature data.

(125) The temperature sensor circuit **16** is a sensor circuit configured to detect a temperature. The temperature sensor circuit **16** includes a current mirror circuit **84**. Specifically, the temperature sensor circuit **16** outputs, as a temperature detection voltage, a temperature-dependent voltage that changes according to an environmental temperature. For example, the temperature sensor circuit **16** generates a temperature detection voltage using a circuit element having temperature dependence. Specifically, the temperature sensor circuit **16** outputs, by using temperature dependence of a forward voltage of a PN junction, the temperature detection voltage whose voltage value changes according to the temperature. As the forward voltage of a PN junction, for example, a voltage between a base and an emitter of a bipolar transistor can be used.

(126) When performing digital temperature compensation processing, the temperature sensor circuit **16** measures a temperature such as an environmental temperature and outputs a result thereof as temperature detection data. The temperature detection data is, for example, data that monotonically increases or monotonically decreases with respect to the temperature. As the temperature sensor circuit **16** in this case, a temperature sensor circuit utilizing a fact that an oscillation frequency of a ring oscillator has temperature dependence can be used. Specifically, the temperature sensor circuit **16** includes a ring oscillator and a counter circuit. The counter circuit counts an output pulse signal, which is an oscillation signal of the ring oscillator, in a count period defined by a clock signal based on an oscillation signal from the oscillation circuit **11**, and outputs a count value as temperature detection data.

(127) The memory **17** stores various types of information used in the integrated circuit **10**. The memory **17** is, for example, a nonvolatile memory. Although the nonvolatile memory is an EEPROM such as a floating gate avalanche injection MOS (FAMOS) memory or a metal-oxide-nitride-oxide-silicon (MONOS) memory, the nonvolatile memory is not limited thereto and may be a one time programmable (OTP) memory or a fuse ROM. Alternatively, the memory **17** may be implemented by a volatile memory such as a RAM.

(128) FIG. **20** illustrates another configuration example of the integrated circuit **10**. In FIG. **20**, a PLL circuit **18** is further provided in addition to the configuration in FIG. **19**. The PLL circuit **18** outputs, to the output circuit **12**, a clock signal obtained by multiplying a frequency of an oscillation clock signal based on an oscillation signal from the oscillation circuit **11**. Accordingly, a clock signal CK obtained by multiplying the frequency of the oscillation signal of the oscillation circuit **11** is output from the terminal TCK. The PLL circuit **18** includes, for example, a phase comparator circuit, a charge pump circuit, a voltage-controlled oscillation circuit, and a divider circuit (not shown). As the PLL circuit **18**, for example, a fractional-N type PLL circuit can be used. For example, a delta-sigma modulation circuit is provided in the control circuit **13**, and the delta-sigma modulation circuit performs delta-sigma modulation, so that the PLL circuit **18**

operates as a fractional-N type PLL circuit. In this way, not only an integer but also a fraction can be set as a division ratio of the PLL circuit **18**, and the clock signal CK of any frequency can be output. In this case, the temperature compensation circuit **15** may perform analog temperature compensation, and implement the temperature compensation by outputting a temperature compensation voltage to the variable capacitance circuit **86** of the oscillation circuit **11**. Alternatively, the temperature compensation circuit **15** may perform digital temperature compensation, and implement the temperature compensation by setting a division ratio of the PLL circuit **18** by delta-sigma modulation based on temperature compensation data and frequency adjustment data.

(129) 5. First Circuit, Second Circuit, First Circuit Element, and Second Circuit Element

(130) Next, an arrangement method of the first circuit, the second circuit, the first circuit element, and the second circuit element in the embodiment will be described with reference to FIG. **21** and the like. As described with reference to FIG. **18** and the like, the integrated circuit **10** according to the embodiment includes the first circuit and the second circuit, the first circuit includes the first circuit element disposed in the first region ARA, and the second circuit includes the second circuit element disposed in the second region ARB. The first circuit element or the first circuit is a circuit element or a circuit having a smaller change in circuit characteristic with respect to a stress than the second circuit element or the second circuit. Hereinafter, specific examples and arrangement methods of the first circuit, the second circuit, the first circuit element, and the second circuit element will be described.

(131) In the embodiment, the first circuit is, for example, a circuit whose circuit characteristic is set using a ratio of a circuit constant of the first circuit element. The circuit constant is, for example, a resistance, a capacitance, or a transistor size, and the first circuit is a circuit whose circuit characteristic is set using a resistance ratio, a capacitance ratio, or a transistor size ratio. The circuit constant is not limited to a resistance, a capacitance, or a transistor size, and may be, for example, an inductance, a transistor threshold, or an amplification factor. As described above, in the case of the first circuit whose circuit characteristic is set using a ratio of a circuit constant of the first circuit element, even when a stress is applied and, for example, the circuit constant of the first circuit element changes, the circuit characteristic set using the ratio of the circuit constant is unlikely to change. That is, a change amount of the ratio of the circuit constant of the first circuit element due to stress application is sufficiently smaller than a change amount of the circuit constant itself of the first circuit element due to stress application. Therefore, for example, even when a stress is applied as illustrated in FIG. **7**, the circuit characteristic of the first circuit set using the ratio of the circuit constant of the first circuit element is unlikely to change. Therefore, in the case of a first circuit element of such a first circuit, even when the first circuit element is disposed in the first region ARA close to the end of the base **2**, it is possible to sufficiently prevent deterioration in the circuit characteristic caused by stress application. By disposing the first circuit element of the first circuit in the first region ARA, an arrangement region of the integrated circuit **10** can be brought close to the end of the base **2**, and an arrangement area of the integrated circuit **10** can be enlarged.

(132) For example, the first circuit is a circuit in which a plurality of passive elements or a plurality of active elements are provided as the first circuit element, and a circuit characteristic is set using a ratio of a circuit constant of the plurality of passive elements or the plurality of active elements. The passive element is, for example, a resistive element, a capacitive element, or an inductor element, and the ratio of the circuit constant of the plurality of passive elements is, for example, a resistance ratio, a capacitance ratio, or an inductor ratio. The active element is, for example, a transistor or a diode, and the ratio of the circuit constant of the plurality of active elements is, for example, a ratio of a transistor size, a ratio of a threshold, a ratio of a forward voltage, or a ratio of an amplification factor. As described above, in the case of the first circuit whose circuit characteristic is set using a ratio of a circuit constant of the plurality of passive elements or the plurality of active elements, even when a stress is applied and the circuit constant of the passive

elements or the active elements is changed, the circuit characteristic set using the ratio of the circuit constant is unlikely to change. Therefore, in the case of passive elements or active elements of such a first circuit, even when the passive elements or active elements are arranged in the first region ARA close to the end of the base **2**, it is possible to sufficiently prevent deterioration in the circuit characteristic caused by stress application. By arranging the passive elements or the active elements of the first circuit in the first region ARA, the arrangement area of the integrated circuit **10** can be enlarged.

(133) The first circuit element disposed in the first region ARA is a plurality of resistive elements provided in a resistance voltage divider circuit, or a plurality of transistors provided in a current mirror circuit. For example, FIG. **21** is a diagram schematically illustrating the arrangement of the first circuit, the second circuit, the first circuit element, and the second circuit element in the integrated circuit **10**. In FIG. **21**, the resistance division circuits **82** and **83** and the current mirror circuit **84** are arranged in the first region ARA. As described with reference to FIGS. **19** and **20**, for example, the resistance division circuit **82** is provided in the reference voltage generation circuit **80**, and the resistance division circuit **83** is provided in the regulator circuit **81**. The current mirror circuit **84** is provided, for example, in the temperature sensor circuit **16**. The resistance division circuits **82** and **83** are circuits for each of which a circuit characteristic is set using a resistance ratio of a plurality of resistive elements, and for example, the circuit characteristic such as a divided voltage generated by the resistance division circuits **82** and **83** is set using the resistance ratio. The resistance division circuits **82** and **83** are circuits for each of which a circuit characteristic is set using a ratio of a circuit constant of a plurality of passive elements, and are circuits for each of which a circuit characteristic is set using a ratio of a circuit constant of a first circuit element. The current mirror circuit **84** is a circuit whose circuit characteristic is set using a size ratio of a plurality of transistors, and for example, the circuit characteristic such as a mirror ratio of a current mirror is set using a transistor size ratio. The current mirror circuit **84** is a circuit whose circuit characteristic is set using a ratio of a circuit constant of a plurality of active elements, and is a circuit whose circuit characteristic is set using a ratio of a circuit constant of a first circuit element. In the case of the resistance division circuits **82** and **83** and the current mirror circuit **84**, even when a stress is applied and a resistance of the resistive elements or a transistor characteristic changes, the circuit characteristic set using the resistance ratio or the transistor size ratio is unlikely to change. Accordingly, in the case of the plurality of resistive elements of the resistance division circuits **82** and **83** and the plurality of transistors of the current mirror circuit **84**, as illustrated in FIG. **21**, even when being arranged in the first region ARA close to the ends of the base **2**, it is possible to prevent bad influence exerted by deterioration in the circuit characteristic caused by stress application. By arranging the plurality of resistive elements and the plurality of transistors in the first region ARA, the arrangement area of the integrated circuit **10** can be enlarged.

(134) The circuit whose circuit characteristic is set using a ratio of a circuit constant of a circuit element is not limited to the resistance division circuits **82** and **83** and the current mirror circuit **84**, and includes various circuits such as an amplifier circuit for which an amplification factor is set using a capacitance ratio or a resistance ratio or a circuit configured to generate a voltage or a current by using a transistor size ratio.

(135) As described, the first circuit is the reference voltage generation circuit **80** configured to generate a reference voltage to be used in the integrated circuit **10**, and the first circuit element is the resistive elements provided in the resistance division circuit **82** of the reference voltage generation circuit **80**. That is, in FIG. **21**, the resistive elements constituting the resistance division circuit **82** of the reference voltage generation circuit **80** are arranged in the first region ARA. In this way, of the reference voltage generation circuit **80**, at least the resistive elements of the resistance division circuit **82** are arranged in the first region ARA. By arranging the resistive elements of the resistance division circuit **82** of the reference voltage generation circuit **80** in the first region ARA in this manner, the resistive elements of the resistance division circuit **82** can be arranged in a

region close to the end of the base **2**, and thus the arrangement area of the integrated circuit **10** can be enlarged. In addition, since the circuit characteristic of the resistance division circuit **82** is set using the resistance ratio, even when the resistive elements of the resistance division circuit **82** are arranged in the first region ARA where an applied stress is larger, the bad influence exerted by the deterioration in the circuit characteristic caused by the stress is minimized.

(136) The first circuit is the regulator circuit **81** configured to generate a regulated voltage to be used in the integrated circuit **10**, and the first circuit element is the resistive elements provided in the resistance division circuit **83** of the regulator circuit **81**. That is, in FIG. **21**, the resistive elements constituting the resistance division circuit **83** of the regulator circuit **81** are arranged in the first region ARA. In this way, of the regulator circuit **81**, at least the resistive elements of the resistance division circuit **83** are arranged in the first region ARA. By arranging the resistive elements of the resistance division circuit **83** of the regulator circuit **81** in the first region ARA in this manner, the resistive elements of the resistance division circuit **83** can be arranged in a region close to the end of the base **2**, and thus the arrangement area of the integrated circuit **10** can be enlarged. In addition, since the circuit characteristic of the resistance division circuit **83** is set using the resistance ratio, even when the resistive elements of the resistance division circuit **83** are arranged in the first region ARA where the applied stress is larger, the bad influence exerted by the deterioration in the circuit characteristic caused by the stress is minimized.

(137) The first circuit is the temperature sensor circuit **16** configured to detect a temperature, and the first circuit element is the plurality of transistors provided in the current mirror circuit **84** of the temperature sensor circuit **16**. That is, in FIG. **21**, the plurality of transistors constituting the current mirror circuit **84** of the temperature sensor circuit **16** are arranged in the first region ARA. In this way, of the temperature sensor circuit **16**, at least the plurality of transistors of the current mirror circuit **84** are arranged in the first region ARA. By arranging the plurality of transistors of the current mirror circuit **84** of the temperature sensor circuit **16** in the first region ARA in this manner, the plurality of transistors of the current mirror circuit **84** can be arranged in a region close to the end of the base **2**, and thus the arrangement area of the integrated circuit **10** can be enlarged. Further, since the circuit characteristic of the current mirror circuit **84** is set using the size ratio of the plurality of transistors, even when the plurality of transistors of the current mirror circuit **84** are arranged in the first region ARA where the applied stress is larger, the bad influence exerted by the deterioration in the circuit characteristic caused by the stress is minimized.

(138) The first circuit is the control circuit **13** or the memory **17**, and the first circuit element is transistors provided in the control circuit **13** or the memory **17**. In this way, as illustrated in FIG. **21**, at least some of the transistors constituting the control circuit **13** or the memory **17** are arranged in the first region ARA. By arranging the transistors of the control circuit **13** or the memory **17** in the first region ARA in this manner, the transistors of the control circuit **13** or the memory **17** can be arranged in a region close to the end of the base **2**, and thus the arrangement area of the integrated circuit **10** can be enlarged. Even when a stress is applied to the transistors of the control circuit **13** and the memory **17** and a circuit characteristic of the transistors changes, circuit characteristics of the control circuit **13** and the memory **17** are unlikely to be affected. For example, since the control circuit **13** is a circuit configured to perform a logic operation and the like, even when a circuit characteristic such as a threshold of the transistors changes due to stress application, the logic operation is unlikely to be affected, and it is considered that there is no malfunction of the control circuit **13**. In addition, even when a circuit characteristic such as a threshold of transistors in a reading circuit and a writing circuit of the memory **17** changes, a reading operation and a writing operation of the memory are unlikely to be affected, and it is considered that there is no malfunction of the memory **17**.

(139) The second circuit element is a passive element, and the passive element is at least one of a capacitive element and a resistive element. In this way, the capacitive element and the resistive element as the second circuit element are arranged in the second region ARB. For example, when

the stress described with reference to FIG. 7 is applied to the capacitive element and the resistive element, a capacitance and a resistance may change, but the applied stress is smaller in the second region ARB than that in the first region ARA. Accordingly, when the capacitive element and the resistive element are arranged in the second region ARB where the applied stress is smaller, the change in the capacitance and the resistance due to the stress can be minimized, and a change in circuit characteristic of the second circuit including, for example, the capacitive element and the resistive element as the second circuit element can be reduced to the minimum. The capacitive element is, for example, a metal-insulator-metal (MIM) capacitor, a polysilicon-insulator-polysilicon (PIP) capacitor, or a metal-oxide-semiconductor (MOS) capacitor. The resistive element is, for example, a polysilicon resistor, a diffused resistor, or a well resistor.

(140) As illustrated in FIG. 21, the second circuit is the oscillation circuit **11** configured to oscillate the vibration element 5, and the second circuit element is at least one of the capacitive element and the resistive element provided in the oscillation circuit **11**. In this way, the capacitive element and the resistive element of the oscillation circuit **11** as the second circuit element are arranged in the second region ARB. For example, when a stress is applied to the capacitive element and the resistive element, a capacitance and a resistance may change, but the applied stress is smaller in the second region ARB than that in the first region ARA. Accordingly, when the capacitive element or the resistive element of the oscillation circuit **11** is disposed in the second region ARB where the applied stress is smaller, the change in the capacitance or the resistance due to the stress can be minimized, and a change in circuit characteristic of the oscillation circuit **11** including the capacitive element or the resistive element can be reduced to the minimum. For example, in a case where the capacitive element is a capacitive element constituting the variable capacitance circuit **86** of the oscillation circuit **11**, when the capacitance of the capacitive element changes due to stress application, an oscillation frequency also fluctuates. In this regard, when the capacitive element of the variable capacitance circuit **86** of the oscillation circuit **11** is disposed in the second region ARB where the applied stress is smaller, the fluctuation in the oscillation frequency caused by the stress application can be reduced to the minimum.

(141) As illustrated in FIG. 21, the second circuit is the temperature compensation circuit **15** configured to perform temperature compensation for an oscillation frequency of the vibration element 5, and the second circuit element is a resistive element provided in the temperature compensation circuit **15**. In this way, the resistive element of the temperature compensation circuit **15** as the second circuit element is disposed in the second region ARB. When the resistive element of the temperature compensation circuit **15** is disposed in the second region ARB where the applied stress is smaller, a change in resistance due to the stress can be minimized, and a change in circuit characteristic of the temperature compensation circuit **15** can also be reduced to the minimum. For example, in the temperature compensation circuit **15**, when a resistance value of the resistive element changes due to stress application, a temperature compensation characteristic also fluctuates. In this regard, when the resistive element of the temperature compensation circuit **15** is disposed in the second region ARB where the applied stress is smaller, the fluctuation in the temperature compensation characteristic caused by the stress application can be reduced to the minimum.

(142) 6. Configuration Examples of Respective Circuits of Integrated Circuit

(143) Next, specific configuration examples of respective circuits of the integrated circuit **10** will be described. FIG. 22 illustrates a configuration example of the reference voltage generation circuit **80**. The reference voltage generation circuit **80** includes an N-type transistor TD1, resistors RD1, RD2, and RD3, and bipolar transistors BP1 and BP2 that are provided between a VDD node and a GND node. The reference voltage generation circuit **80** includes P-type transistors TD2 and TD3 to whose gates a bias voltage VB is input, and a bipolar transistor BP3 provided between a drain node of the transistor TD2 and the GND node. The reference voltage generation circuit **80** is a bandgap reference circuit, and generates and outputs a reference voltage VREF based on a bandgap voltage.

For example, voltages between bases and emitters of the PNP bipolar transistors BP1 and BP2 are defined as V_{BE1} and V_{BE2} , and $\Delta V_{BE} = V_{BE1} - V_{BE2}$. The reference voltage generation circuit **80** outputs the reference voltage V_{REF} of $V_{REF} = K \times \Delta V_{BE} + V_{BE2}$, for example. K is set based on resistance values of the resistors RD1 and RD2. For example, since V_{BE2} has a negative temperature characteristic and ΔV_{BE} has a positive temperature characteristic, the reference voltage V_{REF} of a constant voltage having no temperature dependence can be generated by adjusting the resistance values of the resistors RD1 and RD2. The generated reference voltage V_{REF} is a constant voltage based on a ground voltage. The reference voltage generation circuit **80** is not limited to the configuration in FIG. 22, and for example, circuits of various configurations such as a circuit configured to generate the reference voltage V_{REF} using a work function difference voltage of a transistor can be used.

(144) In the reference voltage generation circuit **80** in FIG. 22, the resistance division circuit **82** is implemented by the resistors RD1 and RD2 that are resistive elements. The reference voltage $V_{REF} = K \times \Delta V_{BE} + V_{BE2}$ is set using K corresponding to a resistance ratio of RD1 and RD2 in the resistance division circuit **82**. Therefore, even when the resistance values of the resistors RD1 and RD2 as resistive elements fluctuate due to stress application, fluctuation in K corresponding to the resistance ratio is the minimum, and thus fluctuation in the reference voltage V_{REF} is also reduced to the minimum. Therefore, even when the resistance division circuit **82** of the reference voltage generation circuit **80** is disposed in the first region ARA where the applied stress is larger, the fluctuation in the reference voltage V_{REF} that is a circuit characteristic of the reference voltage generation circuit **80** can be prevented. By disposing the reference voltage generation circuit **80** in the first region ARA close to the end of the base 2, the arrangement area of the integrated circuit **10** can be enlarged.

(145) FIG. 23 illustrates a configuration example of the regulator circuit **81**. The regulator circuit **81** includes an N-type driving transistor TA1 and resistors RA1 and RA2 provided in series between a VDD node and a GND node, and an operational amplifier OPA. The regulator circuit **81** may include a resistor RA3 and a capacitor CA provided on an output terminal side of the operational amplifier OPA. The reference voltage V_{REF} is input to a non-inverting input terminal of the operational amplifier OPA, and a voltage VDA obtained by dividing a regulated voltage V_{REG1} by the resistors RA1 and RA2 is input to an inverting input terminal. An output terminal of the operational amplifier OPA is coupled to a gate of the transistor TA1 via the resistor RA3, and the regulated voltage V_{REG1} is output from a drain node of the transistor TA1. When resistance values of the resistors RA1 and RA2 are defined as $R1$ and $R2$, the regulator circuit **81** outputs the regulated voltage $V_{REG1} = \{(R1 + R2)/R2\} \times V_{REF}$.

(146) In the regulator circuit **81** in FIG. 23, the resistance division circuit **83** is implemented by the resistors RA1 and RA2 that are resistive elements. The regulated voltage $V_{REG1} = \{(R1 + R2)/R2\} \times V_{REF}$ is set using a resistance ratio based on RA1 and RA2. Therefore, even when the resistance values of the resistors RA1 and RA2 as resistive elements fluctuate due to stress application, fluctuation in the resistance ratio is the minimum, and thus fluctuation in the regulated voltage V_{REG1} is also reduced to the minimum. Therefore, even when the resistance division circuit **83** of the regulator circuit **81** is disposed in the first region ARA where the applied stress is larger, the fluctuation in the regulated voltage V_{REG1} that is a circuit characteristic of the regulator circuit **81** can be prevented. By disposing the regulator circuit **81** in the first region ARA close to the end of the base 2, the arrangement area of the integrated circuit **10** can be enlarged.

(147) FIG. 24 illustrates a first configuration example of the temperature sensor circuit **16**. The temperature sensor circuit **16** includes a constant current source IS1, a bipolar transistor BPE1, and resistors RE1 and RE2. The constant current source IS1, the resistor RE1, the bipolar transistor BPE1, and the resistor RE2 are provided in series between a VDD node and a GND node. Specifically, a coupling node of the constant current source IS1 and one end of the resistor RE1 is coupled to a base of the bipolar transistor BPE1, and the other end of the resistor RE1 is coupled to

a collector of the bipolar transistor BPE1. An emitter of the bipolar transistor BPE1 is coupled to one end of the resistor RE2, and the other end of the resistor RE2 is coupled to the GND node. The resistor RE2 is a variable resistor, and a resistance value of the resistor RE2 is set based on zero-order correction data from the memory 17.

(148) In FIG. 24, when a current flowing from the constant current source IS1 is defined as IE, the resistance values of the resistors RE1 and RE2 are defined as R1 and R2, respectively, and a voltage between the base and the emitter of the bipolar transistor BPE1 is defined as VBE1, a temperature detection voltage is $V_{TS}=V_{BE1}+IE\times(R2-R1)$. As described, the temperature detection voltage VTS contains $IE\times(R2-R1)$ as an offset component, and the offset of the temperature detection voltage VTS can be adjusted by changing the resistance value R2 of the resistor RE2.

(149) FIG. 25 illustrates a second configuration example of the temperature sensor circuit 16. The temperature sensor circuit 16 in FIG. 25 includes constant current sources IS1 and IS2, bipolar transistors BPE1 and BPE2, resistors RE1, RE2, RE3, and RE4, and a buffer circuit 78.

(150) A coupling configuration of the constant current source IS1, the bipolar transistor BPE1, and the resistors RE1 and RE2 is similar to that of the first configuration example in FIG. 24. The constant current source IS2, the resistor RE3, the bipolar transistor BPE2, and the resistor RE4 are provided in series between a VDD node and a node of a collector of the bipolar transistor BPE1. Specifically, a coupling node of the constant current source IS2 and one end of the resistor RE3 is coupled to a base of the bipolar transistor BPE2, and the other end of the resistor RE3 is coupled to a collector of the bipolar transistor BPE2. An emitter of the bipolar transistor BPE2 is coupled to one end of the resistor RE4, and the other end of the resistor RE4 is coupled to the collector of the bipolar transistor BPE1. The resistor RE4 is a variable resistor, and a resistance value of the resistor RE4 is set based on, for example, zero-order correction data from the memory 17.

(151) The buffer circuit 78 includes an operational amplifier OPE and resistors RE5 and RE6. A voltage VGB, which is a collector voltage of the bipolar transistor BPE2, is input to a non-inverting input terminal of the operational amplifier OPE. An inverting input terminal of the operational amplifier OPE is coupled to one end of the resistor RE5, the other end of the resistor RE5 is coupled to one end of the resistor RE6, and the other end of the resistor RE6 is coupled to a GND node. Accordingly, a voltage obtained by dividing an output voltage of the operational amplifier OPE by the resistors RE5 and RE6 is output as the temperature detection voltage VTS from a coupling node of the resistors RE5 and RE6. The output voltage of the operational amplifier OPE is a voltage obtained by adding an offset voltage of the operational amplifier OPE to the voltage VGB.

(152) In FIG. 25, collector voltages of the bipolar transistors BPE1 and BPE2 are defined as VGA and VGB, respectively, currents flowing through the constant current sources IS1 and IS2 are defined as IE, and resistance values of the resistors RE1, RE2, RE3, RE4, RE5, and RE6 are defined as R1, R2, R3, R4, R5, and R6, respectively. Voltages between bases and emitters of the bipolar transistors BPE1 and BPE2 are defined as VBE1 and VBE2. In that case,

$VGA=VBE1+IE\times(2R2-R1)$, and

$VGB=VBE2+IE\times(R4-R3)+VGA=VBE1+VBE2+IE\times(2R2+R4-R1-R3)$. Accordingly, the temperature detection voltage is $V_{TS}=(R5/R6)\times VGB$. The VGB contains $IE\times(2R2+R4-R1-R3)$ as an offset component, and the temperature detection voltage VTS also contains

$(R5/R6)\times IE\times(2R2+R4-R1-R3)$ as an offset component. That is, the offset of the temperature detection voltage VTS can be adjusted by changing the resistance value R2 of the resistor RE2 and the resistance value R4 of the resistor RE4.

(153) In the temperature sensor circuits 16 in FIGS. 24 and 25, the constant current sources IS1 and IS2 are implemented by the current mirror circuit 84. That is, the current IE obtained by current-mirroring a reference current by the current mirror circuit 84 flows from the constant current sources IS1 and IS2. The current mirror circuit 84 is implemented by a first transistor whose drain and gate are coupled and through which a reference current flows from a source to the drain, and a

second transistor whose gate is coupled to the gate of the first transistor and through which a current IE flows. A mirror ratio of the current mirror circuit **84** is set using a transistor size ratio between the first transistor and the second transistor. Therefore, even when circuit characteristics of the first transistor and the second transistor fluctuate due to stress application, fluctuation in the transistor size ratio is the minimum, and thus fluctuation in the current IE is also reduced to the minimum. Therefore, even when the current mirror circuit **84** of the temperature sensor circuit **16** is disposed in the first region ARA where the applied stress is larger, fluctuation in the temperature detection voltage that is a circuit characteristic of the temperature sensor circuit **16** can be prevented. By disposing the temperature sensor circuit **16** in the first region ARA close to the end of the base **2**, the arrangement area of the integrated circuit **10** can be enlarged.

(154) FIG. **26** illustrates a configuration example of the oscillation circuit **11**. The oscillation circuit **11** includes a drive circuit **94**, DC-cut capacitors C1, C2, C4, a reference voltage supply circuit **95**, a first variable capacitance circuit **96**, and a second variable capacitance circuit **97**. The capacitor C4 and the second variable capacitance circuit **97** may be omitted. Capacitors C31 to C3n are provided between the first variable capacitance circuit **96** and the second variable capacitance circuit **97**, and a GND node.

(155) The drive circuit **94** is a circuit configured to drive and oscillate the vibration element **5**. The drive circuit **94** includes a current source ISA, a bipolar transistor BP0, and a resistor RB. The current source ISA is provided between a power supply node of a regulated voltage VREG and the bipolar transistor BP0, and supplies a constant current to the bipolar transistor BP0.

(156) The bipolar transistor BP0 is a transistor configured to drive the vibration element **5**, and a base node thereof is an input node NI of the drive circuit **94** and a collector node thereof is an output node NQ of the drive circuit **94**. The resistor RB is provided between the collector node and the base node of the bipolar transistor BP0.

(157) The DC-cut capacitor C1 is provided between the input node NI of the drive circuit **94** and a wiring LA. By providing such a capacitor C1, a DC component of an oscillation signal is cut off, and only an AC component is transmitted to the input node NI of the drive circuit **94**, and it is possible to properly operate the bipolar transistor BP0.

(158) The reference voltage supply circuit **95** supplies reference voltages VR1 to VRn to the first variable capacitance circuit **96** and the second variable capacitance circuit **97**. The reference voltage supply circuit **95** includes, for example, a plurality of resistive elements provided in series between a node of the regulated voltage VREG and a node of GND, and outputs voltages obtained by dividing the voltage of VREG as the reference voltages VR1 to VRn. The reference voltage supply circuit **95** supplies a reference voltage VRB for bias voltage setting to the wiring LA. Accordingly, an amplitude center voltage of the oscillation signal in the wiring LA can be set to the reference voltage VRB.

(159) The DC-cut capacitor C2 has one end coupled to the wiring LA and the other end coupled to a supply node NS1 of a temperature compensation voltage VCP. The temperature compensation voltage VCP is supplied to the supply node NS1 via a resistor RC1. The first variable capacitance circuit **96** has one end coupled to the supply node NS1 and is supplied with the temperature compensation voltage VCP. The reference voltage supply circuit **95** supplies the reference voltages VR1 to VRn to supply nodes NR1 to NRn at the other end of the first variable capacitance circuit **96**. The capacitors C31 to C3n are provided between the supply nodes NR1 to NRn of the reference voltages VR1 to VRn and a GND node.

(160) The first variable capacitance circuit **96** includes n variable capacitance elements. Further, n is an integer of 2 or more. The n variable capacitance elements are MOS type variable capacitance elements, for example, and are implemented by n transistors. The reference voltages VR1 to VRn are supplied to gates of the n transistors. A source and a drain of each of the n transistors are short-circuited, and the temperature compensation voltage VCP is supplied to the supply node NS1 to which the short-circuited source and drain are coupled. A capacitance of the DC-cut capacitor C2 is

sufficiently larger than a capacitance of the first variable capacitance circuit **96**. By using the first variable capacitance circuit **96** having such a configuration, linearity of a capacitance change of the total capacitance of the first variable capacitance circuit **96** can be secured in a wide voltage range of the temperature compensation voltage VCP. A coupling configuration of the second variable capacitance circuit **97** and the capacitor C4 is similar to the coupling configuration of the first variable capacitance circuit **96** and the capacitor C2, and thus a detailed description thereof is omitted.

(161) In the embodiment, the capacitive elements of the first variable capacitance circuit **96** and the second variable capacitance circuit **97** of the oscillation circuit **11** and the resistive element of the reference voltage supply circuit **95** are arranged in the second region ARB where the applied stress is smaller. For example, when capacitances of capacitive elements such as varactors of the first variable capacitance circuit **96** and the second variable capacitance circuit **97** fluctuate due to stress application, a load capacitance fluctuates, and thus an oscillation frequency also fluctuates. Further, when a resistance of the resistive element of the reference voltage supply circuit **95** fluctuates due to stress application and the reference voltages VR1 to VRn fluctuate, the voltages applied to the capacitive elements of the first variable capacitance circuit **96** and the second variable capacitance circuit **97** fluctuate. Accordingly, the load capacitance fluctuates, and the oscillation frequency also fluctuates. In this regard, in the embodiment, since the capacitive elements and the resistive elements of the oscillation circuit **11** are arranged in the second region ARB where the applied stress is smaller, it is possible to prevent fluctuation in a circuit characteristic such as fluctuation in the oscillation frequency caused by the stress application.

(162) FIG. 27 illustrates a configuration example of the temperature compensation circuit **15**. FIG. 27 illustrates a circuit configured to perform analog temperature compensation, and output the temperature compensation voltage VCP by polynomial approximation using a temperature as a variable. The temperature compensation circuit **15** includes a current generation circuit **70** and a current-voltage conversion circuit **73**. The current generation circuit **70** generates a function current for temperature compensating a frequency-temperature characteristic of the vibration element 5, based on the temperature detection voltage VTS from the temperature sensor circuit **16**. The current-voltage conversion circuit **73** converts the function current from the current generation circuit **70** into a voltage and outputs the temperature compensation voltage VCP.

(163) The current generation circuit **70** includes a linear correction circuit **71** and a higher-order correction circuit **72**. The linear correction circuit **71** outputs a linear current approximating a linear function based on the temperature detection voltage VTS. For example, the linear correction circuit **71** outputs the linear current based on linear correction data corresponding to a linear coefficient of a polynomial in polynomial approximation. The high-order correction circuit **72** outputs a high-order current approximating a high-order function to the current-voltage conversion circuit **73** based on the temperature detection voltage VTS. For example, the high-order correction circuit **72** outputs a high-order current based on high-order correction data corresponding to a high-order coefficient of a polynomial in polynomial approximation. For example, the high-order correction circuit **72** outputs a cubic current approximating a cubic function. The high-order correction circuit **72** may further include a correction circuit configured to perform quartic or higher-order correction.

(164) The current-voltage conversion circuit **73** includes an amplifier circuit AM, a resistor RC, and a capacitor CC. The current-voltage conversion circuit **73** adds the linear current and the high-order current, and performs current-voltage conversion on the added current to output the temperature compensation voltage VCP. Accordingly, the temperature compensation voltage VCP approximating a polynomial function is generated.

(165) FIG. 28 illustrates a configuration example of a function current generation circuit **74** provided in the temperature compensation circuit **15**. The function current generation circuit **74** is provided, for example, in the high-order correction circuit **72** in FIG. 27, and generates high-order function currents such as quadratic and cubic function currents.

(166) As illustrated in FIG. 28, the function current generation circuit 74 includes a reference current generation circuit 75, a first compensation circuit 76, and a second compensation circuit 77. The reference current generation circuit 75 generates a reference current IR. The first compensation circuit 76 performs temperature compensation in a low-temperature range, and the second compensation circuit 77 performs temperature compensation in a high-temperature range. The first compensation circuit 76 and the second compensation circuit 77 include a plurality of differential pair circuits. Reference currents IRF1 and IRF2 obtained by mirroring the reference current IR flow through the differential pair circuits of the first compensation circuit 76. Reference currents IRG1 and IRG2 obtained by mirroring the reference current IR also flow through the differential pair circuits of the second compensation circuit 77. The first compensation circuit 76 generates a current $IF=IF1+IF2$ for temperature compensation in the low-temperature range, and the second compensation circuit 77 generates a current $IG=IG1+IG2$ for temperature compensation in the high-temperature range. Since the reference current IR is a constant current, the reference current $IRF1=IF1+IL1$ and the reference current $IRF2=IF2+IL2$ flowing through the differential pair circuits of the first compensation circuit 76 are also constant currents having constant current values. The reference current $IRG1=IG1+IH1$ and the reference current $IRG2=IG2+IH2$ flowing through the differential pair circuits of the second compensation circuit 77 are also constant currents having constant current values.

(167) In the low-temperature range, the current $IF=IF1+IF2$ increases, whereas the current $IG=IG1+IG2$ decreases. On the other hand, in the high-temperature range, the current $IG=IG1+IG2$ increases, whereas the current $IF=IF1+IF2$ decreases. By using the function current generation circuit 74, it is possible to generate a high-order function current such as a quadratic, cubic, quartic, or quintic function current.

(168) In the embodiment, in the function current generation circuit 74 of the temperature compensation circuit 15, resistive elements through which the currents IF1, IL1, IF2, IL2, IH1, IG1, IH2, and IG2 flow are arranged in the second region ARB where the applied stress is smaller. For example, when resistance values of the resistive elements fluctuate, the currents IF and IG for temperature compensation also fluctuate, and the temperature compensation voltage VCP also fluctuates. Accordingly, the temperature compensation of an oscillation frequency is not appropriately performed, and the oscillation frequency after the temperature compensation also fluctuates. In this regard, in the embodiment, since the resistive elements of the temperature compensation circuit 15 are arranged in the second region ARB where the applied stress is smaller, it is possible to prevent fluctuation in the circuit characteristic such as fluctuation in the temperature compensation and the fluctuation in the oscillation frequency caused by stress application.

(169) 7. Layout Arrangement of Integrated Circuit

(170) FIGS. 29 and 30 illustrate layout arrangement examples of the integrated circuit 10. FIG. 29 illustrates a layout arrangement example of the integrated circuit 10 having the configuration example in FIG. 19, and FIG. 30 is a layout arrangement example of the integrated circuit 10 having the configuration example in FIG. 20. In FIGS. 29 and 30, E2 indicates an inner boundary of the bonding portions 36 and 37 in the plan view described with reference to FIG. 1. The first region ARA described with reference to FIG. 18 and the like is a region overlapping the bonding portions 36 and 37 in the plan view. In FIGS. 29 and 30, the pads PX1 and PX2 coupled to the oscillation circuit 11 are coupled to the vibration element 5, and accordingly the vibration element 5 and the integrated circuit 10 can be electrically coupled to each other.

(171) In FIG. 29, the oscillation circuit 11 is disposed along the first side SD1 of the base 2. The temperature compensation circuit 15 is disposed in a central portion of the base 2, and the pads PX1 and PX2 for coupling to the vibration element 5 are disposed between the oscillation circuit 11 and the temperature compensation circuit 15. The temperature sensor circuit 16, the memory 17, the control circuit 13, and the reference voltage generation circuit 80 are arranged along the fourth

side SD4 of the base 2. The reference voltage generation circuit **80**, the regulator circuit **81**, and the output circuit **12** are arranged along the second side SD2. Specifically, the temperature sensor circuit **16** is disposed at a corner portion where the first side SD1 and the fourth side SD4 intersect, and the reference voltage generation circuit **80** is disposed at a corner portion where the fourth side SD4 and the second side SD2 intersect. The output circuit **12** is disposed at a corner portion where the second side SD2 and the third side SD3 intersect.

(172) In FIG. **29**, the reference voltage generation circuit **80** and the regulator circuit **81** are arranged in a manner of partially overlapping at least the first region ARA described with reference to FIG. **18** and the like. Specifically, the plurality of resistive elements provided in the resistance division circuit **82** of the reference voltage generation circuit **80**, the plurality of resistive elements provided in the resistance division circuit **83** of the regulator circuit **81**, and the like are arranged in the first region ARA. By disposing the first circuit element, which is the resistive elements, in the first region ARA, it is possible to enlarge the arrangement area of the integrated circuit **10** while preventing the fluctuation in the circuit characteristics of the reference voltage generation circuit **80** and the regulator circuit **81** due to stress application.

(173) The temperature sensor circuit **16** is disposed in a manner of at least partially overlapping the first region ARA. Specifically, the plurality of transistors of the current mirror circuit **84** provided in the temperature sensor circuit **16** are arranged in the first region ARA. By disposing the first circuit element, which is the transistors, in the first region ARA, it is possible to enlarge the arrangement area of the integrated circuit **10** while preventing the fluctuation in the circuit characteristic of the temperature sensor circuit **16** due to stress application.

(174) The control circuit **13** and the memory **17** are arranged in a manner of at least partially overlapping the first region ARA. Specifically, at least some of the transistors constituting the control circuit **13** and the memory **17** are arranged in the first region ARA. By disposing the first circuit element, which is the transistors, in the first region ARA, it is possible to enlarge the arrangement area of the integrated circuit **10** while preventing fluctuation in circuit characteristics of the control circuit **13** and the memory **17** due to stress application.

(175) Further, the temperature compensation circuit **15** is disposed in the vicinity of the center, and is disposed in a manner of at least partially overlapping the second region ARB. Specifically, the resistive elements provided in the temperature compensation circuit **15** are arranged in the second region ARB. By disposing the second circuit element, which is the resistive elements, in the second region ARB, it is possible to prevent the resistance values of the resistive elements from fluctuating due to stress application, and to prevent the circuit characteristic in the temperature compensation of the temperature compensation circuit **15** from deteriorating. The capacitive elements or the resistive elements of the oscillation circuit **11** are preferably arranged in the second region ARB.

(176) In FIG. **30**, the PLL circuit **18** is further provided. The oscillation circuit **11** is disposed in the vicinity of the central portion and coupled to the pads PX1 and PX2. The temperature sensor circuit **16**, the reference voltage generation circuit **80**, and the PLL circuit **18** are arranged along the fourth side SD4 of the base 2. The PLL circuit **18**, the regulator circuit **81**, and the output circuit **12** are arranged along the second side SD2, and the memory **17**, the control circuit **13**, and the output circuit **12** are disposed along the third side SD3. Specifically, the temperature sensor circuit **16** is disposed at a corner portion where the first side SD1 and the fourth side SD4 intersect, and the PLL circuit **18** is disposed at a corner portion where the fourth side SD4 and the second side SD2 intersect. The output circuit **12** is disposed at a corner portion where the second side SD2 and the third side SD3 intersect.

(177) Also in FIG. **30**, the plurality of resistive elements of the resistance division circuits **82** and **83** of the reference voltage generation circuit **80** and the regulator circuit **81**, the plurality of transistors of the current mirror circuit **84** of the temperature sensor circuit **16**, and the transistors of the control circuit **13** and the memory **17** are arranged in the first region ARA. Accordingly, it is possible to enlarge the arrangement area of the integrated circuit **10** while preventing the

fluctuation in the circuit characteristics.

(178) By arranging the capacitive elements or the resistive elements of the oscillation circuit **11** in the second region ARB, it is possible to prevent the capacitance values of the capacitive elements or the resistance values of the resistive elements from fluctuating due to stress application, and to prevent the circuit characteristics such as the oscillation frequency of the oscillation circuit **11** from deteriorating. The resistive elements of the temperature compensation circuit **15** are also preferably arranged in the second region ARB.

(179) As described above, the vibrator device according to the embodiment includes: a base including a semiconductor substrate that has a first surface and a second surface in a front and back relationship with the first surface and that has an integrated circuit disposed at the first surface; a vibration element electrically coupled to the integrated circuit; and a lid provided with a recess for accommodating the vibration element, including a side wall around the recess, and having an end surface of the side wall bonded to the first surface at a bonding portion. Further, the integrated circuit includes a first circuit, and the first circuit includes a first circuit element disposed in a first region of the first surface, the first region overlapping the bonding portion in a plan view orthogonal to the first surface. The first circuit element is a passive element or a transistor, and $\theta < 90^\circ$ is satisfied, θ being an angle formed by the first surface and an inner side surface of the side wall.

(180) The vibrator device according to the embodiment includes: the base including the semiconductor substrate having the integrated circuit disposed at the first surface; the vibration element electrically coupled to the integrated circuit; and the lid having the end surface of the side wall bonded to the first surface at the bonding portion. Accordingly, a small-sized vibrator device can be implemented. The first circuit of the integrated circuit includes the first circuit element disposed in the first region overlapping the bonding portion in the plan view. The inner side surface of the side wall of the lid is inclined such that $\theta < 90^\circ$, θ being the angle formed by the first surface and the inner side surface of the side wall. As described, by inclining the inner side surface of the side wall, a stress caused by a load can be dispersed. Accordingly, a stress in a region in the vicinity of the bonding portion is reduced, and a stress applied to the first circuit element in the first region can be reduced, and thus deterioration in performance of the vibrator device caused by the stress can be prevented.

(181) In the embodiment, $\theta \leq 80^\circ$ may be satisfied. In this way, it is possible to further reduce the stress in the region in the vicinity of the bonding portion compared to the case where the relationship of $\theta < 90^\circ$ is satisfied, and it is possible to further reduce the stress applied to the first circuit element in the first region.

(182) In the embodiment, in the lid, the inner side surface may be along a crystal orientation $\langle 111 \rangle$ of single crystal silicon.

(183) In this way, the stress in the region in the vicinity of the bonding portion can be reduced, and the inclination of the inner side surface of the side wall can be formed using the crystal orientation $\langle 111 \rangle$ of single crystal silicon.

(184) In the embodiment, $\theta > 45^\circ$ may be satisfied.

(185) In this way, it is possible to prevent a situation where a restriction is posed on an arrangement space of the vibration element since the angle θ is made unnecessarily small.

(186) In the embodiment, the lid may be formed of a second semiconductor wafer bonded, via the bonding portion by stress application, to a first semiconductor wafer forming the base.

(187) In this way, the first semiconductor wafer and the second semiconductor wafer are bonded to each other, and dicing or the like is performed, whereby a large number of vibrator devices can be separated.

(188) Further, in the embodiment, the integrated circuit may include a second circuit, the first surface may include a second region, the first region may surround the second region in a plan view orthogonal to the first surface, the second circuit may include a second circuit element disposed in

the second region, and the first circuit element or the first circuit may be a circuit element or a circuit having a smaller change in circuit characteristic with respect to a stress than the second circuit element or the second circuit.

(189) In this way, the first circuit element can be disposed in the first region where an applied stress is larger, and an arrangement area of the integrated circuit can be enlarged. The second circuit element can be disposed in the second region where the applied stress is smaller, and deterioration in circuit characteristic caused by the stress can be prevented.

(190) In the embodiment, the first circuit may be a circuit whose circuit characteristic is set using a ratio of a circuit constant of the first circuit element.

(191) As described above, in the case of the first circuit whose circuit characteristic is set using the ratio of the circuit constant of the first circuit element, even when the first circuit element is disposed in the first region, it is possible to prevent the deterioration in the circuit characteristic caused by stress application.

(192) In the embodiment, the first circuit may be a circuit in which a plurality of passive elements or a plurality of active elements are provided as the first circuit element, and whose circuit characteristic is set using a ratio of a circuit constant of the plurality of passive elements or the plurality of active elements.

(193) As described above, in the case of the first circuit whose circuit characteristic is set using the ratio of the circuit constant of the plurality of passive elements or the plurality of active elements, even when the passive elements or the active elements are arranged in the first region, it is possible to prevent the deterioration in the circuit characteristic caused by stress application.

(194) In the embodiment, the first circuit element may be a resistive element provided in a resistance voltage divider circuit or a transistor provided in a current mirror circuit.

(195) In the case of the resistive element of the resistance division circuit or the transistor of the current mirror circuit, it is possible to prevent deterioration in the circuit characteristic caused by stress application even when the resistive element or the transistor is disposed in the first region.

(196) In the embodiment, the first circuit may be a reference voltage generation circuit configured to generate a reference voltage to be used in the integrated circuit, and the first circuit element may be a resistive element provided in a resistance division circuit of the reference voltage generation circuit.

(197) As described above, by disposing the resistive element of the resistance division circuit of the reference voltage generation circuit in the first region, the arrangement area of the integrated circuit can be enlarged. In addition, since a circuit characteristic of the resistance division circuit is set using a resistance ratio, even when the resistive element is disposed in the first region, it is possible to prevent deterioration in the circuit characteristic caused by a stress.

(198) In the embodiment, the first circuit may be a regulator circuit configured to generate a regulated voltage to be used in the integrated circuit, and the first circuit element may be a resistive element provided in a resistance division circuit of the regulator circuit.

(199) As described, by disposing the resistive element of the resistance division circuit of the regulator circuit in the first region, the arrangement area of the integrated circuit can be enlarged. In addition, since a circuit characteristic of the resistance division circuit is set using a resistance ratio, even when the resistive element is disposed in the first region, it is possible to prevent deterioration in the circuit characteristic caused by a stress.

(200) In the embodiment, the first circuit may be a temperature sensor circuit configured to detect a temperature, and the first circuit element may be a transistor provided in a current mirror circuit of the temperature sensor circuit.

(201) As described, by disposing the transistor of the current mirror circuit of the temperature sensor circuit in the first region, the arrangement area of the integrated circuit can be enlarged. In addition, since a circuit characteristic of the current mirror circuit is set using a size ratio of the transistor, even when the transistor of the current mirror circuit is disposed in the first region,

deterioration in the circuit characteristic caused by a stress can be prevented.

(202) In the embodiment, the first circuit may be a control circuit or a memory, and the first circuit element may be a transistor provided in the control circuit or the memory.

(203) As described, by disposing the transistor of the control circuit or the memory in the first region, the arrangement area of the integrated circuit can be enlarged. Even when a stress is applied to the transistor of the control circuit or the memory and a circuit characteristic of the transistor changes, the circuit characteristic of the control circuit or the memory can be maintained.

(204) In the embodiment, the integrated circuit may include a second circuit, the first surface may include a second region, the first region may surround the second region in a plan view orthogonal to the first surface, the second circuit may include a second circuit element disposed in the second region, and the second circuit element may be at least one of a capacitive element and a resistive element.

(205) As described, when the capacitive element or the resistive element is disposed in the second region where an applied stress is small, it is possible to prevent fluctuation in a capacitance or a resistance due to the stress.

(206) In the embodiment, the integrated circuit may include a second circuit, the first surface may include a second region, the first region may surround the second region in a plan view orthogonal to the first surface, the second circuit may include a second circuit element disposed in the second region, the second circuit may be an oscillation circuit configured to oscillate the vibration element, and the second circuit element may be at least one of a capacitive element and a resistive element provided in the oscillation circuit.

(207) As described above, when the capacitive element or the resistive element of the oscillation circuit is disposed in the second region where an applied stress is small, it is possible to prevent fluctuation in a capacitance or a resistance due to the stress and to prevent fluctuation in a circuit characteristic of the oscillation circuit.

(208) In the embodiment, the integrated circuit may include a second circuit, the first surface may include a second region, the first region may surround the second region in a plan view orthogonal to the first surface, the second circuit may include a second circuit element disposed in the second region, the second circuit may be a temperature compensation circuit configured to perform temperature compensation for an oscillation frequency of the vibration element, and the second circuit element may be a resistive element provided in the temperature compensation circuit.

(209) As described, when the resistive element of the temperature compensation circuit is disposed in the second region where an applied stress is small, it is possible to prevent fluctuation in a resistance due to the stress and to prevent fluctuation in a circuit characteristic of the temperature compensation circuit.

(210) Although the embodiment is described in detail above, it can be easily understood by those skilled in the art that a number of modifications can be made without substantially departing from the novel matters and effects of the disclosure. Accordingly, all such modifications are within the scope of the disclosure. For example, a term described at least once together with a different term having a broader meaning or the same meaning in the description or the drawings can be replaced with the different term at any place in the description or the drawings. All combinations of the embodiment and the modifications are also included in the scope of the disclosure. The configurations, operations, and the like of the vibrator device are not limited to those described in the embodiment, and various modifications can be made.

Claims

1. A vibrator device comprising: a base including a semiconductor substrate that has a first surface and a second surface in a front and back relationship with the first surface and that has an integrated circuit disposed at the first surface; a vibration element electrically coupled to the

integrated circuit; and a lid provided with a recess for accommodating the vibration element, including a side wall around the recess, and having an end surface of the side wall bonded to the first surface at a bonding portion, wherein the integrated circuit includes a first circuit, the first circuit includes a first circuit element disposed in a first region of the first surface, the first region overlapping the bonding portion in a plan view orthogonal to the first surface, the first circuit element is a passive element or a transistor, $\theta < 90^\circ$, θ being an angle formed by the first surface and an inner side surface of the side wall, the integrated circuit includes a second circuit, the first surface includes a second region, the first region surrounds the second region in a plan view orthogonal to the first surface, and the second circuit includes a second circuit element disposed in the second region.

2. The vibrator device according to claim 1, wherein $\theta \leq 80^\circ$.

3. The vibrator device according to claim 1, wherein in the lid, the inner side surface is along a crystal orientation $\langle 111 \rangle$ of single crystal silicon.

4. The vibrator device according to claim 1, wherein $\theta > 45^\circ$.

5. The vibrator device according to claim 1, wherein the lid is formed of a second semiconductor wafer bonded, via the bonding portion by stress application, to a first semiconductor wafer forming the base.

6. The vibrator device according to claim 1, wherein the first circuit element is a circuit element having a smaller change in circuit characteristic with respect to a stress than the second circuit element.

7. The vibrator device according to claim 1, wherein the first circuit is a circuit having a smaller change in circuit characteristic with respect to a stress than the second circuit.

8. The vibrator device according to claim 1, wherein the first circuit is a circuit whose circuit characteristic is set using a ratio of a circuit constant of the first circuit element.

9. The vibrator device according to claim 1, wherein the first circuit is a circuit in which a plurality of passive elements or a plurality of active elements are provided as the first circuit element, and whose circuit characteristic is set using a ratio of a circuit constant of the plurality of passive elements or the plurality of active elements.

10. The vibrator device according to claim 1, wherein the first circuit element is a resistive element provided in a resistance voltage divider circuit or a transistor provided in a current mirror circuit.

11. The vibrator device according to claim 1, wherein the first circuit is a reference voltage generation circuit configured to generate a reference voltage to be used in the integrated circuit, and the first circuit element is a resistive element provided in a resistance division circuit of the reference voltage generation circuit.

12. The vibrator device according to claim 1, wherein the first circuit is a regulator circuit configured to generate a regulated voltage to be used in the integrated circuit, and the first circuit element is a resistive element provided in a resistance division circuit of the regulator circuit.

13. The vibrator device according to claim 1, wherein the first circuit is a temperature sensor circuit configured to detect a temperature, and the first circuit element is a transistor provided in a current mirror circuit of the temperature sensor circuit.

14. The vibrator device according to claim 1, wherein the first circuit is a control circuit or a memory, and the first circuit element is a transistor provided in the control circuit or the memory.

15. The vibrator device according to claim 1, wherein the second circuit element is at least one of a capacitive element and a resistive element.

16. The vibrator device according to claim 1, wherein the second circuit is an oscillation circuit configured to oscillate the vibration element, and the second circuit element is at least one of a capacitive element and a resistive element provided in the oscillation circuit.

17. The vibrator device according to claim 1, wherein the second circuit is a temperature compensation circuit configured to perform temperature compensation for an oscillation frequency of the vibration element, and the second circuit element is a resistive element provided in the

temperature compensation circuit.

18. A vibrator device comprising: a base including a semiconductor substrate that has a first surface and a second surface in a front and back relationship with the first surface and that has an integrated circuit disposed at the first surface; a vibration element electrically coupled to the integrated circuit; and a lid provided with a recess for accommodating the vibration element, including a side wall around the recess, and having an end surface of the side wall bonded to the first surface at a bonding portion, wherein the integrated circuit includes a first circuit, the first circuit includes a first circuit element disposed in a first region of the first surface, the first region overlapping the bonding portion in a plan view orthogonal to the first surface, the first circuit element is a passive element or a transistor, $\theta < 90^\circ$, θ being an angle formed by the first surface and an inner side surface of the side wall, and the first circuit is a circuit in which a plurality of passive elements or a plurality of active elements are provided as the first circuit element, and whose circuit characteristic is set using a ratio of a circuit constant of the plurality of passive elements or the plurality of active elements.

19. A vibrator device comprising: a base including a semiconductor substrate that has a first surface and a second surface in a front and back relationship with the first surface and that has an integrated circuit disposed at the first surface; a vibration element electrically coupled to the integrated circuit; and a lid provided with a recess for accommodating the vibration element, including a side wall around the recess, and having an end surface of the side wall bonded to the first surface at a bonding portion, wherein the integrated circuit includes a first circuit, the first circuit includes a first circuit element disposed in a first region of the first surface, the first region overlapping the bonding portion in a plan view orthogonal to the first surface, the first circuit element is a passive element or a transistor, $\theta < 90^\circ$, θ being an angle formed by the first surface and an inner side surface of the side wall, and the first circuit is a reference voltage generation circuit configured to generate a reference voltage to be used in the integrated circuit or the first circuit is a regulator circuit configured to generate a regulated voltage to be used in the integrated circuit.
