

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413210
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Li; Lei

Control circuit with hysteresis control for switching converters and control method thereof

Abstract

A controller for a switching converter has a hysteresis generating circuit to provide an upper hysteresis limit and a lower hysteresis limit based on an output voltage, a switching control circuit for providing a switching control signal, and a frequency locking circuit for adjusting one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal and a clock signal. When the switching converter is in a first mode, a main switch of the switching converter is turned ON by comparing a current sense signal representative of a current flowing through the main switch with the lower hysteresis limit, and is turned OFF by comparing the current sense signal with the upper hysteresis limit. When the switching converter is in a second mode, the main switch is turned ON based on the clock signal, and is turned OFF based on the current sense signal.

Inventors:	Li; Lei (Chengdu, CN)
Applicant:	Chengdu Monolithic Power Systems Co., Ltd. (Chengdu, CN)
Family ID:	83830800
Assignee:	Chengdu Monolithic Power Systems Co., Ltd. (Sichuan, CN)
Appl. No.:	18/449181
Filed:	August 14, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230387892 A1	Nov. 30, 2023

Foreign Application Priority Data

CN	202211006883.8	Aug. 22, 2022
----	----------------	---------------

Publication Classification

Int. Cl.: H03K3/02 (20060101); H02M1/00 (20060101); H02M3/158 (20060101); H03K3/0233 (20060101)

U.S. Cl.:

CPC H03K3/02337 (20130101); H02M1/0025 (20210501); H02M3/158 (20130101);

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5998945	12/1998	Elliott	318/254.1	H02P 25/0925
7116089	12/2005	Nguyen et al.	N/A	N/A
8138734	12/2011	Xi et al.	N/A	N/A
8928300	12/2014	Xi et al.	N/A	N/A
8941367	12/2014	Li et al.	N/A	N/A
9774253	12/2016	Xu	N/A	N/A
9891648	12/2017	Li	N/A	N/A
9979288	12/2017	Mao et al.	N/A	N/A
10666272	12/2019	Li	N/A	N/A
2013/0077359	12/2012	Lindemann	363/39	H02M 1/44
2013/0127430	12/2012	Leung	323/282	H02M 3/157
2019/0190377	12/2018	Santiago	N/A	H02M 3/156

Primary Examiner: De Leon Domenech; Rafael O

Attorney, Agent or Firm: Perkins Coie LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This application claims the benefit of CN application 202211006883.8, filed on Aug. 22, 2022, and incorporated herein by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

(2) The present invention generally relates to electronic circuits, and more particularly, relates to control circuits for voltage regulators and control methods thereof.

2. Description of Related Art

(3) Fixed frequency peak current control is widely used in switching converters. With a fixed frequency peak current control, a reference voltage and a feedback signal representative of an output voltage of a switching converter are sent into an error amplifier to generate a compensation

signal. A main switch of the switching converter is turned ON by a clock signal, and is turned OFF when a current sense signal representative of a current flowing through the main switch increases to be larger than the compensation signal. Owing to an inherent delay of the control circuit, there exists a minimum ON time period for the main switch, i.e., the main switch can be turned OFF only after its ON time period reaches the minimum ON time period.

(4) If the input voltage of the switching converter keeps increasing, the ON time period of the main switch will decrease until it reaches the minimum ON time period, and the ON time period of the main switch cannot be further decreased. As a result, the output voltage of the switching converter will go up with the input voltage, and a large ripple would arise on the output voltage accordingly.

SUMMARY OF THE INVENTION

(5) It is an object of the present invention to provide a controller for a switching converter.

(6) Embodiments of the present invention are directed to a controller for a switching converter. The switching converter comprises a main switch. The controller comprises a hysteresis generating circuit, a switching control circuit, and a frequency locking circuit. The hysteresis generating circuit, configured to provide an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter. The switching control circuit is configured to provide a switching control signal to control the main switch. The frequency locking circuit, configured to adjust one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal and a clock signal. In response to a first mode of the switching converter, the switching control circuit is configured to turn the main switch ON by comparing a current sense signal representative of a current flowing through the main switch with the lower hysteresis limit, and to turn the main switch OFF by comparing the current sense signal with the upper hysteresis limit. In response to a second mode of the switching converter, the switching control circuit is configured to turn the main switch ON based on the clock signal, and to turn the main switch OFF based on the current sense signal.

(7) Embodiments of the present invention are directed to a controller for a switching converter. The switching converter comprises a main switch. The controller comprises a hysteresis generating circuit and a switching control circuit. The hysteresis generating circuit is configured to provide an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter. The switching control circuit is coupled to the hysteresis generating circuit, and is configured to provide a switching control signal based on a current sense signal representative of a current flowing through the main switch, the upper hysteresis limit, and the lower hysteresis limit to turn ON and OFF the main switch. In response to a first mode of the switching converter, the switching control circuit is configured to turn the main switch OFF by comparing the current sense signal with the upper hysteresis limit, and to turn the main switch ON by comparing the current sense signal with the lower hysteresis limit. One of the upper hysteresis limit and the lower hysteresis limit is adjusted such that a difference between the upper hysteresis limit and the lower hysteresis limit is adjusted according to a frequency of the switching control signal.

(8) Embodiments of the present invention are directed to a control method for a switching converter. The switching converter comprises a main switch. The control method comprises providing an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter, providing a switching control signal based on a current sense signal representative of a current flowing through the main switch, the upper hysteresis limit, and the lower hysteresis limit to turn ON and OFF the main switch in response to a first mode of the switching converter, and adjusting one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal. Wherein the main switch is turned OFF by comparing the current sense signal with the upper hysteresis limit, and is turned ON by comparing the current sense signal with the lower hysteresis limit.

(9) These and other features of the present invention will be readily apparent to persons of ordinary

skill in the art upon reading the entirety of this disclosure, which includes the accompanying drawings and claims.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) The present invention can be further understood with reference to the following detailed description and the appended drawings, wherein like elements are provided with like reference numerals.
- (2) FIG. 1 schematically shows a block diagram of a switching converter **100** in accordance with an embodiment of the present invention.
- (3) FIG. 2 schematically illustrates a circuit diagram of a switching control circuit **12A** in accordance with an embodiment of the present invention.
- (4) FIG. 3 schematically illustrates a circuit diagram of the switching control circuit **12B** in accordance with another embodiment of the present invention.
- (5) FIG. 4 schematically illustrates a circuit diagram of a hysteresis generating circuit **13A** in accordance with an embodiment of the present invention.
- (6) FIG. 5 schematically illustrates a circuit diagram of the hysteresis generating circuit **13B** in accordance with another embodiment of the present invention.
- (7) FIG. 6 schematically illustrates a circuit diagram of the switching converter **200** in accordance with an embodiment of the present invention.
- (8) FIG. 7 illustrates a control method **700** for a switching converter in accordance with an embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

(9) Reference will now be made in detail to the preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings. While the invention will be described in conjunction with the preferred embodiments, it will be understood that they are not intended to limit the invention to these embodiments. On the contrary, the invention is intended to cover alternatives, modifications and equivalents, which may be included within the spirit and scope of the invention as defined by the appended claims. Furthermore, in the following detailed description of the present invention, numerous specific details are set forth in order to provide a thorough understanding of the present invention. However, it will be obvious to one of ordinary skill in the art that the present invention may be practiced without these specific details. In other instances, well-known methods, procedures, components, and circuits have not been described in detail so as not to unnecessarily obscure aspects of the present invention.

(10) FIG. 1 schematically shows a block diagram of a switching converter **100** in accordance with an embodiment of the present invention. In the example of FIG. 1, the switching converter **100** comprises a switching circuit **11**, a controller **20**, a current sensing circuit **15**, and a feedback circuit **16**. The switching circuit **11** comprises a main switch, and is configured to convert an input voltage V_{in} into an output voltage V_o . The switching circuit **11** may comprise any suitable topologies, such as buck, boost, buck-boost, flyback, etc. The feedback circuit **16** is coupled to the switching circuit **11** to provide a feedback signal FB based on the output voltage V_o . The current sensing circuit **15** provides a current sense signal V_{cs} based on a current flowing through the main switch.

(11) The controller **20** comprises a switching control circuit **12**, a hysteresis generating circuit **13**, and a frequency locking circuit **14**. The hysteresis generating circuit **13** provides an upper hysteresis limit V_{thh} and a lower hysteresis limit V_{thl} based on the output voltage V_o . The switching control circuit **12** provides a switching control signal PWM to control the main switch. In one embodiment, the switching control circuit **12** is coupled to the hysteresis generating circuit **13**, and provides the switching control signal PWM based on the current sense signal V_{cs} , the

upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} to turn ON and OFF the main switch. In one embodiment, the main switch is turned OFF by comparing the current sense signal V_{cs} with the upper hysteresis limit V_{thh} , and is turned ON by comparing the current sense signal V_{cs} with the lower hysteresis limit V_{thl} . In another embodiment, when the switching converter **100** is in a first mode, the switching control circuit **12** turns the main switch ON by comparing the current sense signal V_{cs} with the lower hysteresis limit V_{thl} , and turns the main switch OFF by comparing the current sense signal V_{cs} with the upper hysteresis limit V_{thh} ; and when the switching converter **100** is in a second mode, the switching control circuit **12** turns the main switch ON based on a clock signal CLK, and turns the main switch OFF based on the current sense signal V_{cs} . The first mode comprises situations of the input voltage varying. For example, the first mode may comprise but not limited to a startup process of the switching converter **100**. The second mode comprises situations of the input voltage kept unchanged. For example, the second mode may comprise but not limited to a normal operation after the startup process of the switching converter **100**. The switching converter **100** in accordance with the embodiments of the present invention can smoothly transit between the first mode and the second mode without a sudden change or jitter of a switching frequency or the output voltage V_o of the switching converter **100**. The frequency locking circuit **14** adjusts one of the upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} based on the switching control signal PWM and the clock signal CLK, and thus controls a frequency of the switching control signal PWM equal to a frequency of the clock signal CLK. In one embodiment, the frequency locking circuit **14** provides a hysteresis adjustment signal F_{adj} to adjust one of the upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} based on a difference between the frequency of the switching control signal PWM and the frequency of the clock signal CLK.

(12) When the input voltage V_{in} varies significantly, the switching converter **100** in accordance with the embodiments of the present invention can prevent an ON time period of the main switch from being reduced to a minimum ON time period, thereby stabilizing the output voltage V_o , and can also keep the switching frequency basically constant to reduce electromagnetic interference.

(13) FIG. 2 schematically illustrates a circuit diagram of the switching control circuit **12A** in accordance with an embodiment of the present invention. In the embodiment of FIG. 2, the switching control circuit **12A** comprises a selection circuit **121** and a comparison circuit **122**. The selection circuit **121** receives the upper hysteresis limit V_{thh} , the lower hysteresis limit V_{thl} , and a selection signal Sel. The selection circuit **121** selects one of the upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} as a current reference signal I_{ref} according to the selection signal Sel. In one embodiment, the selection signal Sel is generated based on the switching control signal PWM. The comparison circuit **122** provides the switching control signal PWM by comparing the current sense signal V_{cs} with the current reference signal I_{ref} . In one embodiment, when the switching control signal PWM controls the main switch to remain OFF, the lower hysteresis limit V_{thl} is selected as the current reference signal I_{ref} based on the selection signal Sel, and the comparison circuit **122** provides the switching control signal PWM to turn the main switch ON by comparing the current sense signal V_{cs} with the lower hysteresis limit V_{thl} . In one embodiment, when the switching control signal PWM controls the main switch to remain ON, the upper hysteresis limit V_{thh} is selected as the current reference signal I_{ref} based on the selection signal Sel, and the comparison circuit **122** provides the switching control signal PWM to turn the main switch OFF by comparing the current sense signal V_{cs} with the upper hysteresis limit V_{thh} . In the example of FIG. 2, the comparison circuit **122** comprises a first input terminal to receive the current sense signal V_{cs} , a second input terminal to receive the current reference signal I_{ref} , and an output terminal to provide the switching control signal PWM. In one embodiment, the selection signal Sel is an inverted signal of the switching control signal PWM. For example, an inverter **123** receives the switching control signal PWM, and provides the selection signal Sel by inverting the switching control signal PWM.

(14) FIG. 3 schematically illustrates a circuit diagram of the switching control circuit **12B** in accordance with another embodiment of the present invention. In the example of FIG. 3, the output terminal of the comparison circuit **122** provides a control signal Ct1, and the switching control circuit **12B** further comprises a flip-flop **126** and a selection circuit **124**. The flip-flop **126** comprises a set terminal S, a reset terminal R, and an output terminal Q. The set terminal S receives the clock signal CLK, the reset terminal R is coupled to the comparison circuit **122** to receive the control signal Ct1, and the output terminal Q provides a control signal Ct2. The selection circuit **124** is coupled to the comparison circuit **122** and the flip-flop **126** to provide the switching control signal PWM based on the control signal Ct1 and the control signal Ct2.

(15) In one embodiment, the selection circuit **124** receives a mode indication signal SSOK. In one example, when the mode indication signal SSOK is in a first status (e.g., logic low), it is indicated that the switching converter **100** is in the first mode, and when the mode indication signal SSOK is in a second status (e.g., logic high), it is indicated that the switching converter **100** is in the second mode. In some examples, a voltage level between a high threshold voltage (e.g., 2V) and a voltage source (e.g., 3.3V) is considered as logic high ("1"), a voltage level between zero voltage (0 V) and a low threshold voltage (e.g., 1V) is considered as logic low ("0"). In one embodiment, when the mode indication signal SSOK is in the first status, the selection circuit **124** selects the control signal Ct1 as the switching control signal PWM, and when the mode indication signal SSOK is in the second status, the selection circuit **124** selects the control signal Ct2 as the switching control signal PWM. In one embodiment, the switching control circuit **12** further comprises a logic circuit **125**. For example, the logic circuit **125** comprises a NOR gate. The logic circuit **125** has a first input terminal to receive the mode indication signal SSOK, a second input terminal to receive an inverted signal of the switching control signal PWM, and an output terminal to provide the selection signal Sel based on the mode indication signal SSOK and the inverted signal of the switching control signal PWM. In one embodiment, when the switching circuit **100** is in the second mode, the selection circuit **121** selects the lower hysteresis limit Vthl as the current reference signal Iref, and the comparison circuit **122** provides the control signal Ct1 to turn the main switch OFF by comparing the current sense signal Vcs with the lower hysteresis limit Vthl. In another embodiment, when the switching circuit **100** is in the second mode, the selection circuit **121** selects the upper hysteresis limit Vthh as the current reference signal Iref, and the comparison circuit **122** provides the control signal Ct1 to turn the main switch OFF by comparing the current sense signal Vcs with the upper hysteresis limit Vthh. In one embodiment, when the switching circuit **100** is in the first mode and the main switch remains OFF under the control of the switching control signal PWM, the selection circuit **121** selects the lower hysteresis limit Vthl as the current reference signal Iref, and the comparison circuit **122** turns the main switch ON by comparing the current sense signal Vcs with the lower hysteresis limit Vthl. In another embodiment, when the switching circuit **100** is in the first mode and the main switch remains ON under the control of the switching control signal PWM, the selection circuit **121** selects the upper hysteresis limit Vthh as the current reference signal Iref, and the comparison circuit **122** turns the main switch OFF by comparing the current sense signal Vcs with the upper hysteresis limit Vthh.

(16) FIG. 4 schematically illustrates a circuit diagram of the hysteresis generating circuit **13A** in accordance with an embodiment of the present invention. As shown in FIG. 4, the hysteresis generating circuit **13A** comprises an error circuit **131**, a controllable current source **132**, and a resistor **133**. In the example of FIG. 4, the error circuit **131** comprises an error amplifier. The error circuit **131** has a first input terminal, a second input terminal, and an output terminal. The first input terminal of the error circuit **131** receives the feedback signal FB, the second input terminal of the error circuit **131** receives a voltage reference Vref, and the error circuit **131** provides an error signal EAO at its output terminal based on a difference between the feedback signal FB and the voltage reference Vref. In the example of FIG. 4, the error signal EAO is provided as the lower hysteresis limit Vthl. An output current of the controllable current source **132** is adjusted under the control of

the hysteresis adjustment signal F_{adj} based on a difference between the frequency of the switching control signal PWM and the frequency of the clock signal CLK. The resistor **133** comprises a first terminal coupled to the output terminal of the error circuit **131**, and a second terminal coupled to the controllable current source **132**. The output current of the controllable current source **132** flows through the resistor **133**, and the upper hysteresis limit V_{thh} is provided at the second terminal of the resistor **133**.

(17) FIG. 5 schematically illustrates a circuit diagram of the hysteresis generating circuit **13B** in accordance with another embodiment of the present invention. In the example of FIG. 5, the hysteresis generating circuit **13B** comprises the error circuit **131**, a controllable current source **135**, and a resistor **134**. As shown in FIG. 5, the error signal EAO is provided as the upper hysteresis limit V_{thh} . An output current of the controllable current source **135** is adjusted under the control of the hysteresis adjustment signal F_{adj} based on a difference between the frequency of the switching control signal PWM and the frequency of the clock signal CLK. The resistor **134** comprises a first terminal coupled to the output terminal of the error circuit **131**, and a second terminal coupled to the controllable current source **135**. The output current of the controllable current source **135** flows through the resistor **134**, and the lower hysteresis limit V_{thl} is provided at the second terminal of the resistor **134**.

(18) In the embodiments of the present invention, one of the upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} is adjusted such that a difference between the upper hysteresis limit V_{thh} and the lower hysteresis limit V_{thl} is adjusted according to the frequency of the switching control signal PWM.

(19) FIG. 6 schematically illustrates a circuit diagram of the switching converter **200** in accordance with an embodiment of the present invention. In the example of FIG. 6, the switching converter **100** is a synchronous buck circuit comprising an input capacitor C_{in} , switches S1 and S2, an inductor L, and an output capacitor C_{out} , which are connected as shown in FIG. 6. For example, the main switch of the switching converter **100** may comprise the switch S1 or the switch S2. The feedback circuit **16** comprises a resistor **R3** and a resistor **R4** working as a resistor divider. The current sensing circuit **15** senses a current flowing through the switch S1 to provide the current sense signal V_{cs} . One with ordinary skill in the art should understand that the current sense signal V_{cs} may also be provided by sensing a current flowing through the switch S2. The switching control signal PWM controls the switches S1 and S2 through a driving circuit **61**.

(20) FIG. 7 illustrates a control method **700** for a switching converter in accordance with an embodiment of the present invention. The control method **700** comprises steps S11-S14.

(21) In step S11, providing an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter.

(22) In step S12, in response to a first mode of the switching converter, providing a switching control signal based on a current sense signal representative of a current flowing through a main switch, an upper hysteresis limit, and a lower hysteresis limit to turn ON and OFF the main switch. The main switch is turned OFF by comparing the current sense signal with the upper hysteresis limit, and is turned ON by comparing the current sense signal with the lower hysteresis limit.

(23) In step S13, in response to a second mode of the switching converter, providing the switching control signal based on a clock signal and the current sense signal. The main switch is turned ON based on the clock signal, and is turned OFF by comparing the current sense signal with the upper hysteresis limit or the lower hysteresis limit.

(24) In step S14, adjusting one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal and the clock signal to control a frequency of the switching control signal equal to a frequency of the clock signal. Wherein one of the upper hysteresis limit and the lower hysteresis limit is adjusted such that a difference between the upper hysteresis limit and the lower hysteresis limit is adjusted according to the frequency of the switching control signal.

(25) Note that in the control method described above, the functions indicated in the boxes can also

occur in a different order than those shown in FIG. 7. For example, two boxes presented one after another can actually be executed essentially at the same time, or sometimes in reverse order, depending on the specific functionality involved.

(26) Obviously many modifications and variations of the present invention are possible in light of the above teachings. It is therefore to be understood that within the scope of the appended claims the invention may be practiced otherwise than as specifically described. It should be understood, of course, the foregoing disclosure relates only to a preferred embodiment (or embodiments) of the invention and that numerous modifications may be made therein without departing from the spirit and the scope of the invention as set forth in the appended claims. Various modifications are contemplated and they obviously will be resorted to by those skilled in the art without departing from the spirit and the scope of the invention as hereinafter defined by the appended claims as only a preferred embodiment(s) thereof has been disclosed.

Claims

1. A controller for a switching converter, wherein the switching converter comprises a main switch, the controller comprising: a hysteresis generating circuit, configured to provide an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter; a switching control circuit, configured to provide a switching control signal to control the main switch; and a frequency locking circuit, configured to adjust one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal and a clock signal; wherein in response to a first mode of the switching converter, the switching control circuit is configured to turn the main switch ON by comparing a current sense signal representative of a current flowing through the main switch with the lower hysteresis limit, and to turn the main switch OFF by comparing the current sense signal with the upper hysteresis limit; and wherein in response to a second mode of the switching converter, the switching control circuit is configured to turn the main switch ON based on the clock signal, and to turn the main switch OFF based on the current sense signal.

2. The controller of claim 1, wherein the frequency locking circuit is configured to adjust one of the upper hysteresis limit and the lower hysteresis limit based on a difference between a frequency of the switching control signal and a frequency of the clock signal.

3. The controller of claim 1, wherein the hysteresis generating circuit further comprises: an error circuit, having an output terminal to provide an error signal as the upper hysteresis limit based on a difference between a feedback signal and a voltage reference, wherein the feedback signal represents the output voltage; a controllable current source, configured to provide an output current, and is further configured to adjust the output current based on a difference between a frequency of the switching control signal and a frequency of the clock signal; and a resistor, comprising a first terminal and a second terminal, wherein the first terminal of the resistor is coupled to the output terminal of the error circuit, the second terminal of the resistor is coupled to the controllable current source, and the lower hysteresis limit is provided at the second terminal of the resistor.

4. The controller of claim 1, wherein the hysteresis generating circuit further comprises: an error circuit, having an output terminal to provide an error signal as the lower hysteresis limit based on a difference between a feedback signal and a voltage reference, wherein the feedback signal represents the output voltage; a controllable current source, configured to provide an output current, and is further configured to adjust the output current based on a difference between a frequency of the switching control signal and a frequency of the clock signal; and a resistor, comprising a first terminal and a second terminal, wherein the first terminal of the resistor is coupled to the output terminal of the error circuit, the second terminal of the resistor is coupled to the controllable current source, and the upper hysteresis limit is provided at the second terminal of

the resistor.

5. The controller of claim 1, wherein the switching control circuit further comprises: a comparison circuit, configured to provide the switching control signal based on the current sense signal, the upper hysteresis limit, and the lower hysteresis limit, wherein the comparison circuit is configured to turn the main switch OFF by comparing the current sense signal with the upper hysteresis limit, and is configured to turn the main switch ON by comparing the current sense signal with the lower hysteresis limit.
6. The controller of claim 1, wherein the switching control circuit further comprises: a comparison circuit, configured to provide a first control signal based on the current sense signal, the upper hysteresis limit, and the lower hysteresis limit; a flip-flop, having a set terminal to receive the clock signal, a reset terminal to receive the first control signal, and an output terminal to provide a second control signal; and a selection circuit, configured to provide the switching control signal based on the first control signal and the second control signal; wherein in response to the first mode of the switching converter, the selection circuit is configured to select the first control signal as the switching control signal, and in response to the second mode of the switching converter, the selection circuit is configured to select the second control signal as the switching control signal.
7. The controller of claim 6, wherein in response to the first mode of the switching converter, the selection circuit is configured to provide the switching control signal by comparing the current sense signal with the upper hysteresis limit during when the main switch remains ON.
8. The controller of claim 6, wherein in response to the first mode of the switching converter, the selection circuit is configured to provide the switching control signal by comparing the current sense signal with the lower hysteresis limit during when the main switch remains OFF.
9. The controller of claim 1, wherein in response to the second mode of the switching converter, the switching control circuit is configured to turn the main switch OFF by comparing the current sense signal with one of the upper hysteresis limit and the lower hysteresis limit.
10. The controller of claim 1, wherein one of the upper hysteresis limit and the lower hysteresis limit is adjusted such that a difference between the upper hysteresis limit and the lower hysteresis limit is adjusted according to a frequency of the switching control signal.
11. A controller for a switching converter, wherein the switching converter comprises a main switch, the controller comprising: a hysteresis generating circuit, configured to provide an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter; and a switching control circuit coupled to the hysteresis generating circuit, configured to provide a switching control signal based on a current sense signal representative of a current flowing through the main switch, the upper hysteresis limit, and the lower hysteresis limit to turn ON and OFF the main switch; wherein in response to a first mode of the switching converter, the switching control circuit is configured to turn the main switch OFF by comparing the current sense signal with the upper hysteresis limit, and to turn the main switch ON by comparing the current sense signal with the lower hysteresis limit; and wherein one of the upper hysteresis limit and the lower hysteresis limit is adjusted such that a difference between the upper hysteresis limit and the lower hysteresis limit is adjusted according to a frequency of the switching control signal.
12. The controller of claim 11, wherein in response to a second mode of the switching converter, the switching control circuit is configured to turn the main switch ON based on a clock signal, and to turn the main switch OFF based on comparing the current sense signal with one of the upper hysteresis limit and the lower hysteresis limit.
13. The controller of claim 12, wherein one of the upper hysteresis limit and the lower hysteresis limit is adjusted based on a difference between the frequency of the switching control signal and a frequency of the clock signal.
14. The controller of claim 11, wherein the hysteresis generating circuit further comprises: an error circuit, having an output terminal to provide an error signal as the upper hysteresis limit based on a difference between a feedback signal and a voltage reference, wherein the feedback signal

represents the output voltage; a controllable current source, configured to provide an output current, and is further configured to adjust the output current based on a difference between the frequency of the switching control signal and a frequency of the clock signal; and a resistor, comprising a first terminal and a second terminal, wherein the first terminal of the resistor is coupled to the output terminal of the error circuit, the second terminal of the resistor is coupled to the controllable current source, and the lower hysteresis limit is provided at the second terminal of the resistor.

15. The controller of claim 11, wherein the hysteresis generating circuit further comprises: an error circuit, having an output terminal to provide an error signal as the lower hysteresis limit based on a difference between a feedback signal and a voltage reference, wherein the feedback signal represents the output voltage; a controllable current source, configured to provide an output current, and is further configured to adjust the output current based on a difference between the frequency of the switching control signal and a frequency of the clock signal; and a resistor, comprising a first terminal and a second terminal, wherein the first terminal of the resistor is coupled to the output terminal of the error circuit, the second terminal of the resistor is coupled to the controllable current source, and the upper hysteresis limit is provided at the second terminal of the resistor.

16. A control method for a switching converter, wherein the switching converter comprises a main switch, the control method comprising: providing an upper hysteresis limit and a lower hysteresis limit based on an output voltage of the switching converter; in response to a first mode of the switching converter, providing a switching control signal based on a current sense signal representative of a current flowing through the main switch, the upper hysteresis limit, and the lower hysteresis limit to turn ON and OFF the main switch, wherein the main switch is turned OFF by comparing the current sense signal with the upper hysteresis limit, and is turned ON by comparing the current sense signal with the lower hysteresis limit; and adjusting one of the upper hysteresis limit and the lower hysteresis limit based on the switching control signal.

17. The control method of claim 16, further comprising: in response to a second mode of the switching converter, providing the switching control signal based on a clock signal and the current sense signal, wherein the main switch is turned ON based on the clock signal, and is turned OFF by comparing the current sense signal with one of the upper hysteresis limit and the lower hysteresis limit.

18. The control method of claim 16, wherein adjusting one of the upper hysteresis limit or the lower hysteresis limit based on the switching control signal further comprises: adjusting one of the upper hysteresis limit and the lower hysteresis limit based on a difference between a frequency of the switching control signal and a frequency of a clock signal.

19. The control method of claim 16, further comprising: controlling a frequency of the switching control signal equal to a frequency of the clock signal by adjusting one of the upper hysteresis limit and the lower hysteresis limit.
