

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400616
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Kimura; Hajime et al.

Semiconductor device

Abstract

A semiconductor device where delay or distortion of a signal output to a gate signal line in a selection period is reduced is provided. The semiconductor device includes a gate signal line, a first and second gate driver circuits which output a selection signal and a non-selection signal to the gate signal line, and pixels electrically connected to the gate signal line and supplied with the two signals. In a period during which the gate signal line is selected, both the first and second gate driver circuits output the selection signal to the gate signal line. In a period during which the gate signal line is not selected, one of the first and second gate driver circuits outputs the non-selection signal to the gate signal line, and the other gate driver circuit outputs neither the selection signal nor the non-selection signal to the gate signal line.

Inventors:	Kimura; Hajime (Kanagawa, JP), Umezaki; Atsushi (Kanagawa, JP)
Applicant:	SEMICONDUCTOR ENERGY LABORATORY CO., LTD. (Atsugi, JP)
Family ID:	1000008779168
Assignee:	Semiconductor Energy Laboratory Co., Ltd. (Atsugi, JP)
Appl. No.:	18/892704
Filed:	September 23, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20250014531 A1	Jan. 09, 2025

Foreign Application Priority Data

JP	2010-201621	Sep. 09, 2010
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc US 18212752 20230622 US 12100366 child-doc US 18892704
continuation parent-doc US 17979836 20221103 US 11688358 20230627 child-doc US 18212752
continuation parent-doc US 17206746 20210319 US 11501728 20221115 child-doc US 17979836
continuation parent-doc US 16711621 20191212 US 10957267 20210323 child-doc US 17206746
continuation parent-doc US 16421661 20190524 US 10510310 20191217 child-doc US 16711621
continuation parent-doc US 16199567 20181126 US 10304402 20190528 child-doc US 16421661
continuation parent-doc US 15995210 20180601 US 10140942 20181127 child-doc US 16199567
continuation parent-doc US 15396862 20170103 US 9990894 20180605 child-doc US 15995210
continuation parent-doc US 14714395 20150518 US 9552761 20170124 child-doc US 15396862
continuation parent-doc US 13225856 20110906 US 9035923 20150519 child-doc US 14714395

Publication Classification

Int. Cl.: **G09G3/36** (20060101); **G09G3/20** (20060101)

U.S. Cl.:

CPC **G09G3/3648** (20130101); **G09G3/2096** (20130101); **G09G3/3677** (20130101);
G09G3/3688 (20130101); G09G2300/0426 (20130101); G09G2300/0814 (20130101);
G09G2300/0819 (20130101); G09G2320/0209 (20130101); G09G2320/0223
(20130101); G09G2320/043 (20130101)

Field of Classification Search

CPC: G09G (3/3677); G09G (3/2096); G09G (2300/0426); G09G (2300/0814); G09G
(2300/0819); G09G (2320/0209); G09G (2320/0223)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5986630	12/1998	Hirakata et al.	N/A	N/A
6876353	12/2004	Morosawa et al.	N/A	N/A
7023410	12/2005	Lee et al.	N/A	N/A
7023419	12/2005	Park	N/A	N/A
7038653	12/2005	Moon	N/A	N/A
7119767	12/2005	Komiya	345/100	G09G 3/3266
7190338	12/2006	Kubota et al.	N/A	N/A
7277070	12/2006	Koyama	N/A	N/A
7283111	12/2006	Kimura	N/A	N/A
7317432	12/2007	Koyama	N/A	N/A
7332742	12/2007	Miyake et al.	N/A	N/A
7333586	12/2007	Jang	N/A	N/A
7339570	12/2007	Kubota et al.	N/A	N/A
7369111	12/2007	Jeon et al.	N/A	N/A
7405716	12/2007	Lee et al.	N/A	N/A
7486268	12/2008	Jang et al.	N/A	N/A
7522145	12/2008	Lee et al.	N/A	N/A

7529334	12/2008	Jang	N/A	N/A
7573445	12/2008	Machida	N/A	N/A
7687808	12/2009	Umezaki	N/A	N/A
7705819	12/2009	Choi	N/A	N/A
7814345	12/2009	Shaver et al.	N/A	N/A
7843421	12/2009	Chang et al.	N/A	N/A
7859507	12/2009	Jang et al.	N/A	N/A
7859510	12/2009	Umezaki	N/A	N/A
7889832	12/2010	Otose et al.	N/A	N/A
7898558	12/2010	Chien et al.	N/A	N/A
7956855	12/2010	Park	N/A	N/A
7978274	12/2010	Umezaki et al.	N/A	N/A
8054279	12/2010	Umezaki et al.	N/A	N/A
8085235	12/2010	Jeon et al.	N/A	N/A
8089446	12/2011	Pak et al.	N/A	N/A
8102340	12/2011	Lee et al.	N/A	N/A
8188477	12/2011	Miyairi et al.	N/A	N/A
8212802	12/2011	Jeon	N/A	N/A
8248352	12/2011	Kim et al.	N/A	N/A
8279210	12/2011	Im et al.	N/A	N/A
8330492	12/2011	Umezaki	N/A	N/A
8405596	12/2012	Kumada	345/98	G09G 3/3677
8520159	12/2012	Umezaki et al.	N/A	N/A
8547368	12/2012	Yokoyama et al.	N/A	N/A
8564523	12/2012	Moon	N/A	N/A
8587508	12/2012	Iwase et al.	N/A	N/A
8624819	12/2013	Kim et al.	N/A	N/A
8654056	12/2013	Otose et al.	N/A	N/A
8718223	12/2013	Murakami et al.	N/A	N/A
8743044	12/2013	Umezaki et al.	N/A	N/A
8902145	12/2013	Umezaki et al.	N/A	N/A
8907348	12/2013	Miyairi et al.	N/A	N/A
8908115	12/2013	Umezaki et al.	N/A	N/A
8937614	12/2014	Otose et al.	N/A	N/A
9070593	12/2014	Umezaki	N/A	N/A
9153341	12/2014	Umezaki	N/A	N/A
9214473	12/2014	Umezaki	N/A	N/A
9263468	12/2015	Umezaki et al.	N/A	N/A
9269317	12/2015	Jeon et al.	N/A	N/A
9461071	12/2015	Umezaki	N/A	N/A
9536903	12/2016	Umezaki et al.	N/A	N/A
9570619	12/2016	Miyairi et al.	N/A	N/A
9606408	12/2016	Umezaki et al.	N/A	N/A
9646714	12/2016	Umezaki	N/A	N/A
9842861	12/2016	Umezaki et al.	N/A	N/A
9893089	12/2017	Miyairi et al.	N/A	N/A
10048558	12/2017	Umezaki et al.	N/A	N/A
10243006	12/2018	Miyairi et al.	N/A	N/A
10297618	12/2018	Umezaki et al.	N/A	N/A
10311960	12/2018	Umezaki	N/A	N/A

10527902	12/2019	Umezaki et al.	N/A	N/A
10622381	12/2019	Miyairi et al.	N/A	N/A
10930683	12/2020	Umezaki et al.	N/A	N/A
11237445	12/2021	Umezaki et al.	N/A	N/A
11967598	12/2023	Umezaki et al.	N/A	N/A
12107092	12/2023	Umezaki et al.	N/A	N/A
2001/0022565	12/2000	Kimura	345/82	G09G 3/3266
2001/0052898	12/2000	Osame	345/211	G09G 3/3688
2005/0088386	12/2004	Kao	345/87	G09G 3/3648
2006/0139293	12/2005	Cho	N/A	N/A
2006/0279513	12/2005	Chung	N/A	N/A
2007/0132700	12/2006	Cho	345/100	G11C 19/28
2007/0146354	12/2006	Kubota. et al.	N/A	N/A
2007/0159438	12/2006	Cho	N/A	N/A
2007/0236427	12/2006	Koyama	N/A	N/A
2007/0290982	12/2006	Kim et al.	N/A	N/A
2008/0007296	12/2007	Umezaki	N/A	N/A
2008/0030434	12/2007	Yamazaki	345/76	G09G 3/3258
2008/0036717	12/2007	Moon	345/87	G09G 3/3677
2008/0055200	12/2007	Lee et al.	N/A	N/A
2008/0062112	12/2007	Umezaki	N/A	N/A
2008/0170064	12/2007	Lee	345/87	G09G 3/3677
2008/0211760	12/2007	Baek et al.	N/A	N/A
2008/0219401	12/2007	Tobita	N/A	N/A
2008/0266477	12/2007	Lee	345/94	G09G 3/3677
2008/0278467	12/2007	Hwang	345/87	G09G 3/3648
2009/0021466	12/2008	Otose et al.	N/A	N/A
2009/0146920	12/2008	Miyake	345/55	G09G 3/3677
2009/0153532	12/2008	Chen et al.	N/A	N/A
2009/0261339	12/2008	Tsai et al.	N/A	N/A
2009/0267883	12/2008	Kim	345/94	G09G 3/3677
2009/0278782	12/2008	Chen	N/A	N/A
2010/0002021	12/2009	Hashimoto	345/88	G09G 3/2003
2010/0026619	12/2009	Umezaki	345/100	G09G 3/3648
2010/0053138	12/2009	Im	345/212	G09G 3/3677
2010/0123654	12/2009	Kimura	349/48	G09G 3/3233
2010/0201668	12/2009	Ko et al.	N/A	N/A
2010/0259512	12/2009	Lin	345/55	G09G 3/3688
2010/0289832	12/2009	Yamamoto et al.	N/A	N/A
2010/0327955	12/2009	Umezaki	N/A	N/A
2010/0328594	12/2009	Ishii	349/139	G09G 3/3688
2011/0115782	12/2010	Song	345/99	G02F 1/133345
2011/0157263	12/2010	Kim	345/698	G09G 3/3677
2011/0187694	12/2010	Umezaki	N/A	N/A
2012/0162183	12/2011	Kwon et al.	N/A	N/A
2015/0060682	12/2014	Weisfield	250/208.1	H10F 39/813
2016/0125829	12/2015	Jeon et al.	N/A	N/A
2016/0189129	12/2015	Yang et al.	N/A	N/A
2017/0018576	12/2016	Umezaki	N/A	N/A
2019/0295673	12/2018	Umezaki	N/A	N/A

2020/0203386	12/2019	Miyairi et al.	N/A	N/A
2021/0320128	12/2020	Umezaki et al.	N/A	N/A
2022/0146872	12/2021	Umezaki et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101303896	12/2007	CN	N/A
101483068	12/2008	CN	N/A
101567172	12/2008	CN	N/A
101568954	12/2008	CN	N/A
101609718	12/2008	CN	N/A
101620841	12/2009	CN	N/A
1895545	12/2007	EP	N/A
1906414	12/2007	EP	N/A
1959420	12/2007	EP	N/A
2226788	12/2009	EP	N/A
2226938	12/2009	EP	N/A
2357642	12/2010	EP	N/A
3223283	12/2016	EP	N/A
02-214817	12/1989	JP	N/A
02-253232	12/1989	JP	N/A
07-318902	12/1994	JP	N/A
2000-347628	12/1999	JP	N/A
2002-032048	12/2001	JP	N/A
2002-055660	12/2001	JP	N/A
2003-016794	12/2002	JP	N/A
2003-076346	12/2002	JP	N/A
2005-522734	12/2004	JP	N/A
2006-190437	12/2005	JP	N/A
2007-011336	12/2006	JP	N/A
2007-034321	12/2006	JP	N/A
2007-151092	12/2006	JP	N/A
2007-226233	12/2006	JP	N/A
2007-241028	12/2006	JP	N/A
2008-009393	12/2007	JP	N/A
2008-058939	12/2007	JP	N/A
2008-089915	12/2007	JP	N/A
2008-107807	12/2007	JP	N/A
2008-129289	12/2007	JP	N/A
2008-140490	12/2007	JP	N/A
2008-146079	12/2007	JP	N/A
2008-197643	12/2007	JP	N/A
2008-251094	12/2007	JP	N/A
4163416	12/2007	JP	N/A
2008-276849	12/2007	JP	N/A
2009-027265	12/2008	JP	N/A
2009-134845	12/2008	JP	N/A
2009-205706	12/2008	JP	N/A
2010-009738	12/2009	JP	N/A
2010-040074	12/2009	JP	N/A

2010-086640	12/2009	JP	N/A
2010-153828	12/2009	JP	N/A
2004-0022358	12/2003	KR	N/A
2006-0129881	12/2005	KR	N/A
2006-0134758	12/2005	KR	N/A
2009-0113080	12/2008	KR	N/A
2010-0027878	12/2009	KR	N/A
2010-0070627	12/2009	KR	N/A
2016-0083498	12/2015	KR	N/A
548465	12/2002	TW	N/A
200502912	12/2004	TW	N/A
200521913	12/2004	TW	N/A
200703182	12/2006	TW	N/A
200709150	12/2006	TW	N/A
200818089	12/2007	TW	N/A
200822038	12/2007	TW	N/A
200826051	12/2007	TW	N/A
200841144	12/2007	TW	N/A
200905436	12/2008	TW	N/A
200914964	12/2008	TW	N/A
200926125	12/2008	TW	N/A
201025236	12/2009	TW	N/A
WO-2003/087921	12/2002	WO	N/A
WO-2004/057561	12/2003	WO	N/A
WO-2005/114630	12/2004	WO	N/A
WO-2008/106049	12/2007	WO	N/A
WO-2009/084272	12/2008	WO	N/A
WO-2009/084280	12/2008	WO	N/A
WO-2010/058746	12/2009	WO	N/A
WO-2010/067641	12/2009	WO	N/A
WO-2010/150607	12/2009	WO	N/A

OTHER PUBLICATIONS

Chinese Office Action (Application No. 201110278110.0) Dated Mar. 23, 2015. cited by applicant
Taiwanese Office Action (Application No. 105142501) Dated Jul. 5, 2017. cited by applicant
Chinese Office Action (Application No. 201610335245.9) Dated Nov. 24, 2017. cited by applicant
Taiwanese Office Action (Application No. 109145808) Dated Mar. 30, 2021. cited by applicant

Primary Examiner: Leiby; Christopher E

Attorney, Agent or Firm: Fish & Richardson P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 18/212,752, filed Jun. 22, 2023, now allowed, which is a continuation of U.S. application Ser. No. 17/979,836, filed Nov. 3, 2022, now U.S. Pat. No. 11,688,358, which is a continuation of U.S. application Ser. No. 17/206,746, filed Mar. 19, 2021, now U.S. Pat. No. 11,501,728, which is a continuation of U.S. application Ser. No. 16/711,621, filed Dec. 12, 2019,

now U.S. Pat. No. 10,957,267, which is a continuation of U.S. application Ser. No. 16/421,661, filed May 24, 2019, now U.S. Pat. No. 10,510,310, which is a continuation of U.S. application Ser. No. 16/199,567, filed Nov. 26, 2018, now U.S. Pat. No. 10,304,402, which is a continuation of U.S. application Ser. No. 15/995,210, filed Jun. 1, 2018, now U.S. Pat. No. 10,140,942, which is a continuation of U.S. application Ser. No. 15/396,862, filed Jan. 3, 2017, now U.S. Pat. No. 9,990,894, which is a continuation of U.S. application Ser. No. 14/714,395, filed May 18, 2015, now U.S. Pat. No. 9,552,761, which is a continuation of U.S. application Ser. No. 13/225,856, filed Sep. 6, 2011, now U.S. Pat. No. 9,035,923, which claims the benefit of a foreign priority application filed in Japan as Serial No. 2010-201621 on Sep. 9, 2010, all of which are incorporated by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

(1) The technical field of the present invention relates to semiconductor devices including gate driver circuits.

2. Description of the Related Art

(2) An active-matrix display device includes a pixel portion which includes a plurality of pixels provided with elements functioning as switches (e.g., transistors) and a driver circuit which includes a source driver circuit and a gate driver circuit. The source driver circuit outputs a video signal to a pixel provided with an element functioning as a switch when the element is on. The gate driver circuit controls switching of the element functioning as a switch.

(3) The gate driver circuit is provided close to the pixel portion. In the case where the gate driver circuit is provided close to one side of the pixel portion, the region of the pixel portion might lean to one side of the display device. Thus, a display device which has a structure in which a gate driver circuit is separated into right and left in the pixel portion has been proposed.

(4) FIG. 58 illustrates the structure of a display device disclosed in Reference 1. In the display device illustrated in FIG. 58, a first gate driver circuit 5108 and a second gate driver circuit 5110 are symmetrically provided in right and left peripheral regions of a display region.

(5) The first gate driver circuit 5108 is provided in the left peripheral region of the display region. The first gate driver circuit 5108 includes a plurality of shift registers (SRC.sub.1 and SRC.sub.3 to SRC.sub.n+1) whose output terminals are connected to odd-numbered gate lines (GL.sub.1 and GL.sub.3 to GL.sub.n+1). The second gate driver circuit 5110 is provided in the right peripheral region of the display region. The second gate driver circuit 5110 includes a plurality of shift registers (SRC.sub.2, SRC.sub.4, . . . and SRC.sub.n) whose output terminals are connected to even-numbered gate lines (GL.sub.2, GL.sub.4, . . . and GL.sub.n).

(6) The first gate driver circuit 5108 controls an electrical connection between a source driver circuit 5112 and a pixel which is provided in an odd-numbered row in the pixel portion 5102. The second gate driver circuit 5110 controls an electrical connection between the source driver circuit 5112 and a pixel which is provided in an even-numbered row in the pixel portion 5102.

REFERENCE

(7) Reference 1: Japanese Published Patent Application No. 2003-076346

SUMMARY OF THE INVENTION

(8) As in the display device described with reference to FIG. 58, in a display device which has a structure in which a gate driver circuit is separated into right and left in a pixel portion, a signal is output from one of a first gate driver circuit and a second gate driver circuit to a gate line (also referred to as a gate signal line) in a period during which a gate line is selected (such a period is also referred to as a selection period). In addition, in a period during which a gate line is not selected (such a period is also referred to as a non-selection period), no signal is output from the first gate driver circuit and the second gate driver circuit to a gate line.

(9) It is an object of one embodiment of the present invention to provide a semiconductor device

- where delay or distortion of a signal output to a gate signal line in a selection period is reduced.
- (10) It is an object of one embodiment of the present invention to provide a semiconductor device where deterioration of transistors included in a first gate driver circuit and a second gate driver circuit is suppressed.
- (11) It is an object of one embodiment of the present invention to provide a semiconductor device where the rise time or fall time of the potential of a gate signal line is short.
- (12) One embodiment of the present invention is a semiconductor device which includes a gate signal line, a first gate driver circuit and a second gate driver circuit which output a selection signal and a non-selection signal to the gate signal line, and a plurality of pixels which are electrically connected to the gate signal line and supplied with the selection signal and the non-selection signal. In a period during which the gate signal line is selected, both the first gate driver circuit and the second gate driver circuit output the selection signal to the gate signal line. In a period during which the gate signal line is not selected, one of the first gate driver circuit and the second gate driver circuit outputs the non-selection signal to the gate signal line, and the other of the first gate driver circuit and the second gate driver circuit outputs neither the selection signal nor the non-selection signal to the gate signal line.
- (13) The first gate driver circuit and the second gate driver circuit may be provided with a pixel portion including the plurality of pixels provided therebetween.
- (14) The semiconductor device may include a source driver circuit for writing a video signal to a pixel corresponding to the gate signal line to which the selection signal is output.
- (15) In one embodiment of the present invention, it is possible to provide a semiconductor device where delay or distortion of a signal output to a gate signal line in a selection period is reduced.
- (16) In one embodiment of the present invention, it is possible to provide a semiconductor device where deterioration of transistors included in a first gate driver circuit and a second gate driver circuit is suppressed.
- (17) In one embodiment of the present invention, it is possible to provide a semiconductor device where the rise time or fall time of the potential of a gate signal line is short.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) In the accompanying drawings:
- (2) FIG. 1A illustrates a structure example of a semiconductor device, and FIG. 1B is a timing chart illustrating an operation example of a semiconductor device;
- (3) FIGS. 2A to 2C each illustrate an operation example of a semiconductor device;
- (4) FIGS. 3A to 3C each illustrate an operation example of a semiconductor device;
- (5) FIG. 4A illustrates a structure example of a gate driver circuit, and FIG. 4B illustrates an operation example of a gate driver circuit;
- (6) FIGS. 5A to 5I are schematic views corresponding to operation examples of a gate driver circuit;
- (7) FIGS. 6A to 6L are timing charts each illustrating an operation example of a gate driver circuit;
- (8) FIGS. 7A to 7L are timing charts each illustrating an operation example of a gate driver circuit;
- (9) FIGS. 8A to 8F are timing charts each illustrating an operation example of a gate driver circuit;
- (10) FIG. 9A illustrates a structure example of a gate driver circuit, and FIG. 9B illustrates an operation example of a gate driver circuit;
- (11) FIGS. 10A and 10B each illustrate a structure example of a gate driver circuit, and FIG. 10C illustrates an operation example of a gate driver circuit;
- (12) FIGS. 11A to 11C each illustrate a structure example of a gate driver circuit;
- (13) FIGS. 12A to 12H each illustrate an operation example of a gate driver circuit;

(14) FIGS. 13A to 13E each illustrate an operation example of a gate driver circuit;

(15) FIG. 14A illustrates a structure example of a gate driver circuit, and FIG. 14B illustrates an operation example of a gate driver circuit;

(16) FIGS. 15A to 15E each illustrate an operation example of a gate driver circuit;

(17) FIGS. 16A and 16B each illustrate an example of a circuit diagram of a semiconductor device;

(18) FIG. 17 is a timing chart illustrating an operation example of a semiconductor device;

(19) FIGS. 18A and 18B each illustrate an operation example of a semiconductor device;

(20) FIGS. 19A and 19B each illustrate an operation example of a semiconductor device;

(21) FIGS. 20A and 20B each illustrate an operation example of a semiconductor device;

(22) FIGS. 21A and 21B each illustrate an operation example of a semiconductor device;

(23) FIG. 22 is a timing chart illustrating an operation example of a semiconductor device;

(24) FIG. 23 is a timing chart illustrating an operation example of a semiconductor device;

(25) FIGS. 24A and 24B each illustrate an example of a circuit diagram of a semiconductor device;

(26) FIGS. 25A and 25B each illustrate an example of a circuit diagram of a semiconductor device;

(27) FIG. 26 illustrates an example of a circuit diagram of a semiconductor device;

(28) FIG. 27 is a timing chart illustrating an operation example of a semiconductor device;

(29) FIGS. 28A and 28B each illustrate an operation example of a semiconductor device;

(30) FIGS. 29A and 29B each illustrate an operation example of a semiconductor device;

(31) FIG. 30 is a timing chart illustrating an operation example of a semiconductor device;

(32) FIGS. 31A and 31B each illustrate an example of a circuit diagram of a semiconductor device;

(33) FIGS. 32A and 32B each illustrate an operation example of a semiconductor device;

(34) FIGS. 33A and 33B each illustrate an operation example of a semiconductor device;

(35) FIGS. 34A and 34B each illustrate an operation example of a semiconductor device;

(36) FIGS. 35A and 35B each illustrate an operation example of a semiconductor device;

(37) FIGS. 36A and 36B each illustrate an example of a circuit diagram of a semiconductor device;

(38) FIGS. 37A and 37B each illustrate an example of a circuit diagram of a semiconductor device;

(39) FIGS. 38A and 38B each illustrate an example of a circuit diagram of a semiconductor device;

(40) FIGS. 39A to 39F each illustrate an example of a circuit diagram of a semiconductor device;

(41) FIGS. 40A to 40D each illustrate an example of a circuit diagram of a semiconductor device;

(42) FIGS. 41A and 41B each illustrate an example of a circuit diagram of a semiconductor device;

(43) FIGS. 42A and 42B each illustrate an operation example of a semiconductor device;

(44) FIGS. 43A and 43B each illustrate an operation example of a semiconductor device;

(45) FIGS. 44A and 44B each illustrate an operation example of a semiconductor device;

(46) FIGS. 45A and 45B each illustrate an operation example of a semiconductor device;

(47) FIGS. 46A to 46D each illustrate a structure example of a display device, and FIG. 46E illustrates a structure example of a pixel;

(48) FIG. 47 illustrates an example of a circuit diagram of a shift register;

(49) FIG. 48 illustrates an example of a circuit diagram of a shift register;

(50) FIG. 49 is a timing chart illustrating an operation example of a shift register;

(51) FIGS. 50A, 50C, and 50D each illustrate a structure example of a source driver circuit, and

(52) FIG. 50B is a timing chart illustrating an operation example of a source driver circuit;

(53) FIGS. 51A to 51G each illustrate an example of a circuit diagram of a protection circuit;

(54) FIGS. 52A and 52B each illustrate a structure example of a semiconductor device including a protection circuit;

(55) FIGS. 53A and 53B each illustrate a structure example of a display device, and FIG. 53C illustrates a structure example of a transistor;

(56) FIGS. 54A to 54C each illustrate a structure example of a display device;

(57) FIG. 55 is a layout diagram of a semiconductor device;

(58) FIGS. 56A to 56H each illustrate an example of an electronic device;

(59) FIGS. 57A to 57D each illustrate an example of an electronic device, and FIGS. 57E to 57H

each illustrate an application of a semiconductor device;

(60) FIG. 58 illustrates a structure example of a display device;

(61) FIG. 59 is a circuit diagram of a semiconductor device which is a comparison example;

(62) FIGS. 60A and 60B each illustrate a calculation result by circuit simulation; and

(63) FIG. 61 illustrates a calculation result by circuit simulation.

DETAILED DESCRIPTION OF THE INVENTION

(64) Examples of embodiments of the present invention will be described below with reference to the drawings. Note that the present invention is not limited to the following description. It will be readily appreciated by those skilled in the art that modes and details of the present invention can be modified in various ways without departing from the spirit and scope of the present invention. The present invention therefore should not be construed as being limited to the following description of the embodiments. Note that in description with reference to the drawings, reference numerals denoting the same portions are used in common in different drawings in some cases. Further, in some cases, the same hatching patterns are applied to similar portions, and the similar portions are not necessarily denoted by reference numerals in different drawings.

(65) Note that the contents of the embodiments can be combined with each other as appropriate. In addition, the contents of the embodiments can be replaced with each other as appropriate.

(66) Further, in this specification, the term “k-th” (k is a natural number) is used in order to avoid confusion among components and do not limit the number of components.

(67) The term “voltage” generally means a difference between potentials at two points (also referred to as a potential difference). However, in an electronic circuit, in a circuit diagram or the like, a difference between a potential at one point and a potential serving as a reference (also referred to as a reference potential) is used in some cases. Further, in some cases, volt (V) is used as the units of voltage and a potential. Thus, in this specification, a difference between a potential at one point and a reference potential is used as the voltage of the point in some cases unless otherwise specified.

(68) Note that in this specification, a transistor has at least three terminals (a source, a drain, and a gate) and has a structure in which the potential of one terminal controls conduction between the other two terminals. Further, the source and the drain of the transistor might be interchanged with each other depending on the structure, operating condition, or the like of the transistor.

(69) A source is part of or the whole of a source electrode, or part of or the whole of a source wiring. A conductive layer functioning as both a source electrode and a source wiring is referred to as a source in some cases without distinction between a source electrode and a source wiring. A drain is part of or the whole of a drain electrode, or part of or the whole of a drain wiring. A conductive layer functioning as both a drain electrode and a drain wiring is referred to as a drain in some cases without distinction between a drain electrode and a drain wiring. A gate is part or the whole of a gate electrode, or part or the whole of a gate wiring. A conductive layer functioning as both a gate electrode and a gate wiring is referred to as a gate in some cases without distinction between a gate electrode and a gate wiring.

(70) Note that in this specification, description that “A and B are connected” indicates the case where A and B are electrically connected in addition to the case where A and B are directly connected. Specifically, the description that “A and B are connected” indicates the case where it is acceptable that A and B have the same nodes considering circuit operation, e.g., the case where A and B are connected through an element functioning as a switch, such as a transistor, and A and B have substantially the same potentials when the element is on, the case where A and B are connected through a resistor and a potential difference generated at opposite ends of the resistor does not affect the operation of a circuit including A and B, or the like.

(71) Note that in this specification, the term “substantially” is used in consideration of various kinds of errors such as an error due to noise, an error due to process variation, an error due to variation in steps of manufacturing an element, or a measurement error.

(72) Note that in this specification, the potential of an L-level signal (also referred to as an L signal) is denoted by **V1**, and the potential of an H-level signal (also referred to as an H signal) is denoted by **V2** (**V2**>**V1**). In addition, in the case where the description “the potential of an L-level signal”, “an L-level potential”, or “voltage **V1**” is used, the potential is substantially **V1**. In the case where the description “the potential of an H-level signal”, “an H-level potential”, or “voltage **V2**” is used, the potential is substantially **V2**.

Embodiment 1

(73) In this embodiment, semiconductor devices including gate driver circuits (also referred to as gate drivers) are described with reference to FIGS. 1A and 1B, FIGS. 2A to 2C, and FIGS. 3A to 3C.

(74) FIG. 1A illustrates a structure example of a semiconductor device including a gate driver circuit. FIG. 1B is a timing chart illustrating an operation example of the semiconductor device. Note that the semiconductor device may include a source driver circuit (also referred to as a source driver), a control circuit, or the like in addition to the gate driver circuit.

(75) In FIG. 1A, the semiconductor device includes a pixel portion **50**, a first gate driver circuit **51**, a second gate driver circuit **52**, and a gate line **54** (also referred to as a gate signal line) connected to the first gate driver circuit **51** and the second gate driver circuit **52**. In FIG. 1A, gate lines G.sub.i to G.sub.i+2 (i is any one of 1 to (m-2)) are illustrated among a plurality of gate lines G.sub.1 to G.sub.m (m is a natural number) included in the semiconductor device.

(76) In the case where the gate line **54** is selected, H signals are input to the gate line **54** from the gate driver circuit **51** and the gate driver circuit **52**. When H signals are input from both the gate driver circuit **51** and the gate driver circuit **52** in this manner, the rise time or fall time of the potential of the gate line **54** can be shortened and delay or distortion of signals output to the gate line **54** can be reduced.

(77) In contrast, in the case where the gate line **54** is not selected, an L signal is output to the gate line **54** from one of the gate driver circuit **51** and the gate driver circuit **52** and no signal is output to the gate line **54** from the other of the gate driver circuit **51** and the gate driver circuit **52**. Thus, some of or all of the transistors included in the other gate driver circuit can be turned off.

(78) Next, an operation example of the semiconductor device illustrated in FIG. 1A is described below. FIGS. 2A to 2C illustrate an operation example of the semiconductor device in a k-th frame. FIGS. 3A to 3C illustrate an operation example of the semiconductor device in a (k+1)th frame.

(79) Note that in FIGS. 2A to 2C and FIGS. 3A to 3C, each arrow indicates that the gate driver circuit (the first gate driver circuit **51** or the second gate driver circuit **52**) outputs a signal to the gate line **54**, and each cross indicates that the gate driver circuit outputs no signal to the gate line **54**.

(80) Here, the direction of each arrow is used properly depending on the kind of a signal output to the gate line **54** from the gate driver circuit. In the case where the gate driver circuit outputs a signal (e.g., a non-selection signal) to the gate line **54**, the direction of each arrow is a direction from the gate line **54** to the gate driver circuit. In the case where the gate driver circuit outputs a signal (e.g., a selection signal) which is different from the above signal (e.g., a non-selection signal) to the gate line **54**, the direction of each arrow is a direction from the gate driver circuit to the gate line **54**.

(81) In the case where the gate line G.sub.i is selected and the gate lines G.sub.i+1 and G.sub.i+2 are not selected in the k-th frame as illustrated in FIG. 2A (corresponding a period k.sub.i in FIG. 1B), H signals are output to the gate line G.sub.i from the gate driver circuit **51** and the gate driver circuit **52**. In addition, L signals are output to the gate lines G.sub.i+1 and G.sub.i+2 from the gate driver circuit **51**, and no signal is output to the gate lines G.sub.i+1 and G.sub.i+2 from the gate driver circuit **52**. Thus, some of or all of the transistors included in the gate driver circuit **52** can be turned off.

(82) Then, in the case where the gate line G.sub.i is selected and the gate lines G.sub.i+1 and

G.sub.i+2 are not selected in the (k+1)th frame as illustrated in FIG. 3A (corresponding a period k+1_.sub.i in FIG. 1B), H signals are output to the gate line G.sub.i from the gate driver circuit 51 and the gate driver circuit 52. In addition, no signal is output to the gate lines G.sub.i+1 and G.sub.i+2 from the gate driver circuit 51, and L signals are output to the gate lines G.sub.i+1 and G.sub.i+2 from the gate driver circuit 52. Thus, some of or all of the transistors included in the gate driver circuit 51 can be turned off.

(83) Similarly, in the case where the gate line G.sub.i+1 is selected and the gate lines G.sub.i and G.sub.i+2 are not selected in the k-th frame as illustrated in FIG. 2B, H signals are output to the gate line G.sub.i+1 from the gate driver circuit 51 and the gate driver circuit 52. In addition, L signals are output to the gate lines G.sub.i and G.sub.i+2 from the gate driver circuit 51, and no signal is output to the gate lines G.sub.i and G.sub.i+2 from the gate driver circuit 52. Thus, some of or all of the transistors included in the gate driver circuit 52 can be turned off.

(84) Then, in the case where the gate line G.sub.i+1 is selected and the gate lines G.sub.i and G.sub.i+2 are not selected in the (k+1)th frame as illustrated in FIG. 3B, H signals are output to the gate line G.sub.i+1 from the gate driver circuit 51 and the gate driver circuit 52. In addition, no signal is output to the gate lines G.sub.i and G.sub.i+2 from the gate driver circuit 51, and L signals are output to the gate lines G.sub.i and G.sub.i+2 from the gate driver circuit 52. Thus, some of or all of the transistors included in the gate driver circuit 51 can be turned off.

(85) Similarly, in the case where the gate line G.sub.i+2 is selected and the gate lines G.sub.i and G.sub.i+1 are not selected in the k-th frame as illustrated in FIG. 2C, H signals are output to the gate line G.sub.i+2 from the gate driver circuit 51 and the gate driver circuit 52. In addition, L signals are output to the gate lines G.sub.i and G.sub.i+1 from the gate driver circuit 51, and no signal is output to the gate lines G.sub.i and G.sub.i+1 from the gate driver circuit 52. Thus, some of or all of the transistors included in the gate driver circuit 52 can be turned off.

(86) Then, in the case where the gate line G.sub.i+2 is selected and the gate lines G.sub.i and G.sub.i+1 are not selected in the (k+1)th frame as illustrated in FIG. 3C, H signals are output to the gate line G.sub.i+2 from the gate driver circuit 51 and the gate driver circuit 52. In addition, no signal is output to the gate lines G.sub.i and G.sub.i+1 from the gate driver circuit 51, and L signals are output to the gate lines G and G.sub.i+1 from the gate driver circuit 52. Thus, some of or all of the transistors included in the gate driver circuit 51 can be turned off.

(87) Since no signal is output to the gate line 54 which is not selected from one of the gate driver circuit 51 and the gate driver circuit 52 in this manner, some of or all of the transistors included in the one of the gate driver circuits can be turned off. Accordingly, deterioration of the transistors can be suppressed.

Embodiment 2

(88) In this embodiment, the structure and operation of a gate driver circuit are described.

(89) <Structure of Gate Driver Circuit>

(90) The structure of a gate driver circuit is described with reference to FIG. 4A.

(91) FIG. 4A illustrates a structure example of a gate driver circuit. The gate driver circuit includes a circuit 10A and a circuit 10B. Note that although FIG. 4A illustrates the case where the gate driver circuit includes the two circuits 10A and 10B, the gate driver circuit may include three or more circuits including the circuits 10A and 10B.

(92) The circuit 10A and the circuit 10B are connected to a wiring 11.

(93) A signal is input to the wiring 11 from the circuit 10A or the circuit 10B, and the wiring 11 functions as a signal line. Note that a signal may be input to the wiring 11 from a circuit which is different from the circuit 10A and the circuit 10B.

(94) Note that in the case where the gate driver circuit in FIG. 4A is used for a display device including a pixel portion, the wiring 11 extends to the pixel portion and is connected to a gate of a transistor in a pixel included in the pixel portion (e.g., a switching transistor or a selection transistor). In that case, the wiring 11 functions as a gate line (also referred to as a gate signal line),

a scan line, or a power supply line.

(95) Alternatively, fixed voltage is applied to the wiring **11** from the circuit **10A** or the circuit **10B**, and the wiring **11** functions as a power supply line. Note that voltage may be applied to the wiring **11** from a circuit which is different from the circuit **10A** and the circuit **10B**.

(96) Next, the functions of the circuit **10A** and the circuit **10B** are described.

(97) The circuit **10A** has a function of controlling the timing of outputting a signal (e.g., a selection signal or a non-selection signal) to the wiring **11**. Alternatively, the circuit **10A** has a function of controlling the timing of outputting no signal to the wiring **11**. Alternatively, the circuit **10A** has a function of outputting a signal (e.g., a non-selection signal) to the wiring **11** in a certain period and outputting a different signal (e.g., a selection signal) to the wiring **11** in a different period. Alternatively, the circuit **10A** has a function of outputting a signal (e.g., a selection signal or a non-selection signal) to the wiring **11** in a certain period and outputting no signal to the wiring **11** in a different period.

(98) As described above, the circuit **10A** functions as a driver circuit or a control circuit. Note that the circuit **10A** may output a different signal to the wiring **11**. In that case, the circuit **10A** can output three or more kinds of signals to the wiring **11**.

(99) The circuit **10B** has a function of controlling the timing of outputting a signal (e.g., a selection signal or a non-selection signal) to the wiring **11**. Alternatively, the circuit **10B** has a function of controlling the timing of outputting no signal to the wiring **11**. Alternatively, the circuit **10B** has a function of outputting a signal (e.g., a non-selection signal) to the wiring **11** in a certain period and outputting a different signal (e.g., a selection signal) to the wiring **11** in a different period. Alternatively, the circuit **10B** has a function of outputting a signal (e.g., a selection signal or a non-selection signal) to the wiring **11** in a certain period and outputting no signal to the wiring **11** in a different period.

(100) As described above, the circuit **10B** functions as a driver circuit or a control circuit. Note that the circuit **10B** may output a different signal to the wiring **11**. In that case, the circuit **10B** can output three or more kinds of signals to the wiring **11**.

(101) <Operation of Gate Driver Circuit>

(102) The operation of the gate driver circuit in FIG. **4A** is described with reference to FIG. **4B** and FIGS. **5A** to **5I**.

(103) FIG. **4B** illustrates an operation example of the gate driver circuit. FIG. **4B** illustrates an output signal OUTA of the circuit **10A** and an output signal OUTB of the circuit **10B** in each operation of the gate driver circuit. FIGS. **5A** to **5I** are schematic views corresponding to operation examples of the gate driver circuit in FIG. **4A**.

(104) Note that the gate driver circuit in FIG. **4A** can perform nine operations illustrated in FIG. **4B** by an appropriate combination of the case where both the circuit **10A** and the circuit **10B** output signals (e.g., non-selection signals) to the wiring **11**, the case where both the circuit **10A** and the circuit **10B** output signals which are different from the signals (e.g., selection signals) to the wiring **11**, and the case where both the circuit **10A** and the circuit **10B** output no signal (e.g., neither a non-selection signal nor a selection signal) to the wiring **11**.

(105) In this embodiment, the nine operations are described. Note that the gate driver circuit in FIG. **4A** does not necessarily perform all the nine operations, and can selectively perform some of the nine operations. In addition, the driver circuit in FIG. **4A** may perform an operation which is different from the nine operations.

(106) Note that in FIG. **4B**, a circle indicates that the circuit (the circuit **10A** or the circuit **10B**) outputs a signal (e.g., a non-selection signal) to the wiring **11**. A double circle indicates that the circuit outputs a signal which is different from the signal (e.g., a selection signal) to the wiring **11**. A cross indicates that the circuit outputs no signal (e.g., neither a non-selection signal nor a selection signal) to the wiring **11**.

(107) Note that in the schematic views in FIGS. **5A** to **5I**, each arrow indicates that the circuit (the

circuit **10A** or the circuit **10B**) outputs a signal to the wiring **11**, and each cross indicates that the circuit outputs no signal to the wiring **11**. Here, the direction of each arrow is used properly depending on the kind of a signal output to the wiring **11** from the circuit. In the case where the circuit outputs a signal (e.g., a non-selection signal) to the wiring **11**, the direction of each arrow is a direction from the wiring **11** to the circuit. In the case where the circuit outputs a signal (e.g., a selection signal) which is different from the above signal (e.g., a non-selection signal) to the wiring **11**, the direction of each arrow is a direction from the circuit to the wiring **11**.

(108) Note that in the schematic views in FIGS. 5A to 5I, the direction of each arrow does not indicate the direction of current and generation of current but indicates that the circuit (the circuit **10A** or the circuit **10B**) outputs a signal to the wiring **11**. The direction of current is determined by the potential of the wiring **11**. When the potential of a signal output from the circuit is substantially equal to the potential of the wiring **11**, current is not generated or the amount of current is extremely small in some cases.

(109) An operation example of the gate driver circuit in FIG. 4A is described below.

(110) In an operation **1** in FIG. 5A, the circuit **10A** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuit **10B** outputs a signal (e.g., a non-selection signal) to the wiring **11**. In an operation **2** in FIG. 5B, the circuit **10A** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuit **10B** outputs no signal to the wiring **11**. In an operation **3** in FIG. 5C, the circuit **10A** outputs no signal to the wiring **11**, and the circuit **10B** outputs a signal (e.g., a non-selection signal) to the wiring **11**. In an operation **4** in FIG. 5D, the circuit **10A** outputs no signal to the wiring **11**, and the circuit **10B** outputs no signal to the wiring **11**.

(111) In an operation **5** in FIG. 5E, the circuit **10A** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuit **10B** outputs a different signal (e.g., a selection signal) to the wiring **11**. In an operation **6** in FIG. 5F, the circuit **10A** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuit **10B** outputs no signal to the wiring **11**. In an operation **7** in FIG. 5G, the circuit **10A** outputs no signal to the wiring **11**, and the circuit **10B** outputs a different signal (e.g., a selection signal) to the wiring **11**. In an operation **8** in FIG. 5H, the circuit **10A** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuit **10B** outputs a different signal (e.g., a selection signal) to the wiring **11**. In an operation **9** in FIG. 5I, the circuit **10A** outputs a different signal (e.g., a non-selection signal) to the wiring **11**, and the circuit **10B** outputs a signal (e.g., a non-selection signal) to the wiring **11**.

(112) As described above, the gate driver circuit in FIG. 4A can perform a variety of operations. Then, the advantage of each operation is described.

(113) In the operation **1** and the operation **5**, when the circuit **10A** and the circuit **10B** output the same signal to the wiring **11**, noise is not easily generated in the potential of the wiring **11**, so that the potential of the wiring **11** can be stabilized. For example, a signal that should not be originally written (e.g., a video signal input to a pixel in a different row) can be prevented from being written to a pixel connected to the wiring **11**. Alternatively, the potential of a video signal held in the pixel connected to the wiring **11** can be prevented from being changed. Accordingly, the display quality of a display device can be improved.

(114) In the operation **1** and the operation **5**, when the circuit **10A** and the circuit **10B** output the same signal to the wiring **11**, a change in potential of the wiring **11** can be made steep (e.g., the rise time or fall time of the potential of the wiring **11** can be shortened). Thus, distortion in the potential of the wiring **11** can be reduced. For example, a signal that should not be originally written (e.g., a video signal input to a pixel in the preceding row) can be prevented from being written to the pixel connected to the wiring **11**. Accordingly, crosstalk can be reduced. Thus, the display quality of the display device can be improved.

(115) In the operation **8** and the operation **9**, when the circuit **10A** and the circuit **10B** output different signals (e.g., a selection signal and a non-selection signal) to the wiring **11**, the potential of the wiring **11** can be a potential which is between the potential of the signal output from the

circuit **10A** and the potential of the signal output from the circuit **10B**. Thus, the potential of the wiring **11** can be controlled with high accuracy.

(116) In the operations **2, 3, 6** and **7**, when one of the circuit **10A** and the circuit **10B** outputs a signal to the wiring **11**, the other of the circuit **10A** and the circuit **10B** outputs no signal. Thus, transistors included in the circuit which outputs no signal can be turned off. Accordingly, deterioration of the transistors can be suppressed.

(117) In the operation **4**, the circuit **10A** and the circuit **10B** output no signal to the wiring **11**; thus, transistors included in the circuit **10A** and the circuit **10B** can be turned off. Accordingly, deterioration of the transistors can be suppressed.

(118) Since deterioration of the transistors can be suppressed in the operations **2, 3, 4, 6**, and **7** as described above, a material which easily deteriorates, such as a non-single-crystal semiconductor (e.g., an amorphous semiconductor or a microcrystalline semiconductor), an organic semiconductor, or an oxide semiconductor, can be used as a semiconductor layer of the transistor. Thus, when a semiconductor device is manufactured, the number of steps can be reduced, yield can be increased, or cost can be reduced. In addition, since a method for manufacturing a semiconductor device is facilitated, the size of the display device can be increased.

(119) Since deterioration of the transistors can be suppressed in the operations **2, 3, 4, 6**, and **7**, it is not necessary to increase the channel width of the transistor in consideration of deterioration of the transistor. Thus, the channel width of the transistor can be decreased, so that the layout area can be decreased. In particular, in the case where the gate driver circuit in this embodiment is used for the display device, the layout area of the gate driver circuit can be decreased; thus, the resolution of the pixel can be increased.

(120) In addition, since the channel width of the transistor can be decreased in the operations **2, 3, 4, 6**, and **7** as described above, the load of the gate driver circuit can be decreased. Thus, the current supply capability of a circuit (e.g., an external circuit) for supplying a signal or the like to the gate driver circuit in this embodiment can be decreased. Consequently, the size of the circuit for supplying the signal or the like can be decreased or the number of IC chips used for the circuit for supplying the signal or the like can be reduced. Further, since the load of the gate driver circuit can be decreased, the power consumption of the gate driver circuit can be reduced.

(121) Next, timing charts at the time when the operation of the gate driver circuit in FIG. **4A** is a combination of some of the operations **1** to **9** illustrated in FIGS. **5A** to **5I** are described below.

(122) Here, a timing chart illustrating the operation of the gate driver circuit in FIG. **4A** includes a plurality of periods. In each period or a transition period from a certain period to a different period, the gate driver circuit in FIG. **4A** can perform any of the operations **1** to **9** illustrated in FIGS. **5A** to **5I**. The gate driver circuit in FIG. **4A** may perform operation which is different from the operations **1** to **9** illustrated in FIGS. **5A** to **5I**.

(123) FIGS. **6A** to **6L** are timing charts each illustrating an operation example of the gate driver circuit. In the timing charts in FIGS. **6A** to **6L**, a period a, a period b, and a period c are sequentially provided and a period d is provided. Note that although the periods a to d are sequentially provided in FIGS. **6A** to **6L**, the order of the periods a to d is not limited to this. In addition, the timing charts may include a period which is different from the periods a to d.

(124) In the timing charts in FIGS. **6A** to **6L**, each solid line indicates that the circuit (the circuit **10A** or the circuit **10B**) outputs a signal to the wiring **11**, and a dotted line indicates that the circuit outputs no signal to the wiring **11**.

(125) The operation of the gate driver circuit in FIG. **4A** in the period a, a transition period from the period a to the period b, the period b, a transition period from the period b to the period c, the period c, and the period d is described with reference to the timing chart illustrated in FIG. **6A**.

(126) In the period a, the transition period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. **4A** performs the operation **2** in FIG. **5B**. In other words, in the period a, the transition period from the period b to the period c, the period c, and the period d,

the circuit **10A** outputs a signal (e.g., a non-selection signal) to the wiring **11** and the circuit **10B** outputs no signal to the wiring **11**.

(127) In the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. **4A** performs the operation **6** in FIG. **5F**. In other words, in the transition period from the period a to the period b and the period b, the circuit **10A** outputs a different signal (e.g., a selection signal) to the wiring **11** and the circuit **10B** outputs no signal to the wiring **11**.

(128) In this manner, in the period a, the transition period from the period a to the period b, the period b, the transition period from the period b to the period c, the period c, and the period d, the circuit **10B** outputs no signal to the wiring **11**. Thus, deterioration of the transistors included in the circuit **10B** can be suppressed. Further, by simple circuit design such as provision of a switch for outputting no signal or turning off a transistor in the circuit **10B**, the power consumption of the circuit **10B** can be reduced.

(129) Note that in the timing chart illustrated in FIG. **6A**, the circuit **10A** does not need to output a signal to the wiring **11** at least one of the periods in the period a, the transition period from the period a to the period b, the period b, the transition period from the period b to the period c, the period c, and the period d.

(130) As illustrated in FIG. **6B**, the circuit **10B** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b. Thus, the change in potential of the wiring **11** can be made steep.

(131) As illustrated in FIG. **6C**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b. Thus, the change in potential of the wiring **11** can be made steep.

(132) As illustrated in FIG. **6D**, the circuit **10B** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(133) As illustrated in FIG. **6E**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(134) As illustrated in FIG. **6F**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c. Thus, the change in potential of the wiring **11** can be made steep.

(135) As illustrated in FIG. **6G**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the period b. Thus, the change in potential of the wiring **11** can be made steep.

(136) As illustrated in FIG. **6H**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and the period c. Thus, the change in potential of the wiring **11** can be made steep.

(137) As illustrated in FIG. **6I**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the period b. Thus, the change in potential of the wiring **11** can be made steep.

(138) As illustrated in FIG. **6J**, the circuit **10B** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c. Thus, the change in potential of the wiring **11** can be made steep.

(139) As illustrated in FIG. **6K**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and the transition period from the period b to the period c and may

output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(140) As illustrated in FIG. **6L**, the circuit **10B** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a, the transition period from the period b to the period c, and the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(141) Note that in the above description, the selection signal and the non-selection signal are examples of signals output from the circuit **10A** and the circuit **10B** and may be any signals as long as they are different from each other.

(142) Next, timing charts at the time when the operation of the gate driver circuit in FIG. **4A** is a combination of some of the operations **1** to **9** illustrated in FIGS. **5A** to **5I** that are different from the timing charts in FIGS. **6A** to **6L** are described below.

(143) FIGS. **7A** to **7L** are timing charts each illustrating an operation example of the gate driver circuit.

(144) The operation of the gate driver circuit in FIG. **4A** in the period a, a transition period from the period a to the period b, the period b, a transition period from the period b to the period c, the period c, and the period d is described with reference to the timing chart illustrated in FIG. **7A**.

(145) In the period a, the transition period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. **4A** performs the operation **3** in FIG. **5C**. In other words, in the period a, the transition period from the period b to the period c, the period c, and the period d, the circuit **10A** outputs no signal to the wiring **11** and the circuit **10B** outputs a signal (e.g., a non-selection signal) to the wiring **11**.

(146) In the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. **4A** performs the operation **7** in FIG. **5G**. In other words, in the transition period from the period a to the period b and the period b, the circuit **10A** outputs no signal to the wiring **11** and the circuit **10B** outputs a different signal (e.g., a selection signal) to the wiring **11**.

(147) In this manner, in the period a, the transition period from the period a to the period b, the period b, the transition period from the period b to the period c, the period c, and the period d, the circuit **10A** outputs no signal to the wiring **11**. Thus, deterioration of the transistors included in the circuit **10A** can be suppressed. Further, by simple circuit design such as provision of a switch for outputting no signal or turning off a transistor in the circuit **10A**, the power consumption of the circuit **10A** can be reduced.

(148) Note that in the timing chart illustrated in FIG. **7A**, the circuit **10B** does not need to output a signal to the wiring **11** at least one of the periods in the period a, the transition period from the period a to the period b, the period b, the transition period from the period b to the period c, the period c, and the period d.

(149) As illustrated in FIG. **7B**, the circuit **10A** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b. Thus, the change in potential of the wiring **11** can be made steep.

(150) As illustrated in FIG. **7C**, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b. Thus, the change in potential of the wiring **11** can be made steep.

(151) As illustrated in FIG. **7D**, the circuit **10A** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(152) As illustrated in FIG. **7E**, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and may output a different signal (e.g., a selection signal) to the wiring

11 in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(153) As illustrated in FIG. 7F, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c. Thus, the change in potential of the wiring **11** can be made steep.

(154) As illustrated in FIG. 7G, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the period b. Thus, the change in potential of the wiring **11** can be made steep.

(155) As illustrated in FIG. 7H, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and the period c. Thus, the change in potential of the wiring **11** can be made steep.

(156) As illustrated in FIG. 7I, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c and the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the period b. Thus, the change in potential of the wiring **11** can be made steep.

(157) As illustrated in FIG. 7J, the circuit **10A** may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and may output a signal (e.g., a non-selection signal) to the wiring **11** in the transition period from the period b to the period c. Thus, the change in potential of the wiring **11** can be made steep.

(158) As illustrated in FIG. 7K, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a and the transition period from the period b to the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(159) As illustrated in FIG. 7L, the circuit **10A** may output a signal (e.g., a non-selection signal) to the wiring **11** in the period a, the transition period from the period b to the period c, and the period c and may output a different signal (e.g., a selection signal) to the wiring **11** in the transition period from the period a to the period b and the period b. Thus, the change in potential of the wiring **11** can be made steep.

(160) Note that in the above description, the selection signal and the non-selection signal are examples of signals output from the circuit **10A** and the circuit **10B** and may be any signals as long as they are different from each other.

(161) Next, timing charts at the time when the operation of the gate driver circuit in FIG. 4A is a combination of some of the operations **1** to **9** illustrated in FIGS. 5A to 5I that are different from the timing charts in FIGS. 6A to 6L and FIGS. 7A to 7L are described below.

(162) FIGS. 8A to 8E are timing charts each illustrating an operation example of the gate driver circuit.

(163) The timing charts in FIGS. 8A to 8C include a period **T1** and a period **T2**. In addition, in FIGS. 8A and 8C, the period **T1** and the period **T2** are alternated; however, as illustrated in FIG. 8B, the plurality of periods **T1** and the plurality of periods **T2** may be alternated. Further, a period which is different from the period **T1** and the period **T2** may be provided.

(164) The operation of the gate driver circuit in FIG. 4A in the period **T1** and the period **T2** is described with reference to the timing chart in FIG. 8A.

(165) In the period **T1**, the timing chart illustrated in FIG. 6A is used. Thus, in the period **T1**, deterioration of the transistors included in the circuit **10B** can be suppressed. Further, in the period **T2**, the timing chart illustrated in FIG. 7A is used. Thus, in the period **T2**, deterioration of the transistors included in the circuit **10A** can be suppressed.

(166) In this manner, in FIG. 8A, the period **T1** in which deterioration of the transistors included in the circuit **10B** can be suppressed and the period **T2** in which deterioration of the transistors

included in the circuit **10A** can be suppressed are alternated.

(167) Here, in the case where the circuit **10A** and the circuit **10B** have similar structures, the degree of deterioration of the transistors included in the circuit **10A** and the degree of deterioration of the transistors included in the circuit **10B** can be substantially equal when the length of the period **T1** and the length of the period **T2** are made substantially equal. Thus, even when the operation of the circuit **10A** and the operation of the circuit **10B** are switched by alternate provision of the period **T1** and the period **T2**, the change in potential of the wiring **11** can be made substantially equal.

(168) Consequently, in the case where the gate driver circuit in FIG. **4A** is used for a display device including a pixel for holding a video signal and the video signal is changed by the potential of the wiring **11** (e.g., feedthrough or capacitive coupling), even when the operation of the circuit **10A** and the operation of the circuit **10B** are switched, a change in video signal held in the a pixel connected to the wiring **11** can be made substantially equal. Thus, the luminance, transmittance, or the like of the pixel can be made substantially equal between the circuit **10A** and the circuit **10B**. Accordingly, display quality can be improved.

(169) In the period **T1**, any of the timing charts illustrated in FIGS. **6A** to **6L** may be used, and in the period **T2**, any of the timing charts illustrated in FIGS. **7A** to **7L** may be used. For example, as illustrated in FIG. **8C**, in the period **T1**, the timing chart in FIG. **6K** may be used, and in the period **T2**, the timing chart in FIG. **7K** may be used.

(170) Next, a timing chart illustrating an operation example of the gate driver circuit in FIG. **4A** in the period **d** illustrated in FIGS. **6A** to **6L**, FIGS. **7A** to **7L**, and FIGS. **8A** and **8C** is described with reference to FIG. **8D**.

(171) FIG. **8D** is a timing chart illustrating an operation example of the gate driver circuit in the period **d**.

(172) In the timing charts illustrated in FIGS. **6A** to **6L**, FIGS. **7A** to **7L**, and FIGS. **8A** and **8C**, the period **d** is divided into a plurality of periods. For example, as illustrated in FIG. **8D**, the period **d** is divided into two periods **d1** and **d2**. Note that the number of division of the period **d** is not limited to this, and the period **d** may be divided into three or more periods. In addition, in FIG. **8D**, the period **d1** and the period **d2** are alternated; however, the plurality of periods **d1** and the plurality of periods **d2** may be alternated.

(173) The operation of the gate driver circuit in FIG. **4A** in the period **d1** and the period **d2** is described with reference to the timing chart in FIG. **8D**.

(174) In the period **d1**, the gate driver circuit performs the operation **2** in FIG. **5B**. In other words, in the period **d1**, the circuit **10A** outputs a signal to the wiring **11** and the circuit **10B** outputs no signal to the wiring **11**. In the period **d2**, the gate driver circuit performs the operation **3** in FIG. **5C**. In other words, in the period **d2**, the circuit **10A** outputs no signal to the wiring **11** and the circuit **10B** outputs a signal to the wiring **11**.

(175) Since signals can be input to gates of the transistors included in the circuit **10A** and the circuit **10B** in this manner, deterioration of the transistors can be suppressed. Thus, even when the operation of the circuit **10A** and the operation of the circuit **10B** are switched, the change in potential of the wiring **11** can be made substantially equal.

(176) Consequently, in the case where the gate driver circuit in FIG. **4A** is used for a display device including a pixel for holding a video signal and the video signal is changed by the potential of the wiring **11** (e.g., feedthrough or capacitive coupling), even when the operation of the circuit **10A** and the operation of the circuit **10B** are switched, a change in video signal held in the a pixel connected to the wiring **11** can be made substantially equal. Thus, the luminance, transmittance, or the like of the pixel can be made substantially equal between the circuit **10A** and the circuit **10B**. Accordingly, display quality can be improved.

(177) Next, a timing chart illustrating a different operation example of the gate driver circuit in FIG. **4A** is described.

(178) In FIGS. **6A** to **6L**, FIGS. **7A** to **7L**, and FIGS. **8A**, **8C**, and **8D**, the potential of the output

signal OUTA in the circuit **10A** and the potential of the output signal OUTB in the circuit **10B** are fixed in each period. Alternatively, in a certain period, the potential of the output signal may have a plurality of values. For example, as illustrated in FIG. **8E**, in the period d, the potential of the output signal OUTA in the circuit **10A** and the potential of the output signal OUTB in the circuit **10B** may each have two values which are alternated.

(179) The potential of the output signal OUTA and the potential of the output signal OUTB in the period d may be changed in an analog fashion.

(180) As described above, the gate driver circuit in FIG. **4A** can perform a variety of operations.

(181) <Different Structure of Gate Driver Circuit>

(182) Next, the structure of a gate driver circuit that is different from the structure in FIG. **4A** is described with reference to FIG. **9A**.

(183) FIG. **9A** illustrates a structure example of a gate driver circuit. The gate driver circuit includes the circuit **10A**, the circuit **10B**, a circuit **10C**, and a circuit **10D**. The circuit **10C** and the circuit **10D** may have a function that is similar to the function of the circuit **10A** or the circuit **10B**.

(184) Note that the gate driver circuit in FIG. **9A** can perform a variety of operations by an appropriate combination of the case where the circuits **10A** to **10D** output signals (e.g., non-selection signals) to the wiring **11**, the case where the circuits **10A** to **10D** output signals which are different from the signals (e.g., selection signals) to the wiring **11**, and the case where the circuits **10A** to **10D** output no signal (e.g., neither a non-selection signal nor a selection signal) to the wiring **11**.

(185) Although FIG. **9A** illustrates the case where the gate driver circuit includes the four circuits connected to the wiring **11** (the circuits **10A** to **10D**), the structure of the gate driver circuit in this embodiment is not limited to this structure. The gate driver circuit in this embodiment may include N (N is a natural number) circuits. Note that the N circuits may have a function that is similar to the function of the circuit **10A** or the circuit **10B**.

(186) <Operation of Gate Driver Circuit>

(187) The operation of the gate driver circuit in FIG. **9A** is described with reference to FIG. **9B**. FIG. **9B** illustrates an operation example of the gate driver circuit.

(188) In the operation **1**, the circuit **10A** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuits **10B** to **10D** output no signal to the wiring **11**. In the operation **2**, the circuit **10B** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuits **10A**, **10C**, and **10D** output no signal to the wiring **11**. In the operation **3**, the circuit **10C** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuits **10A**, **10B**, and **10D** output no signal to the wiring **11**. In the operation **4**, the circuit **10D** outputs a signal (e.g., a non-selection signal) to the wiring **11**, and the circuits **10A** to **10C** output no signal to the wiring **11**.

(189) In the operation **5**, the circuits **10A** and **10C** output signals (e.g., non-selection signals) to the wiring **11**, and the circuits **10B** and **10D** output no signal to the wiring **11**. In the operation **6**, the circuits **10B** and **10D** output signals (e.g., non-selection signals) to the wiring **11**, and the circuits **10A** and **10C** output no signal to the wiring **11**. In the operation **7**, the circuits **10A** to **10D** output signals (e.g., non-selection signals) to the wiring **11**. In the operation **8**, the circuits **10A** to **10D** output no signal to the wiring **11**.

(190) In the operation **9**, the circuit **10A** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuits **10B** to **10D** output no signal to the wiring **11**. In an operation **10**, the circuit **10B** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuits **10A**, **10C**, and **10D** output no signal to the wiring **11**. In an operation **11**, the circuit **10C** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuits **10A**, **10B**, and **10D** output no signal to the wiring **11**. In an operation **12**, the circuit **10D** outputs a different signal (e.g., a selection signal) to the wiring **11**, and the circuits **10A** to **10C** output no signal to the wiring **11**.

(191) In an operation **13**, the circuits **10A** and **10C** output different signals (e.g., selection signals) to the wiring **11**, and the circuits **10B** and **10D** output no signal to the wiring **11**. In an operation **14**,

the circuits **10B** and **10D** output different signals (e.g., selection signals) to the wiring **11**, and the circuits **10A** and **10C** output no signal to the wiring **11**. In an operation **15**, the circuits **10A** to **10D** output different signals (e.g., selection signals) to the wiring **11**.

(192) As described above, the gate driver circuit in FIG. **9A** can perform a variety of operations.

(193) As the number of circuits (e.g., the circuits **10A** and **10B**) included in the gate driver circuit in this embodiment becomes larger, that is, **N** that indicates the number of circuits becomes larger, the frequency of output of signals from the circuits can be reduced. Thus, deterioration of transistors included in the circuits can be suppressed. Note that the size of the circuit increases when **N** becomes too large; thus, **N** is smaller than 6, preferably smaller than 4, more preferably 2.

(194) In the case where the gate driver circuit in this embodiment is used for a display device, **N** is preferably an even number in order that the frame of the display device on a left side and the frame of the display device on a right side be substantially equal. In addition, **N** is preferably an even number in order that the number of circuits on one side and the number of circuits on the other side with a pixel portion provided between the sides be equal.

Embodiment 3

(195) In this embodiment, the structure and operation of a gate driver circuit are described.

(196) <Structure of Gate Driver Circuit>

(197) The structure of a gate driver circuit is described below.

(198) FIGS. **10A** and **10B** and FIGS. **11A** and **11B** each illustrate a structure example of a gate driver circuit. The gate driver circuit includes a circuit **100A** and a circuit **100B**.

(199) The circuit **100A** includes a switch **101A** and a switch **102A**. The switch **101A** is connected between a wiring **112A** and a wiring **111**. The switch **102A** is connected between a wiring **113A** and the wiring **111**.

(200) The circuit **100B** includes a switch **101B** and a switch **102B**. The switch **101B** is connected between a wiring **112B** and the wiring **111**. The switch **102B** is connected between a wiring **113B** and the wiring **111**.

(201) Here, as illustrated in FIG. **10B** and FIG. **11B**, a path between the wiring **112A** and the wiring **111** is referred to as a path **121A**; a path between the wiring **113A** and the wiring **111** is referred to as a path **122A**; a path between the wiring **112B** and the wiring **111** is referred to as a path **121B**; a path between the wiring **113B** and the wiring **111** is referred to as a path **122B**.

(202) Note that the term “a path between A and B” may include the case where a switch is connected between A and B. An element (e.g., a transistor, a diode, a resistor, or a capacitor) or a circuit (e.g., a buffer circuit, an inverter circuit, or a shift register circuit) other than a switch may be connected between A and B. Alternatively, an element (e.g., a resistor or a transistor) may be connected in series or in parallel with the switch between A and B.

(203) Note that the circuit **100A**, the circuit **100B**, and the wiring **111** correspond to the circuit **10A**, the circuit **10B**, and the wiring **11** in Embodiment 2, respectively, and have functions that are similar to the functions of the circuit **10A**, the circuit **10B**, and the wiring **11**, respectively.

(204) Next, the wiring **112A**, the wiring **113A**, the wiring **112B**, and the wiring **113B** are described.

(205) In the case where a clock signal **CK1** is input to the wiring **112A** and the wiring **112B**, the wiring **112A** and the wiring **112B** function as signal lines or clock signal lines (also referred to as clock lines or clock supply lines). In the case where fixed voltage is applied to the wiring **112A** and the wiring **112B**, the wiring **112A** and the wiring **112B** function as power supply lines.

(206) Note that in the case where the same signal or the same voltage is input to the wiring **112A** and the wiring **112B**, the wiring **112A** and the wiring **112B** may be connected to each other. In that case, as illustrated in FIG. **11A**, one wiring **112** may be used as the wiring **112A** and the wiring **112B**. Alternatively, different signals or different voltages may be input to the wiring **112A** and the wiring **112B**.

(207) In the case where voltage **V1** (e.g., power supply voltage, reference voltage, ground voltage, or a negative power supply potential) is applied to the wiring **113A** and the wiring **113B**, the wiring

113A and the wiring **113B** function as power supply lines or grounds. Alternatively, in the case where signals are input to the wiring **113A** and the wiring **113B**, the wiring **113A** and the wiring **113B** function as signal lines.

(208) Note that in the case where the same signal or the same voltage is input to the wiring **113A** and the wiring **113B**, the wiring **113A** and the wiring **113B** may be connected to each other. In that case, as illustrated in FIG. **11A**, one wiring **113** may be used as the wiring **113A** and the wiring **113B**. Alternatively, different signals or different voltages may be input to the wiring **113A** and the wiring **113B**.

(209) Next, the switch **101A**, the switch **102A**, the switch **101B**, and the switch **102B** are described.

(210) The switch **101A** has a function of controlling the timing of bringing the wiring **112A** and the wiring **111** into conduction. Alternatively, the switch **101A** has a function of controlling the timing of supplying the potential of the wiring **112A** to the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK1**, a clock signal **CK2**, or voltage **V2**) which is to be input to the wiring **112A** to the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of supplying an H signal (e.g., the clock signal **CK1**) to the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of supplying an L signal (e.g., the clock signal **CK1**) to the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of raising the potential of the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of lowering the potential of the wiring **111**. Alternatively, the switch **101A** has a function of controlling the timing of keeping the potential of the wiring **111**.

(211) Note that in the case where the clock signal **CK2** corresponds to an inversion signal of the clock signal **CK1**, the clock signal **CK1** and the clock signal **CK2** are preferably signals obtained by inversion of the signals or signals which are substantially 180° out of phase.

(212) The clock signal **CK1** or the clock signal **CK2** may be either a balanced signal or an unbalanced signal. A balanced signal is a signal whose period during which the signal is at an H level and whose period during which the signal is at an L level in one cycle have substantially the same length. An unbalanced signal is a signal whose period during which the signal is at an H level and whose period during which the signal is at an L level in one cycle have different lengths.

(213) Note that in the case where the clock signal **CK1** and the clock signal **CK2** are unbalanced signals and the clock signal **CK2** is not an inversion signal of the clock signal **CK1**, a period during which the clock signal **CK1** is at an H level and a period during which the clock signal **CK2** is at an H level may have substantially the same length.

(214) The switch **102A** has a function of controlling the timing of bringing the wiring **113A** and the wiring **111** into conduction. Alternatively, the switch **102A** has a function of controlling the timing of supplying the potential of the wiring **113A** to the wiring **111**. Alternatively, the switch **102A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113A** to the wiring **111**. Alternatively, the switch **102A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the wiring **111**. Alternatively, the switch **102A** has a function of controlling the timing of supplying the voltage **V1** to the wiring **111**. Alternatively, the switch **102A** has a function of controlling the timing of lowering the potential of the wiring **111**. Alternatively, the switch **102A** has a function of controlling the timing of keeping the potential of the wiring **111**.

(215) The switch **101B** has a function of controlling the timing of bringing the wiring **112B** and the wiring **111** into conduction. Alternatively, the switch **101B** has a function of controlling the timing of supplying the potential of the wiring **112B** to the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK1**, the clock signal **CK2**, or the voltage **V2**) which is to be input to the wiring **112B** to the wiring

111. Alternatively, the switch **101B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of supplying an H signal (e.g., the clock signal CK1) to the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of supplying an L signal (e.g., the clock signal CK1) to the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of raising the potential of the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of lowering the potential of the wiring **111**. Alternatively, the switch **101B** has a function of controlling the timing of keeping the potential of the wiring **111**.

(216) The switch **102B** has a function of controlling the timing of bringing the wiring **113B** and the wiring **111** into conduction. Alternatively, the switch **102B** has a function of controlling the timing of supplying the potential of the wiring **113B** to the wiring **111**. Alternatively, the switch **102B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal CK2 or the voltage V1) which is to be input to the wiring **113B** to the wiring **111**. Alternatively, the switch **102B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the wiring **111**. Alternatively, the switch **102B** has a function of controlling the timing of supplying the voltage V1 to the wiring **111**. Alternatively, the switch **102B** has a function of controlling the timing of lowering the potential of the wiring **111**. Alternatively, the switch **102B** has a function of controlling the timing of keeping the potential of the wiring **111**.

(217) <Operation of Gate Driver Circuit>

(218) Next, an operation example of the gate driver circuit in FIG. **10A** is described below.

(219) FIG. **10C** illustrates an operation example of the gate driver circuit in FIG. **10A**. FIG. **10C** illustrates the states (on and off) of the switch **101A**, the switch **102A**, the switch **101B**, and the switch **102B** in each operation of the gate driver circuit. By a combination of on and off of these switches, the gate driver circuit in FIG. **10A** can perform a variety of operations.

(220) Each operation of the gate driver circuit in FIG. **10A** is described with reference to FIG. **10C**, FIGS. **12A** to **12H**, and FIGS. **13A** to **13E**. Here, the operation of the gate driver circuit in FIG. **10A** for performing the operations **1** to **7** illustrated in FIGS. **5A** to **5G** in Embodiment 2 is described.

(221) First, the operation of the gate driver circuit in FIG. **10A** for performing the operation **1** in FIG. **5A** is described.

(222) As illustrated in an operation **1a** in FIG. **12A**, the switch **101A** is turned on, so that the wiring **112A** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **112A** (e.g., the clock signal CK1) is supplied to the wiring **111**. The switch **102A** is turned on, so that the wiring **113A** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **113A** (e.g., the voltage V1) is supplied to the wiring **111**. The switch **101B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **112B** (e.g., the clock signal CK1) is supplied to the wiring **111**. The switch **102B** is turned on, so that the wiring **113B** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **113B** (e.g., the voltage V1) is supplied to the wiring **111**.

(223) Thus, potentials are supplied from the circuit **100A** and the circuit **100B** to the wiring **111**, so that the operation **1** in FIG. **5A** can be performed.

(224) In the operation **1a** in FIG. **12A**, the switch **101A** and the switch **101B** may be turned off, as in an operation **1b** in FIG. **12B**. Alternatively, in the operation **1a** in FIG. **12A**, the switch **102A** and the switch **102B** may be turned off, as in an operation **1c** in FIG. **12C**. Alternatively, in the operation **1a** in FIG. **12A**, any one of the switch **101A**, the switch **102A**, the switch **101B**, and the switch **102B** may be turned off. Alternatively, in the operation **1a** in FIG. **12A**, the switch **101A** and the switch **102B** may be turned off. Alternatively, in the operation **1a** in FIG. **12A**, the switch **101B** and the switch **102A** may be turned off.

(225) Next, the operation of the gate driver circuit in FIG. **10A** for performing the operation **2** in FIG. **5B** is described.

(226) As illustrated in an operation **2a** in FIG. **12D**, the switch **101A** is turned on, so that the wiring

112A and the wiring **111** are brought into conduction. Thus, the potential of the wiring **112A** (e.g., the clock signal **CK1**) is supplied to the wiring **111**. The switch **102A** is turned on, so that the wiring **113A** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **113A** (e.g., the voltage **V1**) is supplied to the wiring **111**. The switch **101B** is turned off, so that the wiring **112B** and the wiring **111** are brought out of conduction. The switch **102B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(227) Thus, a potential is supplied from the circuit **100A** to the wiring **111** and no potential is supplied from the circuit **100B** to the wiring **111**, so that the operation **2** in FIG. 5B can be performed.

(228) Note that in the operation **2a** in FIG. 12D, the switch **102A** may be turned off, as in an operation **2b** in FIG. 12E. Alternatively, in the operation **2a** in FIG. 12D, the switch **101A** may be turned off, as in an operation **2c** in FIG. 12F.

(229) Next, the operation of the gate driver circuit in FIG. 10A for performing the operation **3** in FIG. 5C is described.

(230) As illustrated in an operation **3a** in FIG. 12G, the switch **101A** is turned off, so that the wiring **112A** and the wiring **111** are brought out of conduction. The switch **102A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **112B** (e.g., the clock signal **CK1**) is supplied to the wiring **111**. The switch **102B** is turned on, so that the wiring **113B** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **113B** (e.g., the voltage **V1**) is supplied to the wiring **111**.

(231) Thus, no potential is supplied from the circuit **100A** to the wiring **111** and a potential is supplied from the circuit **100B** to the wiring **111**, so that the operation **3** in FIG. 5C can be performed.

(232) Note that in the operation **3a** in FIG. 12G, the switch **102B** may be turned off, as in an operation **3b** in FIG. 12H. Alternatively, in the operation **3a** in FIG. 12G, the switch **101B** may be turned off, as in an operation **3c** in FIG. 13A.

(233) Next, the operation of the gate driver circuit in FIG. 10A for performing the operation **4** in FIG. 5D is described.

(234) As illustrated in an operation **4a** in FIG. 13B, the switch **101A** is turned off, so that the wiring **112A** and the wiring **111** are brought out of conduction. The switch **102A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned off, so that the wiring **112B** and the wiring **111** are brought out of conduction. The switch **102B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(235) Thus, no potential is supplied from the circuit **100A** and the circuit **100B** to the wiring **111**, so that the operation **4** in FIG. 5D can be performed.

(236) Next, the operation of the gate driver circuit in FIG. 10A for performing the operation **5** in FIG. 5E is described.

(237) As illustrated in an operation **5a** in FIG. 13C, the switch **101A** is turned on, so that the wiring **112A** and the wiring **111** are brought into conduction. Thus, a different potential of the wiring **112A** (e.g., the clock signal **CK2**) is supplied to the wiring **111**. The switch **102A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Thus, a different potential of the wiring **112B** (e.g., the clock signal **CK2**) is supplied to the wiring **111**. The switch **102B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(238) Thus, different potentials are supplied from the circuit **100A** and the circuit **100B** to the wiring **111**, so that the operation **5** in FIG. 5E can be performed.

(239) Next, the operation of the gate driver circuit in FIG. 10A for performing the operation **6** in FIG. 5F is described.

(240) As illustrated in an operation **6a** in FIG. 13D, the switch **101A** is turned on, so that the wiring

112A and the wiring **111** are brought into conduction. Thus, a different potential of the wiring **112A** (e.g., the clock signal **CK2**) is supplied to the wiring **111**. The switch **102A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned off, so that the wiring **112B** and the wiring **111** are brought out of conduction. The switch **102B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(241) Thus, a different potential is supplied from the circuit **100A** to the wiring **111** and no potential is supplied from the circuit **100B** to the wiring **111**, so that the operation **6** in FIG. **5F** can be performed.

(242) Next, the operation of the gate driver circuit in FIG. **10A** for performing the operation **7** in FIG. **5G** is described.

(243) As illustrated in an operation **7a** in FIG. **13E**, the switch **101A** is turned off, so that the wiring **112A** and the wiring **111** are brought out of conduction. The switch **102A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Thus, a different potential of the wiring **112B** (e.g., the clock signal **CK2**) is supplied to the wiring **111**. The switch **102B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(244) Thus, no potential is supplied from the circuit **100A** to the wiring **111** and a different potential is supplied from the circuit **100B** to the wiring **111**, so that the operation **7** in FIG. **5G** can be performed.

(245) By control of on and off of the switch **101A**, the switch **102A**, the switch **101B**, and the switch **102B** as described above, the operation of the gate driver circuit described with reference to FIGS. **5A** to **5G** in Embodiment 2 can be performed.

(246) Note that in the operation **1a** in FIG. **12A**, the operation **2a** in FIG. **12D**, and the operation **3a** in FIG. **12G**, it is preferable that the potential of the wiring **112A** and the potential of the wiring **112B** be substantially equal. In addition, it is preferable that the potential of the wiring **113A** and the potential of the wiring **113B** be substantially equal. For example, in the case where the voltage **V1** is applied to the wiring **113A** and the wiring **113B**, the clock signal **CK1** is preferably at an L level.

(247) In the operation **5a** in FIG. **13C**, the operation **6a** in FIG. **13D**, and the operation **7a** in FIG. **13E**, in the case where each of the potentials of the wiring **113A** and the wiring **113B** is **V1**, it is preferable that each of the potential of the wiring **112A** and the wiring **112B** be substantially **V2**. For example, the clock signal **CK2** input to the wiring **112A** and the wiring **112B** is preferably at an H level.

(248) The operation of the gate driver circuit in FIG. **10A** for obtaining the timing charts illustrated in FIGS. **6A** to **6L** and FIGS. **7A** to **7L** in Embodiment 2 is described.

(249) Note that the operation of the gate driver circuit in FIG. **4A** in a given period is described with reference to FIGS. **5A** to **5I** in Embodiment 2; however, in order to perform the operation, the gate driver circuit in FIG. **10A** can perform any of the operations illustrated in FIG. **10C** in the given period. For example, in order to perform the operation **1** illustrated in FIG. **5A**, the gate driver circuit in FIG. **10A** can perform any of the operations **1a**, **1b**, and **1c** illustrated in FIG. **10C** (corresponding to FIGS. **12A** to **12C**).

(250) First, the operation of the gate driver circuit in FIG. **10A** for obtaining the timing chart illustrated in FIG. **6A** is described.

(251) As described in Embodiment 2, in the period a, the transition period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. **10A** performs the operation **2** in FIG. **5B**. Thus, in order to perform the operation **2**, in the period a, the transition period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. **10A** can perform any of the operations **2a**, **2b**, and **2c** illustrated in FIG. **10C** (corresponding to FIGS. **12D** to **12F**).

(252) In the transition period from the period a to the period b and the period b, the gate driver

circuit in FIG. 10A performs the operation 6 in FIG. 5F. Thus, in order to perform the operation 6, in the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. 10A can perform the operation 6a illustrated in FIG. 10C (corresponding to FIG. 13D).

(253) In this manner, the gate driver circuit in FIG. 10A can perform operation corresponding to the timing chart illustrated in FIG. 6A.

(254) Note that in the timing chart illustrated in FIG. 6A, in the case where the circuit 100B outputs a signal (e.g., a non-selection signal) to the wiring 111 in the period a and the transition period from the period b to the period c, the gate driver circuit in FIG. 10A can perform, for example, any of the operations 1a, 1b, and 1c illustrated in FIG. 10C (corresponding to FIGS. 12A to 12C).

(255) Note that in the timing chart illustrated in FIG. 6A, in the case where the circuit 100B outputs a different signal (e.g., a selection signal) to the wiring 111 in the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. 10A can perform, for example, the operation 5a illustrated in FIG. 10C (corresponding to FIG. 13C).

(256) In this manner, the gate driver circuit in FIG. 10A can perform operation corresponding to the timing chart illustrated in FIG. 6K.

(257) Similarly, when the gate driver circuit in FIG. 10A performs any of the operations illustrated in FIG. 10C, the timing charts illustrated in FIGS. 6B to 6J and FIG. 6L can be obtained.

(258) Next, the operation of the gate driver circuit in FIG. 10A for obtaining the timing chart illustrated in FIG. 7A is described.

(259) As described in Embodiment 2, in the period a, the transition period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. 10A performs the operation 3 in FIG. 5C. Thus, in order to perform the operation 3, in the period a, the period from the period b to the period c, the period c, and the period d, the gate driver circuit in FIG. 10A can perform any of the operations 3a, 3b, and 3c illustrated in FIG. 10C (corresponding to FIGS. 12G and 12H and FIG. 13A).

(260) In the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. 10A performs the operation 7 in FIG. 5G. Thus, in order to perform the operation 7, in the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. 10A can perform the operation 7a illustrated in FIG. 10C (corresponding to FIG. 13E).

(261) In this manner, the gate driver circuit in FIG. 10A can perform operation corresponding to the timing chart illustrated in FIG. 7A.

(262) Note that in the timing chart illustrated in FIG. 7A, in the case where the circuit 100A outputs a signal (e.g., a non-selection signal) to the wiring 111 in the period a and the transition period from the period b to the period c, the gate driver circuit in FIG. 10A can perform, for example, any of the operations 1a, 1b, and 1c illustrated in FIG. 10C (corresponding to FIGS. 12A to 12C).

(263) Note that in the timing chart illustrated in FIG. 7A, in the case where the circuit 100A outputs a different signal (e.g., a selection signal) to the wiring 111 in the transition period from the period a to the period b and the period b, the gate driver circuit in FIG. 10A can perform, for example, the operation 5a illustrated in FIG. 10C (corresponding to FIG. 13C).

(264) In this manner, the gate driver circuit in FIG. 10A can perform operation corresponding to the timing chart illustrated in FIG. 7K.

(265) Similarly, when the gate driver circuit in FIG. 10A performs any of the operations illustrated in FIG. 10C, the timing charts illustrated in FIGS. 7B to 7J and FIG. 7L can be obtained.

(266) When the gate driver circuit in FIG. 10A performs a combination of the operations illustrated in FIG. 10C as described above, the timing charts illustrated in FIGS. 6A to 6L and FIGS. 7A to 7L can be obtained.

(267) <Structure of Gate Driver Circuit>

(268) Next, the structure of a gate driver circuit that is different from the structure in FIG. 10A is described below. Here, the case where the gate driver circuit includes N (N is a natural number) circuits having a function that is similar to the function of the circuit 100A or the circuit 100B is

described.

(269) FIG. 11C illustrates a structure example of a gate driver circuit. The gate driver circuit includes the circuit 100A, the circuit 100B, a circuit 100C, and a circuit 100D. The circuit 100C and the circuit 100D have a function that is similar to the function of the circuit 100A or the circuit 100B.

(270) The circuit 100C includes a switch 101C and a switch 102C. The switch 101C is connected between a wiring 112C and the wiring 111. The switch 102C is connected between a wiring 113C and the wiring 111. The switch 101C has a function that is similar to the function of the switch 101A or the switch 101B. The switch 102C has a function that is similar to the function of the switch 102A or the switch 102B. The wiring 112C has a function that is similar to the function of the wiring 112A or the wiring 112B and is supplied with a signal or voltage that is similar to the signal or voltage supplied to the wiring 112A or the wiring 112B. The wiring 113C has a function that is similar to the function of the wiring 113A or the wiring 113B and is supplied with a signal or voltage that is similar to the signal or voltage supplied to the wiring 113A or the wiring 113B.

(271) The circuit 100D includes a switch 101D and a switch 102D. The switch 101D is connected between a wiring 112D and the wiring 111. The switch 102D is connected between a wiring 113D and the wiring 111. The switch 101D has a function that is similar to the function of the switch 101A or the switch 101B. The switch 102D has a function that is similar to the function of the switch 102A or the switch 102B. The wiring 112D has a function that is similar to the function of the wiring 112A or the wiring 112B and is supplied with a signal or voltage that is similar to the signal or voltage supplied to the wiring 112A or the wiring 112B. The wiring 113D has a function that is similar to the function of the wiring 113A or the wiring 113B and is supplied with a signal or voltage that is similar to the signal or voltage supplied to the wiring 113A or the wiring 113B.

(272) FIG. 14A illustrates a different structure example of the gate driver circuit. The gate driver circuit includes the circuit 100A and the circuit 100B.

(273) The circuit 100A includes a switch 103A in addition to the switch 101A and the switch 102A. The switch 103A is connected between the wiring 113A and the wiring 111. The switch 103A can perform operation that is similar to the operation of the switch 102A.

(274) The circuit 100B includes a switch 103B in addition to the switch 101B and the switch 102B. The switch 103B is connected between the wiring 113B and the wiring 111. The switch 103B can perform operation that is similar to the operation of the switch 102B.

(275) <Operation of Gate Driver Circuit>

(276) The operation of the gate driver circuit in FIG. 14A is described with reference to FIG. 14B and FIGS. 15A to 15E. Here, the operation of the gate driver circuit in FIG. 14A for performing the operations 1 to 7 illustrated in FIGS. 5A to 5G in Embodiment 2 is described.

(277) First, the operation of the gate driver circuit in FIG. 14A for performing the operation 1 in FIG. 5A is described.

(278) As illustrated in an operation 1d in FIG. 14B, the switch 101A is turned off, so that the wiring 112A and the wiring 111 are brought out of conduction. The switch 102A and the switch 103A are turned on, so that the wiring 113A and the wiring 111 are brought into conduction. Thus, the potential of the wiring 113A (e.g., the voltage V1) is supplied to the wiring 111. The switch 101B is turned off, so that the wiring 112B and the wiring 111 are brought out of conduction. The switch 102B and the switch 103B are turned on, so that the wiring 113B and the wiring 111 are brought into conduction. Thus, the potential of the wiring 113B (e.g., the voltage V1) is supplied to the wiring 111.

(279) Note that in the operation 1d in FIG. 14B, the switch 103A and the switch 103B may be turned off, as in an operation 1e in FIG. 14B. Alternatively, in the operation 1d in FIG. 14B, the switch 102A and the switch 102B may be turned off, as in an operation 1f in FIG. 14B.

Alternatively, in the operations 1d, 1e, and 1f in FIG. 14B, the switch 101A or the switch 101B may be turned off.

(280) Next, the operation of the gate driver circuit in FIG. 14A for performing the operation 2 in FIG. 5B is described.

(281) As illustrated in an operation 2d in FIG. 14B, the switch 101A is turned off, so that the wiring 112A and the wiring 111 are brought out of conduction. The switch 102A and the switch 103A are turned on, so that the wiring 113A and the wiring 111 are brought into conduction. Thus, the potential of the wiring 113A (e.g., the voltage V1) is supplied to the wiring 111. The switch 101B is turned off, so that the wiring 112B and the wiring 111 are brought out of conduction. The switch 102B and the switch 103B are turned off, so that the wiring 113B and the wiring 111 are brought out of conduction.

(282) Note that in the operation 2d in FIG. 14B, the switch 103A may be turned off, as in an operation 2e in FIG. 14B (corresponding to FIG. 15A). Alternatively, in the operation 2d in FIG. 14B, the switch 102A may be turned off, as in an operation 2f in FIG. 14B (corresponding to FIG. 15B). Alternatively, in the operations 2d, 2e, and 2f in FIG. 14B, the switch 101A may be turned off.

(283) Next, the operation of the gate driver circuit in FIG. 14A for performing the operation 3 in FIG. 5C is described.

(284) As illustrated in an operation 3d in FIG. 14B, the switch 101A is turned off, so that the wiring 112A and the wiring 111 are brought out of conduction. The switch 102A and the switch 103A are turned off, so that the wiring 113A and the wiring 111 are brought out of conduction. The switch 101B is turned off, so that the wiring 112B and the wiring 111 are brought out of conduction. The switch 102B and the switch 103B are turned on, so that the wiring 113B and the wiring 111 are brought into conduction. Thus, the potential of the wiring 113B (e.g., the voltage V1) is supplied to the wiring 111.

(285) Note that in the operation 3d in FIG. 14B, the switch 103B may be turned off, as in an operation 3e in FIG. 14B (corresponding to FIG. 15C). Alternatively, in the operation 3d in FIG. 14B, the switch 102B may be turned off, as in an operation 3f in FIG. 14B (corresponding to FIG. 15D). Alternatively, in the operations 3d, 3e, and 3f in FIG. 14B, the switch 101B may be turned off.

(286) Next, the operation of the gate driver circuit in FIG. 14A for performing the operation 4 in FIG. 5D is described.

(287) As illustrated in an operation 4d in FIG. 14B, the switch 101A is turned off, so that the wiring 112A and the wiring 111 are brought out of conduction. The switch 102A and the switch 103A are turned off, so that the wiring 113A and the wiring 111 are brought out of conduction. The switch 101B is turned off, so that the wiring 112B and the wiring 111 are brought out of conduction. The switch 102B and the switch 103B are turned off, so that the wiring 113B and the wiring 111 are brought out of conduction.

(288) Next, the operation of the gate driver circuit in FIG. 14A for performing the operation 5 in FIG. 5E is described.

(289) As illustrated in an operation 5b in FIG. 14B (corresponding to FIG. 15E), the switch 101A is turned on, so that the wiring 112A and the wiring 111 are brought into conduction. Thus, the potential of the wiring 112A (e.g., the clock signal CK1) is supplied to the wiring 111. The switch 102A and the switch 103A are turned off, so that the wiring 113A and the wiring 111 are brought out of conduction. The switch 101B is turned on, so that the wiring 112B and the wiring 111 are brought into conduction. Thus, the potential of the wiring 112B (e.g., the clock signal CK1) is supplied to the wiring 111. The switch 102B and the switch 103B are turned off, so that the wiring 113B and the wiring 111 are brought out of conduction.

(290) Next, the operation of the gate driver circuit in FIG. 14A for performing the operation 6 in FIG. 5F is described.

(291) As illustrated in an operation 6b in FIG. 14B, the switch 101A is turned on, so that the wiring 112A and the wiring 111 are brought into conduction. Thus, the potential of the wiring 112A (e.g.,

the clock signal **CK1**) is supplied to the wiring **111**. The switch **102A** and the switch **103A** are turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned off, so that the wiring **112B** and the wiring **111** are brought out of conduction. The switch **102B** and the switch **103B** are turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(292) Next, the operation of the gate driver circuit in FIG. **14A** for performing the operation **7** in FIG. **5B** is described.

(293) As illustrated in an operation **7b** in FIG. **14B**, the switch **101A** is turned off, so that the wiring **112A** and the wiring **111** are brought out of conduction. The switch **102A** and the switch **103A** are turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction. The switch **101B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Thus, the potential of the wiring **112B** (e.g., the clock signal **CK1**) is supplied to the wiring **111**. The switch **102B** and the switch **103B** are turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(294) By control of on and off of the switch **101A**, the switch **102A**, the switch **103A**, the switch **101B**, the switch **102B**, and the switch **103B** as described above, the operation of the gate driver circuit described with reference to FIGS. **5A** to **5G** in Embodiment 2 can be performed.

Embodiment 4

(295) In this embodiment, a semiconductor device including the gate driver circuit described in any of the above embodiments is described.

(296) <Structure of Semiconductor Device>

(297) A structure example of a semiconductor device in this embodiment is described with reference to FIG. **16A**. FIG. **16A** illustrates an example of a circuit diagram of the semiconductor device. The semiconductor device illustrated in FIG. **16A** includes a circuit **200A** and a circuit **200B** included in a gate driver circuit.

(298) The circuit **200A** includes a transistor **201A**, a transistor **202A**, and a circuit **300A**. The circuit **200B** includes a transistor **201B**, a transistor **202B**, and a circuit **300B**.

(299) Note that in FIG. **16A**, the transistor **201A**, the transistor **202A**, the transistor **201B**, and the transistor **202B** are described as n-channel transistors. The n-channel transistor is turned on when a potential difference V_{gs} between a gate and a source exceeds the threshold voltage V_{th} .

(300) These transistors may be p-channel transistors. The p-channel transistor is turned on when a potential difference V_{gs} between a gate and a source is lower than the threshold voltage V_{th} .

(301) A first terminal of the transistor **201A** is connected to the wiring **112A**. A second terminal of the transistor **201A** is connected to the wiring **111**. A first terminal of the transistor **202A** is connected to the wiring **113A**. A second terminal of the transistor **202A** is connected to the wiring **111**. The circuit **300A** is connected to the wiring **113A**, a wiring **114A**, a wiring **115A**, a wiring **116A**, a gate of the transistor **201A**, and a gate of the transistor **202A**. Note that the circuit **300A** is not necessarily connected to all of the wiring **113A**, the wiring **114A**, the wiring **115A**, and the wiring **116A**, and the circuit **300A** is not connected to any of the wiring **113A**, the wiring **114A**, the wiring **115A**, and the wiring **116A** in some cases.

(302) Note that a portion where the gate of the transistor **201A** and the circuit **300A** are connected to each other is referred to as a node **A1**, and a portion where the gate of the transistor **202A** and the circuit **300A** are connected to each other is referred to as a node **A2**. In addition, the potential of the node **A1** is also referred to as a potential V_{a1} , and the potential of the node **A2** is also referred to as a potential V_{a2} .

(303) A first terminal of the transistor **201B** is connected to the wiring **112B**. A second terminal of the transistor **201B** is connected to the wiring **111**. A first terminal of the transistor **202B** is connected to the wiring **113B**. A second terminal of the transistor **202B** is connected to the wiring **111**. The circuit **300B** is connected to the wiring **113B**, a wiring **114B**, a wiring **115B**, a wiring **116B**, a gate of the transistor **201B**, and a gate of the transistor **202B**. Note that the circuit **300B** is

not necessarily connected to all of the wiring **113B**, the wiring **114B**, the wiring **115B**, and the wiring **116B**, and the circuit **300B** is not connected to any of the wiring **113B**, the wiring **114B**, the wiring **115B**, and the wiring **116B** in some cases.

(304) Note that a portion where the gate of the transistor **201B** and the circuit **300B** are connected to each other is referred to as a node **B1**, and a portion where the gate of the transistor **202B** and the circuit **300B** are connected to each other is referred to as a node **B2**. In addition, the potential of the node **B1** is also referred to as a potential **Vb1**, and the potential of the node **B2** is also referred to as a potential **Vb2**.

(305) Next, the wiring **111**, the wiring **114A**, the wiring **115A**, the wiring **116A**, the wiring **114B**, the wiring **115B**, and the wiring **116B** are described.

(306) The signal **OUTA** is output from the circuit **200A** to the wiring **111**, and the signal **OUTB** is output from the circuit **200B** to the wiring **111**.

(307) The wiring **111** extends to a pixel portion and functions as a gate signal line (also referred to as a gate line), a scan line, or a signal line. Thus, the signal **OUTA** and the signal **OUTB** each correspond to a gate signal, a scan signal, or a selection signal.

(308) In the case where the semiconductor device includes the plurality of circuits **200A**, the wiring **111** may be connected to the wiring **114A** in the circuit **200A** in a different stage (e.g., the next stage). In that case, the signal **OUTA** corresponds to a transfer signal or a start signal. In addition, in the case where the semiconductor device includes the plurality of circuits **200A**, the wiring **111** may be connected to the wiring **116A** in the circuit **200A** in a different stage (e.g., the preceding stage). In that case, the signal **OUTA** corresponds to a reset signal.

(309) In the case where the semiconductor device includes the plurality of circuits **200B**, the wiring **111** may be connected to the wiring **114B** in the circuit **200B** in a different stage (e.g., the next stage). In that case, the signal **OUTB** corresponds to a transfer signal or a start signal. In addition, in the case where the semiconductor device includes the plurality of circuits **200B**, the wiring **111** may be connected to the wiring **116B** in the circuit **200B** in a different stage (e.g., the preceding stage). In that case, the signal **OUTB** corresponds to a reset signal.

(310) Start signals **SP** are input to the wiring **114A** and the wiring **114B**. Thus, the wiring **114A** and the wiring **114B** function as signal lines.

(311) Further, in the case where the semiconductor device includes the plurality of circuits **200A**, the wiring **114A** may be connected to the wiring **111** in the circuit **200A** in a different stage (e.g., the preceding stage). In that case, the wiring **114A** functions as a gate signal line (also referred to as a gate line), a scan line, or a signal line. Thus, the start signal **SP** corresponds to a gate signal, a scan signal, or a selection signal.

(312) Further, in the case where the semiconductor device includes the plurality of circuits **200B**, the wiring **114B** may be connected to the wiring **111** in the circuit **200B** in a different stage (e.g., the preceding stage). In that case, the wiring **114B** functions as a gate signal line (also referred to as a gate line), a signal line, or a scan line. Thus, the start signal **SP** corresponds to a gate signal, a selection signal, or a scan signal.

(313) Note that in the case where the same signal is input to the wiring **114A** and the wiring **114B**, the wiring **114A** and the wiring **114B** may be connected to each other. In that case, one wiring may be used as the wiring **114A** and the wiring **114B**. Alternatively, different signals may be input to the wiring **114A** and the wiring **114B**.

(314) A signal **SELA** is input to the wiring **115A**, and a signal **SELB** is input to the wiring **115B**.

(315) The signal **SELA** and the signal **SELB** are preferably signals obtained by inversion of the signals or signals which are substantially 180° out of phase. In the case where each of the signal **SELA** and the signal **SELB** is a signal which repeatedly shifts between an H level and an L level every given period (e.g., every frame period), each of the signal **SELA** and the signal **SELB** corresponds to a control signal, a clock signal, or a clock control signal. Thus, the wiring **115A** and the wiring **115B** function as signal lines, control lines, or clock signal lines (also referred to as

clock lines or clock supply lines). Each of the signal SELA and the signal SELB may be a signal which repeatedly shifts between an H level and an L level every several periods, every time power supply voltage is input, or in a random manner. In the same period, both the signal SELA and the signal SELB may be at an H level or an L level.

(316) Reset signals RE are input to the wiring **116A** and the wiring **116B**. Thus, the wiring **116A** and the wiring **116B** function as signal lines.

(317) Further, in the case where the semiconductor device includes the plurality of circuits **200A**, the wiring **116A** may be connected to the wiring **111** in the circuit **200B** in a different stage (e.g., the next stage). In that case, the wiring **116A** functions as a gate signal line (also referred to as a gate line), a signal line, or a scan line. Thus, the reset signal RE corresponds to a gate signal, a selection signal, or a scan signal.

(318) Further, in the case where the semiconductor device includes the plurality of circuits **200B**, the wiring **116B** may be connected to the wiring **111** in the circuit **200B** in a different stage (e.g., the next stage). In that case, the wiring **116B** functions as a gate signal line (also referred to as a gate line), a signal line, or a scan line. Thus, the reset signal RE corresponds to a gate signal, a selection signal, or a scan signal.

(319) Note that in the case where the same signal is input to the wiring **116A** and the wiring **116B**, the wiring **116A** and the wiring **116B** may be connected to each other. In that case, one wiring may be used as the wiring **116A** and the wiring **116B**. Alternatively, different signals may be input to the wiring **116A** and the wiring **116B**.

(320) Next, the transistor **201A**, the transistor **202A**, the circuit **300A**, the transistor **201B**, the transistor **202B**, and the circuit **300B** are described.

(321) The transistor **201A** has a function that is similar to the function of the switch **101A** described in Embodiment 3. Alternatively, the transistor **201A** may have a function of performing bootstrap operation. Alternatively, the transistor **201A** may have a function of raising the potential of the node **A1** by bootstrap operation.

(322) In this manner, the transistor **201A** functions as a switch, a buffer, or the like. Note that the transistor **201A** may be controlled in accordance with the potential of the node **A1**.

(323) The transistor **202A** has a function that is similar to the function of the switch **102A** described in Embodiment 3. Note that the transistor **202A** may be controlled in accordance with the potential of the node **A2**.

(324) The circuit **300A** has a function of controlling the potential of the node **A1** or the potential of the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **A1** or the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **A1** or the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of supplying an H signal or the voltage **V1** to the node **A1** or the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **A1** or the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of raising the potential of the node **A1** or the potential of the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of lowering the potential of the node **A1** or the potential of the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of keeping the potential of the node **A1** or the potential of the node **A2**. Alternatively, the circuit **300A** has a function of controlling the timing of setting the node **A1** or the node **A2** to be in a floating state.

(325) Note that the circuit **300A** may be controlled in accordance with the start signal SP, the signal SELA, or the reset signal RE. Alternatively, the circuit **300A** may be controlled in accordance with a signal which is different from the above signal (the start signal SP, the signal SELA, or the reset signal RE) (e.g., the signal OUTA, the clock signal CK1, or the clock signal CK2).

(326) The transistor **201B** has a function that is similar to the function of the switch **101B** described in Embodiment 3. Alternatively, the transistor **201B** may have a function of performing bootstrap

operation. Alternatively, the transistor **201B** may have a function of raising the potential of the node **B1** by bootstrap operation.

(327) In this manner, the transistor **201B** functions as a switch, a buffer, or the like. Note that the transistor **201B** may be controlled in accordance with the potential of the node **B1**.

(328) The transistor **202B** has a function that is similar to the function of the switch **102B** described in Embodiment 3. Note that the transistor **202B** may be controlled in accordance with the potential of the node **B2**.

(329) The circuit **300B** has a function of controlling the potential of the node **B1** or the potential of the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **B1** or the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **B1** or the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **B1** or the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **B1** or the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of raising the potential of the node **B1** or the potential of the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of lowering the potential of the node **B1** or the potential of the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of keeping the potential of the node **B1** or the potential of the node **B2**. Alternatively, the circuit **300B** has a function of controlling the timing of setting the node **B1** or the node **B2** to be in a floating state.

(330) Note that the circuit **300B** may be controlled in accordance with the start signal **SP**, the signal **SELB**, or the reset signal **RE**. Alternatively, the circuit **300B** may be controlled in accordance with a signal which is different from the above signal (the start signal **SP**, the signal **SELB**, or the reset signal **RE**) (e.g., the signal **OUTB**, the clock signal **CK1**, or the clock signal **CK2**).

(331) <Operation of Semiconductor Device>

(332) An operation example of the semiconductor device in FIG. **16A** is described with reference to a timing chart illustrated in FIG. **17**. FIGS. **18A** and **18B**, FIGS. **19A** and **19B**, FIGS. **20A** and **20B**, and FIGS. **21A** and **21B** each illustrate an operation example of the semiconductor device in FIG. **16A**, and FIG. **22** and FIG. **23** are timing charts each illustrating an operation example of the semiconductor device in FIG. **16A**. Note that description of portions which are common with the portions described in the above embodiments is omitted.

(333) First, as illustrated in FIG. **18A**, in a period **a1**, the start signal **SP** is set at an H level. At the timing of when the start signal **SP** is set at an H level, the circuit **300A** starts to supply an H signal or the voltage **V2** to the node **A1**. Thus, the potential of the node **A1** rises. At this time, since the potential of the node **A1** rises, the circuit **300A** supplies an L signal or the voltage **V1** to the node **A2**. Thus, the potential of the node **A2** decreases and is set at an L level. Then, the transistor **202A** is turned off, so that the wiring **113A** and the wiring **111** are brought out of conduction.

(334) Then, the potential of the node **A1** continuously rises. After the potential of the node **A1** rises to $V1 + V_{th.sub.201A}$ ($V_{th.sub.201A}$ is the threshold voltage of the transistor **201A**), the transistor **201A** is turned on, so that the wiring **112A** and the wiring **111** are brought into conduction. Then, the clock signal **CK1** which is at an L level is supplied to the wiring **111** through the transistor **201A**. Accordingly, the signal **OUTA** is set at an L level.

(335) After that, the potential of the node **A1** further rises. Then, the circuit **300A** stops supplying a signal or voltage to the node **A1**, so that the circuit **300A** and the node **A1** are brought out of conduction. Consequently, the node **A1** is set to be in a floating state, so that the potential of the node **A1** is kept at $V1 + V_{th.sub.201A} + V_x$ (V_x is a positive number).

(336) Note that in the period **a1**, instead of stopping the supply of a signal or voltage to the node **A1**, the circuit **300A** may continuously supply the voltage $V1 + V_{th.sub.201A} + V_x$ to the node **A1**.

(337) In contrast, in the period **a1**, at the timing of when the start signal **SP** is set at an H level, the circuit **300B** starts to supply an H signal or the voltage **12** to the node **B1**. Thus, the potential of the

node **B1** rises. At this time, since the signal SELB is at an L level or the potential of the node **B1** rises, the circuit **300B** supplies an L signal or the voltage **V1** to the node **B2**. Thus, the potential of the node **B2** decreases and is set at an L level. Then, the transistor **202B** is turned off, so that the wiring **113B** and the wiring **111** are brought out of conduction.

(338) Then, the potential of the node **B1** continuously rises. After the potential of the node **B1** rises to $V1 + V_{th.sub.201B}$ ($V_{th.sub.201B}$ is the threshold voltage of the transistor **201B**), the transistor **201B** is turned on, so that the wiring **112B** and the wiring **111** are brought into conduction. Then, the clock signal CK1 which is at an L level is supplied to the wiring **111** through the transistor **201B**. Accordingly, the signal OUTB is set at an L level.

(339) After that, the potential of the node **B1** further rises. Then, the circuit **300B** stops supplying a signal or voltage to the node **B1**, so that the circuit **300B** and the node **B1** are brought out of conduction. Consequently, the node **B1** is set to be in a floating state, so that the potential of the node **B1** is kept at $V1 + V_{th.sub.201B} + V_x$.

(340) Note that in the period **a1**, instead of stopping the supply of a signal or voltage to the node **B1**, the circuit **300B** may continuously supply the voltage $V1 + V_{th.sub.201B} + V_x$ to the node **B1**.

(341) Next, as illustrated in FIG. **18B**, in a period **b1**, the start signal SP is set at an L level. Thus, a state is kept in which the circuit **300A** does not supply a signal or voltage to the node **A1**.

Consequently, the node **A1** is kept in a floating state, so that the potential of the node **A1** is kept at $V1 + V_{th.sub.201A} + V_x$. That is, since the transistor **201A** is kept on, the wiring **112A** and the wiring **111** are kept in a conduction state.

(342) Since the potential of the node **A1** is kept at the level that is raised in the period **a1**, a state is kept in which the circuit **300A** supplies an L signal or the voltage **V1** to the node **A2**. Thus, the transistor **202A** is kept off, so that the wiring **113A** and the wiring **111** are kept in a non-conduction state.

(343) At this time, the level of the clock signal CK1 rises from an L level to an H level. Then, the clock signal CK1 which is at an H level is supplied to the wiring **111** through the transistor **201A**, so that the potential of the wiring **111** rises. Then, the potential of the node **A1** is raised to $V2 + V_{th.sub.202A} + V_x$ ($V_{th.sub.202A}$ is the threshold voltage of the transistor **202A**) by parasitic capacitance between the gate of the transistor **201A** and the second terminal of the transistor **201A** because the node **A1** is kept in a floating state. This is so-called bootstrap operation. Thus, the potential of the wiring **111** rises to **V2**, so that the signal OUTA is set at an H level.

(344) In contrast, in the period **b1**, the start signal SP is set at an L level, so that a state is kept in which the circuit **300B** does not supply a signal or voltage to the node **B1**. Thus, the node **B1** is kept in a floating state, so that the potential of the node **B1** is kept at $V1 + V_{th.sub.201B} + V_x$. That is, since the transistor **201B** is kept on, the wiring **112B** and the wiring **111** are kept in a conduction state.

(345) Since the signal SELB is at an L level or the potential of the node **B1** is kept at the level that is raised in the period **a1**, a state is kept in which the circuit **300B** supplies an L signal or the voltage **V1** to the node **B2**. Thus, the transistor **202B** is kept off, so that the wiring **113B** and the wiring **111** are kept in a non-conduction state.

(346) At this time, the level of the clock signal CK1 rises from an L level to an H level. Then, the clock signal CK1 which is at an H level is supplied to the wiring **111** through the transistor **201B**, so that the potential of the wiring **111** rises. Then, the potential of the node **B1** is raised to $V2 + V_{th.sub.202B} + V_x$ ($V_{th.sub.202B}$ is the threshold voltage of the transistor **202B**) by parasitic capacitance between the gate of the transistor **201B** and the second terminal of the transistor **201B** because the node **B1** is kept in a floating state. This is so-called bootstrap operation. Thus, the potential of the wiring **111** rises to **V2**, so that the signal OUTB is set at an H level.

(347) Next, as illustrated in FIG. **19A**, in a period **c1**, the reset signal RE is set at an H level. At the timing of when the reset signal RE is set at an H level, the circuit **300A** supplies an L signal or the voltage **V1** to the node **A1**. Thus, the potential of the node **A1** decreases so as to be the voltage **V1**.

Then, the transistor **201A** is turned off, so that the wiring **112A** and the wiring **111** are brought out of conduction. Since the potential of the node **A1** decreases, the circuit **300A** supplies an H signal or the voltage **V1** to the node **A2**. Thus, the potential of the node **A2** rises. Then, the transistor **202A** is turned on, so that the wiring **113A** and the wiring **111** are brought into conduction. Consequently, the voltage **V1** is supplied to the wiring **111** through the transistor **202A**. Thus, the potential of the wiring **111** decreases, so that the signal **OUTA** is set at an L level.

(348) Note that in the period **c1**, the timing of when the clock signal **CK1** is set at an L level might be earlier than the timing of when the transistor **201A** is turned off. Thus, until the transistor **201A** is turned off, it is preferable that the clock signal **CK1** which is at an L level be supplied to the wiring **111** through the transistor **201A**. When the channel width of the transistor **201A** is increased, the fall time of the signal **OUTA** can be shortened.

(349) In the period **c1**, as for the wiring **111**, there are the following three cases: the case where the voltage **V1** is supplied to the wiring **111** through the transistor **202A**; the case where the clock signal **CK1** which is at an L level is supplied to the wiring **111** through the transistor **201A**; and the case where the voltage **V1** is supplied to the wiring **111** through the transistor **202A** and the clock signal **CK1** which is at an L level is supplied to the wiring **111** through the transistor **201A**.

(350) In contrast, in the period **c1**, at the timing of when the reset signal **RE** is set at an H level, the circuit **300B** supplies an L signal or the voltage **V1** to the node **B1**. Thus, the potential of the node **B1** decreases so as to be the voltage **V1**. Then, the transistor **201B** is turned off, so that the wiring **112B** and the wiring **111** are brought out of conduction. Since the signal **SELB** is kept at an L level, a state is kept in which the circuit **300B** supplies an L signal or the voltage **V1** to the node **B2**. Thus, the potential of the node **B2** is kept at an L level. Then, the transistor **202B** is kept off, so that the wiring **113B** and the wiring **111** are kept in a non-conduction state.

(351) Note that in the period **c1**, the timing of when the clock signal **CK1** is set at an L level might be earlier than the timing of when the transistor **201B** is turned off. Thus, until the transistor **201B** is turned off, it is preferable that the clock signal **CK1** which is at an L level be supplied to the wiring **111** through the transistor **201B**. When the channel width of the transistor **201B** is increased, the fall time of the signal **OUTB** can be shortened.

(352) Next, as illustrated in FIG. **19B**, in the period **d1**, a state is kept in which the circuit **300A** supplies an L signal or the voltage **V1** to the node **A1**. Thus, the potential of the node **A1** is kept at an L level. Then, the transistor **201A** is kept off, so that the wiring **112A** and the wiring **111** are kept in a non-conduction state.

(353) In addition, a state is kept in which the circuit **300A** supplies an H signal or the voltage **V2** to the node **A2**. Thus, the potential of the node **A2** is kept at an H level. Then, the transistor **202A** is kept on, so that the wiring **113A** and the wiring **111** are kept in a conduction state. Consequently, a state is kept in which the voltage **V1** is supplied to the wiring **111** through the transistor **202A**.

(354) In contrast, in the period **d1**, a state is kept in which the circuit **300B** supplies an L signal or the voltage **V1** to the node **B1**. Thus, the potential of the node **B1** is kept at an L level. Then, the transistor **201B** is kept off, so that the wiring **112B** and the wiring **111** are kept in a non-conduction state.

(355) In addition, a state is kept in which the circuit **300B** supplies an L signal or the voltage **V1** to the node **B2**. Thus, the potential of the node **B2** is kept at an L level. Then, the transistor **202B** is kept off, so that the wiring **113B** and the wiring **111** are kept in a non-conduction state.

(356) Next, the operation of the semiconductor device in a period **a2** is similar to the operation of the semiconductor device in the period **a1**, as illustrated in FIG. **20A**. Note that the operation of the semiconductor device in the period **a2** differs from the operation of the semiconductor device in the period **a1** in that the signal **SELA** is set at an L level and that the signal **SELB** is set at an H level.

(357) Next, the operation of the semiconductor device in a period **b2** is similar to the operation of the semiconductor device in the period **b1**, as illustrated in FIG. **20B**. Note that the operation of the semiconductor device in the period **b2** differs from the operation of the semiconductor device in the

period b1 in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(358) Next, the operation of the semiconductor device in a period c2 is described with reference to FIG. 21A. The operation of the semiconductor device in the period c2 differs from the operation of the semiconductor device in the period c1 in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(359) Since the signal SELA is set at an L level, the circuit 300A supplies an L signal or the voltage V1 to the node A2. Thus, the transistor 202A is turned off, so that the wiring 113A and the wiring 111 are brought out of conduction.

(360) In contrast, since the signal SELB is set at an H level, the circuit 300B supplies an H signal or the voltage V2 to the node B2. Thus, the transistor 202B is turned on, so that the wiring 113B and the wiring 111 are brought into conduction. Then, the voltage V1 is supplied to the wiring 111 through the transistor 202B.

(361) Note that in the period c2, the timing of when the clock signal CK1 is set at an L level might be earlier than the timing of when the transistor 201A is turned off. Thus, until the transistor 201A is turned off, it is preferable that the clock signal CK1 which is at an L level be supplied to the wiring 111 through the transistor 201A. When the channel width of the transistor 201A is increased, the fall time of the signal OUTA can be shortened.

(362) Note that in the period c2, the timing of when the clock signal CK1 is set at an L level might be earlier than the timing of when the transistor 201B is turned off. Thus, until the transistor 201B is turned off, it is preferable that the clock signal CK1 which is at an L level be supplied to the wiring 111 through the transistor 201B. When the channel width of the transistor 201B is increased, the fall time of the signal OUTB can be shortened.

(363) In the period c2, as for the wiring 111, there are the following three cases: the case where the voltage V1 is supplied to the wiring 111 through the transistor 202B; the case where the clock signal CK1 which is at an L level is supplied to the wiring 111 through the transistor 201B; and the case where the voltage V1 is supplied to the wiring 111 through the transistor 202B and the clock signal CK1 which is at an L level is supplied to the wiring 111 through the transistor 201B.

(364) Next, the operation of the semiconductor device in the period d2 is described with reference to FIG. 21B. The operation of the semiconductor device in the period d2 differs from the operation of the semiconductor device in the period d1 in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(365) Since the signal SELA is set at an L level, the circuit 300A supplies an L signal or the voltage V1 to the node A2. Thus, the transistor 202A is turned off, so that the wiring 113A and the wiring 111 are brought out of conduction.

(366) In contrast, since the signal SELB is set at an H level, the circuit 300B supplies an H signal or the voltage V2 to the node B2. Thus, the transistor 202B is turned on, so that the wiring 113B and the wiring 111 are brought into conduction. Then, the voltage V1 is supplied to the wiring 111 through the transistor 202B.

(367) The transistor 202A and the transistor 202B are alternately turned on as described above, so that deterioration in characteristics of the transistors can be suppressed. Thus, a material which easily deteriorates, such as a non-single-crystal semiconductor (e.g., an amorphous semiconductor or a microcrystalline semiconductor), an organic semiconductor, or an oxide semiconductor, can be used as a semiconductor layer of the transistor. Accordingly, when a semiconductor device is manufactured, the number of steps can be reduced, yield can be increased, or cost can be reduced. In addition, in the case where the semiconductor device in this embodiment is used for a display device, a method for manufacturing a semiconductor device is facilitated, so that the size of the display device can be increased.

(368) Since deterioration of the transistors can be suppressed, it is not necessary to increase the channel width of the transistor in consideration of deterioration of the transistor. Thus, the channel width of the transistor can be decreased, so that the layout area can be decreased. In particular, in

the case where the semiconductor device in this embodiment is used for a display device, the layout area of the gate driver circuit can be decreased; thus, the resolution of a pixel can be increased. Further, since the channel width of the transistor can be decreased, the load of the gate driver circuit can be decreased. Thus, the power consumption of a driver circuit including the gate driver circuit can be reduced.

(369) In the period **b1** and the period **b2**, the clock signal **CK1** which is at an H level is supplied to the wiring **111** through the transistor **201A** and the transistor **201B**; thus, the rise time or fall time of the signal supplied to the wiring **111** can be shortened. Thus, a video signal for a pixel in a different row can be prevented from being written to a pixel in a selected row. Accordingly, crosstalk can be reduced. Thus, the display quality of the display device can be improved.

(370) Since the rise time or fall time of the signal supplied to the wiring **111** can be shortened, in the case where a scan signal corresponds to a start signal or the like, the drive frequency of the gate driver circuit can be increased. Thus, in the case where the semiconductor device in this embodiment is used for the display device, the size of the display device can be increased or the resolution of the pixel can be increased.

(371) Note that the waveforms of the signal **OUTA** and the signal **OUTB** in the period **T1** correspond to the timing chart in FIG. **6K**. As the waveforms of the signal **OUTA** and the signal **OUTB** in the period **T1**, the waveforms in FIGS. **6A** to **6L** can be used.

(372) Note that the waveforms of the signal **OUTA** and the signal **OUTB** in the period **T2** correspond to the timing chart in FIG. **7K**. As the waveforms of the signal **OUTA** and the signal **OUTB** in the period **T2**, the waveforms in FIGS. **7A** to **7L** can be used.

(373) Note that the clock signal **CK1** can be an unbalanced signal. FIG. **22** is a timing chart illustrating an operation example of the semiconductor device at the time when the length of a period during which the clock signal **CK1** is at an H level is shorter than the length of a period during which the clock signal **CK1** is at an L level in one cycle. In the timing chart in FIG. **22**, the fall time of the signal **OUTA** and the fall time of the signal **OUTB** can be shortened because the clock signal **CK1** which is at an L level can be supplied to the wiring **111** in the period **c1** or the period **c2**. In particular, in the case where the wiring **111** is formed so as to extend to the pixel portion, a video signal that should not be originally written can be prevented from being written to a pixel. Alternatively, the length of the period during which the clock signal **CK1** is at an H level may be longer than the length of the period during which the clock signal **CK1** is at an L level in one cycle.

(374) Note that in the semiconductor device, a multi-phase clock signal can be used. For example, an n-phase (n is a natural number) clock signal can be used in the semiconductor device. The n-phase clock signal is n clock signals whose cycles are shifted by 1/n cycle. FIG. **23** is a timing chart illustrating an operation example of the semiconductor device at the time when a three-phase clock signal is used in the semiconductor device.

(375) Note that the larger n becomes, the lower clock frequency becomes. Thus, power consumption can be reduced. However, when n is too large, the number of signals is increased; thus, the layout area is increased or the size of an external circuit is increased. Accordingly, n is smaller than 8, preferably smaller than 6, more preferably 4 or 3.

(376) Note that in the period **c1**, the period **d1**, the period **c2**, or the period **d2**, the transistor **202A** and the transistor **202B** can be turned on at the same time. Thus, when the voltage **V1** is supplied to the wiring **111** through the transistor **202A** and the transistor **202B**, noise in the wiring **111** can be reduced. Accordingly, a semiconductor device which is hardly affected by noise can be obtained.

(377) Note that in the period **a1**, the period **b1**, the period **a2**, or the period **b2**, one of the transistor **201A** and the transistor **201B** can be turned on. For example, in the period **a1** and the period **b1**, the transistor **201A** can be turned on and the transistor **201B** can be turned off. Alternatively, in the period **a2** and the period **b2**, the transistor **201A** can be turned off and the transistor **201B** can be turned on. Thus, the frequency of turning on the transistor **201A** and the frequency of turning on

the transistor **2011B** are decreased. Accordingly, deterioration of the transistors can be suppressed.

(378) In order to perform such a driving method, for example, it is preferable that a signal input to the wiring **114B** be kept at an L level in the period **T1** and a signal input to the wiring **114A** be kept at an L level in the period **T2**. As another example, it is preferable that a circuit that has a function of keeping the potential of the node **A1** at an L level in accordance with the signal **SELA** in the period **T1** be provided in the circuit **200A** and a circuit that has a function of keeping the potential of the node **B1** at an L level in accordance with the signal **SELB** in the period **T2** be provided in the circuit **200B**.

(379) <Size of Transistor>

(380) Next, the size of a transistor, such as the channel width of a transistor or the channel length of a transistor, is described. Note that the channel width of a transistor can also be referred to as the W/L (W is the channel width and L is the channel length) ratio of a transistor.

(381) It is preferable that the channel width of the transistor **201A** be substantially equal to the channel width of the transistor **201B**. Alternatively, it is preferable that the channel width of the transistor **202A** be substantially equal to the channel width of the transistor **202B**.

(382) By making the transistors have substantially the same channel width in this manner, the transistors can have substantially the same current supply capability or substantially the same degree of deterioration. Accordingly, even when transistors which are selected are switched, the waveforms of output signals **OUT** can be substantially the same.

(383) From a similar reason, it is preferable that the channel length of the transistor **201A** be substantially equal to the channel length of the transistor **201B**. Alternatively, it is preferable that the channel length of the transistor **202A** be substantially equal to the channel length of the transistor **202B**.

(384) Note that in the case where the load of a gate signal line connected to the transistor **201A** or the transistor **201B** is driven is heavy, it is preferable that the channel width of the transistor **201A** be larger than those of the other transistors included in the circuit **200A** or the channel width of the transistor **201B** be larger than those of the other transistors included in the circuit **200B** in the circuit **200B**.

(385) Note that in the case where the load of a gate signal line through which the transistor **201A** or the transistor **201B** is driven is heavy, it is preferable that the channel width of the transistor **201A** or the transistor **201B** be made large. Specifically, each of the channel width of the transistor **201A** and the channel width of the transistor **201B** is preferably 1000 to 30000 μm , more preferably 2000 to 20000 μm , still more preferably 3000 to 8000 μm or 10000 to 18000 μm .

(386) <Structure of Semiconductor Device>

(387) Next, examples of circuit diagrams of a semiconductor device in this embodiment that is different from the structure example of the semiconductor device in FIG. **16A** are described with reference to FIG. **16B**, FIGS. **24A** and **24B**, and FIGS. **25A** and **25B**.

(388) FIG. **16B**, FIGS. **24A** and **24B**, and FIGS. **25A** and **25B** each illustrate an example of a circuit diagram of the semiconductor device.

(389) The semiconductor device illustrated in FIG. **16B** has a structure where a capacitor **203A** is connected between the gate of the transistor **201A** and the second terminal of the transistor **201A** included in the semiconductor device illustrated in FIG. **16A**. Alternatively, the semiconductor device illustrated in FIG. **16B** has a structure where a capacitor **203B** is connected between the gate of the transistor **201B** and the second terminal of the transistor **201B** included in the semiconductor device illustrated in FIG. **16A**.

(390) With such a structure, the potential of the node **A1** or the potential of the node **B1** is likely to rise in bootstrap operation. Thus, a potential difference V_{gs} between the gate and the source of the transistor **201A** can be made larger than a potential difference V_{gs} between the gate and the source of the transistor **201B**. Accordingly, the channel width of the transistor **201A** or the transistor **201B** can be made small. Alternatively, the fall time or rise time of the signal **OUTA** or the signal **OUTB**

can be shortened.

(391) A MOS capacitor can be used as each of the capacitor **203A** and the capacitor **203B**, for example. Note that the material of one electrode of each of the capacitor **203A** and the capacitor **203B** is preferably a material which is similar to the material of each of the gates of the transistor **201A** and the transistor **201B**. Alternatively, the material of the other electrode of each of the capacitor **203A** and the capacitor **203B** is preferably a material which is similar to the material of each of the sources or drains of the transistor **201A** and the transistor **201B**. With such a material, the layout area can be decreased or the capacitance value can be increased.

(392) Note that it is preferable that the capacitance value of the capacitor **203A** and the capacitance value of the capacitor **203B** be substantially equal. Alternatively, it is preferable that an area where one electrode and the other electrode overlap with each other in the capacitor **203A** and an area where one electrode and the other electrode overlap with each other in the capacitor **203B** be substantially equal. With such a structure, between the case where a signal is input from the circuit **200A** to the wiring **111** and the case where a signal is input from the circuit **200B** to the wiring **111**, the wavelengths of the signals input to the wiring **111** can be substantially equal.

(393) In addition, in the semiconductor devices illustrated in FIGS. **16A** and **16B**, as illustrated in FIG. **24A**, the transistor **201A** may be replaced with a diode **211A**. One electrode (e.g., a positive electrode) of the diode **211A** is connected to the node **A1**, and the other electrode (e.g., a negative electrode) of the diode **211A** is connected to the wiring **111**. Alternatively, the transistor **202A** may be replaced with a diode **212A**. One electrode (e.g., a positive electrode) of the diode **212A** is connected to the wiring **111**, and the other electrode (e.g., a negative electrode) of the diode **212A** is connected to the node **A2**.

(394) Further, the transistor **201B** may be replaced with a diode **211B**. One electrode (e.g., a positive electrode) of the diode **211B** is connected to the node **B1**, and the other electrode (e.g., a negative electrode) of the diode **211B** is connected to the wiring **111**. Alternatively, the transistor **202B** may be replaced with a diode **212B**. One electrode (e.g., a positive electrode) of the diode **212B** is connected to the wiring **111**, and the other electrode (e.g., a negative electrode) of the diode **212B** is connected to the node **B2**.

(395) In the semiconductor devices illustrated in FIGS. **16A** and **16B**, as illustrated in FIG. **24B**, the first terminal of the transistor **201A** may be connected to the node **A1**. In addition, the first terminal of the transistor **202A** may be connected to the node **A2** and the gate of the transistor **202A** may be connected to the wiring **111**.

(396) The first terminal of the transistor **201B** may be connected to the node **B1**. In addition, the first terminal of the transistor **202B** may be connected to the node **B2** and the gate of the transistor **202B** may be connected to the wiring **111**.

(397) Next, examples of a semiconductor device which generates a transfer signal in addition to the signal **OUTA** or generates a transfer signal in addition to the signal **OUTB** are described with reference to FIGS. **25A** and **25B**.

(398) In the case where the semiconductor device includes a plurality of circuits (including the circuit **200A** and the circuit **200B**), when a transfer signal is not input to the wiring **111** but is input as a start signal to a circuit in the next stage, delay or distortion of the transfer signal can be further reduced as compared to the signal **OUTA** or the signal **OUTB**. Thus, the semiconductor device can be driven by a signal whose delay or distortion is reduced, so that delay of an output signal of the semiconductor device can be reduced. Alternatively, the timing of storing electricity in the node **A1** or the node **B1** can be made earlier, so that the operation range can be made wider. In addition, a transfer signal may be output to the wiring **111**.

(399) Thus, in the semiconductor devices illustrated in FIGS. **16A** and **16B** and FIGS. **24A** and **24B**, as illustrated in FIG. **25A**, the circuit **200A** may include a transistor **204A**. A first terminal of the transistor **204A** is connected to the wiring **112A**; a second terminal of the transistor **204A** is connected to a wiring **117A**; a gate of the transistor **204A** is connected to the node **A1**. In addition,

the circuit **200B** may include a transistor **204B**. A first terminal of the transistor **204B** is connected to the wiring **112B**; a second terminal of the transistor **204B** is connected to a wiring **117B**; a gate of the transistor **204B** is connected to the node **B1**.

(400) Alternatively, in the semiconductor devices illustrated in FIGS. **16A** and **16B** and FIGS. **24A** and **24B**, as illustrated in FIG. **25B**, the circuit **200A** may include a transistor **205A**. A first terminal of the transistor **205A** is connected to the wiring **113A**; a second terminal of the transistor **205A** is connected to the wiring **117A**; a gate of the transistor **205A** is connected to the node **A2**. In addition, the circuit **200B** may include a transistor **205B**. A first terminal of the transistor **205B** is connected to the wiring **113B**; a second terminal of the transistor **205B** is connected to the wiring **117B**; a gate of the transistor **205B** is connected to the node **B2**.

(401) Note that the transistor **204A** preferably has a function that is similar to the function of the transistor **201A** and the same polarity as the transistor **201A**. The transistor **205A** preferably has a function that is similar to the function of the transistor **202A** and the same polarity as the transistor **202A**. The transistor **204B** preferably has a function that is similar to the function of the transistor **201B** and the same polarity as the transistor **201B**. The transistor **205B** preferably has a function that is similar to the function of the transistor **202B** and the same polarity as the transistor **202B**. Note that the transistor **204A**, the transistor **204B**, the transistor **205A**, and the transistor **205B** may be either n-channel transistors or p-channel transistors.

(402) Note that in the case where the plurality of circuits included in the semiconductor device are connected to each other, the wiring **117A** may be connected to the wiring **114A** in the semiconductor device in a different stage (e.g., the next stage). In addition, the wiring **117B** may be connected to the wiring **114B** in the semiconductor device in a different stage (e.g., the next stage). With such a structure, the wiring **117A** and the wiring **117B** function as signal lines.

(403) Note that in the case where the plurality of circuits included in the semiconductor device are connected to each other, the wiring **117A** may be connected to the wiring **116A** in the semiconductor device in a different stage (e.g., the preceding stage). In addition, the wiring **117B** may be connected to the wiring **116B** in the semiconductor device in a different stage (e.g., the preceding stage). Further, the wiring **117A** may extend to the pixel portion. Furthermore, the wiring **117B** may extend to the pixel portion. With such a structure, the wiring **117A** and the wiring **117B** function as gate signal lines or scan lines.

(404) <Structure of Semiconductor Device>

(405) Next, an example of a circuit diagram of a semiconductor device in this embodiment that is different from the structure examples of the semiconductor device in FIGS. **16A** and **16B**, FIGS. **24A** and **24B**, and FIGS. **25A** and **25B** is described with reference to FIG. **26**.

(406) The semiconductor device illustrated in FIG. **26** has a structure where a transistor **207A** and a transistor **207B** are provided in the semiconductor device illustrated in FIG. **16A**.

(407) A first terminal of the transistor **207A** is connected to the wiring **113A**. A second terminal of the transistor **207A** is connected to the wiring **111**. A gate of the transistor **207A** is connected to the circuit **300A**. A first terminal of the transistor **207B** is connected to the wiring **113B**. A second terminal of the transistor **207B** is connected to the wiring **111**. A gate of the transistor **207B** is connected to the circuit **300B**.

(408) Note that a portion where the gate of the transistor **207A** and the circuit **300A** are connected to each other is referred to as a node **A3**, and a portion where the gate of the transistor **207B** and the circuit **300B** are connected to each other is referred to as a node **B3**.

(409) Note that the transistor **207A** preferably has a function that is similar to the function of the transistor **202A**. The transistor **207B** preferably has a function that is similar to the function of the transistor **202B**.

(410) <Operation of Semiconductor Device>

(411) An operation example of the semiconductor device in FIG. **26** is described with reference to a timing chart illustrated in FIG. **27**. FIGS. **28A** and **28B** and FIGS. **29A** and **29B** each illustrate an

operation example of the semiconductor device in FIG. 26.

(412) The transistor 202A and the transistor 207A are alternately turned on every other gate selection period or every other half cycle of the clock signal CK1 in the period T1. For example, in a period during which the clock signal CK1 is at an H level in the period d1, as illustrated in FIG. 28A, the transistor 202A is turned on and the transistor 207A is turned off. In contrast, in a period during which the clock signal CK1 is at an L level in the period d1, as illustrated in FIG. 28B, the transistor 202A is turned off and the transistor 207A is turned on.

(413) The transistor 202B and the transistor 207B are alternately turned on every other gate selection period or every other half cycle of the clock signal CK1 in the period T2. For example, in a period during which the clock signal CK1 is at an H level in the period d2, as illustrated in FIG. 29A, the transistor 202B is turned on and the transistor 207B is turned off. In contrast, in a period during which the clock signal CK1 is at an L level in the period d2, as illustrated in FIG. 29B, the transistor 202B is turned off and the transistor 207B is turned on.

(414) In this manner, the transistor 202A and the transistor 207A are alternately turned on in the period T1 and the transistor 202B and the transistor 207B are alternately turned on in the period T2. Accordingly, periods during which the transistors are on can be shortened; thus, deterioration of the transistors can be suppressed.

(415) A wiring to which the clock signal CK2 (e.g., an inversion signal of the clock signal CK1) is input may be connected to one of the node A2 and the node A3. In addition, a wiring to which the clock signal CK2 is input may be connected to one of the node B2 and the node B3.

(416) Alternatively, the transistor 202A, the transistor 207A, the transistor 202B, and the transistor 207B may be turned on in the same period (e.g., the period b1 or the period b2). Alternatively, two or more of the transistor 202A, the transistor 207A, the transistor 202B, and the transistor 207B may be turned on in the same period (e.g., the period a1 or the period a2).

(417) The order of turning on the transistor 202A and the transistor 207A may be set to a given order. In addition, the order of turning on the transistor 202B and the transistor 207B may be set to a given order.

(418) Next, a timing chart illustrating an operation example of the semiconductor device in FIG. 26 that is different from the operation example in FIG. 27 is described with reference to FIG. 30.

(419) The transistor 202A, the transistor 207A, the transistor 202B, and the transistor 207B may be sequentially turned on in frame periods. In FIG. 30, in the period T1, a period during which the transistor 202A is on is referred to as a period T1a, and a period during which the transistor 207A is on is referred to as a period T1b. In addition, in the period T2, a period during which the transistor 202B is on is referred to as a period T2a, and a period during which the transistor 207B is on is referred to as a period T2b.

(420) Note that although the timing chart in FIG. 30 illustrate the case where the period T1a, the period T2a, the period T1b, and the period T2b are provided in that order, the order of these periods may be set to a given order. For example, the period T1a, the period T1b, the period T2a, and the period T2b may be provided in that order; a plurality of each of these periods may be provided; or these periods may be provided in a random manner.

(421) In the period d1 in the period T1a, the potential of the node A2 is set at an H level, and the potential of the node A3 (the potential of the node A3 is also referred to as a potential Va3), the potential of the node B2, and the potential of the node B3 (the potential of the node B3 is also referred to as a potential Vb3) are set at an L level. Thus, as illustrated in FIG. 28A, the transistor 202A is turned on and the transistor 207A, the transistor 202B, and the transistor 207B are turned off.

(422) In the period d1 in the period T1b, the potential of the node A3 is set at an H level, and the potential of the node A2, the potential of the node B2, and the potential of the node B3 are set at an L level. Thus, as illustrated in FIG. 28B, the transistor 207A is turned on and the transistor 202A, the transistor 202B, and the transistor 207B are turned off.

(423) In the period d2 in the period T2a, the potential of the node B2 is set at an H level, and the potential of the node A2, the potential of the node A3, and the potential of the node B3 are set at an L level. Thus, as illustrated in FIG. 29A, the transistor 202B is turned on and the transistor 202A, the transistor 207A, and the transistor 207B are turned off.

(424) In the period d2 in the period T2b, the potential of the node B3 is set at an H level, and the potential of the node A2, the potential of the node A3, and the potential of the node B2 are set at an L level. Thus, as illustrated in FIG. 29B, the transistor 207B is turned on and the transistor 202A, the transistor 207A, and the transistor 202B are turned off.

(425) When the semiconductor device illustrated in FIG. 26 performs the above operation, a period during which the transistor is on can be shortened. Alternatively, the frequency of a signal for controlling on and off of the transistor can be lowered, so that power consumption can be reduced.

(426) A plurality of transistors may be provided. A first terminal of each of the plurality of transistors is connected to the wiring 113A, and a second terminal of each of the plurality of transistors is connected to the wiring 111. The plurality of transistors have a function that is similar to the function of the transistor 202A or the transistor 207A. The plurality of transistors may be sequentially turned on in gate selection periods or in frame periods, for example.

(427) In addition, a plurality of transistors may be provided. A first terminal of each of the plurality of transistors is connected to the wiring 113B, and a second terminal of each of the plurality of transistors is connected to the wiring 111. The plurality of transistors have a function that is similar to the function of the transistor 202B or the transistor 207B. The plurality of transistors may be sequentially turned on in gate selection periods or in frame periods, for example.

(428) With provision of such a plurality of transistors, periods during which the transistors are on can be shortened; thus, deterioration of the transistors can be suppressed.

Embodiment 5

(429) In this embodiment, a semiconductor device including the gate driver circuit described in any of the above embodiments is described.

(430) <Structure of Semiconductor Device>

(431) The structure of a semiconductor device in this embodiment is described with reference to FIGS. 31A and 31B. FIGS. 31A and 31B each illustrate an example of a circuit diagram of the semiconductor device.

(432) In FIG. 31A, the circuit 300A includes a transistor 301A, a transistor 302A, and a circuit 400A. The circuit 300B includes a transistor 301B, a transistor 302B, and a circuit 400B.

(433) Structure examples of the transistor 301A, the transistor 302A, the circuit 400A, the transistor 301B, the transistor 302B, and the circuit 400B are described with reference to FIG. 31A. Here, the transistor 301A, the transistor 302A, the transistor 301B, and the transistor 302B are described as n-channel transistors. Note that these transistors may be p-channel transistors.

(434) A first terminal of the transistor 301A is connected to the wiring 114A. A second terminal of the transistor 301A is connected to the node A1. A gate of the transistor 301A is connected to the wiring 114A. A first terminal of the transistor 302A is connected to the wiring 113A. A second terminal of the transistor 302A is connected to the node A1. A gate of the transistor 302A is connected to the wiring 116A. The circuit 400A is connected to the wiring 115A, the node A1, the wiring 113A, and the node A2.

(435) A first terminal of the transistor 301B is connected to the wiring 114B. A second terminal of the transistor 301B is connected to the node B1. A gate of the transistor 301B is connected to the wiring 114B. A first terminal of the transistor 302B is connected to the wiring 113B. A second terminal of the transistor 302B is connected to the node B1. A gate of the transistor 302B is connected to the wiring 116B. The circuit 400B is connected to the wiring 115B, the node B1, the wiring 113B, and the node B2.

(436) Next, examples of the functions of the transistor 301A, the transistor 302A, the circuit 400A, the transistor 301B, the transistor 302B, and the circuit 400B are described.

(437) The transistor **301A** has a function of controlling the timing of bringing the wiring **114A** and the node **A1** into conduction. Alternatively, the transistor **301A** has a function of controlling the timing of supplying the potential of the wiring **114A** to the node **A1**. Alternatively, the transistor **301A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the start signal **SP**, the clock signal **CK1**, the clock signal **CK2**, the signal **SELA**, the signal **SELB**, or the voltage **V2**) which is to be input to the wiring **114A** to the node **A1**. Alternatively, the transistor **301A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **A1**. Alternatively, the transistor **301A** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **A1**. Alternatively, the transistor **301A** has a function of controlling the timing of raising the potential of the node **A1**. Alternatively, the transistor **301A** has a function of controlling the timing of setting the node **A1** to be in a floating state.

(438) As described above, the transistor **301A** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like. Note that the transistor **301A** may be controlled in accordance with the start signal **SP**.

(439) The transistor **302A** has a function of controlling the timing of bringing the wiring **113A** and the node **A1** into conduction. Alternatively, the transistor **302A** has a function of controlling the timing of supplying the potential of the wiring **113A** to the node **A1**. Alternatively, the transistor **302A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113A** to the node **A1**. Alternatively, the transistor **302A** has a function of controlling the timing of supplying the voltage **V1** to the node **A1**. Alternatively, the transistor **302A** has a function of controlling the timing of lowering the potential of the node **A1**. Alternatively, the transistor **302A** has a function of controlling the timing of keeping the potential of the node **A1**.

(440) As described above, the transistor **302A** functions as a switch. Note that the transistor **302A** may be controlled in accordance with the reset signal **RE**.

(441) The circuit **400A** has a function of controlling the potential of the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of supplying an H signal or the voltage **V2** to the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of raising the potential of the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of lowering the potential of the node **A2**. Alternatively, the circuit **400A** has a function of controlling the timing of keeping the potential of the node **A2**.

(442) As described above, the circuit **400A** functions as a control circuit. Note that the circuit **400A** may be controlled in accordance with the signal **SELA** or the potential of the node **A1**.

(443) The transistor **301B** has a function of controlling the timing of bringing the wiring **114B** and the node **B1** into conduction. Alternatively, the transistor **301B** has a function of controlling the timing of supplying the potential of the wiring **114B** to the node **B1**. Alternatively, the transistor **301B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the start signal **SP**, the clock signal **CK1**, the clock signal **CK2**, the signal **SELA**, the signal **SELB**, or the voltage **V2**) which is to be input to the wiring **114B** to the node **B1**. Alternatively, the transistor **301B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **B1**. Alternatively, the transistor **301B** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **B1**. Alternatively, the transistor **301B** has a function of controlling the timing of raising the potential of the node **B1**. Alternatively, the transistor **301B** has a function of controlling the timing of setting the node **B1** to be in a floating state.

(444) As described above, the transistor **301B** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like. Note that the transistor **301B** may be controlled in

accordance with the start signal SP.

(445) The transistor **302B** has a function of controlling the timing of bringing the wiring **113B** and the node **B1** into conduction. Alternatively, the transistor **302B** has a function of controlling the timing of supplying the potential of the wiring **113B** to the node **B1**. Alternatively, the transistor **302B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113B** to the node **B1**.

Alternatively, the transistor **302B** has a function of controlling the timing of supplying the voltage **V1** to the node **B1**. Alternatively, the transistor **302B** has a function of controlling the timing of lowering the potential of the node **B1**. Alternatively, the transistor **302B** has a function of controlling the timing of keeping the potential of the node **B1**.

(446) As described above, the transistor **302B** functions as a switch. Note that the transistor **302B** may be controlled in accordance with the reset signal **RE**.

(447) The circuit **400B** has a function of controlling the potential of the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of raising the potential of the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of lowering the potential of the node **B2**. Alternatively, the circuit **400B** has a function of controlling the timing of keeping the potential of the node **B2**.

(448) As described above, the circuit **400B** functions as a control circuit. Note that the circuit **400B** may be controlled in accordance with the signal **SELB** or the potential of the node **B1**.

(449) Next, structure examples of the circuit **400A** and the circuit **400B** are described with reference to FIG. **31B**.

(450) The circuit **400A** includes a transistor **401A** and a transistor **402A**. The circuit **400B** includes a transistor **401B** and a transistor **402B**.

(451) Structure examples of the transistor **401A**, the transistor **402A**, the transistor **401B**, and the transistor **402B** are described with reference to FIG. **31B**. Here, the transistor **401A**, the transistor **402A**, the transistor **401B**, and the transistor **402B** are described as n-channel transistors. Note that these transistors may be p-channel transistors.

(452) A first terminal of the transistor **401A** is connected to the wiring **115A**. A second terminal of the transistor **401A** is connected to the node **A2**. A gate of the transistor **401A** is connected to the wiring **115A**. A first terminal of the transistor **402A** is connected to the wiring **113A**. A second terminal of the transistor **402A** is connected to the node **A2**. A gate of the transistor **402A** is connected to the node **A1**.

(453) A first terminal of the transistor **401B** is connected to the wiring **115B**. A second terminal of the transistor **401B** is connected to the node **B2**. A gate of the transistor **401B** is connected to the wiring **115B**. A first terminal of the transistor **402B** is connected to the wiring **113B**. A second terminal of the transistor **402B** is connected to the node **B2**. A gate of the transistor **402B** is connected to the node **B1**.

(454) Next, examples of the functions of the transistor **401A**, the transistor **402A**, the transistor **401B**, and the transistor **402B** are described.

(455) The transistor **401A** has a function of controlling the timing of bringing the wiring **115A** and the node **A2** into conduction. Alternatively, the transistor **401A** has a function of controlling the timing of supplying the potential of the wiring **115A** to the node **A2**. Alternatively, the transistor **401A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the signal **SELA** or the voltage **V2**) which is to be input to the wiring **115A** to the node **A2**.

Alternatively, the transistor **401A** has a function of controlling the timing of not supplying a signal

or voltage to the node A2. Alternatively, the transistor **401A** has a function of controlling the timing of supplying an H signal, the voltage **12**, or the like to the node A2. Alternatively, the transistor **401A** has a function of controlling the timing of raising the potential of the node A2.

(456) As described above, the transistor **401A** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like. Note that the transistor **401A** may be controlled in accordance with the signal SELA.

(457) The transistor **402A** has a function of controlling the timing of bringing the wiring **113A** and the node A2 into conduction. Alternatively, the transistor **402A** has a function of controlling the timing of supplying the potential of the wiring **113A** to the node A2. Alternatively, the transistor **402A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal CK2 or the voltage V1) which is to be input to the wiring **113A** to the node A2. Alternatively, the transistor **402A** has a function of controlling the timing of supplying the voltage V1 to the node A2. Alternatively, the transistor **402A** has a function of controlling the timing of lowering the potential of the node A2. Alternatively, the transistor **402A** has a function of controlling the timing of keeping the potential of the node A2.

(458) As described above, the transistor **402A** functions as a switch. Note that the transistor **402A** may be controlled in accordance with the potential of the node A1 or the potential of the wiring **111**.

(459) The transistor **401B** has a function of controlling the timing of bringing the wiring **115B** and the node B2 into conduction. Alternatively, the transistor **401B** has a function of controlling the timing of supplying the potential of the wiring **115B** to the node B2. Alternatively, the transistor **401B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the signal SELB or the voltage V2) which is to be input to the wiring **115B** to the node B2. Alternatively, the transistor **401B** has a function of controlling the timing of not supplying a signal or voltage to the node B2. Alternatively, the transistor **401B** has a function of controlling the timing of supplying an H signal, the voltage V2, or the like to the node B2. Alternatively, the transistor **401B** has a function of controlling the timing of raising the potential of the node B2.

(460) As described above, the transistor **401B** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like. Note that the transistor **401B** may be controlled in accordance with the signal SELB.

(461) The transistor **402B** has a function of controlling the timing of bringing the wiring **113B** and the node B2 into conduction. Alternatively, the transistor **402B** has a function of controlling the timing of supplying the potential of the wiring **113B** to the node B2. Alternatively, the transistor **402B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal CK2 or the voltage V1) which is to be input to the wiring **113B** to the node B2. Alternatively, the transistor **402B** has a function of controlling the timing of supplying the voltage V1 to the node B2. Alternatively, the transistor **402B** has a function of controlling the timing of lowering the potential of the node B2. Alternatively, the transistor **402B** has a function of controlling the timing of keeping the potential of the node B2.

(462) As described above, the transistor **402B** functions as a switch. Note that the transistor **402B** may be controlled in accordance with the potential of the node B1 or the potential of the wiring **111**.

(463) <Operation of Semiconductor Device>

(464) Next, operation examples of the semiconductor device in FIG. **31B** are described with reference to FIGS. **32A** and **32B**, FIGS. **33A** and **33B**, FIGS. **34A** and **34B**, and FIGS. **35A** and **35B**. FIG. **32A**, FIG. **32B**, FIG. **33A**, FIG. **33B**, FIG. **34A**, FIG. **34B**, FIG. **35A**, and FIG. **35B** correspond to the schematic views of the semiconductor device in the period a1, the period b1, the period c1, the period d1, the period a2, the period b2, the period c2, and the period d2 described in Embodiment 4, respectively.

(465) Note that the operation of a portion of the semiconductor device in FIG. **31B** that is common

with a portion of the semiconductor device in FIG. 16A is described with reference to the timing chart in FIG. 17.

(466) First, as illustrated in FIG. 32A, in the period a1, the start signal SP is set at an H level. Thus, the transistor 301A is turned on, so that the wiring 114A and the node A1 are brought into conduction. Then, the start signal SP which is at an H level is supplied to the node A1 through the transistor 301A, so that the potential of the node A1 rises.

(467) After the potential of the node A1 becomes $V2 - V_{th.sub.301A}$ (which is obtained by subtraction of the threshold voltage of the transistor 301A ($V_{th.sub.301A}$) from the potential of the gate of the transistor 301A (e.g., the voltage V2), the transistor 301A is turned off. Thus, the wiring 114A and the node A1 are brought out of conduction, so that the potential of the node A1 rises. When the potential of the node A1 rises, the transistor 402A is turned on; thus, the wiring 113A and the node A2 are brought into conduction. Then, the voltage V1 is supplied to the node A2 through the transistor 402A.

(468) In addition, in the period a1, the signal SELA is set at an H level. Thus, the transistor 401A is turned on, so that the wiring 115A and the node A2 are brought into conduction. Accordingly, the signal SELA which is at an H level is supplied to the node A2 through the transistor 401A. Here, when the current supply capability of the transistor 402A is made higher than the current supply capability of the transistor 401A (e.g., the channel width of the transistor 402A is made larger than the channel width of the transistor 401A), the potential of the node A2 is set at an L level.

(469) Note that in the period a1, the reset signal RE is set at an L level. Thus, the transistor 302A is turned off, so that the wiring 113A and the node A1 are brought out of conduction.

(470) In contrast, in the period a1, the start signal SP is set at an H level. Thus, the transistor 301B is turned on, so that the wiring 114B and the node B1 are brought into conduction. Then, the start signal SP which is at an H level is supplied to the node B1 through the transistor 301B, so that the potential of the node B1 rises.

(471) After the potential of the node B1 becomes $V2 - V_{th.sub.301B}$ (which is obtained by subtraction of the threshold voltage of the transistor 301B ($V_{th.sub.301B}$) from the potential of the gate of the transistor 301B (e.g., the voltage V2), the transistor 301B is turned off. Thus, the wiring 114B and the node B1 are brought out of conduction, so that the potential of the node B1 rises. When the potential of the node B1 rises, the transistor 402B is turned on; thus, the wiring 113B and the node B2 are brought into conduction. Then, the voltage V1 is supplied to the node B2 through the transistor 402B.

(472) In addition, in the period a1, the signal SELB is set at an L level. Thus, the transistor 401B is turned off, so that the wiring 115B and the node B2 are brought out of conduction. Accordingly, the potential of the node B2 is set at an L level.

(473) Note that in the period a1, the reset signal RE is set at an L level. Thus, the transistor 302B is turned off, so that the wiring 113B and the node B1 are brought out of conduction.

(474) Next, as illustrated in FIG. 32B, in the period b1, the start signal SP is set at an L level. Thus, the transistor 301A is kept off, so that the wiring 114A and the node A1 are kept in a non-conduction state.

(475) In addition, in the period b1, the reset signal RE is kept at an L level. Thus, the transistor 302A is kept off, so that the wiring 113A and the node A1 are kept in a non-conduction state. The potential of the node A1 is raised by bootstrap operation. Thus, the transistor 402A is kept on, so that the wiring 113A and the node A2 are kept in a conduction state.

(476) In addition, in the period b1, the signal SELA is kept at an H level. Thus, the transistor 401A is kept on, so that the wiring 115A and the node A2 are kept in a conduction state. Accordingly, the potential of the node A2 is kept at an L level.

(477) In contrast, in the period b1, when the start signal SP is set at an L level, the transistor 301B is kept off; thus, the wiring 114B and the node B1 are kept in a non-conduction state.

(478) In addition, in the period b1, the reset signal RE is kept at an L level. Thus, the transistor

302B is kept off, so that the wiring **113B** and the node **B1** are kept in a non-conduction state. The potential of the node **B1** is raised by bootstrap operation. Thus, the transistor **402B** is kept on, so that the wiring **113B** and the node **B2** are kept in a conduction state.

(479) Further, in the period **b1**, the signal **SELB** is set at an L level. Thus, the transistor **401B** is kept off, so that the wiring **115B** and the node **B2** are kept in a non-conduction state. Accordingly, the potential of the node **B2** is kept at an L level.

(480) Next, as illustrated in FIG. **33A**, in the period **c1**, the start signal **SP** is kept at an L level. Thus, the transistor **301A** is kept off, so that the wiring **114A** and the node **A1** are kept in a non-conduction state.

(481) In addition, in the period **c1**, the reset signal **RE** is set at an H level. Thus, the transistor **302A** is turned on, so that the wiring **113A** and the node **A1** are brought into conduction. Then, the voltage **V1** is supplied to the node **A1** through the transistor **302A**, so that the potential of the node **A1** is lowered and set at an L level. When the potential of the node **A1** is set at an L level, the transistor **402A** is turned off; thus, the wiring **113A** and the node **A2** are brought out of conduction.

(482) Further, in the period **c1**, the signal **SELA** is kept at an H level. Thus, the transistor **401A** is kept on, so that the wiring **115A** and the node **A2** are kept in a conduction state. Then, the signal **SELA** which is at an H level is supplied to the node **A2** through the transistor **401A**, so that the potential of the node **A2** is raised and set at an H level.

(483) In contrast, in the period **c1**, the start signal **SP** is kept at an L level. Thus, the transistor **301B** is kept off, so that the wiring **114B** and the node **B1** are kept in a non-conduction state.

(484) In addition, in the period **c1**, the reset signal **RE** is set at an H level. Thus, the transistor **302B** is turned on, so that the wiring **113B** and the node **B1** are brought into conduction. Then, the voltage **V1** is supplied to the node **B1** through the transistor **302B**, so that the potential of the node **B1** is lowered and set at an L level. When the potential of the node **B1** is set at an L level, the transistor **402B** is turned off; thus, the wiring **113B** and the node **B2** are brought out of conduction.

(485) Further, in the period **c1**, the signal **SELB** is kept at an L level. Thus, the transistor **401B** is kept off, so that the wiring **115B** and the node **B2** are kept in a non-conduction state. Accordingly, the node **B2** is set to be in a floating state, so that the potential of the node **B2** is kept at an L level.

(486) Next, as illustrated in FIG. **33B**, in the period **d1**, the start signal **SP** is kept at an L level. Thus, the transistor **301A** is kept off, so that the wiring **114A** and the node **A1** are kept in a non-conduction state.

(487) In addition, in the period **d1**, the reset signal **RE** is set at an L level. Thus, the transistor **302A** is turned off, so that the wiring **113A** and the node **A1** are kept in a non-conduction state. Then, the node **A1** is set to be in a floating state, so that the potential of the node **A1** is kept at an L level. Thus, the transistor **402A** is kept off, so that the wiring **113A** and the node **A2** are kept in a non-conduction state.

(488) Further, in the period **d1**, the signal **SELA** is kept at an H level. Thus, the transistor **401A** is kept on, so that the wiring **115A** and the node **A2** are kept in a conduction state. Then, the signal **SELA** which is at an H level is supplied to the node **A2** through the transistor **401A**, so that the potential of the node **A2** is raised and set at an H level.

(489) In contrast, in the period **d1**, the start signal **SP** is kept at an L level. Thus, the transistor **301B** is kept off, so that the wiring **114B** and the node **B1** are kept in a non-conduction state.

(490) In addition, in the period **d1**, the reset signal **RE** is set at an L level. Thus, the transistor **302B** is turned off, so that the wiring **113B** and the node **B1** are kept in a non-conduction state. Then, the node **B1** is set to be in a floating state, so that the potential of the node **B1** is kept at an L level. Thus, the transistor **402B** is kept off, so that the wiring **113B** and the node **B2** are kept in a non-conduction state.

(491) Further, in the period **d1**, the signal **SELB** is kept at an L level. Thus, the transistor **401B** is kept off, so that the wiring **115B** and the node **B2** are kept in a non-conduction state. Accordingly, the node **A2** is set to be in a floating state, so that the potential of the node **B2** is kept at an L level.

(492) Next, the operation of the semiconductor device in the period a2 is described with reference to FIG. 34A. The operation of the semiconductor device in the period a2 differs from the operation of the semiconductor device in the period a1 illustrated in FIG. 32A in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(493) Thus, the transistor 401A is turned off; so that the wiring 115A and the node A2 are brought out of conduction.

(494) In contrast, the transistor 401B is turned on, so that the wiring 115B and the node B2 are brought into conduction. Thus, the signal SELB which is at an H level is supplied to the node B2 through the transistor 401B. Here, when the current supply capability of the transistor 402B is made higher than the current supply capability of the transistor 401B (e.g., the channel width of the transistor 402B is made larger than the channel width of the transistor 401B), the potential of the node B2 is set at an L level.

(495) Next, the operation of the semiconductor device in the period b2 is described with reference to FIG. 34B. The operation of the semiconductor device in the period b2 differs from the operation of the semiconductor device in the period b1 illustrated in FIG. 32B in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(496) Thus, the transistor 401A is kept off, so that the wiring 115A and the node A2 are kept in a non-conduction state.

(497) In contrast, the transistor 401B is kept on, so that the wiring 115B and the node B2 are kept in a conduction state.

(498) Next, the operation of the semiconductor device in the period c2 is described with reference to FIG. 35A. The operation of the semiconductor device in the period c2 differs from the operation of the semiconductor device in the period c1 illustrated in FIG. 33A in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(499) Thus, the transistor 401A is kept off, so that the wiring 115A and the node A2 are brought out of conduction. Then, the node A2 is set to be in a floating state, so that the potential of the node A2 is kept at an L level.

(500) In contrast, the transistor 401B is kept on, so that the wiring 115B and the node B2 are kept in a conduction state. Thus, the signal SELB which is at an H level is supplied to the node B2 through the transistor 401B, so that the potential of the node B2 rises.

(501) Next, the operation of the semiconductor device in the period d2 is described with reference to FIG. 35B. The operation of the semiconductor device in the period d2 differs from the operation of the semiconductor device in the period d1 illustrated in FIG. 33B in that the signal SELA is set at an L level and that the signal SELB is set at an H level.

(502) Thus, the transistor 401A is kept off, so that the wiring 115A and the node A2 are brought out of conduction. Then, the node A2 is set to be in a floating state, so that the potential of the node A2 is kept at an L level.

(503) In contrast, the transistor 401B is kept on, so that the wiring 115B and the node B2 are kept in a conduction state. Thus, the signal SELB which is at an H level is supplied to the node B2 through the transistor 401B, so that the potential of the node B2 is kept at an H level.

(504) <Size of Transistor>

(505) Next, the size of a transistor, such as the channel width of a transistor or the channel length of a transistor, is described.

(506) It is preferable that the channel width of the transistor 301A be substantially equal to the channel width of the transistor 301B. Alternatively, it is preferable that the channel width of the transistor 302A be substantially equal to the channel width of the transistor 302B. Alternatively, it is preferable that the channel width of the transistor 401A be substantially equal to the channel width of the transistor 401B. Alternatively, it is preferable that the channel width of the transistor 402A be substantially equal to the channel width of the transistor 402B.

(507) By making the transistors have substantially the same channel width in this manner, the

transistors can have substantially the same current supply capability or substantially the same degree of deterioration. Accordingly, even when transistors which are selected are switched, the waveforms of output signals OUT can be substantially the same.

(508) From a similar reason, it is preferable that the channel length of the transistor **301A** be substantially equal to the channel length of the transistor **301B**. Alternatively, it is preferable that the channel length of the transistor **302A** be substantially equal to the channel length of the transistor **302B**. Alternatively, it is preferable that the channel length of the transistor **401A** be substantially equal to the channel length of the transistor **401B**. Alternatively, it is preferable that the channel length of the transistor **402A** be substantially equal to the channel length of the transistor **402B**.

(509) Specifically, each of the channel width of the transistor **301A** and the channel width of the transistor **301B** is preferably 500 to 3000 μm , more preferably 800 to 2500 μm , still more preferably 1000 to 2000 μm .

(510) Each of the channel width of the transistor **302A** and the channel width of the transistor **302B** is preferably 100 to 3000 μm , more preferably 300 to 2000 μm , still more preferably 300 to 1000 μm .

(511) Each of the channel width of the transistor **401A** and the channel width of the transistor **401B** is preferably 100 to 2000 μm , more preferably 200 to 1500 μm , still more preferably 300 to 700 μm .

(512) Each of the channel width of the transistor **402A** and the channel width of the transistor **402B** is preferably 300 to 3000 μm , more preferably 500 to 2000 μm , still more preferably 700 to 1500 μm .

(513) <Structure of Semiconductor Device>

(514) Next, examples of circuit diagrams of a semiconductor device in this embodiment that is different from the structure example of the semiconductor device in FIG. **31B** are described with reference to FIGS. **36A** and **36B**, FIGS. **37A** and **37B**, FIGS. **38A** and **38B**, FIGS. **39A** to **39F**, FIGS. **40A** to **40D**, and FIGS. **41A** and **41B**.

(515) FIGS. **36A** and **36B**, FIGS. **37A** and **37B**, FIGS. **38A** and **38B**, FIGS. **39A** to **39F**, FIGS. **40A** to **40D**, and FIGS. **41A** and **41B** each illustrate an example of a circuit diagram of the semiconductor device.

(516) The semiconductor device illustrated in FIG. **36A** has a structure where the first terminal of the transistor **202A** included in the semiconductor device illustrated in FIG. **31B**, the first terminal of the transistor **302A** included in the semiconductor device illustrated in FIG. **31B**, and the first terminal of the transistor **402A** included in the semiconductor device illustrated in FIG. **31B** are connected to different wirings. Alternatively, the semiconductor device illustrated in FIG. **36A** has a structure where the first terminal of the transistor **202B** included in the semiconductor device illustrated in FIG. **31B**, the first terminal of the transistor **302B** included in the semiconductor device illustrated in FIG. **31B**, and the first terminal of the transistor **402B** included in the semiconductor device illustrated in FIG. **31B** are connected to different wirings.

(517) In FIG. **36A**, the wiring **113A** is divided into a plurality of wirings **113A_1** to **113A_3**. The wiring **113B** is divided into a plurality of wirings **113B_1** to **113B_3**. The first terminal of the transistor **202A** is connected to the wiring **113A_1**. The first terminal of the transistor **302A** is connected to the wiring **113A_2**. The first terminal of the transistor **402A** is connected to the wiring **113A_3**. The first terminal of the transistor **202B** is connected to the wiring **113B_1**. The first terminal of the transistor **302B** is connected to the wiring **113B_2**. The first terminal of the transistor **402B** is connected to the wiring **113B_3**.

(518) Note that the wirings **113A_1** to **113A_3** have a function that is similar to the function of the wiring **113A**. The wirings **113B_1** to **113B_3** have a function that is similar to the function of the wiring **113B**. For example, voltage such as the voltage V1 can be supplied to the wirings **113A_1** to **113A_3** and the wirings **113B_1** to **113B_3**. Alternatively, different voltages or different signals

may be supplied to the wirings **113A_1** to **113A_3**. Alternatively, different voltages or different signals may be supplied to the wirings **113B_1** to **113B_3**.

(519) In addition, in the structures illustrated in FIG. **31B** and FIG. **36A**, as illustrated in FIG. **37A**, the transistor **302A** may be replaced with a diode **312A**. One electrode (e.g., a positive electrode) of the diode **312A** is connected to the node **A1**, and the other electrode (e.g., a negative electrode) of the diode **312A** is connected to the wiring **116A**. Alternatively, the transistor **402A** may be replaced with a diode **412A**. One electrode (e.g., a positive electrode) of the diode **412A** is connected to the node **A2**, and the other electrode (e.g., a negative electrode) of the diode **412A** is connected to the node **A1**.

(520) Further, the transistor **302B** may be replaced with a diode **312B**. One electrode (e.g., a positive electrode) of the diode **312B** is connected to the node **B1**, and the other electrode (e.g., a negative electrode) of the diode **312B** is connected to the wiring **116B**. Alternatively, the transistor **402B** may be replaced with a diode **412B**. One electrode (e.g., a positive electrode) of the diode **412B** is connected to the node **B2**, and the other electrode (e.g., a negative electrode) of the diode **412B** is connected to the node **B1**.

(521) Further, in the structures illustrated in FIG. **31B** and FIG. **36A**, as illustrated in FIG. **37B**, the first terminal of the transistor **302A** may be connected to the wiring **116A**, and the gate of the transistor **302A** may be connected to the node **A1**. Alternatively, the first terminal of the transistor **402A** may be connected to the node **A1**, and the gate of the transistor **402A** may be connected to the node **A2**.

(522) Furthermore, the first terminal of the transistor **302B** may be connected to the wiring **116B**, and the gate of the transistor **302B** may be connected to the node **B1**. Alternatively, the first terminal of the transistor **402B** may be connected to the node **B1**, and the gate of the transistor **402B** may be connected to the node **B2**.

(523) In the structures illustrated in FIG. **31B**, FIG. **36A**, FIG. **37A**, and FIG. **37B**, as illustrated in FIG. **38A**, the gate of the transistor **402A** may be connected to the wiring **111**. In addition, the gate of the transistor **402B** may be connected to the wiring **111**.

(524) Further, in the structures illustrated in FIG. **31B**, FIG. **36A**, FIGS. **37A** and **37B**, and FIG. **38A**, as illustrated in FIG. **38B**, the first terminal of the transistor **301A** may be connected to a wiring **118A**, and the gate of the transistor **301A** may be connected to the wiring **114A**.

Furthermore, the first terminal of the transistor **301B** may be connected to a wiring **118B**, and the gate of the transistor **301B** may be connected to the wiring **114B**.

(525) Alternatively, the first terminal of the transistor **301A** may be connected to the wiring **114A**, and the gate of the transistor **301A** may be connected to the wiring **118A**. Further, the first terminal of the transistor **301B** may be connected to the wiring **114B**, and the gate of the transistor **301B** may be connected to the wiring **118B**.

(526) Note that in the case where the voltage **12** is applied to the wiring **118A** and the wiring **118B**, the wiring **118A** and the wiring **118B** function as power supply lines. Alternatively, the clock signal **CK2** may be input to the wiring **118A** and the wiring **118B**. Alternatively, different signals or different voltages may be input to the wiring **118A** and the wiring **118B**.

(527) Note that in the case where the same voltage is input to the wiring **118A** and the wiring **118B**, the wiring **118A** and the wiring **118B** may be connected to each other. In that case, one wiring may be used as the wiring **118A** and the wiring **118B**.

(528) In the structures illustrated in FIG. **31B**, FIG. **36A**, FIGS. **37A** and **37B**, and FIGS. **38A** and **38B**, as illustrated in FIG. **39A**, the transistor **401A** may be replaced with a resistor **403A**. The resistor **403A** is connected between the wiring **115A** and the node **A2**. In addition, as illustrated in FIG. **39B**, the transistor **401B** may be replaced with a resistor **403B**. The resistor **403B** is connected between the wiring **115B** and the node **B2**.

(529) With the structures illustrated in FIGS. **39A** and **39B**, in the period **c1** and the period **d1**, the signal **SELB** which is at an L level can be supplied to the node **B2**. Alternatively, in the period **c2**

and the period d2, the signal SELA which is at an L level can be supplied to the node A2. Thus, the potential of the node A2 and the potential of the node B2 can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(530) Further, in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, and FIGS. 38A and 38B, as illustrated in FIG. 39C, a transistor 404A may be provided. A first terminal of the transistor 404A is connected to the wiring 115A; a second terminal of the transistor 404A is connected to the node A2; a gate of the transistor 404A is connected to the node A2. Furthermore, as illustrated in FIG. 39D, a transistor 404B may be provided. A first terminal of the transistor 404B is connected to the wiring 115B; a second terminal of the transistor 404B is connected to the node B2; a gate of the transistor 404B is connected to the node B2.

(531) With the structures illustrated in FIGS. 39C and 39D, as in FIGS. 39A and 39B, the potential of the node A2 and the potential of the node B2 can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(532) Further, in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, FIGS. 38A and 38B, and FIGS. 39A to 39D, as illustrated in FIG. 39E, the circuit 400A may include a transistor 405A and a transistor 406A. A first terminal of the transistor 405A is connected to the wiring 115A; a second terminal of the transistor 405A is connected to the node A2; a gate of the transistor 405A is connected to a portion where the second terminal of the transistor 401A and the second terminal of the transistor 402A are connected to each other. A first terminal of the transistor 406A is connected to the wiring 113A; a second terminal of the transistor 406A is connected to the node A2; a gate of the transistor 406A is connected to the node A1.

(533) Further, as illustrated in FIG. 39F, the circuit 400B may include a transistor 405B and a transistor 406B. A first terminal of the transistor 405B is connected to the wiring 115B; a second terminal of the transistor 405B is connected to the node B2; a gate of the transistor 405B is connected to a portion where the second terminal of the transistor 401B and the second terminal of the transistor 402B are connected to each other. A first terminal of the transistor 406B is connected to the wiring 113B; a second terminal of the transistor 406B is connected to the node B2; a gate of the transistor 406B is connected to the node B1.

(534) With the structures illustrated in FIGS. 39E and 39F, the potential of the node A2 or the potential of the node B2 can be set to V2, so that the amplitude of a signal can be increased.

(535) Alternatively, the first terminal of the transistor 401A and the first terminal of the transistor 405A may be connected to different wirings. For example, in FIG. 40A, the wiring 115A is divided into a plurality of wirings 115A_1 and 115A_2; the first terminal of the transistor 401A is connected to the wiring 115A_1; the first terminal of the transistor 405A is connected to the wiring 115A_2. In that case, the signal SELA may be input to one of the wirings 115A_1 and 115A_2, and the voltage V2 may be supplied to the other of the wirings 115A_1 and 115A_2.

(536) Alternatively, the first terminal of the transistor 401B and the first terminal of the transistor 405B may be connected to different wirings. For example, in FIG. 40B, the wiring 115B is divided into a plurality of wirings 115B_1 and 115B_2; the first terminal of the transistor 401B is connected to the wiring 115B_1; the first terminal of the transistor 405B is connected to the wiring 115B_2. In that case, the signal SELB may be input to one of the wirings 115B_1 and 115B_2, and the voltage V2 may be supplied to the other of the wirings 115B_1 and 115B_2.

(537) With the structures illustrated in FIGS. 40A and 40B, in the period c1 and the period d1, the signal SELB which is at an L level can be supplied to the node B2. Alternatively, in the period c2 and the period d2, the signal SELA which is at an L level can be supplied to the node A2. Thus, the potential of the node A2 and the potential of the node B2 can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(538) Further, in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, FIGS. 38A and 38B, and FIGS. 39A to 39D, as illustrated in FIG. 40C, the circuit 400A may include a transistor 407A, a transistor 408A, and a transistor 409A. A first terminal of the transistor 407A is

connected to the wiring **118A**; a second terminal of the transistor **407A** is connected to the node **A2**; a gate of the transistor **407A** is connected to the wiring **118A**. A first terminal of the transistor **408A** is connected to the wiring **113A**; a second terminal of the transistor **408A** is connected to the node **A2**; a gate of the transistor **408A** is connected to the node **A1**. A first terminal of the transistor **409A** is connected to the wiring **113A**; a second terminal of the transistor **409A** is connected to the node **A2**; a gate of the transistor **409A** is connected to the wiring **115A**.

(539) As illustrated in FIG. **40D**, the circuit **400B** may include a transistor **407B**, a transistor **408B**, and a transistor **409B**. A first terminal of the transistor **407B** is connected to the wiring **118B**; a second terminal of the transistor **407B** is connected to the node **B2**; a gate of the transistor **407B** is connected to the wiring **118B**. A first terminal of the transistor **408B** is connected to the wiring **113B**; a second terminal of the transistor **408B** is connected to the node **B2**; a gate of the transistor **408B** is connected to the node **B1**. A first terminal of the transistor **409B** is connected to the wiring **113B**; a second terminal of the transistor **409B** is connected to the node **B2**; a gate of the transistor **409B** is connected to the wiring **115B**.

(540) With the structures illustrated in FIGS. **40C** and **40D**, in the period **c1** and the period **d1**, the signal **SELB** which is at an L level can be supplied to the node **B2**. Alternatively, in the period **c2** and the period **d2**, the signal **SELA** which is at an L level can be supplied to the node **A2**. Thus, the potential of the node **A2** and the potential of the node **B2** can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(541) Further, in the structures illustrated in FIG. **31B**, FIG. **36A**, FIGS. **37A** and **37B**, FIGS. **38A** and **38B**, FIGS. **39A** to **39F**, and FIGS. **40A** to **40D**, as illustrated in FIG. **41A**, a transistor **206A** and a circuit **500A** may be provided. The circuit **500A** includes a transistor **501A** and a transistor **502A**.

(542) A first terminal of the transistor **206A** is connected to the wiring **113A**. A second terminal of the transistor **206A** is connected to the node **A1**. A first terminal of the transistor **501A** is connected to the wiring **118A**. A second terminal of the transistor **501A** is connected to a gate of the transistor **206A**. A gate of the transistor **501A** is connected to the wiring **118A**. A first terminal of the transistor **502A** is connected to the wiring **113A**. A second terminal of the transistor **502A** is connected to the gate of the transistor **206A**. A gate of the transistor **502A** is connected to the node **A1**.

(543) As illustrated in FIG. **41A**, a transistor **206B** and a circuit **500B** may be provided. The circuit **500B** includes a transistor **501B** and a transistor **502B**.

(544) A first terminal of the transistor **206B** is connected to the wiring **113B**. A second terminal of the transistor **206B** is connected to the node **B1**. A first terminal of the transistor **501B** is connected to the wiring **118B**. A second terminal of the transistor **501B** is connected to a gate of the transistor **206B**. A gate of the transistor **501B** is connected to the wiring **118B**. A first terminal of the transistor **502B** is connected to the wiring **113B**. A second terminal of the transistor **502B** is connected to the gate of the transistor **206B**. A gate of the transistor **502B** is connected to the node **B1**.

(545) Note that in FIG. **41A**, a portion where the gate of the transistor **206A**, the second terminal of the transistor **501A**, and the second terminal of the transistor **502A** are connected to each other is referred to as a node **A3**. In addition, a portion where the gate of the transistor **206B**, the second terminal of the transistor **501B**, and the second terminal of the transistor **502B** are connected to each other is referred to as a node **B3**.

(546) In addition, the gate of the transistor **502A** may be connected to the wiring **111**. Further, the gate of the transistor **502B** may be connected to the wiring **111**.

(547) As another example, as illustrated in FIG. **41B**, the circuit **500A** may be eliminated and the gate of the transistor **206A** may be connected to the node **A2**. In addition, the circuit **500B** may be eliminated and the gate of the transistor **206B** may be connected to the node **B2**. With the structure illustrated in FIG. **41B**, the size of the circuit can be made smaller, so that the layout area can be

decreased or power consumption can be reduced.

(548) Next, examples of the functions of the transistor **206A**, the circuit **500A**, the transistor **501A**, the transistor **502A**, the transistor **206B**, the circuit **500B**, the transistor **501B**, and the transistor **502B** are described with reference to FIGS. **41A** and **41B**.

(549) The transistor **206A** has a function of controlling the timing of bringing the wiring **113A** and the node **A1** into conduction. Alternatively, the transistor **206A** has a function of controlling the timing of supplying the potential of the wiring **113A** to the node **A1**. Alternatively, the transistor **206A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113A** to the node **A1**.

Alternatively, the transistor **206A** has a function of controlling the timing of supplying the voltage **V1** to the node **A1**. Alternatively, the transistor **206A** has a function of controlling the timing of lowering the potential of the node **A1**. Alternatively, the transistor **206A** has a function of controlling the timing of keeping the potential of the node **A1**.

(550) In this manner, the transistor **206A** functions as a switch. Note that the transistor **206A** may be controlled in accordance with the potential of the node **A3**.

(551) The circuit **500A** has a function of controlling the potential of the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of raising the potential of the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of lowering the potential of the node **A3**. Alternatively, the circuit **500A** has a function of controlling the timing of keeping the potential of the node **A3**. Alternatively, the circuit **500A** has a function of inverting the potential of the node **A1** and controlling the timing of outputting the inverted potential to the node **A3**.

(552) As described above, the circuit **500A** functions as a control circuit or an inverter circuit. Note that the circuit **500A** may be controlled in accordance with the potential of the node **A1**.

(553) The transistor **501A** has a function of controlling the timing of bringing the wiring **118A** and the node **A3** into conduction. Alternatively, the transistor **501A** has a function of controlling the timing of supplying the potential of the wiring **118A** to the node **A3**. Alternatively, the transistor **501A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the voltage **V2**) which is to be input to the wiring **118A** to the node **A3**. Alternatively, the transistor **501A** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **A3**. Alternatively, the transistor **501A** has a function of controlling the timing of supplying an H signal or the voltage **V2** to the node **A3**. Alternatively, the transistor **501A** has a function of controlling the timing of raising the potential of the node **A3**.

(554) As described above, the transistor **501A** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like.

(555) The transistor **502A** has a function of controlling the timing of bringing the wiring **113A** and the node **A3** into conduction. Alternatively, the transistor **502A** has a function of controlling the timing of supplying the potential of the wiring **113A** to the node **A3**. Alternatively, the transistor **502A** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113A** to the node **A3**.

Alternatively, the transistor **502A** has a function of controlling the timing of supplying the voltage **V1** to the node **A3**. Alternatively, the transistor **502A** has a function of controlling the timing of lowering the potential of the node **A3**. Alternatively, the transistor **502A** has a function of controlling the timing of keeping the potential of the node **A3**.

(556) As described above, the transistor **502A** functions as a switch.

(557) The transistor **206B** has a function of controlling the timing of bringing the wiring **113B** and the node **B1** into conduction. Alternatively, the transistor **206B** has a function of controlling the timing of supplying the potential of the wiring **113B** to the node **B1**. Alternatively, the transistor **206B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113B** to the node **B1**. Alternatively, the transistor **206B** has a function of controlling the timing of supplying the voltage **V1** to the node **B1**. Alternatively, the transistor **206B** has a function of controlling the timing of lowering the potential of the node **B1**. Alternatively, the transistor **206B** has a function of controlling the timing of keeping the potential of the node **B1**.

(558) As described above, the transistor **206B** functions as a switch. Note that the transistor **206B** may be controlled in accordance with the potential of the node **B3**.

(559) The circuit **500B** has a function of controlling the potential of the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of supplying a signal, voltage, or the like to the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of supplying an L signal or the voltage **V1** to the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of raising the potential of the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of lowering the potential of the node **B3**. Alternatively, the circuit **500B** has a function of controlling the timing of keeping the potential of the node **B3**. Alternatively, the circuit **500B** has a function of inverting the potential of the node **B1** and controlling the timing of outputting the inverted potential to the node **3**.

(560) As described above, the circuit **500B** functions as a control circuit or an inverter circuit. Note that the circuit **500B** may be controlled in accordance with the potential of the node **B1**.

(561) The transistor **501B** has a function of controlling the timing of bringing the wiring **118B** and the node **B3** into conduction. Alternatively, the transistor **501B** has a function of controlling the timing of supplying the potential of the wiring **118B** to the node **B3**. Alternatively, the transistor **501B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the voltage **12**) which is to be input to the wiring **118B** to the node **B3**. Alternatively, the transistor **501B** has a function of controlling the timing of not supplying a signal, voltage, or the like to the node **B3**. Alternatively, the transistor **501B** has a function of controlling the timing of supplying an H signal or the voltage **12** to the node **B3**. Alternatively, the transistor **501B** has a function of controlling the timing of raising the potential of the node **B3**.

(562) As described above, the transistor **501B** functions as a switch, a rectifier element, a diode, a diode-connected transistor, or the like.

(563) The transistor **502B** has a function of controlling the timing of bringing the wiring **113B** and the node **B3** into conduction. Alternatively, the transistor **502B** has a function of controlling the timing of supplying the potential of the wiring **113B** to the node **B3**. Alternatively, the transistor **502B** has a function of controlling the timing of supplying a signal, voltage, or the like (e.g., the clock signal **CK2** or the voltage **V1**) which is to be input to the wiring **113B** to the node **B3**. Alternatively, the transistor **502B** has a function of controlling the timing of supplying the voltage **V1** to the node **B3**. Alternatively, the transistor **502B** has a function of controlling the timing of lowering the potential of the node **B3**. Alternatively, the transistor **502B** has a function of controlling the timing of keeping the potential of the node **B3**.

(564) As described above, the transistor **502B** functions as a switch.

(565) <Operation of Semiconductor Device>

(566) Next, the operation of the semiconductor device in FIG. **41A** is described with reference to FIGS. **42A** and **42B**, FIGS. **43A** and **43B**, FIGS. **44A** and **44B**, and FIGS. **45A** and **45B**. FIG. **42A**, FIG. **42B**, FIG. **43A**, FIG. **43B**, FIG. **44A**, FIG. **44B**, FIG. **45A**, and FIG. **45B** correspond to the

schematic views of the semiconductor device in the period a1, the period b1, the period c1, the period d1, the period a2, the period b2, the period c2, and the period d2, respectively.

(567) In the period a1, the period b1, the period a2, and the period b2, the node A1 has an H-level potential. Thus, like the circuit 400A, the circuit 500A outputs an L signal to the node A3. Then, the transistor 206A is turned off, so that the wiring 113A and the node A1 are brought out of conduction.

(568) Specifically, in the period a1, the period b1, the period a2, and the period b2, the transistor 502A is turned on, so that the wiring 113A and the node A3 are brought into conduction. Thus, the voltage V1 is supplied to the node A3 through the transistor 502A. At this time, the transistor 501A is turned on, so that the wiring 118A and the node A3 are brought into conduction. Thus, the voltage V2 is supplied to the node A3 through the transistor 501A.

(569) Here, when the current supply capability of the transistor 502A is made higher than the current supply capability of the transistor 501A (e.g., the channel width of the transistor 502A is made larger than the channel width of the transistor 501A), the potential of the node A3 is set at an L level.

(570) In the period a1, the period b1, the period a2, and the period b2, the node B1 has an H-level potential. Thus, like the circuit 400B, the circuit 500B outputs an L signal to the node B3. Then, the transistor 206B is turned off, so that the wiring 113B and the node B1 are brought out of conduction.

(571) Specifically, in the period a1, the period b1, the period a2, and the period b2, the transistor 502B is turned on, so that the wiring 113B and the node B3 are brought into conduction. Thus, the voltage V1 is supplied to the node B3 through the transistor 502B. At this time, the transistor 501B is turned on, so that the wiring 118B and the node B3 are brought into conduction. Thus, the voltage V2 is supplied to the node B3 through the transistor 501B.

(572) Here, when the current supply capability of the transistor 502B is made higher than the current supply capability of the transistor 501B (e.g., the channel width of the transistor 502B is made larger than the channel width of the transistor 501B), the potential of the node B3 is set at an L level.

(573) In the period c1, the period d1, the period c2, and the period d2, the node A1 has an L-level potential. Thus, like the circuit 400A, the circuit 500A outputs an H signal to the node A3. Then, the transistor 206A is turned on, so that the wiring 113A and the node A1 are brought into conduction. Then, the voltage V1 is supplied to the node A1 through the transistor 206A.

(574) Specifically, in the period c1, the period d1, the period c2, and the period d2, the transistor 502A is turned off, so that the wiring 113A and the node A3 are brought out of conduction. At this time, the transistor 501A is turned on, so that the wiring 118A and the node A3 are brought into conduction. Thus, the voltage V2 is supplied to the node A3 through the transistor 501A.

(575) In addition, in the period c1, the period d1, the period c2, and the period d2, the node B1 has an L-level potential. Thus, like the circuit 400B, the circuit 500B outputs an H signal to the node B3. Then, the transistor 206B is turned on, so that the wiring 113B and the node B1 are brought into conduction. Then, the voltage V1 is supplied to the node B1 through the transistor 206B.

(576) Specifically, in the period c1, the period d1, the period c2, and the period d2, the transistor 502B is turned off, so that the wiring 113B and the node B3 are brought out of conduction. At this time, the transistor 501B is turned on, so that the wiring 118B and the node B3 are brought into conduction. Thus, the voltage V2 is supplied to the node B3 through the transistor 501B.

(577) In this manner, in the period c1 and the period d1, the transistor 206A is turned on, so that the wiring 113A and the node A1 are brought into conduction. Then, the voltage V1 is supplied to the node A1 through the transistor 206A. Thus, the potential of the node A1 can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(578) In addition, in the period c2 and the period d2, the transistor 206B is turned on, so that the wiring 113B and the node B1 are brought into conduction. Then, the voltage V1 is supplied to the

node B1 through the transistor 206B. Thus, the potential of the node B1 can be fixed, so that a semiconductor device which is hardly affected by noise can be obtained.

(579) <Size of Transistor>

(580) Next, the size of a transistor, such as the channel width of a transistor or the channel length of a transistor, is described.

(581) It is preferable that the channel width of the transistor 501A be substantially equal to the channel width of the transistor 501B. Alternatively, it is preferable that the channel width of the transistor 502A be substantially equal to the channel width of the transistor 502B.

(582) By making the transistors have substantially the same channel width in this manner, the transistors can have substantially the same current supply capability or substantially the same degree of deterioration. Accordingly, even when transistors which are selected are switched, the waveforms of output signals OUT can be substantially the same.

(583) From a similar reason, it is preferable that the channel length of the transistor 501A be substantially equal to the channel length of the transistor 501B. Alternatively, it is preferable that the channel length of the transistor 502A be substantially equal to the channel length of the transistor 502B.

(584) Specifically, each of the channel width of the transistor 501A and the channel width of the transistor 501B is preferably 100 to 2000 μm , more preferably 200 to 1500 μm , still more preferably 300 to 700 μm .

(585) Each of the channel width of the transistor 502A and the channel width of the transistor 502B is preferably 300 to 3000 μm , more preferably 500 to 2000 μm , still more preferably 700 to 1500 μm .

(586) Note that in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, FIGS. 38A and 38B, FIGS. 39A to 39F, FIGS. 40A to 40D, and FIGS. 41A and 41B, the second terminal of the transistor 302A may be connected to the wiring 111, and the second terminal of the transistor 302B may be connected to the wiring 111. Alternatively, a transistor for obtaining such a connection relationship may be provided. With such a structure, the fall time of the signal OUTA and the fall time of the signal OUTB can be shortened.

(587) Alternatively, in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, FIGS. 38A and 38B, FIGS. 39A to 39F, FIGS. 40A to 40D, and FIGS. 41A and 41B, the first terminal of the transistor 302A may be connected to the wiring 118A; the second terminal of the transistor 302A may be connected to the node A2; the gate of the transistor 302A may be connected to the wiring 116A. In addition, the first terminal of the transistor 302B may be connected to the wiring 118B; the second terminal of the transistor 302B may be connected to the node B2; the gate of the transistor 302B may be connected to the wiring 116B. Alternatively, a transistor for obtaining such a connection relationship may be provided. With such a structure, reverse bias can be applied to the transistor 302A and the transistor 302B, so that deterioration of each transistor can be suppressed.

(588) Note that in the structures illustrated in FIG. 31B, FIG. 36A, FIGS. 37A and 37B, FIGS. 38A and 38B, FIGS. 39A to 39F, FIGS. 40A to 40D, and FIGS. 41A and 41B, as illustrated in FIG. 36B, the transistors may be p-channel transistors.

(589) In FIG. 36B, a transistor 201pA, a transistor 202pA, a transistor 301pA, a transistor 302pA, a transistor 401pA, and a transistor 402pA are p-channel transistors and have functions that are similar to the functions of the transistor 201A, the transistor 202A, the transistor 301A, the transistor 302A, the transistor 401A, and the transistor 402A in FIG. 36A, respectively.

(590) Further, in FIG. 36B, a transistor 201pB, a transistor 202pB, a transistor 301pB, a transistor 302pB, a transistor 401pB, and a transistor 402pB are p-channel transistors and have functions that are similar to the functions of the transistor 201B, the transistor 202B, the transistor 301B, the transistor 302B, the transistor 401B, and the transistor 402B in FIG. 36A, respectively.

(591) Note that in the case where the transistors are p-channel transistors, the voltage V1 is supplied to the wiring 113A and the wiring 113B. In that case, a timing chart illustrating the signal

OUTA, the signal OUTB, the clock signal CK1, the start signal SP, the reset signal RE, the signal SELA, the signal SELB, the potential of the node A1, the potential of the node A2, the potential of the node B1, and the potential of the node B2 corresponds to inversion of the timing chart in FIG. 17.

Embodiment 6

(592) In this embodiment, gate driver circuits (also referred to as gate drivers) and display devices including the gate driver circuits are described with reference to FIGS. 46A to 46E, FIG. 47, FIG. 48, and FIG. 49.

(593) <Structure of Display Device>

(594) Structure examples of display devices are described with reference to FIGS. 46A to 46D. The display devices in FIGS. 46A to 46D include a circuit 1001, a circuit 1002, a circuit 1003_1, a circuit 1003_2, a pixel portion 1004, and a terminal 1005.

(595) A plurality of wirings which extend from the circuit 1003_1 and the circuit 1003_2 are arranged over the pixel portion 1004. The plurality of wirings function as gate lines (also referred to as gate signal lines), scan lines, or signal lines. In addition, a plurality of wirings which extend from the circuit 1002 are arranged over the pixel portion 1004. The plurality of wirings function as video signal lines, data lines, signal lines, or source lines (also referred to as source signal lines). Pixels are provided so as to correspond to the plurality of wirings extending from the circuit 1003_1 and the circuit 1003_2 and the plurality of wirings extending from the circuit 1002.

(596) In addition to the above wirings, a wiring functioning as a power supply line, a capacitor line, or the like may be provided over the pixel portion 1004.

(597) The circuit 1001 has a function of controlling the timing of supplying a signal, voltage, current, or the like to the circuit 1002, the circuit 1003_1, and the circuit 1003_2. Alternatively, the circuit 1001 has a function of controlling the circuit 1002, the circuit 1003_1, and the circuit 1003_2. As described above, the circuit 1001 functions as a controller, a control circuit, a timing generator, a power supply circuit, or a regulator.

(598) The circuit 1002 has a function of controlling the timing of supplying a video signal to the pixel portion 1004. Alternatively, the circuit 1002 has a function of controlling the luminance, transmittance, or the like of a pixel included in the pixel portion 1004. As described above, the circuit 1002 functions as a source driver circuit or a signal line driver circuit.

(599) The circuit 1003_1 has a function that is similar to the function of the circuit 10A, the circuit 100A, or the circuit 200A described in the above embodiments. In addition, the circuit 1003_2 has a function that is similar to the function of the circuit 10B, the circuit 100B, or the circuit 200B described in the above embodiments. As described above, the circuit 1003_1 and the circuit 1003_2 each function as a gate driver circuit.

(600) Note that as illustrated in FIGS. 46A and 46B, the circuit 1001 and the circuit 1002 may be formed using a substrate which is different from a substrate 1006 over which the pixel portion 1004 is formed (e.g., a semiconductor substrate or an SOI substrate). In addition, the circuit 1003_1 and the circuit 1003_2 may be formed using the same substrate as the pixel portion 1004.

(601) In the case where the drive frequency of the circuit 1003_1 and the circuit 1003_2 is lower than the drive frequency of the circuit 1001 and the circuit 1002, transistors whose mobility is low may be used as transistors included in the circuit 1003_1 and the circuit 1003_2. Thus, a non-single-crystal semiconductor (e.g., an amorphous semiconductor or a microcrystalline semiconductor), an organic semiconductor, or an oxide semiconductor can be used for semiconductor layers of the transistors included in the circuit 1003_1 and the circuit 1003_2. Accordingly, when a semiconductor device is manufactured, the number of steps can be reduced, yield can be increased, or cost can be reduced. In addition, in the case where the semiconductor device in this embodiment is used for a display device, a method for manufacturing a semiconductor device is facilitated, so that the size of the display device can be increased.

(602) Note that as illustrated in FIGS. 46A, 46C, and 46D, the circuit 1003_1 and the circuit

1003_2 may face each other with the pixel portion **1004** provided therebetween. For example, as illustrated in FIG. **46A**, the circuit **1003_1** is provided on the left side of the pixel portion **1004** and the circuit **1003_2** is provided on the right side of the pixel portion **1004**. Alternatively, as illustrated in FIG. **46B**, the circuit **1003_1** and the circuit **1003_2** may be provided on the same side (e.g., the left side or the right side) of the pixel portion **1004**.

(603) Note that in the structures illustrated in FIGS. **46A** and **46B**, as illustrated in FIG. **46C**, the circuit **1002** may be provided over the same substrate **1006** as the pixel portion **1004**.

(604) Note that in the structures illustrated in FIGS. **46A** to **46C**, as illustrated in FIG. **46D**, part of the circuit **1002** (e.g., a circuit **1002a**) may be provided over the substrate **1006** over which the pixel portion **1004** is provided, and another part of the circuit **1002** (e.g., a circuit **1002b**) may be provided over a substrate which is different from the substrate **1006**. In that case, as the circuit **1002a**, a circuit with comparatively low drive frequency, such as a switch, a shift register, or a selector, is preferably used.

(605) Next, a pixel included in the pixel portion of the display device is described with reference to FIG. **46E**. FIG. **46E** illustrates a structure example of a pixel.

(606) A pixel **3020** includes a transistor **3021**, a liquid crystal element **3022**, and a capacitor **3023**. A first terminal of the transistor **3021** is connected to a wiring **3031**. A second terminal of the transistor **3021** is connected to one electrode of the liquid crystal element **3022** and one electrode of the capacitor **3023**. A gate of the transistor **3021** is connected to a wiring **3032**. The other electrode of the liquid crystal element **3022** is connected to an electrode **3034**. The other electrode of the capacitor **3023** is connected to a wiring **3033**.

(607) A video signal is input from the circuit **1002** illustrated in FIGS. **46A** to **46D** to the wiring **3031**. Thus, the wiring **3031** functions as a signal line, a video signal line, or a source line (also referred to as a source signal line).

(608) A gate signal, a scan signal, or a selection signal is input from the circuit **1003_1** and the circuit **1003_2** illustrated in FIGS. **46A** to **46D** to the wiring **3032**. Thus, the wiring **3032** functions as a gate line (also referred to as a gate signal line), a scan line, or a signal line.

(609) Constant voltage is supplied from the circuit **1001** illustrated in FIGS. **46A** to **46D** to the wiring **3033** and the electrode **3034**. Thus, the wiring **3033** functions as a power supply line or a capacitor line. Further, the electrode **3034** functions as a common electrode or a counter electrode.

(610) Note that precharge voltage may be supplied to the wiring **3031**. The level of the precharge voltage is preferably set substantially equal to the level of the voltage supplied to the electrode **3034**. Alternatively, a signal may be input to the wiring **3033**. In this manner, voltage applied to the liquid crystal element **3022** is controlled, so that the amplitude of a video signal can be decreased and inversion driving can be performed. Alternatively, a signal is input to the electrode **3034**, so that frame inversion driving can be performed.

(611) The transistor **3021** has a function of controlling the timing of bringing the wiring **3031** and the one electrode of the liquid crystal element **3022** into conduction. Alternatively, the transistor **3021** has a function of controlling the timing of writing a video signal to a pixel. In this manner, the transistor **3021** functions as a switch.

(612) The capacitor **3023** has a function of holding a difference between the potential of the one electrode of the liquid crystal element **3022** and the potential of the wiring **3033**. Alternatively, the capacitor **3023** has a function of holding voltage applied to the liquid crystal element **3022** so that the level of the voltage is constant. In this manner, the capacitor **3023** functions as a storage capacitor.

(613) <Structure of Shift Register>

(614) Next, the structure of the gate driver circuit included in the display device is described below. Specifically, the structure of a shift register included in the gate driver circuit is described with reference to FIG. **47** and FIG. **48**. FIG. **47** and FIG. **48** are examples of a circuit diagram of the shift register.

(615) In FIG. 47, a shift register **1100A** includes a plurality of flip-flop circuits **1101A_1** to **1101A_N** (N is a natural number). Note that the circuit **200A** included in the semiconductor device illustrated in FIG. 16A can be used for each of the flip-flop circuits **1101A_1** to **1101A_N** illustrated in FIG. 47.

(616) In addition, a shift register **1100B** includes a plurality of flip-flop circuits **1101B_1** to **1101B_N** (N is a natural number). Note that the circuit **200B** included in the semiconductor device illustrated in FIG. 16A can be used for each of the flip-flop circuits **1101B_1** to **1101B_N** illustrated in FIG. 47.

(617) The shift register **1100A** is connected to wirings **1111_1** to **1111_N**, a wiring **1112A**, a wiring **1113A**, a wiring **1114A**, a wiring **1115A**, a wiring **1116A**, and a wiring **1119A**. In a flip-flop **1101A_i** (i is any one of 1 to N), the wiring **111**, the wiring **112A**, the wiring **113A**, the wiring **114A**, the wiring **115A**, and the wiring **116A** are connected to the wiring **1111_i**, the wiring **1112A**, the wiring **1113A**, a wiring **1111_i-1**, the wiring **1115A**, and a wiring **1111_i+1**, respectively.

(618) Note that in the case where the wiring **112A** is connected to one of the wiring **1112A** and the wiring **1119A**, a portion to which the wiring **112A** is connected may be changed between a flip-flop circuit in an odd-numbered stage and a flip-flop circuit in an even-numbered stage.

(619) In addition, the shift register **1100B** is connected to the wirings **1111_1** to **1111_N**, a wiring **1112B**, a wiring **1113B**, a wiring **1114B**, a wiring **1115B**, a wiring **1116B**, and a wiring **1119B**. In a flip-flop **1101B_i** (i is any one of 1 to N), the wiring **111**, the wiring **112B**, the wiring **113B**, the wiring **114B**, the wiring **115B**, and the wiring **116B** are connected to the wiring **1111_i**, the wiring **1112B**, the wiring **1113B**, the wiring **1111_i-1**, the wiring **1115B**, and the wiring **1111_i+1**, respectively.

(620) Note that in the case where the wiring **112B** is connected to one of the wiring **1112B** and the wiring **1119B**, a portion to which the wiring **112B** is connected may be changed between a flip-flop circuit in an odd-numbered stage and a flip-flop circuit in an even-numbered stage.

(621) The shift register **1100A** outputs signals **GOUTA_1** to **GOUTA_N** to the wirings **1111_1** to **1111_N**. The signals **GOUTA_1** to **GOUTA_N** are signals output from the flip-flops **1101A_1** to **1101A_N**, respectively, and correspond to the signal **OUTA**. The shift register **1100B** outputs signals **GOUTB_1** to **GOUTB_N** to the wirings **1111_1** to **1111_N**. The signals **GOUTB_1** to **GOUTB_N** are signals output from the flip-flops **1101B_1** to **1101B_N**, respectively, and correspond to the signal **OUTB**. Thus, the wirings **1111_1** to **1111_N** have a function that is similar to the function of the wiring **111**.

(622) The signal **GCK1** is input to the wiring **1112A** and the wiring **1112B**, and the signal **GCK2** is input to the wiring **1119A** and the wiring **1119B**. The signal **GCK1** and the signal **GCK2** correspond to the clock signal **CK1** and the clock signal **CK2**, respectively. Thus, the wiring **1112A** and wiring **1119A** have a function that is similar to the function of the wiring **112A**, and the wiring **1112B** and wiring **1119B** have a function that is similar to the function of the wiring **112B**.

(623) The voltage **V1** is supplied to the wiring **1113A** and the wiring **1113B**. Thus, the wiring **1113A** has a function that is similar to the function of the wiring **113A**, and the wiring **1113B** has a function that is similar to the function of the wiring **113B**.

(624) Signals **GSP** are input to the wiring **1114A** and the wiring **1114B**. The signal **GSP** corresponds to the start signal **SP**. Thus, the wiring **1114A** has a function that is similar to the function of the wiring **114A**, and the wiring **1114B** has a function that is similar to the function of the wiring **114B**.

(625) The signal **SELA** is input to the wiring **1115A**, and the signal **SELB** is input to the wiring **1115B**. Thus, the wiring **1115A** has a function that is similar to the function of the wiring **115A**, and the wiring **1115B** has a function that is similar to the function of the wiring **115B**.

(626) Signals **GRE** are input to the wiring **1116A** and the wiring **1116B**. The signal **GRE** corresponds to the reset signal **RE**. Thus, the wiring **1116A** has a function that is similar to the function of the wiring **116A**, and the wiring **1116B** has a function that is similar to the function of

the wiring **116B**.

(627) Note that in the case where the same signal or the same voltage is input to the wiring **1112A** and the wiring **1112B**, the wiring **1112A** and the wiring **1112B** may be connected to each other. In that case, as illustrated in FIG. **48**, one wiring (one wiring **1112**) may be used as the wiring **1112A** and the wiring **1112B**. Alternatively, different signals or different voltages may be input to the wiring **1112A** and the wiring **1112B**.

(628) In the case where the same signal or the same voltage is input to the wiring **1113A** and the wiring **1113B**, the wiring **1113A** and the wiring **1113B** may be connected to each other. In that case, as illustrated in FIG. **48**, one wiring (one wiring **1113**) may be used as the wiring **1113A** and the wiring **1113B**. Alternatively, different signals or different voltages may be input to the wiring **1113A** and the wiring **1113B**.

(629) In the case where the same signal or the same voltage is input to the wiring **1114A** and the wiring **1114B**, the wiring **1114A** and the wiring **1114B** may be connected to each other. In that case, as illustrated in FIG. **48**, one wiring (one wiring **1114**) may be used as the wiring **1114A** and the wiring **1114B**. Alternatively, different signals or different voltages may be input to the wiring **1114A** and the wiring **1114B**.

(630) In the case where the same signal or the same voltage is input to the wiring **1116A** and the wiring **1116B**, the wiring **1116A** and the wiring **1116B** may be connected to each other. In that case, as illustrated in FIG. **48**, one wiring (one wiring **1116**) may be used as the wiring **1116A** and the wiring **1116B**. Alternatively, different signals or different voltages may be input to the wiring **1116A** and the wiring **1116B**.

(631) In the case where the same signal or the same voltage is input to the wiring **1119A** and the wiring **1119B**, the wiring **1119A** and the wiring **1119B** may be connected to each other. In that case, as illustrated in FIG. **48**, one wiring (one wiring **1119**) may be used as the wiring **1119A** and the wiring **1119B**. Alternatively, different signals or different voltages may be input to the wiring **1119A** and the wiring **1119B**.

(632) <Operation of Shift Register>

(633) An operation example of the shift register is described with reference to FIG. **49**. FIG. **49** is a timing chart illustrating the operation example of the shift register. FIG. **49** illustrates the signal GCK1, the signal GCK2, the signal GSP, the signal GRE, the signal SELA, the signal SELB, the signals GOUTA_1 to GOUTA_N, and the signals GOUTB_1 to GOUTB_N.

(634) First, the operation of the flip-flop **1101A_i** in a k-th (k is a natural number) frame and the operation of the flip-flop **1101B_i** in a (k-1)th frame are described.

(635) First, the signal GOUTA_i-1 and the signal GOUTB_i are set at an H level. Then, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period a1 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an L signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an L signal to the wiring **1111_i**.

(636) Then, when the signal GCK1 and the signal GCK2 are inverted, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period b1 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an H signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an H signal to the wiring **1111_i**.

(637) Then, when the signal GCK1 and the signal GCK2 are inverted again, the signal GOUTA_i+1 and the signal GOUTB_i+1 are set at an H level. After that, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period c1 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an L signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs no signal to the wiring **1111_i**.

(638) Then, until the signal GOUTA_i-1 and the signal GOUTB_i are set at an H level again, the flip-flop **1101A_i** and the flip-flop **1101B_i** perform the operation in the period d1 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an L signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs no signal to the wiring **1111_i**.

(639) First, the operation of the flip-flop **1101A_i** in a (k+1)th frame and the operation of the flip-flop **1101B_i** in the k-th frame are described.

(640) First, the signal **GOUTA_{i-1}** and the signal **GOUTB_i** are set at an H level. Then, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period a2 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an L signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an L signal to the wiring **1111_i**.

(641) Then, when the signal **GCK1** and the signal **GCK2** are inverted, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period b2 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs an H signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an H signal to the wiring **1111_i**.

(642) Then, when the signal **GCK1** and the signal **GCK2** are inverted again, the signal **GOUTA_{i+1}** and the signal **GOUTB_{i+1}** are set at an H level. After that, the flip-flop **1101A_i** and the flip-flop **1101B_i** start the operation in the period c2 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs no signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an L signal to the wiring **1111_i**.

(643) Then, until the signal **GOUTA_{i-1}** and the signal **GOUTB_i** are set at an H level again, the flip-flop **1101A_i** and the flip-flop **1101B_i** perform the operation in the period d2 described in Embodiment 4. Thus, the flip-flop **1101A_i** outputs no signal to the wiring **1111_i**, and the flip-flop **1101B_i** outputs an L signal to the wiring **1111_i**.

Embodiment 7

(644) In this embodiment, a source driver circuit (also referred to as a source driver) is described with reference to FIGS. 50A to 50D.

(645) FIG. 50A illustrates a structure example of a source driver circuit. The source driver circuit includes a circuit **2001** and a circuit **2002**. The circuit **2002** includes a plurality of circuits **2002_1** to **2002_N** (N is a natural number). The circuits **2002_1** to **2002_N** include a plurality of transistors **2003_1** to **2003_k** (k is a natural number). The transistors **2003_1** to **2003_k** can be n-channel transistors or p-channel transistors. Alternatively, the transistors **2003_1** to **2003_k** can be used as CMOS switches.

(646) The connection relationship of the circuits **2002_1** to **2002_N** included in the source driver circuit is described taking the circuit **2002_1** as an example. First terminals of the transistors **2003_1** to **2003_k** included in the circuit **2002_1** are connected to wirings **2004_1** to **2004_k**, respectively. Second terminals of the transistors **2003_1** to **2003_k** are connected to source lines **2008_1** to **2008_k** (denoted by S1, S2, and Sk in FIG. 50B), respectively. Gates of the transistors **2003_1** to **2003_k** are connected to a wiring **2005_1**.

(647) The circuit **2001** has a function of controlling the timing of sequentially outputting H signals to the wiring **2005_1** and wirings **2005_2** to **2005_N** or a function of sequentially selecting the circuits **2002_1** to **2002_N**. In this manner, the circuit **2001** functions as a shift register.

(648) The circuit **2001** can output H signals to the wirings **2005_1** to **2005_N** in different orders. Alternatively, the circuit **2001** can select the **2002_1** to **2002_N** in different orders. In this manner, the circuit **2001** functions as a decoder.

(649) The circuit **2002_1** has a function of controlling the timing of bringing the wirings **2004_1** to **2004_k** and the source lines **2008_1** to **2008_k** into conduction. Alternatively, the circuit **2001_1** has a function of controlling the timing of supplying the potentials of the wirings **2004_1** to **2004_k** to the source lines **2008_1** to **2008_k**. In this manner, the circuit **2002_1** functions as a selector. Note that the circuits **2002_2** to **2002_N** have a function that is similar to the function of the circuit **2002_1**.

(650) The transistors **2003_1** to **2003_N** each have a function of controlling the timing of bringing the wirings **2004_1** to **2004_k** and the source lines **2008_1** to **2008_k** into conduction. For example, the transistor **2003_1** has a function of controlling the timing of bringing the wiring **2004_1** and the source line **2008_1** into conduction. Alternatively, the transistors **2003_1** to **2003_N** each have a

function of controlling the timing of supplying the potentials of the wirings **2004_1** to **2004_k** to the source lines **2008_1** to **2008_k**. For example, the transistor **2003_1** has a function of controlling the timing of supplying the potential of the wiring **2004_1** to the source line **2008_1**. In this manner, the transistors **2003_1** to **2003_N** each function as a switch.

(651) Note that in the case where signals corresponding to video signals, such as analog signals corresponding to video signals, are input to the wirings **2004_1** to **2004_k**, the wirings **2004_1** to **2004_k** function as signal lines. Alternatively, digital signals, analog voltage, or analog current may be input to the wirings **2004_1** to **2004_k**.

(652) Next, an operation example of the source driver circuit illustrated in FIG. **50A** is described with reference to a timing chart in FIG. **50B**.

(653) FIG. **50B** illustrates signals **2015_1** to **2015_N** and signals **2014_1** to **2014_k**. The signals **2015_1** to **2015_N** are output signals of the circuit **2001**. The signals **2014_1** to **2014_k** are input to the wirings **2004_1** to **2004_k**, respectively.

(654) Note that one operation period of the source driver circuit corresponds to one gate selection period in a display device. One gate selection period is, for example, divided into a period **T0** to **TN**. The period **T0** is a period during which precharge voltage is applied to pixels in a selected row concurrently and is also referred to as a precharge period. Each of the periods **T1** to **TN** is a period during which video signals are written to pixels in the selected row and is also referred to as a writing period.

(655) First, in the period **T0**, the circuit **2001** outputs H signals to the wirings **2005_1** to **2005_N**. Then, the transistors **2003_1** to **2003_k** are turned on in the circuit **2002_1**, so that the wirings **2004_1** to **2004_k** and the source lines **2008_1** to **2008_k** are brought into conduction. At this time, precharge voltage V_p is applied to the wirings **2004_1** to **2004_k**. Thus, the precharge voltage V_p is output to the source lines **2008_1** to **2008_k** through the transistors **2003_1** to **2003_k**. The precharge voltage V_p is written to pixels in a selected row, so that the pixels in the selected row are precharged.

(656) In the periods **T1** to **TN**, the circuit **2001** sequentially outputs H signals to the wirings **2005_1** to **2005_N**. For example, in the period **T1**, the circuit **2001** outputs an H signal to the wiring **2005_1**. Then, the transistors **2003_1** to **2003_k** are turned on, so that the wirings **2004_1** to **2004_k** and the source lines **2008_1** to **2008_k** are brought into conduction. At this time, Data (**S1**) to Data (**Sk**) are input to the wirings **2004_1** to **2004_k**, respectively. The Data (**S1**) to Data (**Sk**) are input to pixels in a selected row in a first to k-th columns through the transistors **2003_1** to **2003_k**, respectively. In this manner, in the periods **T1** to **TN**, video signals are sequentially written to the pixels in the selected row by k columns.

(657) When video signals are written to pixels by a plurality of columns as described above, the number of video signals or the number of wirings needed for writing video signals to pixels can be reduced. Thus, the number of connections between a substrate over which a pixel portion is formed and an external circuit can be reduced, so that improvement in yield, improvement in reliability, reduction in the number of components, or reduction in cost can be achieved.

(658) Alternatively, when video signals are written to pixels by a plurality of columns, the writing time can be extended. Thus, shortage of write of video signals can be prevented, so that display quality can be improved.

(659) Note that when k is made larger, the number of connections to the external circuit can be reduced. However, if k is too large, the time to write signals to pixels would be shortened. Thus, k is preferably 6 or more, more preferably 3 or more, still more preferably 2.

(660) In particular, in the case where the number of color elements of a pixel is n (n is a natural number), $k=n$ or $k=n \times d$ (d is a natural number) is preferable. For example, in the case where the pixel is divided into three color elements: red (R), green (G), and blue (B), $k=3$ or $k=3 \times d$ is preferable.

(661) For example, in the case where the pixel is divided into m (m is a natural number) subpixels,

$k=m$ or $k=m \times d$ is preferable. For example, in the case where the pixel is divided into two subpixels, $k=2$ is preferable. Alternatively, in the case where the number of color elements of the pixel is n , $k=m \times n$ or $k=m \times n \times d$ is preferable.

(662) A different structure example of the source driver circuit is described with reference to FIG. 50C. Note that in the case where the drive frequencies of the circuit **2001** and the circuit **2002** are low, the circuit **2001** and the circuit **2002** may be formed using a single crystal semiconductor. Thus, the circuit **2001** and the circuit **2002** can be formed using the same substrate as a pixel portion **2007** as illustrated in FIG. 50C. With this structure, the number of connections between the substrate over which the pixel portion is formed and an external circuit can be reduced, so that improvement in yield, improvement in reliability, reduction in the number of components, or reduction in cost can be achieved.

(663) When a gate driver circuit **2006A** and a gate driver circuit **2006B** are also formed using the same substrate as the pixel portion **2007**, the number of connections to the external circuit can be further reduced. Note that the gate driver circuit **2006A** corresponds to the circuit **10A**, the circuit **100A**, or the circuit **200A** described in the above embodiments, and the gate driver circuit **2006B** corresponds to the circuit **10B**, the circuit **100B**, or the circuit **200B** described in the above embodiments.

(664) A different structure example of the source driver circuit is described with reference to FIG. 50D. As illustrated in FIG. 50D, the circuit **2001** may be formed using a substrate which is different from the substrate over which the pixel portion **2007** is formed, and the circuit **2002** may be formed using the same substrate as the pixel portion **2007**. With this structure, the number of connections between the substrate over which the pixel portion is formed and an external circuit can be reduced, so that improvement in yield, improvement in reliability, reduction in the number of components, or reduction in cost can be achieved. Further, since the number of circuits which are formed using the same substrate as the pixel portion **2007** is reduced, the frame can be reduced.

Embodiment 8

(665) In a display device, a protection circuit is provided for a gate line or a source line in some cases in order to prevent an element (e.g., a transistor, a display element, or a capacitor) provided in a pixel from being damaged by electrostatic discharge (ESD), noise, or the like.

(666) In this embodiment, the structure of a protection circuit and the structure of a semiconductor device including the protection circuit are described.

(667) Examples of circuit diagrams of a protection circuit are described with reference to FIGS. 51A to 51G.

(668) A protection circuit **3000** illustrated in FIG. 51A may be used as a protection circuit. The protection circuit **3000** illustrated in FIG. 51A is provided in order to prevent an element provided in a pixel connected to a wiring **3011** from being damaged by electrostatic discharge, noise, or the like. The protection circuit **3000** includes a transistor **3001** and a transistor **3002**. The transistors **3001** and **3002** can be n-channel transistors or p-channel transistors.

(669) A first terminal of the transistor **3001** is connected to a wiring **3012**. A second terminal of the transistor **3001** is connected to the wiring **3011**. A gate of the transistor **3001** is connected to the wiring **3011**. A first terminal of the transistor **3002** is connected to a wiring **3013**. A second terminal of the transistor **3002** is connected to the wiring **3011**. A gate of the transistor **3002** is connected to the wiring **3013**.

(670) A signal (e.g., a scan signal, a video signal, a clock signal, a start signal, a reset signal, or a selection signal) and voltage (e.g., a negative power supply potential, ground voltage, or a positive power supply potential) are supplied to the wiring **3011**. A high power supply potential VDD is supplied to the wiring **3012**. A low power supply potential VSS (or ground voltage) is supplied to the wiring **3013**.

(671) When the potential of the wiring **3011** is between the low power supply potential VSS and the high power supply potential VDD, the transistor **3001** and the transistor **3002** are turned off.

Thus, a signal or voltage supplied to the wiring **3011** is supplied to the pixel which is connected to the wiring **3011**.

(672) Due to the adverse effect of static electricity or the like, a potential which is higher than the high power supply potential VDD or a potential which is lower than the low power supply potential VSS is supplied to the wiring **3011** in some cases. In that case, the element provided in the pixel which is connected to the wiring **3011** might be damaged by the potential which is higher than the high power supply potential VDD or the potential which is lower than the low power supply potential VSS.

(673) In order to prevent such electrostatic discharge, the transistor **3001** is turned on in the case where the potential which is higher than the high power supply potential VDD is supplied to the wiring **3011** due to the adverse effect of static electricity or the like. Then, since electrical charge in the wiring **3011** is transferred to the wiring **3012** through the transistor **3001**, the potential of the wiring **3011** is lowered.

(674) The transistor **3002** is turned on in the case where the potential which is higher than the low power supply potential VSS is supplied to the wiring **3011** due to the adverse effect of static electricity or the like. Then, since the electrical charge in the wiring **3011** is transferred to the wiring **3013** through the transistor **3002**, the potential of the wiring **3011** is raised.

(675) When the protection circuit **3000** is provided as described above, the element provided in the pixel which is connected to the wiring **3011** can be prevented from being damaged by static electricity or the like.

(676) Note that the protection circuit **3000** illustrated in FIG. **51B** or FIG. **51C** may be used as a protection circuit. The structure illustrated in FIG. **51B** corresponds to a structure in which the transistor **3002** and the wiring **3013** are eliminated from the structure illustrated in FIG. **51A**. The structure illustrated in FIG. **51C** corresponds to a structure in which the transistor **3001** and the wiring **3012** are eliminated from the structure in FIG. **51A**.

(677) The protection circuit **3000** illustrated in FIG. **51D** may be used as a protection circuit. The structure illustrated in FIG. **51D** corresponds to a structure in which a transistor **3003** is connected in series between the wiring **3011** and the wiring **3012** and a transistor **3004** is connected in series between the wiring **3011** and the wiring **3013** in the structure illustrated in FIG. **51A**.

(678) In FIG. **51D**, a first terminal of the transistor **3003** is connected to the wiring **3012**; a second terminal of the transistor **3003** is connected to the first terminal of the transistor **3001**; a gate of the transistor **3003** is connected to the first terminal of the transistor **3001**. A first terminal of the transistor **3004** is connected to the wiring **3013**; a second terminal of the transistor **3004** is connected to the first terminal of the transistor **3002**; a gate of the transistor **3004** is connected to the wiring **3013**.

(679) The protection circuit **3000** illustrated in FIG. **51E** may be used as a protection circuit. The structure illustrated in FIG. **51E** corresponds to a structure in which the gate of the transistor **3001** is connected to the gate of the transistor **3003** and the gate of the transistor **3002** is connected to the gate of the transistor **3004** in the structure illustrated in FIG. **51D**.

(680) The protection circuit **3000** illustrated in FIG. **51F** may be used as a protection circuit. The structure illustrated in FIG. **51F** corresponds to a structure in which the transistor **3001** and the transistor **3003** are connected in parallel between the wiring **3011** and the wiring **3012** and the transistor **3002** and the transistor **3004** are connected in parallel between the wiring **3011** and the wiring **3013** in the structure illustrated in FIG. **51A**.

(681) In FIG. **51F**, the first terminal of the transistor **3003** is connected to the wiring **3012**; the second terminal of the transistor **3003** is connected to the wiring **3011**; the gate of the transistor **3003** is connected to the wiring **3011**. The first terminal of the transistor **3004** is connected to the wiring **3013**; the second terminal of the transistor **3004** is connected to the wiring **3011**; the gate of the transistor **3004** is connected to the wiring **3013**.

(682) The protection circuit **3000** illustrated in FIG. **51G** may be used as a protection circuit. The

structure illustrated in FIG. 51G corresponds to a structure in which a capacitor 3005 and a resistor 3006 are connected in parallel between the gate of the transistor 3001 and the first terminal of the transistor 3001 and a capacitor 3007 and a resistor 3008 are connected in parallel between the gate of the transistor 3002 and the first terminal of the transistor 3002 in the structure illustrated in FIG. 51A.

(683) With the structure illustrated in FIG. 51G, damage or deterioration of the protection circuit 3000 itself can be prevented.

(684) For example, in the case where voltage which is higher than a power supply potential is supplied to the wiring 3011, a potential difference V_{gs} between the gate of the transistor 3001 and a source of the transistor 3001 is raised. Thus, the transistor 3001 is turned on, so that the potential of the wiring 3011 is lowered. However, since high voltage is applied between the gate of the transistor 3001 and the second terminal of the transistor 3001, the transistor 3001 might be damaged or deteriorate. In order to prevent damage or deterioration of the transistor 3001, the gate voltage of the transistor 3001 is raised using the capacitor 3005 and the potential difference V_{gs} between the gate of the transistor 3001 and the source of the transistor 3001 is lowered.

(685) Specifically, when the transistor 3001 is turned on, the voltage of the first terminal of the transistor 3001 is raised instantaneously. Then, with capacitive coupling of the capacitor 3005, the gate voltage of the transistor 3001 is raised. In this manner, the potential difference V_{gs} between the gate of the transistor 3001 and the source of the transistor 3001 can be lowered, so that damage or deterioration of the transistor 3001 can be suppressed.

(686) Similarly, in the case where voltage which is lower than the power supply potential is supplied to the wiring 3011, the voltage of the first terminal of the transistor 3002 is lowered instantaneously. Then, with capacitive coupling of the capacitor 3007, the gate voltage of the transistor 3002 is lowered. In this manner, a potential difference V_{gs} between the gate of the transistor 3002 and a source of the transistor 3002 can be lowered, so that damage or deterioration of the transistor 3002 can be suppressed.

(687) Next, the structure of a semiconductor device provided with a protection circuit is described with reference to FIGS. 52A and 52B.

(688) FIG. 52A illustrates a structure example of a semiconductor device in which a protection circuit is provided in a gate line. In FIG. 52A, each of a gate line 3102_1 and a gate line 3102_2 corresponds to the wiring 3011 in FIGS. 51A to 51G.

(689) The wiring 3012 and the wiring 3013 are connected to any of wirings connected to a gate driver circuit 3100. With such a structure, the power supply voltage of the gate driver circuit can be used as power supply voltage for operating the protection circuit 3000, so that the kind of power supply voltages and the number of wirings for supplying power supply voltage to the protection circuit 3000 can be reduced.

(690) FIG. 52B illustrates a structure example of a semiconductor device in which a protection circuit is provided in a terminal to which a signal or voltage is supplied from the outside such as an FPC. In FIG. 52B, the wiring 3012 and the wiring 3013 can be connected to any of external terminals. For example, in the case where the wiring 3012 is connected to a terminal 3101a, in a protection circuit provided in the terminal 3101a, the transistor 3001 can be eliminated. Similarly, in the case where the wiring 3013 is connected to a terminal 3101b, in a protection circuit provided in the terminal 3101b, the transistor 3002 can be eliminated. The same can be said for protection circuits provided in a terminal 3101c and a terminal 3101d.

(691) With such a structure, the number of transistors can be reduced, so that the layout area can be reduced.

Embodiment 9

(692) In this embodiment, the structure of a display device including a transistor and a display element and the structure of the transistor are described with reference to FIGS. 53A to 53C.

(693) For example, a field-effect transistor or a bipolar transistor can be used as a transistor. A thin

film transistor (also referred to as a TFT) can be used as the field-effect transistor. In addition, the field-effect transistor may be a top-gate transistor or a bottom-gate transistor. A channel-etched transistor or a bottom-contact transistor (also referred to as an inverted coplanar transistor) can be used as the bottom-gate transistor. Further, the field-effect transistor may have n-type or p-type conductivity.

(694) Note that the field-effect transistor includes, for example, a gate electrode; a semiconductor layer including a source region, a channel region, and a drain region; and a gate insulating layer provided between the gate electrode and the semiconductor layer in the cross-sectional view. The semiconductor layer is formed using a semiconductor film or a semiconductor substrate.

(695) Examples of semiconductor materials which are used for the semiconductor film or the semiconductor substrate include an amorphous semiconductor, a microcrystalline semiconductor, a single crystal semiconductor, and a polycrystalline semiconductor. In addition, an oxide semiconductor may be used as the semiconductor material.

(696) As the oxide semiconductor, a four-component metal oxide (e.g., an In—Sn—Ga—Zn—O-based metal oxide), a three-component metal oxide (e.g., an In—Ga—Zn—O-based metal oxide, an In—Sn—Zn—O-based metal oxide, an In—Al—Zn—O-based metal oxide, a Sn—Ga—Zn—O-based metal oxide, an Al—Ga—Zn—O-based metal oxide, or a Sn—Al—Zn—O-based metal oxide), or a two-component metal oxide (e.g., an In—Zn—O-based metal oxide, a Sn—Zn—O-based metal oxide, an Al—Zn—O-based metal oxide, a Zn—Mg—O-based metal oxide, a Sn—Mg—O-based metal oxide, an In—Mg—O-based metal oxide, an In—Ga—O-based metal oxide, or an In—Sn—O-based metal oxide) can be used. An In—O-based metal oxide, a Sn—O-based metal oxide, a Zn—O-based metal oxide, or the like can be used as the oxide semiconductor. Further, as the oxide semiconductor, an oxide semiconductor including SiO₂ in a metal oxide that can be used as the oxide semiconductor can be used.

(697) As the oxide semiconductor, a material represented by InMO₃(ZnO)_m (m>0) can be used. Here, M represents one or more metal elements selected from Ga, Al, Mn, or Co. For example, M can be Ga, Ga and Al, Ga and Mn, Ga and Co, or the like.

(698) FIGS. 53A and 53B illustrate structure examples of a display device including a transistor and a display element. A top-gate transistor is used as the transistor in FIG. 53A, and a bottom-gate transistor is used as the transistor in FIG. 53B.

(699) FIG. 53A illustrates a substrate 5260; an insulating layer 5261 provided over the substrate 5260; a semiconductor layer 5262 which is provided over the insulating layer 5261 and is provided with regions 5262a to 5262e; an insulating layer 5263 provided so as to cover the semiconductor layer 5262; a conductive layer 5264 provided over the semiconductor layer 5262 and the insulating layer 5263; an insulating layer 5265 which is provided over the insulating layer 5263 and the conductive layer 5264 and is provided with openings; and a conductive layer 5266 which is provided over the insulating layer 5265 and in the openings provided in the insulating layer 5265.

(700) FIG. 53B illustrates a substrate 5300; a conductive layer 5301 provided over the substrate 5300; an insulating layer 5302 provided so as to cover the conductive layer 5301; a semiconductor layer 5303a provided over the conductive layer 5301 and the insulating layer 5302; a semiconductor layer 5303b provided over the semiconductor layer 5303a; a conductive layer 5304 provided over the semiconductor layer 5303b and the insulating layer 5302; an insulating layer 5305 which is provided over the insulating layer 5302 and the conductive layer 5304 and is provided with an opening; and a conductive layer 5306 which is provided over the insulating layer 5305 and in the opening provided in the insulating layer 5305.

(701) FIG. 53C illustrates a different structure example of the transistor. FIG. 53C illustrates a semiconductor substrate 5352 including a region 5353 and a region 5355; an insulating layer 5356 provided over the semiconductor substrate 5352; an insulating layer 5354 provided over the semiconductor substrate 5352; a conductive layer 5357 provided over the insulating layer 5356; an insulating layer 5358 which is provided over the insulating layer 5354, the insulating layer 5356,

and the conductive layer **5357** and is provided with openings; and a conductive layer **5359** which is provided over the insulating layer **5358** and in the openings provided in the insulating layer **5358**. In FIG. **53C**, a transistor is formed in each of a region **5350** and a region **5351**. The structure of the transistor illustrated in FIG. **53C** may be applied to the transistors illustrated in FIGS. **53A** and **53B**.

(702) Note that as illustrated in FIG. **53A**, the display device may include an insulating layer **5267** which is provided over the conductive layer **5266** and the insulating layer **5265** and is provided with an opening; a conductive layer **5268** which is provided over the insulating layer **5267** and in the opening provided in the insulating layer **5267**; an insulating layer **5269** which is provided over the insulating layer **5267** and the conductive layer **5268** and is provided with an opening; an EL layer **5270** which is provided over the insulating layer **5269** and in the opening provided in the insulating layer **5269**; and a conductive layer **5271** provided over the insulating layer **5269** and the EL layer **5270**. The same can be said for the display device in FIG. **53B**.

(703) Note that as illustrated in FIG. **53B**, the display device may include a liquid crystal layer **5307** which is provided over the insulating layer **5305** and the conductive layer **5306** and a conductive layer **5308** which is provided over the liquid crystal layer **5307**. The same can be said for the display device in FIG. **53A**.

(704) The insulating layer **5261** functions as a base film. The insulating layer **5354** functions as an element isolation layer (e.g., a field oxide film). Each of the insulating layer **5263**, the insulating layer **5302**, and the insulating layer **5356** functions as a gate insulating film. Each of the conductive layer **5264**, the conductive layer **5301**, and the conductive layer **5357** functions as a gate electrode. Each of the insulating layer **5265**, the insulating layer **5267**, the insulating layer **5305**, and the insulating layer **5358** functions as an interlayer film or a planarization film. Each of the conductive layer **5266**, the conductive layer **5304**, and the conductive layer **5359** functions as a wiring, an electrode of a transistor, an electrode of a capacitor, or the like. Each of the conductive layer **5268** and the conductive layer **5306** functions as a pixel electrode, a reflective electrode, or the like. The insulating layer **5269** functions as a partition wall. Each of the conductive layer **5271** and the conductive layer **5308** functions as a counter electrode, a common electrode, or the like.

(705) As each of the substrate **5260** and the substrate **5300**, a glass substrate, a quartz substrate, a semiconductor substrate (e.g., a silicon substrate or a single crystal substrate), an SOI substrate, a plastic substrate, a metal substrate, a stainless steel substrate, a substrate including stainless steel foil, a tungsten substrate, a substrate including tungsten foil, a flexible substrate, or the like may be used.

(706) As a glass substrate, a barium borosilicate glass substrate, an aluminoborosilicate glass substrate, or the like may be used. For a flexible substrate, a flexible synthetic resin such as plastics typified by polyethylene terephthalate (PET), polyethylene naphthalate (PEN), or polyether sulfone (PES), or acrylic may be used. Alternatively, an attachment film (formed using polypropylene, polyester, vinyl, polyvinyl fluoride, polyvinyl chloride, or the like), paper including a fibrous material, a base material film (formed using polyester, polyamide, polyimide, an inorganic vapor deposition film, paper, or the like), or the like may be used.

(707) As the semiconductor substrate **5352**, a single crystal silicon substrate having n-type or p-type conductivity may be used. Alternatively, part of or the whole of the single crystal silicon substrate may be used as the semiconductor substrate **5352**. The region **5353** is a region where an impurity element is added to the semiconductor substrate **5352** and serves as a well. For example, in the case where the semiconductor substrate **5352** has p-type conductivity, the region **5353** has n-type conductivity and serves as an n-well. In the case where the semiconductor substrate **5352** has n-type conductivity, the region **5353** has p-type conductivity and serves as a p-well. The region **5355** is a region where an impurity element is added to the semiconductor substrate **5352** and serves as a source region or a drain region. Note that an LDD (lightly doped drain) region may be formed in the semiconductor substrate **5352**.

(708) For the insulating layer **5261**, a single-layer structure, a layered structure, or the like of an insulating film containing oxygen or nitrogen, such as a silicon oxide film, a silicon nitride film, a silicon oxynitride ($\text{SiO}_{x-y}\text{N}_y$) ($x>y>0$) film, or a silicon nitride oxide (SiN_xO_y) ($x>y>0$) film, can be used. In the case where the insulating layer **5261** has a two-layer structure, for example, an insulating layer can be used in which a silicon nitride film is formed as a first insulating layer and a silicon oxide film is formed as a second insulating layer. In the case where the insulating layer **5261** has a three-layer structure, for example, an insulating layer can be used in which a silicon oxide film is formed as a first insulating layer, a silicon nitride film is formed as a second insulating layer, and a silicon oxide film is formed as a third insulating layer.

(709) For each of the semiconductor layer **5262**, the semiconductor layer **5303a**, and the semiconductor layer **5303b**, a non-single-crystal semiconductor (e.g., amorphous silicon, polycrystalline silicon, or microcrystalline silicon), a single crystal semiconductor, a compound semiconductor or an oxide semiconductor (e.g., ZnO, InGaZnO, SiGe, GaAs, IZO (indium zinc oxide), ITO (indium tin oxide), SnO, TiO, or AlZnSnO (AZTO)), an organic semiconductor, a carbon nanotube, or the like can be used.

(710) The region **5262a** is an intrinsic region where an impurity element is not added to the semiconductor layer **5262** and serves as a channel region. Note that an impurity element may be added to the region **5262a**. The concentration of the impurity element added to the region **5262a** is preferably lower than the concentration of an impurity element added to the region **5262b**, the region **5262c**, the region **5262d**, or the region **5262e**. Each of the region **5262b** and the region **5262d** is a region where an impurity element is added to the semiconductor layer **5262** at lower concentration than the region **5262c** and the region **5262e** and serves as an LDD (lightly doped drain) region. Note that the region **5262b** and the region **5262d** may be eliminated. Each of the region **5262c** and the region **5262e** is a region where an impurity element is added to the semiconductor layer **5262** at high concentration and serves as a source region or a drain region.

(711) The semiconductor layer **5303b** is a semiconductor layer to which phosphorus or the like is added as an impurity element and has n-type conductivity. Note that in the case where an oxide semiconductor or a compound semiconductor is used for the semiconductor layer **5303a**, the semiconductor layer **5303b** may be eliminated.

(712) For each of the insulating layer **5263** and the insulating layer **5356**, a single-layer structure or a layered structure of an insulating film containing oxygen or nitrogen, such as a silicon oxide film, a silicon nitride film, a silicon oxynitride ($\text{SiO}_{x-y}\text{N}_y$) ($x>y>0$) film, or a silicon nitride oxide (SiN_xO_y) ($x>y>0$) film, is preferably used.

(713) As each of the conductive layer **5264**, the conductive layer **5266**, the conductive layer **5268**, the conductive layer **5271**, the conductive layer **5301**, the conductive layer **5304**, the conductive layer **5306**, the conductive layer **5308**, the conductive layer **5357**, and the conductive layer **5359**, a conductive film having a single-layer structure or a layered structure, or the like is preferably used. For the conductive film, the group consisting of aluminum (Al), tantalum (Ta), titanium (Ti), molybdenum (Mo), tungsten (W), neodymium (Nd), chromium (Cr), nickel (Ni), platinum (Pt), gold (Au), silver (Ag), copper (Cu), manganese (Mn), cobalt (Co), niobium (Nb), silicon (Si), iron (Fe), palladium (Pd), carbon (C), scandium (Sc), zinc (Zn), gallium (Ga), indium (In), tin (Sn), zirconium (Zr), and cerium (Ce); a single-layer film containing one element selected from the group; a film formed using a compound containing one or more elements selected from the group; or the like is preferably used. Note that the single-layer film or the compound may contain phosphorus (P), boron (B), arsenic (As), oxygen (O), or the like.

(714) A compound containing one or more elements selected from the plurality of elements (e.g., an alloy), a compound containing nitrogen and one or more elements selected from the plurality of elements (e.g., a nitride film), a compound containing silicon and one or more elements selected from the plurality of elements (e.g., a silicide film), a nanotube material, or the like can be used as the compound. Indium tin oxide (ITO), indium zinc oxide (IZO), indium tin oxide containing

silicon oxide (ITSO), zinc oxide (ZnO), tin oxide (SnO), cadmium tin oxide (CTO), aluminum-neodymium (Al—Nd), aluminum-tungsten (Al—W), aluminum-zirconium (Al—Zr), aluminum-titanium (Al—Ti), aluminum-cerium (Al—Ce), magnesium-silver (Mg—Ag), molybdenum-niobium (Mo—Nb), molybdenum-tungsten (Mo—W), molybdenum-tantalum (Mo—Ta), or the like can be used as an alloy. Titanium nitride, tantalum nitride, molybdenum nitride, or the like can be used for a nitride film. Tungsten silicide, titanium silicide, nickel silicide, aluminum silicon, molybdenum silicon, or the like can be used for a silicide film. A carbon nanotube, an organic nanotube, an inorganic nanotube, a metal nanotube, or the like can be used as a nanotube material. (715) For each of the insulating layer **5265**, the insulating layer **5267**, the insulating layer **5269**, the insulating layer **5305**, and the insulating layer **5358**, an insulating layer having a single-layer structure or a layered structure, or the like is preferably used. As the insulating layer, a film containing oxygen or nitrogen, such as a silicon oxide film, a silicon nitride film, a silicon oxynitride ($\text{SiO}_{x-y}\text{N}_y$) ($x > y > 0$) film, or a silicon nitride oxide (SiN_xO_y) ($x > y > 0$) film; a film containing carbon such as diamond-like carbon (DLC); a film formed using an organic material such as a siloxane resin, epoxy, polyimide, polyamide, polyvinyl phenol, benzocyclobutene, or acrylic; or the like can be used.

(716) The EL layer **5270** includes a light-emitting layer formed using a light-emitting material. The EL layer **5270** may include a hole injection layer formed using a hole injection material, a hole transport layer formed using a hole transport material, an electron transport layer formed using an electron transport material, an electron injection layer formed using an electron injection material, a layer in which a plurality of these materials are mixed, or the like, in addition to the light-emitting layer. The conductive layer **5268**, the EL layer **5270**, and the conductive layer **5271** form an organic EL element.

(717) The liquid crystal layer **5307** includes a liquid crystal containing a plurality of liquid crystal molecules. The state of liquid crystal molecules is mainly determined by voltage applied between a pixel electrode and a counter electrode, and the transmittance of a liquid crystal is changed. For example, an electrically controlled birefringence liquid crystal (also referred to as an ECB liquid crystal), a liquid crystal to which a dichroic pigment is added (also referred to as a GH liquid crystal), a polymer dispersed liquid crystal, a discotic liquid crystal, or the like can be used as the liquid crystal. A liquid crystal exhibiting a blue phase may be used as the liquid crystal. The liquid crystal exhibiting a blue phase contains, for example, a liquid crystal composition including a liquid crystal exhibiting a blue phase and a chiral agent. The liquid crystal exhibiting a blue phase has a short response time of 1 ms or less, and is optically isotropic; thus, alignment treatment is not needed and viewing angle dependence is small. Thus, with the liquid crystal exhibiting a blue phase, operation speed can be improved.

(718) Note that an insulating layer which functions as an alignment film, an insulating layer which functions as a protrusion, or the like may be provided over the insulating layer **5305** and the conductive layer **5306**.

(719) Note that an insulating layer or the like which functions as a color filter, a black matrix, or a protrusion may be formed over the conductive layer **5308**. An insulating layer which functions as an alignment film may be formed below the conductive layer **5308**.

(720) The gate driver circuit and the semiconductor device described in any of the above embodiments can be applied to the display device in this embodiment. In addition, the transistor described in this embodiment can be used in the gate driver circuit and the semiconductor device described in any of the above embodiments. In particular, even in the case where a non-single-crystal semiconductor such as an amorphous semiconductor or a microcrystalline semiconductor, an organic semiconductor, an oxide semiconductor, or the like is used for a semiconductor layer of the transistor, an advantage of suppression of deterioration of the transistor or the like can be obtained with the structures of the gate driver circuit and the semiconductor device described in any of the above embodiments.

Embodiment 10

(721) In this embodiment, the structure of a display device is described with reference to FIGS. 54A to 54C. As structure examples of the display device, FIG. 54A illustrates a top view of the display device and FIGS. 54B and 54C illustrate cross-sectional views taken along line A-B in FIG. 54A.

(722) In FIG. 54A, a driver circuit 5392 and a pixel portion 5393 are formed over a substrate 5400. The driver circuit 5392 includes a gate driver circuit, a source driver circuit, or the like.

(723) FIG. 54B illustrates a substrate 5400; a conductive layer 5401 provided over the substrate 5400; an insulating layer 5402 provided so as to cover the conductive layer 5401; a semiconductor layer 5403a provided over the conductive layer 5401 and the insulating layer 5402; a semiconductor layer 5403b provided over the semiconductor layer 5403a; a conductive layer 5404 provided over the semiconductor layer 5403b and the insulating layer 5402; an insulating layer 5405 which is provided over the insulating layer 5402 and the conductive layer 5404 and is provided with an opening; a conductive layer 5406 provided over the insulating layer 5405 and in the opening in the insulating layer 5405; an insulating layer 5408 provided over the insulating layer 5405 and the conductive layer 5406; a liquid crystal layer 5407 provided over the insulating layer 5405; a conductive layer 5409 provided over the liquid crystal layer 5407 and the insulating layer 5408; and a substrate 5410 provided over the conductive layer 5409.

(724) The conductive layer 5401 functions as a gate electrode. The insulating layer 5402 functions as a gate insulating film. The conductive layer 5404 functions as a wiring, an electrode of a transistor, or an electrode of a capacitor. The insulating layer 5405 functions as an interlayer film or a planarization film. The conductive layer 5406 functions as a wiring, a pixel electrode, or a reflective electrode. The insulating layer 5408 functions as a sealant. The conductive layer 5409 functions as a counter electrode or a common electrode.

(725) Here, parasitic capacitance is generated between the driver circuit 5392 and the conductive layer 5409 in some cases. Accordingly, a signal output from the driver circuit 5392 or the potential of each node is distorted or delayed, and the power consumption of the driver circuit 5392 is increased.

(726) In contrast, when the insulating layer 5408 which functions as a sealant and has lower dielectric constant than the liquid crystal layer is formed over the driver circuit 5392 as illustrated in FIG. 54B, parasitic capacitance generated between the driver circuit 5392 and the conductive layer 5409 can be reduced. Thus, distortion, delay, or the like of the signal output from the driver circuit 5392 or the potential of each node can be reduced. Alternatively, the power consumption of the driver circuit 5392 can be reduced.

(727) As illustrated in FIG. 54C, when the insulating layer 5408 which functions as a sealant is formed over part of the driver circuit 5392, a similar effect can be obtained. Note that in the case where the adverse effect of parasitic capacitance does not matter, the insulating layer 5408 is not necessarily provided.

(728) Note that although a display device provided with a liquid crystal element including a liquid crystal layer is described in this embodiment, other than the liquid crystal element, an EL element, an electrophoretic element, or the like can be used as the display element in the display device.

(729) Since the parasitic capacitance of the driver circuit can be reduced in the display device in this embodiment, distortion or delay of the output signal or the potential of each node can be reduced. Thus, it is not necessary to increase the current supply capability of the transistor, so that the channel width of the transistor can be decreased. Consequently, the layout area of the driver circuit can be decreased, so that the frame of the display device can be decreased or the display device can have higher definition.

Embodiment 11

(730) In this embodiment, a layout diagram (also referred to as a top view) of a semiconductor device is described. For example, FIG. 55 is a layout diagram of the semiconductor device

illustrated in FIG. 31B.

(731) The semiconductor device illustrated in FIG. 55 includes a conductive layer **901**, a semiconductor layer **902**, a conductive layer **903**, a conductive layer **904**, and a contact hole **905**. Note that a different conductive layer, a different contact hole, an insulating film, or the like may be formed. For example, a contact hole for connecting the conductive layer **901** and the conductive layer **903** to each other may be formed.

(732) The conductive layer **901** includes a portion which functions as a gate electrode or a wiring. The semiconductor layer **902** includes a portion which functions as a semiconductor layer of the transistor. The conductive layer **903** includes a portion which functions as a wiring, a source, or a drain. The conductive layer **904** includes a portion which functions as a transparent electrode, a pixel electrode, or a wiring. The conductive layer **901** and the conductive layer **904** can be connected to each other through the contact hole **905** or the conductive layer **903** and the conductive layer **904** can be connected to each other through the contact hole **905**.

(733) Note that when the semiconductor layer **902** is provided in a portion where the conductive layer **901** and the conductive layer **903** overlap with each other, parasitic capacitance between the conductive layer **901** and the conductive layer **903** can be reduced, so that noise can be reduced. For a similar reason, the semiconductor layer **902** may be provided in a portion where the conductive layer **901** and the conductive layer **904** overlap with each other or a portion where the conductive layer **903** and the conductive layer **904** overlap with each other.

(734) Note that when the conductive layer **904** is formed over part of the conductive layer **901** and is connected to the conductive layer **901** through the contact hole **905**, wiring resistance can be lowered.

(735) When the conductive layers **903** and **904** are formed over part of the conductive layer **901**, the conductive layer **901** is connected to the conductive layer **904** through the contact hole **905**, and the conductive layer **903** can be connected to the conductive layer **904** through the different contact hole **905**, the wiring resistance can be further lowered.

(736) When the conductive layer **904** is formed over part of the conductive layer **903** and the conductive layer **903** is connected to the conductive layer **904** through the contact hole **905**, wiring resistance can be lowered.

(737) When the conductive layer **901** or the conductive layer **903** is formed below part of the conductive layer **904** and the conductive layer **904** is connected to the conductive layer **901** or the conductive layer **903** through the contact hole **905**, wiring resistance can be lowered.

Embodiment 12

(738) In this embodiment, examples of an electronic device including the gate driver circuit, the semiconductor device, or the display device described in any of the above embodiments and applications of the semiconductor device are described with reference to FIGS. 56A to 56H and FIGS. 57A to 57H.

(739) FIGS. 56A to 56H and FIGS. 57A to 57D illustrate examples of electronic devices. These electronic devices includes a housing **5000**, a display portion **5001**, a speaker **5003**, an LED lamp **5004**, operation keys **5005**, a connection terminal **5006**, a sensor **5007**, a microphone **5008**, and the like. Note that the operation key **5005** includes a power switch or an operation switch. The sensor **5007** has a function of measuring force, displacement, position, speed, acceleration, angular velocity, rotational frequency, distance, light, liquid, magnetism, temperature, chemical substance, sound, time, hardness, electric field, current, voltage, electric power, radiation, flow rate, humidity, gradient, oscillation, smell, or infrared ray.

(740) FIG. 56A illustrates a mobile computer, which includes a switch **5009**, an infrared port **5010**, and the like in addition to the above components. FIG. 56B illustrates a portable image regenerating device provided with a storage medium (e.g., a DVD reproducing device), which includes a display portion **5002**, a storage medium reading portion **5011**, and the like in addition to the above components. FIG. 56C illustrates a goggle-type display, which includes the display

portion **5002**, a support **5012**, an earphone **5013**, and the like in addition to the above components. FIG. **56D** illustrates a portable game machine, which includes the storage medium reading portion **5011** and the like in addition to the above components.

(741) FIG. **56E** illustrates a projector, which includes a light source **5033**, a projector lens **5034**, and the like in addition to the above components. FIG. **56F** illustrates a portable game machine, which includes the display portion **5002**, the storage medium reading portion **5011**, and the like in addition to the above components. FIG. **56G** illustrates a television receiver, which includes a tuner, an image processing portion, and the like in addition to the above components. FIG. **56H** illustrates a portable television receiver, which can include a charger **5017** capable of transmitting and receiving signals and the like in addition to the above components.

(742) FIG. **57A** illustrates a display, which includes a support base **5018** and the like in addition to the above components. FIG. **57B** illustrates a camera, which includes an external connection port **5019**, a shutter button **5015**, an image reception portion **5016**, and the like in addition to the above components. FIG. **57C** illustrates a computer, which includes a pointing device **5020**, the external connection port **5019**, a reader/writer **5021**, and the like in addition to the above components. FIG. **57D** illustrates a cellular phone, which includes an antenna, a tuner of one-segment (1seg digital TV broadcasts) partial reception service for cellular phones and mobile terminals, and the like in addition to the above components.

(743) The electronic devices illustrated in FIGS. **56A** to **56H** and FIGS. **57A** to **57D** can have a variety of functions in addition to the above functions.

(744) The electronic devices illustrated in FIGS. **56A** to **56H** and FIGS. **57A** to **57D** may have, for example, a function of displaying information (e.g., a still image, a moving image, or a text image) on a display portion; a touch panel function; a function of displaying a calendar, date, time, or the like; a function of controlling processing with software (e.g., a program); a wireless communication function; a function of being connected to a computer network with a wireless communication function; a function of transmitting and receiving data with a wireless communication function; a function of reading a program or data stored in a storage medium and displaying the program or data on a display portion.

(745) Further, the electronic device including a plurality of display portions may have a function of displaying image information mainly on one display portion while displaying text information on another display portion, a function of displaying a three-dimensional image by displaying images where parallax is considered on a plurality of display portions, or the like.

(746) Furthermore, the electronic device including an image reception portion may have a function of photographing a still image, a function of photographing a moving image, a function of automatically or manually correcting a photographed image, a function of storing a photographed image in a storage medium (an external storage medium or a storage medium incorporated in the electronic device), a function of displaying a photographed image on the display portion, or the like.

(747) The electronic devices described in this embodiment each include a display portion for displaying some kind of information. By applying the electronic device in this embodiment to the gate driver circuit, the semiconductor device, or the display device described in the above embodiments to the display portion in the electronic devices in this embodiment, it is possible to achieve improvement in reliability, improvement in yield, reduction in cost, the increase in the size of the display portion, the increase in the definition of the display portion, or the like.

(748) Next, applications of a semiconductor device are described with reference to FIGS. **57E** to **57H**.

(749) An example in which the semiconductor device is incorporated in a building structure is described with reference to each of FIGS. **57E** and **57F**. An example in which the semiconductor device is incorporated in a moving vehicle is described with reference to each of FIGS. **57G** and **57H**.

(750) In FIG. 57E, the semiconductor device is incorporated in a wall that is a building structure. In FIG. 57E, the semiconductor device includes a housing **5022**, a display portion **5023**, a remote control **5024** that is an operation portion, a speaker **5025**, and the like. The semiconductor device is incorporated in the wall of a building and can be provided without requiring a large space.

(751) In FIG. 57F, the semiconductor device is incorporated in a prefabricated bath **5027** that is a building structure. A display panel **5026** included in the semiconductor device is incorporated in the prefabricated bath **5027**, so that a person who takes a bath can watch the display panel **5026**.

(752) Note that although FIGS. 57E and 57F illustrate the wall and the prefabricated bath unit as examples of the building structures, the semiconductor device can be provided in a variety of building structures.

(753) In FIG. 57G, the semiconductor device is incorporated in a display panel **5028** in a car body **5029** of a car and can display information related to the operation of the car or information input from the inside or outside of the car on demand. Note that the semiconductor device may have a navigation function.

(754) In FIG. 57H, the semiconductor device is incorporated in a passenger airplane. FIG. 57H illustrates a usage pattern at the time when a display panel **5031** is provided for a ceiling **5030** above a seat of the passenger airplane. The display panel **5031** is incorporated in the ceiling **5030** through a hinge **5032**, and a passenger can watch the display panel **5031** by stretching of the hinge **5032**. The display panel **5031** has a function of displaying information by the operation of the passenger.

(755) Note that although a car and an airplane are illustrated as moving vehicles in FIGS. 57G and 57H, the semiconductor device can be provided for a variety of vehicles such as two-wheeled vehicles, four-wheeled vehicles (including cars, buses, and the like), trains (including monorails, railroads, and the like), and vessels.

Example 1

(756) In this example, circuit simulation was performed to verify that delay or distortion of a signal output to a gate signal line is decreased in a semiconductor device including two gate driver circuits.

(757) In the circuit simulation, the semiconductor device described in Embodiment 5 with reference to FIG. 31B was used. In the semiconductor device illustrated in FIG. 31B, the wiring **111** corresponds to a gate signal line and the circuits **200A** and **200B** correspond to gate driver circuits.

(758) In addition, FIG. 59 is a circuit diagram of a semiconductor device used as a comparison example. In FIG. 59, a circuit **6200** includes a transistor **6201**, a transistor **6202**, a transistor **6301**, a transistor **6302**, a transistor **6401**, and a transistor **6402**.

(759) A first terminal of the transistor **6201** is connected to a wiring **6112**. A second terminal of the transistor **6201** is connected to a wiring **6111**. A gate of the transistor **6201** is connected to the node C1. A first terminal of the transistor **6202** is connected to a wiring **6113**. A second terminal of the transistor **6202** is connected to the wiring **6111**. A gate of the transistor **6202** is connected to the node C2.

(760) A first terminal of the transistor **6301** is connected to a wiring **6114**. A second terminal of the transistor **6301** is connected to the node C1. A gate of the transistor **6301** is connected to the wiring **6114**. A first terminal of the transistor **6302** is connected to the wiring **6113**. A second terminal of the transistor **6302** is connected to the node C1. A gate of the transistor **6302** is connected to a wiring **6116**. A first terminal of the transistor **6401** is connected to a wiring **6115**. A second terminal of the transistor **6401** is connected to the node C2. A gate of the transistor **6401** is connected to the wiring **6115**. A first terminal of the transistor **6402** is connected to the wiring **6113**. A second terminal of the transistor **6402** is connected to the node C2. A gate of the transistor **6402** is connected to the gate of the transistor **6201**.

(761) FIGS. 60A and 60B and FIG. 61 show results of the circuit simulation. Note that PSpice was

used as calculation software. It is assumed that the threshold voltage of the transistor was 5 V and the field-effect mobility of the transistor was $1 \text{ cm}^2/\text{Vs}$. Further, it is assumed that the voltage amplitude of the clock signal CK1 was 30 V (an H-level potential was 30 V and an L-level potential was 0 V), and ground voltage was 0 V.

(762) Here, the transistor **201A** and the transistor **201B** in FIG. **31B** and the transistor **6201** in FIG. **59** have the same characteristics. Similarly, the transistor **202A** and the transistor **202B** in FIG. **31B** and the transistor **6202** in FIG. **59** have the same characteristics; the transistor **301A** and the transistor **301B** in FIG. **31B** and the transistor **6301** in FIG. **59** have the same characteristics; the transistor **302A** and the transistor **302B** in FIG. **31B** and the transistor **6302** in FIG. **59** have the same characteristics; the transistor **401A** and the transistor **401B** in FIG. **31B** and the transistor **6401** in FIG. **59** have the same characteristics; the transistor **402A** and the transistor **402B** in FIG. **31B** and the transistor **6402** in FIG. **59** have the same characteristics.

(763) The same voltage was input to the wiring **113A** and the wiring **113B** in FIG. **31B** and the wiring **6113** in FIG. **59**. Similarly, the same start pulse SP was input to the wiring **114A** and the wiring **114B** in FIG. **31B** and the wiring **6114** in FIG. **59**; the same reset signal RE was input to the wiring **116A** and the wiring **116B** in FIG. **31B** and the wiring **6116** in FIG. **59**. In addition, the signal SELA was input to the wiring **115A**, and the signal SELB was input to the wiring **115B**. Fixed voltage was input to the wiring **6115**.

(764) FIG. **60A** shows results of the circuit simulation using the circuit diagram illustrated in FIG. **31B**. FIG. **60B** shows results of the circuit simulation using the circuit diagram illustrated in FIG. **59**. FIG. **60A** illustrates the potential Va1 of the node A1, the potential Va2 of the node A2, the potential Vb1 of the node B1, the potential Vb2 of the node B2, and the potential of an output signal OUT of the wiring **111**. In addition, FIG. **60B** illustrates a potential Vc1 of the node C1, a potential Vc2 of the node C2, and the potential of an output signal OUT of the signal line **6111**.

(765) With the use of FIG. **61**, the potential of the output signal OUT of the wiring **111** in FIG. **60A** is compared with the potential of the output signal OUT of the signal line **6111** in FIG. **60B**.

(766) As illustrated in FIG. **61**, it is confirmed that delay of the output signal OUT output to the wiring **111** in FIG. **60A** was further decreased as compared to delay of the output signal OUT output to the signal line **6111** in FIG. **60B**.

(767) This application is based on Japanese Patent Application serial No. 2010-201621 filed with Japan Patent Office on Sep. 9, 2010, the entire contents of which are hereby incorporated by reference.

Claims

1. A display device comprising: a first gate driver circuit; and a second gate driver circuit, wherein each of the first gate driver circuit and the second gate driver circuit comprises a plurality of circuits, wherein at least one of the plurality of circuits comprises first to tenth transistors, wherein one of a source and a drain of the first transistor is electrically connected to a first wiring, wherein the other of the source and the drain of the first transistor is electrically connected to a second wiring, wherein one of a source and a drain of the second transistor is electrically connected to a third wiring, wherein the other of the source and the drain of the second transistor is electrically connected to the first wiring, wherein one of a source and a drain of the third transistor is electrically connected to a gate of the first transistor, wherein the other of the source and the drain of the third transistor is electrically connected to a gate of the third transistor, wherein one of a source and a drain of the fourth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the fourth transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the fifth transistor is electrically connected to a gate of the second transistor, wherein the other of the source and the drain of the fifth transistor is electrically connected to a fourth wiring, wherein a gate of the fifth transistor is electrically

connected to the fourth wiring, wherein one of a source and a drain of the sixth transistor is electrically connected to the gate of the second transistor, wherein the other of the source and the drain of the sixth transistor is electrically connected to the fourth wiring, wherein a gate of the sixth transistor is electrically connected to the gate of the second transistor, wherein one of a source and a drain of the seventh transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the seventh transistor is electrically connected to the gate of the second transistor, wherein a gate of the seventh transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the eighth transistor is electrically connected to a gate of the fourth transistor, wherein the other of the source and the drain of the eighth transistor is electrically connected to a fifth wiring, wherein a gate of the eighth transistor is electrically connected to the fifth wiring, wherein one of a source and a drain of the ninth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the ninth transistor is electrically connected to the gate of the fourth transistor, wherein a gate of the ninth transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the tenth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the tenth transistor is electrically connected to the gate of the first transistor, wherein a gate of the tenth transistor is electrically connected to a sixth wiring, and wherein the fourth wiring is configured to be a clock signal line.

2. The display device according to claim 1, wherein a channel width of the seventh transistor is larger than a channel width of the fifth transistor.

3. The display device according to claim 1, wherein a channel width of the ninth transistor is larger than a channel width of the eighth transistor.

4. The display device according to claim 1, wherein the first wiring comprises a first conductive layer, wherein the one of the source and the drain of the first transistor comprises a second conductive layer, and wherein the first conductive layer and the second conductive layer are electrically connected through a plurality of contact holes in an insulating layer provided between the first conductive layer and the second conductive layer.

5. A display device comprising: a first gate driver circuit; and a second gate driver circuit, wherein each of the first gate driver circuit and the second gate driver circuit comprises a plurality of circuits, wherein at least one of the plurality of circuits comprises first to tenth transistors, wherein one of a source and a drain of the first transistor is electrically connected to a first wiring, wherein the other of the source and the drain of the first transistor is electrically connected to a second wiring, wherein one of a source and a drain of the second transistor is electrically connected to a third wiring, wherein the other of the source and the drain of the second transistor is electrically connected to the first wiring, wherein one of a source and a drain of the third transistor is electrically connected to a gate of the first transistor, wherein the other of the source and the drain of the third transistor is electrically connected to a gate of the third transistor, wherein one of a source and a drain of the fourth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the fourth transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the fifth transistor is electrically connected to a gate of the second transistor, wherein the other of the source and the drain of the fifth transistor is electrically connected to a fourth wiring, wherein a gate of the fifth transistor is electrically connected to the fourth wiring, wherein one of a source and a drain of the sixth transistor is electrically connected to the gate of the second transistor, wherein the other of the source and the drain of the sixth transistor is electrically connected to the fourth wiring, wherein a gate of the sixth transistor is electrically connected to the gate of the second transistor, wherein one of a source and a drain of the seventh transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the seventh transistor is electrically connected to the gate of the second transistor, wherein a gate of the seventh transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the eighth transistor is electrically connected to a

gate of the fourth transistor, wherein the other of the source and the drain of the eighth transistor is electrically connected to a fifth wiring, wherein a gate of the eighth transistor is electrically connected to the fifth wiring, wherein one of a source and a drain of the ninth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the ninth transistor is electrically connected to the gate of the fourth transistor, wherein a gate of the ninth transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the tenth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the tenth transistor is electrically connected to the gate of the first transistor, wherein a gate of the tenth transistor is electrically connected to a sixth wiring, wherein the first wiring is configured to transmit a signal output from the one of the plurality of circuits, wherein the second wiring is configured to be a first clock signal line, wherein the third wiring is configured to be a power supply line, and wherein the fourth wiring is configured to be a second clock signal line.

6. The display device according to claim 5, wherein a channel width of the seventh transistor is larger than a channel width of the fifth transistor.

7. The display device according to claim 5, wherein a channel width of the ninth transistor is larger than a channel width of the eighth transistor.

8. The display device according to claim 5, wherein the first wiring comprises a first conductive layer, wherein the one of the source and the drain of the first transistor comprises a second conductive layer, and wherein the first conductive layer and the second conductive layer are electrically connected through a plurality of contact holes in an insulating layer provided between the first conductive layer and the second conductive layer.

9. A display device comprising: a first gate driver circuit; and a second gate driver circuit, wherein each of the first gate driver circuit and the second gate driver circuit comprises a plurality of circuits, wherein at least one of the plurality of circuits comprises first to tenth transistors, wherein one of a source and a drain of the first transistor is electrically connected to a first wiring, wherein the other of the source and the drain of the first transistor is electrically connected to a second wiring, wherein one of a source and a drain of the second transistor is electrically connected to a third wiring, wherein the other of the source and the drain of the second transistor is electrically connected to the first wiring, wherein one of a source and a drain of the third transistor is electrically connected to a gate of the first transistor, wherein the other of the source and the drain of the third transistor is electrically connected to a gate of the third transistor, wherein one of a source and a drain of the fourth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the fourth transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the fifth transistor is electrically connected to a gate of the second transistor, wherein the other of the source and the drain of the fifth transistor is electrically connected to a fourth wiring, wherein a gate of the fifth transistor is electrically connected to the fourth wiring, wherein one of a source and a drain of the sixth transistor is electrically connected to the gate of the second transistor, wherein the other of the source and the drain of the sixth transistor is electrically connected to the fourth wiring, wherein a gate of the sixth transistor is electrically connected to the gate of the second transistor, wherein one of a source and a drain of the seventh transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the seventh transistor is electrically connected to the gate of the second transistor, wherein a gate of the seventh transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the eighth transistor is electrically connected to a gate of the fourth transistor, wherein the other of the source and the drain of the eighth transistor is electrically connected to a fifth wiring, wherein a gate of the eighth transistor is electrically connected to the fifth wiring, wherein one of a source and a drain of the ninth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the ninth transistor is electrically connected to the gate of the fourth transistor, wherein a gate of the ninth

transistor is electrically connected to the gate of the first transistor, wherein one of a source and a drain of the tenth transistor is electrically connected to the third wiring, wherein the other of the source and the drain of the tenth transistor is electrically connected to the gate of the first transistor, wherein a gate of the tenth transistor is electrically connected to a sixth wiring, wherein the fourth wiring is configured to be a clock signal line, wherein a channel width of the seventh transistor is larger than a channel width of the fifth transistor, and wherein a channel width of the ninth transistor is larger than a channel width of the eighth transistor.

10. The display device according to claim 9, wherein the first wiring comprises a first conductive layer, wherein the one of the source and the drain of the first transistor comprises a second conductive layer, and wherein the first conductive layer and the second conductive layer are electrically connected through a plurality of contact holes in an insulating layer provided between the first conductive layer and the second conductive layer.
