

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413357
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Shao; Jiafeng et al.

Uplink reference signal transmission method, user terminal, and base station

Abstract

An uplink reference signal transmission method, a user terminal, and a base station. The uplink reference signal transmission method includes receiving, by a user terminal, first higher layer signaling indicating at least one uplink reference signal symbol group, where the at least one uplink reference signal symbol group is in 14 symbols or 12 symbols, and where each uplink reference signal symbol group of the at least one uplink reference signal symbol group includes at least one time unit, receiving, by the user terminal, first control information using a physical channel, wherein the first control information indicates an uplink reference signal symbol group corresponding to the user terminal, and sending, by the user terminal, at least one uplink reference signal in the uplink reference signal symbol group corresponding to the user terminal.

Inventors:	Shao; Jiafeng (Beijing, CN), Ma; Sha (Beijing, CN)
Applicant:	Huawei Technologies Co., Ltd. (Shenzhen, CN)
Family ID:	57984595
Assignee:	HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, CN)
Appl. No.:	16/918190
Filed:	July 01, 2020

Prior Publication Data

Document Identifier	Publication Date
US 20200336266 A1	Oct. 22, 2020

Related U.S. Application Data

continuation parent-doc US 15894070 20180212 US 10735159 child-doc US 16918190
continuation parent-doc WO PCT/CN2015/086842 20150813 PENDING child-doc US 15894070

Publication Classification

Int. Cl.: H04L5/00 (20060101); H04L5/14 (20060101); H04W72/04 (20230101)

U.S. Cl.:

CPC H04L5/0048 (20130101); H04L5/0051 (20130101); H04W72/04 (20130101); H04L5/0094 (20130101); H04L5/1469 (20130101)

Field of Classification Search

CPC: H04L (5/0048); H04L (5/0051); H04L (5/0094); H04L (5/1469); H04W (72/04)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6815263	12/2003	Rissing et al.	N/A	N/A
8730850	12/2013	Noh	370/280	H04L 5/143
8804647	12/2013	Ko	370/312	H04L 27/2613
9565676	12/2016	Kothari et al.	N/A	N/A
9609647	12/2016	You	N/A	H04L 5/0051
9794039	12/2016	Kwak	N/A	H04L 27/2636
2008/0069263	12/2007	Murakami	375/267	H04L 27/0008
2008/0212702	12/2007	Pan	375/267	H04B 7/0456
2008/0237895	12/2007	Saeki	N/A	N/A
2009/0046645	12/2008	Bertrand et al.	N/A	N/A
2010/0103867	12/2009	Kishiyama et al.	N/A	N/A
2010/0118805	12/2009	Ishii	N/A	N/A
2011/0092240	12/2010	Aiba et al.	N/A	N/A
2011/0110246	12/2010	Damnjanovic	370/252	H04J 1/04
2011/0110357	12/2010	Chung	370/344	H04W 48/08
2011/0156264	12/2010	Machida	N/A	N/A
2011/0205995	12/2010	Groflen	370/329	H04L 5/0007
2012/0002580	12/2011	Nakashima	370/329	H04W 52/346
2012/0051319	12/2011	Kwon	370/329	H04W 72/20
2012/0082058	12/2011	Gerstenberger et al.	N/A	N/A
2012/0106490	12/2011	Nakashima	370/329	H04W 52/42
2012/0127888	12/2011	Fujishima	370/252	H04W 72/542
2012/0155414	12/2011	Noh	370/329	H04L 1/0026
2012/0182910	12/2011	Nakashima	370/281	H04L 5/0057
2012/0257552	12/2011	Chen	370/280	H04L 5/001
2013/0039332	12/2012	Nazar et al.	N/A	N/A
2013/0107822	12/2012	Papasakellariou	370/329	H04W 72/04
2013/0114564	12/2012	Ogawa et al.	N/A	N/A
2013/0128854	12/2012	Nakashima	370/329	H04L 5/0048

2013/0135984	12/2012	Choi	370/329	H04L 5/0048
2013/0148593	12/2012	Suzuki et al.	N/A	N/A
2013/0336256	12/2012	Chung	370/329	H04L 25/0226
2014/0050192	12/2013	Kim	370/329	H04L 5/0048
2014/0133369	12/2013	Cheng	370/280	H04L 5/0073
2014/0171111	12/2013	Xiao et al.	N/A	N/A
2014/0198747	12/2013	Ouchi	370/329	H04J 11/0053
2014/0241242	12/2013	Josiam et al.	N/A	N/A
2014/0241284	12/2013	Zhou	N/A	N/A
2014/0314026	12/2013	Ko	370/329	H04L 5/0048
2014/0334367	12/2013	Nakashima	370/311	H04W 52/346
2015/0009845	12/2014	Takano	N/A	N/A
2015/0009951	12/2014	Josiam	370/330	H04L 25/0224
2015/0023270	12/2014	Park	370/329	H04L 5/0048
2015/0063272	12/2014	Suzuki	370/329	H04L 5/0048
2015/0078273	12/2014	Aiba	370/329	H04L 5/0035
2015/0085723	12/2014	Chen	370/336	H04B 7/2656
2015/0146642	12/2014	Seo	370/329	H04L 1/06
2015/0181366	12/2014	Chae et al.	N/A	N/A
2015/0187687	12/2014	Fujisawa	N/A	N/A
2015/0222402	12/2014	Ouchi	370/329	H04W 72/21
2015/0230211	12/2014	You	370/330	H04L 5/0051
2015/0249526	12/2014	Kim	370/329	H04J 13/18
2015/0271790	12/2014	Lee	455/450	H04W 48/16
2015/0281996	12/2014	Rubin	370/328	H04W 36/0033
2015/0289234	12/2014	Zhao	370/329	H04L 1/1812
2015/0305059	12/2014	Li	370/329	H04L 1/1812
2015/0334762	12/2014	Yang	370/329	H04W 72/0406
2015/0358133	12/2014	Kusashima	370/280	H04L 5/1469
2016/0021641	12/2015	Nogami	370/330	H04J 11/00
2016/0028520	12/2015	Nogami	370/329	H04L 5/0048
2016/0056942	12/2015	Wang	370/330	H04L 5/0058
2016/0094324	12/2015	Lee	375/267	H04L 5/0051
2016/0105871	12/2015	Kwak	370/336	H04W 56/0015
2016/0127090	12/2015	Takeda	370/329	H04W 72/04
2016/0135147	12/2015	Ouchi	370/329	H04W 52/32
2016/0150490	12/2015	Ouchi	455/522	H04W 72/0446
2016/0183203	12/2015	Larsson	370/329	H04W 52/365
2016/0205704	12/2015	Aiba et al.	N/A	N/A
2016/0227373	12/2015	Tsai et al.	N/A	N/A
2016/0241323	12/2015	Ko	N/A	H04L 5/0048
2016/0249348	12/2015	Kang	N/A	H04W 56/0035
2016/0255649	12/2015	Kusashima et al.	N/A	N/A

2016/0270060	12/2015	Kusashima	N/A	H04W 72/23
2016/0285602	12/2015	Fang et al.	N/A	N/A
2016/0295499	12/2015	Tavildar	N/A	H04W 8/005
2016/0308624	12/2015	Rong	N/A	H04B 17/14
2016/0323850	12/2015	Papasakellariou	N/A	H04L 1/0045
2016/0337817	12/2015	Malladi	N/A	H04W 72/30
2016/0337954	12/2015	Gulati	N/A	H04W 48/17
2016/0345199	12/2015	Nogami et al.	N/A	N/A
2016/0381681	12/2015	Nogami et al.	N/A	N/A
2017/0005770	12/2016	Shimezawa et al.	N/A	N/A
2017/0013613	12/2016	Park	N/A	H04L 27/2613
2017/0034808	12/2016	Ouchi et al.	N/A	N/A
2017/0048834	12/2016	Suzuki	N/A	H04L 5/0091
2017/0105179	12/2016	Kusashima	N/A	H04W 52/30
2017/0118745	12/2016	Hogami et al.	N/A	N/A
2017/0188328	12/2016	Cui et al.	N/A	N/A
2017/0208584	12/2016	Qu	N/A	H04L 5/0091
2017/0245249	12/2016	Suzuki et al.	N/A	N/A
2017/0309547	12/2016	Shimizu et al.	N/A	N/A
2017/0311321	12/2016	Kakashima et al.	N/A	N/A
2017/0346615	12/2016	Liu	N/A	H04L 5/0098
2018/0092074	12/2017	Suzuki	N/A	H04W 72/23
2018/0145808	12/2017	Kem et al.	N/A	N/A
2019/0007934	12/2018	Wang	N/A	H04L 5/0094
2019/0059077	12/2018	Papasakellariou	N/A	H04L 1/0045
2020/0067743	12/2019	Murakami	N/A	H04L 5/0094

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101795145	12/2009	CN	N/A
102223726	12/2010	CN	N/A
102958154	12/2012	CN	N/A
103095442	12/2012	CN	N/A
103096389	12/2012	CN	N/A
103220791	12/2012	CN	N/A
104685948	12/2014	CN	N/A
2731284	12/2013	EP	N/A
2775759	12/2013	EP	N/A
2011095009	12/2010	WO	N/A
2011135788	12/2010	WO	N/A
2012044023	12/2011	WO	N/A
2013151392	12/2012	WO	N/A
2014201614	12/2013	WO	N/A
2014208859	12/2013	WO	N/A
2015035876	12/2014	WO	N/A
2015102290	12/2014	WO	N/A

OTHER PUBLICATIONS

Extended European Search Report, dated Jul. 13, 2018, in European Application No. 15900780.6 (7 pp.). cited by applicant
Intel Corporation, "On DM-RS enhancements for FD-MIMO", 3GPP TSG RAN WG1 Meeting #80, R1-1502393, Athens, Greece, Feb. 17-21, 2015, XP050933452, pp. 1-3. cited by applicant
International Search Report dated May 19, 2016, in corresponding International Patent Application No. PCT/CN2015/06842, 4 pgs. cited by applicant
International Search Report dated May 19, 2016 in corresponding International Patent Application No. PCT/CN2015/086842. cited by applicant
Notice of Reasons for Rejection, dated Nov. 5, 2018, in Japanese Application No. 2018-507523 (8 pp.). cited by applicant
R1-080803, Mitsubishi Electric, "UL Sounding RS Control Signaling for Closed Loop Antenna Selection," 3GPP RAN1#52, Sorrento, Italy, Feb. 11-15, 2008, pp. 1-7. cited by applicant
R1-081364, Texas Instruments, "Sounding Reference Signal In Support of Scheduling Request in E-UTRA," 3GPP TSG RAN WG1 #52bis, Shenzhen, China, Mar. 31-Apr. 4, 2008, pp. 1-7. cited by applicant
R1-102040, Panasonic, "SRS enhancement for LTE-Advanced," 3GPP TSG RAN WG1 Meeting #60bis, Beijing, China, Apr. 12-16, 2010, pp. 1-3. cited by applicant
R1-105144, Huawei, HiSilicon, "Remaining issues for aperiodic sounding," 3GPP TSG RAN WG1 meeting #62 bis, Xi'an, China, Oct. 11-15, 2010 (6 pp.). cited by applicant
R1-106007, Mediatek Inc., "Details on Aperiodic SRS," 3GPP TSG RAN WG1 Meeting #63, Jacksonville, USA, Nov. 15-19, 2010 (3 pp.). cited by applicant
Interdigital, "PUSCH for MTC UE," 3GPP TSG RAN WG1 Meeting #81, R1-153250, Fukuoka, Japan, May 25-29, 2015, total 4 pages. cited by applicant
NTT Docomo et al., "Details on PUSCH for low complexity MTC," 3GPP TSG RAN WG1 Meeting #80bis, Belgrade, Serbia, Apr. 20-24, 2015, R1-152054, total 5 pages. cited by applicant

Primary Examiner: Donabed; Ninos

Assistant Examiner: Belete; Berhanu D

Attorney, Agent or Firm: SLATER MATSIL, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 15/894,070, filed on Feb. 12, 2018, which is a continuation of International Application No. PCT/CN 2015/086842, filed on Aug. 13, 2015. All of the aforementioned patent applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(1) Embodiments of the present invention relate to communications technologies, and in particular, to an uplink reference signal transmission method, a user terminal, and a base station.

BACKGROUND

(2) With fast development of wireless communications technologies, users have higher requirements for data transmission rates. A Long Term Evolution (LTE) communications technology can provide a high-rate data network by using a high-speed low-delay flat network architecture, so as to satisfy the increasing rate transmission requirements of the users.

(3) In a current LTE system, a user terminal may send an uplink reference signal to a base station within a transmission time interval (TTI). The base station may perform channel sounding, channel

estimation, or frequency offset estimation for the user terminal according to the uplink reference signal sent by the user terminal, so as to schedule the user terminal according to a result of the channel sounding, or calibrate a frequency of uplink data of the user terminal according to a result of the frequency offset estimation and then receive, according to the calibrated frequency and a result of the channel estimation, the data sent by the user terminal. The TTI in the current LTE system is 1 ms. The TTI may be reduced to implement a shorter round-trip time and a shorter data transmission delay. If the TTI is reduced, to ensure that the base station normally receives the data sent by the user terminal, and/or that the base station normally schedules the user terminal, the user terminal needs to send sufficient uplink reference signals to the base station. That is, within the TTI, the user terminal needs to have sufficient resources for sending the uplink reference signals. (4) However, when the TTI is reduced, ensuring that the user terminal sends sufficient uplink reference signals decreases a capacity of data transmission by the user terminal within the TTI, reduces efficiency of data transmission, and decreases an uplink capacity of the system.

SUMMARY

(5) Embodiments of the present invention provide an uplink reference signal transmission method, a user terminal, and a base station to resolve problems that a quantity of user terminals supported by a base station is limited and that a capacity of a communications system is limited.

(6) According to a first aspect, an embodiment of the present invention provides an uplink reference signal transmission method, including determining, by a user terminal, an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, determining, by the user terminal, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal, and sending, by the user terminal, an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(7) According to the first aspect, in a first possible implementation of the first aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(8) According to the first aspect or the first possible implementation of the first aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(9) According to the first aspect or the first possible implementation of the first aspect, in a third possible implementation, the time unit includes a time unit in a preset time interval, and the preset time interval includes a guard period.

(10) According to any one of the first aspect to the third possible implementation of the first aspect, in a fourth possible implementation, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, before the sending, by the user terminal, an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal, the method further includes determining, by the user terminal, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal, and the sending, by the user terminal, an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to

the user terminal includes sending, by the user terminal, the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(11) According to the fourth possible implementation of the first aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 uplink subcarriers.

(12) According to any one of the first aspect to the fifth possible implementation of the first aspect, in a sixth possible implementation, the determining, by a user terminal, an uplink reference signal position according to first higher layer signaling includes determining, by the user terminal, uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information, and determining, by the user terminal, the uplink reference signal position in a preset timeslot or subframe according to the frequency domain position information.

(13) According to any one of the first aspect to the fifth possible implementation of the first aspect, in a seventh possible implementation, the determining, by a user terminal, an uplink reference signal position according to first higher layer signaling includes determining, by the user terminal, uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information, and determining, by the user terminal, the uplink reference signal position according to the frequency domain position information and the time domain position information.

(14) According to any one of the first aspect to the seventh possible implementation of the first aspect, in an eighth possible implementation, before the sending, by the user terminal, an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal, the method further includes determining, by the user terminal according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal, and correspondingly, the sending, by the user terminal, an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal includes sending, by the user terminal, the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(15) According to any one of the first aspect to the eighth possible implementation of the first aspect, in a ninth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(16) According to any one of the first aspect to the ninth possible implementation of the first aspect, in a tenth possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(17) According to a second aspect, an embodiment of the present invention further provides an uplink reference signal transmission method, including sending, by a base station, first higher layer signaling to a user terminal, where the first higher layer signaling is used by the user terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, sending, by the base station, second higher layer signaling to the user terminal, or sending first control information to the user terminal by using a physical channel, where the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the

indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal, and receiving, by the base station, an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(18) According to the second aspect, in a first possible implementation of the second aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one symbol exists between every two time units in the plurality of time units.

(19) According to the second aspect or the first possible implementation of the second aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(20) According to the second aspect or the first possible implementation of the second aspect, in a third possible implementation, the time unit is a time unit in a preset time interval, and the preset time interval includes a guard period (GP).

(21) According to any one of the second aspect to the third possible implementation of the second aspect, in a fourth possible implementation, the uplink reference signal position includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and the receiving, by the base station, an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal includes receiving, by the base station, the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(22) According to the fourth possible implementation of the second aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(23) According to any one of the second aspect to the fifth possible implementation of the second aspect, in a sixth possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(24) According to any one of the second aspect to the fifth possible implementation of the second aspect, in a seventh possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(25) According to the sixth or the seventh possible implementation of the second aspect, in an eighth possible implementation, the method further includes sending, by the base station, the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(26) According to any one of the second aspect to the eighth possible implementation of the second aspect, in a ninth possible implementation, before the receiving, by the base station, an uplink

reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal, the method further includes sending, by the base station, third higher layer signaling to the user terminal, or sending second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user terminal, and the receiving, by the base station, an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal includes receiving, by the base station, the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(27) According to any one of the second aspect to the ninth possible implementation of the second aspect, in a tenth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(28) According to any one of the second aspect to the tenth possible implementation of the second aspect, in an eleventh possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(29) According to a third aspect, an embodiment of the present invention further provides a user terminal, including a determining module, configured to determine an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, and determine, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal, and a sending module, configured to send an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(30) According to the third aspect, in a first possible implementation of the third aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(31) According to the third aspect or the first possible implementation of the third aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(32) According to the third aspect or the first possible implementation of the third aspect, in a third possible implementation, the time unit includes a time unit in a preset time interval, and the preset time interval includes a guard period.

(33) According to any one of the third aspect to the third possible implementation of the third aspect, in a fourth possible implementation, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the determining module is further configured to determine, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal, and the sending module is specifically configured to send the uplink reference signal in the time unit of

the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(34) According to the fourth possible implementation of the third aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 uplink subcarriers.

(35) According to any one of the third aspect to the fifth possible implementation of the third aspect, in a sixth possible implementation, the determining module is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information, and determine the uplink reference signal position in a preset timeslot or subframe according to the frequency domain position information.

(36) According to any one of the third aspect to the fifth possible implementation of the third aspect, in a seventh possible implementation, the determining module is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information, and determine the uplink reference signal position according to the frequency domain position information and the time domain position information.

(37) According to any one of the third aspect to the seventh possible implementation of the third aspect, in an eighth possible implementation, the determining module is further configured to determine, according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal, and the sending module is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(38) According to any one of the third aspect to the eighth possible implementation of the third aspect, in a ninth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(39) According to any one of the third aspect to the ninth possible implementation of the third aspect, in a tenth possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(40) According to a fourth aspect, an embodiment of the present invention further provides a base station, including a sending module, configured to send first higher layer signaling to a user terminal, and send second higher layer signaling to the user terminal or send first control information to the user terminal by using a physical channel, where the first higher layer signaling is used by the user terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal, and a receiving module, configured to receive an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(41) According to the fourth aspect, in a first possible implementation of the fourth aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least

one symbol exists between every two time units in the plurality of time units.

(42) According to the fourth aspect or the first possible implementation of the fourth aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(43) According to the fourth aspect or the first possible implementation of the fourth aspect, in a third possible implementation, the time unit is a time unit in a preset time interval, and the preset time interval includes a guard period (GP).

(44) According to any one of the fourth aspect to the third possible implementation of the fourth aspect, in a fourth possible implementation, the uplink reference signal position includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and the receiving module is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(45) According to the fourth possible implementation of the fourth aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(46) According to any one of the fourth aspect to the fifth possible implementation of the fourth aspect, in a sixth possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(47) According to any one of the fourth aspect to the fifth possible implementation of the fourth aspect, in a seventh possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(48) According to the sixth or the seventh possible implementation of the fourth aspect, in an eighth possible implementation, the sending module is specifically configured to send the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(49) According to any one of the fourth aspect to the eighth possible implementation of the fourth aspect, in a ninth possible implementation, the sending module is further configured to send third higher layer signaling to the user terminal, or send second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user terminal, and the receiving module is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(50) According to any one of the fourth aspect to the ninth possible implementation of the fourth aspect, in a tenth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(51) According to any one of the fourth aspect to the tenth possible implementation of the fourth aspect, in an eleventh possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(52) According to a fifth aspect, an embodiment of the present invention further provides a user terminal, including a processor and a transmitter, where the processor is configured to determine an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, and determine, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal, and the transmitter is configured to send an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(53) According to the fifth aspect, in a first possible implementation of the fifth aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(54) According to the fifth aspect or the first possible implementation of the fifth aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(55) According to the fifth aspect or the first possible implementation of the fifth aspect, in a third possible implementation, the time unit includes a time unit in a preset time interval, and the preset time interval includes a guard period.

(56) According to any one of the fifth aspect to the third possible implementation of the fifth aspect, in a fourth possible implementation, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the processor is further configured to determine, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal, and the transmitter is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(57) According to the fourth possible implementation of the fifth aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 uplink subcarriers.

(58) According to any one of the fifth aspect to the fifth possible implementation of the fifth aspect, in a sixth possible implementation, the processor is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information, and determine the uplink reference signal position in a preset timeslot or subframe according to the frequency domain position information.

(59) According to any one of the fifth aspect to the fifth possible implementation of the fifth aspect, in a seventh possible implementation, the processor is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information, and determine the uplink reference signal position according to the frequency domain position information and the time domain position information.

(60) According to any one of the fifth aspect to the seventh possible implementation of the fifth aspect, in an eighth possible implementation, the processor is further configured to determine, according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal, and the transmitter is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(61) According to any one of the fifth aspect to the eighth possible implementation of the fifth aspect, in a ninth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(62) According to any one of the fifth aspect to the ninth possible implementation of the fifth aspect, in a tenth possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(63) According to a sixth aspect, an embodiment of the present invention provides a base station, including a transmitter and a receiver, where the transmitter is configured to send first higher layer signaling to a user terminal, and send second higher layer signaling to the user terminal or send first control information to the user terminal by using a physical channel, where the first higher layer signaling is used by the user terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal, and the receiver is configured to receive an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(64) According to the sixth aspect, in a first possible implementation of the sixth aspect, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one symbol exists between every two time units in the plurality of time units.

(65) According to the sixth aspect or the first possible implementation of the sixth aspect, in a second possible implementation, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms transmission time interval (TTI).

(66) According to the sixth aspect or the first possible implementation of the sixth aspect, in a third possible implementation, the time unit is a time unit in a preset time interval, and the preset time interval includes a guard period (GP).

(67) According to any one of the sixth aspect to the third possible implementation of the sixth aspect, in a fourth possible implementation, the uplink reference signal position includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control

information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and the receiver is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(68) According to the fourth possible implementation of the sixth aspect, in a fifth possible implementation, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(69) According to any one of the sixth aspect to the fifth possible implementation of the sixth aspect, in a sixth possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(70) According to any one of the sixth aspect to the fifth possible implementation of the sixth aspect, in a seventh possible implementation, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(71) According to the sixth or the seventh possible implementation of the sixth aspect, in an eighth possible implementation, the transmitter is specifically configured to send the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(72) According to any one of the sixth aspect to the eighth possible implementation of the sixth aspect, in a ninth possible implementation, the transmitter is further configured to send third higher layer signaling to the user terminal, or send second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user terminal, and the receiver is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(73) According to any one of the sixth aspect to the ninth possible implementation of the sixth aspect, in a tenth possible implementation, the time unit is a time unit corresponding to a single carrier frequency division multiple access (SC-FDMA) symbol, or a time unit corresponding to an orthogonal frequency division multiple access (OFDMA) symbol.

(74) According to any one of the sixth aspect to the tenth possible implementation of the sixth aspect, in an eleventh possible implementation, the uplink reference signal includes a demodulation reference signal (DM-RS) and/or a sounding reference signal (SRS).

(75) According to the uplink reference signal transmission method, user terminal, and base station provided by the embodiments of the present invention, the user terminal may determine the uplink reference signal position according to the first higher layer signaling, where the uplink reference signal position includes the at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes the at least one time unit, and the user terminal determines, in the uplink reference signal position according to the indication information that is of the uplink

reference signal symbol group corresponding to the user terminal and is included in the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal, and then sends the uplink reference signal in the uplink reference signal symbol group corresponding to the user terminal. That is, each user terminal may send, in the uplink reference signal position, an uplink reference signal in an uplink reference signal symbol group corresponding to the user terminal. Even if a TTI is reduced, to ensure that each user terminal sends sufficient uplink reference signals, a quantity of time units in the uplink reference signal symbol group corresponding to the user terminal and/or a quantity of subcarriers of time units in the uplink reference signal symbol group corresponding to the user terminal may be increased in the uplink reference signal position, and there is no need to add a time unit corresponding to an uplink reference signal in every TTI. Therefore, a data transmission rate is ensured, and an uplink capacity of a system is ensured.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) To describe the technical solutions in the embodiments of the present invention or in the prior art more clearly, the following briefly describes the accompanying drawings required for describing the embodiments or the prior art. Apparently, the accompanying drawings in the following description show some embodiments of the present invention, and persons of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.
- (2) FIG. 1 is a schematic structural diagram of a radio frame in a time division duplex (TDD) communications system;
- (3) FIG. 2 is a schematic structural diagram of a radio frame in a frequency division duplex (FDD) communications system;
- (4) FIG. 3 is a flowchart of an uplink reference signal transmission method according to Embodiment 1 of the present invention;
- (5) FIG. 4 is a schematic structural diagram of an uplink reference signal position in a timeslot according to Embodiment 2 of the present invention;
- (6) FIG. 5 is a schematic structural diagram of an uplink reference signal position in a subframe according to Embodiment 2 of the present invention;
- (7) FIG. 6 is a schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a subframe according to Embodiment 2 of the present invention;
- (8) FIG. 7 is another schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a subframe according to Embodiment 2 of the present invention;
- (9) FIG. 8 is a schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a timeslot according to Embodiment 2 of the present invention;
- (10) FIG. 9 is another schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a timeslot according to Embodiment 2 of the present invention;
- (11) FIG. 10 is a schematic structural diagram of an uplink reference signal position in a timeslot according to Embodiment 2 of the present invention;
- (12) FIG. 11 is a flowchart of an uplink reference signal transmission method according to Embodiment 2 of the present invention;
- (13) FIG. 12 is a flowchart of a method for determining an uplink reference signal position in an uplink reference signal transmission method according to Embodiment 2 of the present invention;
- (14) FIG. 13 is a flowchart of another method for determining an uplink reference signal position in an uplink reference signal transmission method according to Embodiment 2 of the present invention;
- (15) FIG. 14 is a flowchart of an uplink reference signal transmission method according to

Embodiment 2 of the present invention;

(16) FIG. 15 is a flowchart of an uplink reference signal transmission method according to Embodiment 3 of the present invention;

(17) FIG. 16A and FIG. 16B are a flowchart of an uplink reference signal transmission method according to Embodiment 4 of the present invention;

(18) FIG. 17 is a schematic structural diagram of a user terminal according to Embodiment 5 of the present invention;

(19) FIG. 18 is a schematic structural diagram of a base station according to Embodiment 6 of the present invention;

(20) FIG. 19 is a schematic structural diagram of a user terminal according to Embodiment 7 of the present invention;

(21) FIG. 20 is a schematic structural diagram of a base station according to Embodiment 8 of the present invention; and

(22) FIG. 21 is a schematic structural diagram of a network system according to Embodiment 9 of the present invention.

DETAILED DESCRIPTION OF ILLUSTRATIVE EMBODIMENTS

(23) To make the objectives, technical solutions, and advantages of the embodiments of the present invention clearer, the following clearly and completely describes the technical solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are some but not all of the embodiments of the present invention. All other embodiments obtained by persons of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

(24) The solution of each embodiment of the present invention is applicable to an LTE communications system or an evolved LTE communications system, such as a Long Term Evolution-Advanced (LTE-A) communications system. The LTE communications system or the LTE-A communications system includes a time division duplex (TDD) communications system and a frequency division duplex (FDD) communications system.

(25) FIG. 1 is a schematic structural diagram of a radio frame in a TDD communications system. As shown in FIG. 1, in the TDD communications system, a radio frame may include 10 subframes: a subframe #0 to a subframe #9, and each subframe includes two 0.5 ms timeslots. The 10 subframes may include uplink subframes, downlink subframes, and special subframes. Specific subframes corresponding to the uplink subframes, the downlink subframes, and the special subframes may be determined according to uplink-downlink configuration information and a table of correspondences between the uplink-downlink configuration information and subframe numbers. Correspondences between uplink-downlink configurations and subframe numbers in the TDD communications system may be shown in the following Table 1.

(26) TABLE-US-00001 TABLE 1 Uplink- Downlink- downlink to-uplink configu- switch-point
Subframe number ration periodicity 0 1 2 3 4 5 6 7 8 9 0 5 ms D S U U U D S U S U 1 5 ms D S U
U D D S U S U 2 5 ms D S U D D D S U S U 3 10 ms D S U U U D D D S U 4 10 ms D S U U
D D D D S U 5 10 ms D S U D D D D D S U 6 5 ms D S U U U D S U S U

(27) In Table 1, D is a downlink subframe, S is a special subframe, and U is an uplink subframe.

(28) As can be learned from FIG. 1, a special subframe in the TDD communications system includes a downlink pilot timeslot (DwPTS), a guard period (GP), and an uplink pilot timeslot (UpPTS). Lengths corresponding to the DwPTS, the GP, and the UpPTS in the special subframe may be determined according to the following Table 2.

(29) TABLE-US-00002 TABLE 2 Downlink with a normal cyclic prefix Downlink with an extended cyclic prefix Uplink pilot Uplink pilot timeslot timeslot Special Uplink with Uplink with Uplink with Uplink with subframe Downlink a normal an extended Downlink a normal an extended configuration pilot timeslot cyclic prefix cyclic prefix pilot timeslot cyclic prefix cyclic

prefix 0 6592 .Math. T.sub.s 2192 .Math. T.sub.s 2560 .Math. T.sub.s 7680 .Math. T.sub.s 2192 .Math. T.sub.s 2560 .Math. T.sub.s 1 19760 .Math. T.sub.s 20480 .Math. T.sub.s 2 21952 .Math. T.sub.s 23040 .Math. T.sub.s 3 24144 .Math. T.sub.s 25600 .Math. T.sub.s 4 26336 .Math. T.sub.s 7680 .Math. T.sub.s 4384 .Math. T.sub.s 5120 .Math. T.sub.s 5 6592 .Math. T.sub.s 4384 .Math. T.sub.s 5120 .Math. T.sub.s 20480 .Math. T.sub.s 6 19760 .Math. T.sub.s 23040 .Math. T.sub.s 7 21952 .Math. T.sub.s 12800 .Math. T.sub.s 8 24144 .Math. T.sub.s — — — 9 13168 .Math. T.sub.s — — —

(30) As can be learned from FIG. 1, a total length of the special subframe is 30720 T.sub.s. With reference to lengths of the DwPTS and the UpPTS in the special subframe in Table 2, a length of the GP in the special subframe may be determined.

(31) FIG. 2 is a schematic structural diagram of a radio frame in an FDD communications system. As shown in FIG. 2, in the FDD communications system, a radio frame may include 20 timeslots: a timeslot #0 to a timeslot #19. The 20 timeslots may be grouped into 10 subframes, and each subframe includes two 0.5 ms timeslots.

(32) In an LTE communications system, transmission resources are classified according to time and frequencies. In a time domain, a maximum time unit is a 10 ms radio frame. This radio frame is divided into ten 1 ms subframes, and each subframe is further divided into two 0.5 ms timeslots. Given a normal cyclic prefix (NCP), a slot includes seven time units. Given an extended cyclic prefix (ECP), a slot includes six time units. In a frequency domain, every 12 subcarriers form a 180 kHz resource element (RE). A minimum time-frequency resource unit is an RE. The RE is a two-dimensional resource including one subcarrier in a frequency domain and duration of one time unit in time domain. A resource block (RB) is a resource block including one slot in the time domain and 12 subcarriers in the frequency domain. For a normal cyclic prefix, an RB includes 84 REs. For an extended cyclic prefix, an RB includes 72 REs.

(33) In each embodiment of the present invention, a TTI may be a subframe, or may be a timeslot, or even may be a time unit. If the TTI is a subframe, the TTI is 1 ms. If the TTI is a timeslot, the TTI may be 0.5 ms. If the TTI is a time unit, the TTI may be duration of the time unit, and the time unit may be an orthogonal frequency division multiple access (OFDMA) symbol or a single carrier frequency division multiple access (SC-FDMA) symbol in an LTE system with a 15 kHz subcarrier spacing, or a symbol in a communications system with a greater subcarrier spacing. It should be noted that the TTI in each embodiment of the present invention may also include a plurality of time units but is shorter than a timeslot.

(34) Embodiment 1 of the present invention provides an uplink reference signal transmission method. A user terminal may send an uplink reference signal of the user terminal to a base station by performing the uplink reference signal transmission method in Embodiment 1. After receiving the uplink reference signal sent by the user terminal, the base station performs channel sounding, channel estimation, or frequency offset estimation for the user terminal according to the uplink reference signal, so as to schedule the user terminal according to a result of the channel sounding, or calibrate a frequency of uplink data of the user terminal according to a result of the frequency offset estimation and then receive, according to the calibrated frequency and a result of the channel estimation, the data sent by the user terminal.

(35) FIG. 3 is a flowchart of an uplink reference signal transmission method according to Embodiment 1 of the present invention. As shown in FIG. 3, the uplink reference signal transmission method may include the following steps.

(36) **S301.** A user terminal determines an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit.

(37) Specifically, the user terminal may be, for example, user equipment (UE), a mobile station (MS), or a mobile terminal. The mobile terminal may be, for example, a mobile phone, a notebook computer, or a tablet computer. The first higher layer signaling may be any higher layer signaling

received by the user terminal. The first higher layer signaling may be radio resource control (RRC) signaling, medium access control (MAC) signaling, or other signaling. The base station may be a base station serving a cell in which the user terminal is located. The uplink reference signal position may include uplink reference signal positions of a plurality of user terminals in the cell of the base station. That is, in the method of Embodiment 1 of the present invention, the plurality of user terminals in the cell of the base station send, in the uplink reference signal position, uplink reference signals in uplink reference signal symbol groups corresponding to the user terminals.

(38) The uplink reference signal position includes at least one uplink reference signal symbol group, where each uplink reference signal symbol group includes at least one time unit. Each user terminal in the plurality of user terminals may correspond to an uplink reference signal symbol group in the uplink reference signal position. Uplink reference signal symbol groups corresponding to different user terminals in the plurality of user terminals may be the same or may be different. If the uplink reference signal symbol groups corresponding to the different user terminals are the same, that is, time domain positions of uplink reference signals of the different user terminals are the same, frequency domain positions of the uplink reference signals of the different user terminals are different, and/or codeword sequences of the uplink reference signals of the different user terminals are different. If the uplink reference signal symbol groups corresponding to the different user terminals are different, that is, the time domain positions of the uplink reference signals of the different user terminals are the same, the frequency domain positions of the uplink reference signals of the different user terminals may be the same or may be different, and the codeword sequences of the uplink reference signals of the different user terminals may be the same or may be different.

(39) The time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may include a subframe or a time unit in a timeslot.

(40) **S302.** The user terminal determines, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal.

(41) Specifically, the second higher layer signaling may also be any higher layer signaling received by the user terminal. The second higher layer signaling may be the same as or different from the first higher layer signaling. The physical channel may be a downlink physical channel, for example, a physical downlink control channel (PDCCH), or an enhanced physical downlink control channel (EPDCCH).

(42) Because the uplink reference signal position includes the uplink reference signal positions of the plurality of user terminals, the user terminal may determine, from the uplink reference signal positions of the plurality of user terminals according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal. The indication information of the uplink reference signal symbol group corresponding to the user terminal may include an identifier of the uplink reference signal symbol group corresponding to the user terminal, and/or an identifier of a time unit in the uplink reference signal symbol group corresponding to the user terminal.

(43) **S303.** The user terminal sends an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(44) Specifically, the user terminal may send the uplink reference signal in at least one time unit of the uplink reference signal symbol group corresponding to the user terminal. The user terminal may further send uplink data in a time-frequency position different from the uplink reference signal position.

(45) In the uplink reference signal transmission method provided by Embodiment 1 of the present

invention, the user terminal may determine the uplink reference signal position according to the first higher layer signaling, where the uplink reference signal position includes the at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes the at least one time unit, and the user terminal determines, in the uplink reference signal position according to the indication information that is of the uplink reference signal symbol group corresponding to the user terminal and is included in the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal, and then sends the uplink reference signal in the uplink reference signal symbol group corresponding to the user terminal. That is, each user terminal may send, in the uplink reference signal position, an uplink reference signal in an uplink reference signal symbol group corresponding to the user terminal. Because the user terminal sends, in the uplink reference signal position, the uplink signal in the uplink reference signal symbol group corresponding to the user terminal, uplink data and the uplink reference signal sent by the user terminal are sent separately on different time-frequency resources. Even if a TTI is reduced, sufficient uplink reference signals may still be sent in the uplink reference signal position, and there is no need to add a time unit corresponding to an uplink reference signal in the TTI. Therefore, a data transmission rate is ensured, and an uplink capacity of a system is ensured.

(46) Embodiment 2 of the present invention further provides an uplink reference signal transmission method. Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(47) Specifically, if each uplink reference signal symbol group includes a plurality of time units, the uplink reference signal symbol group corresponding to the user terminal includes a plurality of time units. The user terminal sends the uplink reference signal in the plurality of time units in which the time interval of at least one time unit exists between every two time units. Therefore, a result of frequency offset estimation performed by the base station after the base station receives the uplink reference signal is more accurate.

(48) For example, if the uplink reference signal position includes a time unit of an uplink reference signal symbol group that is designed in a timeslot, the time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may be a time unit in a timeslot. Given a normal cyclic prefix, a timeslot may include seven symbols, and each symbol is equivalent to a time unit. FIG. 4 is a schematic structural diagram of an uplink reference signal position in a timeslot according to Embodiment 2 of the present invention. As shown in FIG. 4, in the timeslot, the uplink reference signal position may include three uplink reference signal symbol groups. A first uplink reference signal symbol group includes time units corresponding to two symbols #0 and #3. A second uplink reference signal symbol group includes time units corresponding to two symbols #1 and #4. A third uplink reference signal symbol group includes time units corresponding to two symbols #2 and #5. In the uplink reference signal position, quantities of symbols corresponding to time units in the uplink reference signal symbol groups may be different. That is, time units corresponding to the six symbols in the timeslot may also be classified into another quantity of uplink reference signal symbol groups. That is, in the timeslot, the uplink reference signal position may include another quantity of uplink reference signal symbol groups. The another quantity may be greater than 3 and less than 6. The user terminal may select one from a plurality of uplink reference signal symbol groups in the timeslot according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, as the uplink reference signal symbol group corresponding to the user terminal. It should be noted that FIG. 4 is merely an example of the uplink reference signal position in a timeslot. A time unit of each uplink reference signal symbol group in the at least one uplink reference signal symbol group included in the uplink reference signal position may also be distributed in another manner. Details are not further

described herein.

(49) For example, if the uplink reference signal position includes a time unit of an uplink reference signal symbol group that is designed in a subframe, the time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may be a time unit in a subframe. Given a normal cyclic prefix, a subframe may include 14 symbols, and each symbol is equivalent to a time unit. FIG. 5 is a schematic structural diagram of an uplink reference signal position in a subframe according to Embodiment 2 of the present invention. As shown in FIG. 5, in the subframe, the uplink reference signal position may include seven uplink reference signal symbol groups. A first uplink reference signal symbol group includes time units corresponding to two symbols #0 and #7. A second uplink reference signal symbol group includes time units corresponding to two symbols #1 and #8. A third uplink reference signal symbol group includes time units corresponding to two symbols #2 and #9. A fourth uplink reference signal symbol group includes time units corresponding to two symbols #3 and #10. A fifth uplink reference signal symbol group includes time units corresponding to two symbols #4 and #11. A sixth uplink reference signal symbol group includes time units corresponding to two symbols #5 and #12. A seventh uplink reference signal symbol group includes time units corresponding to two symbols #6 and #13. In the uplink reference signal position, quantities of symbols corresponding to time units in the uplink reference signal symbol groups may be different. That is, the 14 symbols in the subframe may also be classified into another quantity of uplink reference signal symbol groups. That is, in the subframe, the uplink reference signal position may include another quantity of uplink reference signal symbol groups. The another quantity may be greater than 7 and less than 14. The user terminal may select one from a plurality of uplink reference signal symbol groups in the subframe according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, as the uplink reference signal symbol group corresponding to the user terminal. It should be noted that FIG. 5 is merely an example of the uplink reference signal position in a subframe. A time unit of each uplink reference signal symbol group in the at least one uplink reference signal symbol group included in the uplink reference signal position may also be distributed in another manner. Details are not further described herein.

(50) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(51) Specifically, to avoid mutual interference between the uplink reference signal sent by the user terminal and an uplink reference signal sent by a user terminal of an earlier release with a 1 ms TTI in a current cell or a neighboring cell, the time unit in each uplink reference signal symbol group may be a time unit different from the time unit of the uplink reference signal corresponding to the 1 ms TTI. In this case, the time unit of the uplink reference signal sent by the user terminal, namely, the time unit in the uplink reference signal symbol group corresponding to the user terminal and determined by the user terminal in the uplink reference signal position, is different from the time unit in which the user terminal of the 1 ms earlier release sends the uplink reference signal.

(52) For example, if the uplink reference signal position includes a time unit of an uplink reference signal symbol group that is designed in a subframe, the time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may be a time unit in a subframe. Given a normal cyclic prefix, a subframe includes two timeslots, and each timeslot includes seven symbols, that is, a subframe may include 14 uplink symbols, and each symbol is equivalent to a time unit. FIG. 6 is a schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a subframe according to Embodiment 2 of the present invention. As shown in FIG. 6, the subframe may include 14 symbols #0 to #13. A sounding reference signal (SRS) in the uplink reference signal corresponding to the 1 ms TTI in the current cell or the neighboring cell may appear on the symbol #13, and a demodulation reference signal (DM-RS) in the uplink reference signal appears on the symbols #3 and #10. Therefore, given

a normal cyclic prefix, to avoid mutual interference between the uplink reference signal sent by the user terminal and the uplink reference signal sent by the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell, symbols corresponding to the SRS and the DM-RS in the 1 ms TTI may be eschewed. In this case, the time unit in each uplink reference signal symbol group in the uplink reference signal position may be a time unit corresponding to a symbol other than the three symbols #3, #10, and #13. That is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #4, #5, #6, #7, #8, #9, #11, or #12. To eschew the SRS in the 1 ms TI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #13, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, #11, or #12. To eschew only the DMRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbols #3 and #10, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #4, #5, #6, #7, #8, #9, #11, #12, or #13.

(53) Given an extended cyclic prefix, a subframe includes two timeslots, and each timeslot includes six symbols, that is, a subframe may include 12 uplink symbols, and each symbol is equivalent to a time unit. FIG. 7 is another schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a subframe according to Embodiment 2 of the present invention. As shown in FIG. 7, the subframe may include 12 symbols #0 to #11. The SRS in the uplink reference signal corresponding to the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell may appear on the symbol #11, and the DM-RS in the uplink reference signal appears on the symbols #2 and #8. Therefore, given an extended cyclic prefix, to avoid mutual interference between the uplink reference signal sent by the user terminal and the uplink reference signal sent by the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell, symbols corresponding to the SRS and the DM-RS in the 1 ms TTI may be eschewed. In this case, the time unit in each uplink reference signal symbol group in the uplink reference signal position may be a symbol other than the three symbols #2, #8, and #11. That is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #3, #4, #5, #6, #7, #9, or #10. To eschew only the SRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #11, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, or #10. To eschew only the DMRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than symbols #2 and #8, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #3, #4, #5, #6, #7, #9, #10, or #11.

(54) For example, if the uplink reference signal position includes a time unit of an uplink reference signal symbol group that is designed in a timeslot, the time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may be a time unit in a timeslot. Given a normal cyclic prefix, a timeslot includes seven symbols, and each symbol is equivalent to a time unit. FIG. 8 is a schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a timeslot according to Embodiment 2 of the present invention. As shown in FIG. 8, the timeslot includes seven symbols #0 to #6. In the timeslot, the DM-RS in the uplink reference signal corresponding to the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell appears on the symbol #3, and the SRS in the uplink reference signal may appear on the symbol #6. Therefore, given a normal cyclic prefix, to avoid mutual interference between the uplink reference signal sent by the user terminal and the uplink reference signal sent by the user terminal of the earlier release with a 1 ms

TTI in the current cell or the neighboring cell, symbols corresponding to the SRS and the DM-RS in the 1 ms TTI may be eschewed. In this case, the time unit in each uplink reference signal symbol group in the uplink reference signal position may be a time unit corresponding to a symbol other than the symbols #3 and #6. That is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #4, or #5. To eschew only the SRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #6, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #3, #4, or #5. To eschew only the DMRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #3, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #4, #5, or #6.

(55) Given an extended cyclic prefix, a timeslot includes six symbols, and each symbol is equivalent to a time unit. FIG. 9 is another schematic structural diagram of a time unit of an uplink reference signal symbol group that is designed in a timeslot according to Embodiment 2 of the present invention. As shown in FIG. 9, the timeslot may include six symbols #0 to #5. In the timeslot, the DM-RS in the uplink reference signal corresponding to the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell appears on the symbol #2, and the SRS in the uplink reference signal may appear on the symbol #5. Therefore, given an extended cyclic prefix, to avoid mutual interference between the uplink reference signal sent by the user terminal and the uplink reference signal sent by the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell, symbols corresponding to the SRS and the DM-RS in the 1 ms TTI may be eschewed. In this case, the time unit in each uplink reference signal symbol group in the uplink reference signal position may be a time unit corresponding to a symbol other than the two symbols #2 and #5. That is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #3, or #4. To eschew only the SRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #5, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #2, #3, or #4. To eschew only the DMRS in the 1 ms TTI, the time unit in each uplink reference signal symbol group may be a time unit corresponding to a symbol other than the symbol #2, that is, the time unit in each uplink reference signal symbol group may include a time unit corresponding to at least one of the symbol #0, #1, #3, #4, or #5.

(56) For example, if the uplink reference signal position includes a time unit of an uplink reference signal symbol group that is designed in a timeslot, the time unit of the at least one uplink reference signal symbol group included in the uplink reference signal position may be a time unit in a timeslot. Given a normal cyclic prefix, a timeslot may include seven symbols, and each symbol corresponds to one time unit. FIG. 10 is a schematic structural diagram of an uplink reference signal position in a timeslot according to Embodiment 2 of the present invention. In the timeslot, a cyclic prefix (CP) added to a time unit corresponding to a symbol #0 is relatively long, and a channel quality of the time unit is unsuitable for performing averaging with channel quality of other time units. Time units corresponding to two symbols #3 and #6 are time units of uplink reference signals corresponding to the user terminal of the earlier release with a 1 ms TTI in the current cell or neighboring cell. Therefore, as shown in FIG. 10, the uplink reference signal position may include time units corresponding to four symbols #1, #2, #4, and #5. The four symbols may be classified into two uplink reference signal symbol groups. One of the two uplink reference signal symbol groups may include time units corresponding to the two symbols #1 and #4, and the other uplink reference signal symbol group may include time units corresponding to the two symbols #2 and #5. It should be noted that FIG. 10 is merely an example of the uplink reference signal position in a timeslot. One of the two uplink reference signal symbol groups may

also include time units corresponding to the two symbols #1 and #5, and the other uplink reference signal symbol group may include time units corresponding to the two symbols #2 and #4. Alternatively, the four SC-FDMA symbols may be classified into four uplink reference signal symbol groups. The user terminal may select one from the two or four uplink reference signal symbol groups according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, as the uplink reference signal symbol group corresponding to the user terminal. (57) Alternatively, the time unit may be a time unit in a preset time interval, and the preset time interval includes a GP.

(58) Specifically, if the preset time interval includes the GP, the preset time interval actually includes an idle time unit available for uplink transmission in the GP.

(59) For example, if a time unit structure of an uplink reference signal symbol group is designed in a GP in a TDD communications system, given a normal cyclic prefix, in a special subframe configuration 1, the GP may include eight symbols, and each symbol is equivalent to a time unit. In the GP, because symbols #0 to #3 are relatively close to a DwPTS, and switching from downlink transmission to uplink transmission of the user terminal in the TDD communications system may not end yet, the time units in each uplink reference signal symbol group in the uplink reference signal position may include time units corresponding to symbols #4 to #7, that is, the user terminal may send the uplink reference signal in a time unit corresponding to at least one symbol included in the uplink reference signal symbol group corresponding to the user terminal, in the time units corresponding to the symbols #4 to #7. Therefore, the uplink reference signal position may include time units corresponding to the four symbols #4, #5, #6, and #7. The time units corresponding to the four symbols may be classified into two uplink reference signal symbol groups. One of the two uplink reference signal symbol groups may include time units corresponding to the two symbols #4 and #6, and the other uplink reference signal symbol group may include time units corresponding to the two symbols #5 and #7, or one of the two uplink reference signal symbol groups may include time units corresponding to the two symbols #4 and #7, and the other uplink reference signal symbol group may include time units corresponding to the two symbols #5 and #6. Alternatively, the time units corresponding to the four symbols may be classified into four uplink reference signal symbol groups. The user terminal may select one from the two or four uplink reference signal symbol groups according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, as the uplink reference signal symbol group corresponding to the user terminal.

(60) Optionally, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers.

(61) A codeword sequence corresponding to the uplink reference signal may include a Zadoff-Chu (ZC) sequence. A length of the ZC sequence is at least 12 codewords. Therefore, each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, and each user terminal has sufficient subcarriers to transmit sufficient codewords of the ZC sequence.

(62) Specifically, each user terminal in the plurality of user terminals may correspond to an uplink reference signal subcarrier group in the uplink reference signal position, that is, on a basis of performing time division multiplexing according to the uplink reference signal symbol groups corresponding to the user terminals, frequency division multiplexing may be further performed on uplink reference signals of different user terminals in the plurality of user terminals by using the uplink reference signal subcarrier groups corresponding to the user terminals, and code division multiplexing may be further performed by using uplink reference signal codewords corresponding to the user terminals. Therefore, when time domain resources are definite, in the solution of this embodiment of the present invention, frequency division multiplexing may be further performed on the uplink reference signals corresponding to the different user terminals. Optionally, when time-

frequency resources are definite, in the solution of this embodiment of the present invention, on a basis of performing time division multiplexing and frequency division multiplexing on the uplink reference signals corresponding to the different user terminals, code division multiplexing may be further performed on the uplink reference signals. Therefore, a quantity of user terminals supported by the base station can be increased, and a system capacity can be increased.

(63) FIG. 11 is a flowchart of an uplink reference signal transmission method according to Embodiment 2 of the present invention. As shown in FIG. 11, optionally, that the user terminal sends an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal in S303 may include the following.

(64) S1101. The user terminal determines, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal.

(65) Specifically, the user terminal may determine, from the at least one uplink reference signal symbol group in the uplink reference signal position according to the indication information of the uplink reference signal symbol group corresponding to the user terminal in the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal, and determine, from the at least one uplink reference signal subcarrier group according to the indication information of the uplink reference signal subcarrier group corresponding to the user terminal, the uplink reference signal subcarrier group corresponding to the user terminal.

(66) Optionally, that the user terminal sends an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal in S303 includes the following.

(67) S1102. The user terminal sends the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(68) Optionally, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(69) Specifically, if the uplink reference signal subcarrier group corresponding to the user terminal includes at least 12 uplink subcarriers, the user terminal sends the uplink reference signal in the at least 12 uplink subcarriers in which a frequency spacing of at least one uplink subcarrier exists between every two uplink subcarriers. In this way, different user terminals may perform sending in comb-like subcarrier positions. Therefore, subcarriers in uplink reference signal subcarrier groups corresponding to different user terminals are more discrete, and it is convenient for the base station to perform channel sounding in a wider frequency domain by using uplink reference signals in limited subcarriers.

(70) FIG. 12 is a flowchart of a method for determining an uplink reference signal position in an uplink reference signal transmission method according to Embodiment 2 of the present invention. As shown in FIG. 12, optionally, that a user terminal determines an uplink reference signal position according to first higher layer signaling in S301 may include the following steps.

(71) S1201. The user terminal determines uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information.

(72) Specifically, the frequency domain position information may include a physical resource block (PRB) index, a resource block group (RBG) index, a virtual resource block (VRB) index, a subcarrier index, or a subcarrier group index.

(73) A PRB and a VRB are different resource allocation units. The PRB includes 12 consecutive subcarriers in the frequency domain and resources of one timeslot in the time domain. In localized

resource allocation, definitions of the VRB and the PRB are the same. In distributed resource allocation, a correspondence exists between the VRB and the PRB. The PRB index is an index of a PRB. The VRB index is an index of a VRB. Therefore, the PRB index may be different from the VRB index. An RBG may include a plurality of PRBs, that is, a quantity of PRBs included in the RBG may be determined according to bandwidth of the user terminal or configured by the base station. The PRB index may be a PRB number. The RBG index may be an RBG number. The VRB index may be a VRB number. The subcarrier index may be a subcarrier number. The subcarrier group index may be a subcarrier group number. A subcarrier group may include at least one subcarrier.

(74) **S1202**. The user terminal determines the uplink reference signal position in a preset timeslot or a preset subframe according to the frequency domain position information.

(75) A frequency domain resource corresponding to the frequency domain position information is within bandwidth of a carrier of the base station. That is, in this embodiment of the present invention, a time domain position of the at least one uplink reference signal symbol group in the uplink reference signal position may be in the preset timeslot or the preset subframe, and a frequency domain position thereof is a position indicated by the frequency domain position information.

(76) Alternatively, Embodiment 2 of the present invention further provides another method for determining an uplink reference signal position. FIG. 13 is a flowchart of another method for determining an uplink reference signal position in an uplink reference signal transmission method according to Embodiment 2 of the present invention. As shown in FIG. 13, that a user terminal determines an uplink reference signal position according to first higher layer signaling in S301 may include the following steps.

(77) **S1301**. The user terminal determines uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information.

(78) The time domain position information may include a symbol index, a symbol group index, a timeslot index, or a subframe index. A symbol may be an OFDMA symbol or an SC-FDMA symbol in an LTE communications system with a 15 kHz subcarrier spacing, or a symbol in a communications system with a greater subcarrier spacing. A timeslot may be a timeslot of a 0.5 ms length in an LTE communications system with a 15 kHz subcarrier spacing, or a timeslot in a communications system with a greater subcarrier spacing, for example, a timeslot of a 0.125 ms length in a communications system with a 60 kHz subcarrier spacing. A subframe may be a 1 ms subframe in an LTE system with a 15 kHz subcarrier spacing, or a subframe in a communications system with a greater subcarrier spacing, for example, a subframe of a 0.25 ms length in a communications system with a 60 kHz subcarrier spacing.

(79) **S1302**. The user terminal determines the uplink reference signal position according to the frequency domain position information and the time domain position information.

(80) That is, a time domain position of the at least one uplink reference signal symbol group in the uplink reference signal position may be a time domain position indicated by the time domain position information, and a frequency domain position thereof may be a frequency domain position indicated by the frequency domain position information.

(81) Optionally, Embodiment 2 of the present invention further provides a method for determining an uplink reference signal. FIG. 14 is a flowchart of an uplink reference signal transmission method according to Embodiment 2 of the present invention. As shown in FIG. 14, optionally, before the user terminal sends the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in S303 in Embodiment 1, the method may further include the following steps.

(82) **S1401**. The user terminal determines, according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding

to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal.

(83) Correspondingly, that the user terminal sends an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal in **S303** may include the following.

(84) **S1402**. The user terminal sends the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(85) Specifically, the at least one codeword sequence corresponding to the user terminal may be a pseudo-random sequence or an orthogonal sequence, for example, a ZC sequence. The user terminal may send the uplink reference signal by using the at least one codeword sequence corresponding to the user terminal.

(86) Optionally, the time unit may be a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(87) Optionally, the uplink reference signal in each embodiment of the present invention may include a DMRS and/or an SRS.

(88) In each uplink reference signal transmission method provided by Embodiment 2 of the present invention, a time interval is set between every two time units in a plurality of time units in each uplink reference signal symbol group, so that each user terminal can send an uplink reference signal in non-consecutive time units in the plurality of time units. This ensures that a result of frequency offset estimation performed by the base station for the user terminal is more accurate. In addition, in the method in Embodiment 2 of the present invention, because the time unit is a time unit different from a preset time unit, mutual interference between the uplink reference signal sent by the user terminal and the uplink reference signal sent by the user terminal of the earlier release with a 1 ms TTI in the current cell or the neighboring cell can be further avoided. The time unit may also be a time unit in at least one time interval in the GP, so that a time unit in a special subframe can be fully used. This reduces a time unit of an uplink reference signal in an uplink subframe, ensures uplink data transmission, and improves data transmission efficiency.

(89) Embodiment 3 of the present invention further provides an uplink reference signal transmission method. FIG. 15 is a flowchart of the uplink reference signal transmission method according to Embodiment 3 of the present invention. As shown in FIG. 15, the method may include the following steps.

(90) **S1501**. A base station sends first higher layer signaling to a user terminal, where the first higher layer signaling is used by the user terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit.

(91) **S1502**. The base station sends second higher layer signaling to the user terminal, or sends first control information to the user terminal by using a physical channel, where the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal.

(92) **S1503**. The base station receives an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(93) Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one symbol exists between every two time units in the plurality of time units.

(94) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(95) Optionally, the time unit is a time unit in a preset time interval, and the preset time interval includes a GP.

(96) Optionally, the uplink reference signal position includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and that the base station receives an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal in S1503 may include the base station receives the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(97) Optionally, if each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(98) Optionally, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(99) Alternatively, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(100) Optionally, the method further includes the base station sends the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(101) Optionally, before the base station receives the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in S1503, the method further includes the base station sends third higher layer signaling to the user terminal, or sends second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user terminal, and correspondingly, that the base station receives an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal in S1503 includes the base station receives the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(102) Optionally, the time unit is a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(103) Optionally, the uplink reference signal may include a DMRS and/or an SRS.

(104) The uplink reference signal transmission method in Embodiment 3 of the present invention is a transmission method corresponding to the uplink reference signal transmission method in Embodiment 1 or 2. A beneficial effect of the method is similar to that of the foregoing

embodiment. Details are not further described herein.

(105) Embodiment 4 of the present invention further provides an uplink reference signal transmission method. Assuming that a cell of a base station includes a first user terminal and a second user terminal, FIG. 16A and FIG. 16B are a flowchart of the uplink reference signal transmission method according to Embodiment 4 of the present invention. As shown in FIG. 16A and FIG. 16B, the method may include the following steps.

(106) **S1601.** The base station sends first uplink reference signal position information to the first user terminal, where the first uplink reference signal position information includes first time domain position information and first frequency domain position information.

(107) The base station may send the first uplink reference signal position information to the first user terminal by using higher layer signaling.

(108) **S1602.** The base station sends second uplink reference signal position information to the second user terminal, where the second uplink reference signal position information includes second time domain position information and second frequency domain position information.

(109) The base station may also send the second uplink reference signal position information to the second user terminal by using higher layer signaling. The higher layer signaling for sending the first uplink reference signal position information by the base station and the higher layer signaling for sending the second uplink reference signal position information by the base station may be the same or may be different.

(110) **S1603.** The base station sends, to the first user terminal by using a physical channel, indication information of an uplink reference signal symbol group corresponding to the first user terminal and indication information of an uplink reference signal subcarrier group corresponding to the first user terminal.

(111) The physical channel may be any downlink physical channel such as a PDCCH or an EPDCCH.

(112) **S1604.** The base station sends, to the second user terminal by using a physical channel, indication information of an uplink reference signal symbol group corresponding to the second user terminal and indication information of an uplink reference signal subcarrier group corresponding to the second user terminal.

(113) The physical channel for sending the indication information of the uplink reference signal symbol group corresponding to the first user terminal and the indication information of the uplink reference signal subcarrier group corresponding to the first user terminal by the base station may be the same as or may be different from the physical channel for sending the indication information of the uplink reference signal symbol group corresponding to the second user terminal and the indication information of the uplink reference signal subcarrier group corresponding to the second user terminal.

(114) **S1605.** The base station sends the first uplink reference signal position information and the second uplink reference signal position information to another base station by using an X2 interface, where the first uplink reference signal position information and the second uplink reference signal position information are used to make an uplink reference signal position of the another base station different from the uplink reference signal positions of the base station.

(115) The uplink reference signal positions of the base station may include a first uplink reference signal position and a second uplink reference signal position.

(116) **S1606.** The first user terminal determines a first uplink reference signal position according to the first time domain position information and the first frequency domain position information, and determines, in the first uplink reference signal position according to the indication information of the uplink reference signal symbol group corresponding to the first user terminal and the indication information of the uplink reference signal subcarrier group corresponding to the first user terminal, the uplink reference signal symbol group corresponding to the first user terminal and the uplink reference signal subcarrier group corresponding to the first user terminal.

(117) **S1607.** The base station sends indication information of a first codeword sequence to the first user terminal.

(118) The base station may send the indication information of the first codeword sequence to the first user terminal by using higher layer signaling or a physical channel.

(119) **S1608.** The first user terminal determines, according to the indication information of the first codeword sequence, the first codeword sequence corresponding to the first user terminal, and sends an uplink reference signal of the first user terminal to the base station in a time unit of the uplink reference signal symbol group corresponding to the first user terminal in a time domain and a subcarrier of the uplink reference signal subcarrier group corresponding to the first user terminal in a frequency domain by using the first codeword sequence.

(120) **S1609.** The second user terminal determines a second uplink reference signal position according to the second time domain position information and the second frequency domain position information, and determines, in the second uplink reference signal position according to the indication information of the uplink reference signal symbol group corresponding to the second user terminal and the indication information of the uplink reference signal subcarrier group corresponding to the second user terminal, the uplink reference signal symbol group corresponding to the second user terminal and the uplink reference signal subcarrier group corresponding to the second user terminal.

(121) The second uplink reference signal position determined by the second user terminal and the first uplink reference signal position determined by the first user terminal may be the same or may be different. The uplink reference signal symbol group corresponding to the second user terminal and determined by the second user terminal and the uplink reference signal symbol group corresponding to the first user terminal and determined by the first user terminal may be the same or may be different. The uplink reference signal subcarrier group corresponding to the second user terminal and determined by the second user terminal and the uplink reference signal subcarrier group corresponding to the first user terminal and determined by the first user terminal may be the same or may be different.

(122) **S1610.** The base station sends indication information of a second codeword sequence to the second user terminal.

(123) The base station may send the indication information of the second codeword sequence to the second user terminal by using higher layer signaling or a physical channel. The base station may send the indication information of the first codeword sequence and the indication information of the second codeword sequence by using the same or different higher layer signaling, or may send the indication information of the first codeword sequence and the indication information of the second codeword sequence by using the same or different physical channels. The base station may also send the indication information of the first codeword sequence by using higher layer signaling, and send the indication information of the second codeword sequence by using a physical channel. Conversely, the base station may also send the indication information of the second codeword sequence by using higher layer signaling, and send the indication information of the first codeword sequence by using a physical channel.

(124) **S1611.** The second user terminal determines, according to the indication information of the second codeword sequence, the second codeword sequence of the second user terminal, and sends an uplink reference signal of the second user terminal to the base station in a time unit of the uplink reference signal symbol group corresponding to the second user terminal in the time domain and a subcarrier of the uplink reference signal subcarrier group corresponding to the second user terminal in the frequency domain by using the second codeword sequence.

(125) **S1612.** The base station receives, in the uplink reference signal symbol group corresponding to the first user terminal in the time domain and the uplink reference signal subcarrier group corresponding to the first user terminal in the frequency domain, the uplink reference signal of the first user terminal that is sent by the first user terminal by using the first codeword sequence, and

receives, in the time unit of the uplink reference signal symbol group corresponding to the second user terminal in the time domain and the subcarrier of the uplink reference signal subcarrier group corresponding to the second user terminal in the frequency domain, the uplink reference signal of the second user terminal that is sent by the second user terminal by using the second codeword sequence.

(126) The uplink reference signal transmission method in Embodiment 4 of the present invention is described in the foregoing embodiment by using a specific example. A beneficial effect of the method is similar to that of the foregoing embodiment. Details are not further described herein.

(127) Embodiment 5 of the present invention further provides a user terminal. The user terminal provided by this embodiment may be configured to perform the uplink reference signal transmission method in Embodiment 1 or Embodiment 2. FIG. 17 is a schematic structural diagram of the user terminal according to Embodiment 5 of the present invention. As shown in FIG. 17, the user terminal **1700** may include a determining module **1701** and a sending module **1702**.

(128) The determining module **1701** is configured to determine an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, and determine, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal.

(129) The sending module **1702** is configured to send an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(130) Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(131) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(132) Optionally, the time unit includes a time unit in a preset time interval, and the preset time interval includes a guard period.

(133) Optionally, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the determining module **1701** is further configured to determine, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal, and the sending module **1702** is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(134) Optionally, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 uplink subcarriers.

(135) Optionally, the determining module **1701** is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information, and determine the uplink reference signal position in a preset timeslot or subframe according to the frequency domain position information.

(136) Optionally, the determining module **1701** is further configured to determine uplink reference

signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information, and determine the uplink reference signal position according to the frequency domain position information and the time domain position information.

(137) Optionally, the determining module **1701** is further configured to determine, according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal, and the sending module **1702** is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(138) Optionally, the time unit is a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(139) The user terminal provided by Embodiment 5 of the present invention can perform the uplink reference signal transmission method in Embodiment 1 or Embodiment 2. For a beneficial effect and an implementation process of the user terminal, refer to the descriptions in the foregoing embodiment. Details are not further described herein.

(140) Embodiment 6 of the present invention further provides a base station. The base station in Embodiment 6 can perform the uplink reference signal transmission method in Embodiment 3. FIG. **18** is a schematic structural diagram of the base station according to Embodiment 6 of the present invention. As shown in FIG. **18**, the base station **1800** includes a sending module **1801** and a receiving module **1802**.

(141) The sending module **1801** is configured to send first higher layer signaling to a user terminal, and send second higher layer signaling to the user terminal or send first control information to the user terminal by using a physical channel, where the first higher layer signaling is used by the user terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal.

(142) The receiving module **1802** is configured to receive an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(143) Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one symbol exists between every two time units in the plurality of time units.

(144) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(145) Optionally, the time unit is a time unit in a preset time interval, and the preset time interval includes a GP.

(146) Optionally, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink

reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and the receiving module **1802** is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(147) Optionally, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(148) Optionally, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(149) Optionally, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(150) Optionally, the sending module **1801** is specifically configured to send the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(151) Optionally, the sending module **1801** is further configured to send third higher layer signaling to the user terminal, or send second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user terminal, and the receiving module **1802** is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(152) Optionally, the time unit is a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(153) The base station provided by Embodiment 6 of the present invention can perform the uplink reference signal transmission method in Embodiment 3. For a beneficial effect and an implementation process of the base station, refer to the descriptions in the foregoing embodiment. Details are not further described herein.

(154) Embodiment 7 of the present invention further provides a user terminal. FIG. **19** is a schematic structural diagram of the user terminal according to Embodiment 7 of the present invention. As shown in FIG. **19**, the user terminal **1900** may include a processor **1901** and a transmitter **1902**.

(155) The processor **1901** is configured to determine an uplink reference signal position according to first higher layer signaling, where the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, and determine, in the uplink reference signal position according to second higher layer signaling or received first control information of a physical channel, an uplink reference signal symbol group corresponding to the user terminal, where the second higher layer signaling or the first control information includes indication information of the uplink reference signal symbol group corresponding to the user terminal.

(156) The transmitter **1902** is configured to send an uplink reference signal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(157) Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one time unit exists between every two time units in the plurality of time units.

(158) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(159) Optionally, the time unit includes a time unit in a preset time interval, and the preset time interval includes a guard period.

(160) Optionally, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the processor **1901** is further configured to determine, in the uplink reference signal position according to the second higher layer signaling or the first control information, the uplink reference signal symbol group corresponding to the user terminal and an uplink reference signal subcarrier group corresponding to the user terminal, where the second higher layer signaling or the first control information further includes indication information of the uplink reference signal subcarrier group corresponding to the user terminal, and the transmitter **1902** is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(161) Optionally, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 uplink subcarriers.

(162) Optionally, the processor **1901** is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes frequency domain position information, and determine the uplink reference signal position in a preset timeslot or subframe according to the frequency domain position information.

(163) Optionally, the processor **1901** is further configured to determine uplink reference signal position information according to the first higher layer signaling, where the uplink reference signal position information includes time domain position information and frequency domain position information, and determine the uplink reference signal position according to the frequency domain position information and the time domain position information.

(164) Optionally, the processor **1901** is further configured to determine, according to third higher layer signaling or received second control information of the physical channel, at least one codeword sequence corresponding to the user terminal, where the third higher layer signaling or the second control information includes indication information of the codeword sequence corresponding to the user terminal, and the transmitter **1902** is specifically configured to send the uplink reference signal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal.

(165) Optionally, the time unit is a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(166) The user terminal provided by Embodiment 7 of the present invention can perform the uplink reference signal transmission method in Embodiment 1 or Embodiment 2. For a beneficial effect and an implementation process of the user terminal, refer to the descriptions in the foregoing embodiment. Details are not further described herein.

(167) Embodiment 8 of the present invention further provides a base station. FIG. **20** is a schematic structural diagram of the base station according to Embodiment 8 of the present invention. As shown in FIG. **20**, the base station **2000** includes a transmitter **2001** and a receiver **2002**.

(168) The transmitter **2001** is configured to send first higher layer signaling to a user terminal, and send second higher layer signaling to the user terminal or send first control information to the user terminal by using a physical channel, where the first higher layer signaling is used by the user

terminal to determine an uplink reference signal position, the uplink reference signal position includes at least one uplink reference signal symbol group, and each uplink reference signal symbol group includes at least one time unit, the second higher layer signaling or the first control information includes indication information of an uplink reference signal symbol group corresponding to the user terminal, and the indication information of the uplink reference signal symbol group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal symbol group corresponding to the user terminal.

(169) The receiver **2002** is configured to receive an uplink reference signal sent by the user terminal in a time unit of the uplink reference signal symbol group corresponding to the user terminal.

(170) Optionally, if each uplink reference signal symbol group includes a plurality of time units, a time interval of at least one symbol exists between every two time units in the plurality of time units.

(171) Optionally, the time unit is a time unit different from a preset time unit, and the preset time unit is a time unit of an uplink reference signal corresponding to a 1 ms TTI.

(172) Optionally, the time unit is a time unit in a preset time interval, and the preset time interval includes a GP.

(173) Optionally, the uplink reference signal position further includes at least one uplink reference signal subcarrier group, and each uplink reference signal subcarrier group includes at least 12 uplink subcarriers, the second higher layer signaling or the first control information further includes indication information of an uplink reference signal subcarrier group corresponding to the user terminal, and the indication information of the uplink reference signal subcarrier group corresponding to the user terminal is used to instruct the user terminal to determine, in the uplink reference signal position, the uplink reference signal subcarrier group corresponding to the user terminal, and the receiver **2002** is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal in a time domain and a subcarrier of the uplink signal subcarrier group corresponding to the user terminal in a frequency domain.

(174) Optionally, a frequency spacing of at least one subcarrier exists between every two subcarriers in the at least 12 subcarriers.

(175) Optionally, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes frequency domain position information, and the frequency domain position information is used by the user terminal to determine the uplink reference signal position in a preset timeslot or subframe.

(176) Optionally, the first higher layer signaling includes uplink reference signal position information, where the uplink reference signal position information includes time domain position information and frequency domain position information, and the time domain position information and the frequency domain position information are used by the user terminal to determine the uplink reference signal position.

(177) Optionally, the transmitter **2001** is specifically configured to send the uplink reference signal position information to another base station by using an X2 interface, where the uplink reference signal position information is used to make an uplink reference signal position of the another base station different from the uplink reference signal position of the base station.

(178) Optionally, the transmitter **2001** is further configured to send third higher layer signaling to the user terminal, or send second control information to the user terminal by using the physical channel, where the third higher layer signaling or the second control information includes indication information of a codeword sequence corresponding to the user terminal, and the indication information of the codeword sequence corresponding to the user terminal is used to instruct the user terminal to determine at least one codeword sequence corresponding to the user

terminal, and the receiver **2002** is specifically configured to receive the uplink reference signal sent by the user terminal in the time unit of the uplink reference signal symbol group corresponding to the user terminal by using the at least one codeword sequence corresponding to the user terminal. (179) Optionally, the time unit is a time unit corresponding to an SC-FDMA symbol, or a time unit corresponding to an OFDMA symbol.

(180) The base station provided by Embodiment 8 of the present invention can perform the uplink reference signal transmission method in Embodiment 3. For a beneficial effect and an implementation process of the base station, refer to the descriptions in the foregoing embodiment. Details are not further described herein.

(181) Embodiment 9 of the present invention further provides a network system. FIG. **21** is a schematic structural diagram of the network system according to Embodiment 9 of the present invention. As shown in FIG. **21**, the network system **2100** may include at least one base station **2101** and at least one user terminal **2102** in a cell of each of the at least one base station.

(182) Each of the at least one base station **2101** may be the base station in Embodiment 6 or Embodiment 8, and can perform the uplink reference signal transmission method provided by Embodiment 3. For a specific structure of each base station, refer to the base station in Embodiment 6 or Embodiment 8. Details are not further described herein. Each of the at least one user terminal **2102** may be the user terminal in Embodiment 5 or Embodiment 7, and can perform the uplink reference signal transmission method in Embodiment 1 or Embodiment 2. For a specific structure of each user terminal, refer to the user terminal in Embodiment 5 or Embodiment 7. Details are not further described herein. Each of the at least one base station **2101** and the at least one user terminal **2102** in the cell of each base station can jointly perform the uplink reference signal transmission method in Embodiment 4. If the network system **2100** includes at least two base stations **2101**, a message may be transmitted between every two base stations in the at least two base stations **2101** by using an X2 interface.

(183) In the network system provided by Embodiment 9 of the present invention, the base station and the user terminal can perform the uplink reference signal transmission method provided by the foregoing embodiment. A beneficial effect of the network system is similar to that of the foregoing embodiment. Details are not further described herein.

(184) Persons of ordinary skill in the art may understand that all or some of the steps of the method embodiments may be implemented by a program instructing relevant hardware. The program may be stored in a computer readable storage medium. When the program runs, the steps of the method embodiments are performed. The foregoing storage medium includes any medium that can store program code, such as a ROM, a RAM, a magnetic disk, or an optical disc.

(185) Finally, it should be noted that the foregoing embodiments are merely intended for describing the technical solutions of the present invention, but not for limiting the present invention. Although the present invention is described in detail with reference to the foregoing embodiments, persons of ordinary skill in the art should understand that they may still make modifications to the technical solutions described in the foregoing embodiments or make equivalent replacements to some or all technical features thereof, without departing from the scope of the technical solutions of the embodiments of the present invention.

Claims

1. An uplink reference signal transmission method, comprising: receiving first higher layer signaling indicating a plurality of uplink reference signal symbol groups and a plurality of uplink reference signal subcarrier groups, wherein the plurality of uplink reference signal symbol groups is in 14 symbols or 12 symbols, and wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one time unit, and wherein each uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier

groups comprises at least 12 uplink subcarriers; receiving first control information via a physical channel, wherein the first control information comprises first indication information indicating an uplink reference signal symbol group, and wherein the first control information further comprises second indication information indicating an uplink reference signal subcarrier group; determining based on the first indication information indicating the uplink reference signal symbol group, a first uplink reference signal symbol group from the plurality of uplink reference signal symbol groups indicated by the first higher layer signaling; and determining, based on the second indication information indicating the uplink reference signal subcarrier group, a first uplink reference signal subcarrier group from the plurality of uplink reference signal subcarrier groups indicated by the first higher layer signaling; and sending an uplink reference signal in a time unit of the first uplink reference signal symbol group and a subcarrier of the first uplink reference signal subcarrier group, wherein the uplink reference signal is a demodulation reference signal (DMRS) or a sounding reference signal (SRS).

2. The method according to claim 1, wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises a plurality of time units, and wherein every two time units in the plurality of time units are separated by a time interval of at least one time unit.

3. The method according to claim 1, wherein the 14 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, #11, #12, and #13 for a normal cyclic prefix, or the 12 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, and #11 for an extended cyclic prefix.

4. The method according to claim 1, wherein the time unit is one symbol.

5. The method according to claim 1, wherein the at least one time unit in each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one of the symbols #0, #1, #2, #3, or #4.

6. The method according to claim 1, wherein every two subcarriers in the at least 12 uplink subcarriers are separated by a frequency spacing of at least one subcarrier.

7. The method according to claim 1, wherein the method further comprises: receiving, by a terminal, third higher layer signaling comprising indication information of at least one codeword sequence; and wherein the sending the uplink reference signal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group comprises: sending, by the terminal, the uplink reference signal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group using the at least one codeword sequence.

8. A communication apparatus, comprising: at least one processor; and a non-transitory memory storing a program for execution by the at least one processor, the program including instructions for: sending first higher layer signaling, wherein the first higher layer signaling indicates a plurality of uplink reference signal symbol groups and a plurality of uplink reference signal subcarrier groups, wherein the plurality of uplink reference signal symbol groups is in 14 symbols or 12 symbols, and wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one time unit, and each uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier groups comprises at least 12 uplink subcarriers; determining a first uplink reference signal symbol group of the plurality of uplink reference signal symbol groups and a first uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier groups; sending first control information via a physical channel, wherein the first control information comprises first indication information, wherein the first indication information indicates the first uplink reference signal symbol group from the plurality of uplink reference signal symbol groups indicated by the first higher layer signaling; and wherein the first control information further comprises second indication information, wherein the second indication information indicates the first uplink reference signal subcarrier group from the plurality of uplink reference signal subcarrier groups indicated by the

first higher layer signaling; and receiving an uplink reference signal in a time unit of the first uplink reference signal symbol group and a subcarrier of the first uplink reference signal subcarrier group.

9. The apparatus according to claim 8, wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol group comprises a plurality of time units, wherein every two time units in the plurality of time units are separated by a time interval of at least one time unit.

10. The apparatus according to claim 8, wherein the 14 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, #11, #12, and #13 for a normal cyclic prefix, or 12 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, and #11 for an extended cyclic prefix.

11. The apparatus according to claim 8, wherein the time unit is one symbol.

12. The apparatus according to claim 8, wherein the at least one time unit in each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one of symbol #0, #1, #2, #3, or #4.

13. The apparatus according to claim 8, wherein every two subcarriers in the at least 12 uplink subcarriers are separated by a frequency spacing of at least one subcarrier.

14. The apparatus according to claim 8, wherein the program further includes instructions for: sending third higher layer signaling comprising indication information of at least one codeword sequence corresponding to a terminal; and wherein the receiving the uplink reference signal from the terminal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group comprises: receiving the uplink reference signal from the terminal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group using the at least one codeword sequence.

15. A communication apparatus, comprising: at least one processor; and a non-transitory memory storing a program for execution by the processor, the program including instructions for: receiving first higher layer signaling indicating a plurality of uplink reference signal symbol groups and a plurality of uplink reference signal subcarrier groups, wherein the plurality of uplink reference signal symbol groups is in 14 symbols or 12 symbols, and wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol group comprises at least one time unit, and each uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier groups comprises at least 12 uplink subcarriers; receiving first control information via a physical channel, wherein the first control information comprises first indication information indicating an uplink reference signal symbol group, and wherein the first control information further comprises second indication information indicating an uplink reference signal subcarrier group; determining based on the first indication information indicating the uplink reference signal symbol group, a first uplink reference signal symbol group from the plurality of uplink reference signal symbol groups indicated by the first higher layer signaling; and determining, based on the second indication information indicating the uplink reference signal subcarrier group, a first uplink reference signal subcarrier group from the plurality of uplink reference signal subcarrier groups indicated by the first higher layer signaling; and sending an uplink reference signal in a time unit of the first uplink reference signal symbol group and a subcarrier of the first uplink reference signal subcarrier, wherein the uplink reference signal is a demodulation reference signal (DMRS) or a sounding reference signal (SRS).

16. The apparatus according to claim 15, wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises a plurality of time units, and wherein every two time units in the plurality of time units are separated by a time interval of at least one time unit.

17. The apparatus according to claim 15, wherein the 14 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, #11, #12, and #13 for a normal cyclic prefix, or the 12 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, and #11 for an extended cyclic prefix.

18. The apparatus according to claim 15, wherein the time unit is one symbol.

19. The apparatus according to claim 15, wherein the at least one time unit in each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one of symbol #0, #1, #2, #3, or #4.
20. The apparatus according to claim 15, wherein every two subcarriers in the at least 12 uplink subcarriers are separated by a frequency spacing of at least one subcarrier.
21. The apparatus according to claim 15, wherein the program further includes instructions for: receiving third higher layer signaling comprising indication information of at least one codeword sequence; and wherein the sending the uplink reference signal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group comprises: sending the uplink reference signal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group using the at least one codeword sequence.
22. An uplink reference signal transmission method, comprising: sending, by an apparatus, first higher layer signaling, wherein the first higher layer signaling indicates a plurality of uplink reference signal symbol groups and a plurality of uplink reference signal subcarrier groups, wherein the plurality of uplink reference signal symbol groups is in 14 symbols or 12 symbols, wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one time unit, and wherein each uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier groups comprises at least 12 uplink subcarriers; determining, by the apparatus, a first uplink reference signal symbol group of the plurality of uplink reference signal symbol groups and a first uplink reference signal subcarrier group of the plurality of uplink reference signal subcarrier groups; sending, by the apparatus, first control information via a physical channel, wherein the first control information comprises first indication information, wherein the first indication information indicates the first uplink reference signal symbol group from the plurality of uplink reference signal symbol groups indicated by the first higher layer signaling, and wherein the first control information further comprises second indication information, wherein the second indication information indicates the first uplink reference signal subcarrier group from the plurality of uplink reference signal subcarrier groups indicated by the first higher layer signaling; and receiving, by the apparatus, an uplink reference signal in a time unit of the first uplink reference signal symbol group and a subcarrier of the first uplink reference signal subcarrier group.
23. The method according to claim 22, wherein each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises a plurality of time units, wherein every two time units in the plurality of time units are separated by a time interval of at least one time unit.
24. The method according to claim 22, wherein the 14 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, #11, #12, and #13 for a normal cyclic prefix, or the 12 symbols comprise symbols #0, #1, #2, #3, #4, #5, #6, #7, #8, #9, #10, and #11 for an extended cyclic prefix.
25. The method according to claim 22, wherein the time unit is one symbol.
26. The method according to claim 22, wherein the at least one time unit in each uplink reference signal symbol group of the plurality of uplink reference signal symbol groups comprises at least one of symbol #0, #1, #2, #3, or #4.
27. The method according to claim 22, wherein every two subcarriers in the at least 12 uplink subcarriers are separated by a frequency spacing of at least one subcarrier.
28. The method according to claim 22, further comprising: sending, by the apparatus, third higher layer signaling comprising indication information of at least one codeword sequence; and wherein the receiving, by the apparatus, the uplink reference signal from a terminal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group comprises: receiving, by the apparatus, the uplink reference signal from the

terminal in the time unit of the first uplink reference signal symbol group and the subcarrier of the first uplink reference signal subcarrier group using the at least one codeword sequence.
