

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413232
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Clark; Kevin et al.

Multi-purpose interface for configuration data and user fabric data

Abstract

An integrated circuit device may include a programmable fabric die having programmable logic fabric and configuration memory that may configure the programmable logic fabric. The integrated circuit device may also include a base die that may provide fabric support circuitry, including memory and/or communication interfaces. The first die and the second die may be coupled using a multi-purpose interface that may allow communication between the first die and the second die. The multi-purpose interface may allow concurrent access to the base die by the programmable logic fabric and the configuration memory by using multiple channels over the multi-purpose interface.

Inventors: Clark; Kevin (San Jose, CA), Weber; Scott J. (Piedmont, CA), Ball; James (San Jose, CA), Gutala; Ravi Prakash (San Jose, CA), Dasu; Aravind Raghavendra (Milpitas, CA)

Applicant: Intel Corporation (Santa Clara, CA)

Family ID: 66327668

Assignee: Altera Corporation (San Jose, CA)

Appl. No.: 17/893004

Filed: August 22, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230056118 A1	Feb. 23, 2023

Related U.S. Application Data

continuation parent-doc US 17094612 20201110 US 11424744 child-doc US 17893004
continuation parent-doc US 16235984 20181228 US 10833679 20201110 child-doc US 17094612

Publication Classification

Int. Cl.: **H03K19/1776** (20200101); **G11C5/02** (20060101); **G11C7/10** (20060101); **H01L25/065** (20230101)

U.S. Cl.:

CPC **H03K19/1776** (20130101); **G11C5/025** (20130101); **G11C7/1078** (20130101); **H01L25/0657** (20130101); H01L2225/06513 (20130101)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9401190	12/2015	Tan et al.	N/A	N/A
10833679	12/2019	Clark et al.	N/A	N/A
11424744	12/2021	Clark	N/A	H03K 19/1776
2013/0181257	12/2012	Ngai	N/A	N/A
2019/0103872	12/2018	Clark et al.	N/A	N/A
2019/0363717	12/2018	Swarbrick et al.	N/A	N/A

Primary Examiner: Tran; Anh Q

Attorney, Agent or Firm: Fletcher Yoder, P.C.

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/094,612, entitled, “MULTI-PURPOSE INTERFACE FOR CONFIGURATION DATA AND USER FABRIC DATA,” filed Nov. 10, 2020, which is a continuation of U.S. patent application Ser. No. 16/235,984, entitled “MULTI-PURPOSE INTERFACE FOR CONFIGURATION DATA AND USER FABRIC DATA,” now U.S. Pat. No. 10,833,679, filed Dec. 28, 2018, each of which is hereby incorporated by reference in its entirety for all purposes.

BACKGROUND

(1) This disclosure relates to interfaces for transfer of data in a multi-dimensional programmable logic device.

(2) This section is intended to introduce the reader to various aspects of art that may be related to various aspects of the present disclosure, which are described and/or claimed below. This discussion is believed to be helpful in providing the reader with background information to facilitate a better understanding of the various aspects of the present disclosure. Accordingly, it may be understood that these statements are to be read in this light, and not as admissions of prior art.

(3) Programmable logic devices are a class of integrated circuits that can be programmed to

perform a wide variety of operations. To that end, programmable logic devices may include circuitry for sending and receiving data. For example, a programmable logic device may include programmable logic elements programmed by a form of memory known as configuration random access memory (CRAM). To program a circuit design into a programmable logic device, the circuit design, which may be compiled into a bitstream, is transmitted and loaded into CRAM cells. Once programmed (e.g., with the bitstream), the programmable logic device may perform operations associated with the circuit design. Operations may, among other things, include data transmission and/or data reception. As such, programmable logic devices may perform operations (e.g., configuration operations, logic operations) that may include data exchange.

(4) The highly flexible nature of programmable logic devices makes them an excellent fit for accelerating many computing tasks. Thus, programmable logic devices are increasingly used as accelerators for networking, storage, data center systems, communications, mobile applications, machine learning, video processing, voice recognition, image recognition, and many other highly specialized tasks, particularly those that would be too slow or inefficient in software running on a processor. As the computing tasks performed by the programmable logic devices become more complex, more flexible and faster interfaces for data exchange processes may be of benefit.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Various aspects of this disclosure may be better understood upon reading the following detailed description and upon reference to the drawings in which:
- (2) FIG. 1 is a block diagram of a programmable logic device that is programmed with a circuit design, in accordance with an embodiment;
- (3) FIG. 2 is a block diagram of a package including the programmable logic device where a fabric die is vertically stacked with a base die and coupled through a multi-purpose parallel configuration interface, in accordance with an embodiment;
- (4) FIG. 3 is a block diagram of an example logical arrangement of the programmable logic device, in accordance with an embodiment;
- (5) FIG. 4 is a block diagram showing a fabric die of the programmable logic device that contains programmable logic fabric with embedded memory and a base die of the programmable logic device that contains non-fabric circuitry that support operations of the fabric die, in accordance with an embodiment;
- (6) FIG. 5 is a block diagram of an example topology of the fabric die having circuitry for a multi-purpose parallel interface, in accordance with an embodiment;
- (7) FIG. 6 is a block diagram of an example topology of the base die having an embedded network-on-chip (NOC) and of circuitry for a multi-purpose parallel interface, in accordance with an embodiment;
- (8) FIG. 7 is a block diagram of an example topology of the base die having circuitry for a multi-purpose parallel interface and a different configuration of the embedded NOC, in accordance with an embodiment;
- (9) FIG. 8 is a block diagram of an example topology of the base die having circuitry for a multi-purpose parallel interface and an embedded NOC integrated with a sector-aligned memory, in accordance with an embodiment;
- (10) FIG. 9 is a block diagram of sector-aligned memory having embedded NOC circuitry integrated with a sector-aligned memory and configurable to exchange data with the programmable logic die via the multi-purpose parallel interface, in accordance with an embodiment;
- (11) FIG. 10 is an example of data transfer between sectors of the programmable logic fabric using the system of FIG. 9, in accordance with an embodiment;

- (12) FIG. 11 is an example of data transfer from a sector of the programmable logic fabric to a memory of the sector-aligned memory using the system of FIG. 9;
- (13) FIG. 12 is a block diagram illustrating a multi-purpose parallel configuration interface to exchange data between embedded memory or programmable fabric in the programmable logic die and the circuitry in the base die, in accordance with an embodiment;
- (14) FIG. 13 is a block diagram illustrating multiple channels on a fabric die that may be used by a multi-purpose parallel interface, in accordance with an embodiment;
- (15) FIG. 14 is a block diagram illustrating multiple channels on a base die that may be used by a multi-purpose parallel interface, in accordance with an embodiment;
- (16) FIG. 15 is a flow chart of a method to use multiple channels using a multi-purpose interface, in accordance with an embodiment;
- (17) FIG. 16 is a block diagram illustrating a retiming process that may facilitate the use of a multi-purpose parallel interface, in accordance with an embodiment;
- (18) FIG. 17 is a timing diagram illustrating a process of retiming, in accordance with an embodiment;
- (19) FIG. 18 is a flow chart of a method to perform retiming during the use a multi-purpose parallel interface, in accordance with an embodiment;
- (20) FIG. 19 is a block diagram illustrating the use of multiple protocols with the multi-purpose parallel interface, in accordance with an embodiment; and
- (21) FIG. 20 is a block diagram of a data processing system that may use the programmable logic device to rapidly respond to data processing requests, in accordance with an embodiment.

DETAILED DESCRIPTION OF SPECIFIC EMBODIMENTS

(22) One or more specific embodiments will be described below. In an effort to provide a concise description of these embodiments, not all features of an actual implementation are described in the specification. It may be appreciated that in the development of any such actual implementation, as in any engineering or design project, numerous implementation-specific decisions must be made to achieve the developers' specific goals, such as compliance with system-related and business-related constraints, which may vary from one implementation to another. Moreover, it may be appreciated that such a development effort might be complex and time consuming, but would nevertheless be a routine undertaking of design, fabrication, and manufacture for those of ordinary skill having the benefit of this disclosure.

(23) When introducing elements of various embodiments of the present disclosure, the articles “a,” “an,” and “the” are intended to mean that there are one or more of the elements. The terms “comprising,” “including,” and “having” are intended to be inclusive and mean that there may be additional elements other than the listed elements. Additionally, it should be understood that references to “one embodiment” or “an embodiment” of the present disclosure are not intended to be interpreted as excluding the existence of additional embodiments that also incorporate the recited features. Furthermore, the phrase A “based on” B is intended to mean that A is at least partially based on B. Moreover, unless expressly stated otherwise, the term “or” is intended to be inclusive (e.g., logical OR) and not exclusive (e.g., logical XOR). In other words, the phrase A “or” B is intended to mean A, B, or both A and B.

(24) The highly flexible nature of programmable logic devices makes them an excellent fit for accelerating many computing tasks. Programmable logic devices are devices that may include customizable and reprogrammable circuitry that can perform digital operations and/or logic functions. To that end, programmable logic devices may be programmed by loading configuration data into configuration memory (e.g., configuration random access memory (CRAM)) that may be embedded in the programmable fabric. The configuration memory may store a logic design (e.g., state machines, truth tables, functions, etc.) that may control configurable logic circuitry to facilitate performance of the programmed tasks. The flexibility in the operations of programmable logic devices also allows reprogramming of the configuration memory (e.g., programming a

portion of a circuit design). For example, a system using programmable logic devices may change context (e.g., change the type of operation performed) by loading new configuration data to the configuration memory. Due to the flexibility afforded by the customizable and reconfigurable design, programmable logic devices are increasingly used as accelerators for machine learning, video processing, voice recognition, image recognition, and many other highly specialized tasks, particularly those that would be too slow or inefficient in software running on a processor. As the complexity of the tasks increase, the dimensions of the configuration data also increase, and may benefit from a high-speed interface for loading configuration memory.

(25) As discussed above, programmable circuitry in the programmable logic device (e.g., configuration memory, programmable logic elements, and embedded memory) may send and receive data (e.g., configuration data, user data, incoming data for processing by the programmable logic elements, data processed by the programmable logic data elements). In order to exchange data with external circuitry or other programmable circuitry in the programmable logic device, the device may include high-speed interfaces. A high-speed interface may be used to increase the speed of the programming and/or reprogramming operations, which may reduce the amount of idle time during which the reprogramming tasks is taking place. The high-speed interface may also be used to increase the speed of data transfer from the programmable logic elements, to facilitate data processing operations. Moreover, programmable logic devices may also have user memory that may be directly accessed by the interface. Direct access to the user memory may facilitate diagnostic operations, such as during debugging, testing, or emulation of a system design, direct and fast access to the user memory may increase the speed of diagnostic tasks.

(26) With the foregoing in mind, the embodiments described herein are related to high-speed interfaces that may be used to read or write data into programmable circuitry in programmable logic devices. As discussed herein programmable circuitry may include embedded memory, such as configuration memory (e.g., CRAM), user memory (e.g., embedded random access memory (ERAM), M20K), and/or programmable fabric, such as intellectual property (IP) blocks, programmable logic elements, and other circuits implemented in the programmable fabric. In the present discussion, configuration data refers to data that may be loaded into the configuration memory or other embedded memory, and fabric data refers to data that is exchanged with the programmable fabric.

(27) In certain embodiments, the programmable logic device may be composed of at least two separate die. The programmable logic devices may include a first die that contains the programmable circuitry and a second die that contains fabric support circuitry, such as memory and/or communication interfaces. The first die and the second die may be coupled via a high-speed interface that allows multi-purpose data exchange between the dies, and both the first die and the second die may include interface control circuitry. In order to provide access to different parts of the programmable circuitry, and in order to allow efficient data exchange with different data types (e.g., configuration data, fabric data, fabric data employing multiple protocols), the high-speed interface may implement multiple channels. Moreover, the channels may operate at any frequency and/or clocking technique to match the number of microbumps in a channel and the bandwidth of the internal bus. The high-speed interface may be used to transport configuration data and/or fabric data. The high-speed interface may be implemented using a 2.5D or a 3D connection. The coupling through the interface may take place via a high-density connection (e.g., microbumps).

(28) In some systems, in some embodiments the programmable logic die may be sectorized, as detailed below. In such systems, the fabric support circuitry in the base die may include network on chip (NOC) circuitry to send and/or receive data (e.g., configuration data, user data) with systems external to the programmable device and/or between sectors in the programmable devices. The fabric support circuitry may also include sector-aligned memory. In some embodiments, the sector-aligned memory may operate as a temporary storage (e.g., cache) for the configuration data or user memory. By incorporating the NOC into the fabric support circuitry, the NOC may resolve

periphery shoreline bandwidth issues of the fabric, while increasing the bandwidth of the fabric. In addition, the communication routes available via the NOC embedded in the fabric support circuitry may enable the fabric to implement design relocations or reconfigurations, provide alternate pathways around powered-down sectors of the fabric, and provide security isolation features. The NOC may be a source of configuration data and/or fabric data and may be integrated to access the multi-purpose high-speed interface.

(29) In addition to the above-described features, the fabric support circuitry may include, among other things, a device controller (sometimes referred to as a secure device manager (SDM)), a sector controller (sometimes referred to as a local sector manager (LSM), region controller), a configuration network on chip (CNOC), data routing circuitry, local (e.g., sectorized, sector-aligned, region-aligned) memory used to store and/or cache configuration programs (bitstreams) or data, memory controllers used to program the programmable logic fabric, input/output (I/O) interfaces or modules for the programmable logic fabric, external memory interfaces (e.g., for a high bandwidth memory (HBM) device), an embedded processor (e.g., an embedded Intel® Xeon® processor by Intel Corporation of Santa Clara, California) or an interface to connect to a processor (e.g., an interface to an Intel® Xeon® processor by Intel Corporation of Santa Clara, California), voltage control circuitry, thermal monitoring circuitry, decoupling capacitors, power clamps, or electrostatic discharge circuitry, to name just a few circuit elements that may be present on the second die.

(30) By way of introduction, FIG. 1 illustrates a block diagram of a system **10** that may employ a programmable logic device **12** that can communicate via a network-on-chip disposed on a separate die that does not include programmable logic fabric, in accordance with embodiments presented herein. Using the system **10**, a designer may implement a circuit design functionality on an integrated circuit, such as a reconfigurable programmable logic device **12**, such as a field programmable gate array (FPGA).

(31) The designer may implement a circuit design to be programmed onto the programmable logic device **12** using design software **14**, such as a version of Intel® Quartus® by Intel Corporation of Santa Clara, California. The design software **14** may use a compiler **16** to generate a low-level circuit-design defined by bitstream **18**, sometimes known as a program object file and/or configuration program, which programs the programmable logic device **12**. Thus, the compiler **16** may provide machine-readable instructions representative of the circuit design to the programmable logic device **12**. For example, the programmable logic device **12** may receive one or more configuration programs (bitstreams) **18** that describe the hardware implementations that should be stored in the programmable logic device **12**. A configuration program (e.g., bitstream) **18** may be programmed into the programmable logic device **12** as a configuration program **20**. The configuration program **20** may, in some cases, represent an accelerator function to perform machine learning functions, video processing functions, voice recognition functions, image recognition functions, networking functions, or other highly specialized task.

(32) To carry out the systems and methods of this disclosure, the programmable logic device **12** may take any suitable form that includes the multi-purpose high-speed parallel interface, which increases the speed of exchange of fabric data and/or configuration data across different portions (e.g., sectors, dies) of the programmable logic device **12**. The multi-purpose parallel interface may also allow reconfiguration of portions of the programmable logic device **12** while concurrently operating a circuit design by allowing concurrent exchange of fabric data and configuration data through distinct microbump channels. As such, in one embodiment, the programmable logic device **12** may have two separate integrated circuit die coupled via the multi-purpose parallel interface. The integrated circuit dies may include controllers for the multi-purpose parallel interface, which may be hard coded circuitry, a soft IP block, and/or custom logic.

(33) One example of the programmable logic device **12** is shown in FIG. 2, but any suitable programmable logic device may be used. In the example of FIG. 2, the programmable logic device

12 includes a fabric die **22** and a base die **24** that are connected to one another via microbumps **26**. The microbumps **26** may couple an interface in the fabric die **22** (e.g., an FPGA microbump interface (FMIB)) to an interface in the base die **24** (e.g., a base microbump interface (BMIB)), as detailed below. In the illustrated diagram of FIG. 2, the fabric die **22** and base die **24** are illustrated in a one-to-one relationship and in an arrangement in which a single base die **24** may attach to several fabric die **22**. Other arrangements, such as an arrangement in which several base die **24** may attach to a single fabric die **22**, or several base die **24** may attach to several fabric die **22** (e.g., in an interleaved pattern along the x- and/or y-direction) may also be used. Peripheral circuitry **28** may be attached to, embedded within, and/or disposed on top of the base die **24**. The base die **24** may attach to a package substrate **32** via C4 bumps **34**. In the example of FIG. 2, two pairs of fabric die **22** and base die **24** are shown communicatively connected to one another via a silicon bridge **36** (e.g., an embedded multi-die interconnect bridge (EMIB)) and microbumps **38** at a silicon bridge interface **39**.

(34) Although the microbumps **26** and the microbumps **38** are described as being employed between the fabric die **22** and the base die **24** or between the edge devices, such as the silicon bridge **36** and the silicon bridge interface **39**, it should be noted that microbumps may be employed at any suitable position between the components of the programmable logic device **12**. For example, the microbumps may be incorporated in any suitable position (e.g., middle, edge, diagonal) between the fabric die **22** and the base die **24**. In the same manner, the microbumps may be incorporated in any suitable pattern or amorphous shape to facilitate interconnectivity between various components (e.g., NOC) described herein.

(35) In combination, the fabric die **22** and base die **24** may operate as a programmable logic device such as a field programmable gate array (FPGA) device. For example, the fabric die **22** and the base die **24** may operate in combination as an FPGA **40**, shown in FIG. 3. It should be understood that the FPGA **40** shown in FIG. 3 is meant to represent the type of circuitry and/or a logical arrangement of a programmable logic device when both the fabric die **22** and the base die **24** operate in combination. That is, some of the circuitry of the FPGA **40** shown in FIG. 3 may be found in the fabric die **22** and some of the circuitry of the FPGA **40** shown in FIG. 3 may be found in the base die **24**. Moreover, for the purposes of this example, the FPGA **40** is referred to as an FPGA, though it should be understood that the device may be any suitable type of programmable logic device (e.g., an application-specific integrated circuit and/or application-specific standard product).

(36) In the example of FIG. 3, the FPGA **40** may include transceiver circuitry **44** for driving signals off of the FPGA **40** and for receiving signals from other devices. The transceiver circuitry **44** may be part of the fabric die **22**, the base die **24**, or a separate die altogether. Interconnection resources **46** may be used to route signals, such as clock or data signals, through the FPGA **40**. The FPGA **40** of FIG. 3 is shown to be sectorized, meaning that programmable logic resources may be distributed through a number of discrete programmable logic sectors **48** (e.g., region, portion).

(37) Each programmable logic sector **48** may include a number of programmable logic elements **50** (also referred herein as FPGA fabric) having operations defined by configuration memory **52** (e.g., configuration random access memory (CRAM)). The programmable logic elements **50** may include combinatorial or sequential logic circuitry. For example, the programmable logic elements **50** may include look-up tables, registers, multiplexers, routing wires, and so forth. A designer may program the programmable logic elements **50** to perform a variety of desired functions. The programmable logic sector **48** may also include user memory **53**. User memory may be in the form of embedded random access memory (ERAM), and/or memory blocks, such as M20K. A power supply **54** may provide a source of voltage and current to a power distribution network (PDN) **56** that distributes electrical power to the various components of the FPGA **40**. Operating the circuitry of the FPGA **40** causes power to be drawn from the power distribution network **56**.

(38) There may be any suitable number of programmable logic sectors **48** on the FPGA **40**. Indeed,

while the illustrated system includes 29 programmable logic sectors **48** are shown here, it should be appreciated that more or fewer may appear in an actual implementation (e.g., in some cases, on the order of 50, 100, or 1000 sectors or more). Each programmable logic sector **48** may include a sector controller (SC) **58** that controls the operation of the programmable logic sector **48**. Each sector controller **58** may be in communication with a device controller (DC) **60**. Each sector controller **58** may accept commands and data from the device controller **60** and may read data from and write data into its configuration memory **52** or user memory **53** based on control signals from the device controller **60**. To that end and, as detailed below, the device controller may employ a data register (DR) and/or an address register (AR) to access data from the configuration memory **52** or user memory **53**.

(39) In addition to these operations, the sector controller **58** and/or device controller **60** may be augmented with additional capabilities. As described herein, a high-speed parallel interface may be used to coordinating memory transactions between local in-fabric memory (e.g., local fabric memory or CRAM being used for data storage) and sector-aligned memory associated with that particular programmable logic sector **48**. Moreover, a NOC may be used to facilitate memory transactions between multiple sectors, multiple dies, and between the programmable logic device and external systems, as discussed herein. NOC may further be employed for decrypting configuration data (bitstreams) **18**, and for locally sequencing reads and writes to implement error detection and correction on the configuration memory **52** or user memory **53**, and sequencing test control signals to effect various test modes.

(40) The sector controllers **58** and the device controller **60** may be implemented as state machines and/or processors. For example, each operation of the sector controllers **58** or the device controller **60** may be implemented as a separate routine in a memory containing a control program. This control program memory may be fixed in a read-only memory (ROM) or stored in a writable memory, such as random-access memory (RAM). The ROM may have a size larger than would be used to store only one copy of each routine. This may allow each routine to have multiple variants depending on “modes,” and the local controller may be placed into any of those modes. When the control program memory is implemented as random access memory (RAM), the RAM may be written with new routines to implement new operations and functionality into the programmable logic sectors **48**. This may provide usable extensibility in an efficient and easily understood way. This may be useful because new commands could bring about large amounts of local activity within the sector at the expense of only a small amount of communication between the device controller **60** and the sector controllers **58**.

(41) Sector controller **58** may include circuitry to manage the high-speed parallel interface (e.g., DR Intercept interface (DRIP)). The high-speed parallel interface may allow fast loading of DR circuitry, which may be used for configuration operations (e.g., CRAM operations), user memory operations (e.g., ERAM operations), and/or test (e.g., scan chains operations). For example, a high-speed interface controller (e.g., DRIP Controller), located in a fabric die, and a base die DRIP Controller, located in a base die, may be used to coordinate operations in the microbump interface, and may be part of the sector controller **58**. The DRIP controllers and the NOC circuitry may also coordinate operations to perform multi-sector high-speed data exchange between base die and fabric die. Each sector controller **58** thus may communicate with the device controller **60**, which may coordinate the operations of the sector controllers **58** and convey commands initiated from outside the FPGA **40**. To support this communication, the interconnection resources **46** may act as a network between the device controller **60** and each sector controller **58**. The interconnection resources may support a wide variety of signals between the device controller **60** and each sector controller **58**. In one example, these signals may be transmitted as communication packets.

(42) The FPGA **40** may be electrically programmed. With electrical programming arrangements, the programmable elements **50** may include one or more logic elements (wires, gates, registers, etc.). For example, during programming, configuration data is loaded into the configuration

memory 52 using pins to transceiver circuitry 44 and input/output circuitry 42. In one example, the configuration memory 52 may be implemented as configuration random-access-memory (CRAM) cells. The use of configuration memory 52 based on RAM technology is described herein is intended to be only one example. Moreover, configuration memory 52 may be distributed (e.g., as RAM cells) throughout the various programmable logic sectors 48 the FPGA 40. The configuration memory 52 may provide a corresponding static control output signal that controls the state of an associated programmable logic element 50 or programmable component of the interconnection resources 46. The output signals of the configuration memory 52 may be applied to configure the gates of metal-oxide-semiconductor (MOS) transistors that control the states of the programmable logic elements 50 or programmable components of the interconnection resources 46.

(43) As stated above, the logical arrangement of the FPGA 40 shown in FIG. 3 may result from a combination of the fabric die 22 and base die 24. The circuitry of the fabric die 22 and base die 24 may be divided in any suitable manner. In one example, shown in block diagram form in FIG. 4, the fabric die 22 contains primarily programmable logic fabric resources, such as the programmable logic elements 50, configuration memory 52, and user memory 53, and may be arranged in sectors such as sectors 65A and 65B. In some cases, this may also entail certain fabric control circuitry such as the sector controller (SC) 58 or device controller (DC) 60. The base die 24 may include supporting circuitry to operate the programmable logic elements 50, configuration memory 52, and user memory 53. As an example, the programmable logic elements 50 may exchange fabric data with the supporting circuitry in the base die 24 and configuration memory may exchange configuration data with the supporting circuitry in the base die 24. As shown here, the base die 24 includes support circuitry 70A, which may support fabric sector 65A, and support circuitry 70B, which may support fabric sector 65B. The base die 24 may also include support circuitry for other sectors of the fabric die 22.

(44) As discussed above, the multi-purpose interface may benefit from the presence of NOC circuitry in the base die (e.g., base die 24). The block diagrams in FIGS. 5, 6, 7, and 8 illustrate an example of a physical arrangement of the fabric die 22 and the base die 24 that may implement a NOC system. For example, a physical arrangement of the fabric die 22 and the base die 24 is shown by FIGS. 5 and 6. In FIG. 5, the fabric die 22 is shown to contain an array of fabric sectors 80 that include fabric resources 82 (e.g., programmable elements programmed by CRAM and/or certain fabric control circuitry such as the sector controller (SC) 58 or device controller (DC) 60) and interface circuitry 84. The interface circuitry 84 may include data routing and/or clocking resources or may include an interface to data routing and/or clocking resources on the base die 24. Thus, the interface circuitry 84 may connect with a microbump (μ bump) interface to connect to the base die 24.

(45) FIG. 6 provides an example complementary arrangement of the base die 24. The base die 24 may represent an active interposer with several sectors 90 surrounded by peripheral circuitry 28 and the silicon bridge interface 39. Although not shown in FIG. 6, each sector 90 may include a variety of fabric support circuitry, which may be described in greater detail below. In any case, the base die 24, in some embodiments, may include data and/or configuration routers 98, and/or data or configuration pathways 99. In some embodiments, portions of the data or configuration pathways 99 may communicate data in one direction, while other portions may communicate data in the opposite direction. In other embodiments, the data or configuration pathways 99 may communicate data bi-directionally.

(46) With the foregoing in mind, the data and/or configuration pathways 99 may make up a network on chip (NOC) system 100. In the embodiment depicted in FIG. 6, the NOC system 100 may be integrated between each sector 90 of the base die 24. As such, the NOC system 100 may enable each of the sectors 90 disposed on the base die 24 to be accessible to each other. Indeed, the NOC system 100 may provide communication paths between each sector 90 via routers 98 or the like. In certain embodiments, the routers 98 may route user data between sectors 90 of the base die

24, to sectors **48** of the fabric die **22**, and the like. Since the base die **24** is separate from the fabric die **22**, the NOC system **100** may be continuously powered on, even when various sectors **48** of the fabric die **22** are powered down. In this way, the NOC system **100** of the base die **24** may provide an available route to different sectors **48** of the fabric die **22** regardless of the positions of powered down sectors **48**.

(47) In some embodiments, the NOC system **100** may include features such as Quality of Service management, Security Management, Debug and Performance measurement and Address virtualization services, and the like. In addition, the NOC system **100** may support caching features and interconnect protocols allowing the memory components of the programmable logic device **12** to be part of a coherent memory system supported by a caching agent.

(48) By vertically aligning the fabric die **22** and the base die **24**, the NOC **100** disposed on the base die **24** may physically span across the same surface area of the fabric die **22**. In certain embodiments, microbumps may be positioned at various locations between the base die **24** and the fabric die **22** to enable the NOC **100** to communicate data between sectors **90** of the base die and sectors **48** of the fabric die **22**. In the example embodiment of the NOC **100** depicted in FIG. 6, the NOC **100** may be positioned around each sector **90**, which may be aligned with a corresponding sector **48** of the fabric die **22**. As such, the NOC **100** may provide additional horizontal and vertical routing wires or pathways to facilitate communication between sectors **48** of the fabric die **22**, between sectors **90** of the base die **24**, or between sectors **48** of the fabric die **22** and sectors **90** of the base die **24**. The additional horizontal and vertical lines provided by the NOC **100** may reduce the amount of quantization performed by the programmable logic device **12**.

(49) Although the data or configuration pathways **99** of the NOC **100** is illustrated in FIG. 6 as being routed around the sectors **90** of the base die **24**, it should be noted that data or configuration pathways **99** of the NOC **100** may be routed across the base die **24** in any suitable manner. By way of example, FIG. 7 illustrates the NOC **100** implemented with data or configuration pathways **99** disposed across the center of the sector **90**. As such, the router **98** may also be positioned in the center of the sector **90**.

(50) In addition, in some embodiments, the data or configuration pathways **99** of the NOC **100** may be wider in certain sectors **90** as compared to other sectors **90**. In any case, it should be understood that the data or configuration pathways **99** may be incorporated into the base die **24**, such that serve desired functions or operations that may be specific to the operations performed by the programmable logic device **12**. That is, if the programmable logic device **12** includes functions that involve regularly transferring data across the fabric die **22**, it may be beneficial to use more of the base die **24** space to include data or configuration pathways **99** that take up more space on the base die **24** to provide increased bandwidth.

(51) With the foregoing in mind, the NOC system **100** may include the data or configuration pathways **99** that allow for efficient multi-dimensional (e.g., three-dimensional, two-dimensional) integration of the NOC system **100** on the programmable logic device **12**. Indeed, the NOC system **100** may enable the fabric die **22** to connect to the peripheral circuitry **28** and other parts of the fabric without communicating via the fabric die **22** or the programmable logic sectors **48** of the fabric die **22**. That is, by employing the NOC system **100** in the base die **24**, the programmable logic device **12** may increase the available bandwidth for communication across the programmable logic sectors **48** because the NOC system **100** provides additional pathways to different parts of the programmable logic device **12**.

(52) In addition, the NOC **100** resolves shoreline issues, supports fast reconfiguration, and enables relocate-ability of functions in the programmable logic sectors **48** based on the increased bandwidth and accessibility to different portions of the fabric die **22** via the base die **24**. That is, as shown in FIG. 9, the NOC system **100** may be integrated with the sector-aligned memory **92** of the base die **24**, such that it spans across the entire base die **24**. As such, the NOC system **100** may access different fabric sectors **80** through various routes in the base die **24**. In addition, the

additional routes enable the NOC system **100** to serve as functional bypass around powered down sectors **80** without affecting the performance of the programmable logic device **12** by avoiding blockages across the programmable logic sectors **48** of the programmable logic device **12**. That is, in some situations, certain sectors **80** of the fabric die **22** may be powered down, thereby preventing communication across the powered down sectors **80**. In this case, the NOC system **100** may provide alternate communication pathways around the powered down sectors **80** to maintain communicative connectedness across the sectors **80** of the fabric die **22** regardless of whether certain sectors **80** are powered down.

(53) The design relocate-ability of the programmable logic sectors **48** is also enhanced by the NOC system **100** because the NOC system **100** may access different sectors **80** of the fabric die **22**. That is, the increased communication flexibility provided by the NOC system **100** being disposed in the base die **24** enables the programmable logic sectors **48** to be repositioned in various sectors **80** of the fabric die **22**, while maintaining communication capabilities between the relocated programmable logic sectors **48**.

(54) Although FIGS. **6** and **7** illustrate two embodiments with different configurations for the NOC **100**, it should be noted that the base die **24** may be configured to include a data or configuration pathways **99** in a variety of shapes, forms, positions, and the like. For example, the data or configuration pathways **99** of different sectors **90** may overlap each other, the entire sector **90** may incorporate the data or configuration pathway **99**, or the like. In addition, microbumps may be used to facilitate communication between the NOC **100** and various sectors **80** of the fabric die **22** and the like.

(55) In addition to facilitating communication of data between sectors **90**, sectors **80**, and the like, the presence of the NOC **100** in the base die **24** may also provide the programmable logic device **12** to incorporate additional circuit features by leveraging the NOC **100** of the base die **24** to improve the communication across the fabric die **22**. By way of example, FIG. **8** provides another embodiment of an arrangement of the base die **24**. Similar to the base die **24** described above, the base die **24** of FIG. **8** may represent an active interposer with several sectors **90** surrounded by peripheral circuitry **28** and the silicon bridge interface **39**. As shown in FIG. **8**, each sector **90** may include a variety of fabric support circuitry, such as sector-aligned memory **92**, memory control circuitry **93**, non-user input control circuitry **94**, non-user output control circuitry **95**, a voltage regulator such as a fully integrated voltage regulator (FIVR) **96**, one or more thermal sensors **97**, data and configuration routers **98**, and/or data or configuration pathways **99**.

(56) Although the following description of the additional circuit features enabled by the NOC **100** embedded in the base die **24** focuses on the ability to transfer data to and from the sector-aligned memory **92**, it should be noted that the additional circuit features are not limited to technologies involving the sector-aligned memory **92**. Indeed, the NOC **100** embedded in the base die **24** may enable a variety of circuit operations to be performed more efficiently and effectively via the programmable logic device **12**. However, for the purposes of discussion, certain operations that involve the sector-aligned memory **92** and the NOC **100** will be described to illustrate some of the functions enabled by incorporating the NOC **100** into the base die **24**.

(57) Referring back to FIG. **8**, the memory control circuitry **93** may be used to program the sector-aligned memory **92**, the CRAM of the fabric die **22**, or both. The non-user input control circuitry **94** and non-user output control circuitry **95** may allow the circuitry of the sectors **90** to exchange data and/or control signals (e.g., via configurable data routing network-on-chip (NOC) or a configuration network on chip (CNOC)). In one example, the non-user input control circuitry **94** and non-user output control circuitry **95** may operate as the sector controller (SC) **58** for a corresponding fabric sector **80** (as shown in FIG. **5**).

(58) The FIVR **96** and the one or more thermal sensors **97** may be used to provide a desired voltage to the corresponding fabric sector **80** (as shown in FIG. **5**), enabling the voltage to be selectively scaled up or down, or removed, depending on power and thermal specifications (e.g., based at least

in part on temperature as measured by a thermal sensor **97** and/or in accordance with a dynamic voltage and frequency scaling (DVFS) scheme). Even though the thermal sensors **97** are in a separate die from that of the programmable logic fabric elements, when the base die **24** is directly adjacent to the fabric die **22** as in this example, the temperature measured by the thermal sensor **97** in the base die **24** may correspond well enough to the fabric die **22** to allow for temperature-based operations (e.g., turn off power to the corresponding fabric sector **80** to prevent a permanent-denial-of-service (PDOS) condition).

(59) In certain embodiments, the data or configuration pathways **99** that make up the NOC system **100** may provide communication paths between each sector **90** via routers **98** mentioned above. As shown in FIG. **9**, by vertically aligning the fabric die **22** and the base die **24** and incorporating the NOC **100** in the base die **24**, memory located in the base die **24** may be accessible in parallel to fabric sectors **80** of the fabric die **22**. FIG. **9** shows an example in which sector-aligned memory **92** may be contained in the base die **24**. The sector-aligned memory **92** may be directly accessible to respective fabric sectors **80** of the fabric die **22** and may contain user data (generated by or accessible by a circuit design programmed into the programmable logic fabric of the base die **24**) or configuration data that may be used to program the programmable logic fabric of the base die **24**. In this disclosure, “directly accessible” refers to a connection between a region of the sector-aligned memory **92** that is associated with a particular fabric sector **80** and that particular fabric sector **80**. In some embodiments, each respective region of the sector-aligned memory **92** associated with a particular fabric sector **80** may be directly accessible to that particular fabric sector **80**, thereby providing each fabric sector **80** with direct access to that region of the sector-aligned memory **92**. For example, there may be N regions of sector-aligned memory **92** that can be accessible by N corresponding fabric sectors **80** at the same time (e.g., in parallel). In some cases, the sector-aligned memory **92** may be accessible to more than one fabric sector **80** or multiple sectors of sector-aligned memory **92** may be accessible to a single fabric sector **80**. Thus, in some cases, the same region of sector-aligned memory **92** may be directly accessible to multiple fabric sectors **80**, while in other cases, a region of sector-aligned memory **92** may be directly accessible only to a single fabric sector **80**. In the example of FIG. **9**, the fabric sectors **80** may access specific regions of sector-aligned memory **92**. The sector-aligned memory **92** is shown in FIG. **9** as vertically stacked memory. This may allow a large amount of memory to be located within the base die **24**. However, the sector-aligned memory **92** may occupy a single plane of the base die **24** in some embodiments.

(60) It should be noted that the fabric sectors **80** may initiate a transfer of data directly between memory locations of the sector-aligned memory **92** of the base die **24** using the NOC **100**, between different fabric sectors **80** of the fabric die **22**, between fabric sectors **80** and memory locations of the sector-aligned memory **92**, and the like. In certain embodiments, the sector controller (SC) **58** may initiate the transfer of data between sectors **80** of the fabric die **22**, between memory locations of the sector-aligned memory **92**, between sectors **80** of the fabric die **22** and memory locations of the sector-aligned memory **92**, and the like. That is, the sector controller (SC) **58** may coordinate the operation of the NOC **100** to facilitate the transfer of the data between the source and destination targets, as specified by the section controller (SC) **58**. In some embodiments, the section controller (SC) **58** may act as a master to initiate the respective transfer and the transfer would then be performed using the NOC **100** after the section controller (SC) **58** initiates the data transfer process.

(61) By way of example, FIG. **10** includes a block diagram of illustrating the transfer of data between sectors **80** of the programmable logic fabric via the NOC circuitry **100** of the base die **24**. Referring to FIG. **10**, in one embodiment, the sector controller (SC) **58** may initiate a transfer of data from sector “A” to sector “B” of the fabric die **22** using the NOC **100** of the base die **24**. That is, the sector controller (SC) **58** may transfer data to a region of the sector-aligned memory **92** aligned with sector “A” of the fabric die **22**, use the NOC **100** to transfer the data to a second

region of the sector-aligned memory **92** aligned with sector “B” of the fabric die **22**, and transfer the data from the second region of the sector-aligned memory **92** to sector “B” of the fabric die **22**. Although the route of the data transfer illustrated in FIG. **10** corresponds to straight paths, it should be noted that the data transferred to different sectors **80** of the fabric die **22** or regions of the sector-aligned memory **92** may use a variety of directions and routes.

(62) In another example, FIG. **11** includes a block diagram illustrating the transfer of data from a sector **80** of the programmable logic fabric to a region of the sector-aligned memory **92** via the NOC circuitry **100** of the base die **24**. Referring to FIG. **11**, in one embodiment, the sector controller (SC) **58** may initiate a transfer of data from sector “A” of the fabric die **22** to region “C” of the sector-aligned memory **92** using the NOC **100** of the base die **24**. That is, the sector controller (SC) **58** may transfer data to a first region of the sector-aligned memory **92** aligned with sector “A” of the fabric die **22** and use the NOC **100** to transfer the data to region “C” of the sector-aligned memory **92** via different regions of the sector-aligned memory **92** or the like. Like FIG. **10**, although the route of the data transfer illustrated in FIG. **11** corresponds to straight paths, it should be noted that the data transferred to different regions of the sector-aligned memory **92** may use a variety of directions and routes. It should be noted that other suitable circuits may also be employed to transfer the data in accordance with the embodiments presented herein.

(63) As shown in FIGS. **10** and **11**, the sector controller (SC) **58** may initiate a transfer of data directly between memory locations within the base die **24** using the NOC system **100**. In this case, the sector controller (SC) **58** may act as the master to initiate the transfer, but then the transfers would be performed directly in the sector-aligned memory **92** and the NOC system **100** of the base die **24** after the sector controller (SC) **58** initiates the transfer. It should also be mentioned that, in some embodiments, that the sector controller (SC) **58** and similar components of the fabric die **22** may also initiate the components (e.g., memory control circuitry **93**, non-user input control circuitry **94**, non-user output control circuitry **95**) of the base die **24** to perform transfers between the sector-aligned memory **92**, the peripheral circuitry **28**, and other components attached to the base die. As a result, data transfers may occur in the base die **24** without involvement of components in the fabric die **22**.

(64) In certain embodiments, the NOC system **100** may also enable the programmable logic device **12** to provide security isolation for one or more of the programmable logic sectors **48**. That is, the NOC system **100** may be employed to communicate certain sensitive or secure data to a portion of programmable logic sectors **48** that may be designated as a security portion of the programmable logic device **12**. Third party programmers may be unable to access the security portion of the programmable logic device **12** without access to the NOC system **100**. Instead, the NOC system **100** may be limited to communication by certain programmers with a level of security credentials.

(65) With this in mind, FIG. **12** illustrates one embodiment in which a base die **24** may exchange data with the fabric die **22** via a high-speed parallel interface (e.g., microbump interface **102**). The microbump interface **102** may couple the base die **24** and/or the fabric die in a sector-to sector level. For example, a sector **80** in the fabric die **22** may be coupled to a corresponding sector **90** in the base die. The sector **80** of the fabric device may include a sector controller **58**, a fabric memory **130**, which may be a configuration memory (CRAM) which may include configuration memory **52** and/or user memory **53**. Sector **80** may also include FPGA fabric **132**, which may include programmable logic elements **50**. In some embodiments, read and/or write access to the memory may be performed with the assistance of an address register (AR) **134** and/or a data register (DR **136**). The AR **134** and the DR **136** may be used to load data into the fabric memory **130** and/or retrieving data from the fabric memory **130**. In some embodiments, the exchange between the fabric memory **130** and the microbump interface **102** may employ the DR **136**.

(66) The microbump interface **102** may occupy a row or column of a fabric sector **80** and a portion of base die sector **90**. The microbump interface **102** may include interface circuitry in the fabric die **22** (e.g., FMIB **103A**) and in the base die **24** (e.g., BMIB **103B**). The FMIB **103A** and the BMIB

103B may be connected via a high-speed microbump interconnect. The **FMIB 103A** may include a data exchange block **FMIB DATA 106** and a control block **FMIB CTRL 116**. The **BMIB 103B** may include a data exchange block **BMIB 108** and a control block **BMIB CTRL 118**. As detailed below, control and command for data operations may be exchanged between control blocks **FMIB CTRL 116** and **BMIB CTRL 118**, and data transfer for the respective commands may be exchanged between data exchange block **FMIB 106** and **BMIB 108**.

(67) The microbump interface **102** may receive or transmit data via a datapath **104**, that may be established between a data exchange block **FMIB DATA 106** of the **FMIB 103A** and a data exchange block **BMIB DATA 108** of the **BMIB 103B**. The data exchange blocks **FMIB 103A** and **BMIB 103B** may be coupled through multiple channels, and may be coupled to each other via a microbump interconnect, as discussed herein. In some embodiments, the datapath **104** may be grouped into source synchronous channels (e.g., data is transmitted with clock signal) with individually centered clocks to maximize micro-bump bandwidth. The interface clocking may be used to facilitate communications and data transfer may be clocked using a single data rate (SDR) clocking, a double data rate (DDR) clocking, a quad data rate (QDR) clocking, or a xY interface clocking. The microbump clocking may be x2, x4 or xY faster with narrower data width (/2, /4 or /Y) compared to the internal wider data buses. Based on microbump design requirements, the microbump clock may be single ended or differential clocking. Data microbumps in the datapath **104** may employ unidirectional RX and/or TX channels or common bi-directional channels.

(68) The microbump interface **102** may also exchange control and/or data signals through a control interfaces **114A**, **114B**, and **114C**. The control interfaces may be established between control block **FMIB CTRL 116** of the **FMIB 103A** and a control block **BMIB CTRL 118** of the **BMIB 103B**. The control interfaces **114A**, **114B**, and **114C** may be used to coordinate operations between the **DRIP controller 122** in the fabric die **22** and the **DRIP controller 124** in the base die **24**. The control interfaces **114A**, **114B**, and **114C** may coordinate operations to facilitate exchanges of data between the fabric memory **130**, the sector-aligned memory **92** of the base die **24**, and/or the **NOC system 100** via the **NOC router 98**. Moreover, it should be noted that remote requests to the microbump interface **102** may arrive via the **NOC system 100** in the base die, as detailed below. Moreover, as discussed above, the base die **24** may have additional resources, including vector engines, compute-in-memory, and other circuitry that may generate and/or receive data, and the microbump interface **102** may be used to exchange data between such circuitry and the fabric memory **130**. As with the datapath **104**, control interfaces **114A**, **114B**, and **114C** may be source synchronous channels with individually centered clocks to maximize micro-bump bandwidth. The interface clocking may be clocked using a single data rate (SDR) clocking, a double data rate (DDR) clocking, a quad data rate (QDR) clocking, or a xY interface clocking. Based on microbump design requirements, the microbump clock may be single ended or differential clocking. Control microbumps for control interfaces **114A**, **114B**, and **114C** may be unidirectional or bi-directional, as detailed below.

(69) As discussed above, the **DRIP controllers 122** and **124** may be implemented using a state machine that may be triggered by events. Events of the state machine may be associated with signals exchanged in the control interfaces **114A-C**. The Table 1 illustrates examples of signals that may be used to perform commands and/or functions using the microbump interface **102**. It should be understood that the this Table 1 is a non-limiting illustrative example of certain features in an embodiment of the microbump interface **102**, and that variations and/or extensions to this example are contemplated by this disclosure. Data microbumps for control interfaces **114A-C** may employ unidirectional RX and/or TX channels or common bi-directional channels. In some embodiments, the control interface may operate in an asynchronous manner.

(70) TABLE-US-00001 TABLE 1 Example of control protocol used to operate microbump interface 102

Interface Description	Control	Control interface 114A
Control interface 114A may be used to communicate with interface handshake protocols between the DRIP controller 122 and 114A the DRIP controller 124. DRIP controller 122 may indicate the sector 80 is ready for DRIP interface operations with a		

“Ready” signal. DRIP controller 124 may indicate completion status for DRIP interfaces with a “Status” signal. The “Status” signal may include additional coding and, as such, control interface 114A may be implemented using a single or multi-bit bus. Control Command from DRIP controller 122 to controller 124. May interface be used to request a configuration operation to controller 114B 124. This may be a memory-mapped interface over micro-bumps to push a command to a queue or first-in first-out (FIFO) buffer on the base die 24. A direct command interface may also be used. Control Command from DRIP controller 124 to DRIP controller 122. interface The command may be a remote command from another sector 114C 80 for a write or read operation. The remote command interface may be used to push a remote DRIP interface command coming via a NOC interface. This may be a memory-mapped interface over micro-bumps to push a command to a queue from the base die 24 to the fabric die 22. A direct command interface may be used.

(71) The DRIP controller **122** in the fabric die may operate in coordination with the sector controller **58**. To that end, DRIP controller **122** may receive instructions from sector controller **58** and/or control the circuitry in the fabric sector **80**, and provide instructions to the AR **134** and the DR **136**. For example, DRIP controller **122** may receive commands from the sector controller **58** that may be associated with management of the microbump interface **102**. In such situation, DRIP controller **122** may generate signals for the appropriate control interfaces **114A-C**. As discussed above, the microbump interface **102** may also receive commands from remote circuitry (e.g., circuitry in other sectors or in a different die) via the NOC system **100**. In such situation, the DRIP controllers **122** and **124** may arbitrate the remote requests and the sector control requests.

(72) In some situations, the sector controller **58** may provide a legacy command that does not account for operations using the microbump DRIP interface **105A**. In such situations, the DRIP controller **122** may generate commands (e.g., override commands) that control the AR **134** and the DR **136** based on operations that employ the DRIP interface **105A**. For example, a sector controller **58** may request loading of configuration data to the fabric memory **130** from data coming from a legacy interface. In such situation, the DRIP controller **122** may, in coordination with the DRIP controller **124**, pull the data from the legacy interface and store in the sector-aligned memory **92** for caching purposes, and load the configuration data to the fabric memory **130** via the microbump interface **102** through the DRIP interface **105A**. The sector-aligned memory may be controlled by a base memory controller.

(73) As discussed above, the microbump interface **102** may implement multiple channels to allow data transference between a base die **22** and a base die **24**. FIGS. **13** and **14** illustrate the interfaces that may be used to perform the data exchange, including coordination for transport of configuration data and/or fabric data. The sector controller **58** may assign any channel of the microbump interface **102** to transport configuration data and/or fabric data. FIG. **13** illustrates an implementation for the interface block FMIB DATA **106** that may have multiple channels **150A**, **150B**, and **150C**, and FIG. **14** illustrates an implementation for the interface block BMIB DATA **108** that may connect to the multiple channels **150A**, **150B**, and **150C**. The channels **150A**, **150B**, and **150C** may be coupled through datapath **104**. The datapath **104** may have a first set of data signals **156** (e.g., microbump data signals) which may be unidirectional links from FMIB DATA **106** to BMIB DATA **108**, and a second set of data signals **158**, which may be unidirectional links from BMIB DATA **108** to FMIB DATA **106**. Accordingly, the datapath **104** may be in half-duplex mode (e.g., bi-directional) when bound to the channels. In some embodiments, all the channels may use a common number of data bits (e.g., the number of data signals **156** and data signals **158** may be the same for all channels). It should be noted that, while the number of data bits used may be common, each channel may employ a different data transfer rate by employing bitslicing and/or managing clocking signals, as detailed below.

(74) The FMIB DATA **106** illustrated in FIG. **13** may implement channels **150A**, **150B**, and **150C**. Each channel may be accessed by the DRIP interface **105A** via DRIP block **155A**, and the fabric data interface **105B** via fabric data block **155B**. Each channel **150A-C** may employ microbump I/O

transmit buffers **164**, which may be coupled to outgoing data lines **160** and outgoing clock lines **161** of the set of data signals **156**. Access to the outgoing data lines **160** may be controlled by a multiplexer **168** and access to the outgoing clock lines **161** may be controlled by a multiplexer **170**. The local sector controller **58** may control the multiplexers **168** and/or **170**. Each channel **150A-C** may employ microbump I/O receive buffers **166** that may be coupled to incoming data lines **162** and incoming clock lines **163**

(75) The DRIP block **155A** may include a receive block **172** and a transmit block **174**. The receive block **172** may receive data from the incoming data lines **162** and a clock signal from the clock line **163**. The receive block **172** may have one or more RX bitslice blocks **173**, that may be used to convert signal from the narrower (e.g., $/1$, $/2$, $/4$, $/Y$) width of the high-speed microbump channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**) to the wider width of the relatively slower speed internal DRIP interface **105A**. For example, the signals of the channel **150A** in the microbump interface **102** may be operating using a 32 bits bus at 1 GHz and the DRIP interface **105A** may employ an internal bus that operates using 128 bits at 250 MHz to provide a common data rate. The RX bitslice blocks **173** may be used to perform buffering and/or queueing associated with the bandwidth matching operation. More generally, the RX bitslice blocks **173** may convert data in a width of the internal data bus (e.g., data bus of the DRIP interface **105A**) to the width of the datapath **104** by choosing a clock frequency division and buffering that may balance the data bandwidth. In some embodiments, each receive block **172** may have pairs of RX bitslice blocks **173** (e.g., 2, 4, 6 RX bitslice blocks) that may be used to accelerate the receiving process.

(76) Similarly, the transmit block **174** of the DRIP block **155A** may send data to outgoing data lines **160** and a clock signal to clock line **161**. The transmit block **174** may have one more TX bitslice blocks **175**, that may be used to convert the signal from wider data width of the DRIP interface **105A** to the narrower data width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**), as discussed above. The TX bitslice blocks **175** may be used to perform buffering and/or queueing associated with the bandwidth matching operation. More generally, the TX bitslice blocks **175** may convert data widths by choosing a frequency divider and/or multiplier and buffering that may balance the outgoing data rate. In some embodiments, each receive block **174** may have pairs of TX bitslice blocks **175** (e.g., 2, 4, 6 RX bitslice blocks) that may be used to accelerate the transmit process.

(77) The fabric data block **155B** may include a receive block **178** and a transmit block **180**. The receive block **172** may receive data from the incoming data signals **162** and a clock signal from the clock line **163**. The receive block **178** may have one more RX bitslice blocks **179**, that may be used to convert signal from the narrower (e.g., $/1$, $/2$, $/4$, $/Y$) width of the high-speed channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**) to the wider width of the internal fabric data interface **105B**, as discussed above. Similarly, the transmit block **180** of the fabric data block **155B** may send data to outgoing data lines **160** and a clock signal to clock line **161**. The transmit block **180** may have one more TX bitslice blocks **181**, that may be used to convert the signal from wider data width of the fabric data interface **105B** to the narrower data width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**), as discussed above.

(78) The RX bitslice blocks **179** and the TX bitslice blocks **181** may be used to perform buffering and/or queueing associated with the bandwidth matching operation. For example, the signals of the channel **150A** in the microbump interface **102** may be operating using a 32 bits bus at 1 GHz and the fabric data interface **105B** may employ an internal bus that operates using 256 bits at 125 MHz to provide a common data rate. The bitslice circuitry may providing clocking a buffering functionality to accommodate the differences in the widths. More generally, the RX bitslice blocks **179** and the TX bitslice blocks **181** may convert between data widths by choosing a clock frequency division and buffering that may balance the incoming and/or outgoing data rate. In some embodiments, bitslice blocks (e.g., RX bitslice blocks **179**, TX bitslice blocks **181**) may be

arranged in pairs to accelerate the transmit process or the receive process.

(79) The BMIB DATA **108** in the base die **24** may be configured using an architecture that may be similar in certain aspects to the FMIB DATA **106**. The BMIB DATA **108** illustrated in FIG. **14** may implement channels **150A**, **150B**, and **150C**, which may be accessed by circuitry in the base die **24**, such as the DRIP controller **124**, memory controller **91**, or NOC router **98**. The choice of the circuitry in the base die **24** associated with each channel **150A-C** may be made based on the function being performed using the specific channel. As discussed above, a channel **150A-C** may be assigned to the DRIP interface **105A**, in which case BMIB DATA **108** may employ DRIP block **205A**. A channel **150A-C** may be assigned to the fabric data interface **105B**, in which case BMIB DATA **108** may employ fabric data block **205B**. Each channel **150A-C** may employ microbump I/O receive buffers **214**, which may be coupled to incoming data lines **160** and incoming clock lines **161** of the set of data signals **156**. Each channel **150A-C** may employ microbump I/O transmit buffers **216** that may be coupled to outgoing data lines **162** and outgoing clock lines **163**. Access to the outgoing data lines **162** may be controlled by a multiplexer **218** and access to the outgoing clock lines **161** may be controlled by a multiplexer **220**. The local sector controller **58** may control the multiplexers **218** and/or **220**.

(80) The DRIP block **205A** may include a receive block **222** and a transmit block **224**. The receive block **222** may receive data from the incoming data lines **160** and a clock signal from the clock line **160**. The receive block **222** may have one or more RX bitslice blocks **223**, that may be used to convert signal from the narrower width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**) to the wider width of the base die circuitry (e.g., width of the DRIP controller **124**, memory controller **91**, NOC router **98**). Similarly, the transmit block **224** of the DRIP block **205A** may send data to outgoing outlines **162** and a clock signal to clock line **162**. The transmit block **224** may have one more TX bitslice blocks **225**, that may be used to convert the signal from data width of the base die circuitry to the data width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**), as discussed above. More generally, the RX bitslice blocks **223** and the TX bitslice blocks **225** may be used to perform buffering and/or queueing associated with the bandwidth matching operation, by performing a clock frequency adjustment and buffering that may balance the data rate through BMIB DATA **108**.

(81) Similarly, the fabric data block **205B** may include a receive block **228** and a transmit block **230**. The receive block **228** may receive data from the incoming data lines **160** and a clock signal from the clock line **161**. The receive block **228** may have one more RX bitslice blocks **229**, that may be used to convert signal from the width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**) to the width the base die circuitry, as discussed above. Similarly, the transmit block **230** of the fabric data block **225B** may send data to outgoing outlines **162** and a clock signal to clock line **163**. The transmit block **230** may have one more TX bitslice blocks **231**, that may be used to convert the signal from data width of the base die circuitry to the data width of the channel (e.g., width of the portion of the datapath **104** bound to the channel **150A-C**). As discussed with respect to other bitslice circuitry, the RX bitslice blocks **229** and the TX bitslice blocks **231** may be used to perform buffering and/or queueing associated with the bandwidth matching operation. Moreover, as discussed above, the bitslice blocks (e.g., RX bitslice blocks **223** and **229**, TX bitslice blocks **225** and **231**) may be arranged in pairs to provide local pipelining and accelerate the transmit process.

(82) Each channel **150A-C** may be assigned to the DRIP interface **105A** or the fabric data interface **105B** by programming of the multiplexers **168**, **170**, **218**, and/or **220**. The programming of the multiplexers may be used to control access of the transmit blocks (e.g., **174**, **180**, **224**, **230**) to the data lines. The receive blocks (e.g., receive blocks **172**, **178**, **222**, **228**) may receive fanned-out data from the buffers (e.g., buffers **166**, **214**), and may be enabled based on the selected assignment. In some embodiments, this assignment may be pre-programmed (e.g., static, not accessible in user mode) or reconfigurable (e.g., accessible in user mode). In some embodiments, the assignment may

be made prior to operation (e.g., configured using configuration data) or adjustable in runtime. For example, a channel **150A-C** may be assigned to the DRIP interface **105A** during a reprogramming period and, following the reprogramming task, re-assigned to the fabric data interface **105B** in non-user mode. In another example, a channel **150A-C** may be initially assigned to the fabric data interface **105B**, re-assigned, in user mode, to the DRIP interface **105A** to allow a transfer of data between the base die **24** and user memory (e.g., ERAM, M20K), and returned to the fabric data interface **105B** for further processing.

(83) In some embodiments, the bitslice blocks may be shared by the DRIP interface **105A** or the data interface **105B**. For example, in some embodiments, a single block, similar to DRIP block **155A** or fabric data block **155B**, and having a receive block (e.g., receive block **172** or receive block **178**) and a transmit block (e.g., transmit block **174** or transmit block **180**), may be accessed by both the DRIP interface **105A** and the data interface **105B**. In such system, a multiplexer may be used to manage the block assignment. The flexible distribution of bitslice blocks may allow optimization of the interface in view of the physical floorplan, the number of wires, and/or the logical protocols in the application.

(84) The clock lines (e.g., clock lines **161** and **163**) may provide clock signals that may be centered with the data bits of the data signals in the data lines (e.g., data lines **160** and **162**). That is, a triggering feature (e.g., an edge) of the clock signal may be aligned with a center of the data. Careful balancing of the clock signals and data bits may decrease the bit-to-bit skew of the source synchronous transmit or receive data buses of the channel. Such implementation may decrease the bit-to-bit skew between multiple data lines. The clock signals may be single ended or differential. Moreover, as the clock lines are multiplexed and, thus, independent, different channels **150A-C** may operate at different data rates using different clock frequencies and/or modes (e.g., single data rate (SDR), double data rate (DDR), or quad data rate (QDR)). Circuitry in different channels (e.g., multiplexers, bitslicing blocks, and buffers) may be shared by the different channels **150A-C**. Similarly, a single channel may be accessed by more than one interface and each interface may have a bitslicing block configured to different data rates. As an example, a physical channel may be shared by a configuration data interface (e.g., DRIP interface **105A**) and a fabric data interface (e.g., fabric data interface **105B**) operating at different data rates.

(85) With the foregoing in mind, FIG. **15** illustrates a method **250** to exchange data employing the multi-purpose interface (e.g., microbump interface **102**) discussed herein. In process block **252**, a channel may be selected. The channel may be selected from available channels. In process block **254**, the channel may be assigned to an interface. The interface may be a configuration data interface (e.g., DRIP interface **105A**) or a fabric data interface (e.g., fabric data interface **105B**). Assignment of the interface may include enabling and/or disabling of logic blocks associated with the interfaces and/or programming of multiplexers, as discussed above. In some embodiments, the multiplexers may be programmed by the local sector controller (e.g., sector controller **58**). In process block **256**, bitslice circuitry may be programmed. It should be noted that process blocks **254** and **256** may be executed at the same time. As discussed above, the bitslice blocks may be adjusted based on the data rate of the data path and a width of the internal bus. In a process block **258**, data exchange may be initiated using the selected channel.

(86) In order to perform fully synchronous read/write operations between circuitry in the fabric die **22** and the base die **24**, a clocking mechanism that may allow for synchronous round-trip timing may be used. The clocking mechanism may perform retiming in the base die **24** based on the incoming clock signals. An example of an embodiment of retiming circuitry **370** that may be used is illustrated in FIG. **16**. FIG. **16** illustrates communication between a FMIB DATA **106** and a BMIB DATA **108** using channel **150A**. In the illustrated example, the channel **150A** may be assigned to the fabric data interface **105B**, and therefore fabric data blocks **155B** and **205B** may be active while DRIP blocks **155A** and **205A** may be disabled. Retiming circuitry **370** may include a local delay locked loop (DLL) **372** and a remote delay line **374**. The retiming circuitry **370** may be

used to generate a local clock **376** that may be used to clock the source synchronous data received in the base die. Moreover, the retiming circuitry **370** may be used to generate a programmable delay to the clock to align the return data to the fabric die clock using the TX data retiming block **378**. As a result, the retiming circuitry **370** may be used to generate synchronous bi-directional operations between the fabric die **22** and base die **24**.

(87) In this source synchronous bi-directional operation, outgoing data signal **383**, clocked to clock signal **382**, may be synchronous to incoming data **391**, which is represented as clocked to a virtual clock signal **390**. To that end, the DLL **372** may phase align the local clock **376** to the received clock **384**. The local clock **376** may then synchronously sample the incoming RX bitslice data **387**. The local clock **376** may be used to clock the base die fabric logic. As the local clock **376** is trained by the clock signal **384**, the base die fabric logic may synchronously sample the input (e.g., in a source synchronous manner). Moreover, the remote delay line **374** may be programmed based on the clock signal **384** of the incoming data to time the operations of the TX bitslice of the fabric data block **205B**. The retiming of the clock signal may be used to emulate the latency in the return communication (e.g., from base die **24** to fabric die **22**). In some embodiments, the use of retiming circuitry **370** may allow the clock line **163** to be inactivated, as the outgoing and incoming data may be effectively synchronized.

(88) The time chart **400** of FIG. **17** illustrates the retiming operation performed by retiming circuitry **370**. Curves in FIG. **17** may refer to signals indicated in FIG. **16**. It should be noted that clock signal **390** may refer to implicit clocks. That is, while no clock signal associated with clock signal **390** may be generated, data signal **391** may be synchronized to it. Clock signal **382** and data signal **383** may be provided by the fabric data interface **105B** to the base die circuitry. Due to latencies in the datapath **104**, the base die may receive a clock signal **384**. The clock signal **384** may be used by the DLL **372** to generate a local clock signal **386** that may be locked to the fabric clock. In some embodiments, the DLL **372** may perform phase locking between the local clock **386** and the received clock **384**.

(89) The local clock signal **386** may be used to perform local clocking of the source synchronous received data. The clock signal **384** may also be used by the delay line **374** to determine a delay **402** that may be incorporated to the return data to and generate return data synchronization, as discussed above. The delay **402** may be calculated using the line latency **404**. As such, the remote delay line **374** may incorporate the delay **402** to the clock signal **384** to generate the delayed clock signal **388**. The TX data retiming block **378** may use the delayed clock to launch the TX return data. Due to the line latency **404**, the returned data **391**, implicitly synchronized to clock signal **390**, may be aligned with the clock signal **382** at the fabric data interface **105B**.

(90) With the foregoing in mind, FIG. **18** illustrates a method **410** for performing retiming based on a remote signal. In a process block **412**, a data signal, clocked to a clock signal, may be received. In some embodiments, the clock signal may be a recovered clock signal from the data signal. In process blocks **414** and **416**, the timing circuitry may program a delay line such that the return data to the fabric die becomes synchronous (e.g., remote training of the base die). To that end, in process block **414** the base die may program the delay line by incrementally increasing or decreasing the delay.

(91) The delay element may be used to compensate for latencies in the data line and/or latencies in the transmission path and minimize the skew between outgoing data and incoming data in the fabric die. In process block **416**, the phase synchronization may be verified. If the return data is not sampled correctly, the method **410** may return to the process block **414** to further adjust the delay line to continue the training process until the a valid data window is achieved. If necessary a sweep of delays values in the delay line may be employed to identify the center of the valid data window. The training process of the delay element to minimize the skew may be performed by a local sector controller. Once the training is done, by verifying a phase lock in process block **416**, return data may be generated and synchronized to a clock generated from the delayed clock in process block

418. Accordingly, the data may be transmitted back to the sender of the remote data signal and may arrive at the sender synchronized with the transmitted data. It should be noted that in some embodiments, the circuitry **370** may have components in the fabric die **22** to facilitate training the return microbump channels.

(92) The fabric data interface **105B** may allow multiple protocols to access the microbump interface **102**, in a manner that employs different protocols simultaneously for different operations. To that end, the fabric data interface **105B** may implement multiple protocol blocks. Protocol blocks may be implemented as hardened circuitry, custom circuitry, or soft IP blocks. The block diagram of FIG. **19** illustrates an example of a configuration of the microbump interface **102** that may be used to provide shared access of the microbump interface **102** to a DRIP interface **105A** and to a fabric data interface **105B** implementing multiple protocol blocks. FIG. **19** illustrates the FMIB DATA **106** coupled to the DRIP interface **105A** and the fabric data interface **105B**. The DRIP interface **105A** may interact with the fabric memory **130** through the DR **136**, as illustrated. The fabric data interface **105B** may interact with the FPGA fabric **132**. In the diagram, the fabric data interface **105B** may include one or more fabric protocols that may intermediate the communication with multiple channels through protocols blocks **450**, **452**, **454**, and **456**.

(93) The block diagram of FIG. **19**, the FMIB DATA **106** is illustrated as having N channels **150A**, **150B**, **150C**, **150D**, and **150E**. In the illustrated block diagram, only channels **150A** and **150B** are illustrated as having a DRIP bitslices block **155A** and a fabric bitslices block **155B**. It should be noted that all channels **150A-E** may have a corresponding DRIP bitslices block **155A** and fabric bitslices block **155B** and, thus, may be accessible to the DRIP interface **105A** and the fabric data interface **105B**. As an example, the channels **150A** and **150B** may be shared by the DRIP interface **105A** and the protocol block **450** in the fabric data interface **105B**. Sharing may take place by enabling and disabling the DRIP block **155A** and/or the fabric data block **155B**, as discussed above. For example, when a programmable logic device is performing configuration operations (e.g., initial configuration, partial reconfiguration), channels **150A** and **150B** may be assigned to the DRIP interface **105A**. When the programmable logic device is performing user mode operations, channels **150A** and **150B** may be assigned to the protocol block **450**. In the illustrated example, protocol block **450** may implement a memory mapped protocol, which may have asynchronous components (e.g., block **456A** and **456B**) and/or synchronous components (e.g., block **458**).

(94) Protocol blocks of the fabric data interface **105B** may also allow flow of different types of data (e.g., different protocols). For example, protocol block **452** may be a shared protocol block that provides access between the FPGA fabric **132** and the microbump interface **102** using a NOC block **460** and a streaming block **462**. The protocol block **452** may provide shared access of blocks **460** and **462** to channel **150C**. The diagram of FIG. **19** also illustrates a debug and trace protocol block **454** that may access channel **150D** and a fabric test protocol block **456**, that may access channel **150E**. Generally, the protocols implemented in the fabric data interface **105B** may be synchronous and/or asynchronous, and the data may be processed using a SDR, a DDR, a QDR, or any other clocking and/or triggering strategy, as discussed above. The clocking mode employed by the protocol blocks may be based on the application. In applications where low latency and/or fully synchronous operations may be of benefit, retiming strategies such as the ones discussed above may be employed.

(95) As discussed above, the multi-purpose microbump interface **102** may allow multiple different functionalities for either the configuration data interface (e.g., DRIP interface **105A**) and/or the fabric data interface (e.g., fabric data interface **105B**). Tables 1 and 2 provide a non-limiting list of applications that may be implemented using the multi-purpose interface described herein.

(96) TABLE-US-00002 TABLE 1 Operations employing configuration data interface (e.g., DRIP interface **105A**). Operation Type Function Read/write Fast parallel write or read of configuration memory (e.g., configuration CRAM) to or from sector-aligned memory or NOC. May data increase speed of configuration and/or partial reconfiguration. Read/write Fast parallel write or read of user

memory (e.g., ERAM, user data M20K) to or from sector-aligned memory or NOC. May increase speed of partial reconfiguration and/or user memory context swapping. FPGA Fast parallel load of automated test pattern generation Test (ATPG) test vectors and/or data from using linear- feedback shift register (LFSR) circuitry from base circuitry and fast retrieval of test sequences for verification to base circuitry.

(97) TABLE-US-00003 TABLE 2 Operations employing fabric data interface (e.g., fabric data interface 105B). Operation Type Function Direct Memory Access Fabric circuitry may directly access base die sectorized memory. Memory Mapped Interfaces Fabric may use memory-mapped interfaces to access base die sectorized memory, NOC circuitry, and/or other base die circuitry. Examples of memory-mapped interfaces include Avalon Memory Map (AVMM) or Advanced Microcontroller Bus Architecture (AMBA) Advanced Extensible Interface (AXI). NOC Fabric may directly access NOC circuitry using NOC interface. The NOC interface may have extended features including security domains, Quality of Service (QoS), and other network features. Streaming Fabric may push streaming data to the sectorized memory, or NOC circuitry, and/or other base die circuitry. This may employ a first-in first-out (FIFO) or a large memory buffer in the fabric. Streaming interfaces that may be mapped include an Avalon Streaming (AVST) or AMBA High-Performance Bus (AHB). Debug and Trace Fabric may use the sectorized memories or NOC as storage for debug and trace operations. Examples of debug and trace operations include SOC capture and trace buffers for debugging traditional software, FPGA storage for real time data capture to debug FPGA design (e.g., Signal Tap), and FPGA storage for real time ASIC emulation data. Fabric Test Fabric may load fast parallel test vectors from base memory or base LFSR circuitry and retrieve scan test data to base die circuitry for verification. Examples of fabric test operation include use of vectors that test scan chains in the programmable fabric, use of ATPG scan chains in ASIC emulation, use of traffic generators in the base die to verify ASIC prototypes in ASIC emulators, and the use of large numbers of LFSR circuitry to perform noise and/or stress tests. Application Specific Interface Base die may include circuitry that performs operations such as compute in memory, vector engines, or any other application specific use case. Either fabric may interact with this circuitry, directly or employing a memory mapped interface.

(98) The programmable logic device **12** may be a data processing system or may be a component of a data processing system. For example, the programmable logic device **12** may be a component of a data processing system **500**, shown in FIG. **20**. The data processing system **500** includes a host processor **502**, memory and/or storage circuitry **504**, and a network interface **506**. The data processing system **500** may include more or fewer components (e.g., electronic display, user interface structures, application specific integrated circuits (ASICs)). The host processor **502** may include any suitable processor, such as an Intel® Xeon® processor or a reduced-instruction processor (e.g., a reduced instruction set computer (RISC), an Advanced RISC Machine (ARM) processor) that may manage a data processing request for the data processing system **500** (e.g., to perform machine learning, video processing, voice recognition, image recognition, data compression, database search ranking, bioinformatics, network security pattern identification, spatial navigation, or the like). The memory and/or storage circuitry **504** may include random access memory (RAM), read-only memory (ROM), one or more hard drives, flash memory, or the like. The memory and/or storage circuitry **504** may be considered external memory to the programmable logic device **12** and may hold data to be processed by the data processing system **500**. In some cases, the memory and/or storage circuitry **504** may also store configuration programs (e.g., bitstream) for programming the programmable logic device **12**. The network interface **506** may allow the data processing system **500** to communicate with other electronic devices. The data processing system **500** may include several different packages or may be contained within a single package on a single package substrate.

(99) In one example, the data processing system **500** may be part of a data center that processes a variety of different requests. For instance, the data processing system **500** may receive a data

processing request via the network interface **506** to perform machine learning, video processing, voice recognition, image recognition, data compression, database search ranking, bioinformatics, network security pattern identification, spatial navigation, or some other specialized task. The host processor **502** may cause the programmable logic fabric of the programmable logic device **12** to be programmed with a particular accelerator related to requested task. For instance, the host processor **502** may instruct that configuration data (bitstream) stored on the memory/storage circuitry **504** or cached in sector-aligned memory of the programmable logic device **12** to be programmed into the programmable logic fabric of the programmable logic device **12**. The configuration data (bitstream) may represent a circuit design for a particular accelerator function relevant to the requested task. Due to the high density of the programmable logic fabric, the proximity of the substantial amount of sector-aligned memory to the programmable logic fabric, or other features of the programmable logic device **12** that are described here, the programmable logic device **12** may rapidly assist the data processing system **500** in performing the requested task. Indeed, in one example, an accelerator may assist with a voice recognition task less than a few milliseconds (e.g., on the order of microseconds) by rapidly accessing and processing large amounts of data in the accelerator using sector-aligned memory.

(100) The methods and devices of this disclosure may be incorporated into any suitable circuit. For example, the methods and devices may be incorporated into numerous types of devices such as microprocessors or other integrated circuits. Exemplary integrated circuits include programmable array logic (PAL), programmable logic arrays (PLAs), field programmable logic arrays (FPLAs), electrically programmable logic devices (EPLDs), electrically erasable programmable logic devices (EEPLDs), logic cell arrays (LCAs), field programmable gate arrays (FPGAs), application specific standard products (ASSPs), application specific integrated circuits (ASICs), and microprocessors, just to name a few.

(101) Moreover, while the method operations have been described in a specific order, it should be understood that other operations may be performed in between described operations, described operations may be adjusted so that they occur at slightly different times or described operations may be distributed in a system which allows the occurrence of the processing operations at various intervals associated with the processing, as long as the processing of overlying operations is performed as desired.

(102) The embodiments set forth in the present disclosure may be susceptible to various modifications and alternative forms, specific embodiments have been shown by way of example in the drawings and have been described in detail herein. However, it may be understood that the disclosure is not intended to be limited to the particular forms disclosed. The disclosure is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the disclosure as defined by the following appended claims. In addition, the techniques presented and claimed herein are referenced and applied to material objects and concrete examples of a practical nature that demonstrably improve the present technical field and, as such, are not abstract, intangible or purely theoretical. Further, if any claims appended to the end of this specification contain one or more elements designated as “means for [perform]ing [a function] . . . ” or “step for [perform]ing [a function] . . . ” it is intended that such elements are to be interpreted under 35 U.S.C. 112(f). For any claims containing elements designated in any other manner, however, it is intended that such elements are not to be interpreted under 35 U.S.C. 112(f).

Claims

1. An integrated circuit device comprising: a first die comprising programmable logic, debug and trace circuitry, and first data exchange circuitry, wherein the first data exchange circuitry is connected to the programmable logic and microbumps; and a second die comprising: second data exchange circuitry that is connected to the microbumps and exchanges data with the first data

- exchange circuitry via the microbumps; and network on chip circuitry connected to the second data exchange circuitry and configurable to provide an interface for the first die to send data to or receive data from systems external to the first die and the second die.
2. The integrated circuit device of claim 1, wherein the microbumps are at least partially included in an interposer die.
 3. The integrated circuit device of claim 2, comprising a package substrate onto which the interposer die is disposed.
 4. The integrated circuit device of claim 1, wherein the systems external to the first die and the second die comprise random-access memory (RAM).
 5. The integrated circuit device of claim 1, wherein the systems external to the first die and the second die comprise high bandwidth memory (HBM).
 6. The integrated circuit device of claim 1, wherein the second die comprises a memory controller communicatively coupled to the second data exchange circuitry via the network on chip circuitry.
 7. The integrated circuit device of claim 1, comprising a plurality of third dies that includes the first die, wherein each die of the plurality of third dies comprises programmable logic.
 8. The integrated circuit device of claim 1, wherein the network on chip circuitry (NoC) comprises vertical NoC circuitry configurable to route data vertically through the second die and horizontal NoC circuitry configurable to route data horizontally through the second die.
 9. The integrated circuit device of claim 1, wherein the network on chip circuitry is configurable to provide address virtualization services.
 10. The integrated circuit device of claim 1, wherein the debug and trace circuitry is configurable to debug the programmable logic.
 11. An integrated circuit device comprising: a first die comprising programmable logic and first data exchange circuitry, wherein the first data exchange circuitry is connected to the programmable logic and microbumps; and a second die comprising: second data exchange circuitry that is connected to the microbumps and exchanges data with the first data exchange circuitry via the microbumps; and network on chip circuitry connected to the second data exchange circuitry and configurable to provide an interface for the first die to send secure data to or receive secure data from systems external to the first die and the second die.
 12. The integrated circuit device of claim 11, wherein the second die is configurable to decrypt the secure data.
 13. The integrated circuit device of claim 12, wherein the first die comprises debug and trace circuitry configurable to debug the programmable logic.
 14. The integrated circuit device of claim 11, wherein the second die comprises a memory controller communicatively coupled to the second data exchange circuitry via the network on chip circuitry.
 15. The integrated circuit device of claim 11, wherein the systems external to the first die and the second die comprise random-access memory (RAM) and high bandwidth memory (HBM).
 16. The integrated circuit device of claim 15, comprising a package substrate onto which an interposer die is disposed, wherein the microbumps are at least partially included in the interposer die.
 17. The integrated circuit device of claim 16, comprising a plurality of third dies that includes the first die, wherein each die of the plurality of third dies comprises programmable logic, and the network on chip circuitry (NoC) comprises vertical NoC circuitry configurable to route data vertically through the second die and horizontal NoC circuitry configurable to route data horizontally through the second die.
 18. A system comprising: a substrate; a first integrated circuit device disposed on the substrate; and a second integrated circuit device disposed on the substrate, wherein the second integrated circuit device comprises: a first die comprising programmable logic, debug and trace circuitry, and first data exchange circuitry, wherein the first data exchange circuitry is connected to the programmable

logic and microbumps; and a second die comprising: second data exchange circuitry that is connected to the microbumps and exchanges data with the first data exchange circuitry via the microbumps; and network on chip circuitry connected to the second data exchange circuitry and configurable to provide an interface for the first die to send secure data to or receive secure data from systems external to the first die and the second die.

19. The system of claim 18, wherein the first integrated circuit device comprises a processor.

20. The system of claim 18, wherein the systems external to the first die and the second die comprise random-access memory (RAM), high bandwidth memory (HBM), or both RAM and HBM.
