

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412692
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Arai; Takayuki et al.

Inductor array

Abstract

An inductor array of the invention includes a magnetic base body, a first internal conductor within the base body, and a second internal conductor adjacent to the first internal conductor. The first and second internal conductors are arranged along a reference axis. The base body includes an inter-conductor region between the first and second internal conductors. The inter-conductor region has a first section cut along a reference plane including the reference axis, and a first reference axis direction dimension of the first section in the reference axis direction may be less than double a shortest distance between the first internal conductor and a surface of the base body in the reference plane. A first aspect ratio of the first section, which is a ratio of a first orthogonal direction dimension in a direction orthogonal to the reference axis to the first reference axis direction dimension, may be less than 1.

Inventors: Arai; Takayuki (Tokyo, JP), Terauchi; Naoya (Tokyo, JP), Kashiwa; Tomoo (Tokyo, JP)

Applicant: TAIYO YUDEN CO., LTD. (Tokyo, JP)

Family ID: 85060704

Assignee: TAIYO YUDEN CO., LTD. (Tokyo, JP)

Appl. No.: 17/849927

Filed: June 27, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230052086 A1	Feb. 16, 2023

Foreign Application Priority Data

JP	2021-124851	Jul. 29, 2021
----	-------------	---------------

Publication Classification

Int. Cl.: H01F17/04 (20060101); H01F27/24 (20060101); H01F27/245 (20060101); H01F27/28 (20060101)

U.S. Cl.:

CPC H01F17/04 (20130101); H01F27/245 (20130101); H01F27/2895 (20130101);

Field of Classification Search

CPC: H01F (17/04); H01F (27/245); H01F (27/2895)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2008/0012674	12/2007	Sano	336/83	H05K 1/0233
2019/0326046	12/2018	Ashizawa	N/A	H01F 27/306
2021/0104353	12/2020	Yamauchi	N/A	H01F 17/04
2021/0134516	12/2020	Yoshioka	N/A	H01F 27/2804
2021/0272736	12/2020	Ashizawa	N/A	H01F 27/29
2021/0272745	12/2020	Wang	N/A	H01F 27/292

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2016-006830	12/2015	JP	N/A
2019-153649	12/2018	JP	N/A
2021-077714	12/2020	JP	N/A

OTHER PUBLICATIONS

SMD Beads and Chokes [Application note] Extended range for EMI noise suppression, United States, October, pp. 1 40, the Internet, the Internet] FERROXCUBE,2006 <

URL:<https://ferroxcube.home.pl/appl/info/SMD-beads%20&%20chokes%20-%20content.pdf> >

(Year: 2006). cited by examiner

Notice of Reasons for Refusal dated Apr. 15, 2025, issued in corresponding Japanese Patent Application No. 2021-124851, with English translation (13 pgs.). cited by applicant

Primary Examiner: Barnes; Malcolm

Attorney, Agent or Firm: Pillsbury Winthrop Shaw Pittman, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This application is based on and claims the benefit of priority from Japanese Patent Application Serial No. 2021-124851 (filed on Jul. 29, 2021), the contents of which are hereby incorporated by

reference in their entirety.

TECHNICAL FIELD

(2) The present disclosure relates to an inductor array, a circuit board including the inductor array, and an electronic device including the circuit board.

BACKGROUND

(3) An inductor array including a plurality of inductors has been known. A plurality of inductors are packaged in a single chip to form such an inductor array. A conventional inductor array includes, for example, a magnetic base body made of a magnetic material, a plurality of internal conductors provided in the base body, and a plurality of external electrodes connected to respective ends of the plurality of internal conductors. Examples of the conventional inductor array are disclosed, for example, in Japanese Patent Application Publication No. 2016-006830 and Japanese Patent Application Publication No. 2019-153649 (the '649 Publication; see FIG. 4).

(4) Since a plurality of inductors are packaged together, an inductor array has an advantage of requiring a small mounting space when mounted on a substrate. However, when the internal conductors included in the inductor array are arranged closer to each other, the magnetic coupling between the inductors is increased, and this makes it difficult for the inductors to exhibit desired characteristics. Therefore, in conventional inductor arrays designed such that each inductor functions as an independent inductor, a large distance is set between the internal conductors to reduce the magnetic coupling between the inductors. For example, in the inductor array **400** shown in FIG. 4 of the '649 Publication, the distance between the metal plates 12, which serve as internal conductors, is about three times as large as the distance from the metal plates 12 to the top surface of the molded body **10**, which serves as a magnetic base body. In conventional inductor arrays including the inductor array of the '649 Publication, the distance between adjacent internal conductors is three or more times as large as the distance from the internal conductors to the surfaces of the magnetic base body. With such structure, the magnitude of the coupling coefficient, which represents magnetic coupling between the inductors, is set at about 0.2 or less, such that each inductor can exhibit desired characteristics.

(5) When the magnetic base body surrounds the internal conductors with even thicknesses, the self-inductance of the inductors can be efficiently increased. Therefore, the distance between the internal conductors in an inductor array is preferably about one to two times as large as the distance from the internal conductors to the surfaces of the magnetic base body, so as to increase the self-inductance efficiently. However, as described above, when the distance between the internal conductors is reduced while maintaining the basic shape and structure of the conventional inductor arrays, the magnetic coupling between the inductors is unfavorably increased. The distance between the internal conductors in the conventional inductor arrays is thus two or more times as large as the distance from the internal conductors to the surfaces of the magnetic base body, so as to maintain, for each of the internal conductors, a distance equal to the distance from the internal conductor to the surfaces of the magnetic base body.

SUMMARY

(6) One object of the present disclosure is to overcome or reduce at least a part of the above drawback. Specifically, one object of the invention is to reduce magnetic coupling between the inductors in an inductor array in which the distance between the internal conductors is less than two times as large as the distance from the internal conductors to the surfaces of the magnetic base body.

(7) Other objects of the present invention will be made apparent through the entire description in the specification. The invention disclosed herein may address other drawbacks in addition to the drawback described above.

(8) An inductor array according to one or more embodiments of the invention comprises: a magnetic base body having a first surface, a second surface opposed to the first surface, and a third surface connecting between the first surface and the second surface; a plurality of internal

conductors having a same shape and arranged within the magnetic base body to be spaced apart from each other along a reference axis extending through the first surface and the second surface; a plurality of first external electrodes provided on the magnetic base body so as to be in contact at least with the third surface, each of the plurality of first external electrodes being connected to one end of associated one of the plurality of internal conductors; and a plurality of second external electrodes provided on the magnetic base body so as to be in contact at least with the third surface, each of the plurality of second external electrodes being connected to the other end of associated one of the plurality of internal conductors. In one or more embodiments of the invention, the plurality of internal conductors include a first internal conductor and a second internal conductor disposed adjacent to the first internal conductor, and the magnetic base body includes an inter-conductor region disposed between the first internal conductor and the second internal conductor and overlapping with both the first internal conductor and the second internal conductor as viewed from a reference axis direction along the reference axis. In one or more embodiments of the invention, the inter-conductor region has a first section cut along a reference plane including the reference axis and perpendicular to the third surface, and a first reference axis direction dimension of the first section in the reference axis direction is less than double a shortest distance between the first internal conductor and a surface of the magnetic base body in the reference plane. In one or more embodiments of the invention, a first aspect ratio of the first section is less than 1, the first aspect ratio being a ratio of a first orthogonal direction dimension in an orthogonal direction orthogonal to the reference axis to the first reference axis direction dimension. The first reference axis direction dimension may be equal to or larger than the distance between the first internal conductor and the fourth surface.

(9) In one or more embodiments of the invention, the first internal conductor has a second section cut along the reference plane, and a second orthogonal direction dimension of the second section in the orthogonal direction is equal to the first orthogonal direction dimension.

(10) In one or more embodiments of the invention, the magnetic base body has a fourth surface opposed to the third surface. A distance between the first internal conductor and the fourth surface may be equal to a distance between the second internal conductor and the fourth surface. A distance between the first internal conductor and the fourth surface may be smaller than a distance between the second internal conductor and the fourth surface.

(11) In one or more embodiments of the invention, the first internal conductor has a second section cut along the reference plane, and a second orthogonal direction dimension of the second section in the orthogonal direction is larger than the first orthogonal direction dimension.

(12) In one or more embodiments of the invention, the first internal conductor has a second section cut along the reference plane, and the first aspect ratio is smaller than a second aspect ratio of the second section, the second aspect ratio being a ratio of a second orthogonal direction dimension in the orthogonal direction to a second reference axis direction dimension in the reference axis direction.

(13) In one or more embodiments of the invention, the second aspect ratio is larger than 1. In one or more embodiments of the invention, a magnitude of a coupling coefficient representing magnetic coupling between the first internal conductor and the second internal conductor is less than 0.2. A magnitude of a coupling coefficient representing magnetic coupling between the first internal conductor and the second internal conductor may be less than 0.1.

(14) An embodiment of the present invention relates to a circuit board including any one of the above-described inductor arrays.

(15) An embodiment of the present invention relates to an electronic device comprising the above circuit board.

Advantageous Effects

(16) With the technique disclosed herein, it is possible to reduce magnetic coupling between the inductors in an inductor array in which the distance between the internal conductors is less than two

times as large as the distance from the internal conductors to the surfaces of the magnetic base body.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a perspective view of an inductor array according to one embodiment of the invention mounted on a mounting substrate.
- (2) FIG. 2 is an exploded view of the inductor array of FIG. 1.
- (3) FIG. 3 is a sectional view schematically showing a section of the inductor array of FIG. 1 cut along the plane extending through a reference axis and perpendicular to the bottom surface of the magnetic base body.
- (4) FIG. 4 is a sectional view showing a section of internal conductors included in the inductor array of FIG. 1.
- (5) FIG. 5 is a perspective view of the inductor array according to another embodiment of the invention.
- (6) FIG. 6 is a sectional view schematically showing a section of the inductor array of FIG. 5 cut along the plane extending through a reference axis and perpendicular to the bottom surface of the magnetic base body.
- (7) FIG. 7 is a perspective view of an inductor array according to another embodiment of the present invention.
- (8) FIG. 8 is a sectional view schematically showing a section of the inductor array of FIG. 7 cut along the plane extending through a reference axis and perpendicular to the bottom surface of the magnetic base body.
- (9) FIG. 9 is a perspective view of the inductor array according to another embodiment of the invention.
- (10) FIG. 10 is a sectional view schematically showing a section of the inductor array of FIG. 9 cut along the plane extending through a reference axis and perpendicular to the bottom surface of the magnetic base body.
- (11) FIG. 11 is a perspective view of the inductor array according to another embodiment of the invention.
- (12) FIG. 12 is a graph showing results of simulation of inductor characteristics performed on an inductor array which is an implementation example of the invention.

DESCRIPTION OF EXAMPLE EMBODIMENTS

- (13) Various embodiments of the present invention will be described hereinafter with reference to the appended drawings. Throughout the drawings, the same components are denoted by the same reference numerals. For convenience of explanation, the drawings are not necessarily drawn to scale. The following embodiments of the present invention do not limit the scope of the claims. The elements described in the following embodiments are not necessarily essential to solve the problem addressed by the invention.
- (14) An inductor array 1 according to one or more embodiments of the present invention will be described with reference to FIGS. 1 to 4. FIG. 1 is a perspective view of the inductor array 1 according to one embodiment of the present invention, and FIG. 2 is an exploded view of the inductor array 1. FIG. 3 is a schematic sectional view of the inductor array 1 along the I-I line, and FIG. 4 is a sectional view showing a section of internal conductors included in the inductor array 1.
- (15) Each of the drawings shows the L axis, the W axis, and the T axis orthogonal to one another. In this specification, the “length” direction, the “width” direction, and the “thickness” direction of the inductor array 1 are referred to as the L-axis direction, W-axis direction, and T-axis direction in FIG. 1, respectively, unless otherwise construed from the context.

(16) As illustrated, the inductor array **1** includes a base body **10**, internal conductors **25A** and **25B** provided in the base body **10**, and external electrodes **21A**, **21B**, **22A**, **22B** provided on a surface of the base body **10**. The internal conductor **25A** is coupled to the external electrode **21A** at one end thereof and to the external electrode **22A** at the other end thereof. The internal conductor **25B** is coupled to the external electrode **21B** at one end thereof and to the external electrode **22B** at the other end thereof. The internal conductor **25A** is disposed at a distance from the internal conductor **25B** in the L-axis direction. Thus, the inductor array **1** includes a first inductor including the internal conductor **25A** and the external electrodes **21A** and **22A**, and a second inductor including the internal conductor **25B** and the external electrodes **21B** and **22B**. The number of internal conductors disposed in the base body **10** is not limited to two. The base body **10** may contain any desired number of internal conductors.

(17) In the inductor array **1** thus configured, the internal conductor **25A** and the external electrodes **21A** and **22A** constitute an inductor **1A**, and the internal conductor **25B** and the external electrodes **21B** and **22B** constitute an inductor **1B**. The inductor **1A** preferably operates with no magnetic interference from the inductor **1B**. Likewise, the inductor **1B** preferably operates with no magnetic interference from the inductor **1A**. Therefore, the inductor array **1** is configured such that the magnitude (absolute value) of the coupling coefficient between the inductor **1A** and the inductor **1B** is low. In one or more embodiments of the invention, the magnitude of the coupling coefficient between the inductor **1A** and the inductor **1B** is 0.2 or less. When a pair of inductors is configured as a common mode coil, the coupling coefficient between the pair of inductors is typically set at 0.4 or higher. Since the magnitude of the coupling coefficient between the inductor **1A** and the inductor **1B** is 0.2 or less, the inductor array **1** cannot function as a common mode coil. Thus, each of the inductor **1A** and the inductor **1B** of the inductor array **1** is configured to function as a separate inductor.

(18) Each of the inductors **1A** and **1B** is used in, for example, a large-current circuit through which a large electric current flows. More specifically, the inductor array **1** may be an inductor used in a DC-to-DC converter (what is called a power inductor).

(19) The inductor array **1** may be mounted on a mounting substrate **2a**. The mounting substrate **2a** has four land portions **3** provided thereon. When the inductor array **1** is mounted on the mounting substrate **2a**, the four external electrodes **21A**, **21B**, **22A**, **22B** of the inductor array **1** are positioned to face the corresponding lands **3**. The inductor array **1** may be mounted on the mounting substrate **2a** by soldering the external electrodes **21A**, **21B**, **22A**, **22B** to the corresponding lands **3**. Thus, a circuit board **2** includes the inductor array **1** and the mounting substrate **2a** on which the inductor array **1** is mounted. In addition to the inductor array **1**, various electronic components may be mounted on the mounting substrate **2a**.

(20) The circuit board **2** can be installed in various electronic devices. Electronic devices in which the circuit board **2** may be installed include smartphones, tablets, game consoles, servers, electrical components of automobiles, and various other electronic devices. The inductor array **1** may be a built-in component embedded in the mounting substrate **2a**.

(21) Since the inductor array **1** is formed as a single chip in which the inductor **1A** with the internal conductor **25A** and the external electrodes **21A**, **22A** and the inductor **1B** with the internal conductor **25B** and the external electrodes **21B**, **22B** are included, it is particularly suitable for small electronic devices that require high-density mounting of electronic components.

(22) In the illustrated embodiment, the base body **10** has a substantially rectangular parallelepiped shape. In one embodiment of the invention, the base body **10** has a length (the dimension in the L-axis direction) of 0.6 mm to 10 mm, a width (the dimension in the W-axis direction) of 0.2 mm to 10 mm, and a thickness (the dimension in the T-axis direction) of 0.2 mm to 10 mm. The base body **10** has a first region situated on a positive side in the L-axis direction with respect to a predetermined boundary on the L-axis, and a second region situated on a negative side with respect to the boundary in the L-axis direction. The first region includes the internal conductor **25A**, and

the second region includes the internal conductor 25B. In this manner, the base body 10 has a plurality of regions, each of which has a single inductor. A region of the base body 10 containing a single inductor has a dimension in the L-axis direction of 0.1 mm to 5.0 mm. The dimensions of the base body 10 are not limited to those specified herein. The term “rectangular parallelepiped” or “rectangular parallelepiped shape” used herein is not intended to mean solely “rectangular parallelepiped” in a mathematically strict sense.

(23) The base body 10 has a first principal surface 10a, a second principal surface 10b, a first end surface 10c, a second end surface 10d, a first side surface 10e, and a second side surface 10f. These six surfaces define the outer periphery of the base body 10. The first principal surface 10a and the second principal surface 10b are opposed to each other, the first end surface 10c and the second end surface 10d are opposed to each other, and the first side surface 10e and the second side surface 10f are opposed to each other. Based on the position of the mounting substrate 2a, the first principal surface 10a lies on the top side of the base body 10, and therefore, the first principal surface 10a may be herein referred to as the “top surface,” and the second principal surface 10a may be herein referred to as the “bottom surface.” Each of the first principal surface 10a, the second principal surface 10b, the first side surface 10e, and the second side surface 10f connects the first end surface 10c to the second end surface 10d.

(24) The inductor array 1 is disposed such that the first principal surface 10a or the second principal surface 10b faces the mounting substrate 2a. One of the principal surfaces that faces the mounting substrate 2a, either the first principal surface 10a or the second principal surface 10b, is herein referred to as a “mounting surface”. In the illustrated embodiment, the second principal surface 10b faces the mounting substrate 2a, so the second principal surface 10b is the “mounting surface”. Thus, the second principal surface 10b may be referred to as the “mounting surface 10b.” Since the “mounting surface” of the base body 10 is the surface facing the mounting substrate 2a, any surface other than the second principal surface 10b may be the mounting surface. The external electrodes 21A, 21B, 22A, 22B provided in the inductor array 1 at least partially contact the mounting surface of the base body 10. In the embodiment shown in FIG. 1, the external electrodes 21A, 21B, 22A, 22B are each partially in contact with the first and second principal surfaces 10A and 10B, so either the first principal surface 10a or the second principal surface 10b can be used as the mounting surface.

(25) In the illustrated embodiment, the first and second principal surfaces 10a and 10b are parallel to the LW plane, the first and second end surfaces 10c and 10d are parallel to the WT plane, and the first and second side surfaces 10e and 10f are parallel to the TL plane.

(26) The top-bottom direction of the inductor array 1 refers to the top-bottom direction in FIG. 1. The thickness direction of the inductor array 1 or the base body 10 may be the direction perpendicular to at least one of the top surface 10a or the mounting surface 10b. The length direction of the inductor array 1 or the base body 10 may be the direction perpendicular to at least one of the first end surface 10c or the second end surface 10d. The width direction of the inductor array 1 or the base body 10 may be the direction perpendicular to at least one of the first side surface 10e or the second side surface 10f. The width direction of the inductor array 1 or the base body 10 may be the direction perpendicular to the thickness and length directions of the inductor array 1 or the base body 10.

(27) In the illustrated embodiment, the external electrode 22A is attached to the base body 10 at a position spaced apart from the external electrode 21A in the W-axis direction, and the external electrode 21B is attached to the base body 10 at a position spaced apart from the external electrode 21A in the L-axis direction. The external electrode 22B is attached to the base body 10 at a position spaced apart from the external electrode 22A in the L-axis direction and spaced apart from the external electrode 21B in the W-axis direction. In the illustrated embodiment, the external electrodes 21A and 21B are provided in contact with the mounting surface 10b, the first side surface 10e, and the top surface 10a of the base body 10, and the external electrodes 22A and 22B

are provided in contact with the mounting surface **10b**, the second side surface **10f**, and the top surface **10a** of the base body **10**. The external electrodes **21A** and **21B** may be provided on the base body **10** such that they are in contact with the mounting surface **10b** and the first side surface **10e** but not with the top surface **10a**. The external electrodes **22A** and **22B** may be provided on the base body **10** such that they are in contact with the mounting surface **10b** and the second side surface **10f** but not with the top surface **10a**. The shape and arrangement of the external electrodes **21A**, **22B**, **22A**, and **22B** are not limited to those explicitly described herein. The external electrodes **21A**, **21B**, **22A**, **22B** may have either the same shape or different shapes. Any two of the external electrodes **21A**, **21B**, **22A**, and **22B** may be selected to have the same shape.

(28) The base body **10** is made of a magnetic material. The magnetic material may be a ferrite material, a soft magnetic alloy material, a composite magnetic material including magnetic particles dispersed in a resin, or any other known magnetic materials. The ferrite material used for the base body **10** may be a Ni—Zn-based ferrite, a Ni—Zn—Cu-based ferrite, a Mn—Zn-based ferrite, or any other ferrite materials.

(29) The metal magnetic particles contained in the magnetic material for the base body **10** are, for example, particles of (1) a metal such as Fe or Ni, (2) a crystalline alloy such as an Fe—Si—Cr alloy, an Fe—Si—Al alloy, or an Fe—Ni alloy, (3) an amorphous alloy such as an Fe—Si—Cr—B—C alloy or an Fe—Si—Cr—B alloy, or (4) a mixture thereof. The composition of the metal magnetic particles contained in the base body **10** is not limited to those described above. For example, the metal magnetic particles contained in the base body **10** may be particles of a Co—Nb—Zr alloy, an Fe—Zr—Cu—B alloy, an Fe—Si—B alloy, an Fe—Co—Zr—Cu—B alloy, an Ni—Si—B alloy, or an Fe—Al—Cr alloy. The Fe-based metal magnetic particles contained in the base body **10** may contain 80 wt % or more Fe. An insulating film may be formed on the surface of each of the metal magnetic particles. The insulating film may be an oxide film made of an oxide of the above metals or alloys. The insulating film provided on the surface of each of the metal magnetic particles may be, for example, a silicon oxide film provided by the sol-gel coating process.

(30) In one or more embodiments, the average particle size of the metal magnetic particles in the base body **10** is from 1.0 μm to 20 μm . The average particle size of the metal magnetic particles contained in the base body **10** may be smaller than 1.0 μm or larger than 20 μm . The base body **10** may contain two or more types of metal magnetic particles having different average particle sizes.

(31) In the base body **10**, the metal magnetic particles may be bonded to each other with an oxide film formed by oxidation of an element included in the metal magnetic particles during a manufacturing process. The base body **10** may contain a binder in addition to the metal magnetic particles. When the base body **10** contains a binder, the metal magnetic particles are bonded to each other by the binder. The binder in the base body **10** may be formed, for example, by curing a thermosetting resin that has an excellent insulation property. Examples of a material for such a binder include an epoxy resin, a polyimide resin, a polystyrene (PS) resin, a high-density polyethylene (HDPE) resin, a polyoxymethylene (POM) resin, a polycarbonate (PC) resin, a polyvinylidene fluoride (PVDF) resin, a phenolic resin, a polytetrafluoroethylene (PTFE) resin, or a polybenzoxazole (PBO) resin.

(32) In one or more embodiments of the invention, the relative magnetic permeability of the base body **10** is 100 or less. In one or more embodiments of the invention, the relative magnetic permeability of the base body **10** is 30 or greater. When the inductor array **1** is used in a high frequency circuit, the relative magnetic permeability of the base body **10** may be lower. For example, when the inductor array **1** operates at a frequency of about 100 MHz, the lower limit of the relative magnetic permeability of the base body **10** may be 20 or greater. When the inductor array **1** operates at a higher frequency band, the lower limit of the relative magnetic permeability of the base body **10** may be 10 or greater. In one or more embodiments of the invention, the relative magnetic permeability of the base body **10** is in the range of 30 to 100 (both inclusive). The base body **10** may be configured to have a relative magnetic permeability in the range of 30 to 100 in its

entire region. As described above, the inductor array **1** may be used in DC-to-DC converters where a low inductance is required. When the base body **10** has a relative magnetic permeability of 100 or less, it is easy to achieve a required low inductance. When the base body **10** has a relative magnetic permeability of 100 or less, it is also easy to achieve high current characteristics. When the base body **10** has a relative magnetic permeability of 100 or less, it is also easy to achieve high insulation properties. When the base body **10** has a relative magnetic permeability of 100 or less, it is possible to reduce the chance of magnetic saturation. Therefore, there is no need to provide a magnetic gap in the base body **10** to improve the DC superposition characteristics.

(33) As mentioned above, the relative magnetic permeability of the base body **10** of the inductor array **1** takes a small value, such as 100 or smaller, so that the self-inductance L of each line of inductor included in the inductor array **1** also takes a small value. Since the self-inductance of each line of inductor is low, magnetic saturation is unlikely to occur in the inductor array **1**. This allows a large current to flow through each line of inductor in the inductor array **1**. Accordingly, in one or more embodiments of the present invention, each line of inductor in the inductor array **1** can achieve increased energy density E_d , which is expressed as the result of dividing the product of the self-inductance L of the inductor and the square of the current I flowing through the inductor by the volume V of the inductor ($E_d = L \times I^2 / V$). For example, when the self-inductance L of each line of inductor in the inductor array **1** is less than 100 nH, the inductor can have E_d of 1500 nH.Math.A.sup.2/mm.sup.3. When the self-inductance L of each line of inductor in the inductor array **1** is less than 50 nH, the E_d can be 2000 nH.Math.A.sup.2/mm.sup.3. When the self-inductance L of each line of inductor in the inductor array **1** is less than 25 nH, the E_d can be 2500 nH.Math.A.sup.2/mm.sup.3.

(34) In one or more embodiments of the invention, the internal conductors **25A**, **25B** have the same shape. In the illustrated embodiment, the internal conductors **25A**, **25B** have the same rectangular parallelepiped shape. Since the internal conductors **25A**, **25B** have the same shape, the inductor array **1** can easily achieve uniform electrical characteristics among the lines (i.e., the inductors **1A**, **1B**) formed therein. The internal conductors **25A**, **25B**, provided within the base body **10**, may be placed at the same level in the T-axis direction. Specifically, as shown in FIG. 3, the internal conductors **25A**, **25B** are at the same level in the T-axis direction such that their respective top surfaces are at the same level in the T-axis direction and their respective bottom surfaces are at the same level in the T-axis direction. The internal conductors **25A**, **25B** may differ from each other in terms of shape due to the manufacturing- and/or measurement-induced errors, but this does not deny that the internal conductors **25A**, **25B** have the same shape as far as the present specification is concerned.

(35) The internal conductors **25A**, **25B** may extend linearly from the first side surface **10e** to the second side surface **10f**. The internal conductors **25A**, **25B** can be shaped in any other manners than the illustrated such that they have winding portions, as will be described below. The other possible shapes of the internal conductors **25A**, **25B** will be described below.

(36) The internal conductor **25A** and the internal conductor **25B** are provided within the base body **10**. In the illustrated embodiment, the internal conductor **25A** is exposed at one end thereof to the outside of the base body **10** from the first side surface **10e** and is connected to the external electrode **21A** at the one end. The internal conductor **25A** is also exposed at the other end thereof to the outside of the base body **10** from the second side surface **10f** and is connected to the external electrode **22A** at the other end. In this manner, the internal conductor **25A** is connected at one end thereof to the external electrode **21A** and connected at the other end thereof to the external electrode **22A**. Similarly, the internal conductor **25B** is exposed at one end thereof to the outside of the base body **10** from the first side surface **10e** and is connected to the external electrode **21B** at the one end. The internal conductor **25B** is also exposed at the other end thereof to the outside of the base body **10** from the second side surface **10f** and is connected to the external electrode **22B** at the other end. In this manner, the internal conductor **25B** is connected at one end thereof to the

external electrode **21B** and connected at the other end thereof to the external electrode **22B**. In this way, to connect the internal conductors **25A** and **25B** to the external electrodes, the internal conductors **25A** and **25B** are not directly connected to a first surface, but are connected to the first surface outside the base body **10** via the external electrodes **21A**, **22A**, **21B** and **22B** formed on the first and second side surfaces. Therefore, the volume of the base body **10** can be increased relative to the overall volume of the inductor array **1**. Consequently, the proportion in volume of the base body **10**, which is made of a magnetic material, can be larger in the inductor array **1**. This can result in higher saturation magnetic flux density of the base body **10**.

(37) The internal conductor **25A** extends linearly from the external electrode **21A** to the second external electrode **22A** in plan view (as viewed from the T axis). Stated differently, the internal conductor **25A** has no parts facing each other in the base body **10** in plan view. Herein, when the internal conductor **25A** has no parts facing each other in the base body in plan view, it can be said that the internal conductor **25A** extends linearly from the external electrode **21A** to the external electrode **22A**. Thus, compared with conventional inductors that have internal conductors with parts facing each other in plan view, the insulation reliability (withstand voltage) can be increased without changing the volume resistivity of the base body **10**. The internal conductor **25A** may be disposed on a straight line drawn from the external electrode **21** to the external electrode **22**. In the illustrated embodiment, the internal conductor **25A** has a rectangular parallelepiped shape. The internal conductor **25A** may include multiple conductor layers arranged in parallel between the external electrode **21A** and the external electrode **22A**. All of the plurality of conductor portions extend linearly from the external electrode **21** to the external electrode **22** and are shaped similarly to each other. Each of the conductor layers included in the internal conductor **25A** has no parts that are disposed to face each other in the base body **10**. Since the plurality of conductor layers are shaped similarly to each other, among the plurality of conductor layers, there is no difference in potential between such parts that face each other in the base body **10**. Therefore, even when the internal conductor **25A** is formed of the plurality of conductor layers as described above, the insulation reliability (withstand voltage) required of the base body **10** can be about the same as when the internal conductor **25A** is formed of a single conductor layer. The plurality of conductor layers included in the internal conductor **25A** may be connected to each other in the base body **10**. The internal conductor **25A** and the internal conductor **25B** may each be formed of a plurality of conductors that are connected to each other by means other than through-holes. The internal conductor **25A** and the internal conductor **25B** may each include a plurality of conductors that are not connected to each other in the base body **10**, but are connected by the external electrodes **21A** and **22A** and the external electrodes **21B** and **22B**.

(38) FIGS. **1** and **3** show a reference axis Ax**1** extending along the L-axis, which is an imaginary axis extending through the first and second end surfaces **10c** and **10d**. In the embodiment shown, the reference axis Ax**1** extends in the direction parallel to the L-axis. The reference axis Ax**1** may extend through the geometric center of gravity of the first end surface **10c** and the geometric center of gravity of the second end surface **10d**. When the first end surface **10c** has a rectangular shape, the geometric center of gravity of the first end surface **10c** lies at the point of intersection of the diagonal lines of the rectangle defining the first end surface **10c**. The internal conductors **25A**, **25B** are arranged along the reference axis Ax**1**. In the direction perpendicular to the reference axis Ax**1**, the internal conductors **25A**, **25B** extend from the first side surface **10e** to the second side surface **10f**.

(39) As shown in FIG. **2**, the inductor array **1** may have a laminated structure having a plurality of magnetic layers stacked on each other. In FIG. **2**, the external electrodes **21A**, **22A**, **21B**, and **22B** are not shown for convenience of description. In the illustrated embodiment, the base body **10** includes magnetic layers **11a** to **11e**. Each of the magnetic layers **11a** to **11e** is made of a magnetic material. The base body **10** includes the magnetic layer **11a**, the magnetic layer **11b**, the magnetic layer **11c**, the magnetic layer **11d**, and the magnetic layer **11e**, which are stacked together in the

stated order from the negative side to the positive side in the L-axis direction. As shown, the magnetic layers **11a**, **11c** and lie may each include a plurality of magnetic layers. Likewise, the magnetic layers other than the magnetic layers **11a**, **11c** and lie may each include a plurality of magnetic layers. The magnetic layer **11a** and the magnetic layer lie are disposed so as to cover the internal conductors **25A** and **25B** on both sides in the L-axis direction, and thus these magnetic layers may be referred to as the cover layers.

(40) The internal conductor **25A** is provided on one surface of the magnetic layer **11b**, and the internal conductor **25B** is provided on one surface of the magnetic layer **11d**. More specifically, the internal conductor **25A** is provided on one of the surfaces of the magnetic layer **11b** intersecting the L axis, or the positive-side surface in the L-axis direction, and the internal conductor **25B** is provided on one of the surfaces of the magnetic layer **11d** intersecting the L axis, or the positive-side surface in the L-axis direction. The internal conductors **25A** and **25B** are formed by, for example, printing a conductive paste made of a highly conductive metal or alloy on each magnetic layer by screen printing. The conductive material contained in the conductive paste may be Ag, Cu, or alloys thereof. In the embodiment shown, the internal conductor **24A** is provided on the magnetic layer **11b** and the internal conductor **25B** is provided on the magnetic layer **11d**, which is a different magnetic layer from the magnetic layer **11b**. The internal conductors **25A** and **25B** may be, however, provided on the same magnetic layer. The internal conductors **25A** and **25B** can be made of other materials and using other techniques. For example, the internal conductors **25A** and **25B** may be formed by sputtering, ink-jetting, or other known methods. The internal conductors **25A** and **25B** may be formed by embedding metal foil or alloy foil in any of the magnetic layers **11a** to lie or by embedding or sandwiching such foil between adjacent ones of the magnetic layers **11a** to lie.

(41) With further reference to FIG. 3, the arrangement and sectional shape of the internal conductors **25A** and **25B** will be further described. FIG. 3 is a sectional view schematically showing the section of the inductor array **1** along the I-I line. More specifically, FIG. 3 shows the section of the inductor array **1** cut along a plane extending through the reference axis Ax1 and perpendicular to the bottom surface **10b** (parallel to the LT plane). The plane extending through the reference axis Ax1 and perpendicular to the bottom surface **10b** may be herein referred to as “the reference plane.” For brevity of explanation, FIG. 3 does not show the external electrodes **21A**, **21B**, **22A**, **22B**.

(42) In one or more embodiments of the present invention, the internal conductor **25B** is spaced apart from the internal conductor **25A** in the direction of the reference axis Ax1. The base body **10** includes an inter-conductor region **10A**. The inter-conductor region **10A** is positioned between the internal conductor **25A** and the internal conductor **25B**. The inter-conductor region **10A** refers to the region of the base body **10** positioned between the internal conductor **25A** and the internal conductor **25B** and overlapping with both the internal conductor **25A** and the internal conductor **25B** as viewed from the reference axis direction along the reference axis Ax1 (i.e., as viewed from the L-axis direction). In the case where the inductor array **1** includes three or more internal conductors, the inter-conductor region may refer to the regions positioned between adjacent ones of the three or more internal conductors and overlapping with both the adjacent ones of the internal conductors as viewed from the reference axis direction along the reference axis Ax1. In the case where the inductor array **1** includes N internal conductors, the inductor array **1** can include N-1 inter-conductor regions.

(43) The inter-conductor region **10A** extends over the entire distance between the internal conductor **25A** and the internal conductor **25B** in the reference axis direction. In other words, the inter-conductor region **10A** is in contact with the internal conductor **25A** at one end thereof in the reference axis direction and is in contact with the internal conductor **25B** at the other end thereof in the reference axis direction.

(44) As shown in FIG. 3, the section of the inter-conductor region **10A** cut along the plane

extending through the reference axis Ax1 and perpendicular to the bottom surface 10b (i.e., the reference plane) has a rectangular shape. For convenience of description, the section of the inter-conductor region 10A cut along the reference plane may be referred to simply as “the section of the inter-conductor region 10A.” As shown, the dimension of the section of the inter-conductor region 10A in the reference axis direction along the reference axis Ax1 (L-axis direction) is referred to as the first reference axis direction dimension a1, and the dimension of the section of the inter-conductor region 10A in the orthogonal direction orthogonal to the reference axis Ax1 (T-axis direction) is referred to as the first orthogonal direction dimension a2.

(45) The internal conductor 25A is spaced apart from the top surface 10a, the bottom surface 10b, and the second end surface 10d of the base body 10 by the distances a3A, a4A, and a5A, respectively. The internal conductor 25B is spaced apart from the top surface 10a, the bottom surface 10b, and the first end surface 10c of the base body 10 by the distances a3B, a4B, and a5B, respectively. In the embodiment shown, as described above, the internal conductors 25A, 25B are at the same level in the T-axis direction, and therefore, the distance a3A is equal to the distance a3B, and the distance a4A is equal to the distance a4B.

(46) In one or more embodiments of the present invention, the internal conductor 25A is positioned in the base body 10 such that the distances a3A, a4A, and a5A are equal to one another. If any one of the distances a3A, a4A, and a5A is smaller than the others, an increased magnetic resistance occurs at a part of the periphery of the internal conductor 25A, resulting in a degraded self-inductance of the inductor 1A. For example, if the distance a3A is smaller than the distances a4A and a5A, the magnetic resistance in the region between the internal conductor 25A and the top surface 10a of the base body 10 is larger than that in the other regions within the base body 10, and thus the self-inductance of the inductor 1A is degraded. When the distances a3A, a4A, and a5A are equal to one another, the magnetic base body 10 can have an even thickness in the periphery of the internal conductor 25A, preventing degradation of the self-inductance of the inductor 1A.

Likewise, the internal conductor 25B is positioned in the base body 10 such that the distances a3B, a4B, and a5B are equal to one another. This can prevent degradation of the self-inductance of the inductor 1B.

(47) In one or more embodiments of the invention, the first aspect ratio, which is the ratio of the first orthogonal direction dimension a2 to the first reference axis direction dimension a1 ($a2/a1$), is less than 1. Since the first aspect ratio of the inter-conductor region 10A is less than 1, the magnetic resistance of the inter-conductor region 10A can be small. Thus, the magnetic flux generated when the electric current flowing through the internal conductor 25A varies is likely to pass through the inter-conductor region 10A and is conversely unlikely to reach the internal conductor 25B, and therefore, the magnetic coupling between the inductor 1A and the inductor 1B can be reduced. Further, since the first aspect ratio of the inter-conductor region 10A is less than 1, the distance between the internal conductor 25A and the internal conductor 25B can be large, and therefore, the length of the magnetic path encircling both the internal conductor 25A and the internal conductor 25B can be large. Thus, the magnetic flux generated when the electric current flowing through the internal conductor 25A varies is unlikely to reach the internal conductor 25B, and therefore, the magnetic coupling between the inductor 1A and the inductor 1B can be reduced.

(48) In the inductor array 1, the pitch between the internal conductors is represented by the first reference axis direction dimension a1 of the inter-conductor region 10A. In one or more embodiments of the present invention, the internal conductors 25A, 25B are positioned such that the first reference axis direction dimension a1 of the inter-conductor region 10A is less than double the shortest distance between the internal conductor 25A and the surface of the base body 10 in the reference plane extending through the reference axis Ax1 and perpendicular to the bottom surface 10b of the base body 10. In the embodiment shown, the smallest of the distances a3A, a4A, and a5A is the shortest distance between the internal conductor 25A and the surface of the base body 10 in the reference plane. When the distances a3A, a4A, and a5A are equal to one another, the internal

conductors **25A**, **25B** are positioned such that the first reference axis direction dimension **a1** of the inter-conductor region **10A** is less than, for example, double the distance **a3A** between the internal conductor **25A** and the top surface **10a** of the base body **10**. Thus, the inductor array **1** can have a small dimension in the reference axis direction and thus have a small mounting area. In conventional inductor arrays, the magnetic base body has an even thickness in the periphery of each internal conductor so as to efficiently improve the self-inductance of each inductor. Since the magnetic base body has an even thickness in the periphery of each internal conductor, the interval between adjacent internal conductors (i.e., the dimension of the inter-conductor region between the adjacent internal conductors in the reference axis direction) is double the shortest distance between the internal conductor and the surface of the base body (for example, the distance between the internal conductor and the top surface of the base body) in the reference plane. Further, in conventional inductor arrays, the interval between adjacent internal conductors is larger than double the shortest distance between the internal conductor and the surface of the base body so as to reduce magnetic coupling. By contrast, in the inductor array **1**, the first aspect ratio of the inter-conductor region **10A** is less than 1, so as to reduce magnetic coupling between the inductor **1A** and the inductor **1B**, and therefore, the pitch between the internal conductor **25A** and the internal conductor **25B** (i.e., the first reference axis direction dimension **a1** of the inter-conductor region **10A**) can be less than double the shortest distance between the internal conductor and the surface of the base body (for example, the distance **a3A** between the internal conductor and the top surface) in the reference plane.

(49) In one or more embodiments of the present invention, the internal conductors **25A**, **25B** are positioned such that the first reference axis direction dimension **a1** of the inter-conductor region **10A** is equal to or larger than the distance **a3A** between the internal conductor **25A** and the top surface **10a** of the base body **10**. Thus, the magnetic resistance in the inter-conductor region **10A** is higher than that in the other regions, and this prevents degradation of the self-inductance of the inductors **1A**, **1B**.

(50) In the case where an inductor array includes three or more internal conductors, the magnetic base body **10** of this inductor array can include two or more inter-conductor regions. The above description of the inter-conductor region **10A** may apply to each of the two or more inter-conductor regions included in the inductor array **1**.

(51) The following now describes the shape of the internal conductors included in the inductor array with reference mainly to FIG. 4. FIG. 4 is an enlarged sectional view showing, on an enlarged scale, the sections of the internal conductors **25A**, **25B** shown in FIG. 3. As shown, the section of the internal conductor **25A** has a dimension **b1A** in the reference axis direction and a dimension **b2A** in the direction perpendicular to the reference axis direction, and the section of the internal conductor **25B** has a dimension **b1B** in the reference axis direction and a dimension **b2B** in the direction perpendicular to the reference axis direction. As described above, the internal conductors **25A**, **25B** have the same shape, and therefore, the dimension **b1A** is equal to the dimension **b1B**, and the dimension **b2A** is equal to the dimension **b2B**. In this specification, when the dimension **b1A** and the dimension **b1B** do not need to be distinguished from each other, the dimension **b1A** and the dimension **b1B** are collectively referred to as the dimension **b1**, and the dimension **b2A** and the dimension **b2B** are collectively referred to as the dimension **b2**.

(52) The ratio of the dimension **b2** to the dimension **b1** ($b2/b1$) is referred to as a second aspect ratio. In one or more embodiments of the invention, the second aspect ratio ($b2/b1$) is equal to or larger than the first aspect ratio ($a2/a1$). For example, the second aspect ratio may be in the range of 0.5 to 1.5. When the shape of the internal conductors **25A**, **25B** is set such that the second aspect ratio approximates 1 (for example, in the range of 0.5 to 1.5), the inductors **1A**, **1B** can have a high self-inductance.

(53) An inductor array according to another embodiment, to which the present invention is applicable, will be now described with reference to FIGS. 5 to 11.

(54) First, an inductor array **101** according to one or more embodiments of the present invention will be described with reference to FIGS. **5** and **6**. FIG. **5** is a perspective view of the inductor array **101**, and FIG. **6** is a sectional view schematically showing a section of the inductor array **101** cut along the plane extending through the reference axis **Ax1** and perpendicular to the bottom surface **10b** of the base body **10** (i.e., the reference plane). The inductor array **101** shown in FIGS. **5** to **6** differs from the inductor array **1** in that it has internal conductors **125A** and **125B** instead of the internal conductors **25A** and **25B**, respectively, and external electrodes **121A**, **122A**, **121B**, and **122B** instead of the external electrodes **21A**, **22A**, **21B**, and **22B**, respectively. The following description does not mention the common features shared between the inductor arrays **101** and **1**.

(55) In the illustrated embodiment, the external electrodes **121A**, **122A**, **121B**, **122B** are all provided on the second principal surface **10b** of the base body **10**. The shapes of the external electrodes **121A**, **122A**, **121B**, **122B** are not limited to those shown. For example, the external electrodes **121A** and **121B** may be provided on the base body **10** such that they are in contact with the second principal surface **10b** and the first side surface **10e**. The external electrodes **122A** and **122B** may be provided on the base body **10** such that they are in contact with the second principal surface **10b** and the second side surface **10f**.

(56) In the embodiment illustrated, the internal conductor **125A** is provided in the base body **10** so as to electrically connect between the external electrode **121A** and the external electrode **122A**. The internal conductor **125A** includes a first portion **125A1**, a second portion **125A2**, and a third portion **125A3**. The first portion **125A1** is connected to the external electrode **121A** at one end and extends in an angled direction with respect to the T axis, and the second portion **125A2** is connected to the external electrode **122A** at one end and extends in an angled direction with respect to the T axis. The third portion **125A3** extends in the W-axis direction and connects the other end of the first portion **125A1** with the other end of the second portion **125A2**.

(57) In the embodiment illustrated, the internal conductor **125B** is provided in the base body **10** so as to electrically connect between the external electrode **121B** and the external electrode **122B**, and has the same shape as the internal conductor **125A**. More specifically, the internal conductor **125B** includes a first portion **125B1**, a second portion **125B2**, and a third portion **125B3**. The first portion **125B1** is connected to the external electrode **121B** at one end and extends in an angled direction with respect to the T axis, and the second portion **125B2** is connected to the external electrode **122B** at one end and extends in an angled direction with respect to the T axis. The third portion **125B3** extends in the W-axis direction and connects the other end of the first portion **125B1** with the other end of the second portion **125B2**.

(58) The internal conductor **125A** extends linearly from the external electrode **121A** to the second external electrode **122A** in plan view (as viewed from the T axis). The internal conductor **125B** may extend linearly from the external electrode **121B** to the second external electrode **122B** in plan view (as viewed from the T axis). In this way, the internal conductors **125A** and **125B** have no parts facing each other in the base body **10** in plan view. Since the internal conductors **125A** and **125B** have no parts facing each other in the base body **10** in plan view, the insulation reliability (withstand voltage) can be increased without changing the volume resistivity of the base body **10**, compared with conventional inductors that have internal conductors with parts facing each other in plan view.

(59) The base body **10** includes an inter-conductor region **110A**. The inter-conductor region **110A** refers to the region of the base body **10** positioned between the internal conductor **125A** and the internal conductor **125B** and overlapping with both the internal conductor **125A** and the internal conductor **125B** as viewed from the reference axis direction along the reference axis **Ax1** (i.e., as viewed from the L-axis direction). The dimension of the section of the inter-conductor region **110A** in the reference axis direction along the reference axis **Ax1** (L-axis direction) is referred to as the first reference axis direction dimension **a11**, and the dimension of the section of the inter-conductor region **110A** in the orthogonal direction orthogonal to the reference axis **Ax1** (T-axis direction) is

referred to as the first orthogonal direction dimension **a12**. The section of the inter-conductor region **110A** refers to the section of the inter-conductor region **110A** cut along the plane extending through the reference axis **Ax1** and perpendicular to the bottom surface **10b**.

(60) The third portion **125A3** of the internal conductor **125A** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the second end surface **10d** of the base body **10** by the distances **a13A**, **a14A**, and **a15A**, respectively. The distances **a13A**, **a14A**, and **a15A** may be equal to one another. The third portion **125B3** of the internal conductor **125B** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the first end surface **10c** of the base body **10** by the distances **a13B**, **a14B**, and **a15B**, respectively. The distances **a13B**, **a14B**, and **a15B** may be equal to one another.

(61) In the inductor array **101**, the first aspect ratio of the inter-conductor region **110A** is defined as the ratio of the first orthogonal direction dimension **a12** to the first reference axis direction dimension **a11** (**a12/a11**). In one or more embodiments of the invention, the first aspect ratio of the inter-conductor region **110A** (**a12/a11**) is less than 1. Thus, the magnetic flux generated when the electric current flowing through the internal conductor **125A** varies is unlikely to reach the internal conductor **125B**, and therefore, the magnetic coupling between the inductors included in the inductor array **101** can be reduced.

(62) In one or more embodiments of the present invention, the first reference axis direction dimension **a11** of the inter-conductor region **110A** is less than double the shortest distance between the internal conductor **25A** and the surface of the base body **10** in the reference plane. Thus, the inductor array **101** can have a small dimension in the reference axis direction and thus have a small mounting area.

(63) The second aspect ratio of the internal conductor **125A** can be defined as the ratio of the dimension of the section of the third portion **125A3** of the internal conductor **125A** in the direction perpendicular to the reference axis direction to the dimension of the same section in the reference axis direction. Likewise, the second aspect ratio of the internal conductor **125B** can be defined as the ratio of the dimension of the section of the third portion **125B3** of the internal conductor **125B** in the direction perpendicular to the reference axis direction to the dimension of the same section in the reference axis direction. In one or more embodiments of the invention, both the second aspect ratio of the internal conductor **125A** and the second aspect ratio of the internal conductor **125B** are equal to or larger than the first aspect ratio of the inter-conductor region **110A** of the inductor array **101**.

(64) Next, an inductor array **201** according to one or more embodiments of the present invention will be described with reference to FIGS. 7 and 8. FIG. 7 is a perspective view of the inductor array **201**, and FIG. 8 is a sectional view schematically showing a section of the inductor array **201** cut along the plane perpendicular to the bottom surface **10b** of the base body **10** (i.e., the reference plane). The inductor array **201** is different from the inductor array **1** in that it includes internal conductors **225A** and **225B** instead of the internal conductors **25A** and **25B**, respectively. The following description does not mention the common features shared between the inductor arrays **201** and **1**.

(65) The internal conductor **225A** is wound spirally around a coil axis **AxA** extending along the T-axis direction, and the internal conductor **225B** is wound spirally around a coil axis **AxB** extending along the T-axis direction.

(66) The base body **10** includes an inter-conductor region **210A**. The inter-conductor region **210A** refers to the region of the base body **10** positioned between the internal conductor **225A** and the internal conductor **225B** and overlapping with both the internal conductor **225A** and the internal conductor **225B** as viewed from the reference axis direction along the reference axis **Ax1** (i.e., as viewed from the L-axis direction). The dimension of the section of the inter-conductor region **210A** in the reference axis direction along the reference axis **Ax1** (L-axis direction) is referred to as the first reference axis direction dimension **a21**, and the dimension of the section of the inter-conductor

region **210A** in the orthogonal direction orthogonal to the reference axis **Ax1** (T-axis direction) is referred to as the first orthogonal direction dimension **a22**. The section of the inter-conductor region **210A** refers to the section of the inter-conductor region **210A** cut along the plane extending through the reference axis **Ax1** and perpendicular to the bottom surface **10b**.

(67) The internal conductor **225A** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the second end surface **10d** of the base body **10** by the distances **a23A**, **a24A**, and **a25A**, respectively. The distances **a23A**, **a24A**, and **a25A** may be equal to one another. The internal conductor **225B** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the first end surface **10c** of the base body **10** by the distances **a23B**, **a24B**, and **a25B**, respectively. The distances **a23B**, **a24B**, and **a25B** may be equal to one another.

(68) In the inductor array **201**, the first aspect ratio of the inter-conductor region **210A** is defined as the ratio of the first orthogonal direction dimension **a22** to the first reference axis direction dimension **a21** ($a22/a21$). In one or more embodiments of the invention, the first aspect ratio of the inter-conductor region **210A** ($a22/a21$) is less than 1. Thus, the magnetic flux generated when the electric current flowing through the internal conductor **225A** varies is unlikely to reach the internal conductor **225B**, and therefore, the magnetic coupling between the inductors included in the inductor array **201** can be reduced.

(69) In one or more embodiments of the present invention, the first reference axis direction dimension **a21** of the inter-conductor region **210A** is less than double the shortest distance between the internal conductor **225A** and the surface of the base body **10** in the reference plane. Thus, the inductor array **201** can have a small dimension in the reference axis direction and thus have a small mounting area.

(70) Next, an inductor array **301** according to one or more embodiments of the present invention will be described with reference to FIGS. **9** and **10**. FIG. **9** is a perspective view of the inductor array **301**, and FIG. **10** is a sectional view schematically showing a section of the inductor array **301** cut along the plane perpendicular to the bottom surface **10b** of the base body **10** (i.e., the reference plane). The inductor array **301** is different from the inductor array **1** in that it includes internal conductors **325A** and **325B** instead of the internal conductors **25A** and **25B**, respectively. The following description does not mention the common features shared between the inductor arrays **301** and **1**.

(71) In the embodiment shown, the internal conductor **325A** includes winding patterns **326A1**, **326A2** extending in the circumferential direction around the reference axis **Ax1**. The winding patterns **326A1** and **326A2** are connected together through the via **VA**. The internal conductor **325B** includes winding patterns **326B1**, **326B2** extending in the circumferential direction around the reference axis **Ax1**. The winding patterns **326B1** and **326B2** are connected together through the via **VB**.

(72) The base body **10** includes an inter-conductor region **310A**. The inter-conductor region **310A** refers to the region of the base body **10** positioned between the internal conductor **325A** and the internal conductor **325B** and overlapping with both the internal conductor **325A** and the internal conductor **325B** as viewed from the reference axis direction along the reference axis **Ax1** (i.e., as viewed from the L-axis direction). The dimension of the section of the inter-conductor region **310A** in the reference axis direction along the reference axis **Ax1** (L-axis direction) is referred to as the first reference axis direction dimension **a31**, and the dimension of the section of the inter-conductor region **310A** in the orthogonal direction orthogonal to the reference axis **Ax1** (T-axis direction) is referred to as the first orthogonal direction dimension **a32**. The section of the inter-conductor region **310A** refers to the section of the inter-conductor region **310A** cut along the plane extending through the reference axis **Ax1** and perpendicular to the bottom surface **10b**.

(73) The internal conductor **325A** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the second end surface **10d** of the base body **10** by the distances **a33A**, **a34A**, and **a35A**, respectively. The distances **a33A**, **a34A**, and **a35A** may be equal to one another. The internal

conductor **325B** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the first end surface **10c** of the base body **10** by the distances **a33B**, **a34B**, and **a35B**, respectively. The distances **a33B**, **a34B**, and **a35B** may be equal to one another.

(74) In the inductor array **301**, the first aspect ratio of the inter-conductor region **310A** is defined as the ratio of the first orthogonal direction dimension **a32** to the first reference axis direction dimension **a31** ($a32/a31$). In one or more embodiments of the invention, the first aspect ratio of the inductor array **301** ($a32/a31$) is less than 1. Thus, the magnetic flux generated when the electric current flowing through the internal conductor **325A** varies is unlikely to reach the internal conductor **325B**, and therefore, the magnetic coupling between the inductors included in the inductor array **301** can be reduced.

(75) In one or more embodiments of the present invention, the first reference axis direction dimension **a31** of the inter-conductor region **310A** is less than double the shortest distance between the internal conductor **325A** and the surface of the base body **10** in the reference plane. Thus, the inductor array **301** can have a small dimension in the reference axis direction and thus have a small mounting area.

(76) The second aspect ratio of the internal conductor **325A** can be defined as the ratio of the dimension **b32** of the section of the internal conductor **325A** in the direction perpendicular to the reference axis direction to the dimension **b31** of the same section in the reference axis direction. In one or more embodiments of the invention, the second aspect ratio of the internal conductor **325A** is equal to or larger than the first aspect ratio of the inter-conductor region **310A**. Likewise, the second aspect ratio of the internal conductor **325B** can be defined as the ratio of the dimension of the section of the internal conductor **325B** in the direction perpendicular to the reference axis direction to the dimension of the same section in the reference axis direction. The second aspect ratio of the internal conductor **325B** is also equal to or larger than the first aspect ratio of the inter-conductor region **310A**.

(77) An inductor array **401** according to one or more embodiments of the invention will now be described with reference to FIG. **11**. FIG. **11** is a sectional view schematically showing a section of the inductor array **401** cut along the plane perpendicular to the bottom surface **10b** of the base body **10** (i.e., the reference plane). The inductor array **401** is different from the inductor array **1** in the arrangement of the internal conductors **25A** and **25B** in the base body **10**. The following description does not mention the common features shared between the inductor arrays **401** and **1**.

(78) As shown, the internal conductor **25A** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the second end surface **10d** of the base body **10** by the distances **a43A**, **a44A**, and **a45A**, respectively. The internal conductor **25A** is positioned closer to the top surface **10a** of the base body **10** than to the bottom surface **10b**. Therefore, the distance **a44A** is larger than the distance **a43A**.

(79) The internal conductor **25B** is spaced apart from the top surface **10a**, the bottom surface **10b**, and the first end surface **10c** of the base body **10** by the distances **a43B**, **a44B**, and **a45B**, respectively. The internal conductor **25B** is positioned closer to the bottom surface **10b** of the base body **10** than to the top surface **10a**. Therefore, the distance **a43B** is larger than the distance **a44B**. In addition, the distance **a43A** between the internal conductor **25A** and the top surface of the base body **10** is smaller than the distance **a43B** between the internal conductor **25B** and the top surface of the base body **10**.

(80) The base body **10** includes an inter-conductor region **410A**. The inter-conductor region **10A** refers to the region of the base body **10** positioned between the internal conductor **25A** and the internal conductor **25B** and overlapping with both the internal conductor **25A** and the internal conductor **25B** as viewed from the reference axis direction along the reference axis **Ax1** (i.e., as viewed from the L-axis direction). The dimension of the section of the inter-conductor region **410A** in the reference axis direction along the reference axis **Ax1** (L-axis direction) is referred to as the first reference axis direction dimension **a41**, and the dimension of the section of the inter-conductor

region **410A** in the orthogonal direction orthogonal to the reference axis **Ax1** (T-axis direction) is referred to as the first orthogonal direction dimension **a42**. The section of the inter-conductor region **410A** refers to the section of the inter-conductor region **410A** cut along the plane extending through the reference axis **Ax1** and perpendicular to the bottom surface **10b** (i.e., the reference plane). In the inductor array **1**, the first orthogonal direction dimension **a2** of the inter-conductor region **10A** is equal to the dimension **b2** of the internal conductor **25A** in the direction perpendicular to the reference axis direction. By contrast, in the inductor array **401**, the internal conductor **25B** is shifted by a shift width toward the negative side in the T-axis direction relative to the internal conductor **25A**, and therefore, the first orthogonal direction dimension **a42** of the inter-conductor region **410A** is smaller than the dimension **b2** of the internal conductor **25A** in the direction perpendicular to the reference axis direction. The shift width equals to **a43B-a43A**, and thus the first orthogonal direction dimension **a42** of the inter-conductor region **410A** is smaller than the dimension **b2** of the internal conductor **25A** in the direction perpendicular to the reference axis direction by **(a43B-a43A)**.

(81) In the inductor array **401**, the first aspect ratio of the inter-conductor region **410A** is defined as the ratio of the first orthogonal direction dimension **a42** to the first reference axis direction dimension **a41** (**a42/a41**). In one or more embodiments of the invention, the first aspect ratio of the inter-conductor region **410A** (**a42/a41**) is less than 1. Thus, the magnetic flux generated when the electric current flowing through the internal conductor **25A** varies is unlikely to reach the internal conductor **25B**, and therefore, the magnetic coupling between the inductors included in the inductor array **401** can be reduced.

(82) In one or more embodiments of the present invention, the first reference axis direction dimension **a41** of the inter-conductor region **410A** is less than double the shortest distance between the internal conductor **25A** and the surface of the base body **10** in the reference plane. Thus, the inductor array **401** can have a small dimension in the reference axis direction and thus have a small mounting area. In the inductor array **401**, the internal conductor **25A** is positioned closer to the top surface **10a** of the base body **10** than is the middle of the base body **10** in the T-axis direction. Therefore, the distance **a43A** between the internal conductor **25A** and the top surface **10a** of the base body **10** is smaller than the distance **a44A** between the internal conductor **25A** and the bottom surface **10b** of the base body **10**. The first reference axis direction dimension **a41** of the inter-conductor region **410A** is less than double the distance **a43A**, which is the smaller of the distances **a43A** and **a44A**. Therefore, as compared to the embodiments in which the internal conductor **25a** is positioned at the middle of the base body **10** in the T-axis direction, the distance between the internal conductor **25A** and the internal conductor **25B** can be smaller, and thus the inductor array can have a smaller dimension in the reference axis direction. In the inductor array **401**, the distance between the internal conductor **25A** and the internal conductor **25B** is less than double the distance **a43A**. However, since the internal conductor **25B** is shifted by the shift width from the internal conductor **25A** in the T-axis direction, the length of the magnetic path encircling both the internal conductor **25A** and the internal conductor **25B** is enlarged by the shift width. Therefore, in the inductor array **401**, the distance between the internal conductor **25A** and the internal conductor **25B** is small, but the internal conductor **25A** and the internal conductor **25B** are at different levels in the T-axis direction, and thus the magnetic coupling between the internal conductor **25A** and the internal conductor **25B** can be reduced.

(83) The Inventor made simulation to compare the ratio of the first aspect ratio to the second aspect ratio with the coupling coefficient for each of the inductor arrays **1**, **401**. For inductor array **1**, four types of inductor arrays were input to a simulator. These inductor arrays were denoted by sample numbers **S11** to **S14** and were each provided with values shown in Table 1 for the first reference axis direction dimension **a1** and the first orthogonal direction dimension **a2** of the inter-conductor region **10A** and the dimensions **b1**, **b2** of the internal conductors **25A**, **25B**. The simulator calculated the self-inductance of the internal conductor **25A** and the mutual inductance between the

internal conductors **25A**, **25B** for these four types of inductor arrays. The coupling coefficient k between the internal conductors **25A**, **25B** was calculated based on the self-inductance and the mutual inductance. Table 2 shows the self-inductance (L), the mutual inductance (M), and the coupling coefficient calculated for each of the inductor arrays. Table 1 also includes the first aspect ratio $AR1$, the second aspect ratio $AR2$, and the ratio $R1$ of the first aspect ratio to the second aspect ratio.

(84) TABLE-US-00001 TABLE 1 $AR2$ $R1$ $a1$ $a2$ $AR1$ $b1$ $b2$ ($=b2/$ ($=AR1/$ # [μm] [μm] ($=a2/a1$) [μm] [μm] $b1$) $AR2$) $S11$ 400 300 0.75 100 300 3.00 0.25 $S12$ 350 200 0.57 150 200 1.33 0.43 $S13$ 300 150 0.50 200 150 0.75 0.67 $S14$ 200 100 0.50 300 100 0.33 1.50

(85) TABLE-US-00002 TABLE 2 # L [nH] M [nH] $k = M/L$ $S11$ 9.43 0.65 0.069 $S12$ 11.00 0.88 0.080 $S13$ 11.13 1.02 0.092 $S14$ 10.00 1.26 0.126

(86) For inductor array **401**, eight types of inductor arrays were input to a simulator. These inductor arrays were denoted by sample numbers $S21$ to $S28$ and were each provided with values shown in Table 3 for the first reference axis direction dimension $a41$ and the first orthogonal direction dimension $a42$ of the inter-conductor region **10A** and the dimensions $b1$, $b2$ of the internal conductors **25A**, **25B**. The simulator calculated the self-inductance of the internal conductor **25A** and the mutual inductance between the internal conductors **25A**, **25B** for these eight types of inductor arrays. The coupling coefficient k between the internal conductors **25A**, **25B** was calculated based on the self-inductance and the mutual inductance. Table 4 shows the self-inductance (L), the mutual inductance (M), and the coupling coefficient calculated for each of the inductor arrays. Table 3 also includes the first aspect ratio $AR1$, the second aspect ratio $AR2$, the ratio $R1$ of the first aspect ratio to the second aspect ratio, and the shift width Z being the difference between the dimension $b2$ and the dimension $a2$. As shown in FIG. 11, the internal conductor **25B** is shifted in the T-axis direction relative to the internal conductor **25A**. The shift width Z represents the shift width by which the internal conductor **25B** is shifted relative to the internal conductor **25A**.

(87) TABLE-US-00003 TABLE 3 $AR2$ $R1$ Z $a41$ $a42$ $AR1$ $b1$ $b2$ ($=b2/$ ($=AR1/$ ($=b2 -$ # [μm] [μm] ($=a42/a41$) [μm] [μm] $b1$) $AR2$) $a42$) $S21$ 400 250 0.63 100 300 3.00 0.21 50 $S22$ 400 200 0.50 100 300 3.00 0.17 100 $S23$ 350 150 0.43 150 200 1.33 0.32 50 $S24$ 350 100 0.29 150 200 1.33 0.21 100 $S25$ 350 50 0.14 150 200 1.33 0.11 150 $S26$ 300 100 0.33 200 150 0.75 0.44 50 $S27$ 300 50 0.17 200 150 0.75 0.22 100 $S28$ 200 50 0.25 300 100 0.33 0.75 50

(88) TABLE-US-00004 TABLE 4 # L [nH] M [nH] $k = M/L$ $S21$ 9.42 0.60 0.064 $S22$ 8.47 0.53 0.063 $S23$ 11.00 0.83 0.075 $S24$ 11.00 0.67 0.061 $S25$ 10.44 0.61 0.058 $S26$ 11.13 0.97 0.087 $S27$ 11.13 0.81 0.073 $S28$ 9.71 1.03 0.106

(89) FIG. 12 is a graph showing results of simulating inductor characteristics for samples $S11$ to $S14$ and $S21$ to $S28$. In FIG. 12, the horizontal axis indicates the ratio $R1$ of the first aspect ratio $AR1$ to the second aspect ratio $AR2$, and the vertical axis indicates the coupling coefficient k . In FIG. 12, the plotted points $P11$ to $P14$ and $P21$ to $P28$ indicate the respective values of the coupling coefficient calculated in the above simulation for the samples $S11$ to $S14$ and $S21$ to $S28$, and the line $C1$ represents an approximate curve based on the points $P11$ to $P14$ and the $P21$ to $P28$.

(90) As shown in the graph of FIG. 12, the coupling coefficient is not higher than 0.2 for all the samples. This simulation result revealed the tendency of the coupling coefficient lowering as the ratio $R1$ of the first aspect ratio to the second aspect ratio is smaller. In particular, when the ratio $R1$ is smaller than 0.75, the coupling coefficient can be 0.1 or lower. Thus, when the dimensions $a1$, $a2$, $b1$, $b2$ are set such that the ratio $R1$ is smaller than 0.75, the coupling coefficient between the internal conductors **25A**, **25B** included in the inductor arrays **1**, **401** can be lower than 0.1.

(91) Next, a description is given of an example method of manufacturing the inductor array **1** according to one embodiment of the present invention. To describe the manufacturing method, FIG. 2 will be referred to as necessary. In one or more embodiments of the invention, the inductor array **1** is produced by a sheet lamination method in which magnetic sheets are stacked together. The first

step of the sheet lamination method for producing the inductor array **1** is to prepare the magnetic sheets. The magnetic sheets are, for example, made from a slurry obtained by mixing and kneading a resin and metal magnetic particles of a soft magnetic material. The slurry is molded into the magnetic sheets using a sheet molding machine such as a doctor blade sheet molding machine. The resin mixed and kneaded together with the metal magnetic particles may be, for example, a polyvinyl butyral (PVB) resin, an epoxy resin, or any other resin materials having an excellent insulation property.

(92) The magnetic sheets are cut into a predetermined shape. Next, a conductive paste is applied to the magnetic sheets cut into a predetermined shape by a known method such as screen printing, thereby forming a plurality of unfired conductor patterns that will later form the internal conductors **25A** and **25B** after firing. The conductive paste is made by mixing and kneading, for example, Ag, Cu, or alloys thereof and a resin.

(93) In the way described above, the magnetic sheets having the unfired conductor patterns formed thereon and the unfired vias formed therein are prepared, and a mother laminate is prepared by stacking together these magnetic sheets and magnetic sheets having no conductors therein or thereon. The magnetic sheets having no conductors formed therein or thereon can contribute to adjust the distance between the internal conductors **25A** and **25B**.

(94) Next, the mother laminate is diced using a cutter such as a dicing machine or a laser processing machine to obtain a chip laminate.

(95) Next, the chip laminate is subjected to heat treatment at a temperature of 600° C. to 850° C. for a duration of 20 to 120 minutes. This heat treatment degreases the chip laminate, and the magnetic sheets and the conductor paste are fired to obtain the base body **10** that includes the internal conductors **25A** and **25B** therein. If the magnetic sheets contain a thermosetting resin, the thermosetting resin may be cured by performing a heat treatment on the chip laminate at a lower temperature. This cured resin serves as the binder that binds together the metal magnetic particles contained in the magnetic sheets. The heat treatment at a lower temperature is performed at a temperature of 100° C. to 200° C. for a duration of approximately 20 to 120 minutes, for example.

(96) Following the heat treatment, a conductive paste is applied to the surface of the chip laminate (that is, the base body **10**) to form the external electrodes **21A**, **22A**, **21B** and **22B**. In the above-described manner, the inductor array **1** is obtained. The inductor arrays **101**, **201** and **301** can be made using the same manufacturing method as the inductor array **1**.

(97) The manufacturing method described above is susceptible of omitting a part of the steps, adding steps not explicitly referred to, and/or reordering the steps. A procedure subjected to such omission, addition, or reordering is also included in the scope of the present invention unless diverged from the purport of the present invention.

(98) The method of manufacturing the inductor array **1** is not limited to the method described above. The inductor array **1** may be produced by a lamination method other than the sheet lamination method (e.g., the printing lamination method), the thin film process, the compression molding process, or other known methods.

(99) The dimensions, materials, and arrangements of the constituent elements described herein are not limited to those explicitly described for the embodiments, and these constituent elements can be modified to have any dimensions, materials, and arrangements within the scope of the present invention. Furthermore, constituent elements not explicitly described herein can also be added to the described embodiments, and it is also possible to omit some of the constituent elements described for the embodiments.

(100) Constituent elements not explicitly described herein can also be added to the above-described embodiments, and it is also possible to omit some of the constituent elements described for the embodiments.

(101) The words “first,” “second,” and “third” used herein are added to distinguish constituent

elements but do not necessarily limit the numbers, orders, or contents of the constituent elements. The numbers added to distinguish the constituent elements should be construed in each context. The same numbers do not necessarily denote the same constituent elements among the contexts. The use of numbers to identify constituent elements does not prevent the constituent elements from performing the functions of the constituent elements identified by other numbers.

Claims

1. An inductor array comprising: a magnetic base body having a first surface, a second surface opposed to the first surface, and a third surface connecting between the first surface and the second surface; a plurality of internal conductors having a same shape and arranged within the magnetic base body along a reference axis extending through the first surface and the second surface; a plurality of first external electrodes provided on the magnetic base body so as to be in contact at least with the third surface, each of the plurality of first external electrodes being connected to one end of associated one of the plurality of internal conductors; and a plurality of second external electrodes provided on the magnetic base body so as to be in contact at least with the third surface, each of the plurality of second external electrodes being connected to the other end of associated one of the plurality of internal conductors, wherein the plurality of internal conductors include a first internal conductor and a second internal conductor disposed adjacent to the first internal conductor, and the magnetic base body includes an inter-conductor region disposed between the first internal conductor and the second internal conductor and overlapping with both the first internal conductor and the second internal conductor as viewed from a reference axis direction along the reference axis, wherein the inter-conductor region has a first section cut along a reference plane including the reference axis and perpendicular to the third surface, and a first reference axis direction dimension of the first section in the reference axis direction is less than double a shortest distance between the first internal conductor and a surface of the magnetic base body in the reference plane, wherein a first aspect ratio of the first section is less than 1, the first aspect ratio being a ratio of a first orthogonal direction dimension in an orthogonal direction orthogonal to the reference axis to the first reference axis direction dimension, and wherein the first internal conductor has a second section cut along the reference plane, and a second orthogonal direction dimension of the second section in the orthogonal direction is larger than the first orthogonal direction dimension.
2. The inductor array of claim 1, wherein the first internal conductor has a second section cut along the reference plane, and a second orthogonal direction dimension of the second section in the orthogonal direction is equal to the first orthogonal direction dimension.
3. The inductor array of claim 2, wherein the magnetic base body has a fourth surface opposed to the third surface, and wherein a distance between the first internal conductor and the fourth surface is equal to a distance between the second internal conductor and the fourth surface.
4. The inductor array of claim 3, wherein the first reference axis direction dimension is equal to or larger than the distance between the first internal conductor and the fourth surface.
5. The inductor array of claim 1, wherein the magnetic base body has a fourth surface opposed to the third surface, and wherein a distance between the first internal conductor and the fourth surface is smaller than a distance between the second internal conductor and the fourth surface.
6. The inductor array of claim 1, wherein the first internal conductor has a second section cut along the reference plane, and the first aspect ratio is smaller than a second aspect ratio of the second section, the second aspect ratio being a ratio of a second orthogonal direction dimension in the orthogonal direction to a second reference axis direction dimension in the reference axis direction.
7. The inductor array of claim 6, wherein the second aspect ratio is larger than 1.
8. The inductor array of claim 1, wherein a magnitude of a coupling coefficient representing magnetic coupling between the first internal conductor and the second internal conductor is less

than 0.2.

9. The inductor array of claim 8, wherein a magnitude of a coupling coefficient representing magnetic coupling between the first internal conductor and the second internal conductor is less than 0.1.

10. The inductor array of claim 1, wherein the magnetic base body has a relative magnetic permeability of 100 or less.

11. A circuit board comprising the inductor array of claim 1.

12. An electronic device comprising the circuit board of claim 11.
