

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12407306

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Blin; Guillaume Alexandre et al.

Radio frequency front end with integrated channel matching calibration

Abstract

Radio frequency (RF) front ends with integrated channel matching calibration are provided herein. In one aspect, a front end system includes: a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of a plurality of antennas, and each of the front end amplification chains includes an amplifier configured to receive a bias current and amplify the corresponding radio frequency signal based on the bias current, a control circuit configured to generate each of the bias currents, and a multiplexor configured to receive the bias currents and provide the bias currents to the corresponding amplifiers.

Inventors: Blin; Guillaume Alexandre (Carlisle, MA), Liang; Bang Li (Ottawa, CA), Obkircher; Thomas (Santa Ana, CA)

Applicant: Skyworks Solutions, Inc. (Irvine, CA)

Family ID: 85153139

Assignee: Skyworks Solutions, Inc. (Irvine, CA)

Appl. No.: 17/817453

Filed: August 04, 2022

Prior Publication Data

Document Identifier

US 20230038733 A1

Publication Date

Feb. 09, 2023

Related U.S. Application Data

us-provisional-application US 63203913 20210804

Publication Classification

Int. Cl.: H03F3/19 (20060101); H03G3/30 (20060101); H04B1/40 (20150101)

U.S. Cl.:

CPC H03F3/19 (20130101); H03G3/3036 (20130101); H04B1/40 (20130101);
H03F2200/451 (20130101); H03G2201/103 (20130101); H03G2201/307 (20130101)

Field of Classification Search

CPC: H03F (3/189); H03F (3/19); H03F (3/191); H03F (3/195); H03F (2200/451); H03G
(3/30); H03G (3/3036); H03G (3/3042); H03G (2201/00); H03G (2201/30); H03G
(2201/103); H03G (2201/307); H04B (1/40); H04B (1/06); H04B (1/16); H04B (1/1607);
H04B (2001/0408); H04B (2001/0416)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6798286	12/2003	Dauphinee	348/E7.052	H01L 22/20
7068100	12/2005	Dauphinee	348/E7.052	G01R 31/31723
7183845	12/2006	Dauphinee	348/E7.052	H04N 7/102
7260377	12/2006	Burns	330/276	G01R 31/2607
7471941	12/2007	Dauphinee	455/341	H04N 7/102
7501888	12/2008	Dauphinee	330/129	H03G 3/3052
7634244	12/2008	Burns	455/340	H04B 1/109
7791412	12/2009	Dauphinee	330/129	G01R 31/2607
7969241	12/2010	Dauphinee	330/129	G01R 31/2607
8094033	12/2011	Dauphinee	324/105	H03G 3/3036
8126094	12/2011	Komaili	375/345	H04L 27/3809
8212593	12/2011	Obkircher	327/119	H03L 7/0814
8374297	12/2012	Komaili	327/551	H04L 27/3863
8417836	12/2012	Obkircher	710/3	G06F 13/4291
8437720	12/2012	Burns	455/340	H03G 3/3036
8525590	12/2012	Joly	330/285	H03F 3/72
8698565	12/2013	Obkircher	331/34	H03L 7/099
8918139	12/2013	Noellert	455/313	H03F 3/24
9077412	12/2014	Chang	N/A	G01S 7/285
9362870	12/2015	Lam	N/A	H03F 1/0266
9596120	12/2016	Yamanouchi	N/A	H04L 27/367
9608576	12/2016	Lam	N/A	H03F 1/0266
9621119	12/2016	Lehtola	N/A	H03F 3/211
9788187	12/2016	Wang	N/A	H04W 8/005
9813169	12/2016	Einzinger	N/A	H04W 52/08
9893687	12/2017	Lehtola	N/A	H03F 1/0261
10003308	12/2017	Lam	N/A	H03F 1/34
10003374	12/2017	Lee	N/A	H03F 3/245
10229902	12/2018	Zhu	N/A	H10D 64/257

10270399	12/2018	Wang	N/A	H03F 1/26
10333470	12/2018	Balteanu	N/A	H03F 1/0244
10396737	12/2018	Domino	N/A	H03F 3/195
10437774	12/2018	Obkircher	N/A	G06F 13/4291
10554188	12/2019	Bergsma	N/A	H03F 3/45475
10560139	12/2019	Brunel	N/A	H04B 1/44
10560202	12/2019	Bergsma	N/A	H04B 1/40
10749562	12/2019	Bai	N/A	H04B 1/44
10812030	12/2019	Ye	N/A	H03F 3/45179
10880116	12/2019	Zhou	N/A	H04L 12/413
10963418	12/2020	Obkircher et al.	N/A	N/A
10998862	12/2020	Liang	N/A	H03K 3/356182
11075779	12/2020	Yu	N/A	H03K 19/0185
11115015	12/2020	Zhou	N/A	H03K 5/24
11245552	12/2021	Brunel	N/A	H04L 5/0094
11256281	12/2021	Liang	N/A	G05F 1/595
11309841	12/2021	Beppu	N/A	H03F 1/0205
11327517	12/2021	Liang	N/A	G05F 1/595
11368179	12/2021	Pehlke	N/A	H04B 1/0057
11392159	12/2021	Liang	N/A	G05F 3/262
11601247	12/2022	Brunel	N/A	H04L 27/2605
11614760	12/2022	Liang	323/280	G05F 3/30
11619958	12/2022	Liang	323/273	G05F 1/468
11770228	12/2022	Brunel	370/329	H04L 27/26025
11848654	12/2022	Ashworth	N/A	H04W 16/26
11956108	12/2023	Drogi	N/A	H04B 7/0604
11990968	12/2023	Chen	N/A	H04B 7/068
12063133	12/2023	Drogi	N/A	H04L 5/0048
12074576	12/2023	Lehtola	N/A	H03G 3/3042
2004/0075494	12/2003	Klomsdorf	330/129	H03F 1/0261
2004/0104771	12/2003	Dauphinee	348/E7.052	H01L 22/20
2004/0105033	12/2003	Dauphinee	348/707	H03G 3/3036
2004/0189382	12/2003	Dauphinee	348/E7.052	G01R 31/31723
2005/0130617	12/2004	Burns	348/E7.052	H01L 22/20
2005/0200406	12/2004	Dauphinee	348/E7.052	H04N 7/102
2005/0208910	12/2004	Burns	348/678	H04N 7/102
2006/0291588	12/2005	Irie	375/297	H04L 27/362
2007/0004372	12/2006	Adams	455/333	H03F 1/0261
2007/0159244	12/2006	Dauphinee	330/84	G01R 31/30
2009/0040059	12/2008	Dauphinee	340/653	H04N 7/102
2009/0066414	12/2008	Dauphinee	330/129	H04N 7/102
2010/0073572	12/2009	Burns	348/707	H03G 3/3036
2010/0277235	12/2009	Dauphinee	330/254	G01R 31/31723
2012/0161878	12/2011	Joly	330/296	H03F 1/0277
2013/0190038	12/2012	Noellert	455/571	H03F 3/195
2014/0027638	12/2013	Chang	250/338.1	G01S 7/285
2016/0248379	12/2015	Lehtola	N/A	H03F 3/195
2016/0322947	12/2015	Ishihara	N/A	H03F 1/34
2017/0149512	12/2016	Einzinger	N/A	H04W 52/08
2017/0194919	12/2016	Lehtola	N/A	H03F 3/195

2017/0214372	12/2016	Muralidharan	N/A	H03F 3/72
2017/0237403	12/2016	Wang	330/288	H03F 1/56
2018/0138877	12/2017	Bergsma	N/A	H03G 3/20
2020/0059202	12/2019	Jo	N/A	H03F 1/305
2020/0266767	12/2019	Wu	N/A	H03F 3/72
2020/0272182	12/2019	Liang	N/A	G05F 1/468
2020/0272183	12/2019	Liang	N/A	G05F 1/575
2020/0295709	12/2019	Beppu	N/A	H03F 3/19
2021/0132642	12/2020	Liang	N/A	H03K 19/0016
2021/0210415	12/2020	Liu	N/A	H03F 3/195
2021/0211107	12/2020	Liu	N/A	H03F 3/245
2021/0218433	12/2020	Liang	N/A	H03F 3/68
2022/0060202	12/2021	Nisbet	N/A	H03F 3/45197
2022/0254812	12/2021	Wang	N/A	H03F 3/213
2022/0271720	12/2021	Shimamoto	N/A	H03F 1/0261
2022/0352888	12/2021	Blin	N/A	H03K 17/6874
2022/0385249	12/2021	Brunel	N/A	H03F 3/211
2022/0385314	12/2021	Kogure	N/A	H03F 3/245
2022/0413533	12/2021	Liang	N/A	G05F 1/575
2023/0012894	12/2022	Liang	N/A	H03F 1/223
2023/0014555	12/2022	Liang	N/A	H03F 3/245
2023/0038733	12/2022	Blin	N/A	H03F 3/245
2023/0100609	12/2022	Liang	713/320	G06F 1/26
2023/0114964	12/2022	Blin	327/526	H03F 3/245
2023/0208044	12/2022	Brunel	370/297	H01Q 5/42
2023/0216449	12/2022	Liang	330/296	H03F 3/19
2023/0216527	12/2022	Raghavan	370/297	H04B 1/0057
2023/0246547	12/2022	Zhou	327/536	H03F 3/191
2023/0253991	12/2022	Blin	455/552.1	H04B 1/1607
2024/0056040	12/2023	Sakurai	N/A	H03F 1/0277
2024/0128936	12/2023	Tahara	N/A	H03F 3/19
2024/0429871	12/2023	Tahara	N/A	H03F 1/565
2024/0429879	12/2023	De Falco	N/A	H03F 1/0266

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2603583	12/2021	GB	N/A

Primary Examiner: Perez; James M

Attorney, Agent or Firm: Knobbe, Martens, Olson & Bear, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S)

(1) Any and all applications for which a foreign or domestic priority claim is identified in the Application Data Sheet as filed with the present application are hereby incorporated by reference under 37 CFR 1.57.

BACKGROUND

Field

(2) Aspects of this disclosure relate to radio frequency (RF) communication systems, and in particular, multi-channel RF communication systems.

Description of the Related Technology

(3) RF communication systems typically include an RF front end which couples transmit and receive paths between a baseband processor and one or more antennas. Such RF communication systems can be used in a variety of different wireless communication modes, including beamforming in which the gain and/or phase of parallel front end communication chains are adjusted to focus a transmit or receive beam at a desired beam angle. The amplifiers used in the front end communication chains may be adjusted for beamforming or other purposes (e.g., such as temperature variations) to improve RF communication.

SUMMARY

(4) The systems, methods and devices of this disclosure each have several innovative aspects, no single one of which is solely responsible for the desirable attributes disclosed herein.

(5) In one aspect, there is provided a front end system comprising: a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of a plurality of antennas, and each of the front end amplification chains further including an amplifier configured to receive a bias current and amplify the corresponding radio frequency signal; a control circuit configured to generate each of the bias currents; and a multiplexor configured to receive the bias currents and provide the bias currents to the corresponding amplifiers.

(6) In some embodiments, the antennas, the front end amplification chains, the control circuit, and the multiplexor are all formed on a single die.

(7) In some embodiments, each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a millimeter wave spectrum or a TeraHertz spectrum.

(8) In some embodiments, each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a 5G spectrum.

(9) In some embodiments, the control circuit includes a current digital-to-analog converter configured to receive a digital reference current value and generate the bias current based on the digital reference current value.

(10) In some embodiments, the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and a temperature coefficient and generate the digital reference current value based on the trim bias current value and the temperature coefficient.

(11) In some embodiments, the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and generate the digital reference current value based on the trim bias current value.

(12) In some embodiments, each of the front end amplification chains comprises a plurality of amplification stages, wherein each of the bias currents corresponding to one of the plurality of amplification stages, and wherein the multiplexor comprises a plurality of multiplexors, each of the plurality of multiplexors configured to receive the bias currents for a corresponding one of the amplification stages and provide the bias currents to the corresponding amplification stages of each of the front end amplification chains.

(13) In some embodiments, the control circuit is further configured to generate the bias current based on a temperature coefficient and a trim bias current.

(14) In some embodiments, each of the front end amplification chains includes an attenuator or a programmable gain stage configured to adjust the gain of the corresponding front end amplification chain.

(15) In another aspect, there is provided a radio frequency device comprising: a plurality of antennas; and a front end system including a plurality of front end amplification chains including

transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of the plurality of antennas, and each of the front end amplification chains includes an amplifier configured to receive a bias current and amplify the corresponding radio frequency signal, a control circuit configured to generate each of the bias currents, and a multiplexor configured to receive the bias currents and provide the bias currents to the corresponding amplifiers.

(16) In some embodiments, the antennas, the front end amplification chains, the control circuit, and the multiplexor are all formed on a single die.

(17) In some embodiments, each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a millimeter wave spectrum.

(18) In some embodiments, each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a 5G spectrum.

(19) In some embodiments, the control circuit includes a current digital-to-analog converter configured to receive a digital reference current value and generate the bias current based on the digital reference current value.

(20) In some embodiments, the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and a temperature coefficient and generate the digital reference current value based on the trim bias current value and the temperature coefficient.

(21) In some embodiments, each of the front end amplification chains comprises a plurality of amplification stages, wherein each of the bias currents corresponding to one of the plurality of amplification stages, and wherein the multiplexor comprises a plurality of multiplexors, each of the plurality of multiplexors configured to receive the bias currents for a corresponding one of the amplification stages and provide the bias currents to the corresponding amplification stages of each of the front end amplification chains.

(22) In some embodiments, the control circuit is further configured to generate the bias current based on a temperature coefficient and a trim bias current.

(23) In some embodiments, the radio frequency device comprises one of the following: a telecommunications device, a telecommunications satellite, a base station, a mobile device, and a radar device.

(24) In yet another aspect, there is provided a method comprising: generating, at a control circuit, a bias current; receiving the bias current at a multiplexor, the multiplexor and control circuit formed on a front end system including a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of a plurality of antennas, and each of the front end amplification chains includes an amplifier configured to receive the bias current and amplify the corresponding radio frequency signal; and providing, by the multiplexor, the bias current to the amplifier of a selected one of the plurality of front end amplification chains.

(25) In some embodiments, the antennas, the front end amplification chains, the control circuit, and the multiplexor are all formed on a single die.

(26) In some embodiments, the control circuit includes a current digital-to-analog converter configured to receive a digital reference current value and generate the bias current based on the digital reference current value.

(27) In some embodiments, the method comprises: receiving, at a shared bias generator circuit of the control circuit, a trim bias current value and a temperature coefficient; and generating, at the shared bias generator circuit, the digital reference current value based on the trim bias current value and the temperature coefficient.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic diagram of one example of a communication network.
- (2) FIG. 2A is a schematic diagram of one example of a communication system that operates with beamforming.
- (3) FIG. 2B is a schematic diagram of one example of beamforming to provide a transmit beam.
- (4) FIG. 2C is a schematic diagram of one example of beamforming to provide a receive beam.
- (5) FIG. 3A is a perspective view of one embodiment of a module that operates with beamforming.
- (6) FIG. 3B is a cross-section of the module of FIG. 3A taken along the lines 3B-3B.
- (7) FIG. 4 is a schematic diagram of one embodiment of a mobile device.
- (8) FIG. 5A is a schematic diagram of a power amplifier system according to one embodiment.
- (9) FIG. 5B is a schematic diagram of a power amplifier system according to another embodiment.
- (10) FIG. 6 is a diagram of an RF system including a plurality of antennas and a plurality of RF front ends in accordance with aspects of this disclosure.
- (11) FIG. 7 is a schematic diagram of an RF front end system including a plurality of amplification chains in accordance with aspects of this disclosure.
- (12) FIG. 8 is a schematic diagram of a front end amplification chain in accordance with aspects of this disclosure.
- (13) FIGS. 9A and 9B are schematic diagrams illustrating different embodiments of RF front ends including amplification chains in accordance with aspects of this disclosure.
- (14) FIGS. 10A and 10B are schematic diagrams illustrating RF front ends in accordance with aspects of this disclosure.
- (15) FIG. 11 is a schematic diagram illustrating another RF front end in accordance with aspects of this disclosure.

DETAILED DESCRIPTION

(16) The following detailed description of certain embodiments presents various descriptions of specific embodiments. However, the innovations described herein can be embodied in a multitude of different ways, for example, as defined and covered by the claims. In this description, reference is made to the drawings where like reference numerals can indicate identical or functionally similar elements. It will be understood that elements illustrated in the figures are not necessarily drawn to scale. Moreover, it will be understood that certain embodiments can include more elements than illustrated in a drawing and/or a subset of the elements illustrated in a drawing. Further, some embodiments can incorporate any suitable combination of features from two or more drawings.

Example 5G Communication Network

- (17) The International Telecommunication Union (ITU) is a specialized agency of the United Nations (UN) responsible for global issues concerning information and communication technologies, including the shared global use of radio spectrum.
- (18) The 3rd Generation Partnership Project (3GPP) is a collaboration between groups of telecommunications standard bodies across the world, such as the Association of Radio Industries and Businesses (ARIB), the Telecommunications Technology Committee (TTC), the China Communications Standards Association (CCSA), the Alliance for Telecommunications Industry Solutions (ATIS), the Telecommunications Technology Association (TTA), the European Telecommunications Standards Institute (ETSI), and the Telecommunications Standards Development Society, India (TSDSI).
- (19) Working within the scope of the ITU, 3GPP develops and maintains technical specifications for a variety of mobile communication technologies, including, for example, second generation (2G) technology (for instance, Global System for Mobile Communications (GSM) and Enhanced Data Rates for GSM Evolution (EDGE)), third generation (3G) technology (for instance, Universal Mobile Telecommunications System (UMTS) and High Speed Packet Access (HSPA)), and fourth generation (4G) technology (for instance, Long Term Evolution (LTE) and LTE-Advanced).

(20) The technical specifications controlled by 3GPP can be expanded and revised by specification releases, which can span multiple years and specify a breadth of new features and evolutions.

(21) In one example, 3GPP introduced carrier aggregation (CA) for LTE in Release 10. Although initially introduced with two downlink carriers, 3GPP expanded carrier aggregation in Release 14 to include up to five downlink carriers and up to three uplink carriers. Other examples of new features and evolutions provided by 3GPP releases include, but are not limited to, License Assisted Access (LAA), enhanced LAA (eLAA), Narrowband Internet of things (NB-IOT), Vehicle-to-Everything (V2X), and High Power User Equipment (HPUE).

(22) 3GPP introduced Phase 1 of fifth generation (5G) technology in Release 15, and plans to introduce Phase 2 of 5G technology in Release 16 (targeted for 2020). Subsequent 3GPP releases will further evolve and expand 5G technology. 5G technology is also referred to herein as 5G New Radio (NR).

(23) 5G NR supports or plans to support a variety of features, such as communications over millimeter wave spectrum, beamforming capability, high spectral efficiency waveforms, low latency communications, multiple radio numerology, and/or non-orthogonal multiple access (NOMA). Although such RF functionalities offer flexibility to networks and enhance user data rates, supporting such features can pose a number of technical challenges.

(24) The teachings herein are applicable to a wide variety of communication systems, including, but not limited to, communication systems using advanced cellular technologies, such as LTE-Advanced, LTE-Advanced Pro, and/or 5G NR.

(25) FIG. 1 is a schematic diagram of one example of a communication network **10**. The communication network **10** includes a macro cell base station **1**, a small cell base station **3**, and various examples of user equipment (UE), including a first mobile device **2a**, a wireless-connected car **2b**, a laptop **2c**, a stationary wireless device **2d**, a wireless-connected train **2e**, a second mobile device **2f**, and a third mobile device **2g**.

(26) Although specific examples of base stations and user equipment are illustrated in FIG. 1, a communication network can include base stations and user equipment of a wide variety of types and/or numbers.

(27) For instance, in the example shown, the communication network **10** includes the macro cell base station **1** and the small cell base station **3**. The small cell base station **3** can operate with relatively lower power, shorter range, and/or with fewer concurrent users relative to the macro cell base station **1**. The small cell base station **3** can also be referred to as a femtocell, a picocell, or a microcell. Although the communication network **10** is illustrated as including two base stations, the communication network **10** can be implemented to include more or fewer base stations and/or base stations of other types.

(28) Although various examples of user equipment are shown, the teachings herein are applicable to a wide variety of user equipment, including, but not limited to, mobile phones, tablets, laptops, IoT devices, wearable electronics, customer premises equipment (CPE), wireless-connected vehicles, wireless relays, and/or a wide variety of other communication devices. Furthermore, user equipment includes not only currently available communication devices that operate in a cellular network, but also subsequently developed communication devices that will be readily implementable with the inventive systems, processes, methods, and devices as described and claimed herein.

(29) The illustrated communication network **10** of FIG. 1 supports communications using a variety of cellular technologies, including, for example, 4G LTE and 5G NR. In certain implementations, the communication network **10** is further adapted to provide a wireless local area network (WLAN), such as WiFi. Although various examples of communication technologies have been provided, the communication network **10** can be adapted to support a wide variety of communication technologies.

(30) Various communication links of the communication network **10** have been depicted in FIG. 1.

The communication links can be duplexed in a wide variety of ways, including, for example, using frequency-division duplexing (FDD) and/or time-division duplexing (TDD). FDD is a type of radio frequency communications that uses different frequencies for transmitting and receiving signals. FDD can provide a number of advantages, such as high data rates and low latency. In contrast, TDD is a type of radio frequency communications that uses about the same frequency for transmitting and receiving signals, and in which transmit and receive communications are switched in time. TDD can provide a number of advantages, such as efficient use of spectrum and variable allocation of throughput between transmit and receive directions.

(31) In certain implementations, user equipment can communicate with a base station using one or more of 4G LTE, 5G NR, and WiFi technologies. In certain implementations, enhanced license assisted access (eLAA) is used to aggregate one or more licensed frequency carriers (for instance, licensed 4G LTE and/or 5G NR frequencies), with one or more unlicensed carriers (for instance, unlicensed WiFi frequencies).

(32) As shown in FIG. 1, the communication links include not only communication links between UE and base stations, but also UE to UE communications and base station to base station communications. For example, the communication network **10** can be implemented to support self-fronthaul and/or self-backhaul (for instance, as between mobile device **2g** and mobile device **2f**).

(33) The communication links can operate over a wide variety of frequencies. In certain implementations, communications are supported using 5G NR technology over one or more frequency bands that are less than 6 Gigahertz (GHz) and/or over one or more frequency bands that are greater than 6 GHz. For example, the communication links can serve Frequency Range 1 (FR1), Frequency Range 2 (FR2), or a combination thereof. In one embodiment, one or more of the mobile devices support a HPUE power class specification.

(34) In certain implementations, a base station and/or user equipment communicates using beamforming. For example, beamforming can be used to focus signal strength to overcome path losses, such as high loss associated with communicating over high signal frequencies. In certain embodiments, user equipment, such as one or more mobile phones, communicate using beamforming on millimeter wave frequency bands in the range of 30 GHz to 300 GHz and/or upper centimeter wave frequencies in the range of 6 GHz to 30 GHz, or more particularly, 24 GHz to 30 GHz.

(35) Different users of the communication network **10** can share available network resources, such as available frequency spectrum, in a wide variety of ways.

(36) In one example, frequency division multiple access (FDMA) is used to divide a frequency band into multiple frequency carriers. Additionally, one or more carriers are allocated to a particular user. Examples of FDMA include, but are not limited to, single carrier FDMA (SC-FDMA) and orthogonal FDMA (OFDMA). OFDMA is a multicarrier technology that subdivides the available bandwidth into multiple mutually orthogonal narrowband subcarriers, which can be separately assigned to different users.

(37) Other examples of shared access include, but are not limited to, time division multiple access (TDMA) in which a user is allocated particular time slots for using a frequency resource, code division multiple access (CDMA) in which a frequency resource is shared amongst different users by assigning each user a unique code, space-divisional multiple access (SDMA) in which beamforming is used to provide shared access by spatial division, and non-orthogonal multiple access (NOMA) in which the power domain is used for multiple access. For example, NOMA can be used to serve multiple users at the same frequency, time, and/or code, but with different power levels.

(38) Enhanced mobile broadband (eMBB) refers to technology for growing system capacity of LTE networks. For example, eMBB can refer to communications with a peak data rate of at least 10 Gbps and a minimum of 100 Mbps for each user. Ultra-reliable low latency communications (uRLLC) refers to technology for communication with very low latency, for instance, less than 2

milliseconds. uRLLC can be used for mission-critical communications such as for autonomous driving and/or remote surgery applications. Massive machine-type communications (mMTC) refers to low cost and low data rate communications associated with wireless connections to everyday objects, such as those associated with Internet of Things (IoT) applications.

(39) The communication network **10** of FIG. **1** can be used to support a wide variety of advanced communication features, including, but not limited to, eMBB, uRLLC, and/or mMTC.

(40) Example Beamforming Systems

(41) FIG. **2A** is a schematic diagram of one example of a communication system **110** that operates with beamforming. The communication system **110** includes a transceiver **105**, signal conditioning circuits **104a1**, **104a2** . . . **104an**, **104b1**, **104b2** . . . **104bn**, **104m1**, **104m2** . . . **104mn**, and an antenna array **102** that includes antenna elements **103a1**, **103a2** . . . **103an**, **103b1**, **103b2** . . . **103bn**, **103m1**, **103m2** . . . **103mn**.

(42) Communications systems that communicate using millimeter wave carriers (for instance, 30 GHz to 300 GHz), centimeter wave carriers (for instance, 3 GHz to 30 GHz), and/or other frequency carriers can employ an antenna array to provide beam formation and directivity for transmission and/or reception of signals.

(43) For example, in the illustrated embodiment, the communication system **110** includes an array **102** of $m \times n$ antenna elements, which are each controlled by a separate signal conditioning circuit, in this embodiment. As indicated by the ellipses, the communication system **110** can be implemented with any suitable number of antenna elements and signal conditioning circuits.

(44) With respect to signal transmission, the signal conditioning circuits can provide transmit signals to the antenna array **102** such that signals radiated from the antenna elements combine using constructive and destructive interference to generate an aggregate transmit signal exhibiting beam-like qualities with more signal strength propagating in a given direction away from the antenna array **102**.

(45) In the context of signal reception, the signal conditioning circuits process the received signals (for instance, by separately controlling received signal phases) such that more signal energy is received when the signal is arriving at the antenna array **102** from a particular direction.

Accordingly, the communication system **110** also provides directivity for reception of signals.

(46) The relative concentration of signal energy into a transmit beam or a receive beam can be enhanced by increasing the size of the array. For example, with more signal energy focused into a transmit beam, the signal is able to propagate for a longer range while providing sufficient signal level for RF communications. For instance, a signal with a large proportion of signal energy focused into the transmit beam can exhibit high effective isotropic radiated power (EIRP).

(47) In the illustrated embodiment, the transceiver **105** provides transmit signals to the signal conditioning circuits and processes signals received from the signal conditioning circuits. As shown in FIG. **2A**, the transceiver **105** generates control signals for the signal conditioning circuits. The control signals can be used for a variety of functions, such as controlling the gain and phase of transmitted and/or received signals to control beamforming.

(48) FIG. **2B** is a schematic diagram of one example of beamforming to provide a transmit beam. FIG. **2B** illustrates a portion of a communication system including a first signal conditioning circuit **114a**, a second signal conditioning circuit **114b**, a first antenna element **113a**, and a second antenna element **113b**.

(49) Although illustrated as included two antenna elements and two signal conditioning circuits, a communication system can include additional antenna elements and/or signal conditioning circuits. For example, FIG. **2B** illustrates one embodiment of a portion of the communication system **110** of FIG. **2A**.

(50) The first signal conditioning circuit **114a** includes a first phase shifter **130a**, a first power amplifier **131a**, a first low noise amplifier (LNA) **132a**, and switches for controlling selection of the power amplifier **131a** or LNA **132a**. Additionally, the second signal conditioning circuit **114b**

includes a second phase shifter **130b**, a second power amplifier **131b**, a second LNA **132b**, and switches for controlling selection of the power amplifier **131b** or LNA **132b**.

(51) Although one embodiment of signal conditioning circuits is shown, other implementations of signal conditioning circuits are possible. For instance, in one example, a signal conditioning circuit includes one or more band filters, duplexers, and/or other components.

(52) In the illustrated embodiment, the first antenna element **113a** and the second antenna element **113b** are separated by a distance d . Additionally, FIG. 2B has been annotated with an angle θ , which in this example has a value of about 90° when the transmit beam direction is substantially perpendicular to a plane of the antenna array and a value of about 0° when the transmit beam direction is substantially parallel to the plane of the antenna array.

(53) By controlling the relative phase of the transmit signals provided to the antenna elements **113a**, **113b**, a desired transmit beam angle θ can be achieved. For example, when the first phase shifter **130a** has a reference value of 0° , the second phase shifter **130b** can be controlled to provide a phase shift of about $-2\pi f(d/v)\cos \theta$ radians, where f is the fundamental frequency of the transmit signal, d is the distance between the antenna elements, v is the velocity of the radiated wave, and π is the mathematic constant pi.

(54) In certain implementations, the distance d is implemented to be about $\frac{1}{2}\lambda$, where λ is the wavelength of the fundamental component of the transmit signal. In such implementations, the second phase shifter **130b** can be controlled to provide a phase shift of about $-\pi \cos \theta$ radians to achieve a transmit beam angle θ .

(55) Accordingly, the relative phase of the phase shifters **130a**, **130b** can be controlled to provide transmit beamforming. In certain implementations, a baseband processor and/or a transceiver (for example, the transceiver **105** of FIG. 2A) controls phase values of one or more phase shifters and gain values of one or more controllable amplifiers to control beamforming.

(56) FIG. 2C is a schematic diagram of one example of beamforming to provide a receive beam. FIG. 2C is similar to FIG. 2B, except that FIG. 2C illustrates beamforming in the context of a receive beam rather than a transmit beam.

(57) As shown in FIG. 2C, a relative phase difference between the first phase shifter **130a** and the second phase shifter **130b** can be selected to about equal to $-2\pi f(d/v)\cos \theta$ radians to achieve a desired receive beam angle θ . In implementations in which the distance d corresponds to about $\frac{1}{2}\lambda$, the phase difference can be selected to about equal to $-\pi \cos \theta$ radians to achieve a receive beam angle θ .

(58) Although various equations for phase values to provide beamforming have been provided, other phase selection values are possible, such as phase values selected based on implementation of an antenna array, implementation of signal conditioning circuits, and/or a radio environment.

(59) FIG. 3A is a perspective view of one embodiment of a module **140** that operates with beamforming. FIG. 3B is a cross-section of the module **140** of FIG. 3A taken along the lines 3B-3B.

(60) The module **140** includes a laminated substrate or laminate **141**, a semiconductor die or IC **142**, surface mount components **143**, and an antenna array including patch antenna elements **151-166**.

(61) Although one embodiment of a module is shown in FIGS. 3A and 3B, the teachings herein are applicable to modules implemented in a wide variety of ways. For example, a module can include a different arrangement of and/or number of antenna elements, dies, and/or surface mount components. Additionally, the module **140** can include additional structures and components including, but not limited to, encapsulation structures, shielding structures, and/or wirebonds.

(62) In the illustrated embodiment, the antenna elements **151-166** are formed on a first surface of the laminate **141**, and can be used to transmit and/or receive signals. Although the illustrated antenna elements **151-166** are rectangular, the antenna elements **151-166** can be shaped in other ways. Additionally, although a 4×4 array of antenna elements is shown, more or fewer antenna

elements can be provided. Moreover, antenna elements can be arrayed in other patterns or configurations. Furthermore, in another embodiment, multiple antenna arrays are provided, such as separate antenna arrays for transmit and receive and/or multiple antenna arrays for MIMO and/or switched diversity.

(63) In certain implementations, the antenna elements **151-166** are implemented as patch antennas. A patch antenna can include a planar antenna element positioned over a ground plane. A patch antenna can have a relatively thin profile and exhibit robust mechanical strength. In certain configurations, the antenna elements **151-166** are implemented as patch antennas with planar antenna elements formed on the first surface of the laminate **141** and the ground plane formed using an internal conductive layer of the laminate **141**.

(64) Although an example with patch antennas is shown, a module can include any suitable antenna elements, including, but not limited to, patch antennas, dipole antennas, ceramic resonators, stamped metal antennas, and/or laser direct structuring antennas.

(65) In the illustrated embodiment, the IC **142** and the surface mount components **143** are on a second surface of the laminate **141** opposite the first surface.

(66) In certain implementations, the IC **142** includes signal conditioning circuits associated with the antenna elements **151-166**. In one embodiment, the IC **142** includes a serial interface, such as a mobile industry processor interface radio frequency front-end (MIPI RFFE) bus and/or inter-integrated circuit (I.sup.2C) bus that receives data for controlling the signal conditioning circuits, such as the amount of phase shifting provided by phase shifters. In another embodiment, the IC **142** includes signal conditioning circuits associated with the antenna elements **151-166** and an integrated transceiver.

(67) The laminate **141** can be implemented in a variety of ways, and can include for example, conductive layers, dielectric layers, solder masks, and/or other structures. The number of layers, layer thicknesses, and materials used to form the layers can be selected based on a wide variety of factors, which can vary with application. The laminate **141** can include vias for providing electrical connections to signal feeds and/or ground feeds of the antenna elements **151-166**. For example, in certain implementations, vias can aid in providing electrical connections between signaling conditioning circuits of the IC **142** and corresponding antenna elements.

(68) The module **140** can be included in a communication system, such as a mobile phone or base station. In one example, the module **140** is attached to a phone board of a mobile phone.

(69) Example Mobile Device

(70) FIG. **4** is a schematic diagram of one embodiment of a mobile device **800**. The mobile device **800** includes a baseband system **801**, a sub millimeter wave (mmW) transceiver **802**, a sub mmW front end system **803**, sub mmW antennas **804**, a power management system **805**, a memory **806**, a user interface **807**, a mmW baseband (BB)/intermediate frequency (IF) transceiver **812**, a mmW front end system **813**, and mmW antennas **814**.

(71) The mobile device **800** can be used communicate using a wide variety of communications technologies, including, but not limited to, 2G, 3G, 4G (including LTE, LTE-Advanced, and LTE-Advanced Pro), 5G NR, WLAN (for instance, WiFi), WPAN (for instance, Bluetooth and ZigBee), WMAN (for instance, WiMax), and/or GPS technologies.

(72) In the illustrated embodiment, the sub mmW transceiver **802**, sub mmW front end system **803**, and sub mmW antennas **804** serve to transmit and receive centimeter waves and other radio frequency signals below millimeter wave frequencies. Additionally, the mmW BB/IF transceiver **812**, mmW front end system **813**, and mmW antennas **814** serve to transmit and receive millimeter waves. Although one specific example is shown, other implementations are possible, including, but not limited to, mobile devices operating using circuitry operating over different frequency ranges and wavelengths.

(73) The sub mmW transceiver **802** generates RF signals for transmission and processes incoming RF signals received from the sub mmW antennas **804**. It will be understood that various

functionalities associated with the transmission and receiving of RF signals can be achieved by one or more components that are collectively represented in FIG. 4 as the sub mmW transceiver **802**. In one example, separate components (for instance, separate circuits or dies) can be provided for handling certain types of RF signals.

(74) The sub mmW front end system **803** aids in conditioning signals transmitted to and/or received from the antennas **804**. In the illustrated embodiment, the front end system **803** includes power amplifiers (PAs) **821**, low noise amplifiers (LNAs) **822**, filters **823**, switches **824**, and signal splitting/combining circuitry **825**. However, other implementations are possible.

(75) For example, the sub mmW front end system **803** can provide a number of functionalities, including, but not limited to, amplifying signals for transmission, amplifying received signals, filtering signals, switching between different bands, switching between different power modes, switching between transmission and receiving modes, duplexing of signals, multiplexing of signals (for instance, duplexing or triplexing), or some combination thereof.

(76) In certain implementations, the mobile device **800** supports carrier aggregation, thereby providing flexibility to increase peak data rates. Carrier aggregation can be used for both Frequency Division Duplexing (FDD) and Time Division Duplexing (TDD), and may be used to aggregate a plurality of carriers or channels. Carrier aggregation includes contiguous aggregation, in which contiguous carriers within the same operating frequency band are aggregated. Carrier aggregation can also be non-contiguous, and can include carriers separated in frequency within a common band or in different bands.

(77) The sub mmW antennas **804** can include antennas used for a wide variety of types of communications. For example, the sub mmW antennas **804** can include antennas for transmitting and/or receiving signals associated with a wide variety of frequencies and communications standards.

(78) The mmW BB/IF transceiver **812** generates millimeter wave signals for transmission and processes incoming millimeter wave signals received from the mmW antennas **814**. It will be understood that various functionalities associated with the transmission and receiving of RF signals can be achieved by one or more components that are collectively represented in FIG. 4 as the mmW transceiver **812**. The mmW BB/IF transceiver **812** can operate at baseband or intermediate frequency, based on implementation.

(79) The mmW front end system **813** aids in conditioning signals transmitted to and/or received from the mmW antennas **814**. In the illustrated embodiment, the front end system **803** includes power amplifiers **831**, low noise amplifiers **832**, switches **833**, up converters **834**, down converters **835**, and phase shifters **836**. However, other implementations are possible. In one example, the mobile device **800** operates with a BB mmW transceiver, and up converters and downconverters are omitted from the mmW front end system. In another example, the mmW front end system further includes filters for filtering millimeter wave signals.

(80) The mmW antennas **814** can include antennas used for a wide variety of types of communications. The mmW antennas **814** can include antenna elements implemented in a wide variety of ways, and in certain configurations the antenna elements are arranged to form one or more antenna arrays. Examples of antenna elements for millimeter wave antenna arrays include, but are not limited to, patch antennas, dipole antenna elements, ceramic resonators, stamped metal antennas, and/or laser direct structuring antennas.

(81) In certain implementations, the mobile device **800** supports MIMO communications and/or switched diversity communications. For example, MIMO communications use multiple antennas for communicating multiple data streams over a single radio frequency channel. MIMO communications benefit from higher signal to noise ratio, improved coding, and/or reduced signal interference due to spatial multiplexing differences of the radio environment. Switched diversity refers to communications in which a particular antenna is selected for operation at a particular time. For example, a switch can be used to select a particular antenna from a group of antennas based on

a variety of factors, such as an observed bit error rate and/or a signal strength indicator.

(82) In certain implementations, the mobile device **800** operates with beamforming. For example, the mmW front end system **803** includes amplifiers having controllable gain and phase shifters having controllable phase to provide beam formation and directivity for transmission and/or reception of signals using the mmW antennas **814**. For example, in the context of signal transmission, the amplitude and phases of the transmit signals provided to an antenna array used for transmission are controlled such that radiated signals combine using constructive and destructive interference to generate an aggregate transmit signal exhibiting beam-like qualities with more signal strength propagating in a given direction. In the context of signal reception, the amplitude and phases are controlled such that more signal energy is received when the signal is arriving to the antenna array from a particular direction.

(83) The baseband system **801** is coupled to the user interface **807** to facilitate processing of various user input and output (I/O), such as voice and data. The baseband system **801** provides the sub mmW and mmW transceivers with digital representations of transmit signals, which are processed by the transceivers to generate RF signals for transmission. The baseband system **801** also processes digital representations of received signals provided by the transceivers. As shown in FIG. 4, the baseband system **801** is coupled to the memory **806** of facilitate operation of the mobile device **800**.

(84) The memory **806** can be used for a wide variety of purposes, such as storing data and/or instructions to facilitate the operation of the mobile device **800** and/or to provide storage of user information.

(85) The power management system **805** provides a number of power management functions of the mobile device **800**. In certain implementations, the power management system **805** includes a PA supply control circuit that controls the supply voltages of the power amplifiers of the front end systems. For example, the power management system **805** can be configured to change the supply voltage(s) provided to one or more of the power amplifiers to improve efficiency, such as power added efficiency (PAE).

(86) In certain implementations, the power management system **805** receives a battery voltage from a battery. The battery can be any suitable battery for use in the mobile device **800**, including, for example, a lithium-ion battery.

(87) Example Power Amplifier Systems

(88) FIG. 5A is a schematic diagram of a power amplifier system **860** according to one embodiment. The illustrated power amplifier system **860** includes a baseband processor **841**, a transmitter/observation receiver **842**, a power amplifier (PA) **843**, a directional coupler **844**, front-end circuitry **845**, an antenna **846**, a PA bias control circuit **847**, and a PA supply control circuit **848**. The illustrated transmitter/observation receiver **842** includes an I/Q modulator **857**, a mixer **858**, and an analog-to-digital converter (ADC) **859**. In certain implementations, the transmitter/observation receiver **842** is incorporated into a transceiver.

(89) The baseband processor **841** can be used to generate an in-phase (I) signal and a quadrature-phase (Q) signal, which can be used to represent a sinusoidal wave or signal of a desired amplitude, frequency, and phase. For example, the I signal can be used to represent an in-phase component of the sinusoidal wave and the Q signal can be used to represent a quadrature-phase component of the sinusoidal wave, which can be an equivalent representation of the sinusoidal wave. In certain implementations, the I and Q signals can be provided to the I/Q modulator **857** in a digital format. The baseband processor **841** can be any suitable processor configured to process a baseband signal. For instance, the baseband processor **841** can include a digital signal processor, a microprocessor, a programmable core, or any combination thereof. Moreover, in some implementations, two or more baseband processors **841** can be included in the power amplifier system **860**.

(90) The I/Q modulator **857** can be configured to receive the I and Q signals from the baseband processor **841** and to process the I and Q signals to generate an RF signal. For example, the I/Q

modulator **857** can include digital-to-analog converters (DACs) configured to convert the I and Q signals into an analog format, mixers for upconverting the I and Q signals to RF, and a signal combiner for combining the upconverted I and Q signals into an RF signal suitable for amplification by the power amplifier **843**. In certain implementations, the I/Q modulator **857** can include one or more filters configured to filter frequency content of signals processed therein.

(91) The power amplifier **843** can receive the RF signal from the I/Q modulator **857**, and when enabled can provide an amplified RF signal to the antenna **846** via the front-end circuitry **845**.

(92) The front-end circuitry **845** can be implemented in a wide variety of ways. In one example, the front-end circuitry **845** includes one or more switches, filters, duplexers, multiplexers, and/or other components. In another example, the front-end circuitry **845** is omitted in favor of the power amplifier **843** providing the amplified RF signal directly to the antenna **846**.

(93) The directional coupler **844** senses an output signal of the power amplifier **823**. Additionally, the sensed output signal from the directional coupler **844** is provided to the mixer **858**, which multiplies the sensed output signal by a reference signal of a controlled frequency. The mixer **858** operates to generate a downshifted signal by downshifting the sensed output signal's frequency content. The downshifted signal can be provided to the ADC **859**, which can convert the downshifted signal to a digital format suitable for processing by the baseband processor **841**. Including a feedback path from the output of the power amplifier **843** to the baseband processor **841** can provide a number of advantages. For example, implementing the baseband processor **841** in this manner can aid in providing power control, compensating for transmitter impairments, and/or in performing digital pre-distortion (DPD). Although one example of a sensing path for a power amplifier is shown, other implementations are possible.

(94) The PA supply control circuit **848** receives a power control signal from the baseband processor **841**, and controls supply voltages of the power amplifier **843**. In the illustrated configuration, the PA supply control circuit **848** generates a first supply voltage $V_{sub.CC1}$ for powering an input stage of the power amplifier **843** and a second supply voltage $V_{sub.CC2}$ for powering an output stage of the power amplifier **843**. The PA supply control circuit **848** can control the voltage level of the first supply voltage $V_{sub.CC1}$ and/or the second supply voltage $V_{sub.CC2}$ to enhance the power amplifier system's PAE.

(95) The PA supply control circuit **848** can employ various power management techniques to change the voltage level of one or more of the supply voltages over time to improve the power amplifier's power added efficiency (PAE), thereby reducing power dissipation.

(96) One technique for improving efficiency of a power amplifier is average power tracking (APT), in which a DC-to-DC converter is used to generate a supply voltage for a power amplifier based on the power amplifier's average output power. Another technique for improving efficiency of a power amplifier is envelope tracking (ET), in which a supply voltage of the power amplifier is controlled in relation to the envelope of the RF signal. Thus, when a voltage level of the envelope of the RF signal increases the voltage level of the power amplifier's supply voltage can be increased. Likewise, when the voltage level of the envelope of the RF signal decreases the voltage level of the power amplifier's supply voltage can be decreased to reduce power consumption.

(97) In certain configurations, the PA supply control circuit **848** is a multi-mode supply control circuit that can operate in multiple supply control modes including an APT mode and an ET mode. For example, the power control signal from the baseband processor **841** can instruct the PA supply control circuit **848** to operate in a particular supply control mode.

(98) As shown in FIG. 5A, the PA bias control circuit **847** receives a bias control signal from the baseband processor **841**, and generates bias control signals for the power amplifier **843**. In the illustrated configuration, the bias control circuit **847** generates bias control signals for both an input stage of the power amplifier **843** and an output stage of the power amplifier **843**. However, other implementations are possible.

(99) FIG. 5B is a schematic diagram of a power amplifier system **870** according to another

embodiment. The illustrated power amplifier system **870** includes a baseband processor **841**, a transmitter/observation receiver **842**, a power amplifier **843**, an antenna array **861**, a PA bias control circuit **847**, and a PA supply control circuit **848**. As shown in FIG. 5B, the antenna array **861** includes an antenna **861** and an observation antenna **863**.

(100) The power amplifier system **870** of FIG. 5B is similar to the power amplifier system **860** of FIG. 5A, except that the power amplifier system **870** omits the directional coupler **844** and the front-end circuitry **845** of FIG. 5A to avoid loading loss at the output of the power amplifier **843**. For example, the power amplifier system **870** can aid in providing low signal loss when transmitting at millimeter wave frequencies. As shown in FIG. 5B, the observation antenna **863** is coupled to the antenna **861** by antenna-to-antenna coupling, and serves to provide an observation signal for the observation path of the transmitter/observation receiver **842**.

(101) Front End Architecture with Integrated Channel Matching

(102) Aspects of this disclosure relate to systems and methods for biasing the amplifiers used in a front end system, in particular for mmW beamforming systems. For example, fine level trimming of amplifiers in the RF front end can be used for third order intercept point (IP3), gain, and/or expansion calibration of both transmit and receive chains for multi-channel devices in order to reach desired levels of matching between RF or mmW channels. In particular, aspects of this disclosure can achieve the comparable or improved levels of calibration/trimming compared to other implementations with a smaller layout area or footprint.

(103) This reduced area can be particularly advantageous for RF systems capable of beamforming at millimeter wave frequencies (e.g., 30 GHz to 300 GHz). For example, the antennas used for millimeter wave frequencies may be patch antennas having a defined size with the front end system formed in the same area occupied by the corresponding antennas (e.g., on opposing sides of a chip). Due to the limited size occupied by the antennas, reducing the size of the RF front end can be helpful in ensuring that the RF front end fits within the allowable area. However, aspects of this disclosure are not limited to RF systems used for beamforming and/or at millimeter wave frequencies and can be used in other RF systems including, for example, 5G RF systems and in the TeraHertz spectrum.

(104) Beamforming at millimeter wave frequencies typically employ a plurality of patch antennas, each of which is driven by a millimeter wave front-end configured to provide accurate phase and amplitude to each of the antennas with respect to each other. FIG. 6 is a diagram of an RF system **600** including a plurality of antennas **602** and a plurality of RF front ends **604** in accordance with aspects of this disclosure.

(105) As shown in FIG. 6, four channels can be collocated on a single chip/module **600** (also referred to as a front end integrated circuit (FEIC)). However, in other embodiments, more or fewer channels can be collocated on a single chip/module. Process variations and other die(s), component(s), PCB(s), and/or module mismatch(es) may result in different gain(s) between the channels included on the chip **600**. In order to facilitate calibration, each channel on the transmit and/or receive side is matched (e.g., for both phase and gain) to the other channels. Embodiments of the RF front end architectures described herein enable accurate gain matching between the various channels of the FEIC **600**, while reducing the area occupied by the RF front end. Alternatively an offset in gain or phase can be desirable to achieve the system level targets in which the FEIC is used. For instance, a phase and gain offset can be used to compensate for different trace length between the FEIC and the antenna patches.

(106) Depending on the embodiment, an RF system may include a relatively large number of channels, each of which are coupled to an RF front end including control circuitry occupying a certain area of the FEIC **600**. As is described herein, aspects of this disclosure provide multiplex biasing blocks and signals between operation modes (e.g., receive and transmit) as well as two or more frequency bands to reduce the die area occupied by the control circuitry.

(107) Additionally, aspects of this disclosure also provide control of a temperature coefficient (e.g.,

which is used to bias amplifiers in the RF front end) while maintaining the room temp calibration. Advantageously, this process can simplify lab work used to calibrate the RF system and reduce automatic test equipment (ATE) test time.

(108) With reference to FIG. 6, the spacing between the patch antennas **602** may be determined by the wavelength of the RF signal (e.g., for a millimeter wave about 4-5 mm) which limits to the size of the FEIC. Thus, area reduction for the FEIC is desirable such that the FEIC can fit within the space dictated by the antenna **602** spacing. Aspects of this disclosure relate to techniques for reducing the space occupied by the biasing circuitry of a multi channel, multi-band, receive/transmit, multi-staged FEIC.

(109) FIG. 7 is a schematic diagram of an RF front end system **900** including a plurality of amplification chains **902a** and **902b** in accordance with aspects of this disclosure. The RF front end system **900** includes two transmit front end amplification chains **902a** and **902b** (also referred to simply as chains), and a control circuit **920**. The transmit chains **902a** and **902b** may operate at different frequency bands. The first transmit chain **902a** includes a programmable attenuator **904a** and a plurality of power amplifiers **906a-910a**. Each of the power amplifiers **906a-910a** provides a stage of amplification. Similarly, the second transmit chain **902b** includes a programmable attenuator **904b** and a plurality of power amplifiers **906b-910b**. Although FIG. 7 illustrates an example including two transmit front end amplification chains **902a**, those skilled in the art would recognize that the RF front end system **900** can also be applied to one or more receive chains as well as receive/transmit chains.

(110) The control circuit **920** includes a bias controller **930** and a plurality of current digital-to-analog converts (DACs) **922a-926b**, each of which is coupled to the bias controller **930** and a corresponding stage or bias circuitry of the power amplifiers **906a-910b**. The bias controller **930** is configured to control each of the programmable attenuators **904a** and **904b** to adjust the attenuation applied to the RF signals received at the programmable attenuators **904a** and **904b**. Depending on the implementation, bias controller **930** can control the programmable attenuators **904a** and **904b** using coarse and/or fine gain steps.

(111) The bias controller **930** is further configured to provide individual bias currents to each amplification stage **906b-910b** of the chains **902a** and **902b** via the corresponding current DACs **922a-926b**. Accordingly, the control circuit **920** is configured to control the gain of each chain **902a** and **902b** as well as matching between channels (e.g., the gain difference between channels).

(112) The gain can also be controlled by altering the structure of the amplification stage (switchable periphery, switchable load etc.). For example, in various embodiments the attenuator can be replaced or complemented by a programmable gain stage. Thus, the control of the gain for each chain is not limited to the particular implementation illustrated in FIG. 7.

(113) FIG. 8 is a schematic diagram of a front end amplification chain **1100** in accordance with aspects of this disclosure. The front end amplification chain **1100** includes a plurality of amplifiers **1102-1106**, each of which provides a stage of amplification. When the chain **1100** is embodied as a transmit chain **1100**, the amplifiers **1102-1106** may be embodied as power amplifiers **1102-1106**. When the chain **1100** is embodied as a receive chain **1100**, the amplifiers **1102-1106** may be embodied as low noise amplifiers **1102-1106**. Although not illustrated, the amplification chain **110** may also include an attenuator and/or programmable gain stage configured to adjust the gain of the amplification chain **110**, similar to the implementation illustrated in FIG. 7.

(114) The chain **1100** is configured to receive a radio frequency input signal RF_IN and output a radio frequency output signal RF_OUT. Each of the amplifiers **1102-1106** can receive a shared reference voltage VDD and a corresponding enable signal EN1-EN3. The amplifiers **1102-1106** can be individually turned off or on to enable bias current calibration on the shared reference voltage VDD line. In some implementations, the reference voltage VDD line may further be shared by other stages or other circuitry within the FEIC.

(115) The difference between all of the amplification stages **1102-1106** being disabled and one of

the amplification stages **1102-1106** being enabled can provide a bias current of the enabled amplification stage **1102-1106**, which can be used to accurately trim/calibrate the bias current and bias point of that particular enabled amplification stage **1102-1106**. This calibration of the individual stages provides an advantage over more traditional calibration techniques in which the current of all amplification stages **1102-1106** change at once, making it more difficult to optimize for each amplification stage **1102-1106**.

(116) The calibration of an RF front end may involve the use of automated test equipment (ATE) to calibrate the gain of each transmit/receive chain. For example, calibration may involve: measuring the gain of the transmit/receive chain, adjust the coarse gain, fine tune the bias current of the output stage for a known output power for a transmit chain or for IP3 for a receive chain, and fine trimming a first stage for gain (e.g., for absolute gain or for gain matching between chains). In some embodiments, gain can be reduced by using a higher attenuation in the coarse adjustment or by reducing the stage bias current. In some embodiments, gain can be increased by increasing the bias current or lowering the coarse adjustment. Gain can also be adjusted by using a programmable gain stage using switchable periphery or switchable/programmable loads or topologies, depending on the embodiment.

(117) FIGS. **9A** and **9B** are schematic diagrams illustrating different embodiments of RF front ends **1200** and **1250** including amplification chains in accordance with aspects of this disclosure. In particular, FIG. **9A** illustrates an embodiment including two independent amplification chains **1202** and **1204** and FIG. **9B** illustrates an embodiment in which two amplification chains **1252** and **1254** receive input from a multiplexor. Although only two amplification chains **1202** and **1204** are illustrated in FIGS. **9A** and **9B**, aspects of this disclosure are not limited thereto and a greater or fewer number of amplification chains can be included in various implementations.

(118) With reference to FIG. **9A**, the RF front end **1200** includes a first amplification chain **1202** and a second amplification chain **1204**. In one embodiment, the first and second amplification chains **1202** and **1204** may be configured to operate in different bands. However, in other embodiments, the first amplification chain **1202** may be configured as a transmit chain while the second amplification chain **1204** may be configured as a receive chain for the same band.

(119) Each of the first and second amplification chains **1202** and **1204** includes a corresponding current DAC **1206a** and **1206b** and a corresponding amplifier **1208a** and **1208b**. Each of the current DACs **1206a** and **1206b** receives an input signal and generates a bias current which is provided to the corresponding amplifier **1208a** and **1208b**.

(120) FIG. **9B** illustrates an alternate embodiment in which a current DAC **1256** is shared between first and second amplification chains **1252** and **1254**. The RF front end **1250** further includes a multiplexer **1258**, first and second optional scaling blocks **1260a** and **1260b**, and first and second amplifiers **1262a** and **1262b**. Similar to the FIG. **9A** embodiment, the first and second amplification chains **1252** and **1254** may be transmit chains which operate in different bands or may be transmit and receive chains which operate in the same band.

(121) The multiplexer **1258** is configured to selectively apply the bias current output from the current DAC **1256** to one of the first and second amplifiers **1262a** and **1262b**. When included, the bias current can be scaled via the scaling blocks **1260a** and **1260b**.

(122) The embodiment of FIG. **9B** can be used for non-concurrent (e.g., TDD) multi-band solutions using different receive and TX chains, and can reuse of the same current DAC **1256** (e.g., bias generator) between the bands with current scaling performed by the scaling blocks **1260a** and **1260b**. In implementations that do not include the scaling blocks **1260a** and **1260b**, the bias current may be scaled inside a sizing/mirror within the amplifiers **1262a** and **1262b** or through an intermediate current mirror.

(123) By sharing the current DAC **1256**, the area occupied by the RF front end **1250** can be reduced (e.g., compared to the RF front end **1200** of FIG. **9A**). The current DAC **1256** can also be shared by more than two amplification chains, resulting in even greater area savings. In addition,

fewer digital traces can be used (e.g., the input lines to the current DAC **1256**). For example, in FIG. **9B** N input lines and one select line may be used to control the current DAC **1256** and the multiplexor, while in FIG. **9A**, two times N input lines are used to provide the two inputs to the two current DACs **1206a** and **1206b**. A digital state machine (not illustrated) can be used to provide the correct input to the current DAC **1256** depending on the mode of operation of the RF front end (e.g., in transmit or receive mode, or depending on the current RF band being used for communication).

(124) Another advantage to the use of a shared current DAC **1256** is that the RF front end **1250** can be more easily redesigned for more/less current by simply adjusting the scaling factor. This can be accomplished by adjusting the ratio of a current mirror or by metal mask adjustments alone. Thus, it can be easy to implement variants, derivatives, and/or adjustments.

(125) The scaling blocks **1260a** and **1260b** (e.g., which may be a current mirror in some implementations) can be placed near the corresponding amplifiers **1262a** and **1262b**, which can enable: a smaller current DAC **1256** (e.g., by using lower current), resulting in better efficiency and a more compact size due to lower current handling. The smaller current DAC **1256** can be implemented with a supply different from the amplifiers **1262a** and **1262b**, enabling a smaller size, lower leakage etc. for the current DAC **1256**. Additionally, the relative close placement of the scaling blocks **1260a** and **1260b** to the corresponding amplifiers **1262a** and **1262b** can also enable shorter traces with high current handling (e.g., the relatively higher current only needs to travel from the scaling block **1260a** or **1260b** to the corresponding amplifier **1262a** or **1262b** rather than from the current DAC **1256** to the amplifiers **1262a** and **1262b**), which may result in fewer issues of reliability and voltage drop across the lines, allows for the use thinner wires upstream of the scaling blocks **1260a** and **1260b**, and an overall smaller area for the RF front end **1250**.

(126) When the RF front end **1250** is used to implement TDD communication, the current DAC **1256** can be used to generate the bias current for transmit and receive chains **1262a** and **1262b**. The scaling blocks **1260a** and **1260b** can be used to scale the bias current, for example, using current mirrors. In other embodiments, current scaling can also be performed inside the power amplifier **1262a** and low noise amplifier **1262b** using sizing/mirror circuitry or through an intermediate mirror.

(127) Similar to the use of the RF front end **1250** for two bands, in the transmit and receive TDD implementation, the area occupied by the RF front end **1250** due to the sharing of the single current DAC **1258** between the power amplifier **1262a** and the low noise amplifier **1262b** is reduced. Some or all of the other benefits described above in connection with the multi-band implementation (e.g., where the amplifiers **1262a** and **1262b** are power amplifiers used in two different bands) may also apply to the TDD implementation in which the first and second chains **1252** and **154** are transmit and receive chains for the same band.

(128) FIGS. **10A** and **10B** are schematic diagrams illustrating RF front ends **1300** and **1350** in accordance with aspects of this disclosure. In particular, FIG. **10A** illustrates an embodiment which includes a plurality of 2:1 multiplexors **1306** and **1308** and FIG. **10A** illustrates an embodiment which includes a single 4:1 multiplexor **1356**.

(129) With reference to FIG. **10A**, the RF front end **1300** includes a control circuit **1302**, a current DAC **1304**, a first multiplexor **1306**, a second multiplexor **1308**, a power amplifier **1310**, a low noise amplifier **1312**, and an antenna **1314**. In some embodiments, the control circuit **1302** includes a proportional to absolute temperature (PTAT) circuit or other bias circuit with predefined or programmable temperature, process, and supply dependence. The control circuit **1302** is configured to generate a digital control signal to control the level of the bias current generated by the current DAC **1304**. Although not illustrated, the control circuit **1302** may further be configured to control the state of the multiplexors **1306** and **1308** such that the current output from the current DAC **1304** is provided to the intended amplifier (e.g., the power amplifier **1310** or the low noise amplifier **1312**).

(130) The first multiplexor **1306** is configured to selectively apply the bias current to one of a first band BAND_A and a second band BAND_B. Although not illustrated, the second multiplexor **1308**, power amplifier **1310**, low noise amplifier **1312**, and antenna **1314** may be duplicated for the first band BAND_A. The second multiplexor **1308** is configured to selectively apply the bias current to one of the power amplifier **1310** and the low noise amplifier **1312**. In some implementations, only one of the amplifiers **1310** and **1312** from both bands BAND_A and BAND_B may be operational at a given time, and thus, the multiplexors **1306** and **1308** may only need to provide the bias current to a single amplifier **1310** and **1312** at a given time.

(131) With reference to FIG. **10B**, the RF front end **1350** includes a control circuit **1352**, a current DAC **1354**, a multiplexor **1356**, a power amplifier **1358**, a low noise amplifier **1360**, and an antenna **1362**. In some embodiments, the control circuit **1302** includes a proportional to absolute temperature (PTAT) circuit or other bias circuit with predefined or programmable temperature, process and supply dependence. The control circuit **1302** is configured to generate a digital control signal to control the level of the bias current generated by the current DAC **1354**. Although not illustrated, the control circuit **1302** may further be configured to control the state of the multiplexor **1356** such that the current output from the current DAC **1354** is provided to the intended amplifier (e.g., the power amplifier **1358** on BAND_B_TX, the low noise amplifier **1360** on BAND_B_RX, BAND_A_TX, or BAND_A_RX). In one embodiment, BAND_A may be 28 GHz and BAND_B may be 39 GHz.

(132) As described herein, an RF front end (e.g., a millimeter wave FEIC) typically include a power amplifier and a low noise amplifier. The low noise amplifier typically operates at lower voltage than the power amplifier to leverage the better noise figure (NF) of the device with shorter gate length (and thus lower breakdown voltage). In contrast, the power amplifier typically operates at higher voltage to increase output power, the supply of which might be varied for Average Power Tracking (APT) or based on different platform/systems.

(133) Using a common bias generator for the power amplifier and the low noise amplifier (e.g., as shown in FIGS. **10A** and **10B**) may involve operating with various output voltages. Accordingly, the 4:1 multiplexor **1356** of FIG. **10B** may include an embedded cascode for voltage protection, enabling different possible supply voltages for the power amplifier **1358** and the low noise amplifier **1360**.

(134) The current DAC **1354** can be used to control the bias point of the power amplifier **1358** and the low noise amplifier **1360** for each stage (e.g., see FIGS. **7** and **8**) included in the transmit or receive chain. In some implementations, the current of the amplifier may be calculated as the reference current multiplied by the digital input code (e.g., the control signal provided to the current DAC **1354**) plus an offset. The reference current may be trimmed during production for each of the transmit and receive chains. The reference current may also be trimmed during production for each amplification stage individually. The reference current may also be trimmed during production for each band. Finally, the reference current may further be trimmed during production for temperature coefficient (e.g., in order to compensate for temperature variations), per amplification stage, per band, and per mode (e.g., transmit and receive). The offset can also be trimmed similarly to the reference current per amplification stage, per band, and per mode.

(135) The trimming of the reference current and the offset can be performed individually for each channel within the FEIC. Certain parameters can be shared/trimmed similarly between channels or between stages. For instance, the temperature coefficient of a given amplification stage may be substantially the same for each channel. Thus, the trimming of the temperature coefficient can be shared between different bands and transmit/receive chains.

(136) The power amplifiers used for millimeter wave frequencies may be comparatively inefficient compared to other frequencies, and thus, the junction temperature rise for the power amplifiers can be significant. Thus, maintaining performance over temperature variations can involve proper temperature compensation of both the power amplifier and low noise amplifier bias current bias as

well as other bias voltages such as cascodes.

(137) Since the different amplification stages of the power amplifier and low noise amplifier chains are biased in different regions (e.g., operation classes) to achieve different performance optimization targets (lower NF, high linearity, gain expansion, gain compression etc.), the optimum temperature coefficient can vary from stage to stage and be difficult to identify by simulation alone. Aspects of this disclosure enable programming and trimming/fusing of the temperature coefficient for each individual amplification stage for each transmit and receive chain, as well as per band and/or per channel. Aspects of this disclosure further enable reprogramming and trimming using a shared/reusable bias generator, such as the current DACs **1304** and **1354**.

(138) FIG. **11** is a schematic diagram illustrating another RF front end embodiment **1400** in accordance with aspects of this disclosure. With reference to FIG. **11**, the RF front end **1400** includes a control circuit **1401** including programmable fuse block **1402**, controller **1404**, a mobile industry processor interface (MIPI) or other serial or parallel interface **1412**, a first control circuit **1418a**, a second control circuit **1418b**, a first current DAC **1420a**, a second current DAC **1420b**. The RF front end **1400** further includes a first multiplexor **1420a**, a second multiplexor **1420b**, a first amplifier **1422**, and a second amplifier **1424**.

(139) The controller **1404** includes a fuse emulator **1406**, a decoder **1408**, a third multiplexor **1410a**, and a fourth multiplexor **1410b**. The MIPI **1412** includes a first set of registers **1414** which may not be reprogrammable and a second set of registers **1416** which may be reprogrammable.

(140) The fuse block **1402** may be a one time programmable fuse block **1402** and can be configured to include digital control values for each stage and each band for both the transmit and receive chains of the RF front end. For example, the fuse block **1402** can store digital control signals for bias trim (e.g., bias current), temperature coefficient, and various bias shaping. The fuse emulator **1406** is configured to receive the digital codes from the fuse block **1402** based on control signals received from the MIPI **1412**. The decoder **1408** can be configured to decode the digital control signals received from the fuse block **1402** into values to be provided to the control circuits **1418a** and **1418b** and the current DACs **1420a** and **1420b** via the third and fourth multiplexors **1410a** and **1410b**.

(141) The first amplifier **1422** may form a first amplification stage (e.g., for a transmit chain) and the second amplifier **1424** may form a second amplification stage for the transmit chain. In other embodiments, the first and second amplifiers may provide amplification stages for a receive chain.

(142) The first amplifier **1422** can receive a bias current via the first control circuit **1418a**, the first current DAC **1420a**, and the first multiplexor **1420a**. Similarly, the second amplifier **1424** can receive a bias current via the second control circuit **1418b**, the second current DAC **1420b**, and the second multiplexor **1420b**. Thus, both amplification stages can receive bias currents simultaneously.

(143) In more detail, the first and second multiplexors **1410a** and **1410b**, together with the decoder **1408**, provide digital codes to the shared control circuits **1418a** and **1418b** as well as to the current DACs **1420a** and **1420b**. The control circuits **1418a** and **1418b** may be implemented as PTAT circuits and may receive digital values indicative of the temperature coefficient and a reference or nominal temperature value (e.g., a reference value for a temperature of 25° C.). The digital control signals provided to the current DACs **1420a** and **1420b** may include a DAC setting value and any offset or shaping control signals.

(144) In order to calibrate the bias currents, the bias current can first be optimized for room temperature, and then the RF front end can be heated to find an optimal value for the temperature coefficient. Alternatively, the temperature optimization can be performed through lab characterization and the optimum result programmed into the RFIC during production test.

(145) In some embodiments, the reference current trimming resolution (e.g., number of bits used to encode the digital control values) may vary between the type of chain (e.g., dependent on whether the chain is a receive or transmit chain). In one example, the trimming resolution may be 3 bits for

a receive chain and 5 bits for a transmit chain.

(146) In some embodiments, the reference current can be trimmed per channel, per receive/transmit chain, per band, and/or per amplification stage. The temperature coefficient can also be trimmed per stage, per band, and per receive/transmit chain.

(147) The reference currents (e.g., bias current) can also be trimmable for value (e.g., to correct process variation, mismatch between channels, and/or simply to achieve a desired new target for optimization), offsets, and temperature coefficient.

(148) At room temperature (e.g., 30° C. for the die or any other value set as room temperature), the temperature coefficient adjustment may not alter the nominal bias current to simplify calibration.

(149) The control circuit **1401** is configured to control and production trim (e.g., calibrate) the bias current per band, per mode (e.g., receive and transmit modes), per channel, and/or per amplification stage. Each amplification stage can be fully turned off to enable current measurement of each amplification stage on a shared supply, thereby simplifying calibration for each amplification stage. The calibration coefficients will be stored in a memory, either a One-Time-Programmable (OTP) or Multiple Time programmable (MTP) Memory or other non-volatile memory during production test. The content of this look-up table can be overwritten to emulate/try out particular coefficients before measuring the results.

(150) The bias DAC can be shared between bands and/or modes (e.g., receive and transmit modes) simultaneously to save area, reduced routing complexity, reduce power consumption, increase reliability, and provide additional design flexibility.

(151) The bias point for each amplifier **1422** and **1424** can be fully controlled at the individual amplification stage level (e.g., using the current DAC **1420a** and **1420b** settings). The bias point for each amplifier **1422** and **1424** can also be fully controlled at the chain level (e.g., using the current DAC **1420a** and **1420b** settings), with integrated trimmable shaping between each amplification stage. The equation used to generate the bias current for each stage can be based on a general control parameter.

(152) Although the FIG. **11** implementation illustrates bias current control for two amplification stages for two bands, the control circuitry **1401** can be scaled to provide bias current to additional channels. Aspects of this disclosure provide for increased area efficiency by sharing the bias current generators (e.g., current DACs) by multiplexing between frequency bands and modes (e.g., receive and transmit modes), including current biasing blocks, voltage biasing blocks, and digital control buses. The different amplifiers can be fully trimmable at the individual amplification stage level to achieve gain matching between channels. The amplifiers can also be trimmed for temperature coefficient, independently of the room temp absolute bias calibration.

CONCLUSION

(153) Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” and the like are to be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” The word “coupled”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate elements. Likewise, the word “connected”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate elements. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, shall refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the above Detailed Description using the singular or plural number may also include the plural or singular number respectively. The word “or” in reference to a list of two or more items, that word covers all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list.

(154) Moreover, conditional language used herein, such as, among others, “can,” “could,” “might,” “can,” “e.g.,” “for example,” “such as” and the like, unless specifically stated otherwise, or

otherwise understood within the context as used, is generally intended to convey that certain embodiments include, while other embodiments do not include, certain features, elements and/or states. Thus, such conditional language is not generally intended to imply that features, elements and/or states are in any way required for one or more embodiments or that one or more embodiments necessarily include logic for deciding, with or without author input or prompting, whether these features, elements and/or states are included or are to be performed in any particular embodiment.

(155) The above detailed description of embodiments of the invention is not intended to be exhaustive or to limit the invention to the precise form disclosed above. While specific embodiments of, and examples for, the invention are described above for illustrative purposes, various equivalent modifications are possible within the scope of the invention, as those skilled in the relevant art will recognize. For example, while processes or blocks are presented in a given order, alternative embodiments may perform routines having steps, or employ systems having blocks, in a different order, and some processes or blocks may be deleted, moved, added, subdivided, combined, and/or modified. Each of these processes or blocks may be implemented in a variety of different ways. Also, while processes or blocks are at times shown as being performed in series, these processes or blocks may instead be performed in parallel, or may be performed at different times.

(156) The teachings of the invention provided herein can be applied to other systems, not necessarily the system described above. The elements and acts of the various embodiments described above can be combined to provide further embodiments.

(157) While certain embodiments of the inventions have been described, these embodiments have been presented by way of example only, and are not intended to limit the scope of the disclosure. Indeed, the novel methods and systems described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the methods and systems described herein may be made without departing from the spirit of the disclosure. The accompanying claims and their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the disclosure.

Claims

1. A front end system comprising: a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of a plurality of antennas, and each of the front end amplification chains further including an amplifier configured to amplify the corresponding radio frequency signal; a control circuit configured to generate a bias current; and a multiplexor configured to receive the bias current from the control circuit and provide the bias current to a selected one of the amplifiers.
2. The front end system of claim 1 wherein the antennas, the front end amplification chains, the control circuit, and the multiplexor are all formed on a single die.
3. The front end system of claim 1 wherein each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a millimeter wave spectrum or a TeraHertz spectrum.
4. The front end system of claim 1 wherein each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a 5G spectrum.
5. The front end system of claim 1 wherein the control circuit includes a current digital-to-analog converter configured to receive a digital reference current value and generate the bias current based on the digital reference current value.
6. The front end system of claim 5 wherein the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and a temperature coefficient and generate

the digital reference current value based on the trim bias current value and the temperature coefficient.

7. The front end system of claim 5 wherein the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and generate the digital reference current value based on the trim bias current value.

8. The front end system of claim 1 wherein each of the front end amplification chains includes a plurality of amplification stages, wherein the bias current includes a plurality of bias currents, each of the bias currents corresponding to one of the plurality amplification stages, and wherein the multiplexor includes a plurality of multiplexors, each of the plurality of multiplexors configured to receive the bias currents for a corresponding one of the amplification stages and provide the bias currents to the corresponding amplification stages of each of the front end amplification chains.

9. The front end system of claim 1 wherein the control circuit is further configured to generate the bias current based on a temperature coefficient and a trim bias current.

10. The front end system of claim 1 wherein each of the front end amplification chains includes an attenuator or a programmable gain stage configured to adjust the gain of the corresponding front end amplification chain.

11. A radio frequency device comprising: a plurality of antennas; and a front end system including a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of the plurality of antennas, and each of the front end amplification chains includes an amplifier configured to amplify the corresponding radio frequency signal, a control circuit configured to generate a bias current, and a multiplexor configured to receive the bias current from the control circuit and provide the bias current to a selected one of the amplifiers.

12. The radio frequency device of claim 11 wherein the antennas, the front end amplification chains, the control circuit, and the multiplexor are all formed on a single die.

13. The radio frequency device of claim 11 wherein each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a millimeter wave spectrum or a TeraHertz spectrum.

14. The radio frequency device of claim 11 wherein each of the front end amplification chains is configured to transmit or receive the radio frequency signals in a 5G spectrum.

15. The radio frequency device of claim 11 wherein the control circuit includes a current digital-to-analog converter configured to receive a digital reference current value and generate the bias current based on the digital reference current value.

16. The radio frequency device of claim 15 wherein the control circuit includes a shared bias generator circuit configured to receive a trim bias current value and a temperature coefficient and generate the digital reference current value based on the trim bias current value and the temperature coefficient.

17. The radio frequency device of claim 11 wherein each of the front end amplification chains includes a plurality of amplification stages, wherein the bias current includes a plurality of bias currents, each of the bias currents corresponding to one of the plurality amplification stages, and wherein the multiplexor includes a plurality of multiplexors, each of the plurality of multiplexors configured to receive the bias currents for a corresponding one of the amplification stages and provide the bias currents to the corresponding amplification stages of each of the front end amplification chains.

18. The radio frequency device of claim 11 wherein the control circuit is further configured to generate the bias current based on a temperature coefficient and a trim bias current.

19. The radio frequency device of claim 11 comprising one of the following: a telecommunications device, a telecommunications satellite, a base station, a mobile device, and a radar device.

20. A method comprising: generating, at a control circuit, a bias current; receiving the bias current

at a multiplexor, the multiplexor and control circuit formed on a front end system including a plurality of front end amplification chains including transmit and receive chains for at least two radio frequency bands, each of the front end amplification chains configured to either transmit or receive radio frequency signals via one of a plurality of antennas, and each of the front end amplification chains includes an amplifier configured to receive the bias current and amplify the corresponding radio frequency signal; and providing, by the multiplexor, the bias current to the amplifier of a selected one of the plurality of front end amplification chains.
