

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413196
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	McHugh; Sean

Tuning acoustic resonators with back-side coating

Abstract

A filter device is provided that includes a substrate and a piezoelectric plate attached to the substrate. A conductor pattern is formed at a first surface of the piezoelectric plate and includes interdigital transducers of series and shunt resonators that each have interleaved fingers at respective diaphragms of the plate suspended. A first dielectric coating layer is formed over the interleaved fingers of the IDTs and on the first surface of the piezoelectric plate; and a second dielectric coating layer is formed on the second surface of the piezoelectric plate that is opposite the first surface. The second dielectric coating layer of the shunt resonator has a greater thickness than a thickness of the at least one second dielectric coating layer of the series resonator.

Inventors:	McHugh; Sean (Santa Barbara, CA)
Applicant:	Murata Manufacturing Co., Ltd. (Nagaokakyo, JP)
Family ID:	87558149
Assignee:	Murata Manufacturing Co., Ltd. (Nagaokakyo, JP)
Appl. No.:	18/169251
Filed:	February 15, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230261626 A1	Aug. 17, 2023

Related U.S. Application Data

us-provisional-application US 63311010 20220216

Publication Classification

Int. Cl.: H03H3/04 (20060101); H03H3/02 (20060101); H03H9/02 (20060101); H03H9/17 (20060101); H03H9/56 (20060101)

U.S. Cl.:

CPC H03H3/04 (20130101); H03H9/02228 (20130101); H03H9/174 (20130101); H03H9/176 (20130101); H03H9/562 (20130101); H03H9/564 (20130101); H03H9/568 (20130101); H03H2003/023 (20130101); H03H2003/0442 (20130101)

Field of Classification Search

CPC: H03H (3/04); H03H (9/02228); H03H (9/174); H03H (9/176); H03H (9/562); H03H (9/564); H03H (9/568); H03H (2003/023); H03H (2003/0442); H03H (3/02); H03H (9/02015); H03H (9/02062)

USPC: 333/133; 333/187; 333/188; 333/193-196

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5705399	12/1997	Larue	N/A	N/A
5853601	12/1997	Krishaswamy et al.	N/A	N/A
6540827	12/2002	Levy et al.	N/A	N/A
6707229	12/2003	Martin	N/A	N/A
7135940	12/2005	Kawakubo et al.	N/A	N/A
7463118	12/2007	Jacobsen	N/A	N/A
7535152	12/2008	Ogami et al.	N/A	N/A
7684109	12/2009	Godshalk et al.	N/A	N/A
7802466	12/2009	Whalen et al.	N/A	N/A
7868519	12/2010	Umeda	N/A	N/A
8278802	12/2011	Lee et al.	N/A	N/A
8344815	12/2012	Yamanaka	N/A	N/A
8829766	12/2013	Milyutin et al.	N/A	N/A
8932686	12/2014	Hayakawa et al.	N/A	N/A
9130145	12/2014	Martin et al.	N/A	N/A
9219466	12/2014	Meltaus et al.	N/A	N/A
9276557	12/2015	Nordquist et al.	N/A	N/A
9281800	12/2015	Tsuzuki	N/A	N/A
9369105	12/2015	Li	N/A	N/A
9425765	12/2015	Rinaldi	N/A	N/A
9525398	12/2015	Olsson	N/A	N/A
9748923	12/2016	Kando et al.	N/A	N/A
9780759	12/2016	Kimura et al.	N/A	N/A
10200013	12/2018	Bower et al.	N/A	N/A
10284176	12/2018	Solal	N/A	B06B 1/0622
10305447	12/2018	Raihn et al.	N/A	N/A
10491192	12/2018	Plesski et al.	N/A	N/A
10601392	12/2019	Plesski et al.	N/A	N/A
10637438	12/2019	Garcia et al.	N/A	N/A

10756697	12/2019	Plesski et al.	N/A	N/A
10790802	12/2019	Yantchev et al.	N/A	N/A
10797675	12/2019	Plesski	N/A	N/A
10826462	12/2019	Plesski et al.	N/A	N/A
10868513	12/2019	Yantchev	N/A	N/A
2002/0079986	12/2001	Ruby et al.	N/A	N/A
2002/0158714	12/2001	Kaitila et al.	N/A	N/A
2003/0199105	12/2002	Kub et al.	N/A	N/A
2004/0041496	12/2003	Imai et al.	N/A	N/A
2004/0090145	12/2003	Bauer et al.	N/A	N/A
2004/0207033	12/2003	Koshido	N/A	N/A
2004/0207485	12/2003	Kawachi et al.	N/A	N/A
2004/0261250	12/2003	Kadota et al.	N/A	N/A
2005/0280476	12/2004	Abe et al.	N/A	N/A
2006/0072875	12/2005	Bhagavatula et al.	N/A	N/A
2006/0125489	12/2005	Feucht et al.	N/A	N/A
2006/0131731	12/2005	Sato	N/A	N/A
2006/0152107	12/2005	Tanaka	N/A	N/A
2006/0222568	12/2005	Wang et al.	N/A	N/A
2007/0001549	12/2006	Kando et al.	N/A	N/A
2007/0090898	12/2006	Kando	N/A	N/A
2007/0170565	12/2006	Hong et al.	N/A	N/A
2007/0188047	12/2006	Tanaka	N/A	N/A
2007/0194863	12/2006	Shibata et al.	N/A	N/A
2010/0064492	12/2009	Tanaka	N/A	N/A
2010/0102669	12/2009	Yamanaka	N/A	N/A
2010/0107388	12/2009	Iwamoto	N/A	N/A
2010/0123367	12/2009	Tai et al.	N/A	N/A
2010/0212127	12/2009	Heinze et al.	N/A	N/A
2010/0223999	12/2009	Onoe	N/A	N/A
2010/0301703	12/2009	Chen et al.	N/A	N/A
2011/0109196	12/2010	Goto	N/A	N/A
2011/0199163	12/2010	Yamanaka	N/A	N/A
2011/0278993	12/2010	Iwamoto	N/A	N/A
2013/0015353	12/2012	Tai et al.	N/A	N/A
2013/0021116	12/2012	Sogoya et al.	N/A	N/A
2013/0057360	12/2012	Meltaus et al.	N/A	N/A
2013/0321100	12/2012	Wang	N/A	N/A
2014/0001919	12/2013	Komatsu	N/A	N/A
2014/0009032	12/2013	Takahashi et al.	N/A	N/A
2014/0113571	12/2013	Fujiwara	N/A	N/A
2014/0145556	12/2013	Kadota	N/A	N/A
2014/0151151	12/2013	Reinhardt	N/A	N/A
2014/0152145	12/2013	Kando et al.	N/A	N/A
2014/0173862	12/2013	Kando et al.	N/A	N/A
2014/0218129	12/2013	Fujiwara	N/A	N/A
2014/0225684	12/2013	Kando et al.	N/A	N/A
2014/0312994	12/2013	Meltaus et al.	N/A	N/A
2015/0070227	12/2014	Kishino et al.	N/A	N/A
2015/0319537	12/2014	Perois et al.	N/A	N/A

2015/0333730	12/2014	Meltaus	N/A	N/A
2016/0028367	12/2015	Shealy	N/A	N/A
2016/0049920	12/2015	Kishino	N/A	N/A
2016/0182009	12/2015	Bhattacharjee	N/A	N/A
2016/0285430	12/2015	Kikuchi et al.	N/A	N/A
2017/0005638	12/2016	Otagawa et al.	N/A	N/A
2017/0063332	12/2016	Gilbert et al.	N/A	N/A
2017/0077902	12/2016	Daimon	N/A	N/A
2017/0104470	12/2016	Koelle et al.	N/A	N/A
2017/0170808	12/2016	Iwaki et al.	N/A	N/A
2017/0179928	12/2016	Raihn et al.	N/A	N/A
2017/0187352	12/2016	Omura	N/A	N/A
2017/0214387	12/2016	Burak et al.	N/A	N/A
2017/0222618	12/2016	Inoue et al.	N/A	N/A
2017/0222622	12/2016	Solal et al.	N/A	N/A
2017/0264263	12/2016	Huang et al.	N/A	N/A
2017/0324394	12/2016	Ebner et al.	N/A	N/A
2017/0359050	12/2016	Irieda et al.	N/A	N/A
2017/0370791	12/2016	Nakamura et al.	N/A	N/A
2018/0062604	12/2017	Koskela et al.	N/A	N/A
2018/0123016	12/2017	Gong et al.	N/A	N/A
2018/0152169	12/2017	Goto et al.	N/A	N/A
2018/0191322	12/2017	Chang et al.	N/A	N/A
2019/0068164	12/2018	Houlden et al.	N/A	N/A
2019/0123721	12/2018	Takamine	N/A	N/A
2019/0131953	12/2018	Gong	N/A	N/A
2019/0148621	12/2018	Feldman et al.	N/A	N/A
2019/0181833	12/2018	Nosaka	N/A	N/A
2019/0245518	12/2018	Ito	N/A	N/A
2019/0273480	12/2018	Lin	N/A	N/A
2019/0273481	12/2018	Michigami	N/A	N/A
2019/0386635	12/2018	Plesski et al.	N/A	N/A
2019/0386637	12/2018	Plesski et al.	N/A	N/A
2019/0386638	12/2018	Kimura et al.	N/A	N/A
2020/0007110	12/2019	Konaka et al.	N/A	N/A
2020/0021271	12/2019	Plesski et al.	N/A	N/A
2020/0091893	12/2019	Plesski et al.	N/A	N/A
2020/0162052	12/2019	Matsuoka et al.	N/A	N/A
2020/0220522	12/2019	Nosaka	N/A	N/A
2020/0228087	12/2019	Michigami et al.	N/A	N/A
2020/0304091	12/2019	Yantchev	N/A	N/A
2020/0328728	12/2019	Nakagawa et al.	N/A	N/A
2020/0336130	12/2019	Turner	N/A	N/A
2020/0373907	12/2019	Garcia	N/A	N/A
2021/0005805	12/2020	Shibata et al.	N/A	N/A
2021/0006228	12/2020	Garcia	N/A	N/A
2021/0013859	12/2020	Turner et al.	N/A	N/A
2021/0013868	12/2020	Plesski	N/A	N/A
2021/0126619	12/2020	Wang et al.	N/A	N/A
2021/0273631	12/2020	Jachowski et al.	N/A	N/A

2021/0384885	12/2020	Daimon et al.	N/A	N/A
2022/0103160	12/2021	Jachowski	N/A	N/A
2022/0216842	12/2021	Nagatomo et al.	N/A	N/A
2022/0216846	12/2021	Yamane et al.	N/A	N/A
2022/0231661	12/2021	McHugh	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1926763	12/2006	CN	N/A
201893487	12/2010	CN	N/A
112352382	12/2020	CN	N/A
112011100580	12/2012	DE	N/A
H0522074	12/1992	JP	N/A
H10209804	12/1997	JP	N/A
2001244785	12/2000	JP	N/A
2002300003	12/2001	JP	N/A
2003078389	12/2002	JP	N/A
2004096677	12/2003	JP	N/A
2004129222	12/2003	JP	N/A
2004304622	12/2003	JP	N/A
2006173557	12/2005	JP	N/A
2007251910	12/2006	JP	N/A
2010103803	12/2009	JP	N/A
2010109949	12/2009	JP	N/A
2010233210	12/2009	JP	N/A
2013528996	12/2012	JP	N/A
2015054986	12/2014	JP	N/A
2016001923	12/2015	JP	N/A
2017220910	12/2016	JP	N/A
2018166259	12/2017	JP	N/A
2018207144	12/2017	JP	N/A
2019186655	12/2018	JP	N/A
2020088459	12/2019	JP	N/A
2020113939	12/2019	JP	N/A
2010047114	12/2009	WO	N/A
2013021948	12/2012	WO	N/A
2015098694	12/2014	WO	N/A
2015156232	12/2014	WO	N/A
2015182521	12/2014	WO	N/A
2016017104	12/2015	WO	N/A
2016052129	12/2015	WO	N/A
2016147687	12/2015	WO	N/A
2018003273	12/2017	WO	N/A
2018079522	12/2017	WO	N/A
2018163860	12/2017	WO	N/A
2019138810	12/2018	WO	N/A
2019241174	12/2018	WO	N/A
2020092414	12/2019	WO	N/A
2020175234	12/2019	WO	N/A
2021060512	12/2020	WO	N/A

2021060523	12/2020	WO	N/A
2022/220155	12/2021	WO	N/A
2022/244746	12/2021	WO	N/A
2023002858	12/2022	WO	N/A

OTHER PUBLICATIONS

T. Takai, H. Iwamoto, et al., I.H.P. Saw Technology and its Application to Microacoustic Components (Invited). 2017 IEEE International Ultrasonics Symposium, Sep. 6-9, 2017. pp. 1-8. cited by applicant

R. Olsson III, K. Hattar et al. "A high electromechanical coupling coefficient SHO Lamb wave lithiumniobate micromechanical resonator and a method for fabrication" Sensors and Actuators A: Physical, vol. 209, Mar. 1, 2014, pp. 183-190. cited by applicant

M. Kadota, S. Tanaka, "Wideband acoustic wave resonators composed of hetero acoustic layer structure," Japanese Journal of Applied Physics, vol. 57, No. 7S1. Published Jun. 5, 2018. 5 pages. cited by applicant

Y. Yang, R. Lu et al. "Towards Ka Band Acoustics: Lithium Niobat Asymmetrical Mode Piezoelectric MEMS Resonators", Department of Electrical and Computer Engineering University of Illinois at Urbana-Champaign, May 2018. pp. 1-2. cited by applicant

Y. Yang, A. Gao et al. "5 Ghz Lithium Niobate Mems Resonators With High Fom of 153", 2017 IEEE 30th International Conference in Micro Electro Mechanical Systems (MEMS). Jan. 22-26, 2017. pp. 942-945. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2019/036433 dated Aug. 29, 2019. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2019/058632 dated Jan. 17, 2020. cited by applicant

G. Manohar, "Investigation of Various Surface Acoustic Wave Design Configurations for Improved Sensitivity." Doctoral dissertation, University of South Florida, USA, Jan. 2012, 7 pages. cited by applicant

Ekeom, D. & Dubus, Bertrand & Volatier, A.. (2006). Solidly mounted resonator (SMR) FEM-BEM simulation. 1474-1477. 10.1109/ULTSYM.2006.371. cited by applicant

Mizutau, K. and Toda, K., "Analysis of lamb wave propagation characteristics in rotated Y-cut X-propagation LiNbO3 plates." Electron. Comm. Jpn. Pt. I, 69, No. 4 (1986): 47-55. doi:10.1002/ecja.4410690406. cited by applicant

Naumenko et al., "Optimal orientations of Lithium Niobate for resonator SAW filters", 2003 IEEE Ultrasonics Symposium—pp. 2110-2113. (Year: 2003). cited by applicant

Webster Dictionary "Meaning of diaphragm" Merriam Webster since 1828. cited by applicant

Safari et al. "Piezoelectric for Transducer Applications" published by Elsevier Science Ltd., pp. 4 (Year: 2000). cited by applicant

Moussa et al. Review on Triggered Liposomal Drug Delivery with a Focus on Ultrasound 2015, Bentham Science Publishers, pp. 16 (Year 2005). cited by applicant

"Acoustic Properties of Solids" ONDA Corporation, 592 Weddell Drive, Sunnyvale, CA 94089, Apr. 11, 2003, pp. 5 (Year 2003). cited by applicant

Bahreynl, B., "Fabrication and Design of Resonant Microdevices" Andrew William, Inc. 2018, NY (Year 2008). cited by applicant

Material Properties of Tibtech Innovations, © 2018 TIBTECH Innovations (Year 2018). cited by applicant

Bousquet, Marie e al. "Single-mode high frequency LiNbO3 Film Bulk Acoustic Resonator," 2019 IEEE International Ultrasonics Symposium (IUS), Glasgow, Scotland, Oct. 6-9, 2019, pp. 84-87. cited by applicant

Wikipedia contributors, "Quartz crystal microbalance," Wikipedia, The Free Encyclopedia,

https://en.wikipedia.org/w/index.php?title=Quartz_crystal_microbalance&oldid=1009990186 (accessed Apr. 9, 2021). cited by applicant

Yantchev, Ventsislav & Katardjiev, Ilia. (2013). Thin film Lamb wave resonators in frequency control and sensing applications: A review. *Journal of Micromechanics and Microengineering*. 23. 043001. 10.1088/0960-1317/23/4/043001. cited by applicant

Wei Pang et al. “Analytical and experimental study on the second harmonic mode response of a bulk acoustic wave resonator” 2010 *J. Micromech. Microeng.* 20 115015; doi: 10.1088/0960-1317/20/11/115015. cited by applicant

Durmus et al. “Acoustic-Based Biosensors” *Encyclopedia of Microfluidics and Nanofluidics*. DOI 10.1007/978-3-642-27758-0_10-2 Springer Science+Business Media New York 2014. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2023/017732 dated Jul. 27, 2023. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2022/082421 dated May 3, 2023. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2022/081095 dated May 30, 2023. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2022/079236 dated Mar. 10, 2023. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2022/081068 dated Apr. 18, 2023. cited by applicant

USPTO/ISA, International Search Report and Written Opinion for PCT Application No. PCT/US2022/080246 dated Mar. 30, 2023. cited by applicant

Gong et al., “Design and Analysis of Lithium-Niobate-Based High Electromechanical Coupling RF-MEMS Resonators for Wideband Filtering”, *IEEE Transactions on Microwave Theory and Techniques*, vol. 61, No. 1, Jan. 2013, pp. 403-413. cited by applicant

Primary Examiner: Salazar, Jr.; Jorge L

Attorney, Agent or Firm: ArentFox Schiff LLP

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) The current application claims priority to U.S. Patent Provisional Application No. 63/311,010, filed Feb. 16, 2022, the entire contents of which are hereby incorporated by reference.

TECHNICAL FIELD

(1) This disclosure relates to radio frequency filters using acoustic wave resonators, and specifically to filters for use in communications equipment.

BACKGROUND

(2) A radio frequency (RF) filter is a two-port device configured to pass some frequencies and to stop other frequencies, where “pass” means transmit with relatively low signal loss and “stop” means block or substantially attenuate. The range of frequencies passed by a filter is referred to as the “pass-band” of the filter. The range of frequencies stopped by such a filter is referred to as the “stop-band” of the filter. A typical RF filter has at least one pass-band and at least one stop-band. Specific requirements on a pass-band or stop-band may depend on the specific application. For example, in some cases a “pass-band” may be defined as a frequency range where the insertion loss of a filter is better than a defined value such as 1 dB, 2 dB, or 3 dB, while a “stop-band” may be

defined as a frequency range where the rejection of a filter is greater than a defined value such as 20 dB, 30 dB, 40 dB, or greater depending on application.

(3) RF filters are used in communications systems where information is transmitted over wireless links. For example, RF filters may be found in the RF front-ends of cellular base stations, mobile telephone and computing devices, satellite transceivers and ground stations, IoT (Internet of Things) devices, laptop computers and tablets, fixed point radio links, and other communications systems. RF filters are also used in radar and electronic and information warfare systems.

(4) Performance enhancements to the RF filters in a wireless system can have broad impact to system performance. Improvements in RF filters can be leveraged to provide system performance improvements such as larger cell size, longer battery life, higher data rates, greater network capacity, lower cost, enhanced security, higher reliability, etc. These improvements can be realized at many levels of the wireless system both separately and in combination, for example at the RF module, RF transceiver, mobile or fixed sub-system, or network levels.

SUMMARY

(5) Thus, according to an exemplary aspect, a filter device is provided that includes a substrate; at least one piezoelectric plate having opposing first and second surfaces and attached to the substrate; a conductor pattern at a first surface of the at least one piezoelectric plate and including a plurality of interdigital transducers (IDTs) of a plurality of resonators, respectively, that each have interleaved fingers at respective diaphragms of the at least one piezoelectric plate suspended over one or more cavities, with the plurality of resonators including a shunt resonator and a series resonator; at least one first dielectric coating layer over at least the interleaved fingers of the IDTs and on the first surface of the at least one piezoelectric plate; and at least one second dielectric coating layer on the second surface of the at least one piezoelectric plate that is opposite the first surface. In this aspect, the at least one second dielectric coating layer of the shunt resonator has a greater thickness than a thickness of the at least one second dielectric coating layer of the series resonator.

(6) Moreover, in an exemplary aspect, the thickness of the at least one second dielectric coating layer of the shunt resonator is configured such that the shunt resonator has a resonance frequency with an anti-resonance (e.g., when impedance is very high) that is approximately at a same frequency as the resonance frequency of the series resonator. Yet further, the thickness of the at least one second dielectric coating layer of the shunt resonator can be approximately ten times the thickness of the at least one second dielectric coating layer of the series resonator. In addition, a thickness of the second dielectric coating layer is greater than a thickness of the first dielectric coating layer. Moreover, the at least one second dielectric coating layer is uniform with opposing surfaces that are parallel to the second surface of the at least one piezoelectric plate.

(7) In another exemplary aspect, an acoustic resonator device is provided that includes a substrate having a surface; a piezoelectric plate attached to the surface of the substrate except for a portion of the piezoelectric plate that forms a diaphragm that spans a cavity; an interdigital transducer (IDT) at a first surface of the piezoelectric plate and having interleaved fingers at the diaphragm; a first dielectric coating layer over at least the interleaved fingers of the IDT and on a first surface of the piezoelectric plate; and a second dielectric coating layer on a second surface of the piezoelectric plate that is opposite the first surface. Moreover, a thickness of the second dielectric coating layer is greater than a thickness of the first dielectric coating layer. In addition, the second dielectric coating layer is uniform with opposing surfaces that are parallel to the second surface of the piezoelectric plate that configures a resonance frequency of the acoustic resonator device.

(8) In yet another exemplary aspect, a method for manufacturing a filter device is provided. In this aspect, the method includes attaching at least one piezoelectric plate having opposing first and second surfaces to a substrate; forming a conductor pattern at a first surface of the at least one piezoelectric plate that includes a plurality of interdigital transducers (IDTs) of a plurality of resonators, respectively, that each have interleaved fingers at respective diaphragms of the at least

one piezoelectric plate suspended over one or more cavities, with the plurality of resonators including a shunt resonator and a series resonator; depositing at least one first dielectric coating layer over at least the interleaved fingers of the IDTs and on the first surface of the piezoelectric plate; depositing at least one second dielectric coating layer on the second surface of the piezoelectric plate that is opposite the first surface; and trimming the at least one second dielectric coating layer to adjust a resonance frequency of at least one of the shunt resonator and the series resonator.

(9) The above simplified summary of example aspects serves to provide a basic understanding of the present disclosure. This summary is not an extensive overview of all contemplated aspects, and is intended to neither identify key or critical elements of all aspects nor delineate the scope of any or all aspects of the present disclosure. Its sole purpose is to present one or more aspects in a simplified form as a prelude to the more detailed description of the disclosure that follows.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The accompanying drawings, which are incorporated into and constitute a part of this specification, illustrate one or more example aspects of the present disclosure and, together with the detailed description, serve to explain their principles and implementations.

(2) FIG. 1 includes a schematic plan view and two schematic cross-sectional views of a transversely-excited film bulk acoustic resonator (XBAR).

(3) FIG. 2A is an expanded schematic cross-sectional view of a portion of the XBAR of FIG. 1.

(4) FIG. 2B is an expanded schematic cross-sectional view of an alternative configuration of the XBAR of FIG. 1.

(5) FIG. 2C is an expanded schematic cross-sectional view of another alternative configuration of the XBAR of FIG. 1.

(6) FIG. 2D is an expanded schematic cross-sectional view of another alternative configuration of the XBAR of FIG. 1.

(7) FIG. 3A is an alternative schematic cross-sectional view of the XBAR of FIG. 1.

(8) FIG. 3B is an alternative schematic cross-sectional view of the XBAR of FIG. 1.

(9) FIG. 4 is a graphic illustrating a shear horizontal acoustic mode in an XBAR resonator of FIG. 1.

(10) FIG. 5 is a schematic block diagram of a filter using XBAR resonators of FIG. 1.

(11) FIGS. 6 and 7 illustrate exemplary resonators 600 and 700 of the filter 500 illustrated in FIG. 5.

(12) FIG. 8 is a graphical illustration of waveforms depicting a frequency response for series and shunt resonator of an exemplary ladder filter according to an exemplary aspect.

(13) FIG. 9 is a graphical illustration of waveforms illustrating a frequency shift between the series and shunt resonator of an exemplary ladder filter according to an exemplary aspect.

(14) FIG. 10 illustrates a flowchart of a method of manufacturing a filter including the series and shunt resonators as described herein according to an exemplary aspect.

(15) Throughout this description, elements appearing in figures are assigned three-digit or four-digit reference designators, where the two least significant digits are specific to the element and the one or two most significant digit is the figure number where the element is first introduced. An element that is not described in conjunction with a figure may be presumed to have the same characteristics and function as a previously-described element having the same reference designator.

DETAILED DESCRIPTION

(16) FIG. 1 shows a simplified schematic top view and orthogonal cross-sectional views of a

transversely-excited film bulk acoustic resonator (XBAR) **100**. XBAR resonators such as the resonator **100** may be used in a variety of RF filters including band-reject filters, band-pass filters, duplexers, and multiplexers. XBARs are particularly suited for use in filters for communications bands with frequencies above 3 GHz.

(17) In general, the XBAR **100** is made up of a thin film conductor pattern formed at one or both surfaces of a piezoelectric plate **110** having parallel front and back surfaces **112**, **114**, respectively (also referred to generally first and second surfaces, respectively). The piezoelectric plate is a thin single-crystal layer of a piezoelectric material such as lithium niobate, lithium tantalate, lanthanum gallium silicate, gallium nitride, or aluminum nitride. The piezoelectric plate is cut such that the orientation of the X, Y, and Z crystalline axes with respect to the front and back surfaces is known and consistent. In the examples described herein, the piezoelectric plates are Z-cut, which is to say the Z axis is normal to the front and back surfaces **112**, **114**. However, XBARs may be fabricated on piezoelectric plates with other crystallographic orientations including rotated Z-cut and rotated YX cut.

(18) The back surface **114** of the piezoelectric plate **110** is attached to a surface of the substrate **120** except for a portion of the piezoelectric plate **110** that forms a diaphragm **115** spanning a cavity **140** formed in the substrate. The portion of the piezoelectric plate that spans (e.g., extends over) the cavity is referred to herein as the “diaphragm” **115** due to its physical resemblance to the diaphragm of a microphone. As shown in FIG. 1, the diaphragm **115** is contiguous with the rest of the piezoelectric plate **110** around all of a perimeter **145** of the cavity **140**. In this context, “contiguous” means “continuously connected without any intervening item”. However, in some cases, the diaphragm **115** is not necessarily contiguous.

(19) The substrate **120** provides mechanical support to the piezoelectric plate **110**. The substrate **120** may be, for example, silicon, sapphire, quartz, or some other material or combination of materials. The back surface **114** of the piezoelectric plate **110** may be bonded to the substrate **120** using a wafer bonding process. Alternatively, the piezoelectric plate **110** may be grown on the substrate **120** or attached to the substrate in some other manner.

(20) “Cavity” has its conventional meaning of “an empty space within a solid body.” The cavity **140** may be a hole completely through the substrate **120** (as shown in Section A-A and Section B-B) or a recess in the substrate **120** (as shown subsequently in FIG. 3A and FIG. 3B). The substrate **120** may be made of a monolithic material, may be made up of multiple materials, a composite of materials, and any combination thereof. The cavity **140** may be formed, for example, by selective etching of the substrate **120** before or after the piezoelectric plate **110** and the substrate **120** are attached.

(21) The conductor pattern of the XBAR **100** includes an interdigital transducer (IDT) **130**. The IDT **130** includes a first plurality of parallel fingers, such as finger **136**, extending from a first busbar **132** and a second plurality of fingers extending from a second busbar **134**. The first and second pluralities of parallel fingers are interleaved. The interleaved fingers overlap for a distance AP, commonly referred to as the “aperture” of the IDT. The center-to-center distance L between the outermost fingers of the IDT **130** is the “length” of the IDT.

(22) In the examples of FIG. 1, FIG. 3A, and FIG. 3B, the IDT **130** is on the front surface **112** (e.g., the first surface) of the piezoelectric plate **110**. In other configurations, the IDT **130** may be on the back surface **114** (e.g., the second surface) of the piezoelectric plate **110** or on both the front and back surfaces **112**, **114**.

(23) The first and second busbars **132**, **134** are configured as the terminals of the XBAR **100**. A radio frequency or microwave signal applied between the two busbars **132**, **134** of the IDT **130** excites a primary acoustic mode within the piezoelectric plate **110**. As will be discussed in further detail, the primary acoustic mode is a bulk shear mode where acoustic energy propagates along a direction substantially orthogonal to the surface of the piezoelectric plate **110**, which is also normal, or transverse, to the direction of the electric field created by the IDT fingers. Thus, the XBAR is

considered a transversely-excited film bulk wave resonator.

(24) The IDT **130** is positioned at or on the piezoelectric plate **110** such that at least the fingers of the IDT **130** are extend at or on the diaphragm **115** of the piezoelectric plate that spans, or is suspended over, the cavity **140**. As shown in FIG. **1**, the cavity **140** has a rectangular cross section with an extent greater than the aperture AP and length L of the IDT **130**. According to other exemplary aspects, the cavity of an XBAR may have a different cross-sectional shape, such as a regular or irregular polygon. The cavity of an XBAR may more or fewer than four sides, which may be straight or curved.

(25) For ease of presentation in FIG. **1**, the geometric pitch and width of the IDT fingers is greatly exaggerated with respect to the length (dimension L) and aperture (dimension AP) of the XBAR. A typical XBAR has more than ten parallel fingers in the IDT. An XBAR may have hundreds, possibly thousands, of parallel fingers in the IDT. Similarly, the thickness of the fingers in the cross-sectional views is greatly exaggerated.

(26) FIG. **2A** shows a detailed schematic cross-sectional view of the XBAR **100** of FIG. **1**. The piezoelectric plate **110** is a single-crystal layer of piezoelectrical material having a thickness t_s . t_s may be, for example, 100 nm to 1500 nm. When used in filters for 5G NR and Wi-Fi™ bands from 3.4 GHz to 7 GHz, the thickness t_s may be, for example, 150 nm to 500 nm.

(27) A front-side dielectric layer **212** (e.g., a first dielectric coating layer or material) can be formed on the front side **112** of the piezoelectric plate **110**. The “front side” of the XBAR is, by definition, the surface facing away from the substrate. The front-side dielectric layer **212** has a thickness t_{fd} . As shown in FIG. **2A** the front-side dielectric layer **212** covers the IDT fingers **238a**, **238b**.

Although not shown in FIG. **2A**, the front-side dielectric layer **212** may also be deposited only between the IDT fingers **238a**, **238b**. In this case, an additional thin (in comparison to t_{fd}) dielectric layer (not shown) may be deposited over the IDT fingers to seal and passivate the fingers.

(28) A back-side dielectric layer **214** (e.g., a second dielectric coating layer or material) can be formed on the back side **114** of the piezoelectric plate **110**. In general, for purposes of this disclosure, the term “back-side” means on a side opposite the conductor pattern of the IDT structure and/or opposite the front-side dielectric layer **212**. Moreover, the back-side dielectric layer **214** has a thickness t_{bd} . The front-side and back-side dielectric layers **212**, **214** may be a non-piezoelectric dielectric material, such as silicon dioxide or silicon nitride. t_{fd} and t_{bd} may be, for example, 0 to 500 nm. t_{fd} and t_{bd} may be less than the thickness t_s of the piezoelectric plate. t_{fd} and t_{bd} are not necessarily equal, and the front-side and back-side dielectric layers **212**, **214** are not necessarily the same material. Either or both of the front-side and back-side dielectric layers **212**, **214** may be formed of multiple layers of two or more materials according to various exemplary aspects.

(29) The IDT fingers **238a**, **238b** may be aluminum, substantially aluminum alloys, copper, substantially copper alloys, beryllium, gold, some other conductive material, or any combination thereof. Thin (relative to the total thickness of the conductors, such as the IDT fingers **238a**, **238b** for example) layers of other metals, such as chromium or titanium, may be formed under and/or over the fingers to improve adhesion between the fingers and the piezoelectric plate **110** and/or to passivate or encapsulate the fingers. The busbars (**132**, **134** in FIG. **1**) of the IDT may be made of the same or different materials as the fingers. The cross-sectional shape of the IDT fingers may be trapezoidal (finger **238a**), rectangular (finger **238b**), some other shape, or any combination thereof.

(30) Dimension p is the center-to-center spacing between adjacent IDT fingers, such as the IDT fingers **238a**, **238b** in FIGS. **2A**, **2B**, and **2C**. The center-to-center spacing may be constant over the length of the IDT, in which case the dimension p may be referred to as the pitch of the IDT and/or the pitch of the XBAR. The center-to-center spacing may vary along the length of the IDT, in which case the pitch of the IDT is the average value of dimension p over the length of the IDT. Each IDT finger, such as the IDT fingers **238a**, **238b** in FIGS. **2A**, **2B**, and **2C**, has a width w measured normal to the long direction of each finger. The width w may also be referred to herein as

the "mark." The width of the IDT fingers may be constant over the length of the IDT, which case the dimension w is the width of each IDT finger. The width of individual IDT fingers may vary along the length of the IDT **130**, in which case dimension w is the average value of the widths of the IDT fingers over the length of the IDT. Note that the pitch p and the width w of the IDT fingers are measured in a direction parallel to the length L of the IDT, as defined in FIG. 1.

(31) The IDT of an XBAR differs substantially from the IDTs used in surface acoustic wave (SAW) resonators. In a SAW resonator, the pitch of the IDT is one-half of the acoustic wavelength at the resonance frequency. Additionally, the mark-to-pitch ratio of a SAW resonator IDT is typically close to 0.5 (i.e. the mark or finger width is about one-fourth of the acoustic wavelength at resonance). In an XBAR, the pitch p of the IDT is typically 2 to 20 times the width w of the fingers. In addition, the pitch p of the IDT is typically 2 to 20 times the thickness t_s of the piezoelectric plate **110**. The width of the IDT fingers in an XBAR is not constrained to one-fourth of the acoustic wavelength at resonance. For example, the width of XBAR IDT fingers may be 500 nm or greater, such that the IDT can be fabricated using optical lithography. The thickness t_m of the IDT fingers may be from 100 nm to about equal to the width w . The thickness of the busbars (**132**, **134** in FIG. 1) of the IDT may be the same as, less than, greater than, or any combination thereof, the thickness t_m of the IDT fingers.

(32) Moreover, the resonance frequency of an XBAR may be related to the total thickness of its diaphragm, including the piezoelectric plate **110**, and the front-side and back-side dielectric layers **212**, **214**. The thickness of one or both dielectric layers may be varied to change the resonance frequencies of various XBARs in a filter. For example, shunt resonators in a ladder filter circuit may incorporate thicker dielectric layers to reduce the resonance frequencies of the shunt resonators relative to series resonators with thinner dielectric layers.

(33) In general, the shunt resonators of a ladder filter should have a low enough resonance frequency such that each anti-resonance is approximately at the same frequency as the resonance of the series resonators. As described above, the thick coating of dielectric layer (e.g., SiO₂ or SiN) that is applied over the IDT fingers reduces the resonance frequency of such shunt resonators. However, the coating over the fingers is often non-uniform (e.g., by the deposition and etching processes) in the fabricated devices due to a shadow cast by the metal electrodes of each IDT finger, which makes it difficult to control spurs in the XBAR's admittance. Thus, as will be described in detail below, an acoustic resonator device and a method for manufacturing the same is provided for applying a dielectric coating (e.g., SiO₂ or SiN) on the back-side of the piezoelectric plate to provide a more uniform fabricated coating than a coating over the fingers, and therefore more accurate predictions of more control of spurs.

(34) Referring back to FIG. 2A, the thickness t_{fd} of the front-side dielectric layer **212** over the IDT fingers **238a**, **238b** may be greater than or equal to a minimum thickness required to deal and passivate the IDT fingers and other conductors on the front side **112** to the piezoelectric plate **110**. The minimum thickness may be, for example, 10 nm to 50 nm depending on the material of the front-side dielectric layer and method of deposition. The thickness of the back-side dielectric layer **214** may be configured to specific thickness to adjust the resonance frequency of the resonator as will be described in more detail below.

(35) Although FIG. 2A discloses a configuration in which IDT fingers **238a** and **238b** are on the top side **112** of the piezoelectric plate **110**, alternative configurations can be provided. For example, FIG. 2B shows an alternative configuration in which the IDT fingers **238a**, **238b** are on the back side **114** of the piezoelectric plate **110** and are covered by a back-side dielectric layer **214**. A front-side dielectric layer **212** may cover the front side **112** of the piezoelectric plate **110**.

(36) FIG. 2C shows an alternative configuration in which IDT fingers **238a**, **238b** are on the front side **112** of the piezoelectric plate **110** and are covered by a front-side dielectric layer **212**. IDT fingers **238c**, **238d** are on the back side **114** of the piezoelectric plate **110** and are covered by a back-side dielectric layer **214**. As previously described, the front-side and back-side dielectric layer

212, 214 are not necessarily the same thickness or the same material.

(37) FIG. 2D shows another alternative configuration in which IDT fingers **238a, 238b** are on the front side **112** of the piezoelectric plate **110** and are covered by a front-side dielectric layer **212**. The surface of the front-side dielectric layer is planarized. The front-side dielectric layer may be planarized, for example, by polishing or some other method. A thin layer of dielectric material having a thickness t_p may cover the IDT finger **238a, 238b** to seal and passivate the fingers. The dimension t_p may be, for example, 10 nm to 50 nm.

(38) FIG. 3A and FIG. 3B show two alternative cross-sectional views along the section plane A-A defined in FIG. 1. In FIG. 3A, a piezoelectric plate **310** is attached to a substrate **320**, which generally can correspond to substrate **120** of FIG. 1. Moreover, a cavity **340**, which does not fully penetrate the substrate **320**, is formed in the substrate under the portion of the piezoelectric plate **310** containing the IDT of an XBAR. The cavity **340** can correspond to cavity **120** and the piezoelectric plate **310** can correspond to piezoelectric plate **110** of FIG. 1 in an exemplary aspect. Moreover, the cavity **340** may be formed, for example, by etching the substrate **320** before attaching the piezoelectric plate **310**. Alternatively, the cavity **340** may be formed by etching the substrate **320** with a selective etchant that reaches the substrate through one or more openings provided in the piezoelectric plate **310**.

(39) FIG. 3B illustrates an alternative aspect in which the substrate **320** includes a base **322** and an intermediate layer **324** that is disposed between the piezoelectric plate **310** and the base **322**. For example, the base **322** may be silicon and the intermediate layer **324** may be silicon dioxide or silicon nitride or some other material, e.g., an intermediate dielectric layer. Although not shown in FIG. 3B, the substrate **320** may include more than one intermediate layer between the base **322** and the piezoelectric plate **310**. As further shown, cavity **340** is formed in the intermediate layer **324** under the portion of the piezoelectric plate **310** containing the IDT fingers of an XBAR, such as the XBAR **100** of FIG. 1. The cavity **340** may be formed, for example, by etching the intermediate layer **324** before attaching the piezoelectric plate **310**. Alternatively, the cavity **340** may be formed by etching the intermediate layer **324**. In some cases, the etching may be performed with a selective etchant that reaches the substrate through one or more openings (not shown) provided in the piezoelectric plate **310**. In this case, the diaphragm **315**, which can correspond to diaphragm **115** of FIG. 1 in an exemplary aspect, may be contiguous with the rest of the piezoelectric plate **310** around a large portion of a perimeter of the cavity **340**. For example, the diaphragm **315** may be contiguous with the rest of the piezoelectric plate **310** around at least 50% of the perimeter of the cavity **340**. As shown in FIG. 3B, the cavity **340** extends completely through the intermediate layer **324**. That is, the diaphragm **315** can have an outer edge that faces the piezoelectric plate **310** with at least 50% of the edge surface of the diaphragm **315** coupled to the edge of the piezoelectric plate **310** facing the diaphragm **315**. This configuration provides for increased mechanical stability of the resonator.

(40) In other configurations, the cavity **340** may extend into, but not through the intermediate layer **324** (i.e., the intermediate layer **324** may extend over the bottom of the cavity on top of the base **322**), or may extend through the intermediate layer **324** into the base **322**.

(41) FIG. 4 is a graphical illustration of the primary acoustic mode of interest in an XBAR. FIG. 4 shows a small portion of an XBAR **400** including a piezoelectric plate **410** and three interleaved IDT fingers **430**. In general, the exemplary configuration of XBAR **400** can correspond to any of the configurations described above and shown in FIGS. 1, 2A to 2D, and 3A to 3B according to an exemplary aspect. Thus, it should be appreciated that piezoelectric plate **410** can correspond to piezoelectric plate **110** and IDT fingers **430** can be implemented according to any of the configurations of fingers **238a** and **238b**, for example.

(42) In operation, an RF voltage is applied to the interleaved fingers **430**. This voltage creates a time-varying electric field between the fingers. The direction of the electric field is lateral, or parallel to the surface of the piezoelectric plate **410**, as indicated by the arrows labeled “electric

field”. Due to the high dielectric constant of the piezoelectric plate **410**, the electric field is highly concentrated in the plate relative to the air. The lateral electric field introduces shear deformation in the piezoelectric plate **410**, and thus strongly excites a shear-mode acoustic mode, in the piezoelectric plate **410**. In this context, “shear deformation” is defined as deformation in which parallel planes in a material remain parallel and maintain a constant distance while translating relative to each other. A “shear acoustic mode” is defined as an acoustic vibration mode in a medium that results in shear deformation of the medium. The shear deformations in the XBAR **400** are represented by the curves **460**, with the adjacent small arrows providing a schematic indication of the direction and magnitude of atomic motion. The degree of atomic motion, as well as the thickness of the piezoelectric plate **410**, have been exaggerated for ease of visualization in FIG. **4**. While the atomic motions are predominantly lateral (i.e. horizontal as shown in FIG. **4**), the direction of acoustic energy flow of the excited primary shear acoustic mode is substantially orthogonal to the surface of the piezoelectric plate, as indicated by the arrow **465**.

(43) An acoustic resonator based on shear acoustic wave resonances can achieve better performance than current state-of-the art film-bulk-acoustic-resonators (FBAR) and solidly-mounted-resonator bulk-acoustic-wave (SMR BAW) devices where the electric field is applied in the thickness direction which may be orthogonal to the direction of the electric field shown in FIG. **4**. In such devices, the acoustic mode is compressive with atomic motions and the direction of acoustic energy flow in the thickness, or lateral, direction. In addition, the piezoelectric coupling for shear wave XBAR resonances can be high (>20%) compared to other acoustic resonators. Thus, high piezoelectric coupling enables the design and implementation of microwave and millimeter-wave filters with appreciable bandwidth.

(44) FIG. **5** is a schematic circuit diagram and layout for a high frequency band-pass filter **500** using XBAR resonators, such as the XBAR **100** discussed above in reference to FIG. **1**. The filter **500** has a ladder filter architecture including three series resonators **510A**, **510B**, **510C** and two shunt resonators **520A**, **520B**. The three series resonators **510A**, **510B**, and **510C** are connected in series between a first port and a second port. In FIG. **5**, the first and second ports are labeled “In” and “Out”, respectively. However, the filter **500** is bidirectional and either port can serve as the input or output of the filter. The two shunt resonators **520A**, **520B** are connected from nodes between the series resonators to ground. All the shunt resonators and series resonators are XBARs on a single die.

(45) The three series resonators **510A**, **B**, **C** and the two shunt resonators **520A**, **B** of the filter **500** are formed on a single plate **512** of piezoelectric material bonded to a silicon substrate (not visible). The series and shunt resonators **510A**, **510B**, **510C**, **520A**, **520B** all have a bonding layer formed on a plate of piezoelectric material. The three series resonators **510A**, **B**, **C** but not the two shunt resonators **520A**, **B** have one or more plates of piezoelectric material bonded to the bonding layer. Each resonator includes a respective IDT (not shown), such as the IDT **130** of FIG. **1**, with at least the fingers of the IDT disposed over a cavity, such as the cavity **140** in the substrate **120** of FIG. **1**, and at or on at least one surface of the piezoelectric material, such as the piezoelectric material **110** of FIG. **1**. In this and similar contexts, the term “respective” means “relating things each to each,” which is to say with at least a one-to-one correspondence. In FIG. **5**, the cavities are illustrated schematically as the dashed rectangles (such as the rectangle **535**). In this example, each IDT is disposed over a respective cavity. In other filters, the IDTs of two or more resonators may be disposed over a single cavity.

(46) FIGS. **6** and **7** illustrate exemplary resonators **600** and **700** of the filter **500** illustrated in FIG. **5** according to an exemplary aspect. In particular, FIG. **6** illustrates a series resonator **600** that includes piezoelectric plate **610** (e.g., corresponding to piezoelectric plate **110** described above), which may be a Z-cut lithium niobate piezoelectric plate in an exemplary aspect. Moreover, a front-side dielectric layer **612** (e.g., a first dielectric coating layer or material) is formed over a first surface of the piezoelectric plate **610** and the IDT fingers **638a** and **638b**. It should be appreciated

that the dielectric layer **612** may be conformally disposed over the IDT fingers **638a** and **638b** in one exemplary aspect or planarized (as described above) in an alternative aspect. Moreover, a back-side coating dielectric layer or material **614** can be disposed on the second surface of the piezoelectric plate **610** that is opposite the IDT fingers **638a** and **638b**. It should be appreciated that the series resonator **600** can have a configuration in which the IDT fingers **638a** and **638b** are disposed on a surface of the piezoelectric plate **610** facing away from the cavity (e.g., FIG. 2A) in one exemplary aspect or facing toward the cavity (e.g., FIG. 2B) in one exemplary aspect. The back-side coating dielectric layer or material **614** is on the opposite side in either case and can be trimmed to adjust the resonance of the series resonator **600**.

(47) Similarly, FIG. 7 illustrates a shunt resonator **700** that includes piezoelectric plate **710** (e.g., corresponding to piezoelectric plate **110** described above), which may also be a Z-cut lithium niobate piezoelectric plate in an exemplary aspect. Moreover, a front-side dielectric layer **712** (e.g., a first dielectric coating layer or material) is formed over a first surface of the piezoelectric plate **710** and the IDT fingers **738a** and **738b**. It should be appreciated that the dielectric layer **712** may be conformally disposed over the IDT fingers **738a** and **738b** in one exemplary aspect or planarized (as described above) in an alternative aspect.

(48) Moreover, a back-side coating dielectric layer or material **714** can be disposed on the second surface of the piezoelectric plate **710** that is opposite the IDT fingers **738a** and **738b**. Similar to series resonator **600** described above, it should be appreciated that the series resonator **700** can have a configuration in which the IDT fingers **738a** and **738b** are disposed at a surface of the piezoelectric plate **710** facing away from the cavity (e.g., FIG. 2A) in one exemplary aspect or facing toward the cavity (e.g., FIG. 2B) in one exemplary aspect. The back-side coating dielectric layer or material **714** is on the opposite side in either case and can be trimmed to adjust the resonance of the series resonator **700**.

(49) Thus, according to an exemplary aspect, the front-side dielectric layer **712** is configured as a passivation layer for the IDT fingers **738a** and **738b** and can be made very thin, for example and in comparison to the back-side coating dielectric layer or material **714**, to minimally cover the IDT fingers **738a** and **738b**, especially in a planarized configuration. As a result, the front-side dielectric layer **712** will have a thickness t_m that is less than the thickness t_{bd7} of back-side coating dielectric layer or material **714**.

(50) According to an exemplary aspect, the configurations of the series resonator **600** and the shunt resonator **700** can be implemented to form the high frequency band-pass filter **500** described above with respect to FIG. 5. In particular, the series resonator **600** can be implemented as one or more of the series resonators **510A**, **B**, **C** and the shunt resonator **700** can be implemented as one or more of shunt resonators **520A** and **520B**. As further shown in FIGS. 6 and 7, the back-side coating dielectric layer or material **614** of the series resonator **600** can have a first thickness t_{bd6} (i.e., in the thickness direction) that is less than a thickness t_{bd7} of the back-side coating dielectric layer or material **714** of the shunt resonator **700**. As described above, applying the dielectric coating (e.g., back-side coating dielectric layers or materials **614** and **714**) on the back-side of the respective piezoelectric plates provides for a more uniform fabricated coating than a coating over the fingers, and, thus, more accurate predictions of more control of spurs. Moreover, trimming the respective back-side coating dielectric layers or materials **614** and **714** to have different thicknesses allows for more fine tuning of the respective resonances of the shunt and series resonators for the filter **500**. This technique provides for an accurate way of configuring the shunt resonators **520A** and **520B** of the ladder filter **500** to have a low enough resonance frequency such that each anti-resonance is approximately at the same frequency as the resonator of the series resonators **510A-C**.

(51) FIG. 8 is a graphical illustration of waveforms depicting a frequency response for series and shunt resonator of an exemplary ladder filter according to an exemplary aspect. In this simulation, each of the series and shunt resonators have the same piezoelectric thickness of 232 nanometers, pitch of 5 μm , mark of 0.5 μm and IDT finger thickness of 377 nanometers. The graph in FIG. 8

compares the admittances, as functions of frequency, of a series resonator **802** and two shunt resonators **804** and **806**. The admittance data results from simulation of the two resonators with a 75 nm dielectric (e.g., SiO₂.sub.2) top coating as shown in waveform **804** and a 75 nm dielectric (e.g., SiO₂.sub.2) back-side coating as shown in waveform **806**. Notably, the simulation assumes a uniform coating for the waveform **804** of the shunt resonator with the top dielectric coating, in which the admittance is very similar to the shunt resonator with back-side coating having a waveform **806**.

(52) However, as explained above, it is difficult to obtain a uniform top coating of the dielectric material over the IDT fingers due to a shadow cast by the metal electrodes, which makes it difficult to control spurs. In contrast, it is more practical and easy from a manufacturing perspective to obtain a uniform back-side coating since there are no IDT fingers. Therefore, the shunt resonator with back-side coating advantageously obtains a similar admittance **806** as the waveform **804**, which is more difficult to obtain in actual manufacturing due to the shadow cast of the metal electrodes as described above.

(53) FIG. **9** is a graphical illustration of waveforms illustrating a frequency shift between the series and shunt resonator of an exemplary ladder filter according to an exemplary aspect. This illustration compares a series resonator (e.g., resonator **600** of FIG. **6**) and a shunt resonator (e.g., resonator **700** of FIG. **7**). The simulation assumes that the respective XBARs have identical dimensions: a 274 nm 120 y LiNbO₃ plate, 350 nm IDT fingers (aluminum), pitch of =4.5 μm, a mark of 1 μm, and 30 nm conformal, top-side coating of SiO₂ having a thickness of 30 nm (e.g., a first dielectric coating layer or material **612** and **712**, respectively). In this example, the back-side coating dielectric layer **614** of series resonator **600** has a thickness t_{bd6} of 10 nanometers and the back-side coating dielectric layer **714** of shunt resonator **700** has a thickness t_{bd7} of 100 nanometers (e.g., a thickness ratio of 1:10), which advantageously produces a desired frequency shift between the series and shunt resonators, respectively. In other words, the thickness of the second dielectric coating layer of the shunt resonator may be approximately ten times the thickness of the second dielectric coating layer of the series resonator. For purposes of this disclosure, the term “approximately” accounts for minor variations in the dimensions that may occur due to manufacturing variations, for example.

(54) FIG. **10** illustrates a flowchart of a method of manufacturing an XBAR or a filter including the series and shunt resonators as described herein according to an exemplary aspect. As shown, the method **1000** starts at **1002** with a substrate and a plate of piezoelectric material and ends at **1012** with a completed XBAR or filter. The flow chart of FIG. **10** includes only major process steps for purposes of describing the exemplary manufacturing method. Various conventional process steps (e.g. surface preparation, cleaning, inspection, baking, annealing, monitoring, testing, etc.) may be performed before, between, after, and during the steps shown in FIG. **10**, as would be appreciated to one skilled in the art.

(55) The piezoelectric plate may be, for example, Z-cut lithium niobate or lithium tantalate as used in the previously presented examples, such as the piezoelectric plate **110** of FIG. **1**. The piezoelectric plate may be some other material and/or some other cut. The substrate may preferably be silicon. The substrate may be some other material that allows formation of deep cavities by etching or other processing.

(56) At **1002**, the piezoelectric plate is bonded to the substrate. For a filter device, multiple piezoelectric plates may be bonded to the substrate, e.g., one for each resonator in an exemplary aspect. In any case, the piezoelectric plate and the substrate may be bonded by a wafer bonding process. Typically, the mating surfaces of the substrate and the piezoelectric plate are highly polished. One or more layers of intermediate materials, such as an oxide or metal, may be formed or deposited on the mating surface of one or both of the piezoelectric plate and the substrate. One or both mating surfaces may be activated using, for example, a plasma process. The mating surfaces may then be pressed together with considerable force to establish molecular bonds

between the piezoelectric plate and the substrate or intermediate material layers.

(57) A variation of the process **1000** is to grow the piezoelectric plate in situ on the substrate. In that process variation, bonding is not required and the action at **1002** would be redefined as “grow piezoelectric plate on substrate.”

(58) At **1004**, a conductor pattern is deposited or otherwise formed at a first surface of the diaphragm of the piezoelectric plate using a metal deposition and patterning one or more conductor layer at a first surface of the piezoelectric plate. A conductor layer may be, for example, aluminum, an aluminum alloy, copper, a copper alloy, or some other conductive metal. Optionally, one or more layers of other materials may be disposed below (i.e. between the conductor layer and the piezoelectric plate) and/or on top of the conductor layer. For example, a thin film of titanium, chrome, or other metal may be used to improve the adhesion between the conductor layer and the piezoelectric plate. A conduction enhancement layer of gold, aluminum, copper or other higher conductivity metal may be formed over portions of the conductor pattern (for example the IDT bus bars and interconnections between the IDTs).

(59) The conductor pattern may be formed at **1004** by depositing the conductor layer and, optionally, one or more other metal layers in sequence over the surface of the piezoelectric plate. The excess metal may then be removed by etching through patterned photoresist. The conductor layer can be etched, for example, by plasma etching, reactive ion etching, wet chemical etching, and other etching techniques. Alternatively, the conductor pattern may be formed using a lift-off process. Photoresist may be deposited over the piezoelectric plate. and patterned to define the conductor pattern. The conductor layer and, optionally, one or more other layers may be deposited in sequence over the surface of the piezoelectric plate. The photoresist may then be removed, which removes the excess material, leaving the conductor pattern.

(60) At **1006**, one or more cavities are formed in the substrate. A separate cavity may be formed for each resonator in a filter device. The one or more cavities may be formed using an anisotropic or orientation-dependent dry or wet etch to open holes from the back side of the substrate to the piezoelectric plate. Alternatively, cavities in the form of recesses in the substrate may be formed by etching the substrate using an etchant introduced through openings in the piezoelectric plate. It should be appreciated that the cavity can be formed before the conductor pattern is formed at the piezoelectric plate in an exemplary aspect. Moreover, another variation of the process **1000** is to form the one or more cavities in the substrate prior to attaching the piezoelectric plate to the substrate. In that process variation, the actions at **1004** and **1006** occur before the action at **1002**.

(61) At **1008**, a front-side dielectric layer may be formed by depositing one or more layers of dielectric material on the first surface of the piezoelectric plate. The one or more dielectric layers may be deposited using a conventional deposition technique such as sputtering, evaporation, or chemical vapor deposition. The one or more dielectric layers may be deposited over the entire surface of the piezoelectric plate, including on top of the conductor pattern. Alternatively, one or more lithography processes (using photomasks) may be used to limit the deposition of the dielectric layers to selected areas of the piezoelectric plate, such as only between the interleaved fingers of the IDTs. Masks may also be used to allow deposition of different thicknesses of dielectric materials on different portions of the piezoelectric plate.

(62) At **1010**, a back-side dielectric layer may be formed. In the case where the cavities formed at **1006** are holes through the substrate, the back-side dielectric layer may be deposited through the cavities using a convention deposition technique such as sputtering, evaporation, or chemical vapor deposition. When the cavities formed at **1002** are recesses that do not fully penetrate the substrate, the back-side dielectric layer must be formed on the piezoelectric plate or the substrate prior to bonding the piezoelectric plate to the substrate. In that case, the actions at **1010** occur before the actions at **1002**. In either case, the back-side dielectric layer can be uniformly deposited on the second surface (opposing the conductor pattern) of the piezoelectric plate. The back-side dielectric layer can then be trimmed at **1012** (e.g., by an etching process or the like) to adjust the resonance

frequency of the respective resonator. Since the back-side dielectric coating layer is uniform, the manufacturing process can more easily control spurs in the XBAR's admittance. For purposes of this disclosure, the term “uniform” as provided a configuration for the back-side dielectric layer **614** or **714** means that the respective layer has opposing surfaces (e.g., a first surface facing and/or coupled to the piezoelectric plate and a second surface opposing this first surface) that generally extend parallel to each other and also parallel to the respective surface of the piezoelectric plate. That is, when the back-side dielectric layer is formed on the diaphragm, it is evenly distributed across the respective surface of the diaphragm, except for minor variations due to the deposition process, for example. In turn, the uniformity of the back-side dielectric layer provides for a more accurate trimming to achieve a desired resonance frequency of the respective resonator since the back-side dielectric layer can be evenly trimmed at the same rate.

(63) In any event, after the front-side and back-side dielectric layers are formed and the back-side dielectric layer is trimmed to tune the frequency, the filter device may be completed. It should be appreciated that the back-side dielectric layers of each of the shunt and series resonators can be trimmed for a different amount of time and thus a different thickness to appropriately shift the frequency of each resonator as needed for the particular filter application. Moreover, actions that may occur to complete the filter device may include depositing and patterning additional metal layers to form conductors other than the IDT conductor pattern; depositing an encapsulation/passivation layer such as SiO₂ or Si₃O₄ over all or a portion of the device; forming bonding pads or solder bumps or other means for making connection between the device and external circuitry; excising individual devices from a wafer containing multiple devices; other packaging steps; and testing.

(64) The aspects described herein additionally include one or more of the following implementation examples described in the following numbered clauses.

(65) Clause 1. A filter device, comprising: a substrate; at least one piezoelectric plate having opposing first and second surfaces and attached to the substrate; a conductor pattern at a first surface of the at least one piezoelectric plate and including a plurality of interdigital transducers (IDTs) of a plurality of resonators, respectively, that each have interleaved fingers at respective diaphragms of the at least one piezoelectric plate suspended over one or more cavities, with the plurality of resonators including a shunt resonator and a series resonator; at least one first dielectric coating layer over at least the interleaved fingers of the IDTs and on the first surface of the at least one piezoelectric plate; and at least one second dielectric coating layer on the second surface of the at least one piezoelectric plate that is opposite the first surface. Moreover, the at least one second dielectric coating layer of the shunt resonator has a greater thickness than a thickness of the at least one second dielectric coating layer of the series resonator.

(66) Clause 2. The filter device according to clause 1, wherein the thickness of the at least one second dielectric coating layer of the shunt resonator is configured such that the shunt resonator has a resonance frequency with an anti-resonance that is approximately at a same frequency as the resonance frequency of the series resonator.

(67) Clause 3. The filter device according to clause 1 or 2, wherein all of the plurality of IDTs are configured to excite shear acoustic waves in the at least one piezoelectric plate in response to respective radio frequency signals applied to each IDT.

(68) Clause 4. The filter device according to any of clauses 1 to 3, wherein the one or more cavities in the substrate are respective cavities for each of the plurality of IDTs.

(69) Clause 5. The filter device according to any of clauses 1 to 4, wherein the at least one piezoelectric plate is a Z-cut lithium niobate piezoelectric plate.

(70) Clause 6. The filter device according to any of clauses 1 to 5, wherein the substrate comprises a base and an intermediate dielectric layer and the one or more cavities extend in the intermediate dielectric layer.

(71) Clause 7. The filter device according to any of clauses 1 to 6, wherein the first surface of the at

least one piezoelectric plate is attached to the substrate such that the conductor pattern faces the one or more cavities.

(72) Clause 8. The filter device according to any of clauses 1 to 7, wherein the at least one first dielectric coating layer is planarized over the interleaved fingers of the IDTs and the first surface of the at least one piezoelectric plate.

(73) Clause 9. The filter device according to any of clauses 1 to 8, wherein the thickness of the at least one second dielectric coating layer of the shunt resonator is approximately ten times the thickness of the at least one second dielectric coating layer of the series resonator.

(74) Clause 10. The filter device according to any of clauses 1 to 9, wherein the at least one second dielectric coating layer is uniform with opposing surfaces that are parallel to the second surface of the at least one piezoelectric plate.

(75) Clause 11. An acoustic resonator device comprising: a substrate having a surface; a piezoelectric plate attached to the surface of the substrate except for a portion of the piezoelectric plate that forms a diaphragm that spans a cavity; an interdigital transducer (IDT) at a first surface of the piezoelectric plate and having interleaved fingers at the diaphragm; a first dielectric coating layer over at least the interleaved fingers of the IDT and on a first surface of the piezoelectric plate; and a second dielectric coating layer on a second surface of the piezoelectric plate that is opposite the first surface. In this aspect, a thickness of the second dielectric coating layer is greater than a thickness of the first dielectric coating layer. Moreover, the second dielectric coating layer is uniform with opposing surfaces that are parallel to the second surface of the piezoelectric plate that configures a resonance frequency of the acoustic resonator device.

(76) Clause 12. The acoustic resonator device according to clause 11, wherein the IDT is configured to excite shear acoustic waves in the piezoelectric plate in response to respective radio frequency signals applied to each IDT.

(77) Clause 13. The acoustic resonator device according to any of clauses 11 to 12, wherein the piezoelectric plate is a Z-cut lithium niobate piezoelectric plate.

(78) Clause 14. The acoustic resonator device according to any of clauses 11 to 13, wherein the substrate comprises a base and an intermediate dielectric layer and the cavity extends in the intermediate dielectric layer.

(79) Clause 15. The acoustic resonator device according to any of clauses 11 to 14, wherein the first surface of the piezoelectric plate is attached to the substrate such that the conductor pattern faces the cavity.

(80) Clause 16. The acoustic resonator device according to any of clauses 11 to 15, wherein the first dielectric coating layer is planarized over the interleaved fingers of the IDT and the first surface of the piezoelectric plate.

(81) Clause 17. A method for manufacturing a filter device, the method comprising attaching at least one piezoelectric plate having opposing first and second surfaces to a substrate; forming a conductor pattern at a first surface of the at least one piezoelectric plate that includes a plurality of interdigital transducers (IDTs) of a plurality of resonators, respectively, that each have interleaved fingers at respective diaphragms of the at least one piezoelectric plate suspended over one or more cavities, with the plurality of resonators including a shunt resonator and a series resonator; depositing at least one first dielectric coating layer over at least the interleaved fingers of the IDTs and on the first surface of the piezoelectric plate; depositing at least one second dielectric coating layer on the second surface of the piezoelectric plate that is opposite the first surface; and trimming the at least one second dielectric coating layer to adjust a resonance frequency of at least one of the shunt resonator and the series resonator.

(82) Clause 18. The method according to clause 17, wherein the at least one second dielectric coating layer is trimmed such that the shunt resonator has a greater thickness than a thickness of the at least one second dielectric coating layer of the series resonator.

(83) Clause 19. The method according to clause 17 or 18, wherein the thickness of the at least one

second dielectric coating layer of the shunt resonator is configured such that the shunt resonator has a resonance frequency with an anti-resonance that is approximately at a same frequency as the resonance frequency of the series resonator.

(84) Clause 20. The method according to clause 17, 18 or 19, wherein the thickness of the at least one second dielectric coating layer of the shunt resonator is approximately ten times the thickness of the at least one second dielectric coating layer of the series resonator.

(85) In general, it is noted that throughout this description, the embodiments and examples shown should be considered as exemplars, rather than limitations on the apparatus and procedures disclosed or claimed. Although many of the examples presented herein involve specific combinations of method acts or system elements, it should be understood that those acts and those elements may be combined in other ways to accomplish the same objectives. With regard to flowcharts, additional and fewer steps may be taken, and the steps as shown may be combined or further refined to achieve the methods described herein. Acts, elements and features discussed only in connection with one embodiment are not intended to be excluded from a similar role in other embodiments.

(86) As used herein, the pair of terms “top” and “bottom” can be interchanged with the pair “front” and “back”. As used herein, “plurality” means two or more. As used herein, a “set” of items may include one or more of such items. As used herein, whether in the written description or the claims, the terms “comprising”, “including”, “carrying”, “having”, “containing”, “involving”, and the like are to be understood to be open-ended, i.e., to mean including but not limited to. Only the transitional phrases “consisting of” and “consisting essentially of”, respectively, are closed or semi-closed transitional phrases with respect to claims. Use of ordinal terms such as “first”, “second”, “third”, etc., in the claims to modify a claim element does not by itself connote any priority, precedence, or order of one claim element over another or the temporal order in which acts of a method are performed, but are used merely as labels to distinguish one claim element having a certain name from another element having a same name (but for use of the ordinal term) to distinguish the claim elements. As used herein, “and/or” means that the listed items are alternatives, but the alternatives also include any combination of the listed items.

Claims

1. A filter device, comprising: a substrate; a piezoelectric layer having opposing first and second surfaces and attached to the substrate; a conductor pattern on the first surface of the piezoelectric layer and including a plurality of interdigital transducers (IDTs) of a plurality of resonators, respectively, that each have interleaved fingers at respective diaphragms of the piezoelectric layer, the diaphragms being suspended over one or more cavities, and the plurality of resonators including a plurality of shunt resonators and a plurality of series resonators in a ladder filter circuit; at least one first dielectric layer over at least the interleaved fingers of the plurality of IDTs and on the first surface of the piezoelectric layer; and at least one second dielectric layer on the second surface of the piezoelectric layer that is opposite the first surface, wherein the at least one second dielectric layer of all of the plurality of shunt resonators has a greater thickness than a thickness of the at least one second dielectric layer of all of the plurality of series resonators, and wherein the at least one second dielectric layer at each of the plurality of resonators is uniform.

2. The filter device according to claim 1, wherein the thickness of the at least one second dielectric layer of at least one shunt resonator of the plurality of shunt resonators is configured such that the at least one shunt resonator has a resonance frequency with an anti-resonance that is approximately at a same frequency as the resonance frequency of at least one series resonator of the plurality of series resonators.

3. The filter device according to claim 1, wherein all of the plurality of IDTs are configured to excite shear acoustic waves in the respective diaphragms of the piezoelectric layer in response to

respective radio frequency signals applied to each IDT of the plurality of IDTs.

4. The filter device according to claim 1, wherein the one or more cavities are in the substrate and are respective cavities for each of the plurality of resonators.

5. The filter device according to claim 1, wherein the at least one second dielectric layer is thicker than the at least one first dielectric layer for each of the plurality of shunt or series resonators.

6. The filter device according to claim 1, wherein the substrate comprises a base and an intermediate dielectric layer and the one or more cavities extend in the intermediate dielectric layer.

7. The filter device according to claim 1, wherein the first surface of the piezoelectric layer is attached to the substrate such that the conductor pattern faces the one or more cavities.

8. The filter device according to claim 1, wherein the at least one first dielectric layer is planarized over the interleaved fingers of the plurality of IDTs and the first surface of the piezoelectric layer.

9. The filter device according to claim 1, wherein the thickness of the at least one second dielectric layer of at least one shunt resonator of the plurality of shunt resonators is approximately ten times the thickness of the at least one second dielectric layer of at least one series resonator of the plurality of series resonators.

10. The filter device according to claim 1, wherein the at least one second dielectric layer is uniform with opposing surfaces that are parallel to the second surface of the piezoelectric layer.

11. The filter device according to claim 10, wherein the at least one second dielectric layer is uniform with opposing surfaces that are parallel in that the opposing surfaces generally extend parallel to each other.

12. The filter device according to claim 1, wherein the first dielectric layer of at least one resonator of the plurality of resonators is conformally disposed over the interleaved fingers of the at least one resonator.

13. The filter device according to claim 1, wherein, when a voltage is applied to the plurality of IDTs, an electric field is excited that is lateral within the piezoelectric layer introducing shear deformation of a bulk acoustic wave, and wherein the bulk acoustic wave propagates orthogonal to a direction of the electric field.

14. A bulk acoustic resonator filter comprising: a series laterally-excited bulk acoustic resonator comprising: a substrate having a base and an intermediate layer; a piezoelectric layer attached to the intermediate layer, and a portion of the piezoelectric layer disposed over a cavity of the series laterally-excited bulk acoustic resonator; an interdigital transducer (IDT) comprising interleaved fingers disposed on the piezoelectric layer; a first dielectric layer on a first surface of the piezoelectric layer between the interleaved fingers; and a second dielectric layer on a second surface of the piezoelectric layer that is opposite the first surface, wherein a thickness of the second dielectric layer is greater than a thickness of the first dielectric layer; a shunt laterally-excited bulk acoustic resonator comprising: a substrate having a base and an intermediate layer; a piezoelectric layer attached to the intermediate layer, and a portion of the piezoelectric layer disposed over a cavity of the shunt laterally-excited bulk acoustic resonator; an IDT comprising interleaved fingers disposed on the piezoelectric layer; a first dielectric layer on a first surface of the piezoelectric layer between the interleaved fingers; and a second dielectric layer on a second surface of the piezoelectric layer that is opposite the first surface, wherein a thickness of the second dielectric layer is greater than a thickness of the first dielectric layer, wherein the second dielectric layer of the shunt laterally-excited bulk acoustic resonator has a greater thickness than a thickness of the second dielectric layer of the series laterally-excited bulk acoustic resonator, wherein the second dielectric layer of the series laterally-excited bulk acoustic resonator is uniform, and wherein the second dielectric layer of the shunt laterally-excited bulk acoustic resonator is uniform.

15. The bulk acoustic resonator filter according to claim 14, wherein, for the series and shunt laterally-excited bulk acoustic resonators, respective IDTs are disposed on the respective piezoelectric layers, such that the respective IDTs faces the respective cavity.

16. The bulk acoustic resonator filter according to claim 14, wherein the first dielectric layer is

planarized over the interleaved fingers of the IDT and the piezoelectric layer of each of the series and shunt laterally-excited bulk acoustic resonators.

17. The bulk acoustic resonator filter according to claim 14, wherein the thickness of the second dielectric layer of the shunt laterally-excited bulk acoustic resonator has a resonance frequency with an anti-resonance that is approximately at a same frequency as a resonance frequency of the series laterally-excited bulk acoustic resonator.

18. The bulk acoustic resonator filter according to claim 14, wherein the bulk acoustic resonator filter comprises a ladder filter circuit, wherein the series laterally-excited bulk acoustic resonator is one of a plurality of series laterally-excited bulk acoustic resonators, the shunt laterally-excited bulk acoustic resonator is one of a plurality of shunt laterally-excited bulk acoustic resonators, and wherein the second dielectric layer of any of the shunt laterally-excited bulk acoustic resonators is thicker than any of the first dielectric layers of any of the series laterally-excited bulk acoustic resonators.

19. The bulk acoustic resonator filter according to claim 14, wherein, when a voltage is applied to the IDTs of each of the series and shunt laterally-excited bulk acoustic resonators, an electric field is excited that is lateral within the respective piezoelectric layer introducing lateral deformation of a bulk acoustic wave, and wherein the bulk acoustic wave propagates orthogonal to a direction of the electric field.

20. The bulk acoustic resonator filter according to claim 14, wherein the first dielectric layer of at least one of series laterally-excited bulk acoustic resonators and the shunt laterally-excited bulk acoustic resonators is conformally disposed over the interleaved fingers.
