

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250271537

Kind Code

A1

Publication Date

August 28, 2025

Inventor(s)

Kolych; Igor et al.

EXPLOITING PARASITIC OR COUPLING TO MERGE WLAN CHANNELS OF WI-FI RADAR

Abstract

The embodiments described herein are directed at techniques to perform delay compensation for non-overlapping channels used for radar measurements. A device may receive a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network. The device may determine a plurality of channel transfer functions (CTF) s based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals. The device may correct each of the plurality of CTFs to generate a plurality of corrected CTFs. The device may merge the plurality of corrected CTFs to produce a merged CTF. The device may sense one or more objects within the wireless network based on the merged CTF.

Inventors: Kolych; Igor (Lviv, UA), Uln; Kiran (Pleasanton, CA)

Applicant: Cypress Semiconductor Corporation (San Jose, CA)

Family ID: 1000007788992

Assignee: Cypress Semiconductor Corporation (San Jose, CA)

Appl. No.: 18/588985

Filed: February 27, 2024

Publication Classification

Int. Cl.: G01S7/00 (20060101); G01S13/56 (20060101); G01S13/86 (20060101); H04L5/00 (20060101); H04W84/12 (20090101)

U.S. Cl.:

CPC G01S7/006 (20130101); G01S13/86 (20130101); H04L5/0048 (20130101); G01S13/56 (20130101); H04W84/12 (20130101)

Background/Summary

TECHNICAL FIELD

[0001] The present disclosure relates generally to a communication device that employs communication protocol (e.g., Wi-Fi, Bluetooth, Bluetooth Low-Energy (BLE), etc.) as a radar for object detection, and more particularly to compensating delay from the radar measurements.

BACKGROUND

[0002] Object sensing technique is widely used to detect an object and estimate the object position and velocity. For example, radar system may be used to perform the object sensing technique by employing a radar transmitter and a radar receiver. The use of radar system in consumer devices, such as smart phones, Internet of Things (IoT) devices, and automotive vehicles, is becoming increasingly popular. IoT devices connected to an access point (AP) can act as radar sensors to perform sensing and tracking of the object. For example, the radar sensors can be used in many applications such as to detect a presence and movements people, vehicles, and animals.

[0003] Object sensing using a wireless local area network (WLAN) (“Wi-Fi sensing or WLAN sensing”) signal is considered as an emerging solution for various applications. One of the reasons is because of the prevalent WLAN devices and the ubiquitous nature of WLAN signals that can lead to a wide coverage. Wi-Fi sensing can sense the environment, detect an object, and interpret a movement of the object. Wi-Fi sensing is capable to see through obstructions (e.g., walls) and simply a radar system that spans the range of the network coverage. Wi-Fi sensing allows for an object detection without mobile devices, allowing for tracking of objects that are not carrying a wireless device. The transmitted wireless signal may experience signal attenuation and amplitude distortion because of the presence of the object. Various applications using the WLAN signals include health monitoring, activity classification, people counting, and step counting.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] The present embodiments are illustrated by way of example, and not of limitation, in the figures of the accompanying drawings.

[0005] FIG. 1A is a block diagram illustrating a wireless local network (WLAN) based object detection system, according to some embodiments of the present disclosure.

[0006] FIG. 1B is a block diagram illustrating a WLAN based object detection system, according to some embodiments of the present disclosure.

[0007] FIG. 1C is a block diagram illustrating a wireless communication device, according to some embodiments of the present disclosure.

[0008] FIG. 1D is a block diagram of a technique for merging of non-overlapping WLAN channels, according to some embodiments of the present disclosure.

[0009] FIG. 2 is a block diagram illustrating a WLAN based object detection system and its functionalities, according to some embodiments of the present disclosure.

[0010] FIG. 3 is a block diagram illustrating a delay compensation technique, according to some embodiments of the present disclosure.

[0011] FIG. 4 is a block diagram illustrating a constellation diagram of a channel transfer function (CTF) before and after a delay compensation technique is implemented, according to some embodiments of the present disclosure.

[0012] FIG. 5 is a block diagram illustrating a constellation diagram of a CTF after the delay compensation technique is implemented as a reference for a particular measurement, according to some embodiments of the present disclosure.

[0013] FIG. 6 is a block diagram illustrating a constellation diagram of a CTF after the delay compensation technique is implemented to detect sensing environment changes, according to some embodiments of the present disclosure.

[0014] FIG. 7 is a block diagram illustrating a delay compensation technique, according to some embodiments of the present disclosure.

[0015] FIG. 8 is a functional block diagram illustrating a delay compensation technique, according to some embodiments of the present disclosure.

[0016] FIG. 9 is a block diagrams illustrating a delay compensation technique, according to some embodiments of the present disclosure.

[0017] FIG. 10 is a functional block diagram illustrating a delay compensation technique implemented to remove the delay from the non-overlapping channels, according to some embodiments of the present disclosure.

[0018] FIG. 11 is a functional block diagram illustrating a delay compensation technique implemented as a reference to remove the delay for a particular measurement, according to some embodiments of the present disclosure.

[0019] FIG. 12A is a flow diagram of a method of delay compensation, according to some embodiments of the present disclosure.

[0020] FIG. 12B is a flow diagram of a method of delay compensation, according to some embodiments of the present disclosure.

[0021] FIG. 13 is a detailed block diagram of the wireless communication device of FIG. 1, according to some embodiments of the present disclosure.

[0022] FIG. 14 illustrates a communication device, according to some embodiments of the present disclosure.

DETAILED DESCRIPTION

[0023] In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of the present embodiments. It will be evident, however, to one skilled in the art that the present embodiments may be practiced without these specific details. In other instances, well-known circuits, structures, and techniques are not shown in detail, but rather in a block diagram in order to avoid unnecessarily obscuring an understanding of this description.

[0024] Reference in the description to “one embodiment” or “an embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment. The phrase “in one embodiment” located in various places in this description does not necessarily refer to the same embodiment.

[0025] A 2.4 Giga Hertz (GHz) frequency band of a wireless local network (WLAN), for example, has a total of 14 channels. In some examples, channels 1, 6 and 11 of the 2.4 GHz frequency band are non-overlapping channels so their bandwidth are usable. In another example, a 5 GHz frequency band offers more frequency space and has 25 channels. However, not all channels of the 5 GHz frequency band are usable. WLAN devices are configured for some operations on the non-overlapping channels.

[0026] Radar measurements may be performed to determine location information of an object. The challenge is to resolve two closely spaced objects which have the same range with respect to the Wi-Fi radar transmitter. To resolve two closely spaced objects requires an object detection system that is capable to obtain an improved sensing resolution.

[0027] Wi-Fi radar measurement performed on the non-overlapping channels may be combined to improve sensing resolution. Improved sensing resolution may resolve two closely spaced objects. Each of the non-overlapping channels may use different receiver chain. Because of this, different channel has a different delay and relative phase. The different delay and relative phase can cause incorrect baseline. As a result, the measurement of the reflected signal received at the receiver may be inaccurate. Note that the reflected signal received at the receiver may include a sensing signal

(reflected signal that is reflected off an object) and a baseline signal. Baseline signal may include signal from a parasitic coupling between the transmitter and the receiver. In addition, baseline signal may also include reflections from environment (e.g., cluttering). While Wi-Fi is described herein, similar techniques may be implemented with any wireless protocols, such as Bluetooth and Blue Low-Energy (BLE).

[0028] Compensating the effect of phase distortion caused in the analog and digital chain of a transceiver includes determining calibration parameters of a receiver operating on a first and second channel to determine changes caused by the phase distortion. Other solutions may also include performing temperature sensing to compensate the phase distortion by calculating a new phase distortion in response to identifying changes in the calibration setting. However, such solutions cannot determine all the parameters that cause the delay.

[0029] The embodiments described herein are directed at techniques to remove the phase distortion and signal propagation delay in analog and digital chain of a receiver to accurately combine overlapping Wi-Fi channels for radar sensing. Such techniques may be implemented, for example, when implemented may increase the increase radar sensing resolution.

[0030] In one embodiment, an apparatus is disclosed, the apparatus includes a device to receive a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network. The device determines a plurality of channel transfer functions (CTF) s based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals. The device corrects each of the plurality of CTFs to generate a plurality of corrected CTFs. The device merges the plurality of corrected CTFs to produce a merged CTF. The device senses one or more objects within the wireless network based on the merged CTF.

[0031] The device determines a peak of a frequency spectrum associated with each of the plurality of CTFs. The peak of the frequency spectrum corresponds to a delay distance. The device determines, based on the peak of the frequency spectrum, a delay. The device subtracts the delay from a phase of a subcarrier of each of the plurality of CTFs so that the peak of a frequency spectrum corresponds to a zero distance.

[0032] FIG. 1A is a block diagram of an example of an object detection system **100** utilizing a wireless device, according to some embodiments of the present disclosure.

[0033] Referring to FIG. 1A, the object detection system **100** may include a wireless device **102**. The wireless device **102** may form a wireless network. The wireless network may be a WLAN. The wireless device **102** may be a WLAN device, a Wi-Fi device, or a be narrow band communication device capable of simultaneously transmitting and receiving a radio frequency (RF) signal as well as detecting a transmission time of the radar signal (WLAN, Wi-Fi, BLE, ZigBee). The WLAN device may include a circuitry for enabling radar sensing operation.

[0034] As shown in FIG. 1A, the wireless device **102** may include multiple transceivers **115a-115n** with transmitters **104a-104n** and receivers **106a-106n**. The transceiver **115a** may be coupled to an antenna **144a** (transmit mode) to transmit a signal. The transceiver **115a** may be coupled to an antenna **144a** (receive mode) to receive a signal (e.g., radio frequency (RF) signal) in the wireless network. The transceiver **115a** switches between the transmit mode and receive mode using a Tx/Rx switch (not shown). For example, the transceiver **115a** operates in transmit mode and receive mode to measure the reference signal. The reference signal may include signal that propagates because of a coupling of the Tx/Rx switch. Similarly, the transceiver **115n** may be coupled to an antenna **144n** to transmit a signal. The transceiver **115n** may be coupled to an antenna **144n** to receive a signal. The transceivers **115a-115n** may down convert the received signal to generate a baseband signal. The baseband signal may be processed (filtering, decoding, digitizing) by a receive chain (not shown) in the transceivers **115a-115n**.

[0035] The object detection system **100** may be configured as a monostatic radar system. The monostatic radar is a radar system includes a transmitter (e.g., **104a-104n**) and receiver (e.g., **106a-106n**) that are separated by a distance comparable to the expected target distance. Note that

although the present disclosure describes a monostatic radar configuration, other suitable radar configurations, such as bistatic or multi-static, may be used. Embodiments of the present disclosure may be implemented with the co-located transmitter and receiver having separate antennas (as shown) or a single antenna with a decoupling mechanism.

[0036] The example embodiments described herein are in the context of a WLAN system for simplicity only. It is to be understood that the embodiments described herein are equally applicable to other wireless devices of networks (e.g., Bluetooth, BLE, Pico networks, cellular networks, femto networks, satellite networks, WLAN, Wi-Fi-Direct, personal area network (PAN), ZigBee, Thread, Z-Wave, Sigfox, near-field communication (NF), millimeter wavelength communication (mm-Wave), or the like). The terms WLAN and Wi-Fi may be used interchangeably herein.

[0037] In some embodiments, the wireless device **102** may detect a presence of an object **112** within the wireless network using a wireless signal (hereinafter referred to as signal **108**). The object **112** may be stationary or moving. Although the object **112** is illustrated as a person, the object **112** may also include (for example) a vehicle, an animal, a building, some furniture, a plant, a wall, or a glass window.

[0038] In some examples, the transmitter **104a** transmits a signal **108** via an antenna **144a** to the environment. The signal **108** propagates through space in the environment. The signal **108** may be reflected by the object **112** that is present within the environment. The signal **108** may be attenuated due to various phenomena (e.g., propagation, diffraction, scattering, multipath fading, or the like). The object **112** may alter the characteristics (e.g., amplitude, phase shift) of the signal **108**. The object **112** can also affect the signal **108** to reflect, diffract, or scatter, which causes the signal to propagate across multiple propagation paths.

[0039] The signal that is altered may travel towards the receiver **106a** and may be received by the receiver **106a** as a reflected signal **121** via an antenna **144a**. In addition, the receiver **106a** may also receive a parasitic signal **122** that travels directly from the transmitter **104a** to the receiver **106a**. Upon receiving the reflected signal **121**, the receiver **106a** performs radar processing on the reflected signal to analyze the reflected signal **121**. After the radar processing, the receiver **106a** determines information about the object **112** within the environment. The information about the object **112** may include movement information (e.g., Doppler velocity and/or total velocity), position information (e.g., distance and/or angles), and/or size information (e.g., width, length, and/or height).

[0040] In some examples, the wireless device **102** is a WLAN device operating as a radar device that can transmit and receive a signal simultaneously. If the object **112** is located far from the wireless device **102** or absent from the environment, the parasitic path associated with parasitic signal **122** may be dominant when compared to the reflected signal from the environment. The parasitic path may be referred to the path that the parasitic signal **122** travels from the transmitter **104a**, **104n** to the receiver **106a**, **106n**. The parasitic path may be assumed as zero distance because of the parasitic path has a small distance.

[0041] FIG. **1B** is a block diagram of an example of a wireless device **130** according to an embodiment.

[0042] Referring to FIG. **1B**, a wireless device **130** may include two receiver channels. For example, the receiver channels include a sensing channel **132** that measures the reflected signal **121**. The reflected signal **121** received at the receiver of the sensing channel **132** may include a sensing signal associated with an object **112** and the baseline signal. The baseline signal may include the parasitic signal caused by the coupling within a transceiver, and the cluttering from the environment. The parasitic signal may also be caused by an internal coupling within the transceiver of the wireless device and an antenna coupling between multiple transceivers.

[0043] A reference channel **134** measures the reference signal **123** that propagates via a coupling of a transmitter and a receiver associated with a transceiver of a wireless device. Reference signal **123** may be associated with a transmitted signal. Reference signal **123** may be used to determine a

transmission time and a shape of the transmitted signal associated with the sensing signal.

[0044] As shown, the receiver **106** as described in FIG. **1** can operate at different (non-overlapped) channels (e.g., sensing channel **132** and reference channel **134**). Each channel may have its own receiver chain with a specific setting. For example, the receiver chain **136** of the sensing channel **132** may include components, such as low-noise amplifier (LNA), mixer, Receiver (Rx)-analog chain and Rx-digital chain. The receiver chain **138** of the sensing channel **134** may include components, such as LNA, mixer, Rx-analog chain, and Rx digital chain. Different components within each channel may cause different delay and relative phase.

[0045] FIG. **1C** is a block diagram illustrating a communication device **102** (hereinafter referred to as device **102**), which may be a communication circuit that includes a transceiver operating using a communication protocol.

[0046] In the example of FIG. **1C**, the device **102** may include a WLAN transceiver **115**. In addition, the device **102** may be implemented on a single die, or may be implemented using multiple dies in a single package. The WLAN transceiver **115** may comprise a transmit chain **118A** and a receive chain **118B** and both the transmit chain **118A** and the receive chain **118B** may be comprised of signal processing components such as a LNA, a mixer, a variable gain amplifier, and a low pass filter (not illustrated). The WLAN transceiver **115** may further comprise a Transmitter/Receiver (Tx/Rx) switch **118C** to switch between the Tx chain **118A** and the Rx chain **118B**. More specifically, the Tx/Rx switch **118C** may selectively couple the port **131** to the Tx chain **118A** to allow for transmission of signals via an antenna **119** or couple the port **131** to the Rx chain **118B** to allow for reception of signals via the antenna **119**. A cable **120** may be coupled to the port **131** and to the antenna **119**. The Tx chain **118A** may also be coupled to an analog-to-digital converter (ADC) **117A** which it may use to digitize received signals and output the digitized signals to a digital demodulator **116** (also referred to as a digital detector) which may extract any information content from the received digitized signals (e.g., by extracting the information bearing signal from a carrier wave). The Rx chain **118B** may also be coupled to a digital-to-analog converter (DAC) **117B** which it may use to convert the digitized received signals and output the analog signals to a digital demodulator **116**.

[0047] As shown in FIG. **1C**, device **102** further includes a processing device **105** and a memory **109** which may include channel merging module **107**. Processing device **105** may execute the channel merging module **107** to perform the channels merging techniques described herein. Although illustrated by way of example as a software module stored in memory **109** and accessed/executed by processing device **105**, the functionality of the channel merging module **107** may be realized using dedicated hardware (e.g., an application specific integrated circuit (ASIC)) or as a firmware module within the processing device **105**. The channel merging module **107** may include a measurement module **107A**, a delay compensation module **107B** and a signal merging module **107C**.

[0048] As will be seen, the processing device **105** may use the method discussed herein to determine a transfer function by using the WLAN transceiver **115** as the receiver device and the reference device.

[0049] FIG. **1D** illustrates a block diagram of a channel merging module **107** according to an embodiment. The channel merging module **107** may be implemented by wireless device **102** of FIG. **1A** to detect the presence of an object (e.g., such as a person) in a wireless channel.

[0050] Referring to FIG. **1D**, channel merging module **107** may include a measurement module **107A**, a delay compensation module **107B** and a signal merging module **107C**.

[0051] The measurement module **107A** receives a reference signal and a reflected signal **121** from the environment. For example, measurement module **107A** receives a reference signal that corresponds to the parasitic signal. Based on the reference signal and the reflected signal **121**, the measurement module **107A** may determine a CTF. The measurement module **107A** may receive the reference signal and the reflected signal **121** from multiple channels. Each channel may contain

different delays (or phase change) that may be caused by the analog and digital chain networks.

[0052] The delay compensation module **107B** may determine a delay and relative phase distortion based on the CTF. For example, the delay compensation module **107B** performs an inverse discrete Fourier transform (IDFT) or correlation to generate a frequency spectrum. The delay compensation module **107B** determines a delay based on a peak in (e.g., IDFT/correlation) frequency spectrum caused by the parasitic or coupling signal.

[0053] The delay compensation module **107B** may compensate the delay by subtracting the delay from the phase of the subcarrier. In this manner, the correlation peak aligns for all WLAN channels.

[0054] The signal merging module **107C** merges the corrected CTF (before or after baselining).

[0055] The corrected CTF may be used to correct future measurements. A peak of the corrected CTF may correspond to a zero distance on the x-axis of the corrected CTF (will be described in details in connection with FIG. 3). The corrected CTF may exclude the parasitic coupling and cluttering by subtracting the baseline. The corrected CTF provides an estimate of the analog/digital chains settings to use for future measurements of a similar environment condition. An average of the corrected CTF for particular channel may be used to remove dynamical changes (e.g., moving object) from the measurement.

[0056] FIG. 2 is a block diagram illustrating a wireless local network (WLAN) based object detection system and its functionalities, according to some embodiments of the present disclosure.

[0057] Referring to FIG. 2, the object detection system **200** may include a 2×2 Wi-Fi circuit **202** being used as 1×1 (1 Tx antenna and 1 Rx antenna) radar transceiver IC. The 2×2 Wi-Fi circuit **202** may include circuitry for enabling radar sensing operation for Wi-Fi device. FIG. 2 shows only one example of a Wi-Fi circuit **202** and various changes may be made to FIG. 2. Note that the Wi-Fi circuit **202** may include any number of each component illustrated in FIG. 2. Note that although the Wi-Fi circuit **202** only shows two transmitting and two receiving antennas (2×2) as illustrated in FIG. 2, any number of antennas may also be used. Although the Wi-Fi circuit **202** only shows two transceivers **115a** and **115b** as shown in FIG. 2, any number of transceivers could also be used.

[0058] In some embodiments, orthogonal frequency division multiplexing (OFDM) repeating symbols may be used as a signal to sense the environment. For example, using the OFDM symbol generator **240**, the transmitter chain **242** transmits an OFDM-based signal **208** to the environment. Although the OFDM-based signal is illustrated in this embodiment, other suitable waveforms (e.g., modulation type) for sensing operations such as an orthogonal time frequency space signal (OTFS) may be used. Any waveform having suitable self-correlation properties may be used for the signal to perform radar sensing in this embodiment. During the transmission operation, a parasitic signal **222** may travel from the transmitter to the receiver. The parasitic signal **222** may be received and processed using a receiver chain **244**. The parasitic signal may be used as a reference signal.

[0059] The receiver chain **244** may receive a reflected signal **221** from the environment. The reflected signal **221** may be based on the signal **208** that is reflected off an object in the environment.

[0060] The receiver and reference signal calculator **246** may obtain the reference signal based on the parasitic signal **222** received by the receiver chain **244**. The receiver and reference signal calculator **246** may obtain the reflected signal **221**.

[0061] Based on the reference signal and the reflected signal **221**, CTF generator **248** (corresponds to the delay compensation module **107B** module) may determine a CTF. For example, the delay compensation module **107B** may extract the complex amplitude of each subcarrier of the reflected signal **221** and the reference signal **222**. Then, for each subcarrier, the delay compensation module **107B** module calculates a ratio between the complex amplitude of the reflected signal **221** and the complex amplitude of the reference signal **222**.

[0062] Note that for a 1×1 Wi-Fi device operating as a 1×1 radar, the CTF may be calculated based on the characteristic of the reflected signal **221** (e.g., shape and transmission time of the reflected signal).

[0063] The CTF generator **248** may perform a delay compensation to compensate a delay and relative phase caused by the analog and digital components of the receiver chain. Pi-jump in phase of the CTF may be compensated if needed. In this manner, during the baselining operation **250**, the static or slowly changing environment and parasitic signal contribution may be removed. Therefore, the reflected signal that may not include the parasitic signal contribution and can be utilized to detect the object accurately.

[0064] The above-described procedures may be repeated for a number of different channels before the reflected signal is used for detecting the object. The reflected signals without the parasitic signal contribution may be merged to obtain a higher resolution measurement for detecting the object accurately.

[0065] After the merging of the signals, the wireless device **102** may perform object detection using the moving target detection operation **252** to detect a presence of an object in the environment. The wireless device **102** may perform object ranging using a ranging operation **254** before the wireless device **102** generates a sensing report based on the presence of the object in the environment. The sensing report may include distance (range), angle and radial velocity of the object relative to the transceiver.

[0066] FIG. **3** illustrates a delay compensation technique for determining a reference constellation for a channel, according to some embodiments of the present disclosure. The reference constellation may refer to a constellation diagram representing the corrected sets $\{\{\textcircled{x}\}\}$ of the corrected CTF. The reference constellation may have a corresponding frequency spectrum including a peak (maximum) that corresponds to a zero delay (without a delay). The peak may also be referred to as maximum in this disclosure.

[0067] Referring to FIG. **3**, a Wi-Fi device with radar capability may include two transceivers. For example, a 2×2 Wi-Fi device includes a first transceiver having a first receiver chain **336** and a second transceiver having a second receiver chain **338**.

[0068] The first receiver chain **336** receives a reference signal **322** that travels from the transmitter of the transceiver. The reference signal **322** may correspond to a signal that travels from a transmitter directly to the receiver via an internal parasitic or design coupling. The parasitic signal may be used to calculate the propagation time of a signal. The second receiver chain **338** receives a reflected signal **321** that is reflected off an object in the environment. The reflected signal **321** may also include parasitic signals from a coupling between two transceivers. Antenna **340** may be utilized to receive a reference signal **322** over a predetermined bandwidth as shown in FIG. **3**. Antenna **342** may be utilized to receive a reflected signal **321** over a predetermined bandwidth as shown in FIG. **3**.

[0069] In-Phase (I) and Quadrature (Q) samples of the ratio of the reflected signal and the reference signal may be represented by a constellation diagram. The IQ samples are out of phase with each other. A constellation diagram is a two-dimensional method of visualizing the signal. For example, the constellation diagram **360** shows a set of subcarriers of the reference signal relative to the transmitted signal on I-Q domain. A particular symbol (e.g., symbol **361**) on the constellation diagram corresponds to a particular frequency (e.g., a particular subcarrier for the OFDM signal). Because of the different delay, the location of the phase of the particular subcarrier on the constellation diagram may shift.

[0070] A frequency spectrum **362** may be generated based on the constellation diagram by using a correlation technique or an inverse discrete Fourier transform (IDFT). The frequency spectrum may be used to determine a peak **363** that corresponds to a zero distance. The peak **363** may correspond to a peak of the frequency spectrum that has a maximum amplitude. For example, when the receiver receives a reference signal or a parasitic signal, the peak **363** of the frequency spectrum corresponds to a zero distance. In this situation, the parasitic signal is dominant compared to the reflected signal.

[0071] FIG. **4** is a diagram illustrating a delay compensation technique for determining a CTF with

and without delay components, according to some embodiments of the present disclosure.

[0072] Referring to FIG. 4, a CTF may be determined based on a reflected signal and a reference signal. For example, delay compensation module 107B of FIG. 1 measures the CTF {x} that provides a constellation diagram 402, which includes delay.

[0073] The delay compensation module 107B module performs correlation (or IDFT) to generate a frequency spectrum |C| 404 that has peak at “delay” distance.

[0074] To remove the delay that is identified in the frequency spectrum 404, the delay compensation module 107B module may determine a delay, Δ . For example, the delay can be determined based on an equation, $\Delta=d/c$, where Δ is a delay, d is a distance obtained from the frequency spectrum 404, and c is the speed of light.

[0075] After the delay has been determined, the delay compensation module 107B module may perform a delay compensation for each subcarrier of the channel. The delay compensation for the subcarrier may be performed according to the following equation to generate the corrected set $\{\{\text{circumflex over (x)}\}\}$.

$$[00001] \hat{x}_j = x_j * \exp(-i \omega_{\text{sub}.j} \Delta)$$

where $\omega_{\text{sub}.j}$ is an angular frequency of a subcarrier j of a channel, Δ is a delay.

[0076] A constellation diagram 406 represents the corrected sets $\{\{\text{circumflex over (x)}\}\}$ of the corrected CTF. The corresponding frequency spectrum 408 includes a peak that corresponds to a zero delay (without a delay). This means the delay caused by the analog and digital component in the receiver chain has been compensated.

[0077] FIG. 5 is a diagram illustrating a delay compensation technique for merging CTFs without delay components, according to some embodiments of the present disclosure.

[0078] Referring to FIG. 5, a constellation diagram 502 represents a corrected CTF of a first wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.k$ without the delay. The horizontal real axis of the constellation diagram represents the Q component, and the vertical real axis of the constellation diagram represents the I component. The delay compensation technique has been applied to the CTF of the first wireless channel. A constellation diagram 504 represents a corrected CTF of a second wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.m$. Similarly, the delay compensation technique has been applied to the CTF of the second wireless channel.

[0079] Because the delay has been compensated in first wireless channel and the second wireless channel, the corrected transfer function of the first wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.k$ and the corrected transfer function of the second wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.m$ can be merged. In this manner, the resolution of the sensing system can be enhanced. For example, a constellation diagram 506 represents a transfer function of the first wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.k$ and the second wireless channel $\{\{\text{circumflex over (x)}\}\}.\text{sub}.m$ that has been merged. Note that although there are only two wireless channels as shown in FIG. 5, more wireless channels may also be measured to accommodate the expected sensing resolution.

[0080] In some embodiments, a plurality of non-overlapping wireless channels include a first non-overlapping wireless channel. The corrected CTF associated with the first non-overlapping wireless channel may be generated based on a first measurement of a first reference signal and a first sensing signal at a first time period. The corrected CTF associated with the first non-overlapping wireless channel may be used to determine a new corrected CTF associated with a second measurement of a second reference signal and a second sensing signal at a second time period.

[0081] FIG. 6 is a diagram illustrating a delay compensation technique based on a reference corrected CTF, according to some embodiments of the present disclosure.

[0082] Referring to FIG. 6, a constellation diagram 602 represents a corrected CTF at time $t.\text{sub}.0$ denoted as $\{\{\text{circumflex over (x)}\}(t.\text{sub}.0)\}$. The corrected CTF at time $t.\text{sub}.0$ can be used as a reference CTF for a measurement at a different time, for example, at time $t.\text{sub}.1$. A constellation diagram 604 represents a corrected CTF of a measurement at time $t.\text{sub}.1$ denoted as $\{x(t.\text{sub}.1)\}$. The delay compensation operation can be applied to the measurement at time $t.\text{sub}.1$ based on the

reference CTF using a minimization Euclidian distance technique. For example, the minimization Euclidian distance technique may be given as $|\{\text{circumflex over (x)}\}(t.\text{sub}.0) - \{\text{circumflex over (x)}\}(t.\text{sub}.1) * \exp(i\omega\Delta)|.\text{sup}.2.\text{fwdarw}.0$ for given Δ where Δ is the delay. Referring to FIG. 6, the minimization Euclidian distance technique may be applied to the measurement at time $t.\text{sub}.1$ as denoted by the constellation diagram 604. The corresponding frequency spectrum 606 indicates a corrected CTF of a measurement at time $t.\text{sub}.1$ with the delay has been compensated.

[0083] This correction technique may be used to compensate pi-jump which is caused by dividing VCO frequency.

[0084] In some embodiments, the corrected CTF associated with the first non-overlapping wireless channel may be subtracted from the new corrected CTF associated to determine a change in an environment between the first time period and the second time period.

[0085] In some embodiments, a second reference signal and a second sensing signal at a future time may be received. The future time may refer to a later time than an initial time. A second CTF based on the second reference signal and a second sensing signal may be determine. The corrected CTF may be compared (e.g., subtracted) from the second CTF to determine the changes in the environment. The corrected CTF may refer to the corrected CTF.

[0086] FIG. 7 is a diagram illustrating a delay compensation technique for detecting environment changes, according to some embodiments of the present disclosure.

[0087] Referring to FIG. 7, a constellation diagram 702 represents a corrected CTF of a measurement at time $t.\text{sub}.1$ denoted as $\{\{\text{circumflex over (x)}\}(t.\text{sub}.1)\}$. A constellation diagram 704 represents a corrected CTF at time $t.\text{sub}.0$ denoted as $\{\{\text{circumflex over (x)}\}(t.\text{sub}.0)\}$.

[0088] The corrected CTF at time $t.\text{sub}.0$ is $\{\{\text{circumflex over (x)}\}(t.\text{sub}.0)\}$ can be used as reference for measurements $\{\text{x}(t.\text{sub}.1)\}$ at time $t.\text{sub}.1$ using minimization Euclidian distance between the measurements at time $t.\text{sub}.1$ and $t.\text{sub}.0$.

[0089] For example, the minimization Euclidian distance technique may be given as $|\{\{\text{circumflex over (x)}\}(t.\text{sub}.0)\} - \{\text{x}(t.\text{sub}.1) * \exp(i\omega\Delta)\}|.\text{sup}.2.\text{fwdarw}.0$ for given Δ where Δ is the delay.

[0090] The corrected CTF of a measurement at time $t.\text{sub}.1$ $\{\{\text{circumflex over (x)}\}(t.\text{sub}.1)\}$ may include information about changes in the environment $\{s(t.\text{sub}.1)\}$.

[0091] The changes in the environment $\{s(t.\text{sub}.1)\}$ may be determined based on the corrected CTF at time $t.\text{sub}.0$. For example, the changes in the environment $\{s(t.\text{sub}.1)\}$ is determined by subtracting the corrected CTF at time $t.\text{sub}.0$ from the corrected CTF of a measurement at time $t.\text{sub}.1$ $\{\{\text{circumflex over (x)}\}(t.\text{sub}.1)\}$. The changes in the environment $\{s(t.\text{sub}.1)\}$ 706 may be determined using $\{s(t.\text{sub}.1)\} = \{\{\text{circumflex over (x)}\}(t.\text{sub}.1) - \{\text{circumflex over (x)}\}(t.\text{sub}.0)\}$. This process may be defined as baselining in which a corrected CTF at a time t is subtracted from a corrected CTF at a future time $(t+x)$. The baselining may remove the parasitic signal and cluttering from the reflected signal received at the receiver.

[0092] After the baselining, the reflected signals from different channels can be merged to increase the sensing resolution. Note that the sensing from different channels can be merged signals after the baselining. For example, the changes in the environment for channel k $\{s(t.\text{sub}.1)\}.\text{sub}.k$ is merged with the changes in the environment for channel m $\{s(t.\text{sub}.1)\}.\text{sub}.m$ after the baselining according to the following equation:

$$[00002] \{s(t_1)\}_{k+m} = \{s(t_1)\}_k + \{s(t_1)\}_m$$

[0093] FIG. 8 is a diagram illustrating a delay compensation technique for reusing settings, according to some embodiments of the present disclosure.

[0094] In some embodiments, if the amplitude of the parasitic signal is equal to the amplitude of the sensing signal, CTF may include multiple peaks. In this case, the first peak of the frequency spectrum may correspond to the parasitic signal. For example, if the parasitic signal is comparable to the sensing signal, the object of closely located objects may appear closer than the actual distance. If the object is far with respect to the receiver, the first peak of the frequency spectrum may correspond to the parasitic signal.

[0095] In some embodiments, if the amplitude value of the parasitic signal is smaller than the amplitude value of the reference signal, a first correlation peak of the CTF may correspond to the parasitic signal. For example, if the reflection of the transmitted signal is larger than parasitic signal, the first peak **802** of the frequency spectrum may correspond to the parasitic signal. Note that the reflection of the transmitted signal may correspond to the reflected signal.

[0096] To improve the detection of the peak in the frequency spectrum, a peak search technique, such as MULTiple Signal Classification (MUSIC) may be used. MUSIC is a high-resolution direction-finding algorithm based on the eigenvalue decomposition of the sensor covariance matrix observed at an array. For example, if the peaks are close to each other, MUSIC can be used to separate the peaks and identify the peak of the frequency spectrum.

[0097] If peaks are aligned for different channels (the distance corresponding to the peak of the frequency spectrum is zero), parameters of the digital or analog front-end of a receiver chain can be determined to establish settings for a particular WLAN channel. For example, the delay compensation technique as described herein may be used to determine a delay for a receiver chain with a particular setting and operating on a particular channel. The receiver chain may have a particular setting for automatic gain control (AGC), imbalance compensation, analog and digital filters, etc. The setting for the particular receiver chain and the delay for the operating channel may be stored. The stored particular setting of the receiver chain and the delay may be used for a future measurement of the particular channel. The stored delay may be used as an initial value to perform the delay compensation technique as described above. Therefore, the stored settings can be used for future measurements to decrease the search operation for the peak in the frequency spectrum.

[0098] In this manner, the delay compensation technique may reduce the computation time for environment with similar conditions.

[0099] For example, as shown in FIG. **8**, a measurement of a sensing signal and a reference signal for a channel are received in step **804** to determine a CTF. Then, a compensation delay technique is applied to estimate the delay for compensating the delay from the sensing signal. The delay estimate may be used as a reference setting in step **806** for the next measurements in step **808** of the same channel. The environment of the measurement for different time of the same channel may be verified in step **810**. For example, a temperature reading may be obtained using a temperature sensor to verify that the environment of the measurement is similar to the environment of the measurement to obtain the reference setting. If the environment of the measurement of the same channel is similar to the environment of the measurement to obtain the reference setting, the reference setting may be used in step **812** for current measurement. The current measurement in step **814** should provide the same delay for CTF that can be corrected.

[0100] FIG. **9** is a diagram illustrating a delay compensation technique for averaging for the corrected CTF, according to some embodiments of the present disclosure.

[0101] Referring to FIG. **9**, an average of a set of corrected CTF may be determined to remove dynamical changes (e.g., movement of a fan). In some embodiments, the plurality of corrected CTFs may be averaged to generate an averaged corrected CTFs.

[0102] The average value may be based on performing the delay compensation on the reference signal and the sensing signal for the channel for at least one iteration. For example, a set of corrected CTF of a channel includes a corrected CTF **902** and a corrected CTF **904**. The average **906** of the corrected of the set of corrected CTF is determined based on the corrected CTF **902** and the corrected CTF **904**.

[0103] FIG. **10** is a block diagram illustrating an example data processing method **1000** for an object sensing according to an embodiment.

[0104] Referring to FIG. **10**, the data processing method is associated with a WLAN radar with two cores performing a measurement at time (or interval) $t_{sub.n}$ for two different WLAN channels m and k to determine the CTF.

[0105] As shown, at **1002**, the reference and the reflected signals may be obtained to determine the

CTF.

[0106] At **1004**, delay compensation may be applied to each channel to compensate the delay caused by filters in the receiving chain. For example, a frequency spectrum $|C(d)|$ for the CTF is determined.

[0107] At **1006**, based on the frequency spectrum, a peak of the frequency spectrum is determined.

[0108] At **1008**, the delay is determined based on the peak of the frequency spectrum.

[0109] At **1010**, the delay is compensated for each subcarrier of the CTF to generate a corrected CTF.

[0110] Method **1002** and **1004** may be repeated for each non-overlapping channel.

[0111] At **1012**, the corrected CTF of the different WLAN channels (e.g., channel k and m) may be merged. For example, the corrected CTF of a channel k and the corrected CTF of k channel m are merged.

[0112] At **1014**, after the corrected CTF of the different WLAN channels are merged at **1012**, the baselining operation as described above (e.g., see FIG. 7) may be applied to the merged corrected CTF of the non-overlapped, k and m channels. The baselining operation may be performed to remove the delay to detect a presence of an object in the environment. The baselining operation may also be performed before the operation **1012**. The baselining operation **1014** may subtract the current measurement from the previous measurement for the same channels to identify changes (e.g., moving objects) in the environment.

[0113] Optionally, the baselining process **1014** may be applied to the channels separately before the merging of the corrected CTF of the channels. For example, firstly, the baselining process is applied to the corrected CTF of the channel k. Secondly, the baselining process is applied to the corrected CTF of the channel m. After the baselining process is performed for the channels k and m, the corrected CTF of a channel k and the corrected CTF of k channel m are merged.

[0114] At **1016**, a ranging may be performed to determine a location information, including target location.

[0115] FIG. 11 is a block diagram illustrating an example data processing method **1000** for an object sensing according to an embodiment.

[0116] Wi-Fi radar may use initialization of delay compensation to reduce computation power. The procedures **1106**, **1108**, **1110** may be similar to procedures **1006**, **1008**, **1010** of FIG. 10.

[0117] At **1101**, an initial measurement of two channels at time (or interval) $t_{\text{sub}.0}$ be performed to determine the CTF. As shown, at **1101**, the reference and the reflected signals may be obtained to determine the CTF of channel k at time $t_{\text{sub}.0}$. Similarly, the reference and the reflected signals may be obtained to determine the CTF of channel m at time $t_{\text{sub}.0}$.

[0118] At **1105**, a reference CTF for a channel may be computed. For example, a reference CTF for channel k is determined. The reference CTF may be determined using procedures **1106**, **1108**, and **1110** as described above.

[0119] At **1107**, a measurement of two channels at time (or interval) $t_{\text{sub}.n}$ may be performed to determine the CTF. As shown, at **1107**, the reference and the reflected signals may be obtained to determine the CTF of channel k at time $t_{\text{sub}.n}$. Similarly, the reference and the reflected signals may be obtained to determine the CTF of channel m at time $t_{\text{sub}.n}$.

[0120] After **1107**, at **1118**, in some embodiments, the delay of a future measurement may be determined using a minimization Euclidian distance technique and based on a reference CTF. For example, a delay compensation may be performed using the reference CTF obtained at **1105**.

[0121] At **1120**, the delay compensation operation can be applied to the measurement at time $t_{\text{sub}.n}$ based on the reference CTF using a minimization Euclidian distance technique. For example, the minimization Euclidian distance technique may be given as $|\{\circ(x)\}(t_{\text{sub}.0}) - x(t_{\text{sub}.n}) * \exp(i\omega\Delta)|_{\text{sup.2.fwdarw.0}}$ for given Δ where Δ is the delay.

[0122] The procedure can continue by applying procedure **1112** which is similar to procedure **1012** of FIG. 10. At **1112**, the corrected CTF of the different WLAN channels (e.g., channel k and m)

may be merged. For example, the corrected CTF of a channel **k** and the corrected CTF of **k** channel **m** are merged.

[0123] FIG. **12A** is a flow diagram of a method **1200** for removing the delay from sensing signals, in accordance with some embodiments of the present disclosure. Method **1200** may be performed by processing logic that may comprise hardware (e.g., circuitry, dedicated logic, programmable logic, a processor, a processing device, a central processing unit (CPU), a system-on-chip (SoC), etc.), software (e.g., instructions running/executing on a processing device), firmware (e.g., microcode), or a combination thereof. For example, the method **1200** may be performed by the processing device **105** executing module **107B**.

[0124] Referring also to FIG. **12A**, at block **1202**, the processing device **105** may receive a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network.

[0125] At block **1204**, the processing device may determine a plurality of CTFs based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals.

[0126] At block **1206**, the processing device **105** may correct each of the plurality of CTFs to generate a plurality of corrected CTFs.

[0127] At block **1208**, the processing device **105** may merge the plurality of corrected CTFs to produce a merged CTF.

[0128] At block **1210**, the processing device **105** may sense one or more objects within the wireless network based on the merged CTF.

[0129] FIG. **12B** is a flow diagram of a method **1220** for performing a delay compensation in accordance with some embodiments of the present disclosure. Method **1100** may be performed by processing logic that may comprise hardware (e.g., circuitry, dedicated logic, programmable logic, a processor, a processing device, a central processing unit (CPU), a system-on-chip (SoC), etc.), software (e.g., instructions running/executing on a processing device), firmware (e.g., microcode), or a combination thereof. For example, the method **1100** may be performed by the processing device **105** executing module **107B**.

[0130] Referring to FIG. **12B**, at block **1222**, the processing device **105** may determine a peak of a frequency spectrum associated with each of the plurality of CTFs, wherein the peak of the frequency spectrum corresponds to a delay distance.

[0131] At block **1224**, the processing device **105** may determine, based on the peak of the frequency spectrum, a delay.

[0132] At block **1226**, the processing device **105** may subtract the delay from a phase of a subcarrier of each of the plurality of CTFs so that the peak of a frequency spectrum corresponds to a zero distance.

[0133] FIG. **13** is a simplified block diagram **1300** of the communication device **102** with a more detailed view of the WLAN device **115** inset, in accordance with some embodiments of the present disclosure. The device **102** may include a general purpose input/output (GPIO) **1305**, and the WLAN device **115**. The WLAN device **115** may be connected to antenna **142** and **144**. The GPIO **1305** may comprise an uncommitted digital signal pin which may be used as an input or output for the WLAN device **115**. The WLAN device **115** may include a processing device **1309**, a memory **1310**, a physical layer chip **1315** and a media access control (MAC) layer chip **1320**. The physical layer chip **1315** may handle conversion of a signal from a clocked digital format into an analog format suitable for longer range transmission and vice versa. The MAC layer chip **1320** may assemble bits received from the physical layer chip **1315** into packets and validate them, as well as receive packets of data from the processing device **1309** for example, and convert them to streams of bits to be provided to the physical layer chip **1315**. It should be noted that FIG. **13** illustrates an embodiment where the WLAN device **115** include their own dedicated processing device and memory, and the instructions for performing the techniques described herein may be included as firmware within the memory of the WLAN device **115**.

[0134] FIG. 14 is a block diagram illustrating a communication device 1400, in accordance with some embodiments of the present disclosure. The communication device 1400 may fully or partially include and/or operate the example embodiments of the communication device 102 or portions thereof as described with respect to FIGS. 1-9. The communication device 1400 may be in the form of a computer system within which sets of instructions may be executed to cause the communication device 1400 to perform any one or more of the methodologies discussed herein. The communication device 1400 may operate as a standalone device or may be connected (e.g., networked) to other machines. In a networked deployment, the communication device 1400 may operate in the capacity of a server or a client machine in server-client network environment, or as a peer machine in a P2P (or distributed) network environment.

[0135] The communication device 1400 may be an Internet of Things (IoT) device, a server computer, a client computer, a personal computer (PC), a tablet, a set-top box (STB), a voice controlled hub (VCH), a Personal Digital Assistant (PDA), a mobile telephone, a web appliance, a network router, switch or bridge, a television, speakers, a remote control, a monitor, a handheld multi-media device, a handheld video player, a handheld gaming device, or a control panel, or any other machine capable of executing a set of instructions (sequential or otherwise) that specify actions to be taken by that machine. Further, while only a single communication device 1400 is illustrated, the term “device” shall also be taken to include any collection of machines that individually or jointly execute a set (or multiple sets) of instructions to perform any one or more of the methodologies discussed herein.

[0136] The communication device 1400 is shown to include processor(s) 1402.

[0137] In embodiments, the communication device 1400 and/or processors(s) 1402 may include processing device(s) 1405 such as a System on a Chip processing device, developed by Cypress Semiconductor Corporation, San Jose, Calif. Alternatively, the communication device 1400 may include one or more other processing devices known by those of ordinary skill in the art, such as a microprocessor or central processing unit, an application processor, a host controller, a controller, special-purpose processor, digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), or the like. Bus system 1401 may include a communication block (not shown) to communicate with an internal or external component, such as an embedded controller or an application processor, via communication interfaces(s) 1409 and/or bus system 1401.

[0138] Components of the communication device 1400 may reside on a common carrier substrate such as an IC die substrate, a multi-chip module substrate, or the like. Alternatively, components of the communication device 1400 may be one or more separate ICs and/or discrete components.

[0139] The memory system 1404 may include volatile memory and/or non-volatile memory which may communicate with one another via the bus system 1401. The memory system 1404 may include, for example, random access memory (RAM) and program flash. RAM may be static RAM (SRAM), and program flash may be a non-volatile storage, which may be used to store firmware (e.g., control algorithms executable by processor(s) 1402 to implement operations described herein). The memory system 1404 may include instructions 1403 that when executed perform the methods described herein. Portions of the memory system 1404 may be dynamically allocated to provide caching, buffering, and/or other memory-based functionalities.

[0140] The memory system 1404 may include a drive unit providing a machine-readable medium on which may be stored one or more sets of instructions 1403 (e.g., software) embodying any one or more of the methodologies or functions described herein. The instructions 1403 may also reside, completely or at least partially, within the other memory devices of the memory system 1404 and/or within the processor(s) 1402 during execution thereof by the communication device 1400, which in some embodiments, constitutes machine-readable media. The instructions 1403 may further be transmitted or received over a network via the communication interfaces(s) 1409. The communication interface(s) 1409 may be where the communication device 102 discussed herein is

implemented.

[0141] While a machine-readable medium is in some embodiments a single medium, the term “machine-readable medium” should be taken to include a single medium or multiple media (e.g., a centralized or distributed database, and/or associated caches and servers) that store the one or more sets of instructions. The term “machine-readable medium” shall also be taken to include any medium that is capable of storing or encoding a set of instructions for execution by the machine and that cause the machine to perform any one or more of the example operations described herein. The term “machine-readable medium” shall accordingly be taken to include, but not be limited to, solid-state memories, and optical and magnetic media.

[0142] The communication device **1400** is further shown to include display interface(s) **1406** (e.g., a liquid crystal display (LCD), touchscreen, a cathode ray tube (CRT), and software and hardware support for display technologies), audio interface(s) **1408** (e.g., microphones, speakers and software and hardware support for microphone input/output and speaker input/output). The communication device **1400** is also shown to include user interface(s) **1410** (e.g., keyboard, buttons, switches, touchpad, touchscreens, and software and hardware support for user interfaces).

[0143] In the above description, numerous details are set forth. It will be apparent, however, to one of ordinary skill in the art having the benefit of this disclosure, that embodiments of the present disclosure may be practiced without these specific details. In some instances, well-known structures and devices are shown in block diagram form, rather than in detail, in order to avoid obscuring the description.

[0144] Some portions of the detailed description are presented in terms of algorithms and symbolic representations of operations on data bits within a computer memory. These algorithmic descriptions and representations are the means used by those skilled in the data processing arts to most effectively convey the substance of their work to others skilled in the art. An algorithm is here and generally, conceived to be a self-consistent sequence of steps leading to a desired result. The steps are those requiring physical manipulations of physical quantities. Usually, though not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared and otherwise manipulated. It has proven convenient at times, principally for reasons of common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

[0145] It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities. Unless specifically stated otherwise as apparent from the above discussion, it is appreciated that throughout the description, discussions utilizing terms such as “transmitting,” “receiving,” “comparing,” “determining,” “detecting,” “classifying,” or the like, refer to the actions and processes of a computing system, or similar electronic computing device, that manipulates and transforms data represented as physical (e.g., electronic) quantities within the computing system's registers and memories into other data similarly represented as physical quantities within the computing system memories or registers or other such information storage, transmission or display devices.

[0146] The words “example” or “exemplary” are used herein to mean serving as an example, instance, or illustration. Any aspect or design described herein as “example” or “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects or designs. Rather, use of the words “example” or “exemplary” is intended to present concepts in a concrete fashion. As used in this application, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or.” That is, unless specified otherwise, or clear from context, “X includes A or B” is intended to mean any of the natural inclusive permutations. That is, if X includes A; X includes B; or X includes both A and B, then “X includes A or B” is satisfied under any of the foregoing instances. In addition, the articles “a” and “an” as used in this application and the appended claims should generally be construed to mean “one or more” unless specified otherwise or clear from context to

be directed to a singular form. Moreover, use of the term “an embodiment” or “one embodiment” or “an implementation” or “one implementation” throughout is not intended to mean the same embodiment or implementation unless described as such.

[0147] Embodiments described herein may also relate to an apparatus for performing the operations herein. This apparatus may be specially constructed for the required purposes, or it may comprise a general-purpose computer selectively activated or reconfigured by a computer program stored in the computer. Such a computer program may be stored in a non-transitory computer-readable storage medium, such as, but not limited to, any type of disk including floppy disks, optical disks, CD-ROMs and magnetic-optical disks, read-only memories (ROMs), random access memories (RAMs), EPROMs, EEPROMs, magnetic or optical cards, flash memory, or any type of media suitable for storing electronic instructions. The term “computer-readable storage medium” should be taken to include a single medium or multiple media (e.g., a centralized or distributed database and/or associated caches and servers) that store one or more sets of instructions. The term “computer-readable medium” shall also be taken to include any medium that is capable of storing, encoding, or carrying a set of instructions for execution by the machine and that causes the machine to perform any one or more of the methodologies of the present embodiments. The term “computer-readable storage medium” shall accordingly be taken to include, but not be limited to, solid-state memories, optical media, magnetic media, any medium that is capable of storing a set of instructions for execution by the machine and that causes the machine to perform any one or more of the methodologies of the present embodiments.

[0148] The algorithms and displays presented herein are not inherently related to any particular computer or other apparatus. Various general-purpose systems may be used with programs in accordance with the teachings herein, or it may prove convenient to construct a more specialized apparatus to perform the required method steps. The required structure for a variety of these systems will appear from the description below. In addition, the present embodiments are not described with reference to any particular programming language. It will be appreciated that a variety of programming languages may be used to implement the teachings of the embodiments as described herein.

[0149] The above description sets forth numerous specific details such as examples of specific systems, components, methods, and so forth, in order to provide a good understanding of several embodiments of the present disclosure. It will be apparent to one skilled in the art, however, that at least some embodiments of the present disclosure may be practiced without these specific details. In other instances, well-known components or methods are not described in detail or are presented in simple block diagram format in order to avoid unnecessarily obscuring the present embodiments. Thus, the specific details set forth above are merely exemplary. Particular implementations may vary from these exemplary details and still be contemplated to be within the scope of the present embodiments.

[0150] It is to be understood that the above description is intended to be illustrative and not restrictive. Many other embodiments will be apparent to those of skill in the art upon reading and understanding the above description. The scope of the embodiments should, therefore, be determined with reference to the appended claims, along with the full scope of equivalents to which such claims are entitled.

Claims

1. A method comprising: receiving a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network; determining a plurality of channel transfer functions (CTF) s based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals; correcting each of the plurality of CTFs to generate a plurality of corrected CTFs; merging the plurality of corrected CTFs to produce a

merged CTF; and sensing one or more objects within the wireless network based on the merged CTF.

2. The method of claim 1, wherein the correcting each of the plurality of CTFs comprises: determining a peak of a frequency spectrum associated with each of the plurality of CTFs, wherein the peak of the frequency spectrum corresponds to a delay distance; determining, based on the peak of the frequency spectrum, a delay; and subtracting the delay from a phase of a subcarrier of each of the plurality of CTFs so that the peak of a frequency spectrum corresponds to a zero distance.

3. The method of claim 1, wherein the reference signal determines a transmission time and a shape of a transmitted signal associated with the plurality of sensing signals.

4. The method claim 1, wherein the plurality of sensing signals comprise a parasitic signal caused by an internal coupling within a transceiver and an antenna coupling between a plurality of transceivers.

5. The method of claim 4, wherein an amplitude value of the parasitic signal is smaller than an amplitude value of the reference signal, a first peak of each of the plurality of CTFs corresponds to the parasitic signal.

6. The method of claim 1, further comprising: averaging the plurality of corrected CTFs to generate an averaged corrected CTFs.

7. The method of claim 1, wherein the plurality of non-overlapping wireless channels include a first non-overlapping wireless channel, the corrected CTF associated with the first non-overlapping wireless channel being generated based on a first measurement at a first time period, and the corrected CTF associated with the first non-overlapping wireless channel being used to determine a new corrected CTF associated with a second measurement at a second time period.

8. The method of claim 7, wherein the corrected CTF associated with the first non-overlapping wireless channel is compared from the new corrected CTF associated with the second measurement at the second time period to determine a change in an environment between the first time period and the second time period.

9. The method of claim 1, wherein the wireless network is a wireless local area network (WLAN).

10. An apparatus comprising: a device configured to receive a reference signal and a sensing signal; a processing device operatively coupled to the device, the processing device configured to: receive a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network; determine a plurality of channel transfer functions (CTF) s based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals; correct each of the plurality of CTFs to generate a plurality of corrected CTFs; merge the plurality of corrected CTFs to produce a merged CTF; and sense one or more objects within the wireless network based on the merged CTF.

11. The apparatus of claim 10, wherein to correct each of the plurality of CTFs, the processing device is configured to: determine a peak of a frequency spectrum associated with each of the plurality of CTFs, wherein the peak of the frequency spectrum corresponds to a delay distance; determine, based on the peak of the frequency spectrum, a delay; and subtract the delay from a phase of a subcarrier of each of the plurality of CTFs so that the peak of a frequency spectrum corresponds to a zero distance.

12. The apparatus of claim 10, wherein the reference signal determines a transmission time and a shape of a transmitted signal associated with the plurality of sensing signals.

13. The apparatus of claim 12, wherein the plurality of sensing signals comprise a parasitic signal caused by an internal coupling within a transceiver and an antenna coupling between a plurality of transceivers.

14. The apparatus of claim 13, wherein an amplitude value of the parasitic signal is smaller than an amplitude value of the reference signal, a first peak of each of the plurality of CTFs corresponds to the parasitic signal.

15. The apparatus of claim 10, the processing device is further configured to: averaging the

plurality of corrected CTFs to generate an averaged corrected CTFs.

16. The apparatus of claim 10, wherein the plurality of non-overlapping wireless channels include a first non-overlapping wireless channel, the corrected CTF associated with the first non-overlapping wireless channel being generated based on a first measurement at a first time period, and the corrected CTF associated with the first non-overlapping wireless channel being used to determine a new corrected CTF associated with a second measurement at a second time period.

17. The apparatus of claim 16, wherein the corrected CTF associated with the first non-overlapping wireless channel is subtracted from the new corrected CTF associated to determine a change in an environment between the first time period and the second time period.

18. The apparatus of claim 10, wherein the wireless network is a wireless area local network (WLAN).

19. A non-transitory computer-readable medium storing instructions that, when executed by one or more processors of a wireless communications device in a wireless network, cause the wireless communications device to: receive a plurality of reference signals and a plurality of sensing signals on a plurality of non-overlapping wireless channels of a wireless network; determine a plurality of channel transfer functions (CTF) s based on one of the plurality of reference signals and a corresponding one of the plurality of sensing signals; correct each of the plurality of CTFs to generate a plurality of corrected CTFs; merge the plurality of corrected CTFs to produce a merged CTF; and sense one or more objects based on the merged CTF.

20. The non-transitory computer-readable medium of claim 19, wherein to correct each of the plurality of CTFs, wherein execution of the instructions further causes the wireless communications device to: determine a peak of a frequency spectrum associated with each of the plurality of CTFs, wherein the peak of the frequency spectrum corresponds to a delay distance; determine, based on the peak of the frequency spectrum, a delay; and subtract the delay from a phase of a subcarrier of each of the plurality of CTFs so that the peak of a frequency spectrum corresponds to a zero distance.
