

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407166
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Inoue; Sadayuki et al.

Distributed power supply management device

Abstract

An operation plan creation circuit creates a power target value of each of a plurality of distributed power supplies on the basis of information received by a communication circuit and capacities of the plurality of distributed power supplies a control parameter generation circuit generates a control parameter of the virtual synchronous generator control implemented in a static inverter of each of the distributed power supplies or information necessary for generating the control parameter. The communication circuit receives measurement information of each of the distributed power supplies, and transmits a control command to each of the distributed power supplies. The control parameter generation circuit generates the control parameter or the information necessary for generating the control parameter on the basis of the information received by the communication circuit, the capacities of the plurality of distributed power supplies, and the power target value of each of the distributed power supplies.

Inventors:	Inoue; Sadayuki (Tokyo, JP), Matsumoto; Koki (Tokyo, JP)
Applicant:	Mitsubishi Electric Corporation (Tokyo, JP)
Family ID:	80117776
Assignee:	MITSUBISHI ELECTRIC CORPORATION (Tokyo, JP)
Appl. No.:	18/014747
Filed (or PCT Filed):	August 05, 2020
PCT No.:	PCT/JP2020/029998
PCT Pub. No.:	WO2022/029924
PCT Pub. Date:	February 10, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230283076 A1	Sep. 07, 2023

Publication Classification

Int. Cl.: H02J3/24 (20060101); G05B19/042 (20060101); H02J3/38 (20060101)

U.S. Cl.:

CPC H02J3/24 (20130101); G05B19/042 (20130101); H02J3/381 (20130101); G05B2219/2639 (20130101)

Field of Classification Search

CPC: H02J (3/24); H02J (3/381); H02J (3/06); H02J (3/46); H02J (3/38); H02J (3/466); H02J (3/48); G05B (19/042)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10389119	12/2018	Nishita	N/A	H02J 3/38
10727784	12/2019	Kobayashi	N/A	H02J 13/00001
2014/0371942	12/2013	Matsuyama	700/297	G05F 1/66
2017/0017251	12/2016	Forbes, Jr.	N/A	H02J 3/00
2018/0275708	12/2017	Forbes, Jr.	N/A	H02J 3/00
2018/0358812	12/2017	Anderson	N/A	H02J 3/381
2020/0212823	12/2019	Gong	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
107910958	12/2017	CN	N/A
108199413	12/2017	CN	N/A
108879766	12/2017	CN	N/A
3780310	12/2020	EP	N/A
2016220396	12/2015	JP	N/A
6070076	12/2016	JP	N/A
2019080476	12/2018	JP	G03C 5/268
2019-176584	12/2018	JP	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion mailed on Oct. 13, 2020, received for PCT Application PCT/JP2020/029998, filed on Aug. 5, 2020, 8 pages including English Translation. cited by applicant

Office Action mailed on Jan. 4, 2022, received for Taiwan Application 110126917, 8 pages including English Translation. cited by applicant

The First Office Action mailed May 19, 2025, in Chinese Application No. 202080104426.5, 16 pages including English translation. cited by applicant

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

(1) The present application is based on PCT filing PCT/JP2020/029998, filed Aug. 5, 2020, the entire contents of which are incorporated herein by reference.

TECHNICAL FIELD

(2) The present disclosure relates to a distributed power supply management device.

BACKGROUND ART

(3) In recent years, the introduction of an energy creation apparatus (hereinafter, also referred to as “energy creation equipment”) using renewable energy such as solar cells has been accelerated in order to reduce a load on the environment. Further, in order to cope with power shortage after the Great East Japan Earthquake, commercialization of a system including an energy storage apparatus (hereinafter, also referred to as “energy storage equipment”) such as a storage battery, a system including a combination of energy creation equipment and energy storage equipment, or the like is in progress. In such systems, a static inverter is used to connect the energy creation equipment and the energy storage equipment to an AC system.

(4) On the other hand, for a power system, it is predicted that thermal power plants serving as a power generation output buffer against fluctuations in demand will be closed in the future from the viewpoint of reducing a power generation cost including a management cost as the amount of power generated by the renewable energy increases. A synchronous generator in such a thermal power plant, however, potentially has an effect (inertial force, synchronizing force, and the like) of suppressing fluctuations when a system frequency fluctuates. For this reason, when thermal power plants are further closed, the number of synchronous generators is reduced, which may make it difficult to keep the power system stable.

(5) In order to solve the above-described problems, development of a control technology for a virtual synchronous generator corresponding to a static inverter having a function of a synchronous generator is in progress. For example, Japanese Patent Laying-Open No. 2019-176584 (PTL 1) discloses a method for setting a control parameter of a distributed power supply (static inverter) having virtual synchronous generator control implemented. Specifically, PTL 1 discloses a method for generating a control parameter for setting virtual inertia for a distributed power supply on the basis of any one of a required inertia value required from a system operator or a virtual inertia value calculated on the basis of a specification and an operation state of the distributed power supply.

CITATION LIST

Patent Literature

(6) PTL 1: Japanese Patent Laying-Open No. 2019-176584

SUMMARY OF INVENTION

Technical Problem

(7) Under the method for generating a control parameter disclosed in PTL 1, the inertial force of the system intended by a system administrator is secured, but it is not possible to secure proportion division of power shared by each distributed power supply due to fluctuations in load or changes in the amount of power generated by the energy creation equipment.

(8) For example, considering a case where two storage batteries each having virtual synchronous generator control implemented as distributed power supplies are connected to a system. It is

assumed that the storage batteries and the static inverter are identical in capacity to each other, and a ratio of state of charge (SOC) at this time is 2:1. In this case, in an operation plan (charge and discharge plan) of the storage batteries, a ratio of a discharge power target value of each storage battery is assumed to be 2:1, which is the same as the ratio of the SOC.

(9) Here, when the load on the entire system increases, the virtual synchronous generator control is performed on each storage battery, and the two storage batteries proportionally output the increased power. At this time, when the control parameters of the virtual synchronous generator control of the two storage batteries are the same, each storage battery additionally outputs the same amount of power.

(10) In the operation plan of the storage batteries described above, however, the two storage batteries output power in accordance with their respective ratios of SOC, and it is desirable that the increased power be also proportionally divided at the ratio of this operation plan.

(11) In PTL 1 described above, since the control parameter is determined only on the basis of the inertial force of the system requested by the system operator, in a case where excess and deficient power when a load fluctuates or power generated by the energy creation equipment fluctuates is proportionally divided among a plurality of distributed power supplies, the excess and deficient power is proportionally divided on the basis of virtual inertia of each distributed power supply. Therefore, there is a problem that excess and deficient power is proportionally divided at a ratio different from the proportional division ratio intended in the original operation plan.

(12) In general, the power target value (operation plan) to be allocated to the plurality of distributed power supplies (for the sake of simplicity of the description, it is assumed that the virtual synchronous generator control is implemented in the static inverter of the system storage battery system) is proportionally divided on the basis of the capacity and SOC of each storage battery, the capacity of the static inverter, and the like. Specifically, in a case of discharging, when the storage battery capacity and the static inverter capacity are the same among the plurality of storage batteries, a large amount of power is allocated to a storage battery having higher SOC. This is because, for example, when the charge power of one of the two storage batteries becomes zero ($SOC=0$), the inertial force of the system is maintained by the remaining one storage battery, so that pseudo inertial force by the static inverter is substantially halved. Therefore, in a case of determining the power proportion division of the plurality of storage batteries, it is necessary to proportionally divide the power so as to make the SOC of each storage battery become zero (fully charged in a case of charging) at almost the same time.

(13) In particular, in a case where a microgrid or the like is constructed using a plurality of distributed power supplies such as a storage battery having virtual synchronous generator control implemented, there is a problem that when power supplied to a system suddenly changes due to a sudden change in load or a sudden change in solar radiation amount, it is difficult to make proportional division of power among distributed power supplies as planned.

(14) The present disclosure has been made to solve the above-described problems, and it is therefore an object of the present disclosure to generate, in a power system in which a plurality of distributed power supplies are connected, each distributed power supply including a static inverter having virtual synchronous generator control implemented, a control parameter of the virtual synchronous generator control that allows excess and deficient power to be proportionally divided so as to make each distributed power supply equal to a ratio of a power target value even when power consumed by a load or power generated by energy creation equipment fluctuates.

Solution to Problem

(15) According to one aspect of the present disclosure, a distributed power supply device manages a plurality of distributed power supplies connected to a distribution system. Each of the plurality of distributed power supplies includes a static inverter having virtual synchronous generator control implemented. The distributed power supply management device includes a communication circuit that communicates with a system management device that manages the distribution system and a

plurality of distributed power supplies, an operation plan creation circuit that creates a power target value of each of the plurality of distributed power supplies on the basis of information received by the communication circuit and capacities of the plurality of distributed power supplies, and a control parameter generation circuit that generates a control parameter of the virtual synchronous generator control in each of the distributed power supplies or information necessary for generating the control parameter. The communication circuit is configured to receive at least one of measurement information of each of the distributed power supplies or a command value from the system management device, and to transmit a control command to each of the distributed power supplies. The control parameter generation circuit generates the control parameter or the information necessary for generating the control parameter on the basis of the information received by the communication circuit, the capacities of the plurality of distributed power supplies, and the power target value of each of the distributed power supplies, and outputs the control parameter generated or the information necessary for generating the control parameter to each of the distributed power supplies via the communication circuit.

Advantageous Effects of Invention

(16) According to the present disclosure, even when power consumed by a load or power generated by energy creation equipment fluctuates, it is possible to make proportional division of power among the plurality of distributed power supplies as planned. Specifically, excess and deficient power can be proportionally divided at a ratio equivalent to the ratio of the power target value at the time of creating the operation plan of the distributed power supplies.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a block diagram illustrating a configuration of a distribution system according to a first embodiment.
- (2) FIG. 2 is a block diagram for further describing a configuration of some devices including a storage battery connected to the distribution system and the distribution system according to the first embodiment.
- (3) FIG. 3 is a block diagram of a CEMS according to the first embodiment.
- (4) FIG. 4 is a block diagram of an operation plan creation circuit in the CEMS according to the first embodiment.
- (5) FIG. 5 is a block diagram of a control parameter generation circuit in the CEMS according to the first embodiment.
- (6) FIG. 6 is a block configuration diagram of a mega solar power conversion device illustrated in FIG. 1.
- (7) FIG. 7 is a block configuration diagram of a system storage battery power conversion device illustrated in FIG. 1.
- (8) FIG. 8 is a block diagram for describing a configuration of a first control circuit that controls a first DC/DC converter of the mega solar power conversion device.
- (9) FIG. 9 is a block diagram for describing a configuration of a second control circuit that controls a first DC/AC converter of the mega solar power conversion device.
- (10) FIG. 10 is a block diagram for describing a configuration of a third control circuit that controls a second DC/DC converter of the storage battery power conversion device.
- (11) FIG. 11 is a block diagram for describing a configuration of a fourth control circuit that controls a second DC/AC converter of the storage battery power conversion device.
- (12) FIG. 12 is a block diagram for describing a configuration of an AC frequency detection circuit illustrated in FIG. 11.
- (13) FIG. 13 is a block diagram for describing a configuration of an inverter voltage control circuit

illustrated in FIG. 11.

(14) FIG. 14 is a block diagram for describing a configuration example of a virtual synchronous generator control circuit illustrated in FIG. 11.

(15) FIG. 15 is a block diagram for describing a configuration of a governor control circuit illustrated in FIG. 14.

(16) FIG. 16 is a block diagram for describing a configuration of a point mass system operation circuit illustrated in FIG. 14.

(17) FIG. 17 is a diagram for describing an area covered by virtual synchronous generator control implemented in the storage battery power conversion device according to the first embodiment.

(18) FIG. 18 is a diagram illustrating an example of a relationship between a speed adjustment rate and a system frequency when a load is suddenly changed under the virtual synchronous generator control implemented in the storage battery power conversion device according to the first embodiment.

(19) FIG. 19 is a diagram illustrating an example of a relationship between a damping factor and a system frequency when a load is suddenly changed under the virtual synchronous generator control implemented in the storage battery power conversion device according to the first embodiment.

(20) FIG. 20 is a diagram illustrating an example of a $\Delta P/\Delta F$ characteristic of the virtual synchronous generator control implemented in the storage battery power conversion device according to the first embodiment.

(21) FIG. 21 is a diagram illustrating a response waveform of a frequency of a system voltage output from a static inverter when a load is suddenly changed under the virtual synchronous generator control implemented in the storage battery power conversion device according to the first embodiment.

(22) FIG. 22 is a diagram illustrating a response waveform of an effective value of AC power output from each static inverter unit when a load is suddenly changed in a stand-alone system including two storage battery power conversion devices each having conventional virtual synchronous generator control implemented.

(23) FIG. 23 is a diagram illustrating a response waveform of a frequency of a system voltage output from each static inverter unit when a load is suddenly changed in a stand-alone system including two storage battery power conversion devices each having conventional virtual synchronous generator control implemented.

(24) FIG. 24 is a diagram illustrating an example of a $\Delta P/\Delta F$ characteristic of a first power conversion device having conventional virtual synchronous generator control implemented.

(25) FIG. 25 is a diagram illustrating an example of a $\Delta P/\Delta F$ characteristic of a second power conversion device having conventional virtual synchronous generator control implemented.

(26) FIG. 26 is a diagram illustrating an example of a $\Delta P/\Delta F$ characteristic of the second power conversion device having the virtual synchronous generator control according to the first embodiment implemented.

(27) FIG. 27 is a diagram illustrating an example of a reference $\Delta P/\Delta F$ characteristic of a power conversion device having the virtual synchronous generator control according to the first embodiment implemented.

(28) FIG. 28 is a diagram for describing an operation of creating a $\Delta P/\Delta F$ characteristic of a power conversion device in a case where the power target value is different using the reference $\Delta P/\Delta F$ characteristic of the power conversion device having the virtual synchronous generator control according to the first embodiment implemented.

(29) FIG. 29 is a diagram for describing an operation of creating a $\Delta P/\Delta F$ characteristic of a power conversion device in a case where the capacity of the static inverter is different using the reference $\Delta P/\Delta F$ characteristic of the power conversion device having the virtual synchronous generator control according to the first embodiment implemented.

(30) FIG. 30 is a diagram illustrating an example of $\Delta P/\Delta F$ characteristics of two power conversion

devices different in inverter capacity and power target value, the two power conversion devices having the virtual synchronous generator control according to the first embodiment implemented.

(31) FIG. 31 is a diagram illustrating response waveforms of effective values of AC power output from two power conversion devices having the $\Delta P/\Delta F$ characteristic illustrated in FIG. 30.

(32) FIG. 32 is a sequence diagram of a normal operation of a distributed power supply management device, focusing on the CEMS illustrated in FIG. 1.

(33) FIG. 33 is a flowchart for describing control processing of the CEMS illustrated in FIG. 1.

(34) FIG. 34 is a flowchart for describing details of operation plan creation processing (S05 of FIG. 33).

(35) FIG. 35 is a flowchart for describing details of control parameter generation processing (S056 of FIG. 34) of a virtual synchronous generator.

(36) FIG. 36 is a flowchart for describing details of reference $\Delta P/\Delta F$ characteristic generation processing (S0562 of FIG. 35).

(37) FIG. 37 is a flowchart for describing details of $\Delta P/\Delta F$ characteristic generation processing (S0563 of FIG. 35).

(38) FIG. 38 is a flowchart for describing details of control parameter generation processing (S0564 of FIG. 35).

(39) FIG. 39 is a flowchart for describing details of operation plan correction processing (S09 of FIG. 33).

(40) FIG. 40 is a flowchart for describing how the storage battery power conversion device operates.

(41) FIG. 41 is a flowchart for describing details of control processing (S204 of FIG. 40) of the second DC/AC converter.

(42) FIG. 42 is a block diagram of a control parameter generation circuit in a CEMS according to a second embodiment.

(43) FIG. 43 is a flowchart for describing details of virtual synchronous generator control parameter generation processing (S056 of FIG. 34) according to the second embodiment.

(44) FIG. 44 is a flowchart for describing how a storage battery power conversion device according to the second embodiment operates.

(45) FIG. 45 is a diagram for describing a concept of a virtual synchronous generator control technology.

DESCRIPTION OF EMBODIMENTS

(46) Hereinafter, embodiments of the present disclosure will be described in detail with reference to the drawings. Note that, in the following description, the same or corresponding parts in the drawings are denoted by the same reference numerals, and no redundant description will be given of such parts in principle.

First Embodiment

(47) (Configuration Example of Distribution System)

(48) First, a configuration example of a distribution system to which a distributed power supply management device according to a first embodiment is applied will be described. Note that a three-phase system will be given as an example in the first embodiment, but the distribution system may be a single-phase system.

(49) FIG. 1 is a block diagram illustrating a configuration example of a distribution system 24 according to the first embodiment. As illustrated in FIG. 1, distribution system 24 receives power from a substation 20. Distribution system 24 is provided with a plurality of step voltage regulators (SVR) 23a to 23c. The plurality of SVRs 23a to 23c are connected in series along a flow of power. To the plurality of SVRs 23a to 23c, a building 112, a condominium 113, a town A 100a to a town D 100d, a factory 110, a mega solar power conversion device 27, system storage battery power conversion devices 41a to 41c, and synchronous generators 30a, 30b are connected. In the following description, SVRs 23a to 23c are also collectively referred to as “SVR 23”. Further,

power conversion devices **41a** to **41c** are also collectively referred to as “power conversion device **41**”.

(50) In distribution system **24**, a plurality of voltmeters **22a**, **22e**, **22f**, **22i**, **22j**, **22x** are installed. Hereinafter, voltmeters **22a**, **22e**, **22f**, **22i**, **22j**, **22x** are also collectively referred to as “voltage meter **22**”. A measurement value of each voltage meter **22** is transmitted to a distribution automation system **21** (hereinafter, also referred to as “DSO **21**”) at predetermined intervals. DSO **21** corresponds to an example of a “system management device” that manages distribution system **24**.

(51) Information on a tap position of the SVR **23**, information on a primary-side voltage and secondary-side voltage are transmitted to DSO **21**. In the first embodiment, SVR **23** provides, at predetermined intervals, notification of the information on the tap position, and the information on the primary-side voltage and the secondary-side voltage, and provides, at irregular intervals, notification of the information on the tap position, and the information on the primary-side voltage and the secondary-side voltage when a tap is changed.

(52) A community energy management system (CEMS) **31** collects information such as various measurement values from each consumer (towns **100a** to **100d**, factory **110**, building **112**, and condominium **113**), power conversion device **27**, synchronous generators **30a**, **30b**, and power conversion devices **41a** to **41c** at predetermined intervals. CEMS **31** notifies DSO **21** of the collected data in response to a request from DSO **21**. Note that power consumed by each consumer in towns **100a** to **100d** and power generated by energy creation equipment are measured by a smart meter (not illustrated) installed for each consumer. CEMS **31** collects the measurement values of the smart meter at predetermined intervals (for example, at intervals of 30 minutes). CEMS **31** corresponds to an example of the “distributed power supply management device”.

(53) A mega solar **26** is connected to power conversion device **27**. System storage batteries **40a** to **40c** are connected to power conversion devices **41a** to **41c**, respectively. Storage batteries **40a** to **40c** are large-capacity storage batteries that are connectable to distribution system **24**. In the following description, storage batteries **40a** to **40c** are also collectively referred to as “storage battery **40**”.

(54) FIG. **2** is a block diagram for further describing the configuration of distribution system **24** illustrated in FIG. **1**.

(55) As illustrated in FIG. **2**, a load **600**, power conversion device **41**, and storage battery **40** are connected to distribution system **24**. Note that, for the sake of simplicity of the description, an impedance **29** of distribution system **24** is represented by a centralized system in FIG. **2**.

Impedance **29** of distribution system **24** includes a reactor component and a resistance component.

(56) (1) CEMS **31**

(57) FIG. **3** is a block diagram illustrating a configuration of CEMS **31** illustrated in FIG. **1**.

(58) As illustrated in FIG. **3**, CEMS **31** includes a communication circuit **11**, a storage circuit **12**, a control parameter generation circuit **13**, an operation plan creation circuit **14**, a transmission data generation circuit **15**, and a control circuit **16**.

(59) Communication circuit **11** communicates with DSO **21**, each consumer (towns **100a** to **100d**, factory **110**, building **112**, and condominium **113**), power conversion device **27**, synchronous generators **30a**, **30b**, and power conversion devices **41a** to **41c** over a communication line **25**.

(60) Storage circuit **12** stores various types of information acquired over communication circuit **11**. The various types of information include a measurement result, status information of each distributed power supply, and the like.

(61) Control parameter generation circuit **13** generates a control parameter of virtual synchronous generator control implemented in each of power conversion devices **41a** to **41c**.

(62) Operation plan creation circuit **14** creates an operation plan of power conversion devices **41a** to **41c** on the basis of a control command from DSO **21**. The operation plan of power conversion devices **41a** to **41c** includes a charge and discharge plan (power target value) of a corresponding one of storage batteries **40a** to **40c**. In the first embodiment, operation plan creation circuit **14**

creates a 24-hour operation plan at intervals of 30 minutes.

(63) Furthermore, operation plan creation circuit **14** determines whether or not it is necessary to correct the operation plan on the basis of the measurement results of power conversion devices **41a** to **41c** collected at intervals of 5 minutes, SOC information of storage batteries **40a** to **40c**, and the like. When it is determined that the operation plan needs to be corrected, operation plan creation circuit **14** corrects the operation plan for a period until the next control command is received from DSO **21**.

(64) Transmission data generation circuit **15** stores the control parameter of the virtual synchronous generator control generated by control parameter generation circuit **13** and the operation plan output from operation plan creation circuit **14**. In response to a transmission command from control circuit **16**, transmission data generation circuit outputs the stored data to communication circuit **11**. Communication circuit **11** transmits the data output from transmission data generation circuit **15** to communication line **25** in accordance with a control signal output from control circuit **16**.

(65) Control circuit **16** is a control circuit for managing a distributed power supply connected to distribution system **24**. Control circuit **16** manages how communication circuit **11**, storage circuit **12**, control parameter generation circuit **13**, operation plan creation circuit **14**, and transmission data generation circuit **15** operate.

(66) (1-1) Operation Plan Creation Circuit **14**

(67) FIG. **4** is a block diagram illustrating a configuration of operation plan creation circuit **14** illustrated in FIG. **3**.

(68) As illustrated in FIG. **4**, operation plan creation circuit **14** includes a storage battery operation plan creation circuit **141**, a power generation prediction circuit **142**, a power consumption prediction circuit **143**, a storage battery operation plan correction circuit **144**, a management circuit **145**, and a management circuit **146**.

(69) Storage battery operation plan creation circuit **141** creates the operation plan (power target value) of power conversion devices **41a**, **41b**, **41c** on the basis of information on the control command notified from DSO **21**, a prediction result of predicting, by power generation prediction circuit **142**, the amount of power to be generated by mega solar **26**, and a prediction result of predicting, by power consumption prediction circuit **143**, the amount of power to be consumed by each consumer. Note that the control command notified from DSO **21** to storage battery operation plan creation circuit **141** includes a planned value of power to be consumed on the downstream side of substation **20** (power to be supplied to distribution system **24**). The planned value of power to be supplied includes a planned value for 24 hours determined at intervals of 30 minutes.

(70) Power generation prediction circuit **142** acquires 24-hour weather forecast information from a weather forecast server (not illustrated) via communication circuit **11**. Power generation prediction circuit **142** predicts the power to be generated by mega solar **26** on the basis of the acquired weather forecast information and information stored in a database (not illustrated) prepared for predicting the power generation.

(71) Power consumption prediction circuit **143** predicts the sum of power to be consumed by each consumer on the basis of clock information (date, day of the week, time) in CEMS **31** and information stored in a database (not illustrated) prepared for predicting the power consumption.

(72) Storage battery operation plan correction circuit **144** determines whether or not it is necessary to correct the operation plan on the basis of the amount of charge and discharge power of power conversion devices **41a** to **41c** and power target value information over communication circuit **11**. When it is determined that correction is necessary, storage battery operation plan correction circuit **144** generates a correction value of the operation plan.

(73) Management circuit **145** manages how the operation plan of the distributed power supply connected to the distribution system **24** is created. Management circuit **145** stores the power target value (charge power target value and discharge power target value) of each of storage batteries **40** generated by storage battery operation plan creation circuit **141** and storage battery operation plan

correction circuit **144**. Management circuit **145** outputs the power target value to control parameter generation circuit **13** and transmission data generation circuit **15** on the basis of a control signal output from management circuit **146**.

(74) Management circuit **146** manages how storage battery operation plan creation circuit **141**, power generation prediction circuit **142**, power consumption prediction circuit **143**, storage battery operation plan correction circuit **144**, and management circuit **145** operate.

(75) (1-2) Control Parameter Generation Circuit **13**

(76) FIG. 5 is a block diagram illustrating a configuration of control parameter generation circuit **13** illustrated in FIG. 3.

(77) As illustrated in FIG. 5, control parameter generation circuit **13** includes a reference $\Delta P/\Delta F$ characteristic calculation circuit **131**, a $\Delta P/\Delta F$ characteristic calculation circuit **132**, a control parameter generation circuit **133**, a virtual synchronous generator model **134**, a management circuit **135**, and a control circuit **136**.

(78) Reference $\Delta P/\Delta F$ characteristic calculation circuit **131** calculates a reference $\Delta P/\Delta F$ characteristic on the basis of information on capacities of static inverters (second DC/AC converters **408**) of power conversion devices **41a** to **41c**.

(79) $\Delta P/\Delta F$ characteristic calculation circuit **132** calculates a $\Delta P/\Delta F$ characteristic on the basis of the reference $\Delta P/\Delta F$ characteristic and the power target value information created by operation plan creation circuit **14** (FIG. 4).

(80) Control parameter generation circuit **133** generates the control parameter of virtual synchronous generator control using virtual synchronous generator model **134** on the basis of the $\Delta P/\Delta F$ characteristic, the information on distribution system **24** (system frequency (reference frequency F_{ref}), ΔF_{max} , and the like) notified from DSO **21**, and the capacity of the static inverter (second DC/AC converter **408**).

(81) Virtual synchronous generator model **134** calculates a speed adjustment rate K_{gd} and a damping factor D_g using the information input from control parameter generation circuit **133**. Control parameter generation circuit **133** calculates an inertia constant M using damping factor D_g .

(82) Management circuit **135** manages the control parameter of the virtual synchronous generator control. Management circuit **135** stores, in a memory (not illustrated), and manages information such as the control parameter output from control parameter generation circuit **133**, the $\Delta P/\Delta F$ characteristic calculated by $\Delta P/\Delta F$ characteristic calculation circuit **132**, and the power target value P_{ref} .

(83) Control circuit **136** manages how reference $\Delta P/\Delta F$ characteristic calculation circuit **131**, $\Delta P/\Delta F$ characteristic calculation circuit **132**, control parameter generation circuit **133**, virtual synchronous generator model **134**, and management circuit **135** operate.

(84) (2) Power Conversion Device **27**

(85) FIG. 6 is a block diagram illustrating a configuration of power conversion device **27** illustrated in FIG. 1.

(86) As illustrated in FIG. 6, power conversion device **27** includes voltmeters **201**, **206**, **210**, ammeters **202**, **207**, **211**, a first DC/DC converter **203**, a first control circuit **204**, a DC bus **205**, a first DC/AC converter **208**, a second control circuit **209**, and a communication interface (I/F) **212**.

(87) Voltmeter **201** measures a DC voltage output from mega solar **26**. Ammeter **202** measures a direct current output from mega solar **26**.

(88) First DC/DC converter **203** converts a first DC voltage output from mega solar **26** into a second DC voltage. First control circuit **204** controls first DC/DC converter **203**.

(89) DC bus **205** transfers the second DC voltage output from first DC/DC converter **203** to first DC/AC converter **208**. Voltmeter **206** measures a voltage of DC bus **205**. Ammeter **207** measures a direct current output from first DC/DC converter **203**.

(90) First DC/AC converter **208** converts DC power output from first DC/DC converter **203** into AC power. Second control circuit **209** controls first DC/AC converter **208**.

(91) Voltmeter **210** measures an AC voltage output from first DC/AC converter **208**. Ammeter **211** measures an alternating current output from first DC/AC converter **208**. Communication I/F **212** communicates with power conversion device **27** and CEMS **31**.

(92) (3) Power Conversion Device **41**

(93) FIG. **7** is a block diagram illustrating a configuration of power conversion device **41** illustrated in FIG. **1**.

(94) As illustrated in FIG. **7**, power conversion device **41** includes voltmeters **401**, **406**, **410**, ammeters **402**, **407**, **411**, a second DC/DC converter **403**, a third control circuit **404**, a DC bus **405**, second DC/AC converter **408**, a fourth control circuit **409**, and a communication I/F **412**.

(95) Voltmeter **401** measures a DC voltage output from storage battery **40**. Ammeter **402** measures a direct current output from storage battery **40**.

(96) Second DC/DC converter **403** converts a third DC voltage output from storage battery **40** into a fourth DC voltage. Third control circuit **404** controls second DC/DC converter **403**.

(97) DC bus **405** transfers the DC voltage output from second DC/DC converter **403** to second DC/AC converter **408**. Voltmeter **406** measures a voltage of DC bus **405**. Ammeter **407** measures a direct current output from second DC/DC converter **403**.

(98) Second DC/AC converter **408** converts DC power output from second DC/DC converter **403** into AC power. Fourth control circuit **409** controls second DC/AC converter **408**.

(99) Voltmeter **410** measures an AC voltage output from second DC/AC converter **408**. Ammeter **411** measures an alternating current output from second DC/AC converter **408**. Communication I/F **412** communicates with power conversion device **41** and CEMS **31**.

(100) Note that a known DC/DC converter can be used as first DC/DC converter **203** (FIG. **6**) and second DC/DC converter **403** (FIG. **7**) as needed. A known inverter can be used as first DC/AC converter **208** (FIG. **6**) and second DC/AC converter **408** (FIG. **7**). First DC/AC converter **208** and second DC/AC converter **408** each correspond to an example of a “static inverter”. Second control circuit **209** and fourth control circuit **409** each correspond to an example of a “static inverter controller”.

(101) (2-1) First Control Circuit **204**

(102) FIG. **8** is a block diagram illustrating a configuration of first control circuit **204** illustrated in FIG. **6**.

(103) As illustrated in FIG. **8**, first control circuit **204** includes a maximum power point tracking (MPPT) control circuit **51**, a voltage control circuit **52**, a first switching circuit **53**, and a fifth control circuit **54**.

(104) MPPT control circuit **51** performs so-called maximum power point tracking (MPPT) control on the basis of the measurement values of voltmeter **201** and ammeter **202**. MPPT control circuit **51** searches for a maximum power point of mega solar **26** to maximize the power generated by mega solar **26**. Specifically, MPPT control circuit **51** generates a control command value of first DC/DC converter **203** so as to make the DC voltage measured by voltmeter **201** equal to a voltage corresponding to the maximum power point.

(105) Voltage control circuit **52** generates, on the basis of the measurement value of voltmeter **206**, a control command value of first DC/DC converter **203** for maintaining the DC voltage (second DC voltage) of DC bus **205** at a predetermined target voltage.

(106) Fifth control circuit **54** outputs control parameters, control target values, and the like of MPPT control circuit **51** and voltage control circuit **52**, and manages a power generation state and the like of mega solar **26**. Fifth control circuit **54** further outputs a control signal of first switching circuit **53**.

(107) First switching circuit **53** selectively outputs either one of the output of MPPT control circuit **51** and the output of voltage control circuit **52** as the control command value of first DC/DC converter **203** in accordance with a control signal from fifth control circuit **54**.

(108) First DC/DC converter **203** is controlled in an MPPT mode or a voltage control mode. In the

MPPT mode, first switching circuit **53** outputs the control command value generated by MPPT control circuit **51**. In the voltage control mode, first switching circuit **53** outputs the control command value generated by voltage control circuit **52**.

(109) (2-2) Second Control Circuit **209**

(110) FIG. **9** is a block diagram illustrating a configuration of second control circuit **209** illustrated in FIG. **6**.

(111) As illustrated in FIG. **9**, second control circuit **209** includes a phase detection circuit **61**, a first sine wave generation circuit **62**, a current control circuit **60**, and a sixth control circuit **67**.

(112) Current control circuit **60** includes a subtractor **63**, a first PI control circuit **64**, a multiplier **65**, a subtractor **66**, a second PI control circuit **68**, and a first PWM converter **69**. Current control circuit **60** enables a control mode in which power is output in synchronization with a system voltage. This control mode is a control method applied to a general power converter for photovoltaic generation installed at a home.

(113) Phase detection circuit **61** detects a phase of the AC voltage from a waveform of the AC voltage measured by voltmeter **210** (FIG. **6**).

(114) First sine wave generation circuit **62** generates a sine wave synchronized with the waveform of the AC voltage on the basis of amplitude of the AC voltage measured by voltmeter **210** and information on the phase detected by phase detection circuit **61**. Note that, in the first embodiment, phase detection circuit **61** detects a zero-cross point of the waveform of the AC voltage, and detects a frequency of the AC voltage from the result of detecting the zero-cross point. Phase detection circuit **61** outputs the detected frequency of the AC voltage to first sine wave generation circuit **62** together with the zero-cross point information.

(115) Current control circuit **60** generates a control command value for controlling first DC/DC converter **208** on the basis of the DC voltage of DC bus **205** measured by voltmeter **206** (FIG. **6**). Subtractor **63** subtracts the DC voltage of DC bus **205** measured by voltmeter **206** from a target value of a DC bus voltage output from sixth control circuit **67**. A value obtained as a result of subtraction by subtractor **63** is input to first PI control circuit **64**.

(116) Multiplier **65** generates a current command value by multiplying a control command value output from first PI control circuit **64** by the sine wave output from first sine wave generation circuit **62**.

(117) Subtractor **66** calculates a deviation between the current command value output from multiplier **65** and the current value of the AC system measured by ammeter **211** (FIG. **6**), and outputs the calculated deviation to second PI control circuit **68**.

(118) Second PI control circuit **68** generates, on the basis of control parameters (proportional gain and integration time) provided from sixth control circuit **67**, a control command value so as to make the deviation output from the subtractor **66** become zero. Second PI control circuit **68** outputs the generated control command value to first PWM converter **69**.

(119) First PWM converter **69** performs PWM control on the control command value input from second PI control circuit **68** to generate a control command value, and outputs the generated control command value to first DC/AC converter **208**.

(120) Sixth control circuit **67** collects measurement results regarding DC bus **205** output from voltmeter **206** and ammeter **207**, measurement results regarding the AC system output from voltmeter **210** and ammeter **211**, status information of first DC/DC converter **203** output from first control circuit **204**, and the like, and notifies CEMS **31** and the like of the collected information via communication I/F **212**.

(121) Further, sixth control circuit **67** notifies first PI control circuit **64** and second PI control circuit **68** of the control parameter. Sixth control circuit **67** notifies CEMS **31** of information on active power and reactive power measured by an effective voltage measurement unit (not illustrated) of the AC system via communication I/F **212**. Sixth control circuit **67** notifies fifth control circuit **54** of measurement values such as an effective voltage and active power of the AC

system. For example, in a case where the effective value of the system voltage exceeds a predetermined value, fifth control circuit **54** switches the control of mega solar **26** from MPPT control to voltage control to suppress an increase in the system voltage.

(122) (3-1) Third Control Circuit **404**

(123) FIG. **10** is a block diagram illustrating a configuration of third control circuit **404** illustrated in FIG. **7**.

(124) As illustrated in FIG. **10**, third control circuit **404** includes a charge control circuit **71**, a discharge control circuit **72**, a second switching circuit **73**, and a seventh control circuit **74**.

(125) Charge control circuit **71** generates a control command value of second DC/DC converter **403** when performing charge control of storage battery **40**.

(126) Discharge control circuit **72** generates a control command value of second DC/DC converter **403** when performing discharge control of storage battery **40**.

(127) Seventh control circuit **74** outputs a control parameter, a control target value, and the like to charge control circuit **71** and discharge control circuit **72**. Seventh control circuit **74** manages a state of charge (SOC), charge power (charge current), discharge power (discharge current), and the like of storage battery **40**. Seventh control circuit **74** outputs a control signal of second switching circuit **73**.

(128) Second switching circuit **73** selectively outputs either one of the output of charge control circuit **71** and the output of discharge control circuit **72** as a control command value of second DC/DC converter **403** in accordance with the control signal from seventh control circuit **74**.

Specifically, second switching circuit **73** outputs, upon receipt of an instruction for charging storage battery **40**, the control command value generated by charge control circuit **71**. On the other hand, second switching circuit **73** outputs, upon receipt of an instruction for discharging storage battery **40**, the control command value generated by discharge control circuit **72**.

(129) (3-2) Fourth Control Circuit **409**

(130) FIG. **11** is a block diagram illustrating a configuration of fourth control circuit **409** illustrated in FIG. **7**.

(131) As illustrated in FIG. **11**, fourth control circuit **409** includes an AC frequency detection circuit **81**, an effective power calculation circuit **82**, a virtual synchronous generator control circuit **83**, an inverter current control circuit **84**, an inverter voltage control circuit **85**, a third switching circuit **86**, and an eighth control circuit **87**.

(132) AC frequency detection circuit **81** detects the phase of the AC voltage from the waveform of the AC voltage measured by voltmeter **410** (FIG. **7**). In the first embodiment, the zero-cross point is detected from the waveform of the AC voltage, and the frequency is detected from a time interval of the detected zero-cross point. Note that the method for detecting the frequency of the AC voltage is not limited to the method using the result of detecting the zero-cross point.

(133) Effective power calculation circuit **82** calculates the effective power using the information on the AC voltage and the alternating current measured by voltmeter **410** and ammeter **411** (FIG. **7**). In the first embodiment, the effective power is calculated by integrating power for one period of the AC voltage waveform on the basis of the zero-cross point detection information and the AC frequency information output from AC frequency detection circuit **81**. Note that the method for calculating the effective power is not limited to the above-described method, and, for example, in a case where the AC system is a three-phase AC, the effective power may be calculated using DQ transformation or the like.

(134) Virtual synchronous generator control circuit **83** imparts, on the basis of the AC voltage frequency information output from AC frequency detection circuit **81** and the AC effective power information output from effective power calculation circuit **82**, inertial force, synchronizing force, and damping force of a synchronous generator to second DC/AC converter **408** (static inverter).

(135) [Virtual Synchronous Generator Control Technology]

(136) Hereinafter, a virtual synchronous generator control technology will be briefly described.

(137) A synchronous generator typically used for thermal power generation has a function of regulating output power in accordance with a frequency (governor function), a function of maintaining an angular velocity (inertial force), a function of synchronizing with a system voltage (synchronizing force), a function of regulating a voltage of a trunk system (automatic voltage regulation function (AVR function)), a function of continuing operation even when an AC system voltage instantaneously drops in the event of a system fault, and the like.

(138) In the virtual synchronous generator control technology, a transient response of the static inverter is controlled to cause the static inverter to mimic the function of the synchronous generator. Specifically, three functions, the governor function, a function mimicking a point mass system model (dynamic characteristics of a rotary machine) based on a swing equation, and the AVR function, are mimicked.

(139) In the first embodiment, in particular, a case where the governor function and the function mimicking a point mass system model based on a swing equation are implemented in second DC/AC converter **408** will be described. FIG. **45** is a conceptual diagram for describing the virtual synchronous generator control technology. Note that the AVR function of the synchronous generator is a function controlled mainly on the basis of an output voltage command or a reactive power command value notified from a host system (CEMS **31** in the first embodiment), and is thus not implemented in the first embodiment. Hereinafter, the governor function and the function mimicking a point mass system model based on a swing equation will be described in detail.

(140) First, the governor function will be described.

(141) A governor in a power plant has a function of controlling output power of a generator by controlling output of a gas turbine or a steam turbine used for thermal power generation and nuclear power generation, guide vanes of a waterwheel used for hydraulic power generation, and the like. When demand power exceeds supply power in the AC power system, the frequency of the system voltage decreases. For a thermal power generator or a hydraulic power generator capable of performing output control, a droop characteristic is imparted to the governor, so that the generator is controlled to increase the power generation when the frequency of the system voltage decreases. On the other hand, when the frequency of the system voltage increases due to the supply power exceeding the demand power, the generator is controlled to reduce the power generation.

(142) FIG. **45** is a diagram schematically illustrating the governor function. As illustrated in FIG. **45**, when an angular velocity ω of the synchronous generator increases, a valve that regulates the inflow of energy moves to the right side, so as to reduce the energy supplied to the synchronous generator. On the other hand, when the angular velocity ω of the synchronous generator decreases, the valve moves to the left side, so as to increase the energy supplied to the synchronous generator. This allows the energy output from the synchronous generator to be controlled only by the frequency of the system voltage of its own terminal (that is, the angular velocity ω of the synchronous generator). Even when the synchronous generator separately perform the above-described operation, the operation is managed on the basis of the frequency of the system voltage, so that it is possible to share a load among a plurality of synchronous generators. For example, the Institute of Electrical Engineers of Japan provides a model constituted of a first-order lag system as a standard model.

(143) In the first embodiment, an operation in a case where a governor is approximated by a model constituted of the above-described first-order lag system as shown by the following expression (1) will be described.

$$-1/\{Kgd \times (1+s \times Tg)\} \quad (1)$$

(144) where, $-1/Kgd$ in the expression (1) represents a proportional gain (Kgd : speed adjustment rate) of the governor, and Tg represents a time constant of the first-order lag system (Tg : governor time constant).

(145) Next, the function mimicking a point mass system model based on a swing equation will be described.

(146) As illustrated in FIG. 45, the synchronous generator includes a rotor having a per unit inertia constant M . For example, when the power generated by mega solar 26 suddenly decreases due to a sudden change in solar radiation amount, the shortage of power cannot be instantaneously covered by the above-described governor control. The synchronous generator converts rotational energy accumulated in the rotor into power and outputs the power to the AC system. At this time, when the angular velocity (rotation speed) of the rotor decreases, the energy supplied under the governor control increases, so as to balance the demand power and the supply power. The following expression (2) shows a swing equation mimicking a point mass system model (generator rotor). The swing equation is obtained by dividing energy P by the angular velocity ω to convert energy P into torque T .

$$T_{in} - T_{out} = M \times d\omega/dt + Dg \times \omega \quad (2)$$

(147) where Dg represents a damping factor and M represents an inertia constant.

(148) In the first embodiment, a case where inertial force, synchronizing force, and damping force of the synchronous generator are mimicked with the expressions (1) and (2) incorporated into the control of the static inverter (second DC/AC converter 408) will be described.

(149) Referring back to FIG. 11, inverter current control circuit 84 generates a control command value for controlling the current of second DC/AC converter 408. Note that inverter current control circuit 84 is different from current control circuit 60 illustrated in FIG. 9 only in control parameter, but has the same circuit configuration and operation, and thus no detailed description will be given below of inverter current control circuit 84.

(150) Inverter voltage control circuit 85 generates a control command value for controlling the voltage of second DC/AC converter 408.

(151) Third switching circuit 86 switches between the control command value from inverter current control circuit 84 and the control command value from inverter voltage control circuit 85 on the basis of the output of eighth control circuit 87.

(152) Eighth control circuit 87 collects the measurement results regarding DC bus 405 from voltmeter 406 and ammeter 407, the status information of second DC/DC converter 403 output from third control circuit 404, and the like, and notifies CEMS 31 and the like of the collected information via communication I/F 412.

(153) Further, eighth control circuit 87 notifies virtual synchronous generator control circuit 83, inverter current control circuit 84, and inverter voltage control circuit 85 of their respective control parameters.

(154) Further, eighth control circuit 87 notifies CEMS 31 of information on the effective voltage of the AC system measured by the effective voltage measurement unit of the AC system (not illustrated) or information on the active power and the reactive power measured by an active and reactive power measurement unit of the AC system (not illustrated) via the communication I/F 412. Eighth control circuit 87 notifies seventh control circuit 74 of the measurement results such as the effective voltage and the active power of the AC system.

(155) (3-2-1) AC Frequency Detection Circuit 81

(156) FIG. 12 is a block diagram illustrating a configuration of AC frequency detection circuit 81 illustrated in FIG. 11.

(157) As illustrated in FIG. 12, AC frequency detection circuit 81 includes a phase detection circuit 810, a frequency detection circuit 811, and a second sine wave generation circuit 812.

(158) Phase detection circuit 810 detects a zero-cross point from the waveform of the system voltage output from voltmeter 410. A method for detecting a phase in phase detection circuit 810 is not limited to the detection of the zero-cross point. For detection of the zero-cross point in an actual machine, an error occurs due to an error in detection of the zero-cross point by voltmeter 410 (mainly an offset error), an error in detection of amplitude by voltmeter 410 (mainly a linearity error), an error in sampling rate when the system voltage waveform is sampled, or the like. Note that, when sampling is performed using a microcomputer or the like, an error in sampling rate may

occur due to a variation in time from carrier interrupt to actual sampling.

(159) Frequency detection circuit **811** detects a system frequency from the period of the zero-cross point output from phase detection circuit **810**. Note that the method for detecting the system frequency is not limited to the method for detecting the system frequency from the period of the zero-cross point.

(160) Second sine wave generation circuit **812** generates a sine wave synchronized with the system voltage on the basis of the result of detecting the zero-cross point by phase detection circuit **810**, the result of detecting the frequency by frequency detection circuit **811**, and the amplitude of the system voltage output from CEMS **31**. AC frequency detection circuit **81** outputs the result of detecting the zero-cross point (time when the zero-cross point is detected), the result of detecting the frequency, and the sine wave information.

(161) (3-2-2) Inverter Voltage Control Circuit **85**

(162) FIG. **13** is a block diagram illustrating a configuration of inverter voltage control circuit **85** illustrated in FIG. **11**.

(163) As illustrated in FIG. **13**, inverter voltage control circuit **85** includes a third sine wave generation circuit **851**, a subtractor **852**, a third PI control circuit **853**, and a second PWM converter **854**.

(164) Inverter voltage control circuit **85** generates a control command value for controlling second DC/AC converter **408** on the basis of the information on the frequency and phase output from virtual synchronous generator control circuit **83** (FIG. **11**) and the information on the amplitude of the system voltage output from eighth control circuit **87** (FIG. **11**). Note that the information on the amplitude of the system voltage from eighth control circuit **87** is input to inverter voltage control circuit **85** via second sine wave generation circuit **812**.

(165) The sine wave information (information on the frequency, phase, and amplitude) from AC frequency detection circuit **81** (FIG. **11**) is input to third sine wave generation circuit **851**. Third sine wave generation circuit **851** generates a target value of the AC voltage output from second DC/AC converter **408** on the basis of the input sine wave information.

(166) Subtractor **852** calculates a deviation between the target value of the AC voltage from third sine wave generation circuit **851** and the voltage measured by voltmeter **410**, and outputs the calculated deviation to third PI control circuit **853**.

(167) Third PI control circuit **853** generates a voltage command value by performing a proportional integral (PI) operation so as to make the input deviation become zero. Third PI control circuit **853** outputs the generated voltage command value to second PWM converter **854**. Note that it is assumed that control parameters (control gain and integration time) for third PI control circuit **853** are provided from eighth control circuit **87**.

(168) Second PWM converter **854** performs pulse width modulation (PWM) control using the voltage command value output from third PI control circuit **853** to generate a control signal. Second PWM converter **854** outputs the generated control signal to second DC/AC converter **408**.

(169) (3-2-3) Virtual Synchronous Generator Control Circuit **83**

(170) FIG. **14** is a block diagram illustrating a configuration of virtual synchronous generator control circuit **83** illustrated in FIG. **11**.

(171) As illustrated in FIG. **14**, virtual synchronous generator control circuit **83** includes a subtractor **832**, a governor control circuit **833**, an adder **835**, a subtractor **836**, and a point mass system operation circuit **837**.

(172) Subtractor **832** calculates a deviation between the result of actually measuring the frequency and the reference frequency F_{ref} output from eighth control circuit **87**.

(173) The output of subtractor **832** is input to governor control circuit **833**. Governor control circuit **833** generates an offset value to be added to the power target value on the basis of the output of subtractor **832**. Details of the operation of governor control circuit **833** will be described later.

(174) Adder **835** adds up the offset value output from governor control circuit **833** and the power

target value Pref input from eighth control circuit **87** to generate a control power target value of point mass system operation circuit **837**.

(175) Subtractor **836** calculates a deviation between the effective power input from effective power calculation circuit **82** and the control power target value input from adder **835**. The output of subtractor **836** is input to point mass system operation circuit **837**.

(176) Point mass system operation circuit **837** calculates the frequency and phase of the system voltage output from power conversion device **41** so as to make the deviation output from subtractor **836** become zero. Note that, in the first embodiment, the control parameters (speed adjustment rate Kgd, governor time constant Tg, inertia constant M, and damping factor Dg) of governor control circuit **833** and point mass system operation circuit **837** are notified from CEMS **31** via eighth control circuit **87**.

(177) (3-2-3-1) Governor Control Circuit **833**

(178) FIG. **15** is a block diagram illustrating a configuration of governor control circuit **833** illustrated in FIG. **14**.

(179) As illustrated in FIG. **15**, governor control circuit **833** includes a multiplier **91**, a first-order lag system model **92**, and a limiter circuit **93**.

(180) Multiplier **91** multiplies the output of subtractor **832** by the proportional gain ($-1/Kgd$) output from eighth control circuit **87**. The output of multiplier **91** is input to first-order lag system model **92**. In the first embodiment, first-order lag system model **92** includes a standard model ($1/(1+s \times Tg)$) of the first-order lag system presented by the Institute of Electrical Engineers of Japan. Limiter circuit **93** performs limiter processing on the output of first-order lag system model **92**.

(181) (3-2-3-2) Point Mass System Operation Circuit **837**

(182) FIG. **16** is a block diagram illustrating a configuration of point mass system operation circuit **837** illustrated in FIG. **14**.

(183) As illustrated in FIG. **16**, point mass system operation circuit **837** includes a subtractor **101**, an integrator **102**, a multiplier **103**, a divider **104**, an adder **105**, and a phase calculation circuit **106**.

(184) Subtractor **101** calculates a deviation between the output of subtractor **836** and the output of multiplier **103**. The output of subtractor **101** is input to integrator **102**.

(185) Integrator **102** divides the output of subtractor **101** by inertia constant M and integrates the output of subtractor **101** to generate a difference value $\Delta\omega$ between the target angular velocity ($2 \times \pi \times$ target frequency (for example, 60 Hz)) of the generator rotor illustrated in FIG. **45** and the angular velocity of the generator rotor. The output of integrator **102** is input to multiplier **103**.

(186) Multiplier **103** multiplies the output of integrator **102** by the damping factor Dg input from eighth control circuit **87**.

(187) Point mass system operation circuit **837** is to mimic the damping force of the synchronous generator under the control of second DC/AC converter **408** on the basis of the deviation between the output of subtractor **836** and the output of multiplier **103**.

(188) Divider **104** divides the output $\Delta\omega$ of integrator **102** by $2 \times \pi$ to convert the output $\Delta\omega$ into a frequency difference value Δf . Adder **105** converts the frequency difference information Δf into the frequency (rotational frequency) of the generator rotor by adding the target frequency (60 Hz) to frequency difference information Δf . The output of adder **105** is input to phase calculation circuit **106**. Phase calculation circuit **106** calculates the phase of the generator rotor.

(189) Next, a transfer function of the swing equation of point mass system operation circuit **837** will be described. The transfer function of the swing equation can be expressed using the proportional gain ($1/Dg$) and the time constant (M/Dg) of the first-order lag system as shown in the following expression (3).

$$(1/M \times s) / \{1 + Dg/M \times (1/s)\} = (1/Dg) \times [1 / \{1 + (M/Dg) \times s\}] \quad (3)$$

(190) Note that the governor time constant Tg and the time constant M/Dg of the point mass system operation unit under the virtual synchronous generator control are determined on the basis

of a response speed required for the system.

(191) (Outline of Operation of Distributed Power Supply Management Device)

(192) Next, an outline of operation of the distributed power supply management device according to the first embodiment will be described.

(193) FIG. 17 is a diagram illustrating an area covered by the virtual synchronous generator control implemented in power conversion device 41. In FIG. 17, the horizontal axis represents a response time, and the vertical axis represents a range of fluctuation in demand.

(194) As illustrated in FIG. 17, the virtual synchronous generator control implemented in the static inverter covers minute fluctuations and short-period fluctuations of the order of about several tens of milliseconds to several minutes. Fluctuations of the order of several minutes or more can be dealt with by load frequency control (LFC) or economic load distribution control (EDC).

Therefore, in the first embodiment, the description will be given on the assumption that the response performance of the virtual synchronous generator control is less than or equal to 1 second.

(195) In the following description, a model including storage battery 40, power conversion device 41, impedance 29 of distribution system 24, and load 600 connected to distribution system 24 illustrated in FIG. 2 is used. For the sake of simplicity of the description, the inverter capacity of power conversion device 41 is set to 4 kW, and the maximum capacity of load 600 is set to 4 kW.

(196) FIG. 18 is a diagram for describing the virtual synchronous generator control implemented in power conversion device 41 according to the first embodiment. FIG. 18 illustrates an example of a relationship between the speed adjustment rate K_{gd} and the system frequency when the power consumed by load 600 is changed without changing the power target value. FIG. 18 illustrates a system frequency at each speed adjustment rate K_{gd} in a steady state when load 600 fluctuates from 2 kW to 4 kW in a state where the power target value of 2 kW is notified from CEMS 31 in FIG. 2. Note that the governor time constant T_g , the inertia constant M , and the damping factor D_g are each kept constant.

(197) In the example of FIG. 18, until K_{gd} becomes 0.343, the system frequency decreases as the numerical value of K_{gd} increases. On the other hand, it is confirmed that the system frequency converges when K_{gd} exceeds 0.343.

(198) FIG. 19 is a diagram for describing the virtual synchronous generator control implemented in power conversion device 41 according to the first embodiment. FIG. 19 illustrates an example of a relationship between the damping factor D_g and the system frequency when the load is suddenly changed. FIG. 19 illustrates a system frequency at each damping factor D_g when the load is changed from 2 kW to 4 kW in a state where the power target value of 2 kW is notified from CEMS 31 in FIG. 2. Note that the governor time constant T_g , the inertia constant M , and the speed adjustment rate K_{gd} ($=0.343$) are each kept constant. In the example of FIG. 19, it is confirmed that the system frequency becomes lower and lower as damping factor D_g decreases.

(199) In general, a limit (upper limit and lower limit) of the system frequency is about the reference frequency (hereinafter, also referred to as F_{ref}) ± 1 to 2%. Therefore, when the reference frequency F_{ref} is 60 Hz, the upper limit of the system frequency is about 61.2 to 60.6 Hz, and the lower limit of the system frequency is about 59.4 to 58.8 Hz. It is therefore necessary to set the speed adjustment rate K_{gd} and the damping factor D_g of the governor control so as to cause the system frequency to fall within the frequency range determined by the above-described limit.

(200) Next, the $\Delta P/\Delta F$ characteristic will be described.

(201) FIG. 20 is a diagram illustrating an example of the $\Delta P/\Delta F$ characteristic. In FIG. 20, the horizontal axis represents difference power ΔP that is a deviation between the power target value and the actual output power of power conversion device 41. The difference power ΔP is positive when the output power of power conversion device 41 is greater than the power target value.

(202) In FIG. 20, the vertical axis represents a difference frequency ΔF that is a deviation between the reference frequency F_{ref} (for example, 60 Hz) of the AC system and the frequency of the AC voltage output from power conversion device 41. The difference frequency ΔF is positive when the

frequency of the AC voltage output from the power conversion device **41** is higher than the reference frequency F_{ref} . ΔF_{max} denotes a maximum value of the difference frequency ΔF .

(203) In virtual synchronous generator control circuit **83** (FIG. **11**) according to the first embodiment, the $\Delta P/\Delta F$ characteristic illustrated in FIG. **20** is determined on the basis of the capacity of the static inverter (second DC/AC converter **408**), the speed adjustment rate K_{gd} , and the damping factor D_g . In FIG. **20**, the power target value is set to half of the capacity of the static inverter (second DC/AC converter **408**) without the charge of storage battery **40** taken into account. FIG. **20** illustrates a $\Delta P/\Delta F$ characteristic in a case where the system frequency when the power consumed by load **600** becomes the same as the capacity of the static inverter (second DC/AC converter **408**) in FIG. **2** is the upper limit ($F_{ref} + \Delta F_{max}$) and the system frequency when the power consumption of load **600** becomes zero is the lower limit ($F_{ref} - \Delta F_{max}$).

(204) In the first embodiment, the $\Delta P/\Delta F$ characteristic illustrated in FIG. **20** is referred to as “reference $\Delta P/\Delta F$ characteristic”. As described above, the reference $\Delta P/\Delta F$ characteristic is a $\Delta P/\Delta F$ characteristic under the condition that half of the capacity of the static inverter is set as the power target value in a discharge mode of storage battery **40**, the system frequency becomes the upper limit ($F_{ref} + \Delta F_{max}$) when the output of the static inverter coincides with the capacity, and the system frequency becomes the lower limit ($F_{ref} - \Delta F_{max}$) when the output of the static inverter becomes zero. Note that details of the discharge mode will be described later.

(205) FIG. **21** is a diagram illustrating a response waveform of the frequency of the AC voltage output from the static inverter when the load is suddenly changed under the virtual synchronous generator control implemented in power conversion device **41** according to the first embodiment.

(206) As described with reference to FIG. **17**, the virtual synchronous generator control implemented in the static inverter covers minute vibrations and short-period fluctuations of the order of about several tens of milliseconds to several minutes. Therefore, response performance of 1 second or less is required for the virtual synchronous generator control. In general, a decrease in the time constant increases the response performance, but causes the response waveform to fluctuate. Further, in a case where a plurality of distributed power supplies operates in cooperation with each other, a problem such as unnecessary cross current may occur. Therefore, in the first embodiment, as illustrated in FIG. **21**, a time constant for governor control circuit **833** (FIG. **15**) and point mass system operation circuit **837** (FIG. **16**) is determined so as to cause the system frequency to converge in about 1 second.

(207) (Conventional Virtual Synchronous Generator Control and Problems Thereof)

(208) Next, a problem in a case where two power conversion devices **41** having a conventional virtual synchronous generator control implemented are installed in distribution system **24** will be described.

(209) FIG. **22** is a diagram illustrating a response waveform of the effective value of the AC power output from each of the static inverters of two power conversion devices **41** having the conventional virtual synchronous generator control implemented. The response waveform illustrated in FIG. **22** indicates the waveform of the effective value of the AC power output from each static inverter when the load is suddenly changed with the two storage battery power conversion devices **41** constituting a stand-alone system.

(210) In FIG. **22**, the inverter capacity of each power conversion device **41** is set to 4 kW, and the power consumed by the load is set to 3.3 kW. With a power target value of a first storage battery (denoted as “BAT1” in the drawing) corresponding to a first power conversion device **41** set to 2.2 kW, and a power target value of a second storage battery (denoted as “BAT2” in the drawing) corresponding to a second power conversion device **41** set to 1.1 kW, the first and second power conversion devices **41** are controlled. In such a state, it is assumed that the power consumed by the load suddenly changes to about a half (1.65 kW) around 5 seconds.

(211) As illustrated in FIG. **22**, before the sudden change in load, power close to the power target value (2.2 kW) is output from first power conversion device **41**, power close to the power target

value (1.1 kW) is output from second power conversion device **41**, and a power ratio between the two is 2:1.

(212) On the other hand, after the sudden change in load, the output power of first power conversion device **41** is 1.35 kW, the output power of second power conversion device **41** is 0.3 kW, and the power ratio between the two is 9:2. It can be seen that after the load suddenly changes as described above, power is output from two power conversion devices **41** at the power proportional division ratio (9:2) different from the expected ratio (2:1).

(213) FIG. **23** illustrates a response waveform of the frequency of the AC voltage output from each static inverter when two power conversion devices **41** having the conventional virtual synchronous generator control implemented are put into operation under the above-described conditions. As illustrated in FIG. **23**, it can be seen that the frequencies of the AC voltages converge to substantially the same frequency by the virtual synchronous generator control even after the sudden change in load.

(214) With reference to FIGS. **24** and **25**, the reason why the power proportional division ratio changes when the load suddenly changes will be described below.

(215) FIG. **24** is a diagram illustrating an example of the $\Delta P/\Delta F$ characteristic of first power conversion device **41** having the conventional virtual synchronous generator control implemented. FIG. **25** is a diagram illustrating an example of the $\Delta P/\Delta F$ characteristic of second power conversion device **41** having the conventional virtual synchronous generator control implemented.

(216) Under the conventional virtual synchronous generator control, the $\Delta P/\Delta F$ characteristic is not switched in accordance with the power target value and the capacity of the static inverter. In the examples of FIGS. **24** and **25**, the static inverters of the two power conversion devices **41** have the same capacity (4 kW), so that it is assumed that the same $\Delta P/\Delta F$ characteristic is imparted.

(217) When the load suddenly changes as illustrated in FIG. **22**, the virtual synchronous generator control implemented in each power conversion device **41** operates such that two power conversion devices **41** share excess and deficient power. At this time, as illustrated in FIG. **23**, two power conversion devices **41** are controlled so as to make the frequencies of the AC voltages output from the static inverters equal to each other.

(218) On the other hand, the difference power ΔP between the power output from each power conversion device **41** and the power target value is determined by the $\Delta P/\Delta F$ characteristics illustrated in FIGS. **24** and **25**. Therefore, when the $\Delta P/\Delta F$ characteristics of two power conversion devices **41** are the same, the difference frequency ΔF is the same, so that the difference power ΔP also has the same value. As a result, as illustrated in FIG. **22**, after the sudden change in load, power is output from two power conversion devices **41** at a proportional division ratio different from an expected power proportional division ratio.

(219) (Virtual Synchronous Generator Control According to First Embodiment)

(220) FIG. **26** is a diagram illustrating an example of the $\Delta P/\Delta F$ characteristic of second power conversion device **41** having the virtual synchronous generator control according to the first embodiment implemented. The solid line in the drawing indicates the $\Delta P/\Delta F$ characteristic of second power conversion device **41**, and the dashed line indicates the $\Delta P/\Delta F$ characteristic of first power conversion device **41** (FIG. **24**).

(221) As illustrated in FIG. **22**, when the power target value (1.1 kW) of second power conversion device **41** is equal to half of the power target value (2.2 kW) of first power conversion device **41** (that is, the power proportional division ratio is 2:1), as illustrated in FIG. **26**, the $\Delta P/\Delta F$ characteristic of second power conversion device **41** is determined so as to make a ratio between the difference power ΔP (ΔP_1 in the drawing) of first power conversion device **41** and the difference power ΔP (ΔP_2 in the drawing) of second power conversion device **41** equal to the power target value (2:1) at the same difference frequency ΔF .

(222) As illustrated in FIG. **26**, it can be seen that, by determining the $\Delta P/\Delta F$ characteristics of two power conversion devices **41**, the ratio of the power shared between two power conversion devices

41 is equal to the ratio (2:1) of the power target value notified from CEMS **31** even when the load changes.

(223) (Method for Creating $\Delta P/\Delta F$ Characteristic)

(224) Next, a method for creating the $\Delta P/\Delta F$ characteristic of each power conversion device **41** in CEMS **31** will be described.

(225) In the first embodiment, when creating the $\Delta P/\Delta F$ characteristic of each power conversion device **41**, CEMS **31** first creates the reference $\Delta P/\Delta F$ characteristic for each power conversion device **41**. In the following description, a method for creating the reference $\Delta P/\Delta F$ characteristic focusing solely on the discharge of storage battery will be described.

(226) An operation mode of storage battery **40** includes the discharge mode in which storage battery **40** is discharged, a charge mode in which storage battery **40** is charged, and a charge and discharge mode in which storage battery **40** is charged and discharged. When storage battery **40** is put into operation in the discharge mode or the charge mode, the reference $\Delta P/\Delta F$ characteristic is created so as to make the difference power ΔP corresponding to $\Delta F_{\max}$ that is the limit of the difference frequency ΔF equal to half of the capacity of the static inverter.

(227) On the other hand, when storage battery **40** is put into operation in the charge and discharge mode (particularly, when the power target value is close to zero), the reference $\Delta P/\Delta F$ characteristic is created so as to make the difference power ΔP corresponding to $\Delta F_{\max}$ equal to the capacity of the static inverter.

(228) Note that CEMS **31** needs to create the reference $\Delta P/\Delta F$ characteristics of a plurality of managed power conversion devices **41** with the same policy. Therefore, CEMS **31** creates the reference $\Delta P/\Delta F$ characteristic with the charge and discharge mode taken into account for first power conversion device **41**, but does not create the reference $\Delta P/\Delta F$ characteristic with the charge mode or the discharge mode taken into account for second power conversion device **41**.

(229) FIG. **27** is a diagram illustrating an example of the reference $\Delta P/\Delta F$ characteristic of power conversion device **41** having the virtual synchronous generator control according to the first embodiment implemented.

(230) In the first embodiment, the reference $\Delta P/\Delta F$ characteristic is created on the basis of information on the limit ($F_{\text{ref}} \pm \Delta F_{\max}$) of the system frequency and information on the capacity of the static inverter notified from DSO **21**.

(231) Specifically, with only the discharge mode taken into account, the reference $\Delta P/\Delta F$ characteristic is created such that, with the power target value P_{ref} set equal to half of the capacity of the static inverter, the system frequency becomes equal to the lower limit ($F_{\text{ref}} - \Delta F_{\max}$) when power conversion device **41** outputs power equal to the capacity of the static inverter, and the system frequency becomes equal to the upper limit ($F_{\text{ref}} + \Delta F_{\max}$) when the output of the static inverter becomes zero.

(232) Note that, with only the charge mode taken into account, when the reference $\Delta P/\Delta F$ characteristic is created such that, with the charge power treated as a negative value, the system frequency becomes equal to the lower limit ($F_{\text{ref}} - \Delta F_{\max}$) when the charge power becomes zero, and the system frequency becomes equal to the upper limit ($F_{\text{ref}} + \Delta F_{\max}$) when the charge power becomes equal to the capacity of the static inverter, the same effect can be produced.

(233) Further, with the charge and discharge mode taken into account, when the reference $\Delta P/\Delta F$ characteristic is created such that, with the power target value P_{ref} set to zero, the system frequency becomes equal to the lower limit ($F_{\text{ref}} - \Delta F_{\max}$) when power equal to the capacity of the static inverter is discharged, and the system frequency becomes equal to the upper limit ($F_{\text{ref}} + \Delta F_{\max}$) when power equal to the capacity of the static inverter is charged, the same effect can be produced.

(234) Next, a method for creating the $\Delta P/\Delta F$ characteristic of each power conversion device **41** using the reference $\Delta P/\Delta F$ characteristic illustrated in FIG. **27** will be described with reference to FIG. **28**.

(235) In the following description, it is assumed that the static inverters of power conversion

devices **41** have the same capacity. In FIG. **28**, a method for creating the $\Delta P/\Delta F$ characteristic using the reference $\Delta P/\Delta F$ characteristic illustrated in FIG. **27** when the power target value is different from the power target value (half of the capacity of the static inverter) based on the reference $\Delta P/\Delta F$ characteristic will be described. The dashed line in the drawing indicates the reference $\Delta P/\Delta F$ characteristic (FIG. **27**), and the solid line indicates the $\Delta P/\Delta F$ characteristic.

(236) When the static inverters have the same capacity, in the first embodiment, a slope of the $\Delta P/\Delta F$ characteristic (solid line in the drawing) is obtained by multiplying a slope of the reference $\Delta P/\Delta F$ characteristic (dashed line in the drawing) by a result obtained by dividing half (0.5 times) of the capacity of the static inverter by the power target value P_{ref} of the power conversion device **41**. For example, when the power target value P_{ref} is 0.25 times the capacity of the static inverter, the slope of the $\Delta P/\Delta F$ characteristic is obtained by multiplying the slope of the reference $\Delta P/\Delta F$ characteristic by $0.5/0.25 (=2)$.

(237) Next, a case where the static inverters of power conversion devices **41** have different capacities will be described. In this case, a method for creating the reference $\Delta P/\Delta F$ characteristic of each power conversion device **41** is different from the above-described creation method.

(238) When the capacity of the static inverter is different among the plurality of power conversion devices **41**, a static inverter capacity as a reference is predetermined. For example, when where three static inverters have capacities of 10 kW, 8 kW, and 4 kW, 8 kW is used as a reference. It goes without saying that there is basically no problem even if any other capacity is selected as a reference. Then, a reference $\Delta P/\Delta F$ characteristic of the static inverter having the reference capacity (8 kW) is created using the creation method described in FIG. **27**.

(239) Next, a reference $\Delta P/\Delta F$ characteristic of the static inverter having a capacity of 4 kW is created using the reference $\Delta P/\Delta F$ characteristic of the static inverter having the reference capacity (8 kW). FIG. **29** is a diagram for describing a method for creating the reference $\Delta P/\Delta F$ characteristic of the static inverter having a capacity of 4 kW. The dashed line in the drawing indicates the reference $\Delta P/\Delta F$ characteristic (FIG. **27**) of the static inverter having the reference capacity, and the solid line indicates the reference $\Delta P/\Delta F$ characteristic of the static inverter having a capacity of 4 kW.

(240) As illustrated in FIG. **29**, a slope of the reference $\Delta P/\Delta F$ characteristic is obtained by multiplying a slope of the reference $\Delta P/\Delta F$ characteristic for the reference capacity (8 kW) by a value obtained by dividing the reference capacity (8 kW this time) by the capacity (4 kW this time) of its own static inverter. Specifically, the slope of the reference $\Delta P/\Delta F$ characteristic of the static inverter having a capacity of 4 kW is calculated by multiplying the slope of the reference $\Delta P/\Delta F$ characteristic of the static inverter having a reference capacity (8 kW) by $8/4 (=2)$. Likewise, a slope of a straight line of a reference $\Delta P/\Delta F$ characteristic of the static inverter having a capacity of 10 kW is calculated by multiplying the slope of the reference $\Delta P/\Delta F$ characteristic of the static inverter having the reference capacity (8 kW) by $8/10 (=0.8)$.

(241) FIG. **30** is a diagram illustrating an example of reference $\Delta P/\Delta F$ characteristics and $\Delta P/\Delta F$ characteristics of two power conversion devices **41** that are different in capacity of the static inverter. In FIG. **30**, a dashed line L1 indicates the reference $\Delta P/\Delta F$ characteristic of the first power conversion device **41**, and a solid line L2 indicates the $\Delta P/\Delta F$ characteristic of the first power conversion device **41**. A dashed line L3 indicates the reference $\Delta P/\Delta F$ characteristic of the second power conversion device **41**, and a solid line L4 indicates the $\Delta P/\Delta F$ characteristic of the second power conversion device **41**.

(242) In the example of FIG. **30**, for first power conversion device **41**, the capacity of the static inverter is 8 kW, and the power target value is 6 kW. For second power conversion device **41**, the capacity of the static inverter is 4 kW, and the power target value is 1 kW.

(243) FIG. **31** is a diagram illustrating waveforms of effective values of AC power output from two power conversion devices **41** illustrated in FIG. **30**. In the example of FIG. **31**, for first power conversion device **41**, the capacity of the static inverter is 8 kW, and the power target value is 2

kW. For second power conversion device **41**, the capacity of the static inverter is 4 kW, and the power target value is 1 kW.

(244) The waveforms in FIG. **31** are obtained by bringing first and second power conversion devices **41** into operation using the control parameters (Tg, Kgd, M, and Dg) generated by virtual synchronous generator control circuit **83** when the two power target values are 2 kW and 1 kW on the basis of the reference $\Delta P/\Delta F$ characteristics (solid lines L1, L3 in the drawing) of two power conversion devices **41** illustrated in FIG. **30**.

(245) FIG. **31** illustrates a waveform of the effective value of the AC power output from each power conversion device **41** when the load suddenly changes from 3 kW to 5.25 kW. As illustrated in FIG. **31**, the power proportional division ratio between first and second power conversion devices **41** is 2:1 both before and after the sudden change in load, showing that the operation is as expected.

(246) As described above, when the plurality of power conversion devices **41** each including the static inverter having the virtual synchronous generator control implemented are connected to distribution system **24**, the $\Delta P/\Delta F$ characteristic is created for each power conversion device **41** on the basis of the capacity of the static inverter and the power target value. Then, the control parameters of virtual synchronous generator control circuit **83** (FIG. **11**) are generated for each power conversion device **41** using the $\Delta P/\Delta F$ characteristic.

(247) With such a configuration, even when the power consumed by load **600** or the power generated by mega solar **26** suddenly changes, the ratio of the power output from each power conversion device **41** can be made equal to the ratio of the power target value notified from CEMS **31**. Accordingly, for example, it is possible to prevent an increase in ratio of the discharge power of storage battery **40** in which the discharge power is set small due to a small SOC to the entire discharge power.

(248) Note that, in the first embodiment, as the method for creating the $\Delta P/\Delta F$ characteristic, a method by which the reference $\Delta P/\Delta F$ characteristic of each power conversion device **41** is created, and the $\Delta P/\Delta F$ characteristic is created, using the created reference $\Delta P/\Delta F$ characteristic, in accordance with the power target value has been described, but the method for creating the $\Delta P/\Delta F$ characteristic is not limited to the above. For example, the control parameters (Tg, Kgd, M, Dg) of virtual synchronous generator control circuit **83** may be directly generated on the basis of the capacity of the static inverter, the power target value, and the SOC information on storage battery **40**.

(249) (Operation of Distributed Power Supply Management Device)

(250) With reference to FIGS. **1** to **41**, how the distributed power supply management device according to the first embodiment operates will be described below in detail.

(251) First, distribution system **24** to which the distributed power supply management device according to the first embodiment is applied will be described with reference to FIG. **1**.

(252) In the first embodiment, in distribution system **24**, the plurality of SVRs **23** are connected in series between substation **20** and power conversion device **27** (alternatively, power conversion device **41a** or town **100a**) in order to regulate the system voltage supplied from substation **20** within a predetermined voltage range.

(253) Power conversion device **27** operates as a current source. Power conversion device **27** is installed near power conversion device **41a**. In the first embodiment, power conversion device **41a** operates as a voltage source. Power conversion device **41a** can also smooth the power generated by mega solar **26** by performing the virtual synchronous generator control.

(254) As the load, towns **100a** to **100d**, factory **110**, building **112**, and condominium **113** exist. The load is supplied with the power supplied from substation **20**, power generated by mega solar **26**, and the discharge power of storage battery **40**. Synchronous generator **30a** serving as an emergency generator is installed in factory **110**, and synchronous generator **30b** serving as an emergency generator is installed in building **112**.

(255) How the distributed power supply management device operates in distribution system **24** that receives the power supplied from substation **20**, the power generated by mega solar **26**, and the discharge power of storage battery **40** will be described below.

(256) FIG. **32** is a sequence diagram for describing a normal operation of the distributed power supply management device, focusing on CEMS **31** illustrated in FIG. **1**.

(257) As illustrated in FIG. **32**, processing in the steady state includes processing performed at intervals of 30 minutes (hereinafter, also referred to as “first processing”) and processing performed at intervals of 5 minutes (hereinafter, also referred to as “second processing”).

(258) When the first processing (processing at intervals of 30 minutes) is started, DSO **21** requests CEMS **31** to output collected measurement data over communication line **25**. Upon receipt of the request from DSO **21**, CEMS **31** transmits, to DSO **21**, the measurement data including the amount of power consumed by each consumer, the amount of power generated by mega solar **26**, the amount of charge and discharge power of storage battery **40**, and the SOC of storage battery **40** collected in the last 30 minutes.

(259) Upon receipt of the measurement data, DSO **21** creates an operation plan of distribution system **24** on the basis of the measurement data and notifies CEMS **31** of the created operation plan. The operation plan of distribution system **24** includes a power supply plan from substation **20** to distribution system **24**, and is necessary for creating an operation plan (charge and discharge plan) of storage battery **40**. DSO **21** creates a 30-minute power supply plan for 24 hours. The 30-minute power supply plan indicates the total amount of power supplied from substation **20** to distribution system **24** for 30 minutes.

(260) Upon receipt of the operation plan (power supply plan) from DSO **21**, CEMS **31** requests power conversion device **41** to transmit measurement data. The measurement data includes the amount of charge and discharge power of storage battery **40** and the SOC information of storage battery **40** for the last 5 minutes. Upon receipt of the request from CEMS **31**, power conversion device **41** notifies CEMS **31** of the measurement data.

(261) CEMS **31** receives the measurement data from all power conversion devices **41a** to **41c** connected to distribution system **24**. At this time, CEMS **31** also collects measurement data such as the amount of power consumed by each consumer and the amount of power generated by mega solar **26** for 30 minutes.

(262) When the collection of the measurement data is completed, CEMS **31** creates the operation plan and control parameter of storage battery **40**. The operation plan of storage battery **40** is the charge and discharge plan of storage battery **40**, and includes a target value (power target value) of the amount of charge and discharge power of storage battery **40**. A method for creating the operation plan and control parameter of storage battery **40** will be described later.

(263) When the creation of the operation plan and control parameter of storage battery is completed, CEMS **31** notifies each power conversion device **41** of the operation plan and control parameter of a corresponding storage battery **40**, and brings the first processing to an end.

(264) Subsequently, CEMS **31** performs the second processing (processing at intervals of 5 minutes). CEMS **31** collects the measurement data from each power conversion device **41** at intervals of 5 minutes. CEMS **31** detects a deviation between the power target value and the actual charge and discharge power on the basis of the collected measurement data. When the deviation is greater than or equal to a predetermined threshold, CEMS **31** recalculates the operation plan (power target value) of storage battery **40** and notifies each power conversion device **41** of the recalculation result. Note that a specific recalculation method will be described later.

(265) (Operation of CEMS **31**)

(266) Next, the operation of CEMS **31** will be described in detail with reference to FIG. **33**.

(267) FIG. **33** is a flowchart of control processing of CEMS **31** illustrated in FIG. **1**. As illustrated in FIG. **33**, when the processing is started, CEMS **31** checks whether the output request of the measurement data has been received from DSO **21** in step (hereinafter, abbreviated as S) **01**. When

the output request has been received (YES in S01), CEMS 31 collects the measurement data from the plurality of power conversion devices 41 in S02. In S03, CEMS 31 notifies DSO 21 of the measurement data stored in storage circuit 12 via communication circuit 11.

(268) On the other hand, when the output request has not been received from DSO 21 (NO in S01) or the measurement data has been transmitted to DSO 21 in S03, CEMS 31 proceeds to S04 and checks whether the operation plan (power supply plan) has been received from DSO 21. When the operation plan has been received (YES in S04), CEMS 31 proceeds to S05 and creates the operation plan (charge and discharge plan) of storage battery 40.

(269) FIG. 34 is a flowchart of processing of creating the operation plan of storage battery 40 (S05 of FIG. 33).

(270) As illustrated in FIG. 34, when the processing is started, CEMS 31 predicts the amount of power generated by mega solar 26 in S051. Specifically, referring back to FIGS. 3 and 4, upon receipt of the operation plan from DSO 21, control circuit 16 (FIG. 3) instructs management circuit 146 (FIG. 4) in operation plan creation circuit 14 to create the operation plan. Upon receipt of the instruction from control circuit 16, management circuit 146 instructs power generation prediction circuit 142 to predict power to be generated by mega solar 26 via storage battery operation plan creation circuit 141.

(271) Upon receipt of the instruction from management circuit 146, power generation prediction circuit 142 accesses a weather forecast server (not illustrated) provided on the Internet to acquire a 24-hour weather forecast from the present to 24 hours later. Power generation prediction circuit 142 predicts the amount of power to be generated for 24 hours from the present to 24 hours later using the acquired 24-hour weather forecast and data stored in a database (not illustrated) used for predicting the amount of power to be generated, the database being managed by power generation prediction circuit 142. Note that the database used for predicting the amount of power to be generated is constructed on the basis of a record of the amount of power generated by mega solar 26 collected at intervals of 30 minutes and information on recorded weather. No description will be given below of a method for constructing the database.

(272) When the amount of power to be generated is predicted in S051, CEMS 31 predicts the amount of power to be consumed by each consumer in S052. Specifically, referring back to FIG. 4, upon receipt of the result of predicting the amount of power to be generated by mega solar 26 from power generation prediction circuit 142, management circuit 146 instructs power consumption prediction circuit 143 to predict the amount of power to be consumed by each consumer via storage battery operation plan creation circuit 141.

(273) Upon receipt of the instruction from management circuit 146, power consumption prediction circuit 143 predicts the amount of power to be consumed by each consumer for 24 hours from the present to 24 hours later using data stored in a database (not illustrated) used for predicting the amount of power to be consumed, the database being managed the power consumption prediction circuit 143. Note that the database used for predicting the amount of power to be consumed is constructed by processing the amount of power consumed by each consumer collected at intervals of 30 minutes on the basis of the date, the time information, and the weather information. No description will be given below of a method for constructing the database.

(274) When the amount of power to be consumed by each consumer is predicted in S052, CEMS 31 creates a demand plan in S053. Specifically, referring back to FIG. 4, upon receipt of the result of predicting the amount of power to be consumed by each consumer from power consumption prediction circuit 143, storage battery operation plan creation circuit 141 calculates the sum of the amount of charge and discharge power of storage batteries 40a to 40c every 30 minutes on the basis of the result of predicting, by power generation prediction circuit 142, the amount of power to be generated by mega solar 26, the result of predicting, by power consumption prediction circuit 143, the amount of power to be consumed by each consumer, and the operation plan (30-minute power supply plan) notified from DSO 21.

(275) When the demand plan has been created in S053, CEMS 31 determines the charge and discharge power (power target value) of storage batteries 40a to 40c in S054. Specifically, referring back to FIGS. 3 and 4, storage battery operation plan creation circuit 141 proportionally divides the charge and discharge power of each storage battery 40 every 30 minutes on the basis of the SOC information and storage battery capacities of storage batteries 40a to 40c collected in storage circuit 12 via communication circuit 11.

(276) In the first embodiment, when creating the 24-hour operation plan of storage battery 40, CEMS 31 determines the charge and discharge power of each storage battery 40 so as to make the SOC of each of storage batteries 40a to 40c become zero at the same time, or to cause storage batteries 40a to 40c to be fully charged in 24 hours.

(277) This is because of the following reason. For example, it is assumed that clouds cross over mega solar 26 for about 5 minutes, and the amount of power generated by mega solar 26 decreases from 10 MW to 4 MW. Note that it is assumed that the capacities of the static inverters of power conversion devices 41a to 41c are 8 MW, 4 MW, and 2 MW, respectively.

(278) Here, it is assumed that power conversion devices 41b, 41c are notified of a storage battery operation plan in which the SOC of storage battery 40a becomes zero first, and storage battery 40a is stopped discharging power, so as to cause the remaining storage batteries 40b, 40c to discharge 1 MW and 0.5 MW, respectively. When the amount of power generated by mega solar 26 decreases by 6 MW due to a sudden change in solar radiation amount, storage batteries 40b, 40c can further discharge only 3 MW and 1.5 MW, respectively, under the virtual synchronous generator control, so that the shortage of 6 MW cannot be covered.

(279) On the other hand, when storage batteries 40a to 40c are in operation, it is possible to discharge up to 14 MW (=8 MW+4 MW+2 MW), so that the power range that can be covered by the virtual synchronous generator control becomes wider. Therefore, when CEMS 31 creates the operation plan (charge and discharge plan) of storage battery 40, it is necessary to create the operation plan so as to make the SOC of each of storage batteries 40a to 40c become zero at almost the same time or to cause storage batteries 40a to 40c to be fully charged.

(280) When the charge and discharge power (power target value) of storage batteries 40a to 40c has been determined in S054, CEMS 31 checks whether the control parameter of the virtual synchronous generator control has been generated for all storage batteries 40a to 40c in S055. When the generation of the control parameter for all storage batteries 40a to 40c is not completed (NO in S055), CEMS 31 proceeds to S056 and generates the control parameter of the virtual generator control.

(281) FIG. 35 is a flowchart of processing of generating the control parameter of the virtual synchronous generator control (S056 of FIG. 34). The processing illustrated in FIG. 35 is performed by control parameter generation circuit 13 (FIG. 5) in CEMS 31.

(282) As illustrated in FIG. 35, when the processing is started, control circuit 136 (FIG. 5) collects, in S0561, the power target value of storage battery 40 for the next 30 minutes, the capacity of second DC/AC converter 408 (static inverter) in power conversion device 41, and the information on distribution system 24 generated by storage battery operation plan creation circuit 141 in S054 of FIG. 34. Note that the information on distribution system 24 includes the upper and lower limits of the system frequency, the response performance of virtual synchronous generator control circuit 83 (FIG. 11), and the like. The upper limit of the system frequency is the reference frequency F_{ref} (for example, 60 Hz)+ ΔF_{max} , and the lower limit of the system frequency is $F_{ref}-\Delta F_{max}$.

(283) When the information collection is completed in S0561, reference $\Delta P/\Delta F$ characteristic calculation circuit 131 calculates the reference $\Delta P/\Delta F$ characteristic for each power conversion device 41 in S0562. The reference $\Delta P/\Delta F$ characteristic will be described below.

(284) In order to generate the control parameter of power conversion device 41 having the virtual synchronous generator control implemented, first, the reference $\Delta P/\Delta F$ characteristic of the static inverter is calculated. Note that, in the first embodiment, a configuration where the control

parameter is generated for the power conversion device **41** will be described, but it is possible to generate, using the same method, a control parameter with a configuration where the virtual synchronous generator control is implemented in a power conversion device capable of regulating the output such as a wind power generation device.

(285) Specifically, as illustrated in FIG. 27, in the discharge mode of storage battery **40**, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** determines the reference $\Delta P/\Delta F$ characteristic such that, with half of the capacity of the static inverter set as the power target value, the frequency of the AC voltage when the static inverter discharges the maximum power becomes equal to the lower limit frequency (difference frequency $\Delta F = -\Delta F_{\max}$ in FIG. 27), and the frequency of the AC voltage when the discharge power of the static inverter is zero becomes equal to the upper limit frequency ($\Delta F = \Delta F_{\max}$ in FIG. 27).

(286) On the other hand, in the charge mode of storage battery **40**, the reference $\Delta P/\Delta F$ characteristic is determined such that, with half of the capacity of the static inverter set as the power target value, the frequency of the AC voltage when the static inverter gives a charge of the maximum power becomes equal to the upper limit frequency ($\Delta F = \Delta F_{\max}$), and the frequency of the AC voltage when the charge power of static inverter is zero becomes equal to the lower limit frequency ($\Delta F = -\Delta F_{\max}$).

(287) Further, in the charge and discharge mode of storage battery **40**, the reference $\Delta P/\Delta F$ characteristic is determined such that, with the power target value of the static inverter set to zero, the frequency of the AC voltage when the static inverter discharges the maximum power becomes equal to the lower limit frequency ($\Delta F = -\Delta F_{\max}$), and the frequency of the AC voltage when the static inverter gives a charge of the maximum power becomes equal to the upper limit frequency ($\Delta F = \Delta F_{\max}$).

(288) FIG. 36 is a flowchart of processing of generating the reference $\Delta P/\Delta F$ characteristic (S0562 of FIG. 35).

(289) As illustrated in FIG. 36, when the processing is started, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** (FIG. 5) collects information on the capacity (C_{inv}) of a target static inverter from control circuit **136** in S05621.

(290) When the information on the capacity of the static inverter has been collected, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** collects system information ($\Delta F_{\max}$) in S05622. Next, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** obtains the slope of the reference $\Delta P/\Delta F$ characteristic using the inverter capacity C_{inv} and $\Delta F_{\max}$ in S05623.

(291) Specifically, when storage battery **40** is in the charge mode or the discharge mode, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** sets the slope of the reference $\Delta P/\Delta F$ characteristic to $-\Delta F_{\max}/(C_{\text{inv}} \times 0.5)$. On the other hand, when storage battery **40** is in the charge and discharge mode, the slope of the reference $\Delta P/\Delta F$ characteristic is set to $-\Delta F_{\max}/C_{\text{inv}}$.

(292) Note that storage battery operation plan creation circuit **141** (FIG. 4) determines which reference $\Delta P/\Delta F$ characteristic in the discharge mode (or the charge mode) or the charge and discharge mode is selected on the basis of the result of the determination of the charge and discharge power of storage battery **40** in the demand plan created in S053 of FIG. 34. Specifically, when the absolute value of the determined charge and discharge power is less than a predetermined value, storage battery operation plan creation circuit **141** selects the charge and discharge mode. Note that the mode thus selected is applied to all power conversion devices **41** connected to distribution system **24**.

(293) Referring back to FIG. 35, when the reference $\Delta P/\Delta F$ characteristic has been calculated in S0562, $\Delta P/\Delta F$ characteristic calculation circuit **132** (FIG. 5) generates the $\Delta P/\Delta F$ characteristic in S0563. Specifically, referring back to FIG. 5, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** outputs the slope of the generated reference $\Delta P/\Delta F$ characteristic to control circuit **136** and $\Delta P/\Delta F$ characteristic calculation circuit **132**.

(294) $\Delta P/\Delta F$ characteristic calculation circuit **132** calculates the $\Delta P/\Delta F$ characteristic on the basis

of the power target value provided from control circuit **136**. FIG. **37** is a flowchart of processing of generating the $\Delta P/\Delta F$ characteristic (**S0563** of FIG. **35**). As illustrated in FIG. **37**, when the processing is started, $\Delta P/\Delta F$ characteristic calculation circuit **132** collects the power target value from control circuit **136** in **S05631**. $\Delta P/\Delta F$ characteristic calculation circuit **132** determines whether the magnitude of the collected power target value exceeds the static inverter capacity C_{inv} in **S05632**.

(295) When the magnitude of the power target value exceeds the static inverter capacity C_{inv} (NO in **S05632**), $\Delta P/\Delta F$ characteristic calculation circuit **132** limits the power target value to the static inverter capacity C_{inv} using the limiter in **S05633**.

(296) $\Delta P/\Delta F$ characteristic calculation circuit **132** obtains the slope of the $\Delta P/\Delta F$ characteristic using the power target value in **S05634**. Specifically, when storage battery **40** is in the discharge mode or the charge mode, the slope of the $\Delta P/\Delta F$ characteristic is set to the slope of the reference $\Delta P/\Delta F$ characteristic $\times (C_{inv} \times 0.5) / \text{the power target value}$. On the other hand, when storage battery **40** is in the charge and discharge mode, it is assumed that variations in power generated by renewable energy such as mega solar **26** or wind power generation are absorbed (power target value is zero), and the $\Delta P/\Delta F$ characteristic depending only on the static inverter capacity, that is, the reference $\Delta P/\Delta F$ characteristic obtained in **S0562** of FIG. **35** is used as it is.

(297) Referring back to FIG. **35**, when the $\Delta P/\Delta F$ characteristic has been generated in **S0563**, control circuit **136** generates the control parameter of the virtual synchronous generator control in **S0564**. With reference to FIGS. **5** and **38**, a method for generating the control parameter will be described.

(298) As illustrated in FIG. **5**, control circuit **136** instructs control parameter generation circuit **133** to generate the control parameter.

(299) Upon receipt of the instruction for generating the control parameter, control parameter generation circuit **133** generates the control parameter on the basis of the slope of the $\Delta P/\Delta F$ characteristic provided from $\Delta P/\Delta F$ characteristic calculation circuit **132**, the system information (reference frequency F_{ref} , ΔF_{max}) input from control circuit **136**, the power target value P_{ref} , and the inverter capacity C_{inv} . In the first embodiment, a case where virtual synchronous generator model **134** that mimics the operation of virtual synchronous generator control circuit **83** (FIG. **11**) is implemented in control parameter generation circuit **13** (FIG. **3**), and the control parameter is generated using this model will be described.

(300) Note that the method for generating the control parameter is not limited to the above, and, for example, a configuration may be employed where, with the relationship between the speed adjustment rate K_{gd} and the system frequency illustrated in FIG. **18** stored as table data associated with each damping factor D_g and the relationship between the damping factor D_g and the system frequency illustrated in FIG. **19** stored as table data associated with each speed adjustment rate K_{gd} , an appropriate speed adjustment rate K_{gd} and an appropriate damping factor D_g are determined using such table data.

(301) In the first embodiment, a mathematical model of the block diagrams illustrated in FIGS. **14** to **16** is used as virtual synchronous generator model **134**, but the virtual synchronous generator model **134** is not limited to such a mathematical model. For example, a configuration may be employed where a transfer function of virtual synchronous generator control circuit **83** (FIG. **11**) is generated from the transfer function of the governor control unit represented by the above-described expression (1) and the swing equation represented by the above-described expression (2), and the control parameter is generated from the generated transfer function.

(302) FIG. **38** is a flowchart of processing of generating the control parameter (**S0564** of FIG. **35**). As illustrated in FIG. **38**, when the generation of the control parameter is started, virtual synchronous generator model **134** (FIG. **5**) initializes the speed adjustment rate K_{gd} and the damping factor D_g by setting the speed adjustment rate K_{gd} and the damping factor D_g to their respective predetermined initial values in **S05641**. In the first embodiment, only the speed

adjustment rate K_{gd} and the damping factor D_g that determine the $\Delta P/\Delta F$ characteristic are generated by virtual synchronous generator model **134**.

(303) When the speed adjustment rate K_{gd} and the damping factor D_g are initialized in **S05641**, virtual synchronous generator model **134** proceeds to **S05642**, and calculates the slope of the $\Delta P/\Delta F$ characteristic using the speed adjustment rate K_{gd} and the damping factor D_g .

(304) In **S05643**, virtual synchronous generator model **134** compares the slope of the $\Delta P/\Delta F$ characteristic calculated in **S05642** with the slope of the $\Delta P/\Delta F$ characteristic generated in **S0563** (FIG. 37) in FIG. 35. Specifically, virtual synchronous generator model **134** checks whether a deviation between the slopes of the two $\Delta P/\Delta F$ characteristics falls within a predetermined allowable range.

(305) When the deviation between the slopes falls within the allowable range, virtual synchronous generator model **134** determines that the slopes of the two $\Delta P/\Delta F$ characteristics coincide with each other (YES in **S05643**), and proceeds to **S05649**.

(306) On the other hand, in a case where the deviation between the slopes falls outside the allowable range, virtual synchronous generator model **134** determines that the slopes of the two $\Delta P/\Delta F$ characteristics do not coincide with each other (NO in **S05643**). In this case, virtual synchronous generator model **134** proceeds to **S05644** and changes the damping factor D_g . In the first embodiment, virtual synchronous generator model **134** adds a predetermined value to the current damping factor D_g .

(307) After changing the damping factor D_g in **S05644**, virtual synchronous generator model **134** checks whether the damping factor D_g falls within a predetermined range in **S05645**. When damping factor D_g falls within the predetermined range (YES in **S05645**), virtual synchronous generator model **134** returns to **S05642** and calculates the slope of the $\Delta P/\Delta F$ characteristic using the changed damping factor D_g .

(308) On the other hand, when the damping factor D_g falls outside the predetermined range (NO in **S05645**), virtual synchronous generator model **134** determines that an appropriate characteristic cannot be obtained with the current speed adjustment rate K_{gd} , and returns the damping factor D_g to the initial value and changes the speed adjustment rate K_{gd} in **S05646**. Specifically, virtual synchronous generator model **134** adds a predetermined value to the current speed adjustment rate K_{gd} (initial value).

(309) After changing the speed adjustment rate K_{gd} in **S05646**, virtual synchronous generator model **134** checks whether the speed adjustment rate K_{gd} falls within a predetermined range in **S05647**. When speed adjustment rate K_{gd} falls outside the predetermined range (NO in **S05647**), virtual synchronous generator model **134** proceeds to **S05648**, sets the speed adjustment rate K_{gd} and the damping factor D_g to their respective default values prepared in advance on the assumption that an appropriate speed adjustment rate K_{gd} and an appropriate damping factor D_g have not been obtained, and then proceeds to **S05649**.

(310) On the other hand, when the speed adjustment rate K_{gd} falls within the predetermined range in **S05647** (YES in **S05647**), virtual synchronous generator model **134** returns to **S05642**, and calculates the slope of the $\Delta P/\Delta F$ characteristic using the changed speed adjustment rate K_{gd} and the damping factor D_g . Virtual synchronous generator model **134** repeatedly performs the processing of **S05642** to **S05647** until **S05654** is determined to be YES in or **S05647** is determined to be NO.

(311) When the speed adjustment rate K_{gd} and the damping factor D_g have been set, control parameter generation circuit **133** calculates the inertia constant M in **S05649**. In the first embodiment, the inertia constant M is calculated on the basis of a response time required for the virtual synchronous generator control. Specifically, the response performance of the virtual synchronous generator control is determined by the governor time constant T_g of governor control circuit **833** (FIG. 14) and the time constant M/D_g of point mass system operation circuit **837** (FIG. 14) obtained by the swing equation. In the first embodiment, the default value of the governor time

constant T_g is used, and the governor time constant T_g is not generated, so that only the time constant of point mass system operation circuit **837** is controlled. The time constant of point mass system operation circuit **837** is obtained by M/D_g from the above-described expression (3). Therefore, in the first embodiment, the inertia constant M is calculated by multiplying the time constant of point mass system operation circuit **837** determined by the default value by the damping factor D_g .

(312) Referring back to FIG. **34**, when the control parameter of the virtual synchronous generator control has been generated in **S056**, control parameter generation circuit **13** returns to **S055** and checks whether the calculation of the control parameters of all power conversion devices **41** connected to distribution system **24** is completed. When the calculation of the control parameters of all power conversion devices **41** is not calculated (NO in **S055**), control parameter generation circuit **13** proceeds to **S056** and calculates the control parameter of next power conversion device **41**. On the other hand, when the calculation of the control parameters of all power conversion devices **41** is completed (YES in **S055**), control parameter generation circuit **13** brings the creation of the operation plan of storage battery **40** to end.

(313) When the creation of the operation plan of storage battery **40** is completed in **S05** of FIG. **33**, storage battery operation plan creation circuit **141** (FIG. **4**) notifies management circuit **145** of the created operation plan (power target value). Upon receipt of the operation plan, management circuit **145** stores the received operation plan in the memory and notifies transmission data generation circuit **15** (FIG. **3**) of the operation plan. Control parameter generation circuit **13** notifies transmission data generation circuit **15** of the generated control parameters.

(314) Upon receipt of the operation plan (power target value) of storage battery **40** and the control parameters, transmission data generation circuit **15** converts the operation plan and the control parameters to a transmission format and outputs the result of the conversion to communication circuit **11** (FIG. **3**). Upon receipt of the data transmitted from transmission data generation circuit **15**, communication circuit **11** transmits the transmitted data to a corresponding power conversion device **41** over communication line **25**.

(315) When the transmission of the operation plans and the control parameters to all power conversion devices **41** is completed in **S10** of FIG. **33**, whether to stop CEMS **31** is checked in **S11**. When CEMS **31** is stopped (YES in **S11**), the processing is brought to an end. On the other hand, when CEMS **31** is not stopped (NO in **S11**), the processing returns to **S01**.

(316) On the other hand, when the operation plan (power supply plan) has not been received from DSO **21** in **S04** of FIG. **33** (NO in **S04**), CEMS **31** proceeds to **S06** and checks whether the collection time of various measurement data has arrived. In the first embodiment, as described above, CEMS **31** collects the measurement data at intervals of 5 minutes. When the collection time of measurement data has not arrived (NO in **S06**), the processing returns to **S01**. On the other hand, when the collection time of measurement data has arrived (YES in **S06**), CEMS **31** collects measurement data in **S07**. In the first embodiment, CEMS **31** collects the amount of charge and discharge power of storage battery **40** for 5 minutes, and the current charge and discharge power and SOC information of storage battery **40** from each of power conversion devices **41a** to **41c** as measurement data.

(317) After collecting the measurement data in **S07**, CEMS **31** checks whether or not the operation plan of storage battery **40** needs to be corrected in **S08**. In **S07**, CEMS **31** compares the current charge and discharge power with the operation plan (power target value) for each of the plurality of storage batteries **40**. Specifically, CEMS **31** checks whether a power difference between the current charge and discharge power and the power target value falls outside a predetermined range and whether the SOC of storage battery **40** falls outside a predetermined allowable range. When the power difference falls outside the predetermined range and/or the SOC falls outside the allowable range in any one of the plurality of storage batteries **40**, CEMS **31** reviews the operation plans of all storage batteries **40**. Note that the operation plan of storage battery **40** in which the power

difference falls outside the predetermined range and/or the SOC falls outside the allowable range may be reviewed.

(318) CEMS **31** checks whether the operation plan of storage battery **40** needs to be corrected in the manner described above, and returns to **S01** and continues the processing when determining that the operation plan of storage battery **40** need not be corrected (NO in **S08**). On the other hand, when determining that the operation plan of storage batteries **40** needs to be corrected (YES in **S08**), CEMS **31** proceeds to **S09** and corrects the operation plans of all storage batteries **40**.

(319) FIG. **39** is a flowchart of processing of correcting the operation plan of storage battery **40** (**S09** of FIG. **33**). The processing illustrated in FIG. **39** is performed by operation plan creation circuit **14** (FIG. **4**) in CEMS **31**.

(320) As illustrated in FIG. **39**, when the processing is started, management circuit **146** (FIG. **4**) instructs, in **S091**, storage battery operation plan correction circuit **144** (FIG. **4**) to correct the operation plan, and transfers the charge and discharge power and the SOC information collected from each power conversion device **41**. In **S092**, management circuit **146** also outputs the operation plan (power target value) of storage battery **40** stored in management circuit **145** (FIG. **4**) and the capacity of the static inverter of power conversion device **41** stored in storage circuit **12** to storage battery operation plan correction circuit **144**.

(321) Storage battery operation plan correction circuit **144** reviews the operation plan of storage battery **40** on the basis of the information provided from management circuit **146**. For example, it is assumed that the output power of power conversion device **41** is twice the power target value because either the predicted value of the power to be generated by mega solar **26** or the predicted value of the power to be consumed by each consumer is different from the actual value.

(322) In such a case, it is assumed that the system frequency decreases to about the same as the lower limit ($F_{ref} - \Delta F_{max}$). When the power shortage further occurs, the system frequency becomes the lower limit, and a situation where power cannot be supplied from power conversion device **41** any more may occur.

(323) Therefore, in the first embodiment, when a ratio between the power target value and the charge and discharge power falls outside a predetermined range, storage battery operation plan correction circuit **144** corrects the operation plan (power target value) of storage battery **40** on the basis of the measurement data collected at intervals of 5 minutes. Specifically, storage battery operation plan correction circuit **144** corrects the operation plan of storage battery **40** on the basis of the current charge and discharge power and the SOC information.

(324) Here, the reason why the SOC is used in correction of the operation plan of storage battery **40** is that when a lithium ion battery is used as storage battery **40**, storage battery **40** may fail or deteriorate rapidly due to overcharge or overdischarge. Therefore, under the normal storage battery control, when the SOC exceeds, for example, 90%, the charge mode of the storage battery is switched from a constant current charge mode to a constant voltage charge mode. In the constant voltage charge mode, the charge power cannot be increased, so that it is necessary to reduce the power target value under the virtual synchronous generator control. Likewise, even in a case of overdischarge, storage battery **40** further deteriorates, so that it is necessary to reduce the discharge power when the SOC falls below 5%, for example. Therefore, the SOC is used in creation and correction of the operation plan of storage battery **40**.

(325) Note that in a case where a lead-acid battery is used as storage battery **40**, the lead-acid battery is resistant to overcharge, but tends to deteriorate due to overdischarge. Therefore, for such a lead-acid battery, for example, it is necessary to reduce the discharge power when the SOC falls below 20%. As described above, in order to suppress deterioration of the storage battery in use, the power target value is corrected using the SOC.

(326) Specifically, storage battery operation plan correction circuit **144** creates the operation plan of storage battery **40** on the basis of the current charge and discharge power, and creates the operation plan of storage battery **40** on the basis of the current charge and discharge power and the

SOC for charging when the SOC is close to the upper limit and discharging when the SOC is close to the lower limit. Specifically, when the SOC is close to the upper limit, the range of the charge power target value is narrowed down, and when the SOC is close to the lower limit, the range of the discharge power target value is narrowed down.

(327) When the operation plan (power target value) of storage battery **40** has been corrected in **S093**, control parameter generation circuit **13** (FIG. **3**) checks whether the calculation of the control parameters of all storage batteries **40** is completed in **S094**. When the calculation of the control parameters of all storage batteries **40** is completed (YES in **S094**), storage battery operation plan correction circuit **144** brings the processing of correcting the operation plan of storage battery **40** to an end. On the other hand, when the correction of the operation plans of all storage batteries **40** is not completed (NO in **S094**), control parameter generation circuit **13** generates the control parameter of the virtual synchronous generator control in **S095**. Note that a method for generating the control parameter of the virtual synchronous generator control is similar to the creation method used in the processing of creating the operation plan of storage battery **40** (**S056** of FIG. **34** and FIG. **35**), and thus no description will be given below of the method.

(328) When the control parameter has been generated in **S095**, control parameter generation circuit **13** returns to **S094**, and checks whether the calculation of the control parameters of all power conversion devices **41** is completed. When the calculation of the control parameters of all power conversion devices **41** is not completed (NO in **S094**), control parameter generation circuit **13** generates the control parameter of next power conversion device **41** in **S095**.

(329) On the other hand, when the calculation of the control parameters of all power conversion devices **41** is completed (YES in **S094**), storage battery operation plan correction circuit **144** brings the processing of correcting the operation plan of storage battery **40** to an end.

(330) Referring back to FIG. **33**, when the operation plan of storage battery **40** has been corrected in **S09**, storage battery operation plan creation circuit **141** notifies management circuit **145** of the corrected operation plan (power target value) in a similar manner to the creation of the operation plan.

(331) When acquiring the operation plan of storage battery **40** from storage battery operation plan creation circuit **141**, management circuit **145** stores the acquired operation plan in a memory (not illustrated) and notifies transmission data generation circuit **15** of the acquired operation plan.

Likewise, control parameter generation circuit **13** notifies transmission data generation circuit **15** of the operation plan and control parameter of storage battery **40**.

(332) Upon receipt of the operation plan and control parameter of storage battery **40**, transmission data generation circuit **15** convert the operation plan and control parameter to a transmission format and outputs the result of the conversion to communication circuit **11**.

(333) Upon receipt of the transmission data from transmission data generation circuit **15**, communication circuit **11** transmits the transmission data to a corresponding power conversion device **41** over communication line **25** (**S10** of FIG. **33**).

(334) When the transmission of the operation plan of storage battery **40** to all power conversion devices **41** is completed in **S10** of FIG. **33**, whether to stop CEMS **31** is checked in **S11**. When CEMS **31** is stopped (YES in **S11**), the processing is brought to an end. On the other hand, when CEMS **31** is not stopped, the processing returns to **S01** and continues.

(335) As described above, in the first embodiment, when creating the operation plan (power target value) of storage battery **40** for power conversion device **41**, the control parameter of the virtual synchronous generator control implemented in the static inverter is generated on the basis of the capacity of the static inverter of each power conversion device **41** and the power target value.

Accordingly, even when the power consumed by load **600** or the power generated by the energy creation equipment such as mega solar **26** fluctuates in a period until the next operation plan is notified from CEMS **31**, the excess and deficient power can be shared using the same proportional division ratio as the operation plan (power target value) of storage battery **40**.

(336) Therefore, for example, in a case where the power generated by mega solar **26** decreases by 50% due to a change in solar radiation amount immediately after notifying all power conversion devices **41** of the operation plan, the shortage of power corresponding to 50% is proportionally divided on the basis of the ratio of the power target value calculated at the time of creating the operation plan. For example, when the charge and discharge power of each of storage batteries **40** has been determined such that the SOC of each of all storage batteries **40** become zero at almost the same time when the power target value is controlled in accordance with the ratio at the time of creating the operation plan, the excess and deficient power is proportionally divided on the basis of the ratio of the power target value even when the power generated by mega solar **26** decreases by 50%, and it is thus possible to perform control such that the SOC of each of all storage batteries **40** become zero at almost the same time.

(337) In the first embodiment, the configuration where, when the control parameter of the virtual synchronous generator control is generated for the static inverter of power conversion device **41**, the control parameter is calculated using the inverter capacity and the power target value has been described, but the present disclosure is not limited to such a configuration, and, for example, in a case where the ratio of the capacity of storage battery **40** to the inverter capacity is different among power conversion devices **41**, for example, the capacity of storage battery **40a** is twice the inverter capacity of power conversion device **41a**, or the capacity of storage battery **40b** is three times the inverter capacity of power conversion device **41b**, the operation plan (power target value) of each storage battery **40** is generated with the capacity ratio taken into account. Alternatively, the same effect can be produced by taking the capacity ratio when generating the control parameter into account.

(338) (Operation of Power Conversion Device **27** and Power Conversion Device **41**)

(339) With reference to FIGS. **6** to **16**, **40**, and **41**, how mega solar power conversion device **27** and storage battery power conversion device **41** operate will be described below.

(340) [Operation of Power Conversion Device **27**]

(341) With reference to FIG. **6**, how mega solar power conversion device **27** operates will be described.

(342) When mega solar **26** starts to generate power, the DC voltage input from mega solar **26** to first DC/DC converter **203** in power conversion device **27** increases. First control circuit **204** monitors the DC voltage measured by voltmeter **201**. When the DC voltage exceeds a predetermined voltage value, first control circuit **204** causes power conversion device **27** to transition from a standby state to the normal operation.

(343) Upon transition to the normal operation, second control circuit **209** in power conversion device **27** controls first DC/AC converter **208**. How power conversion device **27** performs control during the normal operation will be described below.

(344) Referring to FIG. **6**, first control circuit **204** checks whether mega solar **26** is generating power. Specifically, first control circuit **204** checks whether the output voltage of mega solar **26** measured by voltmeter **201** exceeds the predetermined voltage. When the output voltage exceeds the predetermined voltage, first control circuit **204** notifies second control circuit **209** that mega solar **26** can generate power.

(345) Upon receipt of the notification from first control circuit **204**, second control circuit **209** checks whether power is being supplied from substation **20** to distribution system **24** (whether distribution system **24** is in a power failure) on the basis of the AC voltage of distribution system **24** measured by voltmeter **10**.

(346) When confirming that the AC voltage measured by voltmeter **210** is higher than or equal to a predetermined voltage, and distribution system **24** is not in a power failure, second control circuit **209** activates DC/AC converter **208** and instructs first control circuit **204** to start power generation of mega solar **26**.

(347) Note that, in the first embodiment, a case where the DC bus voltage of DC bus **205** is

managed by first DC/AC converter **208** during the normal operation will be described. Further, in the first embodiment, power regenerated from power conversion device **27** to distribution system **24** is managed by the current control by first DC/AC converter **208**, thereby operating the entire distributed power supply management device.

(348) When mega solar **26** is instructed to start power generation by second control circuit **209**, fifth control circuit **54** (FIG. **8**) of first control circuit **204** instructs MPPT control circuit **51** (FIG. **8**) to start maximum power point tracking control of mega solar **26**.

(349) The maximum power point tracking control will be briefly described. Under the maximum power point tracking control, whether the last command value is made greater or less than the power command value before last is managed. Then, the generated power of mega solar **26** measured this time is compared with the generated power of mega solar **26** measured last time, and when the generated power has increased, the command value is changed in the same direction (increasing direction or decreasing direction) as the last time.

(350) Specifically, when the generated power of mega solar **26** measured this time is larger than the generated power measured last time, and the last command value is greater than the command value before last, the current command value is increased. On the other hand, when the last command value is less than the command value before last, the current command value is decreased. On the contrary, when the generated power of mega solar **26** measured this time is smaller than the generated power measured last time, and the last command value is greater than the command value before last, the current command value is decreased. On the other hand, when the last command value is less than the command value before last, the current command value is increased. Controlling the current command value in this manner causes mega solar **26** to be controlled so as to maximize the output power.

(351) First DC/DC converter **203** operates a built-in booster circuit in accordance with a command value output from first control circuit **204** to convert the first DC voltage output from mega solar **26** into the second DC voltage (DC bus voltage of DC bus **205**) and output the second DC voltage.

(352) When the supply of the power generated by mega solar **26** from first DC/DC converter **203** is started, second control circuit **209** controls first DC/AC converter **208** to output (regenerate) the power generated by mega solar **26** to distribution system **24**. Specifically, the DC bus voltage of DC bus **205** is monitored, and when the DC bus voltage exceeds the control target value, the generated power is output in synchronization with the AC voltage supplied from distribution system **24**.

(353) With reference to FIG. **9**, how second control circuit **209** operates will be described.

(354) In second control circuit **209**, phase detection circuit **61** detects the zero-cross point of the waveform of the AC voltage of distribution system **24** measured by voltmeter **210** (FIG. **1**).

(355) First sine wave generation circuit **62** generates a reference sine wave synchronized with the waveform of the AC voltage of distribution system **24** on the basis of information indicating the zero-cross point detected by phase detection circuit **61** and the waveform of the AC voltage measured by voltmeter **210**. First sine wave generation circuit **62** outputs the generated reference sine wave to multiplier **65**.

(356) Voltmeter **206** measures the voltage of DC bus **205** and outputs the measurement value to subtractor **63** and sixth control circuit **67** in current control circuit **60**. Note that current control circuit **60** uses a control method (current control) by which power is output in synchronization with the AC system voltage. This control method is a control method applied to a general power conversion device for photovoltaic generation installed at a home.

(357) Sixth control circuit **67** stores the target voltage of DC bus **205** and outputs the target voltage to subtractor **63**.

(358) Current control circuit **60** controls the current output from first DC/AC converter **208** so as to make the DC bus voltage measured by voltmeter **206** equal to the target voltage. The output of subtractor **63** is input to first PI control circuit **64**. First PI control circuit **64** performs PI control so

as to make the output of the subtractor **63** become zero. The output of first PI control circuit **64** is input to multiplier **65** and is multiplied by the reference sine wave from first sine wave generation circuit **62** to convert into a current command value.

(359) The current command value output from multiplier **65** is input to subtractor **66**. Subtractor **66** calculates a deviation between the current command value and the AC value of distribution system **24** measured by ammeter **211**, and inputs the calculated deviation to second PI control circuit **68**.

(360) Second PI control circuit **68** performs PI control so as to make the deviation output from the subtractor **66** become zero. First PWM converter **69** performs PWM control on the output of second PI control circuit **68** to generate a command value of first DC/AC converter **208**. First DC/AC converter **208** outputs an alternating current in accordance with the command value provided from first PWM converter **69**.

(361) Further, when the AC voltage (AC effective voltage) measured by voltmeter **210** exceeds a predetermined voltage value, or when a request for reducing the power generated by mega solar **26** is notified from CEMS **31**, fifth control circuit **54** (FIG. **8**) in first control circuit **204** switches the control of mega solar **26** from the MPPT control to the voltage control. Specifically, fifth control circuit **54** controls the DC voltage output from mega solar **26** such that the AC voltage (AC effective voltage) measured by voltmeter **210** falls within the predetermined voltage range.

Alternatively, fifth control circuit **54** controls the output voltage of mega solar **26** such that the power generated by mega solar **26** falls within a power range notified from CEMS **31**.

(362) Note that first switching circuit **53** (FIG. **8**) switches between the output of MPPT control circuit **51** and the output of voltage control circuit **52** in accordance with a switching control signal provided from fifth control circuit **54**.

(363) Sixth control circuit **67** collects the measurement results regarding DC bus **205** measured by voltmeter **206** and ammeter **207**, the measurement results regarding distribution system **24** measured by voltmeter **210** and ammeter **211**, the status information of first DC/DC converter **203** output from first control circuit **204**, and the like, and notifies CEMS **31** and the like of the collected information via communication I/F **212**.

(364) Sixth control circuit **67** also notifies CEMS **31**, via communication I/F **212**, of the effective voltage of distribution system **24** measured by an effective voltage measurement unit (not illustrated) or the information on the active power and reactive power of the AC system measured by an active and reactive power measurement unit (not illustrated), and further notifies fifth control circuit **54** of the measurement results of the effective voltage, the active power, and the like of the AC system.

(365) As described above, when the effective value of the AC system voltage exceeds the predetermined value, fifth control circuit **54** suppresses an increase in the AC system voltage by switching the control of mega solar **26** from the MPPT control to the voltage control.

(366) [Operation of Power Conversion Device **41**]

(367) With reference to FIGS. **7**, **10** to **16**, **40**, and **41**, how storage battery power conversion device **41** operates will be described below.

(368) In the first embodiment, since the virtual synchronous generator control is implemented in power conversion device **41**, second DC/AC converter **408** operates as a voltage source by performing voltage control. That is, third control circuit **404** (FIG. **7**) performs control to make the voltage of DC bus **405** constant. With reference to FIG. **10**, how third control circuit **404** operates will be described below.

(369) The voltage of DC bus **405** is measured by voltmeter **406**. The measurement value of voltmeter **406** is input to charge control circuit **71**, discharge control circuit **72**, and seventh control circuit **74**.

(370) Charge control circuit **71** and discharge control circuit **72** control the charge power or the discharge power so as to make the voltage of DC bus **405** equal to the target voltage output from seventh control circuit **74**. Specifically, when storage battery **40** is being discharged, control is

performed such that the discharge power is decreased when the voltage of DC bus **405** is higher than the target voltage, and the discharge power is increased when the voltage of DC bus **405** is lower than the target voltage, thereby making the voltage of DC bus **405** coincident with the target voltage.

(371) On the other hand, when storage battery **40** is being charged, control is performed such that the charge power is increased when the voltage of DC bus **405** is higher than the target voltage, and the charge power is decreased when the voltage of DC bus **405** is lower than the target voltage, thereby making the voltage of the DC bus **405** coincident with the target voltage.

(372) Note that switching between the output of charge control circuit **71** and the output of discharge control circuit **72** is performed by second switching circuit **73**. Seventh control circuit **74** outputs a switching control signal to second switching circuit **73** on the basis of the charge and discharge operation of storage battery **40**.

(373) With reference to FIGS. **11** to **16** and **40**, how fourth control circuit **409** (FIG. **7**) operates will be described below.

(374) FIG. **40** is a flowchart for describing how power conversion device **41** operates.

(375) As illustrated in FIG. **40**, when the processing is started, fourth control circuit **409** initializes various control parameters in **S200**. Subsequently, in **S201**, fourth control circuit **409** collects the voltage values measured by voltmeters **401**, **406**, **410**, the current values measured by ammeters **402**, **407**, **411**, and the status information of storage battery **40**. Note that the measurement value of voltmeter **410** is an AC voltage, so that eighth control circuit **87** (FIG. **11**) calculates the effective value of the AC voltage, and sets the effective value as a voltage value. The measurement value of ammeter **411** is an alternating current, so that eighth control circuit **87** calculates the effective value of the alternating current, and sets the effective value as a current value. A charge and discharge power calculation circuit (not illustrated) in seventh control circuit **74** calculates the charge and discharge power and the amount of charge and discharge power of the storage battery on the basis of the collected data.

(376) The AC voltage of distribution system **24** measured by voltmeter **410** is input to AC frequency detection circuit **81** (FIG. **11**). In **S202**, AC frequency detection circuit **81** detects the zero-cross point of the waveform of the AC voltage.

(377) FIG. **12** is a block diagram illustrating a configuration of AC frequency detection circuit **81** illustrated in FIG. **11**. As illustrated in FIG. **12**, the measurement value of voltmeter **410** is input to phase detection circuit **810**. In **S202** of FIG. **40**, phase detection circuit **810** detects the zero-cross point of the AC voltage. Note that, in the first embodiment, the zero-cross point indicates a point and time at which the waveform of the AC voltage measured by voltmeter **410** changes from negative to positive. Phase detection circuit **810** outputs information indicating the detected zero-cross point to frequency detection circuit **811**.

(378) Frequency detection circuit **811** calculates the period of the AC voltage on the basis of a time of the last detection of the zero-cross point by phase detection circuit **810** and a time of the current detection of the zero-cross point. Frequency detection circuit **811** calculates the frequency of the AC voltage on the basis of the calculated period.

(379) Second sine wave generation circuit **812** outputs information on the zero-cross point detected by phase detection circuit **810** and information on the frequency of the AC voltage detected by frequency detection circuit **811** as sine wave information. The zero-cross point information and the frequency information are output to inverter current control circuit **84**, inverter voltage control circuit **85**, virtual synchronous generator control circuit **83**, and eighth control circuit **87**.

(380) Referring back to FIG. **40**, when the zero-cross point has been detected in **S202** (YES in **S202**), phase detection circuit **810** sets a zero-cross point detection flag in **S203**. When the processing of **S203** is finished, or when the zero-cross point is not detected in **S202** (NO in **S202**), fourth control circuit **409** controls second DC/AC converter **408** in **S204**.

(381) With reference to FIGS. **11** and **41**, the control of second DC/AC converter **408** will be

described below.

(382) As described above, since power conversion device **41** has the virtual synchronous generator control implemented, second DC/AC converter **408** is controlled as a voltage source. That is, second DC/AC converter **408** is voltage-controlled. Therefore, when the power supplied to distribution system **24** is insufficient, second DC/AC converter **408** is controlled to increase the output power. On the other hand, when the power supplied to distribution system **24** is excessive, second DC/AC converter **408** is controlled to decrease the output power.

(383) FIG. **41** is a flowchart for describing details of control processing of second DC/AC converter **408**.

(384) As illustrated in FIG. **41**, after calculating the power value on the basis of the measurement values of voltmeter **410** and ammeter **411** in **S2041**, effective power calculation circuit **82** (FIG. **11**) integrates the calculated power value in **S2042**. When the zero-cross point detection flag is set (YES in **S2043**), effective power calculation circuit **82** proceeds to **S2044**, stores the integral value of the effective power value for one period of the AC voltage in a storage circuit (not illustrated) in eighth control circuit **87**, and zero-initializes the integral value in **S2045**.

(385) When the processing of **S2045** is finished or when the zero-cross point detection flag is not set (NO in **S2043**), inverter voltage control circuit **85** generates a command value of second DC/AC converter **408** in **S2046**.

(386) When the command value is generated in **S2046**, virtual synchronous generator control circuit **83** (FIG. **11**) performs the virtual synchronous generator control. In the first embodiment, one period of the AC voltage is set as a control period. The control period may be an integral multiple of one period of the AC voltage or a predetermined period such as a period of 1 second.

(387) FIG. **14** is a block diagram illustrating a configuration of virtual synchronous generator control circuit **83**.

(388) When determining that the control timing has arrived, eighth control circuit **87** (FIG. **11**) instructs virtual synchronous generator control circuit **83** to generate information on the frequency and the phase used for voltage control. In the first embodiment, the frequency and the phase of the sine wave generated by third sine wave generation circuit **851** (FIG. **13**) in inverter voltage control circuit **85** are updated at the zero-cross point. Therefore, in the first embodiment, the control period corresponds to a period of the zero-cross point detected by AC frequency detection circuit **81**.

(389) As illustrated in FIG. **14**, in virtual synchronous generator control circuit **83**, subtractor **832** subtracts the reference frequency F_{ref} (for example, 60 Hz) input from eighth control circuit **87** from the actual measurement value of the frequency of the AC voltage input from AC frequency detection circuit **81** (FIG. **11**), and outputs the result of the subtraction to governor control circuit **833**. FIG. **15** is a block diagram illustrating a detailed configuration of governor control circuit **833** illustrated in FIG. **14**.

(390) As illustrated in FIG. **15**, in governor control circuit **833**, multiplier **91** multiplies the output of subtractor **832** (FIG. **14**) by the control parameter $(-1/K_{gd})$ notified from eighth control circuit **87**. Multiplier **91** inputs the result of the multiplication to first-order lag system model **92**.

(391) Note that, regarding the speed adjustment rate K_{gd} and the governor time constant T_g used in governor control circuit **833**, the speed adjustment rate K_{gd} and the governor time constant T_g notified from CEMS **31** are set in a register (not illustrated) via eighth control circuit **87** and used.

(392) As described above, first-order lag system model **92** performs an operation to mimic the first-order lag system $(1/(1+s \times T_g))$ using the time constant T_g notified from eighth control circuit **87**, and outputs the result of the operation to limiter circuit **93**.

(393) Limiter circuit **93** puts a limit on the input data. Specifically, limiter circuit **93** puts a limit on the output power of second DC/AC converter **408** so as to prevent the output power from exceeding the power capacity of second DC/AC converter **408**.

(394) Referring back to FIG. **14**, adder **835** adds up the output of governor control circuit **833** and the power target value P_{ref} output from eighth control circuit **87**. Note that the power target value

Pref notified from CEMS 31 is output from eighth control circuit 87.

(395) Subtractor 836 subtracts the actual value of the effective power output from effective power calculation circuit 82 (FIG. 11) from the output of adder 835, and outputs the result of the subtraction to point mass system operation circuit 837. FIG. 16 is a block diagram illustrating a detailed configuration of point mass system operation circuit 837 illustrated in FIG. 15.

(396) As illustrated in FIG. 16, subtractor 101 subtracts the output of multiplier 103 from the output of subtractor 836 (FIG. 14), and outputs the value obtained by the subtraction to integrator 102.

(397) Integrator 102 divides the result of the subtraction from subtractor 101 by the inertia constant M output from eighth control circuit 87, and integrates the result of the division. The output $\alpha\omega$ of integrator 102 corresponds to a difference value relative to the angular velocity ($2\times\pi\times 60$ Hz) of the frequency of the AC voltage. The output $\Delta\omega$ of integrator 102 is input to multiplier 103 and divider 104.

(398) Multiplier 103 multiplies the output $\Delta\omega$ of integrator 102 by the damping factor D_g provided from eighth control circuit 87, and outputs the result of the multiplication to subtractor 101.

(399) Divider 104 converts the output $\Delta\omega$ of integrator 102 into a difference value Δf corresponding to a difference from the reference frequency f_{ref} (60 Hz) by dividing output $\Delta\omega$ by $2\times\pi$. Adder 105 adds up the output Δf of divider 104 and the reference frequency f_{ref} (60 Hz) to generate a frequency ($f_{ref}+\Delta f$) for performing voltage control in inverter voltage control circuit 85 (FIG. 11).

(400) Note that, regarding the inertia constant M and the damping factor D_g used in point mass system operation circuit 837, the inertia constant M and the damping factor D_g generated and notified by CEMS 31 are set in a register (not illustrated) via eighth control circuit 87, and the inertia constant M and the damping factor D_g set in the register are used.

(401) The frequency information ($f_{ref}+\Delta f$) output from adder 105 is input to phase calculation circuit 106. How phase calculation circuit 106 operates will be described below.

(402) In the first embodiment, the frequency information output from adder 105 (FIG. 16) is integrated by phase calculation circuit 106 and output as phase information used when inverter voltage control circuit 85 performs voltage control.

(403) The phase information and the frequency information output from point mass system operation circuit 837 (FIG. 16) are input to third sine wave generation circuit 851 (FIG. 13) in inverter voltage control circuit 85 via second sine wave generation circuit 812 (FIG. 12) in AC frequency detection circuit 81. Third sine wave generation circuit 851 generates the target value of the AC voltage output from power conversion device 41 on the basis of the input information.

(404) Referring back to FIG. 40, when the processing of the virtual synchronous generator control is brought to an end in S205, fourth control circuit 409 checks whether a transmission request of the measurement data has received from CEMS 31 in S206. Upon receipt of the transmission request from CEMS 31 (YES in S206), eighth control circuit 87 (FIG. 11) notifies CEMS 31 of the measurement data via communication I/F 412 (FIG. 7) in S207.

(405) On the other hand, after the measurement data is notified in S207 or when there is no transmission request from CEMS 31 (NO in S206), eighth control circuit 87 proceeds to S208 and checks whether the control information has been received from CEMS 31.

(406) When the control information has been received from CEMS 31 (YES in S208), eighth control circuit 87 sets a control information reception flag in S209. When the processing of S209 is finished, or when the control information has not been received from CEMS 31 (NO in S208), eighth control circuit 87 checks whether or not the zero-cross point detection flag is set in S210. When the zero-cross point detection flag is not set (NO in S210), the processing returns to S201.

(407) On the other hand, when the zero-cross point detection flag is set (YES in S210), second sine wave generation circuit 812 (FIG. 12) takes the frequency and phase information on the system voltage in S211, and resets the zero-cross point detection flag in S212.

(408) When the zero-cross point detection flag is reset in S212, second sine wave generation circuit 812 updates, to the information taken in S211, the frequency and phase information on the system voltage (zero-cross point time information in the first embodiment) in S213.

(409) Upon completion of the processing of S213, eighth control circuit 87 checks whether the control information has been received from CEMS 31 (whether the control information reception flag is set) in S214. When the reception flag is not set (NO in S214), the processing returns to S201.

(410) On the other hand, when the reception flag is set (YES in S214), eighth control circuit 87 replaces each of the frequency target value (reference frequency F_{ref}) and the power target value P_{ref} with the received data in S215. Eighth control circuit 87 updates the control parameter of the virtual synchronous generator control to the control parameter (the speed adjustment rate K_{gd} , the damping factor D_g , and the inertia constant M) received in S216.

(411) When the update of the control parameter is completed in S216, eighth control circuit 87 clears (resets) a register (not illustrated) in which the reception flag is set, and returns to S201.

(412) As described above, the distributed power supply management device according to the first embodiment allows, even when the demand balance largely changes immediately after notifying each of power conversion devices 41a to 41c of the operation plan (power target value) of a corresponding one of storage batteries 40a to 40c created by CEMS 31, the proportional division ratio of the output power of power conversion devices 41a to 41c to be nearly equal to the ratio of the power target value at the time of creating the operation plan. Accordingly, in a case where the operation plan (discharge plan) is created so as to make the SOC of each of storage batteries 40a to 40c become zero at almost the same time after several hours, or in a case where the operation plan (charge plan) is created so as to cause storage batteries 40a to 40c to be fully charged at almost the same time, even when the power consumed by load 600 or the power generated by mega solar 26 largely changes from the power expected at the time of creating the operation plan, it is possible to make the SOC of each of storage batteries 40a to 40c become zero at almost the same time or cause storage batteries 40a to 40c to be fully charged at almost the same time although it is deviated from the expected time, and it is therefore possible to comply with the expected operation plan.

(413) Further, in the conventional virtual synchronous generator control technology, since power conversion devices 41a to 41c equally share the excess and deficient power, the power proportional division ratio for power conversion device 41 having a relatively small power target value becomes high, and the SOC of a corresponding storage battery 40 becomes zero prior to the other storage batteries 40 in some cases. On the other hand, according to the first embodiment, since the excess and deficient power can be proportionally divided at the ratio of the power target value set in the operation plan, the power proportional division ratio for storage battery 40 having a low SOC (that is, the power target value is small) can be kept low.

Second Embodiment

(414) In the first embodiment, the configuration where CEMS 31 generates the control parameter of the virtual synchronous generator control implemented in power conversion device 41 and transmits the control parameter to power conversion device 41 has been described. In a second embodiment, a configuration where CEMS 31 transmits a parameter necessary for generating the control parameter to power conversion device 41, and power conversion device 41 generates the control parameter using the received parameter will be described.

(415) CEMS 31 in the second embodiment 2 differs from CEMS 31 in the first embodiment only in the configuration of control parameter generation circuit 13 (FIG. 5). A distributed power supply management device according to the second embodiment will be described below, focusing on an operation of a portion different from the first embodiment.

(416) FIG. 42 is a block diagram illustrating a configuration of control parameter generation circuit 13 according to the second embodiment. Control parameter generation circuit 13 illustrated in FIG. 42 is obtained by removing control parameter generation circuit 133 and virtual synchronous

generator model **134** from control parameter generation circuit **13** illustrated in FIG. 5 and replacing control circuit **136** with a control circuit **137**.

(417) In the second embodiment, CEMS **31** generates the slope of the $\Delta P/\Delta F$ characteristic, and transmits the generated slope of the $\Delta P/\Delta F$ characteristic, the power target value Pref, the system information (limit value ($F_{ref} \pm \Delta F_{max}$) of the system frequency), the response performance of the virtual synchronous generator control, and the like to power conversion device **41**. Power conversion device **41** generates the control parameter using the data received from CEMS **31** and the capacity of its own static inverter.

(418) In the second embodiment, a configuration where CEMS **31** generates the $\Delta P/\Delta F$ characteristic will be described, but the present disclosure is not limited to such a configuration, and a configuration where CEMS **31** transmits all information necessary for generating the control parameter or intermediately generated data to power conversion device **41**, and power conversion device **41** generates the control parameter using the received data may be employed. This allows a reduction in amount of data transmitted from CEMS **31** to power conversion device **41**.

(419) As illustrated in FIG. **42**, control parameter generation circuit **13** according to the second embodiment includes reference $\Delta P/\Delta F$ characteristic calculation circuit **131**, $\Delta P/\Delta F$ characteristic calculation circuit **132**, management circuit **135**, and control circuit **137**.

(420) Reference $\Delta P/\Delta F$ characteristic calculation circuit **131** calculates the reference $\Delta P/\Delta F$ characteristic on the basis of information on the capacities of the static inverters (second DC/AC converters **408**) of power conversion devices **41a** to **41c**.

(421) $\Delta P/\Delta F$ characteristic calculation circuit **132** calculates the $\Delta P/\Delta F$ characteristic on the basis of the reference $\Delta P/\Delta F$ characteristic and the power target value Pref created by operation plan creation circuit **14** (FIG. 5).

(422) Management circuit **135** stores, in a memory (not illustrated), and manages information such as the slope of the $\Delta P/\Delta F$ characteristic output from $\Delta P/\Delta F$ characteristic calculation circuit **132** and the power target value Pref.

(423) Control circuit **137** manages how reference $\Delta P/\Delta F$ characteristic calculation circuit **131**, $\Delta P/\Delta F$ characteristic calculation circuit **132**, and management circuit **135** operate.

(424) How CEMS **31** according to the second embodiment operates will be described below. The operation of CEMS **31** according to the second embodiment is different from the operation of CEMS **31** according to the first embodiment only in the processing of generating the control parameter of the virtual synchronous generator control (S056 of FIG. 34 and FIG. 35). The operation of a different portion will be described below.

(425) FIG. **43** is a flowchart of the processing of generating the control parameter of the virtual synchronous generator control (S056 of FIG. 34). The processing illustrated in FIG. **43** is performed by control parameter generation circuit **13** (FIG. 42) in CEMS **31**.

(426) As illustrated in FIG. **43**, when the processing is started, first, control circuit **137** collects, in S10561, the power target value Pref calculated from the amount of charge and discharge power of storage battery **40** for the next 30 minutes created in S054 of FIG. 34, the inverter capacity Cinv of second DC/AC converter **408** in power conversion device **41**, and information on distribution system **24** (limit of the system frequency ($F_{ref} \pm \Delta F_{max}$), the response performance of the virtual synchronous generator control). In the second embodiment, in S054 of FIG. 34, storage battery operation plan creation circuit **141** (FIG. 4) creates the power target value Pref of each power conversion device **41**.

(427) When the information is collected in S10561, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** (FIG. 42) calculates reference $\Delta P/\Delta F$ characteristic in S10562. The method for creating reference $\Delta P/\Delta F$ characteristic is the same as the method described in the first embodiment. That is, in the discharge mode or the charge mode of storage battery **40**, the reference $\Delta P/\Delta F$ characteristic is created such that, with half of the inverter capacity serving as the reference set as the power target value (positive in a case of discharging, and negative in a case of charging), the frequency of

the AC voltage when the static inverter discharges the maximum power (when the charge power is zero in a case of charging) becomes equal to the lower limit frequency ($F_{ref}-\Delta F_{max}$), and such that the frequency of the AC voltage when the discharge power of the static inverter is zero (when the maximum power is charged in a case of charging) becomes equal to the upper limit frequency ($F_{ref}+\Delta F_{max}$).

(428) On the other hand, in the charge and discharge mode of storage battery **40**, the reference $\Delta P/\Delta F$ characteristic is created such that, with half of the inverter capacity serving as the reference set as the power target value, the frequency of the AC voltage when the static inverter gives a charge of the maximum power becomes equal to the upper limit frequency, and the frequency of the AC voltage when the charge power of the static inverter becomes zero becomes equal to the lower limit frequency.

(429) After calculating the reference $\Delta P/\Delta F$ characteristic in **S10562**, $\Delta P/\Delta F$ characteristic calculation circuit **132** creates the $\Delta P/\Delta F$ characteristic in **S10563**. Specifically, as illustrated in FIG. **42**, after creating the reference $\Delta P/\Delta F$ characteristic, reference $\Delta P/\Delta F$ characteristic calculation circuit **131** outputs the slope of the generated reference $\Delta P/\Delta F$ characteristic to control circuit **137** and $\Delta P/\Delta F$ characteristic calculation circuit **132**.

(430) $\Delta P/\Delta F$ characteristic calculation circuit **132** calculates the $\Delta P/\Delta F$ characteristic on the basis of the power target value P_{ref} notified from control circuit **137**. Specifically, when the power target value P_{ref} collected from control circuit **137** exceeds the inverter capacity C_{inv} , $\Delta P/\Delta F$ characteristic calculation circuit **132** limits the power target value P_{ref} to the inverter capacity C_{inv} . Then, in the discharge mode or the charge mode of storage battery **40**, $\Delta P/\Delta F$ characteristic calculation circuit **132** calculates the slope of the $\Delta P/\Delta F$ characteristic such that the slope of the $\Delta P/\Delta F$ characteristic = the slope of the reference $\Delta P/\Delta F$ characteristic $\times (C_{inv} \times 0.5) / P_{ref}$.

(431) When the slope of the $\Delta P/\Delta F$ characteristic is calculated, control circuit **137** outputs the slope of the $\Delta P/\Delta F$ characteristic, the power target value P_{ref} , and the system information ($F_{ref} \pm \Delta F_{max}$, response performance of the virtual synchronous generator control, and the like) to management circuit **135**. Management circuit **135** stores the input information in a storage unit (not illustrated) for each power conversion device **41**. The subsequent operation is the same as the operation in the first embodiment, and thus no description will be given below of the operation.

(432) How power conversion device **41** according to the second embodiment operates will be described below.

(433) FIG. **44** is a flowchart focusing on the operation of fourth control circuit **409** (FIG. **11**).

(434) As illustrated in FIG. **44**, when power conversion device **41** is put into operation, as in the first embodiment, fourth control circuit **409** initializes various control parameters and sets the various control parameters to predetermined initial values in **S200**.

(435) After initializing the various control parameters, fourth control circuit **409** collects the measurement values of voltmeters **401**, **406**, **410** and ammeter **402**, **407**, **411** and the status information (such as SOC) of storage battery **40** in **S201**. In the second embodiment, fourth control circuit **409** calculates the charge and discharge power of storage battery **40**, and the amount of charge and discharge power of storage battery **40** on the basis of the collected data.

(436) Next, in **S202**, fourth control circuit **409** detects the zero-cross point of the AC voltage. When the zero-cross point is detected (YES in **S202**), the processing proceeds to **S203**, and the zero-cross point detection flag is set. Note that the zero-cross point indicates a point and time at which the waveform of the AC voltage measured by voltmeter **410** changes from negative to positive as in the first embodiment. AC frequency detection circuit **81** (FIG. **11**) calculates the period of the AC voltage on the basis of time information on the last detection of the zero-cross point by phase detection circuit **810** (FIG. **12**) and time information on the current detection of the zero-cross point, and calculates the frequency of the AC voltage on the basis of the result of the calculation.

(437) Second sine wave generation circuit **812** (FIG. **12**) outputs information on the zero-cross point detected by phase detection circuit **810** and information on the frequency of the AC voltage

detected by frequency detection circuit **811** as sine wave information.

(438) When the processing of **S203** is finished or when the zero-cross point is not detected in **S202** (NO in **S202**), fourth control circuit **409** controls second DC/AC converter **408** in **S204**. As in the first embodiment, fourth control circuit **409** controls second DC/AC converter **408** as a voltage source. Therefore, fourth control circuit **409** increases the output power of second DC/AC converter **408** when the power supplied to distribution system **24** is insufficient, and decreases the output power of second DC/AC converter **408** when the power supplied to distribution system **24** is excessive.

(439) Effective power calculation circuit **82** (FIG. **11**) calculates the effective power value on the basis of the measurement values of voltmeter **410** and ammeter **411**, and integrates the calculated effective power value. When the zero-cross point detection flag is set, effective power calculation circuit **82** stores the integral value of the effective power for one period of the AC voltage in the storage circuit in eighth control circuit **87**, and zero-initializes the integral value. After calculating the effective power, inverter voltage control circuit **85** generates the command value for controlling second DC/AC converter **408**.

(440) When the command value is generated in **S204**, fourth control circuit **409** performs the virtual synchronous generator control in **S205**. As in the first embodiment, one period of the AC voltage is set as a control period. When determining that the control timing has arrived, eighth control circuit **87** (FIG. **11**) instructs virtual synchronous generator control circuit **83** (FIG. **11**) to generate information on the frequency and the phase used for voltage control. In the second embodiment, as in the first embodiment, the frequency and the phase of the AC voltage generated by third sine wave generation circuit **851** (FIG. **13**) in inverter voltage control circuit **85** are updated at the zero-cross point.

(441) In the virtual synchronous generator control circuit (FIG. **14**), subtractor **832** calculates a deviation between the value of the frequency of the AC voltage actually measured by AC frequency detection circuit **81** (FIG. **11**) and the reference frequency F_{ref} output from eighth control circuit **87**, and outputs the calculated deviation to governor control circuit **833**.

(442) Governor control circuit **833** (FIG. **15**) causes multiplier **91** to multiply the deviation output from subtractor **832** by the control parameter $(-1/K_{gd})$ notified from eighth control circuit **87**, and outputs the result of the multiplication to first-order lag system model **92**. Note that, regarding the speed adjustment rate K_{gd} and the governor time constant T_g used by governor control circuit **833**, the speed adjustment rate K_{gd} and the governor time constant T_g generated by eighth control circuit **87** on the basis of the information notified from CEMS **31** and set in a register (not illustrated) are used.

(443) As described in the first embodiment, first-order lag system model **92** performs an operation to mimic the first-order lag system $(1/(1+s \times T_g))$ using the time constant T_g notified from eighth control circuit **87**, and outputs the result of the operation to limiter circuit **93**. Limiter circuit **93** puts a limit on the output power of second DC/AC converter **408** so as to prevent the output power from exceeding the power capacity of second DC/AC converter **408**.

(444) Adder **835** (FIG. **14**) adds up the output of governor control circuit **833** and the power target value P_{ref} output from eighth control circuit **87**. Note that the power target value P_{ref} is notified from CEMS **31**. Subtractor **836** calculates a deviation between the output of adder **835** and the value of the effective power actually measured by effective power calculation circuit **82** (FIG. **11**), and outputs the calculated deviation to point mass system operation circuit **837**.

(445) In point mass system operation circuit **837** (FIG. **16**), subtractor **101** calculates a deviation between the output of subtractor **836** (FIG. **14**) and the output of multiplier **103**, and outputs the calculated deviation to integrator **102**. Integrator **102** divides the output of subtractor **101** by the inertia constant M output from eighth control circuit **87** and integrates the result of the division. The output $\Delta\omega$ of integrator **102** (a difference value corresponding to a difference from the angular velocity of the frequency of the AC voltage) is input to multiplier **103** and divider **104**. Multiplier

103 multiplies the output $\Delta\omega$ of integrator **102** by damping factor D_g output from eighth control circuit **87**, and outputs the result of the multiplication to subtractor **101**. Divider **104** divides the output $\Delta\omega$ of integrator **102** by $2\times\pi$ to convert $\Delta\omega$ into Δf (a difference value corresponding to a difference from the frequency of the AC voltage). Adder **105** adds up the output of divider **104** and the reference frequency F_{ref} (60 Hz) of the AC voltage to generate a frequency used for voltage control in inverter voltage control circuit **85**. Note that, regarding the inertia constant M and the damping factor D_g used in point mass system operation circuit **837**, the inertia constant M and the damping factor D_g generated by eighth control circuit **87** using the information notified from CEMS **31** and set in a register (not illustrated) are used. The frequency information output from adder **105** is output to phase calculation circuit **106**. Phase calculation circuit **106** integrates the frequency information output from adder **105** to generate phase information used for voltage control in inverter voltage control circuit **85**.

(446) The phase information and the frequency information output from point mass system operation circuit **837** are input to third sine wave generation circuit **851** (FIG. **13**) in inverter voltage control circuit **85** via second sine wave generation circuit **812** (FIG. **12**) in AC frequency detection circuit **81**. Third sine wave generation circuit **851** generates the target value of the AC voltage output from power conversion device **41**.

(447) Referring back to FIG. **44**, when the virtual synchronous generator control is finished in **S205**, fourth control circuit **409** checks whether the transmission request of the measurement data has been received from CEMS **31** in **S206**. When the transmission request has been received from CEMS **31** (YES in **S206**), fourth control circuit **409** proceeds to **S207** and notifies CEMS **31** of the measurement data via communication I/F **412**.

(448) After the measurement data is transmitted in **S207** or when the transmission request from CEMS **31** has not been received (NO in **S206**), fourth control circuit **409** checks whether the control information has been received from CEMS **31** in **S208**. When the control information has been received (YES in **S208**), fourth control circuit **409** sets the reception flag of the control information. After the reception flag is set in **S209** or when the control information has not been received from CEMS **31** (NO in **S208**), fourth control circuit **409** checks whether the zero-cross point detection flag is set in **S210**. When the zero-cross point detection flag is not set (NO in **S210**), the processing returns to **S201**.

(449) On the other hand, when the zero-cross point detection flag is set (YES in **S210**), fourth control circuit **409** proceeds to **S211**, causes second sine wave generation circuit **812** to take the frequency and phase information of the AC voltage, and resets the zero-cross point detection flag in **S212**.

(450) After resetting the zero-cross point detection flag in **S212**, fourth control circuit **409** updates, in **S213**, the frequency and phase information of the AC voltage to the frequency and phase taken by second sine wave generation circuit **812** in **S211**.

(451) After updating the frequency and phase information of the AC voltage in **S213**, fourth control circuit **409** checks whether the control information has been received from CEMS **31** (whether the reception flag is set) in **S214**. When the reception flag is not set (NO in **S214**), the processing returns to **S201**. On the other hand, when the reception flag is set (YES in **S214**), fourth control circuit **409** replaces the frequency target value (reference frequency F_{ref}) and the power target value P_{ref} with the received data in **S215**.

(452) Upon receipt of information for generating the control parameter in **S216**, eighth control circuit **87** generates the control parameter of the virtual synchronous generator control. Specifically, the control parameter is generated on the basis of the slope of the $\Delta P/\Delta F$ characteristic generated by CEMS **31**, the system information (the reference frequency F_{ref} , the power target value P_{ref} , ΔF_{max} , and the like), and its own inverter capacity. In the second embodiment, eighth control circuit **87** stores the relationship between the damping factor D_g and the system frequency illustrated in FIG. **19** as table data for each of a plurality of speed adjustment rates K_{gd} . Eighth

control circuit **87** consults the table data on the basis of the information of $\Delta F_{\max}$ to retrieve a combination of the speed adjustment rate K_{gd} and the damping factor D_g that coincides with the slope of the $\Delta P/\Delta F$ characteristic.

(453) Note that the method for generating the control parameter of the virtual synchronous generator control implemented in power conversion device **41** is not limited to the above-described method. For example, as in the first embodiment, a method such as incorporating its own virtual synchronous generator control model or incorporating a mathematical expression representing the virtual synchronous generator control may be used.

(454) After generating the speed adjustment rate K_{gd} and the damping factor D_g , eighth control circuit **87** calculates the inertia constant M from the time constant information of the point mass system operation circuit. As described in the first embodiment, in the method for calculating the inertia constant M , the inertia constant M is calculated so as to make the time constant notified from CEMS **31** equal to (M/D_g) using the above-described expression (3).

(455) After generating the control parameter in **S220** of FIG. **44**, eighth control circuit **87** changes (updates) the control parameter in **S216**. After changing (updating) the control parameter, eighth control circuit **87** clears (resets) the register (not illustrated) in which the reception flag is set, and returns to **S201**.

(456) As described above, according to the second embodiment, in the configuration where the plurality of power conversion devices **41** each having the virtual synchronous generator control implemented are installed in distribution system **24**, even when the power consumed by load **600** or the power generated by mega solar **26** fluctuates, the plurality of power conversion devices **41** can share the excess and deficient power in accordance with the proportional division ratio of the operation plan (power target value) created by CEMS **31**.

(457) Further, in the second embodiment, since a part of the function implemented in CEMS **31** is implemented in power conversion device **41**, the processing load on CEMS **31** can be reduced. For example, in a case where the virtual synchronous generator control is implemented in a household storage battery installed by a general consumer, in the first embodiment, it is necessary for CEMS **31** to generate control parameters of the virtual synchronous generator control for hundreds to thousands of household storage batteries. On the other hand, according to the second embodiment, the processing load on the CEMS **31** can be reduced by implementing a part of the function of the virtual synchronous generator control in the household storage battery.

(458) Further, in a case where the virtual synchronous generator control circuits mounted on the plurality of power conversion devices **41** or household storage batteries are difference in configuration, it is required that, for the configuration where CEMS **31** generates the control parameter, CEMS **31** have a plurality of types of the virtual synchronous generator models illustrated in FIG. **5** or a plurality of types of the table data described in the second embodiment. Further, the number of control parameters to be generated may be different for each virtual synchronous generator control circuit. Even in such a case, the processing of CEMS **31** can be simplified with a configuration where each of power conversion devices **41** and household storage batteries generates the control parameter.

(459) Further, in the first and second embodiments, when creating the operation plan (power target value) for power conversion device **41**, the control parameter is generated on the basis of the capacity of the static inverter of each power conversion device **41** and the power target value, and it is therefore possible to share, even in a case where the power consumed by load **600** or the power generated by mega solar **26** fluctuates in a period until the next operation plan is notified from CEMS **31**, the excess and deficient power at the same proportional division ratio as the operation plan (power target value).

(460) As a result, for example, even when the solar radiation amount changes immediately after the notification of the operation plan, and the power generated by mega solar **26** decreases by 50%, the shortage of power corresponding to 50% is shared on the basis of the ratio of the power target value

calculated at the time of creating the operation plan. Therefore, for example, at the time of creating the operation plan, when the power target values of the plurality of storage batteries **40** are calculated so as to make the SOC become zero at almost the same time, the shortage of power corresponding to 50% is proportionally divided on the basis of the ratio of the power target value, so that the SOC can be controlled to become zero at almost the same time.

(461) In the first and second embodiments, the configuration where the virtual synchronous generator control is implemented in power conversion device **41** for storage battery **40** has been described, but the present disclosure is not limited to this configuration, and it goes without saying that a configuration where the virtual synchronous generator control is implemented in energy creation equipment such as a wind power generator produces the same effect. In particular, in the wind power generator, a generator has an inertial force to rotate a motor with a propeller, and it goes without saying that the same effect is produced.

(462) Further, in the first and second embodiments, the configuration where a plurality of large-capacity storage batteries such as storage battery **40** are installed in distribution system **24** has been described, but the virtual synchronous generator control may be implemented in a power conversion device of a household storage battery or a power conversion device for an electric vehicle, and control similar to the control performed by CEMS **31** may be performed. In this case, there may be hundreds of power conversion devices connected to distribution system **24**.

Furthermore, a configuration where a large-capacity (for example, several hundred kW to several MW as a storage battery capacity) storage battery such as storage battery **40** and a household storage battery (several kW) are installed can produce the same effect.

(463) Further, in the first and second embodiments, power conversion device **41** for storage battery **40** has been described, but the present invention is not limited to such a configuration, and a configuration where the virtual synchronous generator control is implemented in a power conversion device that controls a static inverter as a voltage source (for example, a solar cell (including a household solar cell) and a system that supplies power generated by a wind power generator and a fuel cell to distribution system **24** can also produce the same effect by using the above-described method to generate the control parameter of the virtual synchronous generator control.

(464) Furthermore, it is also possible to use a storage battery installed in a vehicle such as an electric vehicle (EV), a plug-in hybrid electric vehicle (PHEV), or a fuel cell vehicle (FCV).

(465) Note that, in the first and second embodiments, for the sake of simplicity of the description, the operation in a case of the single-phase AC or using power conversion device **41** having the inverter capacity of several kW in the description of FIGS. **21** to **31** has been described, but the present disclosure is not limited to such a configuration.

(466) Further, in the first and second embodiments, the configuration where the distributed power supply management device is applied to the distribution system has been described, but the present disclosure is not limited to such a configuration, and a configuration where the distributed power supply management device is applied to a transmission system or a stand-alone microgrid also produces the same effect.

(467) Furthermore, in the first and second embodiments, the three-phase AC has been given as an example, but a single-phase AC or a single-phase three-wire AC may be used. Furthermore, even a configuration where a power conversion device (three-phase AC) for a system storage battery and a household storage battery system (single-phase AC) both exist can also produce the same effect with a configuration where the control parameter of the virtual synchronous generator control is generated using the above-described method.

(468) Note that, in the first and second embodiments, the configuration where, when the control parameter of the virtual synchronous generator control is generated for the static inverter in power conversion device **41**, the control parameter is generated using the capacity of the static inverter and the power target value has been described, but the present disclosure is not limited to such a

configuration. In the first embodiment, a configuration where, when ratios of the capacity of the storage battery to the capacity of the static inverter are different from each other, for example, the capacity of storage battery **40a** is twice the capacity of the static inverter in power conversion device **41a**, and the capacity of storage battery **40b** is three times the capacity of the static inverter in power conversion device **41b**, the operation plan (power target value) is generated with the capacity ratios taken into account, or the ratios are taken into account when generating the control parameter can produce the same effect.

(469) In the second embodiment, the configuration where the system information and the slope information of the $\Delta P/\Delta F$ characteristic are transmitted in addition to the power target value so as to allow the control parameter to be generated in power conversion device **41**, but the information to be transmitted is not limited to such information, and a configuration where information that allows the control parameter to be generated in power conversion device **41** is transmitted from CEMS **31** can produce the same effect.

(470) In the first and second embodiments, the configuration where the virtual synchronous generator model (FIG. 5) is incorporated and the configuration where the relationship between the damping factor D_g and the system frequency (FIG. 19) is stored as table data with the relationship associated with each of the plurality of speed adjustment rates K_{gd} , a combination of the speed adjustment rate K_{gd} and the damping factor D_g that approximately coincides with the slope of the $\Delta P/\Delta F$ characteristic is retrieved on the basis of the ΔF_{max} information, or the relationship between the speed adjustment rate K_{gd} and the system frequency (FIG. 18) is stored as table data with the relationship associated with each of the plurality of damping factors D_g , and a combination of the speed adjustment rate K_{gd} and the damping factor D_g that approximately coincides with the slope of the $\Delta P/\Delta F$ characteristic is retrieved on the basis of the ΔF_{max} information have been described, but the present disclosure is not limited to such configurations. For example, it goes without saying that another method such as incorporating the virtual synchronous generator control circuit as a mathematical model may be employed.

(471) Furthermore, in the first and second embodiments, the configuration where the $\Delta P/\Delta F$ characteristic is calculated when the control parameter is generated has been described, but the present disclosure is not limited to such a configuration, and, for example, a configuration where a distribution system model (digital twin) of substation and below is implemented in CEMS **31**, and the control parameter is generated so as to allow optimal operation in an expected use case using the distribution system model may be employed. Furthermore, a configuration where AI is implemented in the above-described configuration and the control parameter is generated using the AI may be employed.

(472) Note that, in the first and second embodiments, the configuration where communications between CEMS **31** and DSO **21** are performed at intervals of 30 minutes, and communications between CEMS **31** and power conversion device **41** are performed at intervals of 5 minutes has been given above, but the present disclosure is not limited to such a configuration. For example, communications between CEMS **31** and power conversion device **41** may be performed at intervals of 1 minute.

(473) Further, in the first and second exemplary embodiments, the governor model in governor control circuit **833** (FIG. 14) is modeled as the first-order lag system, but the present disclosure is not limited to such a configuration, and a configuration where the governor model is built as a second-order lag system, a low pass filter (LPF), or the like may be employed.

(474) Furthermore, in the first and second embodiments, point mass system operation circuit **837** (FIG. 14) is modeled by the integrator and the feedback loop, but the present disclosure is not limited to such a configuration, and it goes without saying that the point mass system operation circuit may be modeled as, for example, a first-order lag system, a second-order lag system, or an LPF. Furthermore, in the first and second embodiments, for the sake of simplicity of the description, the VQ control widely used in the virtual synchronous generator control has not been

described above, but even a configuration where the present disclosure is applied to a power conversion device having the VQ control implemented as the virtual synchronous generator control can produce the same effect. Furthermore, the configuration of point mass system operation circuit **837** (FIG. **14**) is not limited to the circuit illustrated in FIG. **16**.

Description of Modification

(475) In the first and second embodiments, the case where the control circuits in power conversion device **27** and power conversion device **41** have the configurations illustrated in FIGS. **6** to **16**, and CEMS **31** has the hardware configuration illustrated in FIGS. **3** to **5** has been described for easy understanding of the description, but a similar control function can be implemented even with a configuration where a function of each block or some blocks is implemented by software running on a central processing unit (CPU). Alternatively, a similar control function can be implemented by function division of software and hardware of at least some blocks.

(476) Note that, for the above-described embodiments and modification, the configurations described in the embodiments are originally intended to form, with neither mismatch nor discrepancy, any desired combination including combinations not mentioned herein.

(477) It should be understood that the embodiments disclosed herein are illustrative in all respects and not restrictive. The scope of the present disclosure is defined by the claims rather than the above description, and the present disclosure is intended to include the claims, equivalents of the claims, and all modifications within the scope.

REFERENCE SIGNS LIST

(478) **11**: communication circuit, **12**: storage circuit, **13**: control parameter generation circuit, **14**: operation plan creation circuit, **15**: transmission data generation circuit, **16**: control circuit, **20**: substation, **21**: distribution automation system (DSO) **22**, **201**, **206**, **210**, **401**, **406**, **410**: voltmeter, **23**: step voltage regulator (SVR), **24**: distribution system, **25**: communication line, **26**: mega solar, **27**: mega solar power conversion device, **28**: switch, **29**: impedance, **30a**, **30b**: synchronous generator, **31**: CEMS, **40**, **40a** to **40c**: system storage battery, **41**, **41a** to **40c**: storage battery power conversion device, **51**: MPPT control circuit, **52**: voltage control circuit, **53**: first switching circuit, **54**: fifth control circuit, **61**: phase detection circuit, **62**: first sine wave generation circuit, **63**, **66**, **101**, **832**, **836**, **852**: subtractor, **64**: first PI control circuit, **65**, **91**, **103**: multiplier, **67**: sixth control circuit, **68**: second PI control circuit, **69**: first PWM converter, **71**: charge control circuit, **72**: discharge control circuit, **73**: second switching circuit, **74**: seventh control circuit, **81**: AC frequency detection circuit, **82**: effective power calculation circuit, **83**: virtual synchronous generator control circuit, **84**: inverter current control circuit, **85**: inverter voltage control circuit, **86**: third switching circuit, **87**: eighth control circuit, **92**: first-order lag system model, **93**: limiter circuit, **102**: integrator, **104**: divider, **105**, **835**: adder, **106**: phase calculation circuit, **100a** to **100d**: town, **110**: factory, **112**: building, **113**: condominium, **141**: storage battery operation plan creation circuit, **142**: power generation prediction circuit, **143**: power consumption prediction circuit, **144**: storage battery operation plan correction circuit, **135**, **145**, **146**: management circuit, **131**: reference $\Delta P/\Delta F$ characteristic calculation circuit, **132**: $\Delta P/\Delta F$ characteristic calculation circuit, **133**: control parameter generation circuit, **134**: virtual synchronous generator model, **136**: control circuit, **202**, **207**, **211**, **402**, **407**, **411**: ammeter, **203**: first DC/DC converter, **204**: first control circuit, **205**, **405**: DC bus, **208**: first DC/AC converter, **209**: second control circuit, **212**, **412**: communication I/F, **403**: second DC/DC converter, **404**: second control circuit, **408**: second DC/AC converter, **409**: fourth control circuit, **810**: phase detection circuit, **811**: frequency detection circuit, **812**: second sine wave generation circuit, **833**: governor control circuit, **837**: point mass system operation circuit, **851**: third sine wave generation circuit, **853**: third PI control circuit, **854**: second PWM converter, **600**: load

Claims

1. A distributed power supply management device that manages a plurality of distributed power supplies connected to a distribution system, each of the plurality of distributed power supplies including a static inverter in which virtual synchronous generator control is implemented, the distributed power supply management device comprising: a communication circuit to communicate with the plurality of distributed power supplies; an operation plan creation circuit to create a power target value of each of the plurality of distributed power supplies on a basis of information received by the communication circuit and capacities of the plurality of distributed power supplies; and a control parameter generation circuit to generate a control parameter for the virtual synchronous generator control in each of the distributed power supplies or information necessary for generating the control parameter, wherein the communication circuit is configured to receive measurement information of each of the distributed power supplies, and to transmit a control command to each of the distributed power supplies, and the control parameter generation circuit generates the control parameter or the information necessary for generating the control parameter on a basis of the information received by the communication circuit, the capacities of the plurality of distributed power supplies, and the power target value of each of the distributed power supplies, and outputs the control parameter generated or the information necessary for generating the control parameter as the control command to each of the distributed power supplies via the communication circuit.
2. The distributed power supply management device according to claim 1, wherein the control parameter generation circuit generates the control parameter on a basis of information indicating a capacity of the static inverter of each of the distributed power supplies and the power target value of each of the distributed power supplies generated by the operation plan creation circuit.
3. The distributed power supply management device according to claim 1, wherein the control parameter generation circuit generates the control parameter on a basis of the power target value of each of the distributed power supplies generated by the operation plan creation circuit and information for managing the distribution system.
4. The distributed power supply management device according to claim 1, wherein the control parameter generation circuit generates a reference $\Delta P/\Delta F$ characteristic indicating a relationship between (i) a difference frequency that is a deviation between a reference frequency and a system frequency and (ii) difference power that is a deviation between the power target value and output power of the static inverter when half of a capacity of the static inverter is set as the power target value, and generates a $\Delta P/\Delta F$ characteristic of each of the distributed power supplies using a ratio between the power target value generated by the operation plan creation circuit and the half of the capacity of the static inverter on a basis of the reference $\Delta P/\Delta F$ characteristic generated.
5. The distributed power supply management device according to claim 4, wherein the control parameter generation circuit calculates a slope of the $\Delta P/\Delta F$ characteristic of each of the distributed power supplies on a basis of (i) a slope of the reference $\Delta P/\Delta F$ characteristic and (ii) the ratio between the power target value generated by the operation plan creation circuit and the half of the capacity of the static inverter.
6. The distributed power supply management device according to claim 5, wherein the control parameter generation circuit calculates a maximum value of the difference frequency corresponding to a maximum value of the difference power for the $\Delta P/\Delta F$ characteristic of each of the distributed power supplies, and generates the control parameter on a basis of the maximum value of the difference frequency.
7. The distributed power supply management device according to claim 4, wherein the communication circuit notifies each of the distributed power supplies of (i) the power target value generated by the operation plan creation circuit and (ii) information indicating the $\Delta P/\Delta F$ characteristic of each of the distributed power supplies generated by the control parameter generation circuit or information being used when the $\Delta P/\Delta F$ characteristic is generated.
8. The distributed power supply management device according to claim 1, wherein each of the

distributed power supplies includes a control circuit to perform the virtual synchronous generator control, the control circuit includes a governor control circuit to mimic a governor function of a synchronous generator and a point mass system operation circuit to mimic a swing equation of the synchronous generator, and the control parameter generation circuit generates, as the control parameter, at least one of a gain of the governor control circuit or a damping factor of the point mass system operation circuit.

9. The distributed power supply management device according to claim 8, wherein the communication circuit notifies each of the distributed power supplies of (i) at least one of the gain of the governor control circuit or the damping factor of the point mass system operation circuit, and (ii) the power target value generated by the operation plan creation circuit.
