

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12387871
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Wongsasulux; Jakrapong et al.

Leakage transformer

Abstract

A leakage transformer is provided. The leakage transformer includes a first plate, a second plate, a plurality of winding pillars, a primary winding, a secondary winding and a plurality of magnetic shunt elements. Each magnetic shunt element is disposed between the two corresponding winding pillars, and there is a gap between every two neighboring magnetic shunt elements. Alternatively, the magnetic shunt element is disposed on the first plate and aligned with the corresponding winding pillar, and there is a gap between the magnetic shunt element and the second plate. A leakage inductance of the leakage transformer is determined by the gap.

Inventors: Wongsasulux; Jakrapong (Samutprakarn, TH), Suraprechakul; Chaiwichit (Samutprakarn, TH)

Applicant: Delta Electronics (Thailand) Public Company Limited (Samutprakarn, TH)

Family ID: 69960398

Assignee: Delta Electronics (Thailand) Public Company Limited (Samutprakarn, TH)

Appl. No.: 18/222279

Filed: July 14, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230360849 A1	Nov. 09, 2023

Related U.S. Application Data

division parent-doc US 16814245 20200310 PENDING child-doc US 18222279

Publication Classification

Int. Cl.: H01F27/34 (20060101); H01F3/12 (20060101); H01F27/28 (20060101); H01F38/08 (20060101)

U.S. Cl.:

CPC H01F27/34 (20130101); H01F27/28 (20130101); H01F38/08 (20130101);

Field of Classification Search

CPC: H01F (27/34); H01F (27/28); H01F (38/08); H01F (3/10); H01F (3/12); H01F (27/306); H01F (27/24); Y02B (70/10)

USPC: 336/178; 336/220-223; 336/133; 336/155-165

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2145703	12/1938	Wirz	336/160	H01F 38/08
2578395	12/1950	Brooks	315/231	H01F 38/10
5726615	12/1997	Bloom	N/A	N/A
7116204	12/2005	Fushimi	N/A	N/A
2005/0068149	12/2004	Fushimi	N/A	N/A
2005/0088113	12/2004	Ushijima et al.	N/A	N/A
2005/0286270	12/2004	Petkov et al.	N/A	N/A
2008/0088403	12/2007	Suzuki	336/198	H05B 41/2822
2010/0019875	12/2009	Ger	336/220	H01F 3/10
2014/0286054	12/2013	Krause	N/A	N/A
2017/0324343	12/2016	Ishigaki et al.	N/A	N/A
2017/0330678	12/2016	Harrison	N/A	H01F 3/10

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2859766	12/2006	CN	N/A
101006533	12/2006	CN	N/A
201247685	12/2008	CN	N/A
201319301	12/2008	CN	N/A
101840769	12/2009	CN	N/A
202275691	12/2011	CN	N/A
203103100	12/2012	CN	N/A
203941798	12/2013	CN	N/A
104952591	12/2014	CN	N/A
108880280	12/2017	CN	N/A
109787484	12/2018	CN	N/A
1078557	12/2000	EP	N/A
H05299271	12/1992	JP	N/A
H06267772	12/1993	JP	N/A
H09120910	12/1996	JP	N/A
2005108933	12/2004	JP	N/A
2016185632	12/2015	WO	N/A

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a Divisional Application of U.S. patent application Ser. No. 16/814,245 filed on Mar. 10, 2020 and entitled “LEAKAGE TRANSFORMER”, the entirety of which is hereby incorporated by reference.

FIELD OF THE INVENTION

(1) The present disclosure relates to a leakage transformer, and more particularly to have a leakage inductance provided by introducing the magnetic shunt elements.

BACKGROUND OF THE INVENTION

(2) The resonant converter becomes more and more popular in power electronics industry. In order to achieve higher power density, the inductor and the transformer are combined together. Generally, the leakage inductance of transformer is created by making a loose coupling between the primary and secondary windings. However, it requires large distance for achieving high leakage inductance, which deteriorates the power density.

(3) Therefore, there is a need of providing a leakage transformer to obviate the drawbacks encountered from the prior arts.

SUMMARY OF THE INVENTION

(4) It is an objective of the present disclosure to provide a high leakage transformer. The leakage inductance of the high leakage transformer is determined by a gap defined by the magnetic shunt elements rather than the gap between the winding pillars. Therefore, both the high power density and the high leakage inductance are taken into consideration. In addition, the winding of the leakage transformer are split into a plurality of parts wound around the winding pillars respectively, which can significantly reduce the proximity loss on windings.

(5) In accordance with an aspect of the present disclosure, there is provided a leakage transformer. The leakage transformer includes a first plate, a second plate, a plurality of first winding pillars, a plurality of second winding pillars, a primary winding, a secondary winding and a plurality of magnetic shunt elements. The plurality of first winding pillars is disposed on the first plate. The plurality of second winding pillars is disposed on the second plate and aligned with the plurality of first winding pillars respectively. The primary winding is wound around the plurality of first winding pillars. The secondary winding is wound around the plurality of second winding pillars. Each magnetic shunt element is disposed between the first winding pillar and the corresponding second winding pillar. There is a gap between every two neighboring magnetic shunt elements, and a leakage inductance of the leakage transformer is determined by the at least one gap.

(6) In accordance with another aspect of the present disclosure, there is provided a leakage transformer. The leakage transformer includes a first plate, a second plate, a plurality of winding pillars, a primary winding, a secondary winding and a plurality of magnetic shunt element. The plurality of winding pillars is disposed on the first plate. The primary winding and the secondary winding are wound around the plurality of winding pillars. The plurality of magnetic shunt elements is disposed on the first plate and aligned with the plurality of winding pillars respectively. There is a gap between the magnetic shunt element and the second plate, and a leakage inductance of the leakage transformer is determined by the gaps.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic exploded view illustrating a leakage transformer according to a first embodiment of the present disclosure;
- (2) FIG. 2 is a schematic cross-sectional view illustrating the leakage transformer according to the first embodiment of the present disclosure;
- (3) FIG. 3 is a schematic circuit diagram illustrating an equivalent circuit of the leakage transformer according to the first embodiment of the present disclosure;
- (4) FIG. 4 is a schematic exploded view illustrating a leakage transformer according to a second embodiment of the present disclosure;
- (5) FIG. 5 is a schematic cross-sectional view illustrating the leakage transformer according to the second embodiment of the present disclosure; and
- (6) FIG. 6 is a schematic circuit diagram illustrating an equivalent circuit of the leakage transformer according to the second embodiment of the present disclosure.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

- (7) The present disclosure will now be described more specifically with reference to the following embodiments. It is to be noted that the following descriptions of preferred embodiments of this disclosure are presented herein for purpose of illustration and description only. It is not intended to be exhaustive or to be limited to the precise form disclosed.
- (8) FIG. 1 is a schematic exploded view illustrating a leakage transformer according to a first embodiment of the present disclosure, and FIG. 2 is a schematic cross-sectional view illustrating the leakage transformer according to the first embodiment of the present disclosure. As shown in FIG. 1 and FIG. 2, the leakage transformer 1 includes a first plate 11, a second plate 12, a plurality of first winding pillars 13, a plurality of second winding pillars 14, a primary winding 15, a secondary winding 16 and a plurality of magnetic shunt elements 17. In an embodiment, the leakage transformer 1 further includes two side pillars 19 between the first plate 11 and the second plate 12.
- (9) The plurality of first winding pillars 13 is disposed on the first plate 11, and the first winding pillars 13 are arranged with a specific interval. The plurality of second winding pillars 14 is disposed on the second plate 12, and the second winding pillars 14 are arranged with a specific interval. The second winding pillars 14 are aligned with the first winding pillars 13 respectively. Namely, the number of the first winding pillars 13 and the number of the second winding pillars 14 are the same, and the first winding pillars 13 are corresponding to the second winding pillars 14 one-to-one. In an embodiment, the number of the plurality of first winding pillars 13 is even, and the number of the plurality of second winding pillars 14 is even as well.
- (10) The primary winding 15 is wound around the plurality of first winding pillars 13. In an embodiment, the primary winding 15 is split into a plurality of parts wound around the plurality of first winding pillars 13 respectively. The plurality of parts of the primary winding 15 may be connected in series or in parallel. The secondary winding 16 is wound around the plurality of second winding pillars 14. In an embodiment, the secondary winding 16 is split into a plurality of parts wound around the plurality of second winding pillars 14 respectively. The plurality of parts of the secondary winding 16 may be connected in series or in parallel. In addition, the primary winding 15 and the secondary winding 16 are for example but not limited to coil or PCB (printed circuit board) trace.
- (11) Each of the plurality of magnetic shunt elements 17 is disposed between the corresponding first winding pillar 13 and second winding pillar 14. There is a gap 18 between every two neighboring magnetic shunt elements 17, and a leakage inductance of the leakage transformer 1 is determined by the at least one gap 18. In other words, the leakage inductance of the leakage transformer 1 is adjusted by varying the at least one gap 18. In an embodiment, the magnetic shunt element 17 is directly connected with the corresponding first winding pillar 13 and second winding

pillar **14**. In another embodiment, even there is a distance between the magnetic shunt element **17** and the corresponding first winding pillar **13** or second winding pillar **14**, the distance therebetween is not large enough to affect the leakage inductance of the leakage transformer **1**.

(12) Consequently, the leakage inductance of the leakage transformer **1** is determined by a gap **18** defined by the magnetic shunt elements **17** rather than the gap between the winding pillars. Namely, the gap **18** is able to provide high leakage inductance without keeping large distance between the primary winding **15** and the secondary winding **16**, which improves the power density. Therefore, both the high power density and the high leakage inductance are taken into consideration. In addition, the winding of the leakage transformer **1** are split into a plurality of parts wound around the winding pillars respectively, which can significantly reduce the proximity loss on windings. Moreover, since the primary winding **15** and secondary winding **16** are wound around different winding pillars, the capacitive coupling is low, which can reduce the common mode noise.

(13) In the embodiment shown in FIG. **1** and FIG. **2**, the leakage transformer **1** includes two first winding pillars **13**, two second winding pillars **14**, two magnetic shunt elements **17**, and one gap **18** between the two neighboring magnetic shunt elements **17**. Meanwhile, the equivalent circuit of the leakage transformer **1** in this embodiment is shown in FIG. **3**, where R_{top} is the reluctance of the first plate **11**, R_{bot} is the reluctance of the second plate **12**, R_{sh} is the reluctance of the side pillar **19**, R_m is the reluctance of the winding pillars, R_{shunt} is the sum of the reluctance of the gap **18** and the reluctance of the two magnetic shunt elements **17**, MMF_p is the primary magnetomotive force, MMF_{sec} is the secondary magnetomotive force. MMF_p is the result of multiplying the number of turns of the primary winding **15** by the primary current, and MMF_{sec} is the result of multiplying the number of turns of the secondary winding **16** by the secondary current. The reluctance value of the magnetic shunt element **17** is much smaller than the reluctance value of the gap **18**.

(14) FIG. **4** is a schematic exploded view illustrating a leakage transformer according to a second embodiment of the present disclosure, and FIG. **5** is a schematic cross-sectional view illustrating the leakage transformer according to the second embodiment of the present disclosure. As shown in FIG. **4** and FIG. **5**, the leakage transformer **2** includes a first plate **21**, a second plate **22**, a plurality of winding pillars **23**, a primary winding **24**, a secondary winding **25** and a plurality of magnetic shunt elements **26**. In an embodiment, the leakage transformer further includes two side pillars **28** between the first plate **21** and the second plate **22**.

(15) The plurality of winding pillars **23** is disposed on the first plate **21**, and the winding pillars **23** are arranged with a specific interval. In an embodiment, the number of the plurality of winding pillars **23** is even. In an embodiment, the plurality of winding pillars **23** is directly connected with the second plate **22**. In another embodiment, even there is a distance between the winding pillar **23** and the second plate **22**, the distance therebetween is not large enough to affect the leakage inductance of the leakage transformer **2**.

(16) The primary winding **24** and the secondary winding **25** are wound around the plurality of winding pillars **23**. In particular, the primary winding **24** is wound around the winding pillars **23** and the magnetic shunt element **26**, and the secondary winding **25** is wound around the winding pillars **23** only. In an embodiment, the primary winding **24** is split into a plurality of parts wound around the plurality of winding pillars **23** respectively. The plurality of parts of the primary winding **24** may be connected in series or in parallel. In an embodiment, the secondary winding **25** is split into a plurality of parts wound around the plurality of winding pillars **23** respectively. The plurality of parts of the secondary winding **25** may be connected in series or in parallel. In addition, the primary winding **24** and the secondary winding **25** are for example but not limited to coil or PCB (printed circuit board) trace.

(17) The magnetic shunt elements **26** are aligned with the winding pillars **23** respectively. Namely, the number of the magnetic shunt elements **26** and the number of the winding pillars **23** are the same, and the magnetic shunt elements **26** are corresponding to the winding pillars **23** one-to-one.

There is a gap 27 between the magnetic shunt element 26 and the second plate 22, and a leakage inductance of the leakage transformer 2 is determined by the gaps 27. In other words, the leakage inductance of the leakage transformer 2 is adjusted by varying the gaps 27. In addition, the gap between the winding pillar 23 and the second plate 22 is mandatory for disposing the magnetizing inductance (L_m).

(18) Consequently, the leakage inductance of the leakage transformer 2 is determined by a gap 27 defined by the magnetic shunt elements 26 rather than the gap between the winding pillars 23. Therefore, both the high power density and the high leakage inductance are taken into consideration. In addition, the winding of the leakage transformer 2 are split into a plurality of parts wound around the winding pillars 23 respectively, which can significantly reduce the proximity loss on windings.

(19) In the embodiment shown in FIG. 4 and FIG. 5, the leakage transformer 2 includes two winding pillars 23, two magnetic shunt elements 26, and two gaps 27 between the magnetic shunt element 26 and the second plate 22. Meanwhile, the equivalent circuit of the leakage transformer 2 in this embodiment is shown in FIG. 6, where R_{top} is the reluctance of the second plate 22, R_{bot} is the reluctance of the first plate 21, R_{sh} is the reluctance of the side pillar 28, R_m is the sum of the reluctance of gap between the winding pillar 23 and the second plate 22 and the reluctance of the winding pillars 23, R_{shunt} is the sum of the reluctance of the gap 27 and the reluctance of the two magnetic shunt elements 26, MMF_p is the primary magnetomotive force, MMF_{sec} is the secondary magnetomotive force. MMF_p is the result of multiplying the number of turns of the primary winding 24 by the primary current, and MMF_{sec} is the result of multiplying the number of turns of the secondary winding 25 by the secondary current.

(20) From the above descriptions, the present disclosure provides a leakage transformer. The leakage inductance of the leakage transformer is determined by a gap defined by the magnetic shunt elements rather than the distance between the primary and secondary windings and the gap between the winding pillar and the second plate. Therefore, both the high power density and the high leakage inductance are taken into consideration. In addition, the winding of the leakage transformer are split into a plurality of parts wound around the winding pillars respectively, which can significantly reduce the proximity loss on windings.

(21) While the disclosure has been described in terms of what is presently considered to be the most practical and preferred embodiments, it is to be understood that the disclosure needs not be limited to the disclosed embodiment.

Claims

1. A leakage transformer, comprising: a first plate and a second plate; a plurality of first winding pillars interiorly disposed on the first plate; a plurality of second winding pillars interiorly disposed on the second plate and aligned with the plurality of first winding pillars respectively; a primary winding wound around the plurality of first winding pillars; a secondary winding wound around the plurality of second winding pillars; a plurality of magnetic shunt elements, wherein each magnetic shunt element is disposed between a corresponding pair of the first winding pillar and the second winding pillar, there is a gap between every two neighboring magnetic shunt elements, and a leakage inductance of the leakage transformer is determined by the at least one gap; and two side pillars, wherein each of the two side pillars is disposed directly between the first plate and the second plate, and wherein each magnetic shunt element is interiorly disposed between the two side pillars, wherein the primary winding is split into a plurality of parts wound around the plurality of first winding pillars respectively, and the plurality of parts of the primary winding are connected in series or in parallel; the secondary winding is split into a plurality of parts wound around the plurality of second winding pillars respectively, and the plurality of parts of the secondary winding are connected in series or in parallel.

2. The leakage transformer according to claim 1, wherein the leakage inductance of the leakage transformer is adjusted by varying the at least one gap.
 3. The leakage transformer according to claim 1, wherein the number of the plurality of first winding pillars is even, and the number of the plurality of second winding pillars is even.
 4. The leakage transformer according to claim 1, wherein the magnetic shunt element is directly connected with the corresponding first and second winding pillars.
-