

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent
Kind Code
Date of Patent
Inventor(s)

12389036
B2
August 12, 2025
Han; Jingning et al.

Efficient context model computation design in transform coefficient coding

Abstract

An encoded bitstream is decodable by a processor configured to execute instructions to store, in a first line buffer, first values of a first scan-order diagonal line scanned immediately before a current scan-order diagonal line of a transform block; and store, in a second line buffer, second values of a second scan-order diagonal line scanned immediately before the first scan-order diagonal line. The first values of the first line buffer and the second values of the second line buffer are interleaved in a destination buffer. Using the destination buffer, a probability distribution is selected for coding a current value of the current scan-order diagonal line. The current value is entropy decoded from the bitstream using the probability distribution. One of the second line buffer or the first line buffer is replaced with current values of the current scan-order diagonal line for coding values of an immediately subsequent scan-order diagonal line.

Inventors: Han; Jingning (Santa Clara, CA), Zern; James (San Francisco, CA), Zhang; Linfeng (Palo Alto, CA), Chiang; Ching-Han (San Jose, CA), Xu; Yaowu (Saratoga, CA)

Applicant: GOOGLE LLC (Mountain View, CA)

Family ID: 69885644

Assignee: GOOGLE LLC (Mountain View, CA)

Appl. No.: 18/641482

Filed: April 22, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240276015 A1	Aug. 15, 2024

Related U.S. Application Data

continuation parent-doc US 17866707 20220718 US 11991392 child-doc US 18641482
continuation parent-doc US 17106898 20201130 US 11405646 20220802 child-doc US 17866707
continuation parent-doc US 16693438 20191125 US 10869060 20201215 child-doc US 17106898
continuation-in-part parent-doc US 15883323 20180130 US 10506242 20191210 child-doc US
16693438

Publication Classification

Int. Cl.: **H04N19/88** (20140101); **H04N19/129** (20140101); **H04N19/13** (20140101);
H04N19/184 (20140101); **H04N19/60** (20140101)

U.S. Cl.:

CPC **H04N19/60** (20141101); **H04N19/129** (20141101); **H04N19/13** (20141101);
H04N19/184 (20141101); **H04N19/88** (20141101);

Field of Classification Search

CPC: H04N (19/60); H04N (19/129)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7054493	12/2005	Schwartz	375/E7.064	H04N 19/176
7941433	12/2010	Benson	707/748	G06F 16/283
8692695	12/2013	Fallon	341/51	G06Q 40/04
8742958	12/2013	Fallon	341/51	G06Q 40/04
9106913	12/2014	Sole Rojals	N/A	H04N 19/18
9264706	12/2015	Karczewicz	N/A	H04N 19/103
9294769	12/2015	Jeon	N/A	H04N 19/91
9338449	12/2015	Sole Rojals	N/A	H04N 19/436
9497472	12/2015	Coban	N/A	H04N 19/102
9538175	12/2016	Karczewicz	N/A	H04N 19/463
9544584	12/2016	Lim	N/A	H04N 19/176
9544597	12/2016	Han	N/A	H04N 19/625
9571860	12/2016	Sze	N/A	H04N 19/61
9596464	12/2016	Song	N/A	H04N 19/436
9661338	12/2016	Karczewicz	N/A	H04N 19/176
9693054	12/2016	Jeon	N/A	H04N 19/182
9800870	12/2016	Guo	N/A	H04N 19/159
10440369	12/2018	Young	N/A	H04N 19/176
10484695	12/2018	Young	N/A	H04N 19/184
10645381	12/2019	Joshi	N/A	H04N 19/70
10893280	12/2020	Young	N/A	H04N 19/93
11178409	12/2020	Young	N/A	H04N 19/60
11477462	12/2021	Young	N/A	H04N 19/124
2011/0188572	12/2010	Min	375/E7.243	H04N 19/593

2012/0082218	12/2011	Misra	375/E7.243	H04N 19/86
2012/0195377	12/2011	Auyeung	375/E7.243	H04N 19/176
2012/0230417	12/2011	Sole Rojals	375/240.18	H04N 19/176
2013/0188699	12/2012	Joshi	375/240.12	H04N 19/42
2013/0230097	12/2012	Sole Rojals	375/240.02	H04N 19/18
2013/0315300	12/2012	Lee	375/240.02	H04N 19/70
2013/0329784	12/2012	Chuang	375/240.02	H04N 19/176
2013/0329786	12/2012	Thoreau	375/240.12	H04N 19/176
2014/0119439	12/2013	Guo	375/240.12	H04N 19/70
2015/0110173	12/2014	Bultje	375/240.18	H04N 19/40
2015/0110409	12/2014	Bultje	382/239	H04N 19/13
2015/0215646	12/2014	Piao	375/240.18	H04N 19/176
2015/0358621	12/2014	He	375/240.02	H04N 19/91
2015/0370787	12/2014	Akbacak	704/2	G06F 40/47
2016/0191917	12/2015	Fu	375/240.07	H04N 19/13
2016/0373741	12/2015	Zhao	N/A	H04N 19/70
2017/0223378	12/2016	Tao	N/A	H04N 19/56
2017/0310998	12/2016	Zhao	N/A	H04N 19/182
2017/0318311	12/2016	Said	N/A	H04N 19/14
2018/0063547	12/2017	Kobayashi	N/A	G06T 7/223
2018/0199054	12/2017	Hsu	N/A	H04N 19/176
2018/0199062	12/2017	Zhang	N/A	H04N 19/59
2021/0365811	12/2020	Xu	N/A	G06N 5/02
2022/0343555	12/2021	Zhang	N/A	G06T 7/10

OTHER PUBLICATIONS

Bankoski et al., “VP8 Data Format and Decoding Guide”, Independent Submission RFC 6389, Nov. 2011, 305 pp. cited by applicant

Bankoski et al., “VP8 Data Format and Decoding Guide draft-bankoski-vp8-bitstream-02”, Network Working Group, Internet-Draft, May 18, 2011, 288 pp. cited by applicant

“Introduction to Video Coding Part 1: Transform Coding”, Mozilla, Mar. 2012, 171 pp. cited by applicant

“Overview VP7 Data Format and Decoder”, Version 1.5, On2 Technologies, Inc., Mar. 28, 2005, 65 pp. cited by applicant

Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Amendment 2: New profiles for professional applications, International Telecommunication Union, Apr. 2007, 75 pp. cited by applicant

Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, Amendment 1: Support of additional colour spaces and removal of the High 4:4:4 Profile, International Telecommunication Union, Jun. 2006, 16 pp. cited by applicant

Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, Version 3, International Telecommunication Union, Mar. 2005, 343 pp. cited by applicant

Bankoski, et al., “Technical Overview of VP8, An Open Source Video Codec for the Web”, Jul. 11, 2011, 6 pp. cited by applicant

Series H: Audiovisual and Multimedia Systems, Coding of moving video: Implementors Guide for H.264: Advanced video coding for generic audiovisual services, International Telecommunication Union, Jul. 30, 2010, 15 pp. cited by applicant

Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of

moving video, Advanced video coding for generic audiovisual services, International Telecommunication Union, Version 11, Mar. 2009, 670 pp. cited by applicant
Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, International Telecommunication Union, Version 12, Mar. 2010, 676 pp. cited by applicant
Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, Version 8, International Telecommunication Union, Nov. 1, 2007, 564 pp. cited by applicant
Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, Version 1, International Telecommunication Union, May 2003, 282 pp. cited by applicant
“VP8 Data Format and Decoding Guide, WebM Project”, Google On2, Dec. 1, 2010, 103 pp. cited by applicant
“VP6 Bitstream and Decoder Specification”, Version 1.02, On2 Technologies, Inc., Aug. 17, 2006, 88 pp. cited by applicant
“VP6 Bitstream and Decoder Specification”, Version 1.03, On2 Technologies, Inc., Oct. 29, 2007, 95 pp. cited by applicant
Vivienne Sze et al. “Chapter 8: Entropy Coding in HEVC”, High Efficiency Video Coding (HEVC), Springer International Publishing, Jan. 1, 2014, pp. 209-269. cited by applicant
T. Nguyen et al., “Non-CE11: Proposed Cleanup for Transform Coefficient Coding”, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11, 8th Meeting, San Jose, CA, Feb. 1-10, 2012, <http://wftp3.itu.int/av-arch/jctvc-site/>, Document No. JCTVC-H0228 (Jan. 20, 2012), 6 pgs. cited by applicant
International Search Report and Written Opinion in PCT/US2019/015930, mailed Apr. 30, 2019, 17 pgs. cited by applicant
Joel Sole et al, “Transform Coefficient Coding in HEVC”; IEEE Transactions on Circuits and Systems for Video Technology, Institute of Electrical and Electronics Engineers, vol. 22, No. 12, Dec. 1, 2012, pp. 1765-1777. cited by applicant

Primary Examiner: Habib; Irfan

Attorney, Agent or Firm: Young Basile Hanlon & MacFarlane, P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application is a continuation of U.S. application patent Ser. No. 17/866,707, filed, Jul. 18, 2022, which is a continuation of U.S. application patent Ser. No. 17/106,898, filed, Nov. 30, 2020, which is a continuation of U.S. application patent Ser. No. 16/693,438, filed Nov. 25, 2019, which is a continuation in part of U.S. application patent Ser. No. 15/883,323, filed Jan. 30, 2018, the entire disclosures of which are hereby incorporated by reference.

BACKGROUND

(1) Digital video streams may represent video using a sequence of frames or still images. Digital video can be used for various applications including, for example, video conferencing, high definition video entertainment, video advertisements, or sharing of user-generated videos. A digital video stream can contain a large amount of data and consume a significant amount of computing or communication resources of a computing device for processing, transmission, or storage of the video data. Various approaches have been proposed to reduce the amount of data in video streams,

including compression and other encoding techniques.

SUMMARY

(2) A first aspect is a non-transitory computer-readable storage medium having stored thereon an encoded bitstream decodable by a processor configured to execute instructions to store, in a first line buffer, first values of a first scan-order diagonal line scanned immediately before a current scan-order diagonal line of a transform block; store, in a second line buffer, second values of a second scan-order diagonal line scanned immediately before the first scan-order diagonal line; interleave the first values of the first line buffer and the second values of the second line buffer in a destination buffer; select, using the destination buffer, a probability distribution for coding a current value of the current scan-order diagonal line; entropy decode, from the encoded bitstream, the current value using the probability distribution; and replace, for coding values of an immediately subsequent scan-order diagonal line to the current scan-order diagonal line, one of the second line buffer or the first line buffer with current values of the current scan-order diagonal line.

(3) A second aspect is non-transitory computer-readable storage medium having stored thereon an encoded bitstream decodable by a processor configured to perform instructions to select a template for entropy-decoding values related to transform coefficients of a transform block, the template indicating, for a to-be-decoded value, scan positions of decoded values, the scan positions arranged, in the template, in at least two template anti-diagonal lines; decode the values related to the transform coefficients based on a scan order, the scan order traversing the values along scan-order anti-diagonal lines; maintain, for coding first values of the values related to the transform coefficients, a first line buffer and a second line buffer, where the first values are arranged along a current scan-order anti-diagonal line, where the first line buffer corresponds to a first scan-order anti-diagonal line scanned, based on the scan order, immediately before the current scan-order anti-diagonal line, and where the second line buffer corresponds to a second scan-order anti-diagonal line scanned, based on the scan order, immediately before the first scan-order anti-diagonal line; for a current value of the current scan-order anti-diagonal line, determine a context using the first line buffer and the second line buffer, and entropy decode, from the encoded bitstream, the current value using the context; and replace, for coding values of an immediately subsequent scan-order anti-diagonal line to the current scan-order anti-diagonal line, one of the second line buffer or the first line buffer with the current scan-order anti-diagonal line.

(4) A third aspect is a non-transitory computer-readable storage medium having stored thereon an encoded bitstream generated by a processor configured to execute instructions to select a scan order for traversing, along scan-order anti-diagonal lines, a block of values related to transform coefficients of a transform block; select a template for entropy-coding the values related to the transform coefficients, the template indicating, for a to-be-coded value, scan positions of already coded values, the scan positions arranged, in the template, in at least two template anti-diagonal lines; maintain, for coding first values of the values related to the transform coefficients, where the first values are arranged along a current scan-order anti-diagonal line, a first line buffer and a second line buffer, where the first line buffer corresponds to a first scan-order anti-diagonal line scanned, using the scan order, immediately before the current scan-order anti-diagonal line, and where the second line buffer corresponds to a second scan-order anti-diagonal line scanned, using the scan order, immediately before the first scan-order anti-diagonal line; for a current value of the current scan-order anti-diagonal line, determine a context using the first line buffer and the second line buffer, and entropy encode, in the encoded bitstream, the current value using the context; replace, for coding values of an immediately subsequent scan-order anti-diagonal line to the current scan-order anti-diagonal line, one of the second line buffer or the first line buffer with the current scan-order anti-diagonal line.

(5) These and other aspects of the present disclosure are disclosed in the following detailed description of the embodiments, the appended claims and the accompanying figures.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The description herein makes reference to the accompanying drawings wherein like reference numerals refer to like parts throughout the several views.
- (2) FIG. 1 is a schematic of a video encoding and decoding system.
- (3) FIG. 2 is a block diagram of an example of a computing device that can implement a transmitting station or a receiving station.
- (4) FIG. 3 is a diagram of a video stream to be encoded and subsequently decoded.
- (5) FIG. 4 is a block diagram of an encoder according to implementations of this disclosure.
- (6) FIG. 5 is a block diagram of a decoder according to implementations of this disclosure.
- (7) FIG. 6 is a flowchart diagram of a process for encoding a transform block in an encoded video bitstream using level maps according to an implementation of this disclosure.
- (8) FIG. 7 is a diagram illustrating the stages of transform coefficient coding using level maps in accordance with implementations of this disclosure.
- (9) FIG. 8 is a diagram of previously coded neighbors in a non-zero map according to an implementation of this disclosure.
- (10) FIG. 9 is a flowchart diagram of a process for coding a transform block using level maps according to an implementation of this disclosure.
- (11) FIGS. 10A-B is a diagram of examples of templates for determining a coding context according to implementations of this disclosure.
- (12) FIG. 11 is a flowchart diagram of a process for coding a transform block using level maps according to an implementation of this disclosure.
- (13) FIG. 12 is an example of an illustration of using a template to determine a context according to implementations of this disclosure.
- (14) FIG. 13 is a diagram of an example of a scan order that aligns value along anti-diagonal lines according to the implementations of this disclosure.
- (15) FIG. 14 is flowchart diagram of a process for cache management for context selection according to implementations of this disclosure.
- (16) FIG. 15 is flowchart diagram of a process for using a moving window for context selection according to implementations of this disclosure.
- (17) FIG. 16 is flowchart diagram of a process for coding a transform block of transform coefficients according to an implementation of this disclosure.

DETAILED DESCRIPTION

- (18) As mentioned above, compression schemes related to coding video streams may include breaking images into blocks and generating a digital video output bitstream (i.e., an encoded bitstream) using one or more techniques to limit the information included in the output bitstream. A received bitstream can be decoded to re-create the blocks and the source images from the limited information. Encoding a video stream, or a portion thereof, such as a frame or a block, can include using temporal or spatial similarities in the video stream to improve coding efficiency. For example, a current block of a video stream may be encoded based on identifying a difference (residual) between the previously coded pixel values, or between a combination of previously coded pixel values, and those in the current block.
- (19) Encoding using spatial similarities can be known as intra prediction. Intra prediction attempts to predict the pixel values of a block of a frame of video using pixels peripheral to the block; that is, using pixels that are in the same frame as the block but that are outside the block. A prediction block resulting from intra prediction is referred to herein as an intra predictor. Intra prediction can be performed along a direction of prediction where each direction can correspond to an intra prediction mode. The intra prediction mode can be signalled by an encoder to a decoder.

- (20) Encoding using temporal similarities can be known as inter prediction. Inter prediction attempts to predict the pixel values of a block using a possibly displaced block or blocks from a temporally nearby frame (i.e., reference frame) or frames. A temporally nearby frame is a frame that appears earlier or later in time in the video stream than the frame of the block being encoded. A prediction block resulting from inter prediction is referred to herein as inter predictor.
- (21) Inter prediction is performed using a motion vector. A motion vector used to generate a prediction block refers to a frame other than a current frame, i.e., a reference frame. Reference frames can be located before or after the current frame in the sequence of the video stream. Some codecs use up to eight reference frames, which can be stored in a frame buffer. The motion vector can refer to (i.e., use) one of the reference frames of the frame buffer. As such, one or more reference frames can be available for coding a current frame.
- (22) As mentioned above, a current block of a video stream may be encoded based on identifying a difference (residual) between the previously coded pixel values and those in the current block. In this way, only the residual and parameters used to generate the residual need be added to the encoded bitstream. The residual may be encoded using a lossy quantization step.
- (23) The residual block can be in the pixel domain. The residual block can be transformed into the frequency domain resulting in a transform block of transform coefficients. The transform coefficients can be quantized resulting into a quantized transform block of quantized transform coefficients. The quantized coefficients can be entropy encoded and added to an encoded bitstream. A decoder can receive the encoded bitstream, entropy decode the quantized transform coefficients to reconstruct the original video frame.
- (24) Entropy coding is a technique for “lossless” coding that relies upon probability models that model the distribution of values occurring in an encoded video bitstream. By using probability models based on a measured or estimated distribution of values, entropy coding can reduce the number of bits required to represent video data close to a theoretical minimum. In practice, the actual reduction in the number of bits required to represent video data can be a function of the accuracy of the probability model, the number of bits over which the coding is performed, and the computational accuracy of fixed-point arithmetic used to perform the coding.
- (25) In an encoded video bitstream, many of the bits are used for one of two things: either content prediction (e.g., inter mode/motion vector coding, intra prediction mode coding, etc.) or residual coding (e.g., transform coefficients).
- (26) Encoders may use techniques to decrease the amount of bits spent on transform coefficient coding. For example, level maps, as further described below, can be used for coding transform coefficients. Herein, for brevity and unless otherwise clear from the context, transform coefficient(s) means quantized transform coefficient(s), and transform block(s) means quantized transform coefficient(s).
- (27) The values of the transform coefficients can be split into two planes: a lower plane and a higher plane. A maximum level is associated with the lower plane. The lower plane indicates for a transform coefficient a value that is “up to whether the coefficient is less than or equal the maximum level.” For example, if the maximum level is 2, then the lower plane indicates whether a coefficient is 0, 1, 2, or greater than 2. As such, “up to whether the coefficient is less than or equal 2” means that the lower plane indicates that the value of a coefficient is either 0, 1, 2, or greater than 2. Any coefficient whose value is greater than 2 (e.g., the maximum level) can be represented in lower plane with one value that indicates “greater than 2” (i.e., 3 or above). The higher plane corresponds to coefficient values that are, in this example, 3 or above. As such, each of the values of the lower plane can be one of four values, namely 0, 1, 2, or “greater than 2.” In an example, a coefficient that is greater than 2 can be represented by the value 3 in the lower plane.
- (28) In general, the lower plane (i.e., values of the lower plane) appears much more frequently than the higher plane. This is so because for every value of higher plane, a corresponding value necessary exists in the lower plane. However, some of the values of the lower plane may not have

corresponding values in the higher plane. For example, a transform coefficient with a value of 7 would have corresponding values in the lower plane (e.g., a value of 3 since 7 is greater than 2) and a value in the lower plane (e.g., 5). However, a transform coefficient with a value of 2 does not have a corresponding value in the higher map. As such, the compression performance (i.e., speed of compression) of the lower plane can have a significant impact on the overall compression performance.

(29) As described above, entropy coding a sequence of symbols is typically achieved by using a probability model to determine a probability p for the sequence and then using binary arithmetic coding to map the sequence to a binary codeword at the encoder and to decode that sequence from the binary codeword at the decoder. The length (i.e., number of bits) of the codeword is given by $-\log(p)$. The efficiency of entropy coding can be directly related to the probability model. Throughout this document, $\log$ denotes the logarithm function to base two (2) unless specified otherwise.

(30) A model, as used herein, can be, or can be a parameter in, a lossless (entropy) coding. A model can be any parameter or method that affects probability estimation for entropy coding.

(31) A purpose of context modeling is to obtain probability distributions for a subsequent entropy coding engine, such as arithmetic coding, Huffman coding, and other variable-length-to-variable-length coding engines. To achieve good compression performance, a large number of context models may be required. For example, some video coding systems can include hundreds or even thousands of context models for transform coefficient coding alone. Each context model can correspond to a probability distribution.

(32) As already mentioned, residuals for a block of video are transformed into transform blocks of transform coefficients. The transform blocks are in the frequency domain and one or more transform blocks may be generated for a block of video. The transform coefficients are quantized and entropy coded into an encoded video bitstream. A decoder uses the encoded transform coefficients and the reference frames to reconstruct the block. Entropy coding a transform coefficient involves the selection of a context model (also referred to as probability context model or probability model) which provides estimates of conditional probabilities for coding the binary symbols of a binarized transform coefficient.

(33) The available context models in a codec may be available as a list, an array, a file, or some other suitable data structure. The list of context models can be ordered. That is, a respective context index can be associated with each context model. As such, selecting a context model can involve determining a context index. The context index is then used to select (e.g., retrieve, access, etc.) the corresponding context model.

(34) Coding the transform coefficients of a transform block, such as coding the values of the lower plane corresponding to the transform block, can include visiting each value of the lower plane, determining a context index for the value of the lower plane, retrieving the context model associated with the context index, and entropy coding the value using the context model.

(35) The values of the lower plane are visited (e.g., processed) along a scan order. The scan order can also be referred to as a processing order. Visiting the values of the lower plane along a scan order can include generating a one-dimensional array. Determining a context index, for a current transform coefficient of a transform block, can include accessing other values in the one-dimensional array. These other values are values that correspond to other transform coefficients that neighbor the current transform coefficients in the 2-dimensional transform block. While these other transform coefficients may neighbor the current transform coefficient block in the 2-dimensional block, the corresponding values may not be neighboring values in the one-dimensional array. The arrangement of the values of the lower plane in the one-dimensional array depends on the scan order.

(36) As further explained below with respect to FIG. 12, accessing the respective other values for each transform coefficient can impose certain computational barrier, especially for the decoder

speed.

(37) Implementations of this disclosure can result in improved compression performance by arranging and accessing values of the lower plane that are required for determining context indexes in such ways as to optimize memory access. The values of the lower plane can be arranged along anti-diagonal lines of a scan order in one or more line buffers such that determining a context index for a value of the lower plane accesses contiguous locations in two or more line buffers. A scan order that aligns values along anti-diagonal lines and methods for accessing the values from line buffers are described.

(38) By integrating the scan order (e.g., processing order) of the values of the lower plane and the computation method of a context index, access to non-contiguous locations of line buffers can be reduced and parallel computing can be exploited. As such, implementations of this disclosure can have reduced computational.

(39) Efficient context model computation design in transform coefficient coding is described herein first with reference to a system in which the teachings may be incorporated.

(40) FIG. 1 is a schematic of a video encoding and decoding system **100**. A transmitting station **102** can be, for example, a computer having an internal configuration of hardware such as that described in FIG. 2. However, other suitable implementations of the transmitting station **102** are possible. For example, the processing of the transmitting station **102** can be distributed among multiple devices.

(41) A network **104** can connect the transmitting station **102** and a receiving station **106** for encoding and decoding of the video stream. Specifically, the video stream can be encoded in the transmitting station **102** and the encoded video stream can be decoded in the receiving station **106**. The network **104** can be, for example, the Internet. The network **104** can also be a local area network (LAN), wide area network (WAN), virtual private network (VPN), cellular telephone network or any other means of transferring the video stream from the transmitting station **102** to, in this example, the receiving station **106**.

(42) The receiving station **106**, in one example, can be a computer having an internal configuration of hardware such as that described in FIG. 2. However, other suitable implementations of the receiving station **106** are possible. For example, the processing of the receiving station **106** can be distributed among multiple devices.

(43) Other implementations of the video encoding and decoding system **100** are possible. For example, an implementation can omit the network **104**. In another implementation, a video stream can be encoded and then stored for transmission at a later time to the receiving station **106** or any other device having memory. In one implementation, the receiving station **106** receives (e.g., via the network **104**, a computer bus, and/or some communication pathway) the encoded video stream and stores the video stream for later decoding. In an example implementation, a real-time transport protocol (RTP) is used for transmission of the encoded video over the network **104**. In another implementation, a transport protocol other than RTP may be used, e.g., an HTTP-based video streaming protocol.

(44) When used in a video conferencing system, for example, the transmitting station **102** and/or the receiving station **106** may include the ability to both encode and decode a video stream as described below. For example, the receiving station **106** could be a video conference participant who receives an encoded video bitstream from a video conference server (e.g., the transmitting station **102**) to decode and view and further encodes and transmits its own video bitstream to the video conference server for decoding and viewing by other participants.

(45) FIG. 2 is a block diagram of an example of a computing device **200** that can implement a transmitting station or a receiving station. For example, the computing device **200** can implement one or both of the transmitting station **102** and the receiving station **106** of FIG. 1. The computing device **200** can be in the form of a computing system including multiple computing devices, or in the form of a single computing device, for example, a mobile phone, a tablet computer, a laptop

computer, a notebook computer, a desktop computer, and the like.

(46) A CPU **202** in the computing device **200** can be a central processing unit. Alternatively, the CPU **202** can be any other type of device, or multiple devices, capable of manipulating or processing information now-existing or hereafter developed. Although the disclosed implementations can be practiced with a single processor as shown, e.g., the CPU **202**, advantages in speed and efficiency can be achieved using more than one processor.

(47) A memory **204** in the computing device **200** can be a read-only memory (ROM) device or a random access memory (RAM) device in an implementation. Any other suitable type of storage device can be used as the memory **204**. The memory **204** can include code and data **206** that is accessed by the CPU **202** using a bus **212**. The memory **204** can further include an operating system **208** and application programs **210**, the application programs **210** including at least one program that permits the CPU **202** to perform the methods described here. For example, the application programs **210** can include applications **1** through **N**, which further include a video coding application that performs the methods described here. The computing device **200** can also include a secondary storage **214**, which can, for example, be a memory card used with a computing device **200** that is mobile. Because the video communication sessions may contain a significant amount of information, they can be stored in whole or in part in the secondary storage **214** and loaded into the memory **204** as needed for processing.

(48) The computing device **200** can also include one or more output devices, such as a display **218**. The display **218** may be, in one example, a touch sensitive display that combines a display with a touch sensitive element that is operable to sense touch inputs. The display **218** can be coupled to the CPU **202** via the bus **212**. Other output devices that permit a user to program or otherwise use the computing device **200** can be provided in addition to or as an alternative to the display **218**. When the output device is or includes a display, the display can be implemented in various ways, including by a liquid crystal display (LCD), a cathode-ray tube (CRT) display or light emitting diode (LED) display, such as an organic LED (OLED) display.

(49) The computing device **200** can also include or be in communication with an image-sensing device **220**, for example a camera, or any other image-sensing device **220** now existing or hereafter developed that can sense an image such as the image of a user operating the computing device **200**. The image-sensing device **220** can be positioned such that it is directed toward the user operating the computing device **200**. In an example, the position and optical axis of the image-sensing device **220** can be configured such that the field of vision includes an area that is directly adjacent to the display **218** and from which the display **218** is visible.

(50) The computing device **200** can also include or be in communication with a sound-sensing device **222**, for example a microphone, or any other sound-sensing device now existing or hereafter developed that can sense sounds near the computing device **200**. The sound-sensing device **222** can be positioned such that it is directed toward the user operating the computing device **200** and can be configured to receive sounds, for example, speech or other utterances, made by the user while the user operates the computing device **200**.

(51) Although FIG. 2 depicts the CPU **202** and the memory **204** of the computing device **200** as being integrated into a single unit, other configurations can be utilized. The operations of the CPU **202** can be distributed across multiple machines (each machine having one or more of processors) that can be coupled directly or across a local area or other network. The memory **204** can be distributed across multiple machines such as a network-based memory or memory in multiple machines performing the operations of the computing device **200**. Although depicted here as a single bus, the bus **212** of the computing device **200** can be composed of multiple buses. Further, the secondary storage **214** can be directly coupled to the other components of the computing device **200** or can be accessed via a network and can comprise a single integrated unit such as a memory card or multiple units such as multiple memory cards. The computing device **200** can thus be implemented in a wide variety of configurations.

(52) FIG. 3 is a diagram of an example of a video stream **300** to be encoded and subsequently decoded. The video stream **300** includes a video sequence **302**. At the next level, the video sequence **302** includes a number of adjacent frames **304**. While three frames are depicted as the adjacent frames **304**, the video sequence **302** can include any number of adjacent frames **304**. The adjacent frames **304** can then be further subdivided into individual frames, e.g., a frame **306**. At the next level, the frame **306** can be divided into a series of segments **308** or planes. The segments **308** can be subsets of frames that permit parallel processing, for example. The segments **308** can also be subsets of frames that can separate the video data into separate colors. For example, the frame **306** of color video data can include a luminance plane and two chrominance planes. The segments **308** may be sampled at different resolutions.

(53) Whether or not the frame **306** is divided into the segments **308**, the frame **306** may be further subdivided into blocks **310**, which can contain data corresponding to, for example, 16×16 pixels in the frame **306**. The blocks **310** can also be arranged to include data from one or more segments **308** of pixel data. The blocks **310** can also be of any other suitable size such as 4×4 pixels, 8×8 pixels, 16×8 pixels, 8×16 pixels, 16×16 pixels or larger.

(54) FIG. 4 is a block diagram of an encoder **400** in accordance with implementations of this disclosure. The encoder **400** can be implemented, as described above, in the transmitting station **102** such as by providing a computer software program stored in memory, for example, the memory **204**. The computer software program can include machine instructions that, when executed by a processor such as the CPU **202**, cause the transmitting station **102** to encode video data in manners described herein. The encoder **400** can also be implemented as specialized hardware included in, for example, the transmitting station **102**. The encoder **400** has the following stages to perform the various functions in a forward path (shown by the solid connection lines) to produce an encoded or compressed bitstream **420** using the video stream **300** as input: an intra/inter prediction stage **402**, a transform stage **404**, a quantization stage **406**, and an entropy encoding stage **408**. The encoder **400** may also include a reconstruction path (shown by the dotted connection lines) to reconstruct a frame for encoding of future blocks. In FIG. 4, the encoder **400** has the following stages to perform the various functions in the reconstruction path: a dequantization stage **410**, an inverse transform stage **412**, a reconstruction stage **414**, and a loop filtering stage **416**. Other structural variations of the encoder **400** can be used to encode the video stream **300**.

(55) When the video stream **300** is presented for encoding, the frame **306** can be processed in units of blocks. At the intra/inter prediction stage **402**, a block can be encoded using intra-frame prediction (also called intra-prediction) or inter-frame prediction (also called inter-prediction), or a combination of both. In any case, a prediction block can be formed. In the case of intra-prediction, all or a part of a prediction block may be formed from samples in the current frame that have been previously encoded and reconstructed. In the case of inter-prediction, all or part of a prediction block may be formed from samples in one or more previously constructed reference frames determined using motion vectors.

(56) Next, still referring to FIG. 4, the prediction block can be subtracted from the current block at the intra/inter prediction stage **402** to produce a residual block (also called a residual). The transform stage **404** transforms the residual into transform coefficients in, for example, the frequency domain using block-based transforms. Such block-based transforms include, for example, the Discrete Cosine Transform (DCT) and the Asymmetric Discrete Sine Transform (ADST). Other block-based transforms are possible. Further, combinations of different transforms may be applied to a single residual. In one example of application of a transform, the DCT transforms the residual block into the frequency domain where the transform coefficient values are based on spatial frequency. The lowest frequency (DC) coefficient at the top-left of the matrix and the highest frequency coefficient at the bottom-right of the matrix. It is worth noting that the size of a prediction block, and hence the resulting residual block, may be different from the size of the

transform block. For example, the prediction block may be split into smaller blocks to which separate transforms are applied.

(57) The quantization stage **406** converts the transform coefficients into discrete quantum values, which are referred to as quantized transform coefficients, using a quantizer value or a quantization level. For example, the transform coefficients may be divided by the quantizer value and truncated. The quantized transform coefficients are then entropy encoded by the entropy encoding stage **408**. Entropy coding may be performed using any number of techniques, including token and binary trees. The entropy-encoded coefficients, together with other information used to decode the block, which may include for example the type of prediction used, transform type, motion vectors and quantizer value, are then output to the compressed bitstream **420**. The information to decode the block may be entropy coded into block, frame, slice and/or section headers within the compressed bitstream **420**. The compressed bitstream **420** can also be referred to as an encoded video stream or encoded video bitstream, and the terms will be used interchangeably herein.

(58) The reconstruction path in FIG. 4 (shown by the dotted connection lines) can be used to ensure that both the encoder **400** and a decoder **500** (described below) use the same reference frames and blocks to decode the compressed bitstream **420**. The reconstruction path performs functions that are similar to functions that take place during the decoding process that are discussed in more detail below, including dequantizing the quantized transform coefficients at the dequantization stage **410** and inverse transforming the dequantized transform coefficients at the inverse transform stage **412** to produce a derivative residual block (also called a derivative residual). At the reconstruction stage **414**, the prediction block that was predicted at the intra/inter prediction stage **402** can be added to the derivative residual to create a reconstructed block. The loop filtering stage **416** can be applied to the reconstructed block to reduce distortion such as blocking artifacts.

(59) Other variations of the encoder **400** can be used to encode the compressed bitstream **420**. For example, a non-transform based encoder **400** can quantize the residual signal directly without the transform stage **404** for certain blocks or frames. In another implementation, an encoder **400** can have the quantization stage **406** and the dequantization stage **410** combined into a single stage.

(60) FIG. 5 is a block diagram of a decoder **500** in accordance with implementations of this disclosure. The decoder **500** can be implemented in the receiving station **106**, for example, by providing a computer software program stored in the memory **204**. The computer software program can include machine instructions that, when executed by a processor such as the CPU **202**, cause the receiving station **106** to decode video data in the manners described below. The decoder **500** can also be implemented in hardware included in, for example, the transmitting station **102** or the receiving station **106**.

(61) The decoder **500**, similar to the reconstruction path of the encoder **400** discussed above, includes in one example the following stages to perform various functions to produce an output video stream **516** from the compressed bitstream **420**: an entropy decoding stage **502**, a dequantization stage **504**, an inverse transform stage **506**, an intra/inter-prediction stage **508**, a reconstruction stage **510**, a loop filtering stage **512** and a post filtering stage **514**. Other structural variations of the decoder **500** can be used to decode the compressed bitstream **420**.

(62) When the compressed bitstream **420** is presented for decoding, the data elements within the compressed bitstream **420** can be decoded by the entropy decoding stage **502** to produce a set of quantized transform coefficients. The dequantization stage **504** dequantizes the quantized transform coefficients (e.g., by multiplying the quantized transform coefficients by the quantizer value), and the inverse transform stage **506** inverse transforms the dequantized transform coefficients using the selected transform type to produce a derivative residual that can be identical to that created by the inverse transform stage **412** in the encoder **400**. Using header information decoded from the compressed bitstream **420**, the decoder **500** can use the intra/inter-prediction stage **508** to create the same prediction block as was created in the encoder **400**, e.g., at the intra/inter prediction stage **402**. At the reconstruction stage **510**, the prediction block can be added to the derivative residual to

create a reconstructed block. The loop filtering stage **512** can be applied to the reconstructed block to reduce blocking artifacts. Other filtering can be applied to the reconstructed block. In an example, the post filtering stage **514** is applied to the reconstructed block to reduce blocking distortion, and the result is output as an output video stream **516**. The output video stream **516** can also be referred to as a decoded video stream, and the terms will be used interchangeably herein. (63) Other variations of the decoder **500** can be used to decode the compressed bitstream **420**. For example, the decoder **500** can produce the output video stream **516** without the post filtering stage **514**. In some implementations of the decoder **500**, the post filtering stage **514** is applied after the loop filtering stage **512**. The loop filtering stage **512** can include an optional deblocking filtering stage. Additionally, or alternatively, the encoder **400** includes an optional deblocking filtering stage in the loop filtering stage **416**.

(64) Some codecs may use level maps to code (i.e., encode by an encoder or decode by a decoder) a transform block. That is, some codecs may use level maps to code the transform coefficients of the transform blocks. In level map coding, the transform block is decomposed into multiple level maps such that the level maps break down (i.e., reduce) the coding of each transform coefficient value into a series of binary decisions each corresponding to a magnitude level (i.e., a map level). The decomposition can be done by using a multi-run process. As such, a transform coefficient of the transform block is decomposed into a series of level binaries and a residue according to the equation:

$$(65) \text{coefficient}[r][c] = \{(\sum_{k=0}^T \text{level}_k[r][c]) + \text{residue}[r][c]\} * \text{sign}[r][c] \text{Where}$$

$$\text{residue}[r][c] = \text{absolute}(\text{coefficient}[r][c]) - T - 1 \text{sign}[r][c] = \begin{cases} 1 & \text{if coefficient}[r][c] > 0 \\ -1 & \text{if coefficient}[r][c] < 0 \end{cases}$$

(66) In the above equation, coefficient[r][c] is the transform coefficient of the transform block at the position (row=r, column=c), T is the maximum level, level.sub.k is the level map corresponding to map level k, residue is a coefficient residual map, and sign is the sign map of the transform coefficients. These terms are further described below with respect to FIG. 7. The transform coefficients of a transform block can be re-composed using the same equation, such as by a decoder, from encoded level, maps, residual map residue, and sign map sign.

(67) A zeroth run can be used to determine a non-zero map (also referred to as a level-0 map) which indicates which transform coefficients of the transform block are zero and which are non-zero. Level maps corresponding to runs 1 through a maximum (i.e., threshold) level T (i.e., level-1 map, level-2 map, . . . , level-T map) are generated in ascending order from level 1 to the maximum level T. The level map for level k, referred to as the level-k map, indicates which transform coefficients of the transform block have absolute values greater to or equal to k. The level maps are binary maps. A final run generates a coefficients residue map. If the transform block contains transform coefficient values above the maximum level T, the coefficients residue map indicates the extent (i.e., residue) that these coefficients are greater than the maximum level T.

(68) When generating (i.e., coding) the level-k map, only the positions (r, c) corresponding to positions (r, c) of the level-(k-1) map which are equal to 1 (i.e., level.sub.k-1[r][c]=1) need be processed—other positions of the level-(k-1) are determined to be less than k and, therefore, there is no need to process them for the level-k map. This reduces processing complexity and reduces the amount of binary coding operations.

(69) As the level maps contain binary values, the above and left neighbors of a value to be encoded are binary values. A context model based on the binary values of any number of previously coded neighbors can be determined. The context model can fully utilize information from all these neighbors. The previously coded neighbors can be neighbors in the same level map or a preceding level map, such as an immediately preceding level map. The immediately preceding map of the level-k (e.g., level-2) map is the level-(k-1) (e.g., level-1) map. Contexts according to this disclosure can be less complex thereby resulting in efficient models for coding the level maps.

(70) When encoding a level- k map, the fully coded level- $(k-1)$ map and the partially coded level- k map can be used as context information for context modeling. As compared to transform coefficient coding of other video systems, which code one coefficient value at a time before moving to next transform coefficient, implementations of this disclosure can reduce the cardinality of the reference sample set. This is so because, as further described herein, the information from the level- $(k-1)$ map and partially coded level- k map are binary information. The binary information enables the use of sophisticated spatial neighboring templates for context modeling binary information. Such spatial neighboring templates can better capture statistical characteristics of transform blocks, especially those with larger transform block sizes.

(71) FIG. 6 is a flowchart diagram of a process 600 for encoding a transform block in an encoded video bitstream using level maps according to an implementation of this disclosure. The process 600 can be implemented in an encoder such as the encoder 400. The encoded video bitstream can be the compressed bitstream 420 of FIG. 4.

(72) The process 600 can be implemented, for example, as a software program that can be executed by computing devices such as transmitting station 102. The software program can include machine-readable instructions that can be stored in a memory such as the memory 204 or the secondary storage 214, and that can be executed by a processor, such as CPU 202, to cause the computing device to perform the process 600. In at least some implementations, the process 600 can be performed in whole or in part by the entropy encoding stage 408 of the encoder 400.

(73) The process 600 can be implemented using specialized hardware or firmware. Some computing devices can have multiple memories, multiple processors, or both. The steps or operations of the process 600 can be distributed using different processors, memories, or both. Use of the terms “processor” or “memory” in the singular encompasses computing devices that have one processor or one memory as well as devices that have multiple processors or multiple memories that can be used in the performance of some or all of the recited steps.

(74) The process 600 is now explained with reference to FIG. 7. FIG. 7 is a diagram illustrating the stages 700 of transform coefficient coding using level maps in accordance with implementations of this disclosure. FIG. 7 includes the zigzag forward scan order 702, a transform block 704, a non-zero map 706, a level-1 map 707, a level-2 map 709, an end-of-block map 726, a sign map 732, and a coefficient residual map 734.

(75) The process 600 can receive a transform block, such as the transform block 704 of FIG. 7. The transform block can be received from the quantization step of an encoder, such as the quantization stage 406 of the encoder 400 of FIG. 4. The transform block 704 includes zero and non-zero transform coefficients. Some of the non-zero coefficients may be negative values.

(76) At 602, a non-zero map is encoded. The non-zero map indicates positions of the transform block that contain non-zero transform coefficients. The non-zero map can also be referred to as the level-0 map.

(77) The non-zero map 706 of FIG. 6 illustrates a non-zero map. The non-zero map can be generated by traversing the transform block 704 in a scan order, such as the zigzag forward scan order 702 of FIG. 7, and indicating in the non-zero map 706, using binary values, whether the corresponding transform coefficient is a zero or a non-zero. In the non-zero map 706, a non-zero transform coefficient of the transform block 704 is indicated with the binary value 1 (one) and a zero transform coefficient is indicated with the binary value 0 (zero). However, the indication can be reversed (i.e., a zero to indicate a non-zero transform coefficient and one (1) to indicate a zero transform coefficient).

(78) In an implementation, zero transform coefficients that are beyond (i.e., come after) the last non-zero transform coefficient, based on the scan order of the transform block, are not indicated in the non-zero map. For example, using the zigzag forward scan order 702 to scan the transform block 704, the last non-zero transform coefficient 708, corresponding to scan position 11, is the last indicated transform coefficient in the non-zero map 706 at last non-zero coefficient 710. No values

are indicated in the non-zero map **706** for the transform coefficients corresponding to the scan positions 12-15 of the zigzag forward scan order **702**.

(79) At **604**, the process **600** encodes a respective lower-range level map. Each lower-range map has a map level up to a maximum level. A lower-range level map indicates which values of the non-zero transform coefficients are equal to the map level of the lower-range map and which values of the non-zero transform coefficients are greater than the map level.

(80) For each map level k , up to the maximum level T , a lower-range level map level.sub.k is encoded. Each lower-range level map indicates which values of the transform block are equal to the map level of the lower-range level map and which values of the transform block are greater than the map level. As such, the process **600**, using multiple runs (i.e., each run corresponding to a level $k=1, 2, \dots, T$), breaks down the coding of transform coefficients into a series of binary decisions each corresponding to a magnitude level. The binary decision of a coefficient at row and column (r, c) in the transform block at level k can be defined by:

$$(81) \quad \text{level}_k[r][c] = \begin{cases} 1 & \text{if absolute(coefficient}[r][c]) > k \\ 0 & \text{if absolute(coefficient}[r][c]) \leq k \end{cases}$$

(82) For example, for $k=1$ (i.e., for the level-1 map **707**), the process **600** determines for each transform coefficient of the transform block **704** whether the absolute value of the transform coefficient is greater than k (i.e., 1) or less than or equal to k . For the transform coefficient **720** (i.e., at $r=0, c=0$), as the absolute value of -7 (i.e., $|-7|=7$) is greater than 1, the process **600** sets the corresponding value **722** of the level-1 map **707** to 1. For the last non-zero transform coefficient **708** (i.e., at $r=2, c=2$), as the absolute value of -1 (i.e., $|-1|=1$) is equal to k (i.e., 1), the process **600** sets the corresponding value **716** of the level-1 map **707** to 0. The last non-zero transform coefficient in the transform block (e.g., the last non-zero transform coefficient **708**) can be referred to as the highest AC coefficient).

(83) In an implementation, to generate a lower plane, the process **600** can scan the preceding level map backwards starting at the last 1 value of the previous level map. For a level- k map, the preceding level map is the level- $(k-1)$ map corresponding to the preceding map level $(k-1)$. That is, for $k=2$, the preceding level map is the level-1 map. For $k=1$, the preceding level map is the level-0 map (i.e., the non-zero map). For the level-1 map **707**, scanning of the non-zero map **706** starts at the last non-zero coefficient **710**. For the level-2 map **709**, scanning of the level-1 map **707** starts at the last non-zero coefficient **724**. In generating a level- k map, the process **600** need only process the transform coefficients corresponding to 1 values in the level- $(k-1)$. The process **600** need not process the transform coefficients corresponding to non 1 values as those values are already determined to either be equal to $k-1$ (i.e., the zero values of the level- $(k-1)$ map) or are less than $k-1$ (i.e., the blank values of the level- $(k-1)$ map).

(84) In an implementation, the maximum level T can be fixed. For example, the maximum level T can be provided as a configuration to the process **600**, the maximum level T can be hard-coded in a program that implements the process **600**, or the maximum level T can be set statistically or adaptively based on previously coded transform blocks or other blocks of the encoded video bitstream. Alternatively, the maximum level T is determined by the process **600**. That is, the process **600** can test different values for the maximum level T (i.e., $T=1, 2, 3, 4, \dots$) and determine which value provides the best compression performance. The value of the maximum level T that results in the best compression can be encoded in the video bitstream, which a decoder, such as the decoder **500** of FIG. 5 can decode and use. A maximum level T of 2 or 3 has been determined to provide acceptable compression as compared to other values for the maximum level T .

(85) At **606**, the process **600** encodes a coefficient residual map. Each residual coefficient of the coefficient residual map corresponds to a respective (i.e., co-located) non-zero transform coefficient of the transform block having an absolute value exceeding the maximum level. The

residual coefficient for a transform coefficient at location (r, c) of the transform block can be calculated using the formula (1):

$$(86) \text{ residue}[r][c] = \text{absolute}(\text{coefficient}[r][c]) - T - 1 \quad (1)$$

(87) FIG. 7 illustrates a coefficients residue map **734**. In the example of FIG. 7, the maximum level T is equal to two (2). As such, the coefficients residue map **734** contains the residuals of the transform coefficients of the transform block **704** the absolute values of which are greater than 2. A residual coefficient is the extent to which the absolute value of a transform coefficient exceeds the maximum level T. The absolute values of two values of the transform block **704** are greater than the value of the maximum level T (i.e., 2), namely the transform coefficient **720** (i.e., $|-7|=7>2$) and transform coefficient **739** (i.e., $|4|=4>2$). Respectively, the coefficients residue map **734** includes residual **736** and residual **738**. Using the formula (1), the residual **736** is set to 5 (i.e., $\text{absolute}(-7)-3=4$) and the residual **738** is set to 1 (i.e., $\text{absolute}(4)-3=1$).

(88) The residual coefficients of the coefficients residue map **734** can be encoded in the encoded video bitstream using binary coding. A probability distribution that fits the statistics of the residual coefficients of the coefficients residue map can be used. The probability distribution can be a geometric distribution, a Laplacian distribution, a Pareto distribution, or any other distribution.

(89) Encoding the residual coefficients in the encoded video bitstream provides several benefits, such as over video coding systems that encode the transform coefficients. As each residual coefficient is smaller in magnitude than its corresponding transform coefficient, less bits are required to encode the residual coefficient. Additionally, as there are fewer residual coefficients to encode (e.g., 2 in the coefficient residual map **734** of FIG. 7) than non-zero transform coefficients (e.g., 7 in the transform block **704** of FIG. 7), additional compression can result.

(90) In an implementation of the process **600**, a sign map can also be encoded. A sign map indicates which transform coefficients of the transform block have positive values and which transform coefficients have negative values. Transform coefficients that are zero need not be indicated in the sign map. The sign map **732** of FIG. 7 illustrates an example of a sign map for the transform block **704**. In the sign map, negative transform coefficients are indicated with a -1 and positive transform coefficients are indicated with a 1. In some implementations, the sign of a positive coefficient may be indicated with a 0 and the sign of a negative coefficient may be indicated with a 1.

(91) In an implementation of the process **600**, encoding a non-zero map, at **602**, can also include generating an end-of-block map for the transform block and interleaving the non-zero map and the end-of-block map in the encoded video bitstream.

(92) The end-of-block map indicates whether a non-zero transform coefficient of the transform block is the last non-zero coefficient with respect to a given scan order. If a non-zero coefficient is not the last non-zero coefficient in the transform block, then it can be indicated with the binary value 0 (zero) in the end-of-block map. If, on the other hand, a non-zero coefficient is the last non-zero coefficient in the transform block, then it can be indicated with the binary value 1 (one) in the end-of-block map.

(93) For example, as the transform coefficient **720** of the transform block **704** is followed by another non-zero transform coefficient (e.g., the transform coefficient -1 corresponding to scan location 2), the transform coefficient **720** is not the last non-zero transform coefficient, it is indicated with the end-of-block value **728** of zero. On the other hand, as the transform coefficient corresponding to the scan location 11 (i.e., the last non-zero transform coefficient **708**) is the last non-zero coefficient of the transform block **704**, it is indicated with the end-of-block value **730** of 1 (one).

(94) The process **600** can, by traversing the non-zero map and the end-of-block maps in a same scan order, interleave values from the non-zero map **706** and the end-of-block map **726** in the encoded bitstream. The process **600** can use the zigzag forward scan order **702** or any arbitrary

scan order. For each position (r, c), the value at that row and column of the non-zero map **706** (i.e., nz_map[r][c]) is coded first. If the value nz_map[r][c] is 1, then the corresponding value from the end-of-block map **726** (i.e., eob_map[r][c]) is coded next to indicate whether the position (r, c) of the transform block **704** contains the last nonzero transform coefficient. The process **600** ends the coding of the non-zero map (e.g., the non-zero map **706**) when eob_map[r][c] equals to 1 or when the last position in the transform block (e.g., the scan position 15 of the zigzag forward scan order **702**) is reached. That is, when encoding a value of 1 from the non-zero map **706**, the value is followed by another syntax element (i.e., a value to be encoded in the encoded video bitstream) from a corresponding (i.e., co-located) end-of-block map **726** value to indicate whether the 1 value is the last 1 value of the non-zero map **706**.

(95) In an implementation, encoding a non-zero map, at **602**, can also include determining a coding context for a value (i.e., to-be-coded value) of the non-zero map. The coding context of a to-be-coded value at a current position (r, c) can be based on previously coded non-zero neighboring values of the to-be-coded value in the non-zero map. The coding context can also be based on the position of the to-be-coded value within the non-zero map.

(96) As mentioned above, the context information can be determined based on the number of non-zero previously coded neighbors of the current position and can be calculated using the sum

$$(97) \text{ non_zero_map_sum}(r, c) = \sum_{(r', c') \in \text{nb}(r, c)} \text{nz_map}(r', c') \quad (2)$$

(98) In equation (2), non_zero_map_sum(r, c) is the number of non-zero previously coded neighbors of the to-be-coded value of the non-zero block at position (r, c), nb(r, c) is the set of previously coded neighbors of the to-be-coded value at location (r, c) of the non-zero map, and nz_map(r', c') is the value at position (r', c') in the non-zero map. Equation (1) is further explained with reference to FIG. 8.

(99) FIG. 8 is a diagram of previously coded neighbors in a non-zero map **800** according to an implementation of this disclosure. FIG. 8 includes a to-be-encoded value, current value **802**, an unavailable context neighbor **806** (i.e., a neighboring value for which context information is not available), and coded context neighbors, such as coded context neighbor **808**. Ten coded context neighbors are illustrated. Which values are included in the set of neighbors depends on the scan order. For example, using the zigzag forward scan order **702** of FIG. 7, the set of neighbors illustrated in FIG. 8 includes the coded context neighbors **804** which includes neighbors that are above and to the left of the current value **802**. For the current value **802**, non_zero_map_sum(2,2)=5. This value (i.e., 5) can be used as context information to determine a probability model for coding the current value **802** of the non-zero map **800**.

(100) As indicated above, the coding context can also be based on the position of the to-be-coded value within the non-zero map or, equivalently, in the transform block. The positions of the transform block can be grouped into context groups. For example, four context groups can be set: a first group corresponding to the DC coefficient (i.e., r=0 and c=0), a second group corresponding to the top row except for the AC coefficient (i.e., r=0 and c>0), a third group corresponding to the left-most column except for the AC coefficient (i.e., r>0 and c=0), and a fourth group corresponding to all other coefficients (i.e., r>0 and c>0). As such, the current value **802** corresponds to the fourth context group.

(101) In an implementation, encoding a non-zero map, at **602**, can also include determining a coding context for each value of the end-of-block map. The process **600** can determine a context model for a to-be-encoded value of the end-of-block map based on the location of the to-be-encoded value with respect to the frequency information of the transform block. That is, the position of the transform coefficient in the transform block can be used as the context for determining the context model for encoding a corresponding (i.e., co-located) to-be-encoded value of the end-of-block map. The transform block can be partitioned into areas such that each area corresponds to a context. The partitioning can be based on the rationale that the likelihood is very

low that the end-of-block is at the DC location of the transform block but that the likelihood increases further from the DC coefficient.

(102) In some implementations, a lower-range level map can be a binary map having dimensions corresponding to the dimensions of the transform block and, as indicated above, a map level k . A position of the lower-range level map can be set to one (1) when a corresponding value in the preceding level map (i.e., level map $k-1$ as described below) is one (1) and the corresponding transform coefficient is greater than the map level k of the lower-range level map. A position of the lower-range level map can be set to a value of zero when a corresponding value in the preceding level map has a value of one and the corresponding transform coefficient is equal to the map level k of the lower-range level map. A position of the lower-range level map can have no value when a corresponding value in the preceding level map has a value of zero.

(103) In an implementation of the process **600**, encoding a lower-range level map for a level, at **604**, can also include determining, based on a scan order of the lower-range level map, a level-map coding context for a value of the lower-range level map. As indicated above, encoding a value of a lower-range level map k amount to encoding a binary value, namely whether the corresponding (i.e., co-located) transform coefficient of the transform block is equal k or is above k . The encoding of binary values results in simple contexts. As such, multiple neighboring values of a value can be used as the context for determining a context model for the value.

(104) As also indicated above, scanning of the lower-range level map can proceed in a backwards scan order. As such, when encoding a value, neighboring values below and to the right of the to-be-encoded value (if, for example, the scan order is the zigzag forward scan order or **702** of FIG. 7) will have already been encoded. Therefore, first neighboring values (e.g., below and right neighboring values) in the lower-range level map can be used as context. Additionally, second neighboring values (e.g., top and left neighboring values) in the immediately preceding level- $(k-1)$ map can also be used as context. The preceding level map of a lower-range level- k map is the lower-range level- $(k-1)$ map, for $k>2$; and the preceding level map for the level-1 map is the non-zero map.

(105) As described above, the coding of the transform coefficients is a multi-pass process. In the first pass, the non-zero map **706**, which describes the locations of non-zero coefficients in the transform block, is coded following the forward scan order. In subsequent passes, the values of the non-zero coefficients following the backward scan order (i.e., from the position of the highest AC coefficient to the position of the DC coefficient) are coded. Coding the non-zero map **706** can be implemented using the steps: 1. Initialize $i=0$, where i denotes the scan position, and $i=0$ corresponds to the DC position (e.g., the transform coefficient **720**). 2. Code a binary non-zero flag $nz[i]$ indicating whether the quantized transform coefficient at scan position i is zero. For example, a zero value ($nz[i]=0$) can be coded when the quantized transform coefficient is zero (i.e., the value in the non-zero map **706** at scan position i is zero); otherwise (the value in the non-zero map **706** at scan position i is 1), a one value ($nz[i]=1$) is coded. In another example, a zero value ($nz[i]=0$) can be coded when the quantized transform coefficient is not zero; otherwise, a one value ($nz[i]=1$) is coded. 3. If $nz[i]$ indicates that the transform coefficient at scan position i is non-zero (e.g., $nz[i]=1$), then code a binary flag indicating whether all the coefficients at scan positions higher than i are all zero. That is, when a 1 value of the non-zero map **706** is coded, then a value at the same scan position in the end-of-block map **726** is then coded. 4. Set i to the next scan position ($i=i+1$). 5. Repeat Steps 2-4 until EOB is met (i.e., until the end-of-block value **730** is coded). 6. Set $nz[j]=0$ for all $j>EOB$. That is, set all transform coefficients after the end-of-block value **730** to 0.

(106) During the quantization process, such as described with respect to the quantization stage **406** of FIG. 4, a rate distortion optimized quantization (RDOQ) process determines (e.g., calculates, selects, etc.), for transform coefficients of a transform block, respective quantized transform coefficients according to a rate distortion cost of each of the quantized transform coefficients.

(107) For example, in response to receiving a transform coefficient value x , the RDOQ may

initially provide a quantized transform coefficient $Q(x)$. The quantized transform coefficient $Q(x)$ may be first obtained by minimizing the distortion (e.g., a loss in video quality). However, when the RDOQ considers the rate (e.g., a number of bits) of coding the quantized transform coefficient $Q(x)$ in addition to the distortion, the RDOQ may obtain another quantized transform coefficient $Q'(x)$ that provides a better overall rate distortion cost. This process can continue until an optimal quantized transform coefficient is obtained for the transform coefficient value x . As such, the quantized coefficient value of a transform coefficient may change during the coding process of the transform coefficient and/or the transform block that includes the transform coefficient.

(108) As described above, coding the non-zero map **706** uses a forward scan order and coding the subsequent level maps uses a backward scan. As such, estimating the rate cost of changing a transform coefficient value can be difficult since the first pass and the second (or a subsequent) pass of coding use different scan orders: one forward and one backward.

(109) More specifically, in the first pass where the scan order is forward (from the DC coefficient to the highest AC coefficient), a change to the quantized coefficient value at scan position i can impact the rate cost of coding coefficients at scan positions j that follow the scan position i (i.e., $j > i$); and in the second pass, where the scan order is backward (from the highest AC coefficient to the DC coefficient), a change to the quantized coefficient at scan position i can impact the rate cost of coding coefficients at scan positions j' that precede the scan position i (i.e., $j' < i$).

(110) As such, to estimate the cost of coding a coefficient at scan position i , information from transform coefficients at scan positions $j > i$ and transform coefficients at scan positions $j' < i$ are required thereby creating a bi-directional dependency. This bi-directional dependency may significantly complicate the RDOQ process.

(111) To avoid the bi-directional dependency, implementations according to this disclosure can, instead of interleaving EOB indications (i.e., end-of-block values of the end-of-block map **726**) after non-zero values of the non-zero map **706**, first code the EOB symbol and proceed to process the non-zero map **706** in a backward scan order. As such, backward scan orders can be used for all passes of the coding of the transform block using level maps. By using backward scan orders in all passes, only information from transform coefficients at scan positions j following the scan position of a current transform coefficient i (i.e., $j > i$) are required for estimating the rate cost of coding the coefficient at scan position i . As such, complexity is reduced, which in turns leads to more efficient implementation of the RDOQ. Accordingly, coding a transform block using level maps can be implemented using the steps: 1. Code EOB. 2. Set $nz[j]=0$ for all $j > \text{EOB}$, and set $nz[\text{EOB}]=1$. Terminate the process if $\text{EOB} < 1$. 3. Initialize $i = \text{EOB} - 1$. 4. Code $nz[i]$ indicating whether the quantized transform coefficient at scan position i is zero ($nz[i]=0$) or not ($nz[i]=1$). 5. Set $i = i - 1$. 6. Repeat Steps 3-5 until $i = -1$.

(112) In the above steps, the EOB is as described with respect to FIGS. **6-7**. That is the EOB indicates the location of the last non-zero coefficient of the transform block. However, other semantics for the EOB are possible. For example, in an implementation, the EOB can indicate the location immediately after the last non-zero coefficient of the transform block. As such, and referring to FIG. **7** for illustration, the EOB would indicate the scan position 12 (instead of the scan position 11 as described with respect to FIGS. **6-7**).

(113) When the EOB indicates the position immediately after the last non-zero coefficient, then the steps above can be given by the following: 1. Code EOB. 2. Set $nz[j]=0$ for all $j \geq \text{EOB}$, and set $nz[\text{EOB}-1]=1$. Terminate the process if $\text{EOB} \leq 1$. 3. Initialize $i = \text{EOB} - 2$. 4. Code $nz[i]$ indicating whether the quantized transform coefficient at scan position i is zero ($nz[i]=0$) or not ($nz[i]=1$). 5. Set $i = i - 1$. 6. Repeat Steps 3-5 until $i = -1$.

(114) FIG. **9** is a flowchart diagram of a process **900** for coding a transform block using level maps according to an implementation of this disclosure. The process **900** can be implemented by an encoder such as the encoder **400** of FIG. **4**. When implemented by an encoder, coding means encoding in an encoded bitstream, such as the compressed bitstream **420** of FIG. **4**. For example,

the process **900** can be performed in whole or in part by the entropy encoding stage **408** of the encoder **400**. The process **900** can be performed by a decoder such as the decoder **500** of FIG. 5. When implemented by a decoder, coding means decoding from an encoded bitstream, such as the compressed bitstream **420** of FIG. 5. For example, the process **900** can be performed in whole or in part by the entropy decoding stage **502** of the decoder **500** and the encoded video bitstream can be the compressed bitstream **420** of FIG. 5.

(115) Implementations of the process **900** can be performed by storing instructions in a memory such as the memory **204** of the receiving station **106** to be executed by a processor such as CPU **202**, for example.

(116) The process **900** can be implemented using specialized hardware or firmware. Some computing devices can have multiple memories, multiple processors, or both. The steps or operations of the process **900** can be distributed using different processors, memories, or both. For simplicity of explanation, the process **900** is depicted and described as a series of steps or operations. However, the teachings in accordance with this disclosure can occur in various orders and/or concurrently. Additionally, steps in accordance with this disclosure may occur with other steps not presented and described herein. Furthermore, not all illustrated steps or operations may be used to implement a method in accordance with the disclosed subject matter.

(117) At **902**, the process **900** codes an end-of-block indicator of the transform block. In an implementation, the scan position of the EOB can be coded. For example, and referring to FIG. 7, the scan position 11 corresponding to the last non-zero transform coefficient **708** can be coded. In another example, the scan position 12, corresponding to the coefficient following the last non-zero transform coefficient **708** in the forward scan order, is coded. In an implementation, the end-of-block indicator can be coded using a context model.

(118) At **904**, the process **900** codes the non-zero map in the backward scan order starting at the last non-zero coefficient of the transform block. The non-zero map indicates which transform coefficients of a transform block have a zero value and which transform coefficients of the transform block have a non-zero value. The process **900** codes the non-zero map that is similar to the non-zero map **706** of FIG. 7. The process **900** codes a binary value indicating whether a quantized transform coefficient at a scan position of the scan order is zero or non-zero. For example, for a scan position *i*, the process **900** can code a zero if the quantized transform coefficient at the scan position *i* is zero; otherwise a 1 is coded.

(119) At **906**, the process **900** codes a respective lower-range level map having a respective map level up to a maximum level *T*. A lower-range level map having to a map level indicates the transform coefficients of the transform block are equal, in absolute value, to the respective map level and which transform coefficients of the transform block are, in absolute value, greater than the respective map level. When implemented by a decoder, the process **900** decodes values from the encoded video bitstream to reconstruct lower-range level-*k* maps encoded as described with respect to **604** of the process **600**.

(120) For example, to reconstruct a level-1 map, the process **900** starts from the highest non-zero transform coefficient traversing backwards to determine which of transform coefficients are equal to 1 and which are greater than 1. That is, using the reconstructed non-zero map of the non-zero map **706** of FIG. 7, and starting at the last non-zero coefficient **710** and traversing backwards to the value **740**, the process **900** reconstructs the level-1 map **707** of FIG. 7. For each 1 value of the reconstructed non-zero map, the process **900** decodes a value from the encoded video bitstream and reconstructs the level-1 map **707**. The values decoded by the process **900** are zero and one (1) values.

(121) To reconstruct a level-2 map, the process **900** uses the same procedure as that used to generate the level-1 map except that, instead of traversing the reconstructed non-zero map, the process **900** uses the reconstructed level-1 map. The process **900** repeats all the steps until the maximum level number of level maps are reconstructed.

(122) In an implementation, the maximum level T can be provided to the process **900** via a configuration. In another implementation, the maximum level T can be signaled, by an encoder, in the encoded video bitstream. As such, the process **900** decodes the maximum level T from the encoded video bitstream.

(123) At **908**, the process **900** codes a coefficient residual map. Each residual coefficient of the coefficient residual map corresponds to a respective transform coefficient of the transform block having an absolute value that exceeds the maximum level. When implemented by a decoder, the process **900** reconstructs, e.g., the coefficient residual map **734** of FIG. 7. For each one (1) value of the level-T map, the process **900** decodes a corresponding residual value from the encoded bitstream to reconstruct the coefficient residual map **734** of FIG. 7.

(124) In some implementations, the process **900** can include coding a sign map, at **910**. The sign map can be a sign map such as described with respect to the sign map **732** of FIG. 7. The sign map indicates which transform coefficients of the transform block have positive values and which transform coefficients have negative values.

(125) For a transform block of size $N \times N$, in the worst case $N \times N - 1$ bins (binary symbols) may need to be context coded to determine the EOB position. For example, when $N=32$, in the worst cost, a total of 1023 bins may be context coded (i.e., coded using a context model) to determine the EOB position.

(126) Some implementations can use scan positions groups to reduce the number of context-coded bins required to code the EOB position. As such, coding the scan position corresponding to the end-of-block position can include coding an index of a scan positions group that includes the scan position and coding an offset within the scan positions group, the offset corresponding to a position of the scan position within the scan positions group.

(127) In an implementation of level maps, the value $EOB=0$ can be reserved for indicate that all transform coefficients of the block are zero. That is, when $EOB=0$, then the block is an all-zero block.

(128) In an example of such implementations, the scan positions can be partitioned (e.g., grouped) into 11 scan positions groups: 1, 2, [3, 4], [5-8], [9-16], [17-32], [33-64], [65-128], [129-256], [257-512], [513-1024]. That is, the group with index 0 includes only the scan position 1; the group with index 1 includes only the scan position 2; the group with index 4 includes the scan positions 9-16; and so on. For example, assuming that the scan position 50, corresponding to the EOB, is to be coded, then the index 6 of a scan positions group [33-64] that includes the scan position 50 is coded and the offset 17 (i.e., $50-33=17$) within the scan positions group [33-64] is coded.

(129) In an implementation, the index of the group that includes the coded scan position corresponding to the end-of-block is context-coded (i.e., is coded using arithmetic coding using a context model) and the offset within the scan positions group can be coded in by-pass mode. By-pass mode, which may also be referred to as the literal mode, means that the value to be coded is not coded using a context model. The by-pass mode can be used, for example, when the offset values within a range are equally probable. To code the offset 17, five (5) bits are required. As such, in this example, the number of context coded bins for EOB is at most 10 corresponding to the group indexes $\{0, 1, \dots, 10\}$.

(130) In an implementation, the index of the group that includes the coded scan position corresponding to the end-of-block is context-coded (i.e., coded using a context model) and at least some of the most significant bits of the offset within the scan positions group can also be context-coded. That is, the offset value can be considered to include prefix bits (i.e. most significant bits) and suffix bits (i.e., least significant bits). The prefix bits can be context-coded and the suffix bits can be coded using by-pass mode. Any number of bits of the offset value can be considered the most significant bits. For example, the offset value 17 corresponds to the binary string 10001. If the first 2 bits are considered most significant, then the bits 10 are context-coded and the bits 001 are by-pass coded (i.e., coded using by-pass mode). If the first 3 bits are considered most significant,

then the bits 100 are context-coded and the bits 01 are by-pass coded.

(131) The scan positions can be grouped into scan position groups in any number of ways. In an implementation, and as illustrated by the above group, each group can include a power of 2 number of scan positions. The power of 2 can be the index scan position groups minus 1 (i.e., index -1). For example, the scan position groups at index 5 (i.e., the group [17-32]) includes $2^{\text{sup.}5-1}$ ($=2^{\text{sup.}4}=16$) scan positions. As such, to code an offset within a scan position groups having an index inx , only $(\text{inx}-1)$ bits are required. For example, one (1) bit is required to code an offset in the group having index 2 (the group [3,4]), two (2) bits are required to code an offset in the group having index 3 (the group [9-16]), and so on.

(132) In an implementation, the number of scan positions in each scan positions group can be limited to a maximum predetermined number (i.e., a ceiling). For example, the group size can be limited to no greater than 16. As such, the above group can be modified as follows: 1, 2, [3, 4], [5-8], [9-16], [17-32], [33-48], [49-64], . . . , [1009-1024]. As such, coding an offset requires no more than 4 bits. To code an EOB position of 50 using the modified groups, the index 7, which corresponds to the scan positions group [49-64], can be coded using arithmetic coding with context models. The offset 1 ($=50-49$) can be coded in bypass mode by using 4 bits, namely 0001.

(133) In some implementations, the value $\text{EOB}=0$ is not reserved for indicating that all transform coefficients of the block are zero. In such implementations, the scan positions groups can start at 0 and end at 1023, such as 0, 1, [2, 3], [4-7], [8-15], [16-31], [32-63], [64-127], [128-255], [256-511], [512-1023].

(134) As described above, the values of the non-zero map **706** include binary values. The binary values indicate whether a transform coefficient at a given location of the transform block is zero or non-zero. As such, the values of the non-zero map can be considered non-zero flags. The binary values enable the use of sophisticated spatial neighboring templates for context modeling. Such spatial neighboring templates can better capture statistical characteristics of transform blocks, especially those with larger transform block sizes. Accordingly, the coding of non-zero flags (and thus, the coding of transform coefficients) can be improved by fully utilizing the information of neighboring non-zero flags when determining a context for selecting a context model.

(135) A template captures the coded history of the non-zero flags (i.e., values of the non-zero map) that are coded before a current non-zero flag. A template can define (e.g., specify, select, set, or any way define), for a current scan position, the scan positions of the non-zero map values that are to be used for determining the context for coding the current value. Equivalently, a template can be defined in terms of the Cartesian coordinates, within the non-zero map, of the non-zero values to be used for determining the context.

(136) FIGS. **10A-10B** is a diagram of examples **1000** of templates for determining a coding context according to implementations of this disclosure. In FIGS. **10A-10B**, values (i.e., circles representing values of a non-zero map) shaded using the pattern **1004** are to-be-coded values; and the values shaded with the pattern **1002** are values for which context information are available because these values are coded before a to-be-coded value **1032**. In the examples of FIGS. **10A-10B**, the to-be-coded value **1032** depicts the current value of the non-zero map to be coded. The examples of FIGS. **10A-10B** are non-limiting examples. Templates having other shapes and/or sizes are also possible.

(137) In an example, the number of non-zero values corresponding to the template positions can be used as the context for coding the current value. For example, the values corresponding to the template positions can be added and the sum can be used as the context. In some cases, a template position may not be available, such as, for example, if the context position is outside the boundaries of the block. In an example, an unavailable value can be assumed to be zero (0). In another example, an unavailable value can be assumed to be one (1).

(138) A codec can use multiple transform types. For example, a transform type can be the transform type used by the transform stage **404** of FIG. **4** to generate the transform block. For example, the

transform type (i.e., an inverse transform type) can be the transform type to be used by the dequantization stage **504** of FIG. **5**. Available transform types can include a one-dimensional Discrete Cosine Transform (1D DCT) or its approximation, one-dimensional Discrete Sine Transform DST (1D DST) or its approximation, a two-dimensional DCT (2D DCT) or its approximation, two-dimensional DST (2D DST) or its approximation, and an identity transform. Other transform types can be available. In an example, a one-dimensional transform (1D DCT or 1D DST) can be applied in one dimension (e.g., row or column) and the identity transform applied in the other dimension.

(139) In the cases where a 1D transform (e.g., 1D DCT, 1D DST) is used (e.g., 1D DCT is applied to columns (or rows, respectively) of a transform block), the quantized coefficients can be coded by using a row-by-row (i.e., raster) scanning order or a column-by-column scanning order. In the cases where 2D transforms (e.g., 2D DCT) are used, a different scanning order may be used to code the quantized coefficients. As indicated above, different templates can be used to derive contexts for coding the non-zero flags of the non-zero map based on the types of transforms used. As such, in an implementation, the template can be selected based on the transform type used to generate the transform block. As indicated above, examples of a transform type include: 1D DCT applied to rows (or columns) and an identity transform applied to columns (or rows); 1D DST applied to rows (or columns) and an identity transform applied to columns (or rows); 1D DCT applied to rows (or columns) and 1D DST applied to columns (or rows); a 2D DCT; and a 2D DST. Other combinations of transforms can comprise a transform type.

(140) As indicated above with respect to FIG. **9**, the non-zero map can be coded in the backward scan order starting at the last non-zero coefficient (i.e., starting at the highest AC transform coefficient) of the transform block. As such, the coded history of a current value (i.e., a current non-zero flag) of the non-zero map includes values that are to the right and below the current value in the two-dimensional non-zero map, such as the non-zero map **706**.

(141) When a 1D vertical transform type is applied, the to-be-coded value **1032** is more correlated with vertical neighbor values than with horizontal neighbor values. As such, a template **1010** can be used in the case a 1D transform (e.g., 1D DCT) is applied to columns. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1010** comprises the values at the seven positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x+4, y)$, $(x, y+1)$, $(x+1, y+1)$, and $(x+1, y+2)$.

(142) When a 1D horizontal transform type is applied, the to-be-coded value **1032** is more correlated with horizontal neighbor values than with vertical neighbor values. As such, a template **1020** can be used in the case a 1D transform (e.g., 1D DCT) is applied to rows. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1020** comprises the values at the seven positions $(x+1, y)$, $(x, y+1)$, $(x+1, y+1)$, $(x, y+2)$, $(x+1, y+2)$, $(x, y+3)$, and $(x, y+4)$.

(143) When a 2D transform type (e.g., 2D DCT, 2D DST) is applied, a template **1030** can be used. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1030** comprises the values at the seven positions $(x+1, y)$, $(x+2, y)$, $(x, y+1)$, $(x+1, y+1)$, $(x+2, y+1)$, $(x, y+2)$, and $(x+1, y+2)$.

(144) In some examples of templates, the non-zero value that is scanned immediately before the to-be-coded value **1032** is not included in the template. That is, if the to-be-coded value **1032** is at scan position i , then the non-zero value at scan position $(i-1)$ is not included in the template. Even though the non-zero map is coded in a backward scan order, the scan order of the scan order can depend on the transform type. The scan order of the backward scan order is the order in which non-zero values of the non-zero map are visited from the highest AC value to the DC value. In an example, a vertical scan order can be used when a 1D horizontal transform type is used. As such, the scan order proceeds in column-wise order (e.g., from bottom to top). In an example, a horizontal scan order can be used when a 1D vertical transform type is used. As such, the scan

order proceeds in row-wise order (e.g., from right to left).

(145) Template **1040** is another example of a template that can be used when a 1D-transform type is applied to columns. In the template **1040**, the non-zero value that is scanned immediately before the to-be-coded value **1032** is not included in the template. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1040** comprises the values at the seven positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x+4, y)$, $(x+1, y+1)$, $(x+1, y+1)$, and $(x+1, y+2)$.

(146) Template **1050** is another example of a template that can be used when a 1D-transform type is applied to rows. In the template **1050**, the non-zero value that is scanned immediately before the to-be-coded value **1032** is not included in the template. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1040** comprises the values at the seven positions $(x, y+1)$, $(x+1, y+1)$, $(x, y+2)$, $(x+1, y+2)$, $(x, y+3)$, $(x+1, y+3)$, and $(x, y+4)$.

(147) Template **1060** is an example of a template that can be used when a 2D transform (e.g., 2D DCT, 2D DST) is used. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1040** comprises the values at the seven positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x, y+1)$, $(x+1, y+1)$, $(x, y+2)$, and $(x, y+3)$.

(148) Each of templates **1010-1060** includes seven (7) positions. However, a template can include more or less positions and/or can have other shapes. For example, template **1070** is another example of a template that can be used when a 2D transform type is used. The template **1070** includes eight (8) positions. Assuming that the to-be-coded value **1032** is at position (x, y) of the non-zero map, then the template **1040** comprises the values at the eight positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x, y+1)$, $(x+1, y+1)$, $(x, y+2)$, $(x+1, y+2)$, and $(x, y+3)$.

(149) In other examples, a template can include five (5) positions. For example, a template **1088** of FIG. **10B**, which includes the positions $(x+1, y)$, $(x, y+1)$, $(x+2, y)$, $(x, y+2)$, $(x+1, y+1)$, can be used for 2D-transform types. For example, templates **1080**, **1082**, **1083** can be used for a vertical 1D-transform type. The template **1080** includes the positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x+4, y)$, and $(x, y+1)$. The template **1082** includes the positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x+4, y)$, and $(x+1, y+1)$. The template **1083** includes the positions $(x, y+1)$, $(x, y+2)$, $(x, y+3)$, $(x+1, y)$, $(x+1, y+1)$. For example, templates **1084**, **1086**, and **1087** can be used for a horizontal 1D-transform type. The template **1084** includes the positions $(x+1, y)$, $(x+2, y)$, $(x+3, y)$, $(x, y+1)$, $(x+1, y+1)$. The template **1086** includes the positions $(x, y+1)$, $(x, y+2)$, $(x, y+3)$, $(x, y+4)$, and $(x+1, y+1)$. The template **1087** includes the positions $(x, y+1)$, $(x, y+2)$, $(x, y+3)$, $(x, y+4)$, and $(x+1, y)$. In some implementation, the positions $(x+1, y)$ and $(x, y+1)$ can be replaced by the positions $(x+1, y+2)$ and $(x+2, y+1)$, respectively.

(150) In some implementations, coding of a level- k map, where $k > 0$, can also use different templates (e.g., templates as described above) depending upon transform types. For example, as described above, one template may be used for 2D-transform type, one template may be used for vertical 1D-transform type, and another template may be used for horizontal 1D-transform type.

(151) In some implementations, the contexts used to code the non-zero flags can depend upon the locations (i.e., the scan positions or the block positions) of the non-zero flags. As such, in some implementations, the transform-type-dependent templates, described above, can be combined with the locations of the non-zero flags to determine a context. To avoid using too many contexts, which may lead to the so-called context dilution problem, the locations can be classified into regions. For example, the classification may be dependent upon the transform type.

(152) As described above with respect to FIG. **7**, the level maps are coded sequentially. That is, the non-zero map **706** is coded, then the level-1 map is coded, then the level-2 map is coded, and then the coefficient residual map **734** is coded. However, in some implementations, a different coding structure can be used.

(153) As described above with respect to FIGS. **10A-10B**, coding of a level- k map, where $k > 0$, can also use different templates (e.g., templates as described above) depending upon transform types. That is, a template, as described above can be used to determine a context for coding whether a

coefficient at (x, y) is greater than 1 (e.g., using a corresponding value of a level-1 map, such as the level-1 map **707** of FIG. 7) or is greater than 2 (e.g., using a corresponding value of a level-2 map, such as the level-2 map **709** of FIG. 7).

(154) As such, each coefficient can be coded up to whether the coefficient is greater than the maximum level. In the example of FIG. 7, the maximum level is 2. As such, each coefficient can be coded up to whether the coefficient is greater than 2 (using corresponding values of level maps) before proceeding to coding of a next coefficient. In an implementation, a coefficient value that is greater than 2 (i.e., a coefficient value that is greater than the maximum level) can be represented by the value 3 (i.e., the maximum level+1). As such, coding a coefficient “up to whether the coefficient is greater than maximum level (e.g., 2)” (i.e., coding an “up-to” value) can mean coding a value 0, 1, 2, . . . , (maximum level+1) (e.g. 3) corresponding, respectively and in the case what the maximum level is 2, to a coefficient having a value equal to 0, equal to 1, equal to 2, and greater than 2. For brevity, and as mentioned above, a value that results from coding a coefficient “up to whether the coefficient is greater than maximum level” is referred to herein as an “up-to” value.

(155) The “up-to” values of the coefficients of the transform block can be referred to collectively as a “lower plane” or a first plane. The coefficient residual map, such as the coefficient residual map **734** of FIG. 7, is also referred to herein as the “higher plane” or second plane.

(156) FIG. 11 is a flowchart diagram of a process **1100** for coding a transform block using level maps according to an implementation of this disclosure. Unlike the process **900** which codes the level maps sequentially (i.e., each map is coded before proceeding to coding the next map), the process **1100** codes, for each non-zero coefficient, using a template, and in a case where the maximum level is 2 (i.e., T=2), whether the coefficient is 0, 1, 2, or greater than 2 (represented by the value 3). That is, the process **1100** codes the “up-to” value of the lower plane of a coefficient before proceeding to the next coefficient in the scan order. The process **1100** can include blocks similar to those of the process **900**. Descriptions of the similar blocks (e.g., **902**, **908**, and **910**) are omitted. Some implementations of the process **1100** can include the block **910** before the block **908**.

(157) The process **1100** can be implemented by an encoder such as the encoder **400** of FIG. 4. When implemented by an encoder, coding means encoding in an encoded bitstream, such as the compressed bitstream **420** of FIG. 4. For example, the process **1100** can be performed in whole or in part by the entropy encoding stage **408** of the encoder **400**. The process **1100** can be performed by a decoder such as the decoder **500** of FIG. 5. When implemented by a decoder, coding means decoding from an encoded bitstream, such as the compressed bitstream **420** of FIG. 5. For example, the process **1100** can be performed in whole or in part by the entropy decoding stage **502** of the decoder **500** and the encoded video bitstream can be the compressed bitstream **420** of FIG. 5.

(158) Implementations of the process **1100** can be performed by storing instructions in a memory such as the memory **204** of the receiving station **106** to be executed by a processor such as CPU **202**, for example.

(159) The process **1100** can be implemented using specialized hardware or firmware. Some computing devices can have multiple memories, multiple processors, or both. The steps or operations of the process **1100** can be distributed using different processors, memories, or both. For simplicity of explanation, the process **1100** is depicted and described as a series of steps or operations. However, the teachings in accordance with this disclosure can occur in various orders and/or concurrently. Additionally, steps in accordance with this disclosure may occur with other steps not presented and described herein. Furthermore, not all illustrated steps or operations may be used to implement a method in accordance with the disclosed subject matter.

(160) At **1102**, the process **1100** determines whether there are more non-zero coefficients to code. If so, the process **1100** proceeds to **1104** to code a current quantized transform coefficient at (x, y); otherwise, the process **1100** proceeds to **908** followed by **910**. At **1104**, the process **1100** selects a

template for coding a current quantized transform coefficient. As used in this disclosure, “select” means to identify, construct, determine, specify, generate, or other select in any manner whatsoever. The template can be a template as described with respect to FIGS. **10A-10B**. In an example, the same template is used for coding all the coefficients of the transform block. As such, the template can be selected once for the process **1100** and be performed before the block **1102**.

(161) At **1106**, the process **1100** determines a context using the template. The process **1100** can determine the context using the template in any number of ways. Each template position corresponds to a lower plane value (e.g., 0, 1, . . . , T+1). Combinations of the values can be used to determine the context. For example, a sum of the values can be used. For example, a weighted sum can be used to determine the context. The weight assigned to a position can be set based on the distance to an “origin.” In an example, the origin can be the location (x, y) of the current transform coefficient for which the context is being determined. Examples of distance include a scan position distance (e.g., a difference between the scan position of the current coefficient and a position of the template) or a Cartesian distance. However, other ways of setting the weight can be available. In yet another example, a non-linear function can be used. For examples, the maximum or minimum value in the template can be used for determining the context. In yet another example, the context can be determined using a combination of the sum and the maximum values. Other methods and/or values, or combinations of methods and/or values, can be used for determining the context from the template.

(162) Using the sum (i.e., addition) of the values at the positions of the template to determine a context is now given. It should be understood that the following can be used with any method for determining the context using the template.

(163) The process **1100** can add up (sums) the values corresponding to the positions of the template. When using a template for deriving a context for coding a coefficient, each of the positions of the template can have one of the values 0, 1, 2, or 3 (i.e., when T=2). As such, if the template includes N positions, then the maximum sum can be 3*N. For example, if a template that includes 5 positions is selected at **1104**, then the maximum sum can be 15 (=3*5); if a template that includes 7 positions is selected, then the maximum sum can be 21 (=3*7).

(164) In an implementation, where level maps as described with respect to FIG. 7 are used, to determine a value for a position of the template, the values, at the same positions in the non-zero maps and the level-k maps can be added or counted. For example, assuming that the position of the last non-zero transform coefficient **708** is a position of the template, then the value of the template at that position can be determined to be the sum of the values at **710** (i.e., 1) and **716** (i.e., 0) of the non-zero map **706** and level-1 map **707**. As such, the value is 1. As another, assuming that the position of the transform coefficient **739** is a position of the template, then the value of the template at that position can be determined to be the sum of the values at the corresponding locations of in the non-zero map **706**, the level-1 map **707**, and the level-2 map **709**. As such, the value is 3. As such, the context index can be determined using a sum of the values corresponding to positions of the template where each value of the template is determined by summing respective values of at least some of the level maps.

(165) In another implementation, the level maps, including the zero map and as described with respect to FIG. 7 are not generated. Instead, a lower plane one-dimensional array, level, can be used to indicate whether a transform coefficient is one of 0, 1, . . . , T+1. Whereas the lower plane mentioned above is a 2-dimensional structure corresponding to the transform block, the lower plane one-dimensional array, level, is generated as a result of the scan order. The lower plane one-dimensional array, level, is referred to as the lower-plane array.

(166) Given a scan position i, level[i]={0, 1, . . . , T+1}. The lower plane array, level, can include values for all transform coefficients of the transform block. Alternatively, the lower plane array can include values for coefficients up to the end-of-block coefficient. That is, the lower plane array, level, can include values for each transform coefficient up to and including the last non-zero

coefficient of the transform block.

(167) In the case of an encoder, the lower plane array, level, can be generated a priori before coding its values in a bitstream. Alternatively, the lower plane array, level, can be generated as coefficients are encoded. For example, the lower plane array can be generated using the steps: 1) for a scan position, determine a corresponding “up-to” value, 2) code the “up-to” value, and 3) store/place the “up-to” at the scan position in the lower plane, level. The steps 2 and 3 can be reversed. In the case of a decoder, the lower plane array, level, can be populated with values as the values are decoded from the bitstream.

(168) The sum for determining the context index can be calculated by adding the respective values of the lower plane array, level. For example, assuming that the template includes 5 positions corresponding to the scan positions l.sub.1, l.sub.2, l.sub.3, l.sub.4, and l.sub.5, then the sum can be determined as $\text{sum} = \text{level}[\text{l1}] + \text{level}[\text{l2}] + \text{level}[\text{l3}] + \text{level}[\text{l4}] + \text{level}[\text{l5}]$.

(169) Using the sum, the process **1100** can determine a context index (e.g., a variable ctx). The context index can be determined using an operation that is similar to the operation $((\text{counts}+1) \gg 1)$ as described above. However, instead of using “count,” a “sum” is used. As such, the process **1100** uses $((\text{sum}+1) \gg 1)$ for determining the context index.

(170) The context index ctx may be out of range. For example, assuming that the sum is 15, the transform class is TX_CLASS_2D, and that (x, y) is (1, 2), then the context index is $((\text{sum}+1) \gg 1) + 6 = ((15+1) \gg 1) + 6 = 14$. However, the number of available contexts for the TX_CLASS_2D, using the above example, is 11. As such, the context index is out of range. Equivalently, a sum that results in a context index that is out of range can itself be considered out of range. If the context index is out of the range, then, the process **1100** can set the context index to a predetermined number. As such, the process **1100** can determine the context index using a formula such as $\min(((\text{sum}+1) \gg 1), \text{predetermined number})$. As such, the value $((\text{sum}+1) \gg 1)$ is upper-bounded by the predetermined number. In an example, the predetermined number can be 4. In an example, the predetermined number can depend on the transform class type. The predetermined number can be selected in any other ways.

(171) The context index ctx can be used to select a context for coding the current transform coefficient; more specifically, to code the “up-to” value of the current transform coefficient. At **1108**, the process **1100** codes the coefficient using the context.

(172) An implementation of the process **1100** that uses the lower plane array, level, for coding transform coefficients of the transform block can be summarized using the following procedure:

(173) TABLE-US-00001 1. for (i=eob-1; i>=0; i--) { 2. if (i < eob-1) code level[i]>0; 3. if (level[i] > 0) { 4. for (j=0; j<T; j++) { 5. code level[i] > j+1 6. if (level[i] == j+1) 7. break; 8. } 9. } 10. } 11. for (i==0; i < eob; i++) { 12. if level[i] != 0 13. code sign[i] 14. } 15. for (i=eob-1; i >= 0; i--) 16. if level[i] > T 17. code level[i] -T-1

(174) The steps 1-10 can be repeated for each transform coefficient up to the last non-zero coefficient of the transform block. For a transform coefficient at scan position i, the steps 2-9 code the “up-to” value. That is, the steps 2-9 code “up to whether a transform coefficient of the transform block is greater than a maximum level of the level maps.” For example, assuming that the maximum level T=2 and i<eob-1, if level[i]=3, then the steps 2-9 code the bits 111; if level[i]=0, then the steps 2-9 code the bit 0; and if level[i]=2, then the steps 2-9 code the bits 110. The steps 11-14 code the sign bits (e.g., the values of the sign map **732** of FIG. 7) of the non-zero transform coefficients up to the last non-zero coefficient. The steps 15-17 code, for each non-zero coefficient that is greater than the maximum level T (i.e., level[i]>T), a residual for the transform coefficient. That is, the steps 15-17 code a value from the higher plane. The values of the residuals can be as described with respect to the coefficient residual map **734**.

(175) Blocks **1102-1108** of FIG. 11 correspond to coding the lower plane and block **908** corresponds to coding the higher plane described above.

(176) Using the coding structure described in FIG. 11 for coding a transform coefficient (i.e., a quantized transform coefficient), as compared to the coding structure described with respect to FIG. 9, better throughput can be obtained. Better throughput can mean that a transform block can be decoded faster using the coding structure of the process 1100 than that of the process 900.

(177) FIG. 12 is an example of an illustration 1200 of using a template to determine a context according to implementations of this disclosure. The illustration 1200 uses a template, as described with respect to FIGS. 10A-10B, to determine a context index for a to-be-coded value 1032. The template used in the illustration 1200 is the template 1088 of FIG. 10B. However, other templates, such as the template 1070, can be used. The to-be-coded value can be the to-be-coded value 1032 of FIGS. 10A-10B. In FIG. 10B, the neighbors of the to-be-coded value 1032 are shown as having actual values. In FIG. 12, the neighbors of the to-be-coded value 1032 are numbers (i.e., 1-5) for case of reference.

(178) As described with respect to FIG. 11, coding proceeds in a backward scan order and the lower plane array, level, can be created. In the case of an encoder, “coding” means encoding, and a “to-be-coded” value means a value that is to be added to a compressed bitstream, such as the compressed bitstream 420 of FIG. 4. In the case of a decoder, “coding” means decoding, and a “to-be-coded” value means a value that is to be read from, or decoded from, a compressed bitstream, such as the compressed bitstream 420 of FIG. 5. The values of the lower plane array, level, are arranged according to the scan order.

(179) The scan order determines a mapping from scan order positions (i.e., locations) of the one-dimensional lower plane array, level, to Cartesian locations of the transform block, or the lower plane; equivalently, the scan order determines a mapping from the Cartesian locations to scan order positions.

(180) As described above, the template indicates, for a to-be-coded value of the lower plane, the scan positions of coded levels of the lower plane. Equivalently, as there is a one-to-one correspondence between scan positions and Cartesian coordinates for a given scan order, the template can indicate Cartesian coordinates. The coordinates can be absolute coordinates, using the DC coefficient as the origin. Alternatively, the coordinates can be relative coordinates (e.g., defined as vertical and horizontal offsets from the to-be-coded value). The neighbors specified by the template are arranged along template anti-diagonal lines. For example, and referring again to the template 1088 of FIG. 12, neighbors 1 and 3 are arranged along a template anti-diagonal line 1202; and the neighbors 2, 4, and 5 are arranged along a template anti-diagonal line 1204. As such, and depending on the number of neighboring locations of the template, the scan positions indicated by the template are arranged, in the template, in at least two template anti-diagonal lines. For example, while the scan positions indicated by the template 1088 are arranged along two template anti-diagonal lines, the scan positions indicated by the template 1070 of FIG. 10A are arranged along three template anti-diagonal lines.

(181) An illustration of using the template 1088 with different scan orders is now given. The illustration uses a 4×4 block; however, the disclosure is not limited to any block size. Using a backward vertical scan order 1208 to process a 4×4 lower plane 1216, the value of the one-dimensional lower plane at a scan position 1210 (i.e., the scan position 14 in the scan order) corresponds to the lower plane value that corresponds to the transform coefficient at Cartesian location (1, 0) of the transform block. Assuming that the scan position 1210 is the to-be-coded value 1032, and superimposing the template 1088 on the backward vertical scan order 1208, then the neighboring locations 1-5 of the template 1088 correspond, respectively, to the scan positions 10, 6, 13, 9, and 12. Sorted in ascending order, the neighboring scan positions are 6, 9, 10, 12, and 13. As can be seen, the scan positions are not contiguous. That is, the scan positions are not sequential.

(182) As another example, using the backward horizontal scan order 1212, the same Cartesian location (1, 0) corresponds to a scan position 11 (the scan position 11 in the scan order). Assuming

that the scan position 1214 is the to-be-coded value **1032**, and superimposing the template **1088** on the backward horizontal scan order **1212**, then the neighboring locations 1-5 of the template **1088** correspond, respectively, to the scan positions 10, 9, 7, 6, and 3. Sorted in ascending order, the neighboring scan positions are 3, 6, 7, 9, and 10. Again, the scan positions of the neighboring locations are not contiguous (i.e., sequential).

(183) Lower plane array **1206** illustrates a hypothetical ordering of values of a lower plane (not shown) according to a hypothetical scan order. As can be seen in the lower plane array **1206**, the example of the backward vertical scan order **1208**, and the example of the backward horizontal scan order **1212**, the neighboring values 1-5 of the to-be-coded value **1032** using the template **1088** are located sparsely (i.e., non-contiguously) in the 1-dimensional lower plane array, level. As such, deriving a context model using the five neighbors of the template **1088** requires accessing sparse points in the 1-dimensional array.

(184) It is noted that for nearly all computing platforms, including x86, ARM, and hardware-implemented codecs, the 2-dimensional array transform coefficient is stored in 1-D array (also referred to as line buffer). Lower plane arrays can also stored in line buffers. As accessing non-continuous (i.e., non-contiguous) data from line buffers downgrades data caching performance, using scan orders and/or techniques whereby neighboring values are located contiguously in line buffers can improve coding performance.

(185) FIG. **13** is a diagram of an example **1300** of a scan order that aligns values along anti-diagonal lines according the implementations of this disclosure. The example **1300** includes a block **1302**. The block **1302** can be a transform block from which lower plane values can be determined. That is, a lower plane block is not generated, rather the values of the lower plane block are inferred from the transform coefficients. Alternative, the block **1302** can represent a lower plane. That is, the lower plane can be generated and stored in memory from the transform coefficients. For simplicity of explanation, the block **1302** is assumed to be the 2-dimensional lower plane.

(186) The block **1302** is shown as an 8×8 block. However, this disclosure is not limited to any particular block size. As indicated above, the lower plane would include, at a Cartesian location, a value for a transform coefficient at the same Cartesian location of the transform block. However, for illustration purposes, the cells of the block **1302** show the scan position of the respective cell, instead of the particular value at that cell. As indicated above, a lower plane, such as the block **1302** can be generated as values an encoded in a bitstream. Accordingly, the block **1302** may not be fully populated with values. For example, if a current scan position is x, then the block **1302** may only include values for scan positions lower than (or lower than and including) scan position x.

(187) The scan order of the example **1300** can be referred to as an anti-diagonally aligned scan order. Using the anti-diagonally aligned scan order, a codec can advantageously process (to determine context indexes) all values in one scan-order anti-diagonal line using efficient parallel computing thereby improving cache performance.

(188) Four scan-order anti-diagonal lines are indicated in the example **1300**. A scan-order anti-diagonal line **1304** includes the scan positions 54-57; a scan-order anti-diagonal line **1306** includes the scan positions 49-53; a scan-order anti-diagonal line **1308** includes the scan positions 43-48; and a scan-order anti-diagonal line **1310** includes the scan positions 36-42.

(189) Each scan-order anti-diagonal line is a line such that levels in the block **1302** having the same value col+row are considered to be on the same scan-order anti-diagonal line. For example, the scan-order anti-diagonal line **1304** includes those values having col+row=3. As such, the scan-order anti-diagonal line **1304** includes the values corresponding to the scan position 54 (corresponding to the value at block **1302** location (0, 3)), the scan position 55 (corresponding to the value at block **1302** location (1, 2)), the scan position 56 (corresponding to the value at block **1302** location (2, 1)), and the scan position 57 (corresponding to the value at block **1302** location (3, 0)).

(190) As mentioned above, a template of neighboring positions can be used for determining a

context for coding a value at a specific scan position of the block **1302**. The template **1088** of FIG. **10B** is again used for illustration purposes. As also mentioned above, any combination of the values of the neighboring positions can be used to determine a context index (i.e., ctx) that is used to select a context model. For illustration purposes, the sum combination (i.e., addition) is used herein.

(191) Super-imposing the template **1088** on each of the scan positions of the scan-order anti-diagonal line **1306** indicates that the template anti-diagonal line **1202** of FIG. **12** coincides with the scan-order anti-diagonal line **1308** and the template anti-diagonal line **1204** of FIG. **12** coincides with the scan-order anti-diagonal line **1310**. As such, coding values (e.g., of the scan positions 49-53) of a current scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1306**) uses the values of a first scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1308**) coded immediately before the current scan-order anti-diagonal line and the values of a second scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1310**) coded immediately before the first scan-order anti-diagonal line. The scan-order anti-diagonal line **1310** is said to be “older” than the scan-order anti-diagonal line **1308** since its values are coded first.

(192) In the following, the notation $\{\tilde{\text{X}}\}$ (i.e., a number with a tilde on top) means “the value of the lower plane at scan location X”. For example, custom character means the value of the lower plane (i.e., the block **1302**) at scan location 31. That is, and referring to the lower plane array, level, of FIG. **11**, $\text{level}[31] = \text{img alt="lower plane icon" data-bbox="358 358 378 378"/>custom character$. Additionally, the notation $O(X)$ refers to the context index of the context to be used for coding the value at scan position x. $O(X)$ is calculated using the neighboring values identified in the template using an operation, such as an addition operation.

(193) Referring to the block **1302**, the context indexes of the contexts for coding the values at scan location 50, 51, and 52 are, respectively $O(50) = \text{img alt="lower plane icon" data-bbox="475 458 495 478"/>custom character + \text{img alt="lower plane icon" data-bbox="665 458 685 478"/>custom character + \text{img alt="lower plane icon" data-bbox="855 458 875 478"/>custom character + \text{img alt="lower plane icon" data-bbox="1045 458 1065 478"/>custom character$, $O(51) = \text{img alt="lower plane icon" data-bbox="475 480 495 500"/>custom character + \text{img alt="lower plane icon" data-bbox="665 480 685 500"/>custom character + \text{img alt="lower plane icon" data-bbox="855 480 875 500"/>custom character + \text{img alt="lower plane icon" data-bbox="1045 480 1065 500"/>custom character$, and $O(52) = \text{img alt="lower plane icon" data-bbox="475 515 495 535"/>custom character + \text{img alt="lower plane icon" data-bbox="665 515 685 535"/>custom character + \text{img alt="lower plane icon" data-bbox="855 515 875 535"/>custom character + \text{img alt="lower plane icon" data-bbox="1045 515 1065 535"/>custom character$. If a value is not available, as indicated above with respect to FIGS. **10A-10B**, it can be assumed to be zero. As such, the context index of the context for coding the value at scan location 11 is $O(11) = 0 + \{\tilde{9}\} + \{\tilde{3}\} + \{\tilde{8}\} + \{\tilde{4}\}$ since scan location 1312 is not available (i.e., the scan location 1312 is outside the bounds of the transform block of the block **1302**).

(194) As can be seen from $O(5)$, $O(51)$ and $O(52)$, the values used for determining the context models of two consecutive positions in a scan-order anti-diagonal line overlap. For example, one value (e.g., custom character) from the scan-order anti-diagonal line **1308** and two values (e.g., custom character and custom character) from the scan-order anti-diagonal line **1310** are re-used for determining the context indexes $O(50)$ and $O(51)$; and one value (e.g., custom character) from the scan-order anti-diagonal line **1308** and two values (e.g., custom character and custom character) from the scan-order anti-diagonal line **1310** are re-used for determining the context indexes $O(51)$ and $O(52)$. This pattern is repeated for all values of a scan-order diagonal line.

(195) To reiterate, two consecutive scan positions (e.g., scan positions 50 and 51) along the same scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1306**) share previously coded values (e.g., custom character, custom character, and custom character) for calculating context indexes. The shared values are along previously coded scan-order anti-diagonal lines (e.g., the scan-order anti-diagonal lines **1308**, **1310**) corresponding to the template anti-diagonal lines (e.g., the template anti-diagonal lines **1202**, **1204**).

(196) Additionally, it is noted that the values of each previously coded scan-order anti-diagonal line, which are required for coding a current to-be-coded value, are contiguous along the respective scan-order anti-diagonal line. For example, for determining the context index $O(50)$, the required

values  custom character and  custom character are contiguous along the scan-order anti-diagonal line **1308**, and the required values  custom character,  custom character, and  custom character are contiguous along the scan-order anti-diagonal line **1310**. Accordingly, by storing the values of each scan-order anti-diagonal line in a separate line buffer, determining a context index can be performed by accessing contiguous locations in each line buffer thereby improving coding performance.

(197) The minimum number of line buffers depends on the number of template anti-diagonal lines. For example, as the template **1088** includes two template anti-diagonal lines (i.e., template anti-diagonal lines **1202**, **1204**), two line buffers need be maintained. For example, if the template **1070** of FIG. **10A** is used, then three line buffers need be maintained.

(198) For a transform block of size $N \times N$, where $M > N$, each line buffer can include a maximum of N values. As such, for the block **1302** (which is of size 8×8), and using the template **1088**, two line buffers each of size 8 can be used. Line buffer LB1 can correspond to the scan-order anti-diagonal line **1310**. Line buffer LB2 can correspond to the scan-order anti-diagonal line **1308**.

(199) The total number of scan-order anti-diagonal lines for a lower plane of size $N \times N$ is $2N-1$. For example, the block **1302** includes $2*8-1=15$ scan-order anti-diagonal lines. In an implementation, each scan-order anti-diagonal line can have an index L , where $L=0, 1, \dots, 2N-2$. The number of values in a scan-order anti-diagonal line L , $NUM(L)$, can be given by:

$$(200) \text{ NUM}(L) = \begin{cases} L + 1 & \text{if } L < N \\ 2N - L - 1 & \text{if } L \geq N \end{cases}$$

(201) For example, a scan-order anti-diagonal **1314**, with an index $L=0$ and, includes $(L+1)=(0+1)=1$ value. The scan-order anti-diagonal line **1310** has an index of $L=8$. Accordingly, the scan-order anti-diagonal line **1310** includes $(2*8-8-1)=7$ values.

(202) As some of the scan-order anti-diagonal lines may not include N number of values, some locations of the corresponding line buffer can be assumed to be zero. The number of assumed-to-be-zero locations of the line buffer is equal to $(N-NUM(L))$. For example, as the scan-order anti-diagonal line **1308** has an index of $L=9$, a corresponding line includes 2 (i.e., $8-NUM(9)=8-(2*8-9-1)=8-6=2$) assumed-to-be-zero locations.

(203) In an implementation, the assumed-to-be-zero locations of a line buffer can be assumed to be at the head of the line buffer. In another implementation, the assumed-to-be-zero locations can be at the tail of the line buffer.

(204) In an implementation, the values in the line buffers can be arranged with reference to an edge of the transform block. For example, the bottom edge can be used as the reference. That is, values of a scan-order anti-diagonal line that are closer to the reference edge (e.g., bottom edge) are stored toward the front of the line buffer. In such a case, if a scan-order anti-diagonal line visits locations from the top of the block towards the bottom of the block, then the scan locations of the scan-order anti-diagonal line are arranged, in the corresponding line buffer, in the reverse of the traversal order; and if a scan-order anti-diagonal line visits locations from the bottom of the block towards the top of the block, then the scan locations of the scan-order anti-diagonal line are arranged, in the corresponding line buffer, in the traversal order.

(205) Accordingly, the line buffer LB1 can be arranged as $LB1=[0, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}]$ and the line buffer LB2 can be arranged as $LB2=[0, 0, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}]$. The values of the current scan-order anti-diagonal line can also be arranged in a line buffer, CURR_LB. Accordingly, a CURR_LB can be associated with the scan-order anti-diagonal line **1306**. After coding all the values of the scan-order anti-diagonal line **1306**, CURR_LB can be arranged as $CURR_LB=[0, 0, 0, \text{custom character}, \text{custom character}, \text{custom character}, \text{custom character}]$. As such, the value at scan position x can be found at index y in CURR_LB. For example, the value at scan

position 49 can be found at CURR_LB[3], the value at scan position 53 can be found at CURR_LB[7], and so on.

(206) Calculating the context index $O(x)$ of the context to be used for coding the value at scan position x where the scan position x corresponds to location y in the CURR_LB can be performed using the formula:

$$(207) O(\text{CURR_LB}[y]) = (\text{LB2}[y - 1] + \text{LB2}[y]) + (\text{LB1}[y - 2] + \text{LB1}[y - 1] + \text{LB1}[y])$$

(208) That is, determining the context index for a value at scan location y uses: 1) the values at scan positions $(y-1)$ and (y) of the line buffer corresponding to the most recently coded scan-order anti-diagonal line and 2) the values at scan positions $(y-2)$, $(y-1)$, and (y) of the line buffer corresponding to the oldest coded scan-order anti-diagonal line. As such, only contiguous location in each line buffer are accessed. While one arrangement of values in line buffers and an indexing scheme are described, a person skilled in art can appreciate that other arrangements and indexing schemes are possible.

(209) As indicated above, and when using the template **1088**, the context model of a value of a scan-order anti-diagonal line depends on the previous two scan-order anti-diagonal lines. As such, caching data (i.e., values of the lower plane) for context reference modeling can be localized to two scan-order anti-diagonal lines, each of size N , rather than being scattered, for example, over the entire $N \times N$ transform block.

(210) FIG. **14** is flowchart diagram of a process **1400** for cache management for context selection according to implementations of this disclosure. The process **1400** can be implemented, for example, as a software program that may be executed by computing devices such as transmitting station **102** or receiving station **106**. The software program can include machine-readable instructions that may be stored in a memory such as the memory **204** or the secondary storage **214**, and that, when executed by a processor, such as CPU **202**, may cause the computing device to perform the process **1400**. The process **1400** may be implemented in whole or in part in the entropy encoding stage **408** of the encoder **400** and/or entropy decoding stage **502** of the decoder **500**. The process **1400** can be implemented using specialized hardware or firmware. Multiple processors, memories, or both, may be used.

(211) The process **1400** can be used when coding (i.e., encoding or decoding) a transform block. The transform block can be of size $N \times N$. The process **1400** can be used with a transform block coding process that codes a transform block using a lower plane and a higher map. Specifically, the process **1400** can be used in the coding of the lower plane. The lower plane and the higher map can be as described above.

(212) At **1402**, the process **1400** maintains line buffers for scan-order anti-diagonal lines. Maintain can mean generate, calculate, store, determine, allocate, or maintain in any other way. The numbers of line buffers maintained by the process **1400** can depend on the number of template anti-diagonal lines. For example, the process **1400** can maintain, for each of the template anti-diagonal lines, a respective line buffer. For example, if the template used is a template such as the template **1088** of FIG. **10B**, then the process **1400** can maintain two line buffers, LB1 and LB2 as described above. Each of the line buffers can be of size N . In describing the process **1400**, the template **1088** is used. However, a template of different size or having more than two template anti-diagonal lines can be used.

(213) At **1404**, the process **1400** stores in LB1 first coded anti-diagonal coefficient levels. The anti-diagonal coefficient levels can be the values of the scan-order anti-diagonal line as described with respect to FIG. **13**. For example, the process **1400** stores in LB1 the values of the scan-order anti-diagonal line **1310**, as described above.

(214) At **1406**, the process **1400** stores in LB2 second coded anti-diagonal coefficient levels. For example, the process **1400** stores in LB2 the values of the scan-order anti-diagonal line **1308**, as described above.

(215) At **1408**, the process **1400** references LB1 and LB2 to compute a context index for each

coefficient level in a third anti-diagonal line. For example, the third anti-diagonal line can be the scan-order anti-diagonal line **1306**. The process **1400** references LB1 and LB2 as described above. The first line buffer LB1 can correspond to the first scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1310**) that is farther than the second scan-order anti-diagonal line (e.g., the scan-order anti-diagonal line **1308**) to the third anti-diagonal line (i.e., the current scan-order anti-diagonal line being coded, such as the scan-order anti-diagonal line **1306**).

(216) At **1410**, the process **1400** determines whether there are more scan-order anti-diagonal lines to code. Alternatively, the process **1400**, at **1410**, determines whether there are more lower plane values to code or transform coefficients to code. If so, the process **1400** proceeds to **1412**; otherwise, the process **1400** ends at **1414**.

(217) At **1412**, the process **1400** replaces LB1 with the third anti-diagonal line. When all the coefficient levels of the third anti-diagonal line are coded, the values stored in LB1 are no longer needed. That is, the values stored in LB1 are not used to determine a context index for coding any other value after the third anti-diagonal line is coded.

(218) However, the values of the third anti-diagonal line and the values of the second anti-diagonal line are used in determining contexts for the next anti-diagonal line. For example, after coding the values of the scan-order anti-diagonal line **1306**, a codec proceeds to code the values of the next scan-order anti-diagonal line, namely the scan-order anti-diagonal line **1304**. In coding the values of the scan-order anti-diagonal line **1304**, the values of the scan-order anti-diagonal lines **1306**, **1308** are used. As such, the process **1400** retains LB2 and replaces LB1 with the scan-order anti-diagonal line **1306**. That is, the process **1400** replaces the oldest-coded scan-order anti-diagonal line with the last coded scan-order anti-diagonal line.

(219) The process **1400** repeats the above steps. However, in repeating the steps, LB1 and LB2 are interchanged. That is, before coding a new scan-order anti-diagonal line, the process **1400** replaces the oldest line buffer (the one of the LB1 and LB2 that was coded first) with the last coded (i.e., most recently coded) scan-order anti-diagonal line. The process **1400** repeats until all scan-order anti-diagonal lines of the lower plane are coded.

(220) As described above with respect to O(50) and O(51), determining the context model for a positions in a scan-order anti-diagonal line overlaps with its nearest neighbors. A Implementations of this disclosure can leverage this repeated pattern to more efficiently calculate context indexes by using a moving window.

(221) FIG. **15** is a flowchart of a process **1500** for using a moving window for context selection according to implementations of this disclosure. The process **1500** can leverage the hardware capabilities of a codec to improve coding performance. The process **1500** interleaves the data of two line buffers into one destination buffer. The values of the destination buffer are used to implement the moving window as described with respect to cumulative sums.

(222) At **1502**, the process **1500** stores in a first line buffer, LB1, first coded anti-diagonal coefficient levels and stores in a second line buffer, LB2, second coded anti-diagonal coefficient levels. The line buffers LB1 and LB2 can be as described above with respect to the process **1400**.

(223) At **1504**, the process **1500** interleaves the value of the first line buffer LB1 and the second line buffer LB2 into a destination buffer, DEST_BUF. For example, assuming that, as described above, LB1=[0, , custom character, , custom character, , custom character, , custom character] and the LB2=[0, 0, , custom character, , custom character, , custom character, , custom character], then the destination buffer DEST_BUF=[0, 0, , custom character, 0, , custom character, , custom character, , custom character, , custom character, , custom character, , custom character, , custom character]. More generally, if LB1=[B2, B4, B6, B8, . . .] and LB2=[B1, B3, B5, B7, . . .], then DEST_BUF=[B1, B2, B3, B4, B5, B6, B7, B8, . . .].

(224) Some hardware platforms, such as x86 and ARM, support direct interleave operation between two buffers (for example, via the operations unpacklo, unpackhi). Such operations can typically take two line buffers (e.g., LB1 and LB2) as input, interleave the data of the two lines buffers, and write the result into a destination buffer (e.g., DEST_BUF). As such, a codec implemented on such platforms, obtaining the DEST_BUF can be performed via the hardware instructions.

(225) At **1506**, the process **1500** calculates cumulative sums. In an implementation, the cumulative sums can be stored in a cumulative sums array, CUM_SUM. The cumulative sums are obtained over the destination buffer. The number of cumulative sums can be equal the total number of values in the destination buffer plus 1. The first cumulative sum value is zero and each subsequent cumulative sum value adds the subsequent value from the destination buffer. As such, the values of the cumulative sums array, CUM_SUM, can be calculated using the formula:

(226) $CUM_SUM[i + 1] = CUM_SUM[i] + DEST_BUF[i]$, where $CUM_SUM[0] = 0$.

(227) Using the above formula, the cumulative sums array can include the following values:

$$CUM_SUM[0] = 0$$

$$CUM_SUM[1] = 0 + B1$$

$$CUM_SUM[2] = 0 + B1 + B2$$

(228) $CUM_SUM[3] = 0 + B1 + B2 + B3$

$$CUM_SUM[4] = 0 + B1 + B2 + B3 + B4$$

.Math.

$$CUM_SUM[9] = 0 + B1 + B2 + B3 + B4 + .Math. + B9$$

.Math.

(229) At **1508**, the process **1500** determines a context index using the cumulative sums. The calculated context index can be used to determine the context. The context can be determined using a difference of two cumulative sums. Which two cumulative sums are used depends on the size of the template. In an case that the template size is $tz_size=5$, the context index of a value at index i of the current scan-order anti-diagonal line can be calculated using the formula:

(230) $Contextindex[i] = CUM_SUM[tz_size + 2(i - 1)] - CUM_SUM[2(i - 1)]$

(231) For example, for a template of size 5, Context Index[1] can be given by

$CUM_SUM[5] - CUM_SUM[0]$; Context Index[2] can be given by $CUM_SUM[7] - CUM_SUM[2]$;

Context Index[3] can be given by $CUM_SUM[9] - CUM_SUM[4]$; and so on.

(232) FIG. **16** is flowchart diagram of a process **1600** for coding a transform block of transform coefficients according to an implementation of this disclosure. The process **1600** can be implemented, for example, as a software program that may be executed by computing devices such as transmitting station **102** or receiving station **106**. The software program can include machine-readable instructions that may be stored in a memory such as the memory **204** or the secondary storage **214**, and that, when executed by a processor, such as CPU **202**, may cause the computing device to perform the process **1600**. The process **1600** may be implemented in whole or in part in the entropy encoding stage **408** of the encoder **400** and/or the entropy decoding stage **502** of the decoder **500**. The process **1600** can be implemented using specialized hardware or firmware. Multiple processors, memories, or both, may be used.

(233) At **1602**, the process **1600** identifies a lower plane. The lower plane can be as described above with respect to FIGS. **11-13**. That is, values of the lower plane code an “up-to” value for some of the transform coefficients of the transform block. In an implementation, the lower plane includes values for transform coefficients up to the last non-zero coefficient of the transform block.

(234) In the case of an encoder, create, form, produce, select, construct, determine, specify, generate, or other identify in any manner whatsoever. In the case of the encoder, the values of the lower plane are to be encoded in a encoded bitstream, such as the compressed bitstream **420** of

FIG. 4. In the case of a decoder, identify can mean identify the transform block for which the lower plane values are to be decoded.

(235) At **1604**, the process **1600** processes the lower plane according to a scan order. The scan can be the anti-diagonally aligned scan order as described above. The scan order can be the scan order of the example **1300**, as described with respect to FIG. **13**.

(236) At **1606**, the process **1600** selects a template for entropy-coding the values of the lower plane. The template indicates, for a to-be-coded value of the lower plane, scan positions of already coded values of the lower plane. The scan positions are arranged, in the template, in at least two template anti-diagonal lines. For example, the template can be the template **1088**, as described with respect to FIG. **12**. Accordingly, the template anti-diagonal lines can be the template anti-diagonal lines **1202**, **1204**.

(237) At **1608**, the process **1600** determines whether there are more values of the lower plane to code. If so, the process proceeds to **1610**; otherwise the process terminates at **1614**.

(238) At **1610**, the process selects, based on the template anti-diagonal lines, two or more line buffers. As used in this disclosure, “select” means to create, form, produce, identify, construct, determine, specify, generate, or other select in any manner whatsoever. Each of the two or more line buffers corresponds to a respective scan-order anti-diagonal line. For example, as described with respect to FIG. **13**, in coding values of the scan-order anti-diagonal line **13-6**, a first line buffer **LB1** corresponding to the scan-order anti-diagonal line **1310** is used and a second line buffer **LB2** corresponding to the scan-order anti-diagonal line **1308** are selected.

(239) At **1612**, the process **1600** determines a context using the two or more line buffers. As described above with respect to FIGS. **10A-10B** and FIG. **13**, the process **1600** determines a context index using the neighboring values identified by the template. The context index is determined using a combination of the values. In an implementation, the combination is the sum of the values. Using the context index, a context is identified, retrieved, accessed, or the like for coding the current value.

(240) At **1614**, the process **1600** codes the value using the determined context. After **1614**, the process **1600** proceeds back to **1608** to determine whether there are additional values to code.

(241) The process **1600** can additionally include an operation for coding a higher plane including residual coefficients. A maximum level can be associated with the lower plane and each residual coefficient of the higher plane corresponding to a respective non-zero transform coefficient of the transform block having an absolute value exceeding the maximum level.

(242) In an example of the process **1600**, the template includes five scan positions arranged along two template anti-diagonal lines. For example, the template can be the template **1088** of FIG. **12**. A first template anti-diagonal line (e.g., the template anti-diagonal line **1202**) includes at least two of the five scan positions and a second template anti-diagonal (e.g., the template anti-diagonal line **1204**) includes at least three scan positions. Each of the at least three scan positions are different from each of the at least two scan positions.

(243) In an example of the process **1600**, the template includes seven scan positions arranged along three template anti-diagonal lines. For example, the template can be the template **1070** of FIG. **10A**. A first template anti-diagonal line includes at least two scan positions of the seven scan positions, a second template anti-diagonal line includes at least three scan positions of the seven scan positions, and a third template anti-diagonal line includes at least four scan positions of the seven scan positions. Each of the at least two scan positions, the at least three scan positions, and the at least four scan positions are different scan positions.

(244) In yet another example, the process **1600** additionally includes maintaining, for coding values of a current scan-order anti-diagonal line, a first line buffer and a second line buffer. The first line buffer and the second line buffer can be as described with respect to FIG. **14**. As such, the first line buffer can correspond to a first scan-order anti-diagonal line scanned, using the backward scan order, immediately before the current anti-diagonal line; and the second line buffer corresponds to a

second scan-order anti-diagonal line scanned, using the backward scan order, immediately before the first anti-diagonal line. The process **1600** also includes, as described with respect to FIG. **14**, replacing, for coding coefficients of an immediately subsequent scan-order anti-diagonal line to the current scan-order anti-diagonal line, the second line buffer with the first line buffer and replace the first line buffer with a line buffer corresponding to the current anti-diagonal line.

(245) In yet another example, the process **1600** can include interleaving the first line buffer and the second line buffer in a destination buffer. The destination buffer can be used for determining the context for coding the current value. The destination buffer can be as described with respect to FIG. **15**.

(246) In an implementation of the process **1600**, determining the context for coding the current value using the destination buffer can include calculating a respective cumulative sum for each location of the destination buffer, and determining the context using a difference between a first cumulative sum and a second cumulative sum. The first cumulative sum and the second cumulative sum can be selected based on a position of the current value.

(247) For simplicity of explanation, the processes **600**, **900**, **1100**, **1400**, **1500**, and **1600** are each depicted and described as a series of blocks, steps, or operations. However, the blocks, steps, or operations in accordance with this disclosure can occur in various orders and/or concurrently. Additionally, other steps or operations not presented and described herein may be used. Furthermore, not all illustrated steps or operations may be required to implement a technique in accordance with the disclosed subject matter.

(248) The aspects of encoding and decoding described above illustrate some encoding and decoding techniques. However, it is to be understood that encoding and decoding, as those terms are used in the claims, could mean compression, decompression, transformation, or any other processing or change of data.

(249) The words “example” or “implementation” are used herein to mean serving as an example, instance, or illustration. Any aspect or design described herein as “example” or “implementation” is not necessarily to be construed as preferred or advantageous over other aspects or designs. Rather, use of the words “example” or “implementation” is intended to present concepts in a concrete fashion. As used in this application, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or”. That is, unless specified otherwise, or clear from context, “X includes A or B” is intended to mean any of the natural inclusive permutations. That is, if X includes A; X includes B; or X includes both A and B, then “X includes A or B” is satisfied under any of the foregoing instances. In addition, the articles “a” and “an” as used in this application and the appended claims should generally be construed to mean “one or more” unless specified otherwise or clear from context to be directed to a singular form. Moreover, use of the term “an implementation” or “one implementation” throughout is not intended to mean the same embodiment or implementation unless described as such.

(250) Implementations of transmitting station **102** and/or receiving station **106** (and the algorithms, methods, instructions, etc., stored thereon and/or executed thereby, including by encoder **400** and decoder **500**) can be realized in hardware, software, or any combination thereof. The hardware can include, for example, computers, intellectual property (IP) cores, application-specific integrated circuits (ASICs), programmable logic arrays, optical processors, programmable logic controllers, microcode, microcontrollers, servers, microprocessors, digital signal processors or any other suitable circuit. In the claims, the term “processor” should be understood as encompassing any of the foregoing hardware, either singly or in combination. The terms “signal” and “data” are used interchangeably. Further, portions of transmitting station **102** and receiving station **106** do not necessarily have to be implemented in the same manner.

(251) Further, in one aspect, for example, transmitting station **102** or receiving station **106** can be implemented using a general-purpose computer or general-purpose processor with a computer program that, when executed, carries out any of the respective methods, algorithms and/or

instructions described herein. In addition, or alternatively, for example, a special purpose computer/processor can be utilized which can contain other hardware for carrying out any of the methods, algorithms, or instructions described herein.

(252) Transmitting station **102** and receiving station **106** can, for example, be implemented on computers in a video conferencing system. Alternatively, transmitting station **102** can be implemented on a server and receiving station **106** can be implemented on a device separate from the server, such as a hand-held communications device. In this instance, transmitting station **102** can encode content using an encoder **400** into an encoded video signal and transmit the encoded video signal to the communications device. In turn, the communications device can then decode the encoded video signal using a decoder **500**. Alternatively, the communications device can decode content stored locally on the communications device, for example, content that was not transmitted by transmitting station **102**. Other transmitting station **102** and receiving station **106** implementation schemes are available. For example, receiving station **106** can be a generally stationary personal computer rather than a portable communications device and/or a device including an encoder **400** may also include a decoder **500**.

(253) Further, all or a portion of implementations of the present disclosure can take the form of a computer program product accessible from, for example, a tangible computer-usable or computer-readable medium. A computer-usable or computer-readable medium can be any device that can, for example, tangibly contain, store, communicate, or transport the program for use by or in connection with any processor. The medium can be, for example, an electronic, magnetic, optical, electromagnetic, or a semiconductor device. Other suitable mediums are also available.

(254) The above-described embodiments, implementations and aspects have been described in order to allow easy understanding of the present disclosure and do not limit the present disclosure. On the contrary, the disclosure is intended to cover various modifications and equivalent arrangements included within the scope of the appended claims, which scope is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structure as is permitted under the law.

Claims

1. A non-transitory computer-readable storage medium having stored thereon an encoded bitstream, the encoded bitstream decodable by a processor configured to execute instructions to: store, in a first line buffer, first values of a first scan-order diagonal line scanned immediately before a current scan-order diagonal line of a transform block; store, in a second line buffer, second values of a second scan-order diagonal line scanned immediately before the first scan-order diagonal line; interleave the first values of the first line buffer and the second values of the second line buffer in a destination buffer; select, using the destination buffer, a probability distribution for coding a current value of the current scan-order diagonal line; entropy decode, from the encoded bitstream, the current value using the probability distribution; and replace, for coding values of an immediately subsequent scan-order diagonal line to the current scan-order diagonal line, one of the second line buffer or the first line buffer with current values of the current scan-order diagonal line.
2. The non-transitory computer-readable storage medium of claim 1, wherein to interleave the first values of the first line buffer and the second values of the second line buffer in the destination buffer comprises to: use a hardware instruction to interleave the first values and the second values in the destination buffer.
3. The non-transitory computer-readable storage medium of claim 2, wherein the hardware instruction is one of `unpackhi` or `unpacklo`.
4. The non-transitory computer-readable storage medium of claim 2, wherein the processor is further configured to perform instructions to: calculate respective cumulative sums for at least some locations of the destination buffer.

5. The non-transitory computer-readable storage medium of claim 4, wherein to calculate the respective cumulative sums for the at least some locations of the destination buffer comprises to: add a destination buffer value at a location of the at least some locations of the destination buffer to a cumulative sum corresponding to an immediately preceding location of the destination buffer.
6. The non-transitory computer-readable storage medium of claim 5, wherein to determine, using the destination buffer, the probability distribution for coding the current value of the current scan-order diagonal line comprises to: calculate a difference between a first cumulative sum corresponding to a first location of the destination buffer and a second cumulative sum corresponding to a second location of the destination buffer, wherein the first cumulative sum and the second cumulative sum are selected based on a position of the current value; and determine the probability distribution using the difference.
7. The non-transitory computer-readable storage medium of claim 6, wherein a distance between the first location of the destination buffer and the second location of the destination buffer is related to a number of scan positions of already coded values of a template, wherein the template indicates, for a to-be-coded value, scan positions arranged, in the template, in at least two anti-diagonal lines.
8. A non-transitory computer-readable storage medium having stored thereon an encoded bitstream decodable by a processor configured to perform instructions to: select a template for entropy decoding values related to transform coefficients of a transform block, the template indicating, for a value to be decoded, scan positions of decoded values, the scan positions arranged, in the template, in at least two template anti-diagonal lines; decode the values related to the transform coefficients based on a scan order, the scan order traversing the values along scan-order anti-diagonal lines; maintain, for coding first values of the values related to the transform coefficients, a first line buffer and a second line buffer, wherein the first values are arranged along a current scan-order anti-diagonal line, wherein the first line buffer corresponds to a first scan-order anti-diagonal line scanned, based on the scan order, immediately before the current scan-order anti-diagonal line, and wherein the second line buffer corresponds to a second scan-order anti-diagonal line scanned, based on the scan order, immediately before the first scan-order anti-diagonal line; for a current value of the current scan-order anti-diagonal line: determine a context using the first line buffer and the second line buffer; and entropy decode, from the encoded bitstream, the current value using the context; and replace, for coding values of an immediately subsequent scan-order anti-diagonal line to the current scan-order anti-diagonal line, one of the second line buffer or the first line buffer with the current scan-order anti-diagonal line.
9. The non-transitory computer-readable storage medium of claim 8, wherein the processor is further configured to: interleave the first line buffer and the second line buffer in a destination buffer, wherein the destination buffer is used for determining contexts for coding values of the current scan-order anti-diagonal line.
10. The non-transitory computer-readable storage medium of claim 9, wherein the processor is further configured to: calculate a respective cumulative sum for each location of the destination buffer.
11. The non-transitory computer-readable storage medium of claim 10, wherein to calculate the respective cumulative sum for some location of the destination buffer comprises to: add a destination buffer value at the some location of the destination buffer to a cumulative sum corresponding to an immediately preceding location of the destination buffer.
12. The non-transitory computer-readable storage medium of claim 11, wherein to determine the context using the first line buffer and the second line buffer comprises to: determine the context using a difference between a first cumulative sum corresponding to a first location of the destination buffer and a second cumulative sum corresponding to a second location of the destination buffer, wherein the first cumulative sum and the second cumulative sum are selected based on a position of the current value.
13. The non-transitory computer-readable storage medium of claim 12, wherein a distance between

the first location of the destination buffer and the second location of the destination buffer is related to a number of the scan positions of already decoded values of the template.

14. The non-transitory computer-readable storage medium of claim 8, wherein the template comprises five scan positions arranged along two template anti-diagonal lines, wherein a first template anti-diagonal line includes at least two of the five scan positions and a second template anti-diagonal includes at least three scan positions, each of the at least three scan positions being different from each of the at least two of the five scan positions.

15. A non-transitory computer-readable storage medium having stored thereon an encoded bitstream generated by a processor configured to execute instructions to: select a scan order for traversing, along scan-order anti-diagonal lines, a block of values related to transform coefficients of a transform block; select a template for entropy coding the values related to the transform coefficients, the template indicating, for a to-be-coded value, scan positions of already coded values, the scan positions arranged, in the template, in at least two template anti-diagonal lines; maintain, for coding first values of the values related to the transform coefficients, wherein the first values are arranged along a current scan-order anti-diagonal line, a first line buffer and a second line buffer, wherein the first line buffer corresponds to a first scan-order anti-diagonal line scanned, using the scan order, immediately before the current scan-order anti-diagonal line, and wherein the second line buffer corresponds to a second scan-order anti-diagonal line scanned, using the scan order, immediately before the first scan-order anti-diagonal line; for a current value of the current scan-order anti-diagonal line: determine a context using the first line buffer and the second line buffer; and entropy encode, in the encoded bitstream, the current value using the context; and replace, for coding values of an immediately subsequent scan-order anti-diagonal line to the current scan-order anti-diagonal line, one of the second line buffer or the first line buffer with the current scan-order anti-diagonal line.

16. The non-transitory computer-readable storage medium of claim 15, wherein the processor is further configured to execute instructions to: interleave the first line buffer and the second line buffer in a destination buffer, wherein the destination buffer is used for determining contexts for coding values of the current scan-order anti-diagonal line.

17. The non-transitory computer-readable storage medium of claim 16, wherein the processor is further configured to execute instructions to: calculate a respective cumulative sum for each location of the destination buffer.

18. The non-transitory computer-readable storage medium of claim 17, wherein to calculate the respective cumulative sum for some location of the destination buffer comprises to: add a destination buffer value at the some location of the destination buffer to a cumulative sum corresponding to an immediately preceding location of the destination buffer.

19. The non-transitory computer-readable storage medium of claim 18, wherein to determine the context using the first line buffer and the second line buffer comprises to: determine the context using a difference between a first cumulative sum corresponding to a first location of the destination buffer and a second cumulative sum corresponding to a second location of the destination buffer, wherein the first cumulative sum and the second cumulative sum are selected based on a position of the current value.

20. The non-transitory computer-readable storage medium of claim 19, wherein a distance between the first location of the destination buffer and the second location of the destination buffer is related to a number of the scan positions of the already coded values of the template.
