

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279803

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Li; Weiguang et al.

Communication Apparatus, Communication Control Method, and Communication System

Abstract

An apparatus includes one or more channel groups, each group comprising a first coupler, first channels, and second couplers. The first coupler includes a first end and second ends. One end of each of the first channels is coupled to a corresponding one of the second ends, and the other end is coupled to a corresponding one of the second couplers. The first channel includes a first branch and a second branch. An impedance of the first branch is greater than an impedance of the second branch. The first channel is used to select the first branch or the second branch, to transmit a communication signal, so that a signal of a first channel connected to a source node or a destination node flows through a low-impedance branch, and a signal of a first channel not connected to the source node or the destination node flows through a high-impedance branch.

Inventors: Li; Weiguang (Dongguan, CN), Wu; Chao (Wuhan, CN), Pan; Dao (Dongguan, CN), Li; Yaqi (Dongguan, CN), Zhu; Weiwei (Dongguan, CN), Lin; Zefeng (Dongguan, CN)

Applicant: Huawei Technologies Co., Ltd. (Shenzhen, CN)

Family ID: 91068858

Appl. No.: 19/210180

Filed: May 16, 2025

Foreign Application Priority Data

CN

202211448416.0

Nov. 18, 2022

Related U.S. Application Data

parent WO continuation PCT/CN2023/103522 20230628 PENDING child US 19210180

Publication Classification

Int. Cl.: H04B3/54 (20060101); H04B3/04 (20060101)

U.S. Cl.:

CPC H04B3/54 (20130101); H04B3/04 (20130101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This is a continuation of International Patent Application No. PCT/CN2023/103522 filed on Jun. 28, 2023, which claims priority to Chinese Patent Application No. 202211448416.0 filed on Nov. 18, 2022. The disclosures of the aforementioned applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

[0002] The present disclosure relates to the field of communication technologies, and in particular, to a communication apparatus, a communication control method, and a communication system.

BACKGROUND

[0003] International Telecommunication Union-Telecommunication (ITU-T) Gigabit Home Networking (G.hn) is a point-to-multipoint (P2MP) wired communication technology used for a plurality of media such as a power line, a twisted pair, a coaxial cable, and a plastic optical fiber, and uses an orthogonal-frequency division multiplexing (OFDM) technology to modulate a signal on a wired medium for transmission. Other wired point-to-multipoint technologies further include a power line communication (PLC) technology like Homeplug, a coaxial cable-based technology like Multimedia over Coax Alliance (MoCA), and the like.

[0004] The Institute of Electrical and Electronics Engineers (IEEE) 802.3 (“Ethernet”) also defines various communication technologies based on various media, including a twisted pair medium. Common media of the Ethernet technology include twisted pair-based network cables such as Category 5 cables, Category 5e cables, and Category 6 cables. The Ethernet technology is mainly used for point-to-point communication, and also supports point-to-multipoint communication of carrier sense multiple access with collision detection (CSMA/CD).

[0005] A typical point-to-multipoint communication system includes a master node and a slave node, and usually includes one master node and a plurality of slave nodes. The master node usually establishes domain information on a device connected to an uplink base router. Other secondary routers or slave routers joins the established domain information as slave nodes to form a network.

[0006] Usually, in point-to-multipoint wired communication, the master node and the slave node are directly connected through a cable. In this case, a transmission rate between nodes is an important factor that affects communication effect.

SUMMARY

[0007] Embodiments of the present disclosure provide a communication apparatus, a communication control method, and a communication system, to improve a transmission rate between nodes.

[0008] To achieve the foregoing objective, the following technical solutions are used in the present disclosure.

[0009] According to a first aspect, an embodiment of the present disclosure provides a communication apparatus. The communication apparatus may be used in a wired communication system. For example, the communication apparatus is used in a point-to-multipoint communication system. The communication apparatus includes one or more channel groups. The channel group

includes a first coupler, a plurality of first channels, and a plurality of second couplers. The first coupler includes a first end and a plurality of second ends. One ends of the plurality of first channels are correspondingly coupled to the plurality of second ends, and the other ends of the plurality of first channels are correspondingly coupled to the plurality of second couplers. The first channel includes a first branch and a second branch, where an impedance of the first branch is greater than an impedance of the second branch, and the first channel is used to select to transmit, through the first branch, a communication signal transmitted by the communication apparatus, or transmit the communication signal through the second branch.

[0010] According to the communication apparatus provided in this embodiment of the present disclosure, the first channel includes the first branch and the second branch that have the different impedances, and the first channel has a function of selecting whether the communication signal flows through the first branch or the communication signal flows through the second branch. In this case, some (one or more) first channels may select to transmit the communication signal through the first branch, and some (one or more) first channels may select to transmit the communication signal through the second branch. However, the impedance of the first branch is greater than the impedance of the second branch. Therefore, signal power allocated to the first channel on which the communication signal flows through the first branch is low, and signal power allocated to the first channel on which the communication signal flows through the second branch is high. In this way, not all first channels are allocated equal signal power, so that lower signal power can be allocated to the first channel not connected to a source node or a destination node, and higher signal power can be allocated to the first channel connected to the source node or the destination node, to improve a transmission rate of the first channel connected to the source node or the destination node, thereby increasing a transmission rate between two nodes coupled to two ends of the first channel. In addition, each first channel may dynamically switch, based on an application scenario, whether the communication signal flows through the first branch or the second branch, to implement dynamic allocation of the signal power. In this case, the first channel connected to the source node or the destination node at each moment may select the communication signal to flow through the second branch, to obtain higher signal power through allocation, so that the first channel connected to the source node or the destination node at each moment may have a higher transmission rate.

[0011] In a possible implementation, an inductive reactance of the first branch is greater than an inductive reactance of the second branch. An inductor or a ferrite bead has a feature of allowing a low frequency to pass through and blocking a high frequency. Therefore, a larger inductive reactance is set on the first branch to enable the first branch to have the larger impedance, and in a case in which the impedance of the first branch is greater than the impedance of the second branch, a low-frequency signal in the communication signal may be transmitted through the first branch in this manner. This helps a communication device perform sensing, to obtain a communication status of the first channel.

[0012] In a possible implementation, a resistance of the first branch is greater than a resistance of the second branch. In this way, a structure of the first channel is simple, and costs are low.

[0013] In a possible implementation, a capacitive reactance of the first branch is greater than a capacitive reactance of the second branch. In this way, the structure of the first channel is simple, and the costs are low.

[0014] In a possible implementation, the first branch includes a first passive circuit, the second branch includes a second passive circuit, and the first channel further includes a first switching circuit. The first passive circuit and the second passive circuit are connected in parallel, and are connected in series to the first switching circuit; and an impedance of the first passive circuit is greater than an impedance of the second passive circuit. The first switching circuit is configured to: select, based on a first control signal, the first passive circuit to communicate with the second coupler, or select, based on a first control signal, the second passive circuit to communicate with

the second coupler. Passive circuits are disposed on the first branch and the second branch to adjust the impedances of the first branch and the second branch, which is simple in structure and is easy to implement.

[0015] In a possible implementation, the first branch includes a first passive circuit, the second branch includes a second passive circuit, and the first channel further includes a first switching circuit. The first passive circuit and the second passive circuit are connected in parallel, and are connected in series to the first switching circuit; and an impedance of the first passive circuit is greater than an impedance of the second passive circuit, or an inductive reactance of the first passive circuit is greater than an inductive reactance of the second passive circuit. The first switching circuit is configured to: select, based on a first control signal, the first passive circuit to communicate with the second coupler, or select, based on a first control signal, the second passive circuit to communicate with the second coupler. Passive circuits are disposed on the first branch and the second branch to adjust the impedances of the first branch and the second branch, which is simple in structure and is easy to implement.

[0016] In a possible implementation, the communication apparatus further includes a controller, and the controller is configured to output the first control signal.

[0017] In a possible implementation, the first passive circuit includes at least one of a resistor, a capacitor, an inductor, or a ferrite bead. This is an implementation with a simple structure.

[0018] In a possible implementation, the second passive circuit includes a signal line. This is an implementation with a simple structure.

[0019] In a possible implementation, the channel group further includes a second channel, the second channel includes a third coupler, and the third coupler is coupled to the first end. The third coupler is disposed in the communication apparatus, so that the communication apparatus not only has a capability of transmitting a signal from the first coupler side to the second coupler side, but also has a capability of transmitting a signal from the second coupler side to the first coupler side. In other words, the communication apparatus has a bidirectional transmission capability. In addition, because the first channel includes the first branch and the second branch that have the different impedances, by adjusting and controlling a flow path of the communication signal, the first channel connected to the source node or the destination node may have a smaller impedance, and the first channel not connected to the source node or the destination node may have a larger impedance. In this way, when the communication apparatus performs bidirectional transmission, signal power in a communication path is always the highest, and a transmission rate can be improved.

[0020] In a possible implementation, the second channel further includes a third passive circuit, a fourth passive circuit, and a second switching circuit. The third passive circuit and the fourth passive circuit are connected in parallel, and are coupled in series to the second switching circuit between the third coupler and the first end; and an impedance of the third passive circuit is greater than an impedance of the fourth passive circuit, or an inductive reactance of the third passive circuit is greater than an inductive reactance of the fourth passive circuit. The second switching circuit is configured to: select, based on a second control signal, the third passive circuit to communicate with the first end, or select, based on a second control signal, the fourth passive circuit to communicate with the first end. The third coupler, the third passive circuit, the fourth passive circuit, and the second selection circuit are disposed in the communication apparatus, so that the communication apparatus not only has the capability of transmitting the signal from the first coupler side to the second coupler side, but also has the capability of transmitting the signal from the second coupler side to the first coupler side, and further has energy of transmitting a signal from a second coupler side to another second coupler side. In addition, the first channel includes the first branch and the second branch that have the different impedances. The flow path of the communication signal is adjusted and controlled, so that the first channel connected to the source node or the destination node can have the smaller impedance, and the first channel not

connected to the source node or the destination node can have the larger impedance. The second channel includes the third passive circuit and the fourth passive circuit that have the different impedances. The flow path of the communication signal is adjusted and controlled, so that when the communication signal flows through the third coupler, the second channel can have a smaller impedance, and when the communication signal does not flow through the third coupler, the second channel can have a larger impedance. In this way, when the communication apparatus performs transmission, a communication loop is always a normal loop, and another branch is always a high-impedance loop, to ensure that the signal power in the communication path is always the highest, and the transmission rate can be improved.

[0021] In a possible implementation, the first coupler further includes a third end, and the third end is coupled in series to a fifth passive circuit. This is a possible transmission manner.

[0022] In a possible implementation, the communication apparatus includes two parallel channel groups. In this way, the communication apparatus is not only applicable to a single-input single-output data transmission mode, but also applicable to a multiple-input multiple-output data transmission mode, and has a wide application scope.

[0023] In a possible implementation, the communication apparatus is integrated into an endpoint (EP) device, a tail end node device, a domain master (DM) device, or a central coordinator (CCO) device. In this way, an architecture of a communication system can be simplified.

[0024] According to a second aspect, an embodiment of the present disclosure provides a communication apparatus, including a channel group. The channel group includes a first coupler, a third channel, a fourth channel, and a plurality of second couplers. The first coupler includes a first end and a plurality of second ends. The third channel is coupled between the second end and the second coupler, the fourth channel is coupled between the second end and the second coupler, and the second end and the second coupler that are coupled to the third channel are different from the second end and the second coupler that are coupled to the fourth channel. An impedance of the third channel is greater than an impedance of the fourth channel. The communication apparatus provided in this embodiment of the present disclosure includes the third channel and the fourth channel. However, the impedances of the third channel and the fourth channel are unequal.

Therefore, signal power allocated to the third channel and the fourth channel is also unequal. In a case in which transmit power is fixed, the signal power allocated to the fourth channel with the smaller impedance is higher than the signal power allocated to the third channel with the larger impedance, thereby implementing fixed allocation of the signal power. In this way, a signal transmission rate on the fourth channel can be improved.

[0025] In a possible implementation, the channel includes a sixth passive circuit, the fourth channel includes a signal line, and an impedance of the sixth passive circuit is greater than an impedance of the signal line, or an inductive reactance of the sixth passive circuit is greater than an inductive reactance of the signal line. This is an implementation with a simple structure.

[0026] In a possible implementation, the channel group further includes a third coupler, and the third coupler is coupled to the first end. The third coupler is disposed in the communication apparatus, so that the communication apparatus not only has a capability of transmitting a signal from the first coupler side to the second coupler side, but also has a capability of transmitting a signal from the second coupler side to the first coupler side. In other words, the communication apparatus has a bidirectional transmission capability.

[0027] According to a third aspect, an embodiment of the present disclosure provides a communication system. The communication system includes a first device and a plurality of second devices, and the plurality of second devices are coupled to the first device through first cables respectively. The first device includes a communication apparatus, and the communication apparatus is the communication apparatus according to either the first aspect or the second aspect.

[0028] The communication system provided in this embodiment of the present disclosure includes the communication apparatus according to the first aspect or the second aspect. Beneficial effect of

the communication system is the same as beneficial effect of the communication apparatus.

[0029] In a possible implementation, the communication system further includes a third device, and the third device is coupled to the first device through a second cable.

[0030] In a possible implementation, the communication apparatus includes two parallel channel groups, and the second device is coupled to the first device through two first cables.

[0031] According to a fourth aspect, an embodiment of the present disclosure provides a communication control method, applied to a communication apparatus, where the communication apparatus includes the communication apparatus according to any implementation of the first aspect. The communication control method includes: A communication signal received by the communication apparatus and a communication signal sent by the communication apparatus are transmitted through first channels; a first channel used to connect to a source node and a destination node selects to transmit the communication signal through a first branch; and a first channel not used to connect to the source node and the destination node selects to transmit the communication signal through a second branch.

[0032] The communication control method provided in this embodiment of the present disclosure is applied to the communication apparatus according to the first aspect. Beneficial effect of the communication control method is the same as beneficial effect of the communication apparatus.

[0033] In a possible implementation, the communication control method further includes: The communication signal is transmitted through second channels; and the second channel selects, based on a second control signal, the communication signal to be transmitted through a third passive circuit, or selects, based on a second control signal, the communication signal to be transmitted through a fourth passive circuit.

[0034] In a possible implementation, when a second channel is used to connect to the source node or the destination node, the second control signal sent by a controller to the second channel controls a second switching circuit to select the communication signal to be transmitted through the fourth passive circuit; and when a second channel is not used to connect to the source node or the destination node, the second control signal sent by the controller to the second channel controls the second switching circuit to select the communication signal to be transmitted through the third passive circuit.

[0035] In a possible implementation, the communication control method further includes: A first coupler receives the communication signal sent by the source node, and one of a plurality of second couplers outputs the communication signal to the destination node; and the first channel used to connect to the destination node is obtained.

[0036] In a possible implementation, the communication control method further includes: One of a plurality of second couplers receives the communication signal sent by the source node, a first coupler outputs the communication signal to the destination node, and the controller obtains the first channel used to connect to the source node.

[0037] In a possible implementation, the communication control method further includes: One of a plurality of second couplers receives the communication signal, and another of the plurality of second couplers outputs the communication signal; and the controller obtains the first channel used to connect to the source node and the first channel used to connect to the destination node.

[0038] In a possible implementation, the controller senses a signal frame, and obtains the first channel used to connect to the source node and the first channel used to connect to the destination node.

[0039] According to a fifth aspect, an embodiment of the present disclosure provides a computer-readable storage medium. The computer-readable storage medium stores computer program code, and when the instructions are run on a computer, the computer is enabled to perform the communication control method according to the fourth aspect.

[0040] According to a sixth aspect, an embodiment of the present disclosure provides a computer

program product. When the computer program product is run on a computer, the computer is enabled to perform the communication control method according to the fourth aspect.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0041] FIG. 1 is a diagram of a point-to-multipoint system in one-to-many star networking according to an embodiment of the present disclosure;

[0042] FIG. 2 is a diagram of an architecture of a communication apparatus according to an embodiment of the present disclosure;

[0043] FIG. 3 is a diagram of an architecture of a communication system according to an embodiment of the present disclosure;

[0044] FIG. 4 is a schematic of a topology structure of a communication system according to an embodiment of the present disclosure;

[0045] FIG. 5 is a schematic of a topology structure of another communication system according to an embodiment of the present disclosure;

[0046] FIG. 6 is a schematic of a topology structure of still another communication system according to an embodiment of the present disclosure;

[0047] FIG. 7 is a schematic of a topology structure of yet another communication system according to an embodiment of the present disclosure;

[0048] FIG. 8 is a schematic of a topology structure of still yet another communication system according to an embodiment of the present disclosure;

[0049] FIG. 9A is a diagram of an architecture of another communication system according to an embodiment of the present disclosure;

[0050] FIG. 9B is a schematic of a topology structure of a further communication system according to an embodiment of the present disclosure;

[0051] FIG. 10A is a diagram of an architecture of still another communication system according to an embodiment of the present disclosure;

[0052] FIG. 10B is a diagram of an architecture of yet another communication system according to an embodiment of the present disclosure;

[0053] FIG. 11A is a schematic of a topology structure of a still further communication system according to an embodiment of the present disclosure;

[0054] FIG. 11B is a schematic of a topology structure of a yet further communication system according to an embodiment of the present disclosure;

[0055] FIG. 12 is a schematic of a topology structure of a communication apparatus according to an embodiment of the present disclosure;

[0056] FIG. 13 is a schematic of a topology structure of another communication apparatus according to an embodiment of the present disclosure; and

[0057] FIG. 14 is a schematic of a topology structure of still yet another communication apparatus according to an embodiment of the present disclosure.

DESCRIPTION OF EMBODIMENTS

[0058] The following describes technical solutions in embodiments of the present disclosure with reference to accompanying drawings in embodiments of the present disclosure. It is clear that the described embodiments are merely a part rather than all of embodiments of the present disclosure.

[0059] Terms such as “first” and “second” below are merely for ease of description, and shall not be understood as an indication or implication of relative importance or implicit indication of a quantity of indicated technical features. Therefore, a feature limited by “first”, “second”, or the like may explicitly or implicitly include one or more features. In the descriptions of the present disclosure, unless otherwise stated, “a plurality of” means two or more.

[0060] In addition, in embodiments of the present disclosure, orientation terms such as “up”, “down”, “left”, and “right” may include but are not limited to orientations of schematically placed components in relative accompanying drawings. It should be understood that these orientation terms may be relative concepts. The orientation terms are used for relative description and clarification, and may vary correspondingly based on a change in an orientation in which the component is placed in the accompanying drawings.

[0061] In embodiments of the present disclosure, unless otherwise clearly specified and limited, a term “connection” should be understood in a broad sense. For example, the “connection” may be a fixed connection, a detachable connection, an integral connection, may be a direct connection, or an indirect connection implemented through an intermediate medium. In addition, a term “coupling” may be a direct electrical connection, or may be an indirect electrical connection through an intermediate medium. A term “contact” may be direct contact or indirect contact through an intermediate medium.

[0062] In embodiments of the present disclosure, a term “and/or” describes an association relationship between associated objects and indicates that three relationships may exist. For example, A and/or B may indicate the following cases: Only A exists, both A and B exist, and only B exists, where A and B may be singular or plural. A character “/” usually indicates an “or” relationship between the associated objects.

[0063] Before embodiments of the present disclosure are described, technical terms and background technologies in the present disclosure are described first.

[0064] Domain master (DM): usually configures a device communicating with an uplink base routing device as a domain management mode, and establishes domain information. The device communicating with the uplink base routing device may be referred to as a domain management device, and another secondary routing device or slave routing device joins the domain to form a network.

[0065] Endpoint (EP): The another secondary routing device or slave routing device that joins the domain may be referred to as an endpoint device.

[0066] Single-input single-output (SISO): is a communication manner in which a transmit antenna and a receive antenna are used at a transmit end and a receive end respectively, so that signals are transmitted and received through the antennas at the transmit end and the receive end.

[0067] Multiple-input multiple-output (MIMO): is a communication manner in which a plurality of transmit antennas and a plurality of receive antennas are used at the transmit end and the receive end respectively, so that signals are transmitted and received through the plurality of antennas at the transmit end and the receive end, thereby improving communication quality.

[0068] Signal-to-noise ratio (SNR): is a ratio of a signal to noise in an electronic device or an electronic system. The signal is an electronic signal that comes from the outside of the device and that needs to be processed by the device, the noise is an irregular extra signal (or information) that does not exist in an original signal that is generated after the electronic signal passes through the device, and the signal does not change as the original signal changes.

[0069] Embodiments of the present disclosure provide a communication system, to implement point-to-multipoint transmission/communication. For example, the communication system is a point-to-multipoint (P2MP) wired communication system.

[0070] A typical P2MP communication system includes a master node and a slave node, and usually includes one master node and a plurality of slave nodes, for example, a master node domain master and a slave node endpoint defined in the G.hn protocol, or a master node CCO and a slave node station defined in the Homeplug protocol. The domain master is usually configured as a DM mode in a device connected to an uplink base router, to establish domain information. Another secondary router or slave router joins the domain as an EP to form a network. Similarly, the central coordinator is configured as a CCO mode in a device connected to an uplink base router, to establish domain information. Another secondary router or slave router joins the domain as a STA

to form a network.

[0071] An example P2MP system is shown. As shown in FIG. 1, the P2MP system includes a DM and a plurality of endpoints. In FIG. 1, an example in which the P2MP system includes an endpoint EP 1, an endpoint EP 2, an endpoint EP 3, . . . , and an endpoint EP n is used for description. The DM and the endpoints are directly connected through cables to form star topology networking, to implement P2MP wired communication.

[0072] For the P2MP wired communication, when a networking manner is star networking, because the P2MP communication is used, only one of the plurality of endpoints is in communication at a same moment. However, in this case, other endpoints are still used as loads and connected to a star bus. These endpoints that are used as the loads still consume energy, resulting in waste. As a result, signal strength of the endpoint that is in communication is not enough, which affects an SNR, and finally causes a problem of a low transmission rate.

[0073] To resolve a problem in the P2MP communication that the transmission rate of the endpoint is reduced because signal power of the endpoint that is in communication currently is not enough due to energy consumption of the load connected to the star bus, embodiments of the present disclosure provide a communication apparatus, to reallocate power consumption on the star bus, to resolve the problem of energy consumption by the load.

[0074] In some embodiments, the communication system is applicable to the Homeplug protocol, and the communication apparatus is coupled to a CCO device and/or a tail end node device in the communication system.

[0075] In some other embodiments, the communication system is applicable to the Homeplug protocol, and the communication apparatus is integrated into the CCO device and/or the tail end node device in the communication system.

[0076] In still some embodiments, the communication system is applicable to the G.hn protocol, and the communication apparatus is coupled to a DM device and/or an EP device in the communication system.

[0077] In still some embodiments, the communication system is applicable to the G.hn protocol, and the communication apparatus is integrated into the DM device and/or the EP device in the communication system.

[0078] Certainly, the communication system may also be applicable to another protocol, provided that the communication apparatus is coupled to a master node and/or a slave node in the communication system.

[0079] In embodiments of the present disclosure, an example in which the communication system includes the DM device and the EP device is used for description. Certainly, the DM device may be replaced with the CCO device, and the EP device may be replaced with the tail end node device.

[0080] For a structure of a communication apparatus 1, as shown in FIG. 2, the communication apparatus 1 includes one or more channel groups. In FIG. 2, an example in which the communication apparatus 1 includes one channel group is used for description.

[0081] Still refer to FIG. 2. The channel group includes a first coupler 10, a plurality of first channels 20, and a plurality of second couplers 30.

[0082] In this embodiment of the present disclosure, the first coupler 10 includes a first end 11 and a plurality of second ends 12. It may be understood that, for clear description in this embodiment of the present disclosure, an example in which a cable outlet of the first end 11 faces a left side of the first coupler 10, and a cable outlet of the second end 12 faces a right side of the first coupler 10 is used for description. However, in a winding layout structure of the first coupler 10, directions of the cable outlets of the first end 11 and the second end 12 are not limited, provided that the cable outlets of the first end 11 and the second end 12 are properly disposed based on the layout structure. In the communication apparatus 1, a structure coupled to the first end 11 is different from a structure coupled to the second end 12. With reference to the following descriptions, the first end 11 and the second end 12 of the first coupler 10 may be defined through the coupled structures.

[0083] In some embodiments, a quantity of second ends **12** is the same as a quantity of first channels **20** and a quantity of second couplers **30**. For example, the communication apparatus **1** includes m first channels **20**, m second couplers **30**, and m second ends **12**.

[0084] One ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second ends, and the other ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second couplers **30**. Alternatively, it is understood as that the plurality of first channels **20** are correspondingly coupled between the plurality of second ends **12** and the plurality of second couplers **30**.

[0085] Each first channel **20** has one end and the other end, which are referred to as a first end of the first channel **20** and a second end of the first channel **20** in this example. In this case, the one ends of the plurality of first channels **20** are a plurality of first ends of the plurality of first channels **20**, and the second ends of the plurality of first channels **20** are a plurality of second ends of the plurality of first channels **20**. The plurality of first ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second ends **12** of the first coupler **10**, and the plurality of first ends of the plurality of first channels **20** are in a one-to-one correspondence with the plurality of second ends **12** of the first coupler **10**. The plurality of second ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second couplers **30**, and the plurality of second ends of the plurality of first channels **20** are in a one-to-one correspondence with the plurality of second couplers **30**. The plurality first channels **20** shown in a topology structure shown in FIG. 2 are placed in parallel. However, in an actual layout, the plurality first channels **20** are not limited to be placed in parallel, provided that the plurality first channels **20** are properly placed based on a requirement.

[0086] In some embodiments, the first channel **20** includes a first branch **21** and a second branch **22**, and an impedance of the first branch **21** is greater than an impedance of the second branch **22**.

[0087] The impedance is a physical quantity that indicates performance of an element or electrical performance of a circuit. The impedance is a ratio of a peak voltage (U_m) (or valid value) at two ends of a passive circuit in an alternating current circuit to a peak current (I_m) (or valid value) passing through the circuit, and the impedance is indicated by z and a unit is ohm (Ω). When a value of U is fixed, a larger value of z indicates a smaller value of I , and the impedance limits the current. The impedance (electrical impedance), also referred to as an electrical impedance, and is a collective name of blocking effect of a resistor, an inductor, and a capacitor on an alternating current in the circuit. The impedance is a complex number. A real part is referred to as a resistance, and an imaginary part is referred to as a reactance. The blocking effect of the capacitor on the alternating current in the circuit is referred to as a capacitive reactance, the blocking effect of the inductor on the alternating current in the circuit is referred to as an inductive reactance, and the capacitive reactance and the inductive reactance are collectively referred to as the reactance.

[0088] In this embodiment of the present disclosure, the impedance of the first branch **21** may be an impedance between the first coupler **10** and the second coupler **30**. Similarly, the impedance of the second branch **22** may be an impedance between the first coupler **10** and the second coupler **30**.

[0089] In some embodiments, the impedance of the first branch **21** is far greater than the impedance of the second branch **22**. For example, the first branch **21** is a high-impedance branch, and the second branch **22** is a signal line straight-through path. Alternatively, for example, the impedance of the first branch **21** is more than five times the impedance of the second branch **22**. For example, the impedance of the first branch **21** is 10 times, 15 times, 20 times, 30 times, 50 times, and above the impedance of the second branch **22**.

[0090] In some other embodiments, an inductive reactance of the first branch **21** is greater than an inductive reactance of the second branch **22**.

[0091] The first channel **20** is used to select to transmit, through the first branch **21**, a communication signal transmitted by the communication apparatus **1**, or transmit the communication signal through the second branch **22**.

[0092] In other words, in this embodiment of the present disclosure, for the first channel **20**, the communication signal is transmitted either through the first branch **21** or through the second branch **22**. For example, for the first channel **20** connected to a source node or a destination node, the communication signal is transmitted through the second branch **22**. For the first channel **20** not connected to the source node or the destination node, the communication signal is transmitted through the first branch **21**.

[0093] Certainly, a flow direction of the signal is not limited in this embodiment of the present disclosure. For example, the communication signal may be output after flowing to the second coupler **30** through the first channel **20**, or the second coupler **30** may receive the communication signal and transmit the communication signal in a direction away from the second coupler **30** through the first channel **20**.

[0094] According to the communication apparatus **1** provided in this embodiment of the present disclosure, the first channel **20** includes the first branch **21** and the second branch **22** that have the different impedances, and the first channel **20** has a function of selecting whether the communication signal flows through the first branch **21** or the communication signal flows through the second branch **22**. In this case, some (one or more) first channels **20** may select to transmit the communication signal through the first branch **21**, and some (one or more) first channels **20** may select to transmit the communication signal through the second branch **22**. However, the impedance of the first branch **21** is greater than the impedance of the second branch **22**. Therefore, signal power allocated to the first channel **20** on which the communication signal flows through the first branch **21** is low, and signal power allocated to the first channel **20** on which the communication signal flows through the second branch **22** is high. In this way, not all first channels **20** are allocated equal signal power, so that lower signal power can be allocated to the first channel **20** not connected to the source node or the destination node, and higher signal power can be allocated to the first channel **20** connected to the source node or the destination node, to improve a transmission rate of the first channel **20** connected to the source node or the destination node, thereby increasing a transmission rate between two nodes coupled to two ends of the first channel **20**. In addition, each first channel **20** may dynamically switch, based on an application scenario, whether the communication signal flows through the first branch **21** or the second branch **22**. In this case, the first channel **20** connected to the source node or the destination node at each moment may select the communication signal to flow through the second branch **22**, to obtain higher signal power through allocation, so that the first channel **20** connected to the source node or the destination node at each moment may have a higher transmission rate.

[0095] The following uses several examples to schematically describe the communication apparatus, a communication control method of the communication apparatus, and a communication system to which the communication apparatus is applied that are provided in embodiments of the present disclosure.

EXAMPLE 1

[0096] As shown in FIG. **3**, an embodiment of the present disclosure provides a communication system. The communication system includes a first device **100**, a plurality of second devices **200**, and a third device **300**.

[0097] The communication system provided in this embodiment of the present disclosure may be, for example, a P2MP communication system or another wired communication system, for example, a wired communication system based on a network cable, a twisted pair, a power line, and a direct current power supply cable.

[0098] The first device **100** has a first port **110** and a plurality of second ports **120**, and the plurality of second devices **200** are coupled to the first device **100** through first cables **400** respectively. In other words, the plurality of second devices **200** are correspondingly coupled to the plurality of second ports **120** through a plurality of first cables **400**, and the second devices **200** are in a one-to-one correspondence with the second ports **120**.

[0099] Certainly, the first device **100** may further include a port used for another function. This is not limited in this embodiment of the present disclosure. This embodiment of the present disclosure merely shows the first port **110** and the second port **120**.

[0100] The third device **300** is coupled to the first port **110** of the first device **100** through a second cable **500**.

[0101] In the communication system shown in FIG. 3, the first device **100** may be understood as an intermediate transmission medium, and the third device **300** completes communication with the second device **200** through the first device **100**.

[0102] The first cable **400** and the second cable **500** may be, for example, a power line, a network cable, a twisted pair, or a direct current power supply cable.

[0103] In some embodiments, the third device **300** is a DM device, and the second device **200** is an EP device. The DM described below may be understood as the DM device in the communication system. The EP may be understood as the EP device in the communication system.

[0104] In some embodiments, the first device **100** includes a communication apparatus **1** provided in this embodiment of the present disclosure. The communication apparatus **1** reallocates signal power on a communication path, to increase a transmission rate of the second device **200** that is in communication.

[0105] In terms of a structure of the communication apparatus **1**, in some embodiments, the communication apparatus **1** uses a SISO data transmission mode.

[0106] As shown in FIG. 4, the communication apparatus **1** includes a channel group. The channel group includes a first coupler **10**, a plurality of first channels **20**, and a plurality of second couplers **30**.

[0107] The first coupler **10** includes a first end **11** and a plurality of second ends **12**. One ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second ends, and the other ends of the plurality of first channels **20** are correspondingly coupled to the plurality of second couplers **30**.

[0108] For example, the first coupler **10** is a combiner, and the first coupler **10** is configured to convert one path of signal into a plurality of paths of signals. For example, the first coupler **10** includes a first coil **L1** and a plurality of second coils **L2**, two ends of the first coil **L1** are coupled to the first end **11** of the first combiner **10**, and two ends of the second coil **L2** are coupled to the second end **12** of the first combiner **10**. The first coil **L1** is magnetically coupled to the second coil **L2**, and the plurality of second coils **L2** may also be electromagnetically coupled to each other. In some embodiments, a quantity of turns of the first coil **L1** is different from a quantity of turns of the second coil **L2**, and a signal amplitude can be amplified or reduced by adjusting a ratio of the quantity of turns of the first coil **L1** to the quantity of turns of the second coil **L2**.

[0109] For example, the second coupler **30** includes a third coil **L3** and a fourth coil **L4** that are magnetically coupled, two ends of the third coil **L3** are coupled to the first channel **20**, and two ends of the fourth coil **L4** are coupled to an external port of the communication apparatus **1**. The second coupler **30** is configured to couple a received signal to the first cable **400** for transmission.

[0110] The first channel **20** includes a first branch **21** and a second branch **22**, and an impedance of the first branch **21** is greater than an impedance of the second branch **22**. The first channel **20** is used to select to transmit, through the first branch **21**, a communication signal transmitted by the communication apparatus **1**, or transmit the communication signal through the second branch **22**.

[0111] Therefore, the first branch **21** presents a high resistance to the communication signal, and the second branch **22** presents a low resistance to the communication signal. Alternatively, the signal transmitted by the communication apparatus **1** is a broadband signal, and the first branch **21** has different passage and resistance degrees for different frequency bandwidths. For example, the first branch **21** presents the high resistance to signals of some frequency bandwidths, and presents the low resistance to signals of some frequency bandwidths.

[0112] In some embodiments, an inductive reactance of the first branch **21** is greater than an

inductive reactance of the second branch **22**.

[0113] An inductor or a ferrite bead has a feature of allowing a low frequency to pass through and blocking a high frequency. Therefore, a larger inductive reactance is set on the first branch **21** to enable the first branch **21** to have the larger impedance, and in a case in which the impedance of the first branch **21** is greater than the impedance of the second branch **22**, a low-frequency signal in the communication signal may be transmitted through the first branch **21** in this manner. This helps a communication device perform sensing, to obtain a communication status of the first channel **20**.

[0114] In some embodiments, a resistance of the first branch **21** is greater than a resistance of the second branch **22**. In this way, a structure of the first channel **20** is simple, and costs are low.

[0115] In some embodiments, a capacitive reactance of the first branch **21** is greater than a capacitive reactance of the second branch **22**. In this way, the structure of the first channel **20** is simple, and the costs are low.

[0116] In terms of the structure of the first channel **20**, in some embodiments, the first branch **21** includes a first passive circuit, the second branch **22** includes a second passive circuit, and the first channel **20** further includes a first switching circuit **23**.

[0117] The first passive circuit and the second passive circuit are connected in parallel, and are connected in series to the first switching circuit **23**; and an impedance of the first passive circuit is greater than an impedance of the second passive circuit.

[0118] In some embodiments, the first passive circuit includes one or more of, for example, a resistor, an inductor, a ferrite bead, and a capacitor.

[0119] In some embodiments, the second passive circuit includes one or more of, for example, the resistor, the inductor, the ferrite bead, and the capacitor.

[0120] Types of passive components included in the first passive circuit and the second passive circuit may be the same, provided that the impedance of the first passive circuit is greater than the impedance of the second passive circuit.

[0121] For example, the first passive circuit and the second passive circuit each include a resistor, and a resistance value of a first resistor included in the first passive circuit is greater than a resistance value of a second resistor included in the second passive circuit.

[0122] In some other embodiments, the second passive circuit includes a signal line, and the second passive circuit is a straight-through path (or referred to as a signal normal loop).

[0123] In this embodiment of the present disclosure, an example in which the first branch **21** includes the first passive circuit, the first branch **21** is a signal high-impedance path, the second branch **22** includes a signal line, and the second branch **22** is a signal low-impedance path is used for description.

[0124] In some embodiments, an inductive reactance of the first passive circuit is greater than an inductive reactance of the second passive circuit.

[0125] For example, the first passive circuit and the second passive circuit each include only an inductor, or the first passive circuit includes an inductor, and the second passive circuit includes a signal line.

[0126] In this embodiment of the present disclosure, the first switching circuit **23** is configured to: select, based on a first control signal, the first passive circuit to communicate with the second coupler **30**, or select, based on a first control signal, the second passive circuit to communicate with the second coupler **30**.

[0127] For example, the first switching circuit **23** includes a two-input one-output selector switch, where a fixed end of the selector switch is coupled to the second device **30**, a selection end of the selector switch is coupled to the first passive circuit or the second passive circuit, and a control end of the selector switch is configured to receive the first control signal.

[0128] For example, if the first control signal controls the selector switch to be in an off state F, the communication signal flows in the first branch **21**. In this case, a corresponding loop is referred to as a high-impedance loop. If the first control signal controls the selector switch to be in the on state

O, the communication signal flows in the second branch **22**. In this case, a corresponding loop is referred to as a normal loop.

[0129] Certainly, the communication signal may alternatively flow in the first branch **21** when the first control signal controls the selector switch to be in the on state O. The communication signal may alternatively flow in the second branch **22** when the first control signal controls the selector switch to be in the off state F.

[0130] Alternatively, for example, the first switching circuit **23** is a three-input one-output selector switch, and the selection end of the selector switch may further choose to communicate with another device (for example, the Ethernet), to transmit a communication signal of the another device to the second device **200**.

[0131] Certainly, that the first switching circuit **23** is connected in series to the first passive circuit (or the second passive circuit) may be shown in FIG. **4**. The first switching circuit **23** is coupled to the second end **12** of the first coupler **10**, and the first passive circuit is coupled to the second coupler **30**. Alternatively, the first switching circuit **23** may be coupled to the second coupler, and the first passive circuit may be coupled to the second end **12** of the first coupler **10**.

[0132] In some embodiments, the communication apparatus **1** further includes a controller, and the controller is configured to output the first control signal.

[0133] When the communication apparatus **1** is used in the communication system, the third device **300** sends a communication signal (for example, a signal source generated by a demodulation chip). The signal source may be, for example, differential signals, including a differential signal P and a differential signal N. The differential signal P and the differential signal N are a pair of differential signals having a same frequency and opposite phases. The communication signal sent by the third device **300** is transmitted to the communication apparatus **1** through the second cable **500**. The first coupler **10** couples the communication signal to each second coupler **30**, and then the second coupler **30** transmits the communication signal to the second device **200** through the first cable **400**, to complete signal transmission.

[0134] The second device **200** includes, for example, a transformer. The second device **200** includes a fifth coil L5 and a sixth coil L6 that are magnetically coupled. Two ends of the fifth coil L5 are coupled to the first cable **400**, to couple the communication signal output by the communication apparatus **1** to the sixth coil L6.

[0135] The following schematically describes the communication control method provided in this embodiment of the present disclosure.

[0136] An embodiment of the present disclosure provides a communication control method. For example, the communication control method may be applied to the communication apparatus **1**.

[0137] The communication control method includes:

[0138] A communication signal received by the communication apparatus **1** and a communication signal sent by the communication apparatus **1** are transmitted through the first channel **20**; the first channel **20** used to connect to a source node or a destination node selects to transmit the communication signal through the first branch **21**; and the first channel **20** not used to connect to the source node or the destination node selects to transmit the communication signal through the second branch **22**.

[0139] The first channel **20** used to connect to the source node or the destination node is referred to as the first channel **20** that is in communication currently, and the first channel **20** that is in communication currently selects to transmit the communication signal through the first branch **21**. The first channel **20** not used to connect to the source node or the destination node is referred to as the first channel **20** that is not in communication, and the first channel **20** that is not in communication selects to transmit the communication signal through the second branch **22**. Not in communication herein does not mean that no communication signal is transmitted, but that the communication signal is not transmitted to the source node or the destination node.

[0140] In some embodiments, the communication apparatus **1** further includes a second channel,

and the communication control method further includes:

[0141] The communication signal is transmitted through the second channel **40**; and the second channel **40** selects, based on a second control signal, the communication signal to be transmitted through a third passive circuit **42**, or selects, based on a second control signal, the communication signal to be transmitted through a fourth passive circuit **43**.

[0142] For example, when the second channel **40** is used to connect to the source node or the destination node, the second control signal sent by the controller to the second channel **40** controls a second switching circuit **44** to select the communication signal to be transmitted through the fourth passive circuit **43**.

[0143] In other words, when the communication signal needs to be transmitted to the source node or the destination node through the second channel **40**, the fourth passive circuit **43** in the second channel **40** transmits the communication signal.

[0144] When the second channel **40** is not used to connect to the source node or the destination node, the second control signal sent by the controller to the second channel **40** controls the second switching circuit **44** to select the communication signal to be transmitted through the third passive circuit **42**.

[0145] In other words, when the communication signal does not need to be transmitted to the source node or the destination node through the second channel **40**, the third passive circuit **42** in the second channel **40** transmits the communication signal.

[0146] In some embodiments, the third device **300** is used as the source node (source ID, SID), the second device **200** is used as the destination node (destination ID, DID, or may be a target node), and the communication signal flows from a side on which the first coupler **10** is located to a side on which the second coupler **30** is located.

[0147] For example, the first coupler **10** receives the communication signal sent by the source node, and one of the plurality of second couplers **30** outputs the communication signal to the destination node. The first channel **20** used to connect to the destination node is obtained.

[0148] For example, the third device **300** is used as the source node, a second device **200** is used as the destination node, and other second devices are used as sensing nodes. The first coupler **10** receives the communication signal sent by the third device **300**, and couples the communication signal to the plurality of first channels **20**. The first channel **20** that is in communication with the destination node is the first channel **20** that is in communication, and the first channel **20** that is in communication with the sensing node is the first channel **20** that is not in communication.

[0149] The first channel **20** that is in the plurality of first channels **20** and that is in communication transmits the communication signal to the second coupler **30** through the second branch **22**, and the first channel **20** that is in the plurality of first channels **20** and that is not in communication transmits the communication signal to the second coupler **30** through the first branch **21**. Each second coupler **30** outputs the communication signal received by the second coupler **30** as an output of the communication apparatus **1**, and transmits the communication signal to the second device **200**.

[0150] The P2MP communication system belongs to a point-to-multipoint communication system based on a time-division duplex (TDD) technology. For the second device **200** (for example, the EP), at a same moment, only one of the plurality of second devices **200** exchanges data with the third device **300** (for example, the DM). In this case, the other second devices **200** are in a sensing state (reading a frame header of a data frame to determine whether the frame data is sent to the other second devices **200**). Therefore, the second device **200** that exchanges data with the third device **300** is referred to as the destination node in a communication state, and the other second devices **200** are referred to as the sensing nodes in the sensing state.

[0151] When the third device **300** is used as the source node and the second device **200** is used as the destination node, the source node, the destination node, and the sensing node is known in the communication system. Therefore, the controller may directly know the first channel **20** that is in

communication and the first channel **20** that is not in communication.

[0152] In some embodiments, the communication control method includes:

[0153] A correspondence between the second device **200** and the first channel **20** in the communication apparatus **1** is obtained.

[0154] Alternatively, it is understood as that a correspondence between the second device **200** and the communication apparatus **1** is obtained by learning that the second device **200** is coupled to the first channel **20** through the first cable **400**.

[0155] The second device **200** that is used as the destination node and the second device **200** that is used as the sensing node are known. Therefore, after the correspondence between the second device **200** and the first channel **20** is obtained, the first channel **20** that is in the communication state may be learned of, and the communication signal needs to flow through the second branch **22**. The first channel **20** that is not in the communication state may be learned of, and the communication signal needs to flow through the first branch **21**.

[0156] In this case, the controller sends the first control signal to each of the plurality of first channels **20**, and the first control signal sent by the controller to the first channel **20** connected to the source node or the destination node controls the first switching circuit **23** to select the communication signal to be transmitted through the second branch **22**. The first control signal sent by the controller to the first channel **20** not connected to the source node controls the first switching circuit **23** to select the communication signal to be transmitted through the first branch **21**, so that the first coupler **10** receives the communication signal, and the second coupler **30** outputs the communication signal.

[0157] As shown in FIG. 4, an n.sup.th endpoint EP n is used as the destination node, and other endpoints are used as the sensing nodes. In the first channel **20** coupled to the endpoint (a first endpoint EP **1** and a second endpoint EP **2** shown in FIG. 4) other than the n.sup.th endpoint EP n, a bolded part indicates a current return path from the first coupler **10** to the second coupler **30**, under control of the first control signal, a switching switch in the first switching circuit **23** is in the off state F, and the switching switch is coupled to the first branch **21**. The entire current loop needs to flow through a high-impedance first passive circuit. An impedance of the entire current loop is very large, and is the high-impedance loop. A current I₁ of the entire loop is large.

[0158] In the first channel **20** coupled to the n.sup.th endpoint EP n, a bolded part indicates a current return path from the first coupler **10** to the second coupler **30**, under the control of the first control signal, the switching switch in the first switching circuit **23** is in the on state O, and the switching switch is coupled to the second branch **22**. The entire current loop flows through a low-resistance signal line (or second passive circuit). An impedance of the entire current loop is very small, and is the normal loop. A current I₂ of the entire loop is large, and the current I₂ of the normal loop is far greater than the current I₁ of the high-resistance loop. In this way, in a process of transmitting the communication signal, most signal power is allocated to the normal loop, so that a transmission rate of the loop that is in communication can be improved.

[0159] In some other embodiments, the second device **200** is used as the source node, the third device **300** is used as the destination node, and a communication signal flows from the side on which the second coupler **30** is located to the side on which the first coupler **10** is located.

[0160] For example, one of a plurality of second couplers **30** receives the communication signal sent by the source node, a first coupler **10** outputs the communication signal to the destination node, and the controller obtains the first channel **20** used to connect to the source node.

[0161] For example, the controller senses a signal frame, and may learn of the source node and the destination node by demodulating a frame header, to learn of a correspondence between the second coupler **30** configured to be coupled to the source node and the first channel **20**, and determine the first channel **20** connected to the source node (the first channel **20** that is in communication currently) and the first channel **20** not connected to the source node (the first channel **20** that is not in communication currently).

[0162] The first control signal sent by the controller to the first channel **20** connected to the source node or the destination node controls the first switching circuit **23** to select the communication signal to be transmitted through the second branch **22**. The first control signal sent by the controller to the first channel **20** not connected to the source node controls the first switching circuit **23** to select the communication signal to be transmitted through the first branch **21**.

[0163] For example, as shown in FIG. **4**, the n.sup.th endpoint EP n is used as the source node, the other endpoints are used as the sensing nodes, and the DM is used as the destination node. In the first channel **20** coupled to the endpoint (the endpoints used as the sensing nodes, namely, the first endpoint EP **1** and the second endpoint EP **2** shown in FIG. **4**) other than the n.sup.th endpoint EP n, the bolded part indicates the current return path from the second coupler **30** to the first coupler **10**, under the control of the first control signal, the switching switch in the first switching circuit **23** is in the off state F, and the switching switch is coupled to the first branch **21**. The entire current loop needs to flow through the high-impedance first passive circuit. The impedance of the entire current loop is very large, and is the high-impedance loop. Therefore, signal power in the endpoints used as the sensing nodes is almost not transmitted to the DM.

[0164] In the first channel **20** coupled to the n.sup.th endpoint EP n, the bolded part indicates the current return path from the first coupler **10** to the second coupler **30**, under the control of the first control signal, the switching switch in the first switching circuit **23** is in the on state O, and the switching switch is coupled to the second branch **22**. The entire current loop flows through the low-resistance signal line (or second passive circuit). The impedance of the entire current loop is very small, and is the normal loop. Therefore, most signal power sent by the n.sup.th endpoint EP n used as the source point may be transmitted to the DM.

[0165] After the execution, the channel changes, the DM or the endpoint is used as a receive end, channel estimation may be performed again based on an additional channel estimation (ACE) symbol, a payload symbol in a frame structure is demodulated to obtain data, and the branch is dynamically switched again.

[0166] According to the communication apparatus **1** provided in this embodiment of the present disclosure, the first channel **20** includes the first branch **21** and the second branch **22** that have the different impedances, and the first channel **20** has a function of selecting whether the communication signal flows through the first branch **21** or the communication signal flows through the second branch **22**. In this case, some (one or more) first channels **20** may select to transmit the communication signal through the first branch **21**, and some (one or more) first channels **20** may select to transmit the communication signal through the second branch **22**. However, the impedance of the first branch **21** is greater than the impedance of the second branch **22**. Therefore, signal power allocated to the first channel **20** on which the communication signal flows through the first branch **21** is low, and signal power allocated to the first channel **20** on which the communication signal flows through the second branch **22** is high. In this way, not all first channels **20** are allocated equal signal power, so that lower signal power can be allocated to the first channel **20** not connected to the source node or the destination node, and higher signal power can be allocated to the first channel **20** connected to the source node or the destination node, to improve a transmission rate of the first channel **20** connected to the source node or the destination node, thereby increasing a transmission rate between two nodes coupled to two ends of the first channel **20**. In addition, each first channel **20** may dynamically switch, based on an application scenario, whether the communication signal flows through the first branch **21** or the second branch **22**, to implement dynamic allocation of the signal power. In this case, the first channel **20** connected to the source node or the destination node at each moment may select the communication signal to flow through the second branch **22**, to obtain higher signal power through allocation, so that the first channel **20** connected to the source node or the destination node at each moment may have a higher transmission rate.

EXAMPLE 2

[0167] An architecture of a communication system in Example 2 is the same as that in Example 1, and a main difference lies in the structure of the communication apparatus **1** in the first device **100**.

[0168] An embodiment of the present disclosure provides a communication system. The communication system includes a first device **100**, a plurality of second devices **200**, and a third device **300**.

[0169] For a coupling relationship among the first device **100**, the second device **200**, and the third device **300**, refer to the related descriptions in Example 1.

[0170] The first device **100** includes a communication apparatus **1** provided in this embodiment of the present disclosure. The communication apparatus **1** reallocates signal power on a communication path, to increase a transmission rate of the second device **200** that is in communication.

[0171] In terms of a structure of the communication apparatus **1**, in some embodiments, the communication apparatus **1** uses a SISO data transmission mode.

[0172] As shown in FIG. 5, the communication apparatus **1** includes a channel group. The channel group includes a first coupler **10**, a plurality of first channels **20**, a plurality of second couplers **30**, and a third coupler **41**.

[0173] Structures and coupling manners of the first coupler **10**, the plurality of first channels **20**, and the plurality of second couplers **30** are the same as those in Example 1. In this example, the third coupler **41** is mainly described.

[0174] As shown in FIG. 5, the channel group further includes a second channel **40**. The second channel **40** includes the third coupler **41**, one end of the third coupler **41** is coupled to a first end **11** of the first coupler **10**, and the other end of the third coupler **41** is coupled to an external port of the communication apparatus **1**.

[0175] In this example, a structure of the first channel **20** is different from a structure of the second channel **40**. Therefore, the first end **11** and the second end **12** of the first coupler **10** may be distinguished by determining circuit structures to which the ports of the first coupler **10** are coupled.

[0176] For example, the third coupler **41** includes a transformer. The transformer includes a seventh coil **L7** and an eighth coil **L8** that are magnetically coupled. Two ends of the seventh coil **L7** are coupled to the external port of the communication apparatus **1**, and two ends of the eighth coil **L8** are coupled to the first end **11** of the first coupler **10**.

[0177] In this way, a communication signal output by the third device **300** may be coupled to the first coupler **10** through the third coupler **41**, and then coupled and transmitted to the second device **200**. A signal output by the second device **200** may also be coupled to the first coupler **10** through the second coupler **30**, and then coupled and transmitted to the third device **300**.

[0178] In other words, when the communication apparatus **1** provided in this embodiment of the present disclosure is used in the communication system, the communication system can implement bidirectional transmission. In other words, the third device **300** can send the signal to the second device **200**, and the second device **200** can send the signal to the third device **300**.

[0179] Based on this, the communication control method provided in this embodiment of the present disclosure includes:

[0180] The third device **300** is used as a source node, the second device **200** is used as a destination node, and the communication signal flows from a side on which the third coupler **41** is located to a side on which the second coupler **30** is located.

[0181] For example, the third coupler **41** receives a communication signal sent by the third device **300**, and couples the communication signal to the first coupler **10**. The first coupler receives the communication signal, and outputs the communication signal through the second coupler **30**.

[0182] The third coupler **41** communicates with the third device **300** through a second cable **500**, and the communication signal output by the third device **300** may be transmitted to the third coupler **41**. The communication signal received by the first coupler **10** is the communication signal

coupled by the third coupler **41**. A process in which the first coupler **10** receives the communication signal and outputs the communication signal through the second coupler **30** is the same as that in Example 1.

[0183] In other words, in a communication process in which the third device **300** sends the signal to the second device **200**, compared with Example 1, this example includes a coupling process of the third coupler **41**, and other communication processes are similar.

[0184] Because the communication apparatus provided in this example has a bidirectional communication function, in addition to using the third device **300** as the source node and using the second device **200** as the destination node, the second device **200** may be used as the source node and the third device **300** may be used as the destination node. In this case, the source node and the destination node need to be obtained first.

[0185] The communication control method provided in this embodiment of the present disclosure is the same as that in Example 1. Refer to the related descriptions.

[0186] For example, as shown in FIG. 5, an n.sup.th endpoint EP n is used as the source node, other endpoints are used as sensing nodes, and a DM is used as the destination node. In the first channel **20** coupled to the endpoint (the endpoints used as the sensing nodes, namely, a first endpoint EP **1** and a second endpoint EP **2** shown in FIG. 5) other than the n.sup.th endpoint EP n, a bolded part indicates a current return path from the second coupler **30** to the first coupler **10**, under control of a first control signal, a switching switch in a first switching circuit **23** is in an off state F, and the switching switch is coupled to a first branch **21**. The entire current loop needs to flow through a high-impedance first passive circuit. An impedance of the entire current loop is very large, and is a high-impedance loop. Therefore, signal power in the endpoints used as the sensing nodes is almost not transmitted to the DM.

[0187] In the first channel **20** coupled to the n.sup.th endpoint EP n, a bolded part indicates a current return path from the first coupler **10** to the second coupler **30**, under the control of the first control signal, the switching switch in the first switching circuit **23** is in an on state O, and the switching switch is coupled to a second branch **22**. The entire current loop flows through a low-resistance signal line (or second passive circuit). An impedance of the entire current loop is very small, and is a normal loop. Therefore, most signal power sent by the n.sup.th endpoint EP n used as the source point may be transmitted to the DM.

[0188] According to the communication apparatus **1** provided in this embodiment of the present disclosure, the third coupler **41** is disposed in the communication apparatus **1**, so that the communication apparatus **1** not only has a capability of transmitting the signal from the first coupler **10** side to the second coupler **30** side, but also has a capability of transmitting the signal from the second coupler **30** side to the first coupler **10** side. In other words, the communication apparatus **1** has a bidirectional transmission capability. In addition, because the first channel **20** includes the first branch **21** and the second branch **22** that have different impedances, by adjusting and controlling a flow path of the communication signal, the first channel **20** connected to the source node or the destination node may have a smaller impedance, and the first channel **20** not connected to the source node or the destination node may have a larger impedance. In this way, when the communication apparatus **1** performs bidirectional transmission, signal power in the communication path is always the highest, and a transmission rate can be improved.

EXAMPLE 3

[0189] An architecture of a communication system in Example 3 is the same as that in Example 2, and a main difference lies in the structure of the communication apparatus **1** in the first device **100**.

[0190] An embodiment of the present disclosure provides a communication system. The communication system includes a first device **100**, a plurality of second devices **200**, and a third device **300**.

[0191] For a coupling relationship among the first device **100**, the second device **200**, and the third device **300**, refer to the related descriptions in Example 1.

[0192] The first device **100** includes a communication apparatus **1** provided in this embodiment of the present disclosure. The communication apparatus **1** reallocates signal power on a communication path, to increase a transmission rate of the second device **200** that is in communication.

[0193] In terms of a structure of the communication apparatus **1**, in some embodiments, the communication apparatus **1** uses a SISO data transmission mode.

[0194] As shown in FIG. **6**, the communication apparatus **1** includes a channel group. The channel group includes a first coupler **10**, a plurality of first channels **20**, a plurality of second couplers **30**, a third coupler **41**, a third passive circuit **42**, a fourth passive circuit **43**, and a second switching circuit **44**.

[0195] Structures and coupling manners of the first coupler **10**, the plurality of first channels **20**, the plurality of second couplers **30**, and the third coupler **41** are the same as those in Example 2. In this example, the third passive circuit **42**, the fourth passive circuit **43**, and the second switching circuit **44** are mainly described.

[0196] As shown in FIG. **6**, the channel group further includes a second channel **40**. The second channel **40** includes the third coupler **41**, the third passive circuit **42**, the fourth passive circuit **43**, and the second switching circuit **44**.

[0197] One end of the third coupler **41** is coupled to a first end **11** of the first coupler **10**, and the other end of the third coupler **41** is coupled to an external port of the communication apparatus **1**. A structure of the third coupler **41** may be the same as the structure of the third coupler **41** in Example 2.

[0198] In this embodiment of the present disclosure, an impedance of the third passive circuit **42** is greater than an impedance of the fourth passive circuit **43**.

[0199] In some embodiments, the third passive circuit **42** may include one or more of, for example, a resistor, an inductor, a ferrite bead, and a capacitor.

[0200] In some embodiments, the fourth passive circuit **43** may include one or more of, for example, the resistor, the inductor, the ferrite bead, and the capacitor.

[0201] Types of passive components included in the third passive circuit **42** and the fourth passive circuit **43** may be the same, provided that the impedance of the third passive circuit **42** is greater than the impedance of the fourth passive circuit **43**.

[0202] For example, the third passive circuit **42** and the fourth passive circuit **43** each include a resistor, and a resistance value of a third resistor included in the third passive circuit **42** is greater than a resistance value of a fourth resistor included in the fourth passive circuit **43**.

[0203] In some other embodiments, the fourth passive circuit **43** includes a signal line, and the fourth passive circuit **43** is a straight-through path (or referred to as a signal normal loop). In FIG. **6**, an example in which the fourth passive circuit **43** includes a signal line is used for description.

[0204] In this embodiment of the present disclosure, an inductive reactance of the third passive circuit **42** may alternatively be greater than an inductive reactance of the fourth passive circuit **43**.

[0205] The third passive circuit **42** and the fourth passive circuit **43** are connected in parallel, and are coupled in series to the second switching circuit **44** between the third coupler **41** and the first end **11** of the first coupler **10**.

[0206] The third passive circuit **42** (or the fourth passive circuit **43**) is connected in series to the second switching circuit **44**. In FIG. **6**, an example in which the second switching circuit **44** is disposed close to the first end **11** is used for description, or the second switching circuit **44** may alternatively be disposed close to the third coupler **41**.

[0207] The second switching circuit **44** is configured to: select, based on a second control signal, the third passive circuit **42** to communicate with the first end **11**, or select, based on a second control signal, the fourth passive circuit **43** to communicate with the first end **11**.

[0208] For example, the second control signal may be output through a controller in the communication apparatus **1**, and the controller may output a corresponding second control signal

based on an obtained source node and an obtained destination node.

[0209] For example, a structure of the second switching circuit **44** may be the same as a structure of a first switching circuit **23**, and a control process of the second switching circuit **44** may also be the same as the control process of the first switching circuit **23**.

[0210] In this example, if a structure of the first channel **20** is different from a structure of the second channel **40** (for example, structures of components and a coupling relationship between the components), the first end **11** and a second end **12** of the first coupler **10** may be distinguished by determining circuit structures to which the ports of the first coupler **10** are coupled. If the structure of the first channel **20** is the same as the structure of the second channel **40**, any one of the plurality of ports of the first coupler **10** may be used as the first end **11** or the second end **12**.

[0211] When the communication apparatus **1** provided in this embodiment of the present disclosure is used in the communication system, the communication system can implement signal transmission on three transmission paths. In other words, the third device **300** can send a signal to the second device **200**, the second device **200** can send a signal to the third device **300**, and the second device **200** can send a signal to the second device **200**.

[0212] With reference to the communication control method provided in this embodiment of the present disclosure, the following schematically describes a communication process of the communication apparatus **1** provided in this embodiment of the present disclosure.

[0213] The communication control method provided in this embodiment of the present disclosure includes:

[0214] The third device **300** is used as a source node, the second device **200** is used as a destination node, and a communication signal flows from a side on which the third coupler **41** is located to a side on which the second coupler **30** is located.

[0215] For example, the third coupler **41** receives the communication signal sent by the third device **300**, and couples the communication signal to the first coupler **10**. The first coupler receives the communication signal, and outputs the communication signal through the second coupler **30**.

[0216] The third coupler **41** communicates with the third device **300** through a second cable **500**, and the communication signal output by the third device **300** may be transmitted to the third coupler **41**.

[0217] The third coupler **41** sends the communication signal to the first coupler **10** through the second channel **40**. In the second channel **40**, a bolded part indicates a current loop path from the third coupler **41** to the first coupler **10**. Under control of the second control signal, a switching switch in the second switching circuit **44** is in an on state **O**, and the switching switch is coupled to the fourth passive circuit **43**. An impedance of the entire current loop is small, and is a normal loop. Therefore, most signal power transmitted by the third coupler **41** is transmitted to the first coupler **10**.

[0218] In FIG. **6**, an example in which an n.sup.th endpoint EP n is used as the destination node is used for description. A process in which the first coupler **10** receives the communication signal and outputs the communication signal through the second coupler **30** is the same as that in Example 1.

[0219] The communication control method provided in this embodiment of the present disclosure further includes:

[0220] The second device **200** is used as the source node, and the third device **300** is used as the destination node. A communication signal flows from the side on which the second coupler **30** is located to the side on which the third coupler **41** is located.

[0221] In FIG. **6**, an example in which the n.sup.th endpoint EP n is used as the source node is used for description. A process in which the second coupler **30** receives the communication signal and transmits the communication signal to the first coupler **10** is the same as that in Example 2.

[0222] Still refer to FIG. **6**. The first coupler **10** sends the communication signal to the third coupler **41** through the second channel **40**. In the second channel **40**, the bolded part indicates the current loop path from the first coupler **10** to the third coupler **41**. Under the control of the second

control signal, the switching switch in the second switching circuit **44** is in the on state O, and the switching switch is coupled to the fourth passive circuit **43**. The impedance of the entire current loop is small, and is the normal loop. Therefore, most signal power transmitted by the first coupler **10** is transmitted to the third coupler **41**. The third coupler **41** communicates with the third device **300** through the second cable **500**, to receive the communication signal sent by the second device **200**.

[0223] The communication control method provided in this embodiment of the present disclosure further includes:

[0224] A second device **200** is used as the source node, and another second device **200** is used as the destination node. A communication signal flows from a side on which the second coupler **30** is located to a side on which the second coupler **30** is located.

[0225] One of a plurality of second couplers **30** receives the communication signal, and another of the plurality of second couplers **30** outputs the communication signal. The controller obtains the first channel **20** used to connect to the source node and the first channel **20** used to connect to the destination node.

[0226] The controller obtains a correspondence between the first channel **20** and the second coupler **30** configured to be coupled to the source node and a correspondence between the first channel **20** and the second coupler **30** configured to be coupled to the destination node, and determines the first channels **20** that are in communication currently. The second control signal sent by the controller to the second channel **40** controls the second switching circuit **44** to select the communication signal to be transmitted through the third passive circuit **42**.

[0227] In FIG. 7, an example in which the n.sup.th endpoint EP n is used as the source node, and a second endpoint EP 2 is used as the destination node is used for description.

[0228] The second coupler **30** corresponding to the source node receives the communication signal, and the communication signal is transmitted to the second end **12** (referred to as an n.sup.th second end **12** in this specification) of the first coupler **10** through the first channel **20**. In this case, the first channel **20** serves as the first channel **20** that is in communication, and the communication signal is transmitted to the first coupler **10** through a second branch **22**. For a control process of the first channel **20**, refer to the foregoing related descriptions of the control process of the first channel **20** that is in communication.

[0229] The n.sup.th second end **12** is magnetically coupled to a 2.sup.nd second end **12** (the second end **12** correspondingly coupled to the second endpoint EP 2), and couples the communication signal to the first channel **20** coupled to the 2.sup.nd second end **12**. In this case, the first channel **20** serves as the first channel **20** that is in communication, and the communication signal is transmitted to the second coupler **30** (the second coupler **30** corresponding to the second endpoint EP 2) through the second branch **22**. For a control process of the first channel **20**, refer to the foregoing related descriptions of the control process of the first channel **20** that is in communication.

[0230] The first channel **20** corresponding to another endpoint belongs to the first channel **20** that is not in communication, and an impedance of a current loop is large. Signal power transmitted by the n.sup.th second end **12** is almost not transmitted to the first channel **20** that is not in communication, and power waste is small. For a control process of the first channel **20** that is not in communication, refer to the foregoing related descriptions of the control process of the first channel **20** that is not in communication.

[0231] In addition, the communication signal does not need to flow through the second channel **40**, and the bolded part in the second channel **40** indicates the current loop path of the second channel **40**. Under the control of the second control signal, the switching switch in the second switching circuit **44** is in an off state F, and the switching switch is coupled to the third passive circuit **42**. Flowing through the high-impedance third passive circuit **42**, the impedance of the entire current loop is large, and is a high-impedance loop. Therefore, the signal power transmitted by the n.sup.th

second end **12** is almost not transmitted to the third coupler **41**, and the power waste is small.

[0232] According to the communication apparatus **1** provided in this embodiment of the present disclosure, the third coupler **41**, the third passive circuit **42**, the fourth passive circuit **43**, and the second selection circuit **44** are disposed in the communication apparatus **1**, so that the communication apparatus **1** not only has a capability of transmitting the signal from the first coupler **10** side to the second coupler **30** side, but also has a capability of transmitting the signal from the second coupler **30** side to the first coupler **10** side, and further has energy of transmitting the signal from a second coupler **30** side to another second coupler **30** side. In addition, the first channel **20** includes a first branch **21** and the second branch **22** that have different impedances. A flow path of the communication signal is adjusted and controlled, so that the first channel **20** connected to the source node or the destination node can have a smaller impedance, and the first channel **20** not connected to the source node or the destination node can have a larger impedance. The second channel **40** includes the third passive circuit **42** and the fourth passive circuit **43** that have the different impedances. The flow path of the communication signal is adjusted and controlled, so that when the communication signal flows through the third coupler **41**, the second channel **40** can have a smaller impedance, and when the communication signal does not flow through the third coupler **41**, the second channel **40** can have a larger impedance. In this way, when the communication apparatus **1** performs transmission, a communication loop is always the normal loop, and another branch is always the high-impedance loop, to ensure that the signal power in the communication path is always the highest, and the transmission rate can be improved.

EXAMPLE 4

[0233] An architecture of a communication system in Example 4 is the same as that in Example 1, and a main difference lies in the structure of the communication apparatus **1** in the first device **100**.

[0234] An embodiment of the present disclosure provides a communication system. The communication system includes a first device **100**, a plurality of second devices **200**, and a third device **300**.

[0235] For a coupling relationship among the first device **100**, the second device **200**, and the third device **300**, refer to the related descriptions in Example 1.

[0236] In terms of a structure of the communication apparatus **1**, in some embodiments, the communication apparatus **1** uses a SISO data transmission mode.

[0237] As shown in FIG. **8**, the communication apparatus **1** includes a channel group. The channel group includes a first coupler **10**, a plurality of first channels **20**, and a plurality of second couplers **30**.

[0238] On the basis of including a first end **11** and a second end **12**, the first coupler **10** further includes a third end **13**, and the third end **13** is coupled in series to a fifth passive circuit.

[0239] The fifth passive circuit may include passive components such as a capacitor, a resistor, an inductor, and a ferrite bead. In FIG. **8**, an example in which the fifth passive circuit includes a resistor **R** is used for description.

[0240] For example, the first coupler **10** is a combiner, and the first coupler **10** is configured to convert one path of signal into a plurality of paths of signals. For example, the first coupler **10** includes a first coil **L1**, a plurality of second coils **L2**, and a third coil **L3**. Two ends of the first coil **L1** are coupled to the first end **11** of the first combiner **10**, two ends of the second coil **L2** are coupled to the second end **12** of the first combiner **10**, and two ends of the third coil **L3** are coupled to the third end **13** of the first combiner **10**. The first coil **L1** is magnetically coupled to the second coil **L2**, the first coil **L1** is magnetically coupled to the third coil **L3**, the second coil **L2** is magnetically coupled to the third coil **L3**, and the plurality of second coils **L2** may also be electromagnetically coupled to each other.

[0241] As shown in FIG. **8**, the two ends of the third coil **L3** are separately coupled in series to the resistor **R**, and the two ends of the first coil **L1** are coupled to a signal line.

[0242] A structure of the first channel **20** may be the same as that in Example 1.

[0243] When the communication apparatus **1** is used in the communication system, the first coil **L1** is coupled to a transmit unit TX of the third device **300**, and the third coil **L3** is coupled to a receive unit RX of the third device **300** through the resistor R.

[0244] The following schematically describes the communication control method provided in this embodiment of the present disclosure.

[0245] An embodiment of the present disclosure provides a communication control method. For example, the communication control method may be applied to the communication apparatus **1**.

[0246] The communication control method includes:

[0247] The third device **300** is used as a source node, the second device **200** is used as a destination node, and a communication signal flows from a side on which the first coupler **10** is located to a side on which the second coupler **30** is located.

[0248] The transmit unit TX in the third device **300** sends the communication signal, and the communication signal is transmitted to the communication apparatus **1** through a second cable **500**. The first coupler **10** couples the communication signal to each second coupler **30**, and then the second coupler **30** transmits the communication signal to the second device **200** through a first cable **400**, to complete signal transmission. In a process in which the communication signal on the first coil **L1** is coupled to the second coil **L2**, the resistor connected in series to the third coil **L3** enables a channel in which the third coil **L3** is located to be a high-impedance channel, to prevent signal flow.

[0249] A second device **200** is used as the source node, another second device **200** is used as the destination node, and a communication signal flows from a side on which the second coupler **30** is located to a side on which the second coupler **30** is located. For details, refer to the related descriptions in Example 1.

[0250] The second device **200** is used as the source node, the third device **300** is used as the destination node, and a communication signal flows from the side on which the second coupler **30** is located to the side on which the first coupler **10** is located.

[0251] The communication signal sent by the second device **200** is coupled to the second coil **L2** of the first coupler **10**, and the second coil **L2** is magnetically coupled to the third coil **L3**, to transmit the communication signal to the receive unit RX of the third device **300**. In this case, the transmit unit TX in the third device **300** is in a high-impedance state, and impedes flow of the communication signal.

[0252] In FIG. **8**, an example in which an n.sup.th endpoint EP n is used as the source node is used for description. The first channel **20** corresponding to the n.sup.th endpoint EP n is the first channel **20** that is in communication, and the first channel **20** corresponding to another endpoint belongs to the first channel **20** that is not in communication. For a control process, refer to the related descriptions of FIG. **7** in Example 3.

EXAMPLE 5

[0253] A main difference between Example 5 and Example 1 to Example 3 lies in that the communication apparatus **1** uses a MIMO data transmission mode, and the communication apparatus **1** includes two channel groups.

[0254] An embodiment of the present disclosure provides a communication system. The communication system includes a first device **100**, a plurality of second devices **200**, and a third device **300**.

[0255] For a coupling relationship among the first device **100**, the second device **200**, and the third device **300**, refer to the related descriptions in Example 1.

[0256] The first device **100** includes a communication apparatus **1** provided in this embodiment of the present disclosure. The communication apparatus **1** reallocates signal power on a communication path, to increase a transmission rate of the second device **200** that is in communication.

[0257] In terms of a structure of the communication apparatus **1**, in some embodiments, the

communication apparatus **1** uses a MIMO data transmission mode.

[0258] As shown in FIG. **9A**, the communication apparatus **1** includes two parallel channel groups, and a structure of the channel group may be any channel group shown in Example 1 to Example 3. When the communication apparatus **1** is used in the communication system, the second device **200** is coupled to both the two channel groups, and the third device is also coupled to both the two channel groups.

[0259] For example, as shown in FIG. **9B**, the structure of the channel group is the channel group shown in FIG. **6**. FIG. **9B** shows the structure of the communication apparatus **1** and a coupling relationship between the communication apparatus **1** and the second device **200** and a coupling relationship between the communication apparatus **1** and the third device **300**.

[0260] Certainly, each second device **200** needs to be coupled to both the two channel groups. However, a port in the channel group to which the second device **200** is coupled is not limited in this embodiment of the present disclosure. The correspondence in FIG. **9B** is merely an example, and constitute no limitation.

[0261] The communication apparatus **1** provided in this embodiment of the present disclosure is not only applicable to the SISO data transmission mode, but also applicable to the MIMO data transmission mode, and has a wide application scope.

EXAMPLE 6

[0262] A main difference between this example and Example 1 to Example 5 lies in that in this example, the first device **100** and the third device **300** are integrated into a same device, and the first device **100** is no longer coupled to the third device **300** through the second cable **500**.

[0263] An embodiment of the present disclosure provides a communication system. The communication system includes a first device **100** and a plurality of second devices **200**, and the first device **100** is coupled to the plurality of second devices **200**.

[0264] As shown in FIG. **10A**, the first device **100** is used as a master node, and the second device **200** is used as a slave node. In other words, a communication apparatus **1** is integrated into the master node.

[0265] Alternatively, as shown in FIG. **10B**, the first device **100** is used as the slave node, one of the second devices **200** is used as the master node, and others of the second devices **200** are used as slave nodes. In other words, the communication apparatus **1** is integrated into the slave node.

[0266] In other words, the plurality of second devices **200** in this embodiment of the present disclosure may be all slave nodes, or one of the plurality of second devices **200** is the master node, and others of the plurality of second devices **200** are the slave nodes.

[0267] For example, as shown in FIG. **11A**, the first device **100** is a DM, the second device **200** is an EP, and the communication apparatus **1** provided in this embodiment of the present disclosure is integrated into the DM.

[0268] Alternatively, for example, as shown in FIG. **11B**, the first device **100** is used as the EP (a first endpoint EP **1**), one of the second devices **200** is used as the DM, and others of the second devices **200** are used as endpoints EPs (a second endpoint EP **2** to an n.sup.th endpoint EP **n**).

[0269] Certainly, in this example, the communication apparatus **1** may be any communication apparatus **1** shown in Example 1 to Example 5. FIG. **11A** and FIG. **11B** are merely examples, and constitute no limitation.

[0270] In some embodiments, for example, a controller may be integrated into a communication chip in the first device **100**.

[0271] The communication apparatus **1** is integrated into the first device **100**, so that an architecture of the communication system can be simplified.

EXAMPLE 7

[0272] In this example, the structure of the communication system is the same as the structures in Example 1 to Example 6, but the structure of the communication apparatus **1** is different.

[0273] An embodiment of the present disclosure provides a communication system. The

communication system may be the communication system shown in FIG. 3, FIG. 9A, or FIG. 10A. Refer to the related descriptions in FIG. 3, FIG. 9A, or FIG. 10A.

[0274] A first device **100** in the communication system includes a communication apparatus **1** provided in this embodiment of the present disclosure. As shown in FIG. 12, the communication apparatus **1** includes a channel group. The channel group includes a first coupler **10**, a third channel **27**, a fourth channel **28**, and a plurality of second couplers **30**. An impedance of the third channel **27** is greater than an impedance of the fourth channel **28**. Alternatively, an inductive reactance of the third channel **27** is greater than an inductive reactance of the fourth channel **28**.

[0275] A structure of the first coupler **10** may be the same as the structure of the first coupler **10** in Example 1. For example, the first coupler **10** includes a first end **11** and a plurality of second ends **12**.

[0276] The third channel **27** is coupled between the second end **12** and the second coupler **30**, and the fourth channel **28** is coupled between the second end **12** and the second coupler **30**. The third channel **27** and the fourth channel **28** are disposed in parallel, and the second end **12** and the second coupler **30** that are coupled to the third channel **27** are different from the second end **12** and the second coupler **30** that are coupled to the fourth channel **28**.

[0277] Certainly, the communication apparatus **1** may include one or more third channels **27**, and the communication apparatus **1** may also include one or more fourth channels **28**. In FIG. 12, an example in which the communication apparatus **1** includes a plurality of third channels **27** and one fourth channel **28** is merely used for description.

[0278] In some embodiments, as shown in FIG. 12, the third channel **27** includes a sixth passive circuit, the fourth channel **28** includes a signal line, and an impedance of the sixth passive circuit is greater than an impedance of the signal line.

[0279] For example, the sixth passive circuit includes passive components such as a capacitor, an inductor, a resistor, and a ferrite bead.

[0280] In some embodiments, the fourth channel **28** may also include the sixth passive circuit, provided that the impedance of the sixth passive circuit is greater than an impedance of the sixth passive circuit.

[0281] In some other embodiments, an inductive reactance of the sixth passive circuit is greater than an inductive reactance of the sixth passive circuit.

[0282] The communication apparatus **1** provided in this embodiment of the present disclosure includes the third channel **27** and the fourth channel **28**. However, the impedances of the third channel **27** and the fourth channel **28** are unequal. Therefore, signal power allocated to the third channel **27** and the fourth channel **28** is also unequal. In a case in which transmit power is fixed, the signal power allocated to the fourth channel **28** with the smaller impedance is higher than the signal power allocated to the third channel **27** with the larger impedance, thereby implementing fixed allocation of the signal power. In this way, a signal transmission rate on the fourth channel **28** can be improved.

[0283] In some embodiments, as shown in FIG. 13, the channel group further includes a third coupler **41**, and the third coupler **41** is coupled to the first end **11** of the first coupler **10**.

[0284] A structure of the third coupler **41** may be the same as the structure of the third coupler **41** in Example 2.

[0285] The third coupler **41** is disposed in the communication apparatus **1**, so that not only a communication signal can be transmitted from a side on which the first coupler **10** is located to a side on which the second coupler **30** is located, but also a communication signal can be transmitted from the side on which the second coupler **30** is located to the side on which the first coupler **10** is located, and an application scenario of the communication apparatus **1** is widened.

[0286] In some embodiments, the communication apparatus **1** includes two parallel channel groups, so that the communication apparatus **1** is not only applicable to a SISO data transmission mode, but also applicable to a MIMO data transmission mode, and has a wide application scope.

[0287] In some embodiments, as shown in FIG. 14, the communication apparatus 1 may alternatively be integrated into a DM.

[0288] An application scenario of the communication apparatus 1 provided in this example may be the same as that of the communication apparatus 1 provided in Example 1 to Example 6 only by replacing the communication apparatus 1 provided in Example 1 to Example 6 with the communication apparatus 1 provided in this example.

[0289] An embodiment of the present disclosure further provides a computer-readable storage medium. The computer-readable storage medium stores computer program code, and when the instructions are run on a computer, the computer is enabled to perform the communication control method.

[0290] An embodiment of the present disclosure further provides a computer program product. When the computer program product is run on a computer, the computer is enabled to perform the communication control method.

[0291] The foregoing descriptions are merely specific implementations of the present disclosure, but are not intended to limit the protection scope of this application. Any variation or replacement within the technical scope disclosed in the present disclosure shall fall within the protection scope of this application. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

Claims

1. A communication apparatus comprising: a first channel group comprising: a first coupler comprising a first end and a plurality of second ends; a plurality of second couplers; and a plurality of first channels, wherein each first channel of the plurality of first channels comprises: a first branch having a first impedance; a second branch having a second impedance less than the first impedance; a third end coupled to a corresponding second end of the plurality of second ends; and a fourth end coupled to a corresponding second coupler of the plurality of second couplers, wherein the first channel is configured to select the first branch or the second branch to transmit a communication signal.
2. The communication apparatus of claim 1, wherein a first inductive reactance of the first branch is greater than a second inductive reactance of the second branch.
3. The communication apparatus of claim 1, wherein a first resistance of the first branch is greater than a second resistance of the second branch.
4. The communication apparatus of claim 1, wherein the first branch comprises a first passive circuit, wherein the second branch comprises a second passive circuit connected in parallel to the first passive circuit, and wherein the first channel further comprises a switching circuit configured to select, based on a control signal, the first passive circuit or the second passive circuit to communicate with the corresponding second coupler, wherein the first passive circuit and the second passive circuit are connected in series to the switching circuit, and wherein a third impedance of the first passive circuit is greater than a fourth impedance of the second passive circuit.
5. The communication apparatus of claim 4, further comprising a controller configured to output the control signal.
6. The communication apparatus of claim 4, wherein the first passive circuit comprises at least one of a resistor, a capacitor, an inductor, or a ferrite bead.
7. The communication apparatus of claim 4, wherein the second passive circuit comprises a signal line.
8. The communication apparatus of claim 1, wherein the first channel group further comprises a second channel comprising a third coupler coupled to the first end.
9. The communication apparatus of claim 8, wherein the second channel further comprises: a first

passive circuit; a second passive circuit connected in parallel to the first passive circuit, wherein a third impedance of the first passive circuit is greater than a fourth impedance of the second passive circuit; and a switching circuit configured to select, based on a control signal, the first passive circuit or the second passive circuit to communicate with the first end, wherein the first passive circuit and the second passive circuit are coupled in series to the switching circuit between the third coupler and the first end.

10. The communication apparatus of claim 1, wherein the first coupler further comprises a fifth end coupled in series to a passive circuit.

11. The communication apparatus of claim 1, further comprising a second channel group connected in parallel to the first channel group.

12. The communication apparatus of claim 1, wherein the communication apparatus is an endpoint device, a station device, a domain master device, or a central coordinator device.

13. A communication apparatus comprising: a channel group comprising: a first coupler comprising a first end and a plurality of second ends; a plurality of second couplers; a first channel having a first impedance and is coupled between one of the plurality of second ends and one of the plurality of second couplers; and a second channel having a second impedance less than the first impedance and is coupled between another one of the plurality of second ends and another one of the plurality of second couplers, and wherein a first impedance of the first channel is greater than a second impedance of the second channel.

14. The communication apparatus of claim 13, wherein the first channel comprises a passive circuit, wherein the second channel comprises a signal line, and wherein a third impedance of the passive circuit is greater than a fourth impedance of the signal line.

15. The communication apparatus of claim 13, wherein the channel group further comprises a third coupler coupled to the first end.

16. A communication control method, implemented by a communication apparatus, the communication control method comprising transmitting first communication signals through first channels by: selecting, by one of the first channels connecting to a source node or a destination node, to transmit a first communication signal of the first communication signals through a first branch; and selecting, by another one of the first channels not connecting to the source node or the destination node, to transmit a second communication signal of the first communication signals through a second branch.

17. The communication control method of claim 16, further comprising transmitting the first communication signals through a second channel, wherein transmitting the first communication signals through the second channel comprises: selecting, by the second channel and based on a control signal, a selected passive circuit from either a first passive circuit or a second passive circuit; and transmitting the first communication signals through the selected passive circuit.

18. The communication control method of claim 17, wherein selecting the selected passive circuit comprises: sending, by a controller, the control signal to the second channel; controlling, based on the control signal, a switching circuit to select the selected passive circuit; selecting, by the switching circuit, the second passive circuit as the selected passive circuit when the second channel connects to the source node or the destination node; or selecting, by the switching circuit, the first passive circuit as the selected passive circuit when the second channel is not connected to the source node or the destination node.

19. The communication control method of claim 16, further comprising: receiving, by a first coupler, second communication signals from the source node; outputting, by one of a plurality of second couplers, the second communication signals to the destination node; and obtaining a first channel of the first channels connected to the destination node.

20. The communication control method of claim 16, further comprising: receiving, by one of a plurality of second couplers, second communication signals from the source node; outputting, by a

first coupler, the second communication signals to the destination node; and obtaining, by the controller, a first channel of the first channel connected to the source node.
