

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250284244

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

DEWA; Andrew et al.

SYSTEM AND METHOD FOR PHASE SPATIAL LIGHT MODAULTOR

Abstract

A system includes: a spatial light modulator (SLM) having a first array of pixels; a phase spatial light modulator (PSLM) optically coupled to and illuminating the SLM, the PSLM having a second array of pixels; and control circuitry coupled to the SLM and PSLM. The control circuitry is configured to: obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; provide the target hologram to the PSLM; and provide a control data to the SLM. The SLM is configured to adjust the first array of pixels responsive to the control data. The PSLM is configured to adjust the second array of pixels responsive to the target hologram.

Inventors: DEWA; Andrew (Plano, TX), Bartlett; Terry A. (Dallas, TX)

Applicant: TEXAS INSTRUMENTS INCORPORATED (Dallas, TX)

Family ID: 1000007743476

Appl. No.: 18/599203

Filed: March 08, 2024

Publication Classification

Int. Cl.: G03H1/22 (20060101); G03H1/08 (20060101)

U.S. Cl.:

CPC G03H1/2294 (20130101); G03H1/0808 (20130101); G03H2222/12 (20130101);
G03H2225/32 (20130101)

Background/Summary

BACKGROUND

[0001] Modern projectors include a light source, a spatial light modulator (SLM), and a controller for the light source and the SLM. An example SLM may use pixels to change the angle of reflected light. Use of an additional phase spatial light modulator (PSLM) could enhance an image while adding control complexity. Computing the hologram for a PSLM in a high dynamic range (HDR) display or projector is computationally intensive. One PSLM and SLM control technique involves computing a hologram frame-by-frame using iterative Fourier transform analysis and scaling SLM pixel values based on the hologram, which would be expensive to implement, and may add frame delay.

SUMMARY

[0002] In an example, a system comprises: a spatial light modulator (SLM) having a first array of pixels; a phase spatial light modulator (PSLM) optically coupled to and illuminating the SLM, the PSLM having a second array of pixels; and control circuitry coupled to the SLM and PSLM. The control circuitry is configured to: obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; provide the target hologram to the PSLM; and provide a control data to the SLM. The SLM is configured to adjust the first array of pixels responsive to the control data. The PSLM is configured to adjust the second array of pixels responsive to the target hologram.

[0003] In another example, a method comprises: determining, by control circuitry, sub-holograms for a plurality of brightness zones; combining, by the control circuitry, the sub-holograms to produce a target hologram; and transmitting, by the control circuitry, the target hologram.

[0004] In yet another example, a projector comprises: a PSLM having an array of pixels; and a controller coupled to the PSLM. The controller is configured to: obtain zone brightness data; obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and the zone brightness data; combine the sub-holograms to produce a target hologram; and provide the target hologram to the PSLM, wherein the PSLM is configured to adjust the array of pixels based on the target hologram.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0005] FIG. 1 is a diagram of a system in accordance with various examples.

[0006] FIG. 2 is a diagram of another system in accordance with various examples.

[0007] FIG. 3 is a diagram of a projector in accordance with various examples.

[0008] FIG. 4 is a diagram of transforming target brightness zones to a hologram image in accordance with various examples.

[0009] FIG. 5 is a diagram representing transformation of a baseline hologram to sub-holograms in accordance with various examples.

[0010] FIG. 6 is a diagram representing tiling of sub-holograms to form a target hologram in accordance with various examples.

[0011] FIG. 7 is a flowchart showing a phase spatial light modulator controller method in accordance with various examples.

[0012] FIG. 8 is a flowchart showing a projector control method in accordance with various examples.

[0013] FIG. 9 is a flowchart showing a projector method in accordance with various examples.

DETAILED DESCRIPTION

[0014] The same reference numbers or other reference designators are used in the drawings to designate the same or similar features. Such features may be the same or similar either by function and/or structure.

[0015] In the described examples, a projector controller (sometimes just controller hereafter) provides controls signals for a light source, a phase spatial light modulator (PSLM), and a spatial light modulator (SLM). The controller may include one or more circuits. The circuits of the controller may be integrated circuits (ICs) or other circuits. In the described examples, the controller reduces the computational overhead (improving speed and/or bandwidth) of PSLM control compared to techniques that use real-time hologram computation, such as an iterative Fourier transform analysis, to determine the hologram used for PSLM control. In some examples, the controller is configured to: obtain a baseline hologram; determine a sub-hologram for each of a plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; and provide the target hologram to the PSLM. The figures hereafter provide additional details and example systems, controllers, and control options.

[0016] FIG. 1 is a diagram of a system **100** in accordance with various examples. In some examples, system **100** is a projector such as a traditional projector, an augmented reality (AR) display, a virtual reality (VR) display, a smart headlight, a heads-up display (HUD), an automotive ground projector, a 3D display, or another type of projector.

[0017] The example system **100** is not intended to be limiting and the control techniques described herein may be used in any other system to efficiently control a PSLM such as PSLM **160**. As shown, system **100** includes a controller **102**, a light source **150**, the PSLM **160**, an SLM **170**, a processor **180**, and a memory **190**. The controller **102** has a first terminal **104**, a second terminal **106**, a third terminal **108**, a fourth terminal **109**, and a fifth terminal **110**. The light source **150** has a terminal **152** and an optical output **154**. The PSLM **160** has a terminal **162**, an optical input **164**, and an optical output **166**. The SLM **170** has a terminal **172**, an optical input **174**, and an optical output **176**. The processor **180** has a terminal **182**. The memory **190** has a terminal **192**.

[0018] In the example of FIG. 1, the PSLM **160** includes an array of pixels **168**. In some examples, the array of pixels **168** may include mechanical elements, electro-optical elements, thermo-optical elements, magneto-optical elements, microelectromechanical system (MEMS) elements, and related control elements (e.g., an array of memory cells). In some examples, the PSLM **160** is a phase light modulator (PLM) having pixels **168** that are micromirrors having adjustable heights to affect the phase of light. In another example the PSLM **160** is a ferroelectric liquid crystal on silicon (FLCoS) device having pixels **168** that affect the phase of light.

[0019] In the example of FIG. 1, the controller **102** includes a processor **120**, image analysis circuitry **112**, SLM control circuitry **116**, PSLM control circuitry **130**, and illumination control circuitry **140**. The processor **120** has a first terminal **122**, a second terminal **124**, a third terminal **126**, a fourth terminal **128**, and a fifth terminal **129**. The image analysis circuitry **112** has a first terminal **114** and a second terminal **115**. The SLM control circuitry **116** has a first terminal **117**, a second terminal **118**, and a third terminal **119**. The PSLM control circuitry **130** has a first terminal **132**, a second terminal **134**, and a third terminal **136**. The illumination control circuitry **140** has a first terminal **142** and a second terminal **144**.

[0020] As shown, the first terminal **104** of the controller **102** is coupled to the terminal **182** of the processor **180**. The second terminal **106** of the controller **102** is coupled to the terminal **192** of the memory **190**. As another option, the processor **180** and the memory **190** may be coupled together and are in communication with the controller **102** and the processor **120** via a single interface. The third terminal **108** of the controller **102** is coupled to the terminal **152** of the light source **150**. The fourth terminal **109** of the controller **102** is coupled to the terminal **162** of the PSLM **160**. The fifth terminal **110** of the controller **102** is coupled to the terminal **172** of the SLM **170**. The optical

output **154** of the light source **150** is optically coupled to the optical input **164** of the PSLM **160**. The optical output **166** of the PSLM is optically coupled to the optical input **174** of the SLM **170**. The optical output **176** of the SLM **170** provides projected video **196**.

[0021] As shown, the first terminal **122** of the processor **120** is coupled to the first terminal **104** of the controller **102**. The second terminal **124** of the processor **120** is coupled to the second terminal **106** of the controller **102**. The third terminal **126** of the processor **120** is coupled to the first terminal **114** of the image analysis circuitry **112**. The fourth terminal **128** of the processor **120** is coupled to the second terminal **118** of the SLM control circuitry **116**. The fifth terminal **129** of the processor **120** is coupled to the first terminal **132** of the PSLM control circuitry **130**. The second terminal **134** of the PSLM control circuitry is coupled to the first terminal **142** of the illumination control circuitry **140**. The third terminal **136** of the PSLM control circuitry **130** is coupled to the fourth terminal **109** of the controller **102**. The second terminal **144** of the illumination control circuitry **140** is coupled to the third terminal **108** of the controller **102**. The second terminal **115** of the image analysis circuitry **112** is coupled to the first terminal **117** of the SLM control circuitry **116**. The third terminal **119** of the SLM control circuitry **116** is coupled to the fifth terminal **110** of the controller **102**.

[0022] In some examples, the processor **180** can be a central processing unit (CPU), a graphics processing unit (GPU), or a specialized processor programmed to perform image compression or decompression operations. In different examples, the processor **180** may include a processing pipeline, buffering, and control logic for performing image compression or decompression operations. Also, the processor **180** may include multiple processors, controllers, or engines to perform image compression or decompression operations. In one example, the processor **180** uses buffering and logic with a pipelined data path architecture to perform the image compression or decompression operations. Interleaving blocks in a single pipeline can present some limitations, as the single pipeline becomes a bandwidth bottleneck. Duplicating the pipeline increases bandwidth, but at the cost of logic area. In an example, the processing, buffering, and control logic are bundled into an image compression or decompression engine. A processing system may include multiple processing engines. The number of processing engines and an interleaving factor can be varied to ensure that an available compression bandwidth is in line with the compression bandwidth used by the compression tasks being performed. As used herein, “interleaving factor” refers to the number of processing queues and related stages of pipelined hardware for a processing engine. When queuing blocks of an image for compression operations, multiple blocks of the image are processed through different stages of the pipelined hardware of a processing engine in a manner that reduces the amount of waiting time for each processing stage and improves the overall processing speed relative to processing one block at a time. In one example, eight processing engines could be used, with each processing engine interleaving 32 blocks. In this example, the interleaving factor is 32. In other examples, the number of processing engines and the interleaving factor may vary. Without limitation, the number of processing engines may be two, four, six, eight, ten, or another integer number of processing engines. Without limitation, the interleaving factor may be two, four, eight, sixteen, or another integer number.

[0023] In some examples, the memory **190** may include read-only-memory (ROM), random access memory (RAM), electrically erasable programmable read-only memory (EEPROM), flash memory, and/or other non-transitory computer readable memory types. In different examples, the memory **190** may correspond to a single memory unit or multiple memory units. In some examples, the memory **190** stores configuration parameters for use by the controller **102**.

[0024] In some examples, the controller **102** operates to: receive video data from the processor **180** at the first terminal **104**; receive configuration data from the memory **190** at the second terminal **106**; provide first control signals (CS1) for the SLM **170** at the fifth terminal **110** responsive to the video data, the configuration data, operations of the image analysis circuitry **112**, operations of the processor **120**, and/or operations of the SLM control circuitry **116**; provide second control signals

(CS2) for the PSLM at the fourth terminal **109** responsive to the video data, the configuration data, operations of the image analysis circuitry **112**, operations of the processor **120**, and/or operations of the PSLM control circuitry **130**; and provide third control signals (CS3) for the light source **150** at the third terminal **108** responsive to the video data, the configuration data, operations of the image analysis circuitry **112**, operations of the processor **120**, operations of the PSLM control circuitry **130**, and/or operations of the illumination control circuitry **140**.

[0025] In some examples, the controller **102** is configured to provide CS3 to control the light source **150**, provide CS2 to control the PSLM **160**, and provide CS1 to control the SLM **170**. The control of the light source **150**, the PSLM **160**, and the SLM **170** by the controller **102** results in the projected video **196**. In some examples, the SLM **170** creates the image for the projected video **196** based on CS1, the PSLM **160** control brightness zones of the projected video **196** based on CS2, and the light source **150** controls illumination on-time and illumination off-time intervals based on CS3. Together, the SLM **170**, the PSLM **160**, and the light source **150** control dynamic range and colors of the projected video **196**.

[0026] In some examples, the image analysis circuitry **112** may include hardware accelerators or a processor configured to perform image analysis and compare determined image attribute metrics to related thresholds. To prevent lag, image analysis circuitry **112** performs operations at a rate that enables per frame analysis. As another option, the image analysis circuitry **112** may skip analysis of some frames (e.g., skipping every other frame or skipping further analysis of frames responsive to a similarity metric). Based on the image analysis and related metrics, the image analysis circuitry **112** determines image analysis results. In some examples, the image analysis circuitry **112** determines zone brightness data responsive to the image analysis results.

[0027] In some examples, the processor **120** may include one or more processor cores or engines configured to: receive video data at the first terminal **122**; receive configuration data at the second terminal **124**; provide configuration control signals at the third terminal **126** responsive to the configuration data; receive image analysis results from the image analysis circuitry **112** at the third terminal **126**; provide pixel data at the fourth terminal **128** responsive to the video data, configuration data, and/or image analysis results; and provide zone brightness data at the fifth terminal **129** responsive to the video data, configuration data, and/or image analysis results. In some examples, the processor **120** may perform the operations of the image analysis circuitry **112**. In some examples, the processor **120** may include one or more processor cores or engines configured to adjust or limit operations of the image analysis circuitry **112**, the SLM control circuitry **116**, the PSLM control circuitry **130**, and/or the illumination control circuitry **140** responsive to user preferences or other configuration options. Example configuration or user preference options may include limiting or prioritizing the image attribute metrics to be used by the image analysis circuitry **112**, adjusting thresholds to be used by the image analysis circuitry **112**, limiting or adjusting control sequence options available for use by the SLM control circuitry **116**, limiting or adjusting brightness zone options available for use by the PSLM control circuitry **130**, adjusting the baseline hologram or selecting from different baseline hologram options for use by the PSLM control circuitry **130**. Example configuration or user preference options may also account for configuration or user preference options such as color preferences or adjustments, power efficiency options, display frame rate adjustments, and/or other configuration or user preference options.

[0028] In some examples, the SLM control circuitry **116** may include hardware accelerators configured to: receive image analysis results at the first terminal **117**; receive pixel data and/or configuration data at the second terminal **118**; and produce CS1 at the third terminal **119** responsive to the image analysis results, the pixel data, and/or the configuration data. In some examples, CS1 includes control signals to control pixels **178** of the SLM **170**. In some examples, CS1 is synchronized with CS2 and/or CS3 to synchronize operations of the SLM **170**, the light source **150**, and/or the PSLM **160**.

[0029] In some examples, the PSLM control circuitry **130** is a field-programmable gate array (FPGA) or other programmable logic. In some examples, the PSLM control circuitry **130** operates to: receive zone brightness data at the first terminal **132** responsive to image analysis results; obtain a baseline hologram; determine a sub-hologram for each of a plurality of brightness zones indicated by the zone brightness data responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; and provide CS2 at the third terminal **136**, where CS2 includes the target hologram. In some examples, CS2 includes the target hologram. In some examples, the target hologram includes a multi-bit value for each of the pixel **168** to control a respective mirror position (e.g., height). In some examples, the zone brightness data provided to the PSLM control circuitry **130** is determined by the image analysis circuitry **112** responsive to image analysis results. In other examples, the zone brightness data provided to the PSLM control circuitry **130** is determined by the processor **120** responsive to image analysis results. In some examples, CS2 is synchronized with CS1 and/or CS3 to synchronize operations of the SLM **170**, the light source **150**, and/or the PSLM **160**.

[0030] In the example of FIG. **1**, the PSLM control circuitry **130** is also configured to provide control signals (CS4) at the second terminal **134** to the illumination control circuitry **140** responsive to a target lighting configuration determined for the target hologram. In some examples, CS4 may include lighting configuration data for each color controlled by the illumination control circuitry **140**.

[0031] In some examples, the illumination control circuitry **140** operates to: receive CS4 at the first terminal **142**; and provide CS3 at the second terminal **144** responsive to CS4. CS3 may include control voltages for each color controlled by the light source **150**. In some examples, CS3 includes control voltages for red, green, and blue colors controlled by the light source **150**. In some examples, CS3 is synchronized with CS1 and/or CS2 to synchronize operations of the SLM **170**, the light source **150**, and/or the PSLM **160**.

[0032] In some examples, the image analysis circuitry **112**, the SLM control circuitry **116**, the PSLM control circuitry **130**, and the processor **120**, and the illumination control circuitry **140** operate at a rate that enables image analysis, brightness zone generation, target hologram generation, control sequence selection/generation, generation of CS1, CS2, and CS3, and accounting for configuration and user preference options to be completed for each image frame. In such examples, the individual and combined operations of the image analysis circuitry **112**, the processor **120**, the SLM control circuitry **116**, the PSLM control circuitry **130**, and the illumination control circuitry **140** are performed within an interval determined by the target display frame rate. In some examples, configuration or user preference adjustments may be performed at another rate or upon request.

[0033] In some examples, the light source **150** provides light responsive to CS3. The light source **150** may include one or more lasers or other light sources. In some examples, the light source **150** may separately control the intensity of red light, the intensity of green light, and the intensity of blue light for each image frame responsive to CS3.

[0034] In some examples, the PSLM **160** may perform phase spatial modulation of light responsive to CS2 using mechanical, electro-optical, thermo-optical, and/or magneto-optical, and/or MEMS control options. In one example, the PSLM **160** is a PLM having MEMS mirrors with adjustable heights, where the height of the mirrors affects the phase of the light. In another example, the PSLM **160** is an FLCoS in which a voltage applied to a cell affects the phase of light. In some examples, CS2 includes a hologram. A hologram is an image formed by the interference of light from a coherent light source. In a hologram, pixel values are sent to pixels of the PSLM **160**, and the pixel values. The PSLM **160** alters the coherent, for example laser, wavefront using interference to create a target image that is different than the pixel values. The PSLM **160** produces a target image at the SLM **170** based on light from the light source **150** and pixel values of the PSLM **160**.

[0035] In some examples, the SLM **170** may perform spatial modulation of light responsive to CS1

using mechanical, electro-optical, thermo-optical, magneto-optical, and/or MEMS control options. Examples of the SLM **170** include, but are not limited to, a DMD, a LCoS device, or a liquid crystal display device.

[0036] FIG. **2** is a diagram of another system **200** in accordance with various examples. In some examples, system **200** is a projector such as a traditional projector, an AR display, a VR display, a smart headlight, an HUD, a 3D display, or another type of projector.

[0037] The example system **200** is not intended to be limiting and the control techniques described herein may be used in any other system to efficiently control a PSLM such as the PSLM **160**. As shown, the system **200** includes a system-on-a-chip (SoC) **202**, SLM control circuitry **210**, PSLM control circuitry **220**, illumination control circuitry **232**, the light source **150**, the PSLM **160**, and the SLM **170**. The SoC **202** has a first terminal **204**, a second terminal **206**, and a third terminal **208**. The SLM control circuitry **210** has a first terminal **212** and a second terminal **214**. The PSLM control circuitry **220** has a first terminal **222**, a second terminal **224**, and a third terminal **226**. The illumination control circuitry **232** has a first terminal **234** and a second terminal **236**. The light source **150** has the terminal **152** and the optical output **154**. The PSLM **160** has the terminal **162**, the optical input **164**, and the optical output **166**. The SLM **170** has the terminal **172**, the optical input **174**, and the optical output **176**.

[0038] The first terminal **204** of the SoC **202** is adapted to receive video data. The second terminal **206** of the SoC **202** is coupled to the first terminal **212** of the SLM control circuitry **210**. The third terminal **208** of the SoC **202** is coupled to the first terminal **222** of the PSLM control circuitry **220**. The second terminal **214** of the SLM control circuitry **210** is coupled to the terminal **172** of the SLM **170**. The second terminal **224** of the PSLM control circuitry **220** is coupled to the terminal **162** of the PSLM **160**. The third terminal **226** of the PSLM control circuitry **220** is coupled to the first terminal **234** of the illumination control circuitry **232**. In the example of FIG. **2**, the PSLM control circuitry **220** includes a memory **228**. In some examples, the memory **228** stores a baseline hologram **230**. The second terminal **236** of the illumination control circuitry **232** is coupled to the terminal **152** of the light source **150**. The optical output **154** of the light source **150** is coupled to the optical input **164** of the PSLM. The optical output **166** of the PSLM **160** is coupled to the optical input **174** of the SLM **170**. The optical output **176** of the SLM **170** provides the projected video **196**.

[0039] In the example of FIG. **2**, the SoC **202**, the SLM control circuitry **210**, the PSLM control circuitry **220**, and the illumination control circuitry **232** perform the same or similar operations as the controller **102** of FIG. **1**. More specifically, the SoC **202** may perform the same or similar operations as the processor **120** and the image analysis circuitry **112**. The SLM control circuitry **210** may perform the same or similar operations as the SLM control circuitry **116**. The PSLM control circuitry **220** may perform the same or similar operations as the PSLM control circuitry **130**. The illumination control circuitry **232** may perform the same or similar operations as the illumination control circuitry **140**.

[0040] In some examples, the SoC **202** operates to: receive video data at the first terminal **204**; provide high dynamic range (HDR) scaled pixel data at the second terminal **206** responsive to the video data; and provide zone brightness data at the third terminal **208** responsive to the video data. In some examples, the SoC **202** provides pixel data including a multi-bit code for each of the pixels **178** of the SLM **170**. If the bit depth of the pixel data from the SoC **202** matches the bit depth supported by the SLM **170**, scaling of the pixel data from the SoC **202** may be avoided. In some examples, the SoC **202** can vary the number of bits for each multi-bit code. If the number of bits provided by the SoC **202** for each multi-bit code is at least a target number of bits, the pixel data is referred to as HDR scaled pixel data. In some examples, “zone brightness data” includes data that defines the number of zones, the position of zones, and a brightness level for each zone. In some examples, the SoC **202** may be an LCD flat panel SoC configured to determine zone brightness data responsive to video data. If the pixel data provided by the SoC **202** is not HDR scaled, the

SLM control circuitry **210** may perform HDR scaling of the pixel data provided by the SoC **202**.

[0041] In some examples, the SLM control circuitry **210** may include hardware accelerators configured to: receive pixel data at the first terminal **212**; and produce CS1 at the second terminal **214** responsive to the pixel data. In some examples, the pixel data is HDR scaled pixel data and the SLM control circuitry **210** is configured to provide CS1 at the second terminal **214** responsive to the HDR scaled pixel data. In other examples, the pixel data is not HDR scaled pixel data. In such examples, the SLM control circuitry **210** is configured to: perform HDR scaling of the pixel data; and provide CS1 at the second terminal **214** responsive to the HDR scaled pixel data.

[0042] In some examples, the PSLM control circuitry **220** operates to: receive zone brightness data at the first terminal **222**; obtain a baseline hologram; determine a sub-hologram for each of a plurality of brightness zones indicated by the zone brightness data responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; provide CS2 at second terminal **224**, where CS2 includes the target hologram. In some examples, CS2 includes the target hologram and control voltages. The PSLM control circuitry **220** is also configured to provide CS4 at the third terminal **226** responsive to the zone brightness data and the target hologram.

[0043] In some examples, the illumination control circuitry **232** operates to: receive CS4 at the first terminal **234**; and provide CS3 at the second terminal **236** responsive to CS4. CS3 may include control voltages for each color controlled by the light source **150**. In some examples, CS3 includes control voltages for red, green, and blue colors controlled by the light source **150**.

[0044] In some examples, the SoC **202**, the SLM control circuitry **210**, the PSLM control circuitry **220**, and the illumination control circuitry **232** operate at a rate that enables image analysis, generation of zone brightness data, target hologram generation, control sequence selection/generation, generation of CS1, CS2, CS3, and accounting for configuration and user preference options to be completed for each image frame. In such examples, the individual and combined operations of the SoC **202**, the SLM control circuitry **210**, the PSLM control circuitry **220**, and the illumination control circuitry **232** are performed within an interval determined by the target display frame rate. In some examples, configuration or user preference adjustments may be performed at another rate or upon request. In the example of FIG. 2, the light source **150**, the PSLM **160**, and the SLM **170** perform the same or similar operations as described in FIG. 1 to generate the projected video **196**.

[0045] FIG. 3 is a diagram of a projector **300** in accordance with various examples. In some examples, the projector **300** may include some or all of the components of the system **100** or the system **200**. As shown, the projector **300** includes a controller **302**, a light source **150A**, a focusing lens **314**, a PSLM **160A**, an SLM **170A**, and a projection lens **324** in the arrangement shown. In some examples, the controller **302** is an example of the controller **102** in FIG. 1. In some examples, the controller **302** includes the SoC **202**, the SLM control circuitry **210**, the PSLM control circuitry **220**, and the illumination control circuitry **232** in FIG. 2.

[0046] As shown, the controller **302** has a first terminal **304**, a second terminal **308**, a third terminal **309**, and a fourth terminal **310**. The first terminal **304** of the controller **302** is an example of the first terminal **104** of the controller **102** in FIG. 1. The second terminal **308** of the controller **302** is an example of the third terminal **108** of the controller **102** in FIG. 1. The third terminal **309** of the controller **302** is an example of the fourth terminal **109** of the controller **102** in FIG. 1. The fourth terminal **310** of the controller **302** is an example of the fifth terminal **110** of the controller **102** in FIG. 1. The light source **150A** has the terminal **152** and the optical output **154**. The PSLM **160A** has the terminal **162**, the optical input **164**, and the optical output **166**. The SLM **170A** has the terminal **172**, the optical input **174**, and the optical output **176**.

[0047] In the example of FIG. 3, the controller **302** operates to: receive video data at the first terminal **304**; provide CS1 at the fourth terminal **310** responsive to the video data; provide CS2 at

the third terminal **309** responsive to the video data; and provide CS3 at the second terminal **308** responsive to the video data. In some examples, the controller operates to: generate zone brightness data responsive to video data or related image analysis results; obtain a baseline hologram; determine a sub-hologram for each of a plurality of brightness zones indicated by the zone brightness data responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; and provide CS2 at the third terminal **309**, where CS2 includes the target hologram.

[0048] In the example of FIG. 3, the controller **302** operates to provide CS1, CS2, and CS3 responsive to the video data. The light source **150A** operates to: receive CS3 at the terminal **152**; and provide collimated laser light at the optical output **154** responsive to CS3. The focusing lens **314** operates to focus the collimated laser light. The PSLM **160A** operates to: receive CS2 at the terminal **162**; receive focused collimated laser light at the optical input **164**; and reflect the focused collimated laser light at the optical output **166** responsive to CS2. The SLM **170A** operates to: receive CS1 at the terminal **172**; receive reflected light from the PSLM **160A** at the optical input **174**; and reflect light at the optical output **176** responsive to CS1. The projection lens **324** operates to: receive reflected light from the SLM **170A**; and produce the projected video **196** responsive to the reflected light from the SLM **170A**. In the example of FIG. 3, each of the SLM **170A** and the PSLM **160A** is reflective. In other examples, the PSLM **160A** is reflective and the SLM **170A** is transmissive. In other examples, the PSLM **160A** is transmissive and the SLM **170A** is reflective. In other examples, each of the SLM **170A** and the PSLM **160A** is transmissive. In different example, the orientation, spacing, and relative position of the light source **150A**, the focusing lens **314**, PSLM **160A**, the SLM **170A**, and the projection lens **324** may vary.

[0049] FIG. 4 is a diagram **400** of transforming target brightness zones **402** to a hologram image **414** in accordance with various examples. As shown, the diagram **400** includes the target brightness zones **402**, a digital image **404**, a baseline hologram **407**, sub-holograms **408**, a target hologram **412**, the hologram image **414**, and related operations **416**, **418**, **422**, and **424**. In some examples, the target brightness zones **402** may be defined by the zone brightness data described in FIGS. 1, 2, and 3. In some examples, the target brightness zones **402** define zone sizes, zone positions, and a brightness level for each zone based on video data or related image analysis results. In the example of FIG. 4, the target brightness zones **402** are organized as rows or columns of zones including a first row of zones (1,1) to (1,4), a second row of zones (2,1) to (2,4), and a third row of zones (3,1) to (3,4). In other examples, the image space, the zone sizes, the number of zone rows, and/or the number of zone columns may vary.

[0050] In some examples, the target brightness zones **402** are determined by performing image analysis as described herein. Example image analysis operations may account for predefined zones or selectable zones of an image. For each zone, an average local brightness or histogram is determined. The brightness level for the zone is then set based on the average local brightness or a histogram metric (e.g., an average value or other metric). In some examples, the target brightness zones **402** or related zone brightness data may be used to scale pixel data to account for the brightness zones. In some examples, such scaling may be relative to a maximum brightness level, which can be adjusted by a PSLM.

[0051] In some examples, the target brightness zones **402** or related parameters are used to obtain a digital image **404** based on the operation **416**. In some examples, the number of zones and/or the size of zones for the target brightness zones **402** may be based on predetermined capabilities of an SoC (e.g., the SoC **202** in FIG. 2) or a processor (e.g., the processor in FIG. 1) that generates brightness zones. In other examples, the target brightness zones **402** may be based on a target projector specification, where an SoC (e.g., the SoC **202** in FIG. 2) or a processor (e.g., the processor in FIG. 1) is selected for its ability to support target brightness zones **402** that comply with the target projector specification. In some examples, the operation **416** may determine or obtain an image size and zone size based on the target brightness zones **402** or related parameters.

In some examples, the digital image **404** includes a zone **406** with a target zone size that matches the size of each of the target brightness zones **402**. The target zone size may be based on size parameters or the number of target brightness zones **402**. In other examples, the digital image **404** may be a default digital image, where information or analysis of the target brightness zones **402** is not used. In such other examples, the target brightness zones **402** may be determined later and scaling operations may be used to account for the difference between a target zone size and a default or predetermined size of the zone **406**.

[0052] In some examples, the digital image **404** is used to obtain a baseline hologram **407** based on the operation **418**. In some examples, the operation **418** includes an iterative phase retrieval algorithm such as a Gerchberg-Saxton or similar algorithm. Such algorithms are used to determine the PSLM image plane that will result in the digital image **404** at the far field plane (at the SLM). In some examples, the operations **416** and **418** are offline operations performed before ongoing projector control operations (e.g., before operations of the SLM controller circuitry **210** and the PSLM controller circuitry **220**). In some examples, the baseline hologram **407** may be stored in memory of the PSLM controller circuitry. For example, the baseline hologram **407** may be an example of the baseline hologram **230** stored in the memory **228** of the PSLM controller circuitry **220** in FIG. 2). The baseline hologram **407** is used as PSLM control data to generate the digital image **404** at the far field plane (e.g., at the SLM **170** or **170A** in FIGS. 1, 2, and 3).

[0053] The sub-holograms **408** are the result of transforming the baseline hologram **407** to each target zone position using operation **420**. In some examples, the operation **420** involves multiplying the baseline hologram **407** by respective brightness zone transforms. In the example of FIG. 4, the resulting sub-holograms **408** include sub-holograms **410A** to **410L**. Specially, sub-hologram **410A** relates to zone position (1,1) of the target brightness zones **402**. Sub-hologram **410B** relates to zone position (1,2) of the target brightness zones **402**. Sub-hologram **410C** relates to zone position (1,3) of the target brightness zones **402**. Sub-hologram **410D** relates to zone position (1,4) of the target brightness zones **402**. Sub-hologram **410E** relates to position (2,1) of the target brightness zones **402**. Sub-hologram **410F** relates to position (2,2) of the target brightness zones **402**. Sub-hologram **410G** relates to position (2,3) of the target brightness zones **402**. Sub-hologram **410H** relates to position (2,4) of the target brightness zones **402**. Sub-hologram **410I** relates to position (3,1) of the target brightness zones **402**. Sub-hologram **410J** relates to position (3,2) of the target brightness zones **402**. Sub-hologram **410K** relates to position (3,3) of the target brightness zones **402**. Sub-hologram **410L** relates to position (3,4) of the target brightness zones **402**. In the example of FIG. 4, 12 target zone positions are represented. In other examples, the number of target zone positions and respective sub-holograms may vary.

[0054] In some examples, the operation **420** is based on position shift parameters A.sub.i and B.sub.i. In the example of FIG. 4, the zone **406** is centered in the digital image **404**. For the example of FIG. 4, the sub-hologram **410A** is obtained using a negative A.sub.i to shift one zone up from a central zone position and a negative B.sub.i to shift 1.5 zones to the left from a central zone position. The sub-hologram **410B** is obtained using a negative A.sub.i to shift one zone up from a central zone position and a negative B.sub.i to shift 0.5 zones to the left from a central zone position. The sub-hologram **410C** is obtained using a negative A.sub.i to shift one zone up from a central zone position and a positive B.sub.i to shift 0.5 zones to the right from a central zone position. The sub-hologram **410D** is obtained using a negative A.sub.i to shift one zone up from a central zone position and a positive B.sub.i to shift 1.5 zones to the right from a central zone position.

[0055] The sub-hologram **410E** is obtained using a zeroed A.sub.i so there is no shift up or down from a central zone position and a negative B.sub.i to shift 1.5 zones to the left from a central zone position. The sub-hologram **410F** is obtained using a zeroed A.sub.i so there is no shift up or down from a central zone position and a negative B.sub.i to shift 0.5 zones to the left from a central zone position. The sub-hologram **410G** is obtained using a zeroed A.sub.i so there is no shift up or down

from a central zone position and a positive B.sub.i to shift 0.5 zones to the right from a central zone position. The sub-hologram **410H** is obtained using a zeroed A.sub.i so there is no shift up or down from a central zone position and a positive B.sub.i to shift 1.5 zones to the right from a central zone position.

[0056] The sub-hologram **410I** is obtained using a positive A.sub.i to shift one zone down from a central zone position and a negative B.sub.i to shift 1.5 zones to the left from a central zone position. The sub-hologram **410J** is obtained using a positive A.sub.i to shift one zone down from a central zone position and a negative B.sub.i to shift 0.5 zones to the left from a central zone position. The sub-hologram **410K** is obtained using a positive A.sub.i to shift one zone down from a central zone position and a positive B.sub.i to shift 0.5 zones to the right from a central zone position. The sub-hologram **410L** is obtained using a positive A.sub.i to shift one zone down from a central zone position and a positive B.sub.i to shift 1.5 zones to the right from a central zone position.

[0057] In the example of FIG. 4, the sub-hologram **410A** relates to zone position (1,1) of the target brightness zones **402** and zone position (1,1) of the hologram image **414**. The sub-hologram **410B** relates to zone position (1,2) of the target brightness zones **402** and zone position (1,2) of the hologram image **414**. The sub-hologram **410C** relates to zone position (1,3) of the target brightness zones **402** and zone position (1,3) of the hologram image **414**. The sub-hologram **410D** relates to zone position (1,4) of the target brightness zones **402** and zone position (1,4) of the hologram image **414**. The sub-hologram **410E** relates to zone position (2,1) of the target brightness zones **402** and zone position (2,1) of the hologram image **414**. The sub-hologram **410F** relates to zone position (2,2) of the target brightness zones **402** and zone position (2,2) of the hologram image **414**. The sub-hologram **410G** relates to zone position (2,3) of the target brightness zones **402** and zone position (2,3) of the hologram image **414**. The sub-hologram **410H** relates to zone position (2,4) of the target brightness zones **402** and zone position (2,4) of the hologram image **414**. The sub-hologram **410I** relates to zone position (3,1) of the target brightness zones **402** and zone position (3,1) of the hologram image **414**. The sub-hologram **410J** relates to zone position (3,2) of the target brightness zones **402** and zone position (3,2) of the hologram image **414**. The sub-hologram **410K** relates to zone position (3,3) of the target brightness zones **402** and zone position (3,3) of the hologram image **414**. The sub-hologram **410L** relates to zone position (3,4) of the target brightness zones **402** and zone position (3,4) of the hologram image **414**.

[0058] In some examples, the digital image **404** may have a zone **406** that is not centered. For example, the zone **406** may be in an upper left corner, an upper right corner, a lower left corner, a lower right corner, or another location. For each different position of the zone **406**, the shift parameters A.sub.i and B.sub.i used to determine sub-holograms, such as the sub-holograms **408**, would vary. If the zone **406** is bigger than a target zone size, the operation **420** may apply a first scaling factor (e.g., scale by a value less than 1) to reduce the zone size in the hologram image **414** that will result from each sub-hologram relative to the zone **406**. If the zone **406** is smaller than a target zone size, the operation **420** may apply a second scaling factor (e.g., scale by a value less than 1) to increase the zone size in the hologram image **414** that will result from each sub-hologram relative to the zone **406**.

[0059] In some examples, the operation **420** is an offline operation (before real-time projector control operations are performed) to reduce computation complexity during real-time projector control operations. In such examples, PSLM controller circuitry (e.g., the PSLM controller circuitry **220** in FIG. 2) may have more memory and less processing power. In other examples, the operation **420** is an online operation performed while real-time projector control operations are being performed. In such examples, PSLM controller circuitry (e.g., the PSLM controller circuitry **220** in FIG. 2) may have less memory and more processing power.

[0060] In some examples, the target hologram **412** combines the sub-holograms **408** based on the operation **422**. In some examples, the operation **422** includes: selecting a portion of each of the

sub-holograms **408** based on respective zone brightness levels; and combining the selected portions together to form the target hologram **412**. In some examples, the size of each selected portion for each of the sub-holograms **408** is proportional to the respective brightness levels. For example, a sub-hologram related to a brightest zone of the hologram image **414** will have a larger portion selected versus a sub-hologram related to a less bright zone of the hologram image **414**. To form the target hologram **412**, **12** sub-hologram portions (1 for each of the sub-holograms **408**) are combined. In some examples, combining sub-holograms involves adding the sub-hologram portions or tiles together. The resulting target hologram **412** includes the data for the PSLM that will result in the hologram image **414** at the SLM, including the different brightness levels for each of the zones.

[0061] To form the hologram image **414** from the target hologram **412**, the operation **424** is performed. In some examples, the operation **424** includes providing the target hologram **412** to a PSLM (e.g., the PSLM **160** or **160A** herein) and providing light from a light source (e.g., the light source **150** or **150A** herein). In some examples, forming the hologram image **414** involves adjusting or setting the intensity of light from the light source to support the target brightness zones of hologram image **414**.

[0062] In the example of FIG. **4**, the digital image **404** and the hologram image **414** are considered to be in the image domain, which represents a visible image or related pixel data. In contrast, the baseline hologram **407**, the sub-holograms **408**, and the target hologram **412** are considered to be in the hologram domain, which represents hologram data. Such hologram data appears as random noise in the image domain and is used as control data for a PSLM. In other words, the pixel data for a PSLM is in the hologram domain, while the far field image at the SLM is in the image domain. In the image domain and/or the hologram domain mathematical operations may include frequency domain operations and/or spatial domain operations.

[0063] In the example of FIG. **4**, applying the baseline hologram **407** to a PSLM results in a hologram image at the SLM equivalent to the digital image **404**, where only zone **406** is illuminated. Applying the sub-hologram **410A** to a PSLM results in a hologram image at the SLM with only zone position (1,1) illuminated. Applying the sub-hologram **410B** to a PSLM results in a hologram image at the SLM with only zone position (1,2) illuminated. Applying the sub-hologram **410C** to a PSLM results in a hologram image at the SLM with only zone position (1,3) illuminated. Applying the sub-hologram **410D** to a PSLM results in a hologram image at the SLM with only zone position (1,4) illuminated. Applying the sub-hologram **410E** to a PSLM results in a hologram image at the SLM with only zone position (2,1) illuminated. Applying the sub-hologram **410F** to a PSLM results in a hologram image at the SLM with only zone position (2,2) illuminated. Applying the sub-hologram **410G** to a PSLM results in a hologram image at the SLM with only zone position (2,3) illuminated. Applying the sub-hologram **410H** to a PSLM results in a hologram image at the SLM with only zone position (2,4) illuminated. Applying the sub-hologram **410I** to a PSLM results in a hologram image at the SLM with only zone position (3,1) illuminated. Applying the sub-hologram **410J** to a PSLM results in a hologram image at the SLM with only zone position (3,2) illuminated. Applying the sub-hologram **410K** to a PSLM results in a hologram image at the SLM with only zone position (3,3) illuminated. Applying the sub-hologram **410L** to a PSLM results in a hologram image at the SLM with only zone position (3,4) illuminated. Applying the target hologram **412** to a PSLM results in the hologram image **414**, where the different zones of the hologram image **414** have different brightness levels due to light being distributed differently to the different zones by the PSLM responsive to the target hologram **412**.

[0064] FIG. **5** is a diagram **500** representing transformation of a baseline hologram to sub-holograms in accordance with various examples. In the example of FIG. **5**, the baseline hologram **407** is transformed to obtain the sub-holograms **410A** to **410L** based on the operation **420** described in FIG. **4**. In some examples, the transformation of the baseline hologram **407** to obtain sub-holograms is based on $\text{holo.sub.i}(m, n) = \text{holo.sub.base}(m, n)e^{j\sup.2\pi(mA.\sup.i.\sup.+nB.\sup.i.\sup.)}$,

where A.sub.i and B.sub.i are the position (or phase) shift parameters. In some examples, the baseline hologram **407** is given as holo.sub.base(m, n), where m and n are the row and column numbers for each pixel in the hologram. Each of the sub-holograms **410A** to **410L** may be given as: holo.sub.i(m, n)=holo.sub.base(m, n)e.sup.2π(mA.sup.i.sup.+nB.sup.i.sup.), where A.sub.i and B.sub.i are the position (or phase) shift parameters. As described in FIG. 4, the particular position shift parameter values may vary depending on the position of the zone **406** in the digital image **404**. Other sub-holograms may similarly be determined using a respective position shift transform (sometimes referred to as a brightness zone transform herein).

[0065] FIG. 6 is a diagram **600** representing tiling of sub-holograms to form a target hologram in accordance with various examples. The sub-holograms in FIG. 6 include the sub-holograms **410A** to **410L** described in FIGS. 4 and 5. The target hologram in FIG. 6 includes the target hologram **412** described in FIG. 4. For the example of FIG. 6, the operation **422** selects a respective portion or tile **602A** to **602L** for each of the sub-holograms **410A** to **410L** and combines the selected portions or tiles tile **602A** to **602L** to form the target hologram **412**. The relative size of the respective portion or tile **602A** to **602L** for each of the sub-holograms **410A** to **410L** is proportional to the target brightness level for each of the zones in the hologram image **414**. In some examples, the target hologram is given as: Holo.sub.target(m,n), where m is pixel and n In different examples, the total number of sub-holograms used to form the target hologram **412** may vary depending on the total number of zones in the target brightness zones **402** and the resulting hologram image **414**.

[0066] In the diagram **600**, the sub-hologram **410A** includes a respective tile (or portion) **602A**, the sub-hologram **410K** includes a respective tile **602K**, and the sub-hologram **410L** includes a respective tile **602L**. Likewise, each of the sub-holograms **602B** to **602J** includes a respective tile. The size of each of the tiles **602A** to **602L** in the target hologram **412** determines the amount of power allocated to each respective zone in the hologram image **414**. In the example of FIG. 6, vertical tiling is used to define the tiles **602A** to **602L**. In other examples, horizontal tiling, rectangular tiling, or other tiling options may be used to select portions of each of the sub-holograms **410A** to **410L** and the resulting target hologram **412**. To form the hologram image **414** in the far field (e.g., at the surface or optical input **174** of the SLM **170**), the target hologram **412** is provided to a PSLM such as the PSLM **160** in FIGS. 1 and 2, or the PSLM **160A** in FIG. 3.

[0067] In some examples, the target hologram **412** is given as:

$$[00001] \text{Holo}_{\text{target}}(m, n) = \text{Math.}_{i=1}^I \text{mask}_i(m, n)\text{holo}_i(m, n), \quad \text{Equation(1)}$$

where i is a given zone, I is the total number of zones, holo.sub.i(m, n) are the sub-holograms in the space defined by m and n (the row and column numbers for each pixel in the hologram), and mask.sub.i(m, n) is given as:

$$[00002] \text{Equation(2). } \text{mask}_i(m, n) = \begin{cases} 1 & \text{in area where mask is to be extracted} \\ 0 & \text{elsewhere} \end{cases} \quad \text{Equation(3).}$$

$$\text{For } i \text{ not equal to } j, \text{ Math.}_{i=1}^I \text{ Math.}_{j=1}^I \text{mask}_i(m, n)\text{mask}_j(m, n) = 0. \quad \text{Equation}$$

$$\text{Also, power}_i = \text{Math.}_{m=1}^M \text{ Math.}_{n=1}^N \text{mask}_i(m, n),$$

where power.sub.i is the relative power directed to zone i, and α is a power scaling factor applied to each zone.

[0068] FIG. 7 is a flowchart showing a PSLM controller method **700** in accordance with various examples. The PSLM controller method **700** may be performed, for example, by the controller **102** in FIG. 1, the PSLM control circuitry **130** in FIG. 1, the PSLM control circuitry **220** in FIG. 2, or the controller **302** in FIG. 3. As shown, the PSLM controller method **700** includes obtaining a baseline hologram at block **702**. In some examples, operations **416** and/or **418** described in FIG. 4 and related options may be used to obtain a baseline hologram at block **702**. At block **704**, a sub-hologram for each of a plurality of brightness zones is determined responsive to the baseline hologram and respective brightness zone transforms (see e.g., the diagram **500** of FIG. 5). In some examples, operation **420** described in FIGS. 4 and 5 and related options may be used to obtain sub-

holograms at block **704**. At block **706**, the sub-holograms are combined to produce a target hologram (see e.g., the diagram **600** of FIG. **6**). In some examples, operation **422** described in FIGS. **4** and **5** and related options may be used to produce a target hologram at block **706**. At block **708**, the target hologram is provided to a PSLM (e.g., the PSLM **160** of FIGS. **1** and **2**, or the PSLM **160** in FIG. **3**). In some examples, providing a target hologram to a PSLM at block **708** results in a hologram image (e.g., the hologram image **414** in FIG. **4**) at the far field (e.g., the surface of the SLM), where the hologram image includes target brightness zones (e.g., the target brightness zones **402**) with respective brightness levels.

[0069] FIG. **8** is a flowchart showing a projector control method **800** in accordance with various examples. The projector control method **800** may be performed, for example, by the controller **102** in FIG. **1**, the SLM control circuitry **210**, PSLM control circuitry **220**, and the illumination control circuitry **232** in FIG. **2**, or the controller **302** in FIG. **3**. As shown, the projector control method **800** includes obtaining a baseline hologram at block **802**. In some examples, operations **416** and/or **418** described in FIG. **4** and related options may be used to obtain a baseline hologram at block **802**. At block **804**, zone brightness data is obtained. In some examples, operation **416** described in FIG. **4** and related options may be used to obtain zone brightness data at block **804**. At block **806**, a sub-hologram for each of a plurality of brightness zones is determined responsive to the baseline hologram and respective brightness zone transforms (see e.g., the diagram **500** of FIG. **5**). In some examples, operation **420** described in FIGS. **4** and **5** and related options may be used to obtain sub-holograms at block **806**. At block **808**, the sub-holograms are scaled and combined to produce a target hologram (see e.g., the diagram **600** of FIG. **6**) responsive to the zone brightness data. In some examples, operation **422** described in FIGS. **4** and **5** and related options may be used to produce a target hologram at block **808**. At block **810**, the target hologram is provided to a PSLM (e.g., CS2 includes the target hologram). In some examples, providing a target hologram to a PSLM at block **810** results in a hologram image (e.g., the hologram image **414** in FIG. **4**) at the far field (e.g., the surface of the SLM), where the hologram image includes target brightness zones (e.g., the target brightness zones **402**) with respective brightness levels. At block **812**, an illumination control signal (e.g., CS4 or related signals herein) may be adjusted responsive to the target hologram. In some examples, adjustment of the illumination control signal may be used to dynamically adjust a maximum brightness level during projector control operations. The light (adjusted or not) from the light source is applied to the PSLM, which directs the light to the SLM responsive to the target hologram to generate a hologram image at the surface of the SLM.

[0070] FIG. **9** is a flowchart showing a projector method **900** in accordance with various examples. As shown, the projector method **900** includes producing light using a light source (e.g., the light source **150** or **150A** herein) based on a first control signal (e.g., CS3 herein) at block **902**. At block **904**, a hologram image is formed using a PSLM (e.g., the PSLM **160** or **160A** herein) based on a second control signal (e.g., CS2 herein) and based on the light produced at block **902**. At block **906**, an image (e.g., the projected video **196** herein) is produced using an SLM (e.g., the SLM **170** or **170A** herein) based on the hologram image and a third control signal (e.g., CS1 herein). In some examples, the projector method **900** includes focusing light via a focusing lens (e.g., the focusing lens **314** herein) between the light source and the PSLM. In some examples, the projector method **900** includes passing an image through a projection lens (e.g., the projection lens **324** herein).

[0071] In some examples, a system (e.g., the system **100** in FIG. **1**, the system **200** in FIG. **2**, or the projector **300** in FIG. **3**) includes: an SLM (e.g., the SLM **170** in FIGS. **1** and **2**, or the SLM **170A** in FIG. **3**) having a first array of pixels (e.g., the array of pixels **178** in FIG. **1**); a PSLM (e.g., the PSLM **160** in FIGS. **1** and **2**, or the PSLM **160A** in FIG. **3**) optically coupled to and illuminating the SLM, the PSLM having a second array of pixels (e.g., the array of pixels **168** in FIG. **1**); and control circuitry (e.g., the controller **102** or related components in FIG. **1**, the SLM control circuitry **210**, the PSLM control circuitry **220**, and the illumination control circuitry **232** in FIG. **2**, or the controller **302** in FIG. **3**) coupled to the SLM and PSLM.

[0072] The control circuitry is configured to: obtain a baseline hologram (e.g., the baseline hologram **407** in FIGS. **4** and **5**); determine sub-holograms for a plurality of brightness zones (e.g., the sub-holograms **408** in FIG. **4**, or related sub-holograms **410A** to **410L** in FIGS. **5** and **6**) responsive to the baseline hologram and respective brightness zone transforms (see e.g., the transforms of the diagram **500** in FIG. **5**). The control circuitry is also configured combine the sub-holograms to produce a target hologram (see e.g., the diagram **600** in FIG. **6**); provide the target hologram to the PSLM; and provide control data to the SLM. In such examples, the SLM is configured to adjust the first array of pixels responsive to the control data. The is PSLM configured to adjust the second array of pixels responsive to the target hologram.

[0073] In some examples, the control circuitry is configured to: receive video data (e.g., the video data received at the first terminal **104** of the controller **102** in FIG. **1**, or the video data received at the first terminal **204** of the SoC **202** in FIG. **2**); produce pixel data (e.g., the pixel data at the second terminal **206** of the SoC **202** in FIG. **2**) responsive to the video data; and produce zone brightness data (e.g., the zone brightness data at the third terminal **208** of the SoC **202** in FIG. **2**) responsive to the video data.

[0074] In some examples, the control circuitry is further configured to: receive the pixel data; produce control data (e.g., CS1 herein) responsive to the pixel data; and provide the control data to the SLM. In some examples, the control circuitry is further configured to scale or select a portion of the sub-holograms responsive to the zone brightness data (see e.g., the diagram **600** of FIG. **6**).

[0075] In some examples, the system includes: illumination control circuitry (e.g., the illumination control circuitry **140** in FIG. **1**, or the illumination control circuitry **232** in FIG. **2**) coupled to the control circuitry; and a light source (e.g., the light source **150** in FIGS. **1** to **3**) coupled to the illumination control circuitry and optically coupled to the PSLM. In such examples, the control circuitry is further configured to produce an illumination control signal (e.g., CS4 herein) responsive to the target hologram and to transmit the illumination control signal to the illumination control circuitry. The illumination control circuitry is configured to control the light source based on the illumination control signal.

[0076] In some examples, the respective brightness zone transforms include multiplication of the baseline hologram by a phase function (see e.g., the transforms in the diagram **500** of FIG. **5**). In some examples, combining the sub-holograms to form the target hologram includes tiling the sub-holograms horizontally or vertically (see e.g., the tiling in the diagram **600** of FIG. **6**). In some examples, obtaining the baseline hologram comprises performing an iterative phase retrieval algorithm (e.g., a Gerchberg-Saxton algorithm or similar algorithm).

[0077] In some examples, a method includes: determining, by control circuitry (e.g., the controller **102** in FIG. **1**, the SLM control circuitry **210**, PSLM control circuitry **220**, and the illumination control circuitry **232** in FIG. **2**, or the controller **302** in FIG. **3**) sub-hologram for a plurality of brightness zones (e.g., the sub-holograms **408** in FIG. **4**); combining, by the control circuitry, the sub-holograms to produce a target hologram (see e.g., the diagram **600** in FIG. **6**); and transmitting, by the control circuitry, the target hologram (e.g., the target hologram may be included with CS2 herein).

[0078] In some examples, the method includes: obtaining a baseline hologram (e.g., the baseline hologram **407** in FIGS. **4** and **5**); and determining sub-holograms for the plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms (see e.g., the diagram **500** of FIG. **5**). In some examples, the respective brightness zone transforms include multiplication of the baseline hologram by a respective phase function (e.g., multiplication by $e.\sup.2\pi(mA+nB)$ as described for FIG. **5**).

[0079] In some examples, the method includes: determining the baseline hologram based on an iterative phase retrieval algorithm (e.g., a Gerchberg-Saxton algorithm or similar algorithm); and storing the baseline hologram in a memory (e.g., the memory **228** in FIG. **2**). In such examples, obtaining the baseline hologram includes retrieving the baseline hologram from the memory.

[0080] In some examples, the method includes: obtaining zone brightness data (e.g., based on operations of the controller **102** in FIG. **1**, operations of the SoC **202** in FIG. **2**, or operations of the controller **302** in FIG. **2**); and scaling or tiling the sub-holograms responsive to the zone brightness data (see e.g., the diagram **600** in FIG. **6**). In some examples, combining the sub-holograms to form the target hologram includes tiling the sub-holograms horizontally or vertically. In some examples, the method includes adjusting an illumination control signal (e.g., CS4 herein) responsive to the target hologram.

[0081] In some examples, a projector (e.g., the system **100** in FIG. **1**, the system **200** in FIG. **2**, or components of the projector **300** in FIG. **3**) includes: a PSLM (e.g., the PSLM **160** in FIG. **1**) having an array of pixels (e.g., the array of pixels **168** in FIG. **1**; and a controller (e.g., the controller **102** in FIG. **1**, the PSLM control circuitry **220** in FIG. **2**, or the controller **302** in FIG. **3**) coupled to the PSLM. The controller is configured to: obtain zone brightness data; obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and the zone brightness data; combine the sub-holograms to produce a target hologram; and provide the target hologram to the PSLM, wherein the PSLM is configured to adjust the array of pixels based on the target hologram. In some examples, the baseline hologram may be precomputed and stored in memory to reduce real-time computation. In some examples, the controller is configured to produce an illumination control signal (e.g., CS4 herein) responsive to the target hologram. In some examples, the controller is configured to: determine each sub-hologram by multiplying the baseline hologram by a respective phase function; and scale each sub-hologram based on the zone brightness data. In some examples, the controller is configured to combine the sub-holograms to form the target hologram based on tiling the sub-holograms horizontally or vertically. In some examples, the controller includes an FPGA.

[0082] In this description, the term “couple” may cover connections, communications, or signal paths that enable a functional relationship consistent with this description. For example, if device A generates a signal to control device B to perform an action: (a) in a first example, device A is coupled to device B by direct connection; or (b) in a second example, device A is coupled to device B through intervening component C if intervening component C does not alter the functional relationship between device A and device B, such that device B is controlled by device A via the control signal generated by device A.

[0083] Also, in this description, the recitation “based on” means “based at least in part on.” Therefore, if X is based on Y, then X may be a function of Y and any number of other factors.

[0084] A device that is “configured to” perform a task or function may be configured (e.g., programmed and/or hardwired) at a time of manufacturing by a manufacturer to perform the function and/or may be configurable (or reconfigurable) by a user after manufacturing to perform the function and/or other additional or alternative functions. The configuring may be through firmware and/or software programming of the device, through a construction and/or layout of hardware components and interconnections of the device, or a combination thereof.

[0085] As used herein, the terms “terminal”, “node”, “interconnection”, “pin” and “lead” are used interchangeably. Unless specifically stated to the contrary, these terms are generally used to mean an interconnection between or a terminus of a device element, a circuit element, an integrated circuit, a device or other electronics or semiconductor component.

[0086] A circuit or device that is described herein as including certain components may instead be adapted to be coupled to those components to form the described circuitry or device. For example, a structure described as including one or more semiconductor elements (such as transistors), one or more passive elements (such as resistors, capacitors, and/or inductors), and/or one or more sources (such as voltage and/or current sources) may instead include only the semiconductor elements within a single physical device (e.g., a semiconductor die and/or integrated circuit (IC) package) and may be adapted to be coupled to at least some of the passive elements and/or the sources to form the described structure either at a time of manufacture or after a time of manufacture, for

example, by an end-user and/or a third-party.

[0087] Circuits described herein are reconfigurable to include additional or different components to provide functionality at least partially similar to functionality available prior to the component replacement. Components shown as resistors, unless otherwise stated, are generally representative of any one or more elements coupled in series and/or parallel to provide an amount of impedance represented by the resistor shown. For example, a resistor or capacitor shown and described herein as a single component may instead be multiple resistors or capacitors, respectively, coupled in parallel between the same nodes. For example, a resistor or capacitor shown and described herein as a single component may instead be multiple resistors or capacitors, respectively, coupled in series between the same two nodes as the single resistor or capacitor.

[0088] While certain elements of the described examples are included in an integrated circuit and other elements are external to the integrated circuit, in other examples, additional or fewer features may be incorporated into the integrated circuit. In addition, some or all of the features illustrated as being external to the integrated circuit may be included in the integrated circuit and/or some features illustrated as being internal to the integrated circuit may be incorporated outside of the integrated circuit. As used herein, the term “integrated circuit” means one or more circuits that are: (i) incorporated in/over a semiconductor substrate; (ii) incorporated in a single semiconductor package; (iii) incorporated into the same module; and/or (iv) incorporated in/on the same printed circuit board.

[0089] Uses of the phrase “ground” in the foregoing description include a chassis ground, an Earth ground, a floating ground, a virtual ground, a digital ground, a common ground, and/or any other form of ground connection applicable to, or suitable for, the teachings of this description. In this description, unless otherwise stated, “about,” “approximately” or “substantially” preceding a parameter means being within ± 10 percent of that parameter or, if the parameter is zero, a reasonable range of values around zero.

[0090] Modifications are possible in the described examples, and other examples are possible, within the scope of the claims.

Claims

1. A system comprising: a spatial light modulator (SLM) having a first array of pixels; a phase spatial light modulator (PSLM) optically coupled to and illuminating the SLM, the PSLM having a second array of pixels; and control circuitry coupled to the SLM and PSLM, wherein the control circuitry is configured to: obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms; combine the sub-holograms to produce a target hologram; provide the target hologram to the PSLM; and provide control data to the SLM, the SLM configured to adjust the first array of pixels responsive to the control data, and the PSLM configured to adjust the second array of pixels responsive to the target hologram.
2. The system of claim 1, wherein the control circuitry is configured to: receive video data; produce pixel data responsive to the video data; and produce zone brightness data responsive to the video data for the plurality of brightness zones.
3. The system of claim 2, wherein the control circuitry is further configured to: receive the pixel data; produce the control data responsive to the pixel data; and provide the control data to the SLM.
4. The system of claim 2, wherein the control circuitry is further configured to: scale the sub-holograms responsive to the zone brightness data.
5. The system of claim 1, further comprising: illumination control circuitry coupled to the control circuitry; and a light source coupled to the illumination control circuitry and optically coupled to the PSLM, wherein the control circuitry is further configured to produce an illumination control signal responsive to the target hologram and to transmit the illumination control signal to the

illumination control circuitry, and the illumination control circuitry is configured to control the light source based on the illumination control signal.

6. The system of claim 1, wherein the respective brightness zone transforms include multiplication of the baseline hologram by a phase function.
 7. The system of claim 1, wherein combining the sub-holograms to form the target hologram includes tiling the sub-holograms horizontally or vertically.
 8. The system of claim 1, wherein obtaining the baseline hologram comprises performing an iterative phase retrieval algorithm.
 9. A method comprising: determining, by control circuitry, sub-holograms for a plurality of brightness zones; combining, by the control circuitry, the sub-holograms to produce a target hologram; and transmitting, by the control circuitry, the target hologram.
 10. The method of claim 9, further comprising: obtaining a baseline hologram; and determining the sub-holograms of the plurality of brightness zones responsive to the baseline hologram and respective brightness zone transforms.
 11. The method of claim 10, wherein the respective brightness zone transforms include multiplication of the baseline hologram by a phase function.
 12. The method of claim 10, further comprising: determining the baseline hologram based on an iterative phase retrieval algorithm; and storing the baseline hologram in a memory, wherein obtaining the baseline hologram includes retrieving the baseline hologram from the memory.
 13. The method of claim 9, further comprising: obtaining zone brightness data; and scaling the sub-holograms responsive to the zone brightness data.
 14. The method of claim 9, wherein combining the sub-holograms to form the target hologram includes tiling the sub-holograms horizontally or vertically.
 15. The method of claim 9, further comprising adjusting an illumination control signal responsive to the target hologram.
 16. A projector comprising: a phase spatial light modulator (PSLM) having an array of pixels; and a controller coupled to the PSLM, the controller configured to: obtain zone brightness data; obtain a baseline hologram; determine sub-holograms for a plurality of brightness zones responsive to the baseline hologram and the zone brightness data; combine the sub-holograms to produce a target hologram; and provide the target hologram to the PSLM, wherein the PSLM is configured to adjust the array of pixels based on the target hologram.
 17. The projector of claim 16, wherein the controller is configured to produce an illumination control signal responsive to the target hologram.
 18. The projector of claim 16, wherein the controller is configured to: determine each sub-hologram by multiplying the baseline hologram by a respective phase function; and scale each sub-hologram based on the zone brightness data.
 19. The projector of claim 18, wherein the controller is configured to combine the sub-holograms to form the target hologram based on tiling the sub-holograms horizontally or vertically.
 20. The projector of claim 16, wherein the controller includes a field-programmable gate array (FPGA).
-