

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413197
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Wang; Xiaodong et al.

Band-pass filter circuit and multiplexer

Abstract

Provided are a band-pass filter circuit and a multiplexer. The band-pass filter circuit includes an electromagnetic LC filter circuit and acoustic resonance units. At least one of the acoustic resonance units each includes at least one first acoustic resonator and at least one second acoustic resonator. The first acoustic resonator is connected in series between the band-pass filter circuit and the electromagnetic LC filter circuit. Each of the at least one second acoustic resonator is connected to a terminal of the at least one first acoustic resonator, where the first terminal of the band-pass filter circuit serves as an input terminal or output terminal of the band-pass filter circuit. One or more of the acoustic resonance units are connected on an input side of the electromagnetic LC filter circuit; and the remaining of the acoustic resonance units are connected on an output side of the electromagnetic LC filter circuit.

Inventors:	Wang; Xiaodong (Anhui, CN), He; Chenggong (Anhui, CN), Zuo; Chengjie (Anhui, CN), He; Jun (Anhui, CN)
Applicant:	ANHUI ANUKI TECHNOLOGIES CO., LTD. (Anhui, CN)
Family ID:	81370801
Assignee:	ANHUI ANUKI TECHNOLOGIES CO., LTD. (Anhui, CN)
Appl. No.:	18/257274
Filed (or PCT Filed):	September 07, 2022
PCT No.:	PCT/CN2022/117518
PCT Pub. No.:	WO2023/147724
PCT Pub. Date:	August 10, 2023

Prior Publication Data

Document Identifier	Publication Date
---------------------	------------------

Foreign Application Priority Data

CN

202210115860.4

Feb. 07, 2022

Publication Classification

Int. Cl.: H03H7/00 (20060101); H03H7/01 (20060101); H03H9/58 (20060101)

U.S. Cl.:

CPC H03H7/0161 (20130101); H03H7/0115 (20130101); H03H9/581 (20130101);

Field of Classification Search

CPC: H03H (7/00); H03H (7/0153); H03H (7/0161); H03H (7/12); H03H (7/175); H03H (7/1783); H03H (9/54); H03H (9/542); H03H (9/581); H03H (9/62); H03H (9/64); H03H (9/205)

USPC: 333/167; 333/174; 327/552; 327/557

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11929725	12/2023	He	N/A	H03H 9/605
12316302	12/2024	Hurwitz	N/A	H03H 9/6483
2006/0139125	12/2005	Shiga-ken	N/A	N/A
2015/0070107	12/2014	Tokuda	N/A	N/A
2017/0093365	12/2016	Xu	N/A	N/A
2017/0126201	12/2016	Iwamoto	N/A	N/A
2019/0028085	12/2018	Kato	N/A	N/A
2019/0326883	12/2018	Kim et al.	N/A	N/A
2019/0356300	12/2018	Knapp	N/A	N/A
2020/0028479	12/2019	Ta	N/A	N/A
2022/0263485	12/2021	He et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
103208669	12/2012	CN	N/A
109672421	12/2018	CN	N/A
109672422	12/2018	CN	N/A
111490749	12/2019	CN	N/A
211830724	12/2019	CN	N/A
113556095	12/2020	CN	N/A
114448382	12/2021	CN	N/A
216794959	12/2021	CN	N/A
2596914	12/2021	GB	N/A
H0998046	12/1996	JP	N/A

2003243966	12/2002	JP	N/A
2019024155	12/2018	JP	N/A
2020014204	12/2019	JP	N/A
2021190908	12/2020	JP	N/A
2021-0141914	12/2020	KR	N/A
2005055423	12/2006	WO	N/A
2013180003	12/2012	WO	N/A
2015194581	12/2016	WO	N/A
2021227347	12/2020	WO	N/A

OTHER PUBLICATIONS

Japanese Office Action received for JP Application No. 2023-537701 on Jun. 25, 2024, 6 pgs. cited by applicant

Chinese Office Action received for CN Application No. 202210115860.4 on Mar. 31, 2023, 15 pgs. cited by applicant

International Search Report and Written Opinion received for PCT Serial No. PCT/CN2022/117518 on Dec. 2, 2022, 9 pgs. cited by applicant

European Search Report issued on Oct. 15, 2024 for corresponding EP Application No. 22902463.3 (11 pages). cited by applicant

First Office Action issued on Oct. 30, 2024 for corresponding Korean Application No. 10-2023-7020699 (13 pages including English Translation). cited by applicant

Primary Examiner: Nguyen; Hai L

Attorney, Agent or Firm: Merchant & Gould P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This application is a national stage of International Application No. PCT/CN2022/117518, filed on Sep. 7, 2022, which claims priority to Chinese Patent Application No. 202210115860.4, filed on Feb. 7, 2022, with the China National Intellectual Property Administration, both of which are incorporated herein by reference in their entirety.

FIELD

(2) The present disclosure relates to the technical field of filtering, and in particular to a band-pass filter circuit and a multiplexer.

BACKGROUND

(3) A filter circuit is widely applied in an integrated circuit. An example of such filter circuit is a multiplexer used in the integrated circuit. In modern communications, there is a growing demand for a filter circuit with wide passband and high suppression. Although an electromagnetic LC filter, a duplexer and a multiplexer according to a conventional technology can achieve a low insertion loss within a wide passband, it is difficult to realize a steep roll-off and strong suppression of a wide adjacent band. A method to enhance the suppression characteristic of the adjacent band is to increase a quantity of stages of the filter circuit, which results in an increased dimension of the device and an increased insertion loss.

SUMMARY

(4) A band-pass filter circuit and a multiplexer are provided according to embodiments of the present disclosure, in order to improve a roll-off slope of the band-pass filter circuit, enhance a

suppression characteristic of an adjacent band, and filter an interference signal.

(5) A band-pass filter circuit is provided in the present disclosure. The band-pass filter circuit includes an electromagnetic LC filter circuit and acoustic resonance units. At least one acoustic resonance unit of the acoustic resonance units each includes at least one first acoustic resonator and at least one second acoustic resonator; the at least one first acoustic resonator is connected in series between a first terminal of the band-pass filter circuit and a first terminal of the electromagnetic LC filter circuit; each of the at least one second acoustic resonator is connected to a terminal of the at least one first acoustic resonator; where the first terminal of the band-pass filter circuit serves as an input terminal or output terminal of the band-pass filter circuit; one or more of the acoustic resonance units are connected on an input side of the electromagnetic LC filter circuit; and the remaining one or more of the acoustic resonance units are connected on an output side of the electromagnetic LC filter circuit.

(6) In an embodiment, each acoustic resonance unit other than the at least one acoustic resonance unit includes only one acoustic resonator. One or more acoustic resonators included in an acoustic resonance unit other than the at least one acoustic resonator unit are all connected in series between a second terminal of the band-pass filter circuit and a second terminal of the electromagnetic LC filter circuit, or the one or more acoustic resonators included in an acoustic resonance unit other than the at least one acoustic resonator unit are connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit. The second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

(7) In an embodiment, the at least one acoustic resonance unit each includes a first port, a second port, and three acoustic resonators. The three acoustic resonators include two first acoustic resonators and one second acoustic resonator. The two first acoustic resonators are connected in series between the first port and the second port, the second acoustic resonator is connected to a terminal of the at least one first acoustic resonator; and the at least one acoustic resonance unit is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit. The first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

(8) In an embodiment, the band-pass filter circuit further includes one or both of: at least one first circuit element, each of which includes a first terminal connected to the first port of one of the at least one acoustic resonance unit, and a second terminal connected to the second port of the acoustic resonance unit; and at least one first circuit element, connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit.

(9) In an embodiment, at least one acoustic resonance unit other than the at least one acoustic resonance unit each includes one first port, one second port, and at least three acoustic resonators. The at least three acoustic resonators include at least one first acoustic resonator and at least two second acoustic resonators. The at least one first acoustic resonator is connected in series between the first port and the second port, each of the at least two second acoustic resonators is connected to a terminal of the at least one first acoustic resonator. The at least one acoustic resonance unit is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit. The first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, the first terminal of the electromagnetic

LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

(10) In an embodiment, the at least one acoustic resonance unit other than the at least one acoustic resonance unit each further includes a second circuit element. The second circuit element is connected in parallel between the first port and the second port. The second circuit element includes an inductor or a capacitor.

(11) In an embodiment, a quantity of acoustic resonance units connected between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit is two or more, and adjacent ones of the acoustic resonance units share one of the at least two second acoustic resonators.

(12) In an embodiment, the band-pass filter circuit further includes a substrate and one chip. The electromagnetic LC filter circuit includes at least one inductor and at least one capacitor. The chip is disposed on a side of the substrate. All acoustic resonators in the acoustic resonance units are disposed on the chip. The at least one capacitor is disposed on the chip. The at least one inductor is disposed in the substrate.

(13) In an embodiment, the band-pass filter circuit further includes a substrate and at least two chips. The electromagnetic LC filter circuit includes at least one inductor or at least one capacitor. The at least two chips are disposed on a side of the substrate. All acoustic resonators in the acoustic resonance units are disposed on one of the at least two chips, and the at least one inductor or the at least one capacitor is disposed on another of the at least two chips.

(14) In an embodiment, the band-pass filter circuit further includes a substrate and at least one chip. The electromagnetic LC filter circuit includes at least one inductor or at least one capacitor. The at least one chip is disposed on a side of the substrate. All acoustic resonators in the acoustic resonance units are disposed on the at least one chip. The at least one inductor or the at least one capacitor is disposed in the substrate.

(15) In an embodiment, the band-pass filter circuit further includes an encapsulation layer, a conductive layer, and at least two chips. The electromagnetic LC filter circuit includes at least one inductor and at least one capacitor. The conductive layer is formed as at least one inductor and a connector. All acoustic resonators in the acoustic resonance units are disposed on one of the at least two chips. The at least one capacitor is disposed on another of the at least two chips. The encapsulation layer covers the at least two chips and the conductive layer, and exposes the connector.

(16) A multiplexer is further provided according to the present disclosure. The multiplexer includes the band-pass filter circuit according to any of the above embodiments.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic structural diagram of a band-pass filter circuit according to an embodiment of the present disclosure;

(2) FIG. 2 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;

- (3) FIG. 3 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (4) FIG. 4 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (5) FIG. 5 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (6) FIG. 6 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (7) FIG. 7 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (8) FIG. 8 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (9) FIG. 9 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (10) FIG. 10 is a schematic diagram showing a performance of a band-pass filter circuit as shown in FIG. 9;
- (11) FIG. 11 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (12) FIG. 12 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (13) FIG. 13 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (14) FIG. 14 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure;
- (15) FIG. 15 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure; and
- (16) FIG. 16 is a schematic structural diagram of a multiplexer according to an embodiment of the present disclosure.

DETAILED DESCRIPTION OF EMBODIMENTS

(17) The present disclosure is illustrated below in conjunction with the drawings and embodiments. It should be understood that the specific embodiments described hereafter are only intended to explain the present disclosure, not to limit the present disclosure. It should be further noted that only parts related to the present disclosure, rather than all structures, are shown in the drawings, for ease of description.

(18) A band-pass filter circuit is provided according to an embodiment of the present disclosure. FIG. 1 is a schematic structural diagram of a band-pass filter circuit according to an embodiment of the present disclosure. Reference is made to FIG. 1. The band-pass filter circuit includes an electromagnetic LC filter circuit **00** and at least two acoustic resonance units **10**. At least one acoustic resonance unit **10** of the at least two acoustic resonance units **10** each includes at least one first acoustic resonator **111** and at least one second acoustic resonator **112**. The first acoustic resonator **111** is connected in series between a first terminal of the band-pass filter circuit and a first terminal of the electromagnetic LC filter circuit **00**. The second acoustic resonator **112** is connected to a terminal of the first acoustic resonator **111**. The first terminal of the band-pass filter circuit serves as an input terminal or output terminal of the band-pass filter circuit. At least one of the acoustic resonance units **10** is connected on an input side of the electromagnetic LC filter circuit **00**, and at least one of the acoustic resonance units **10** is connected on an output side of the electromagnetic LC filter circuit **00**.

(19) The electromagnetic LC filter circuit **00** may include an inductor and a capacitor. The electromagnetic LC filter circuit **00** may realize a passband under a specific configuration of the inductor and the capacitor. The electromagnetic LC filter circuit **00** may realize a wide passband.

An input signal, when passes through the electromagnetic LC filter circuit **00**, may be filtered by the electromagnetic LC filter circuit **00**. In a case that at least one acoustic resonance unit **10** is connected on the input side of the electromagnetic LC filter circuit **00**, at least one acoustic resonance unit **10** may be connected in series between an input terminal of the band-pass filter circuit and an input terminal of the electromagnetic LC filter circuit **00**; and alternatively, the at least one acoustic resonance unit **10** may be connected in parallel between the input terminal of the band-pass filter circuit and the input terminal of the electromagnetic LC filter circuit **00**. In a case that at least one acoustic resonance unit **10** is connected on the output side of the electromagnetic LC filter circuit **00**, the at least one acoustic resonance unit **10** may be connected in series between an output terminal of the band-pass filter circuit and an output terminal of the electromagnetic LC filter circuit **00**; and alternatively, the at least one acoustic resonance unit **10** may be connected in parallel between the output terminal of the band-pass filter circuit and the output terminal of the electromagnetic LC filter circuit **00**.

(20) The acoustic resonator in the acoustic resonance unit **10** has a high quality factor, and therefore the acoustic resonance unit **10** is of better frequency selectivity. In other words, the acoustic resonance unit **10** has a large roll-off slope in a frequency transition region between a passband and a stopband. That is, a transition between the passband and the stopband in the band-pass filter circuit has a high speed and a high efficiency. As there are the acoustic resonance unit **10** connected on the input side of the electromagnetic LC filter circuit **00** and the acoustic resonance unit **10** connected on the output side of the electromagnetic LC filter circuit **00**, the acoustic resonance units may both contribute to increasing the roll-off slop on both sides of the passband of the electromagnetic LC filter circuit **00**. Therefore, the band-pass filter circuit has both a wide passband and a steep roll-off slop, which improves a filtering effect of the band-pass filter circuit. The roll-off slope on both sides of the passband includes a roll-off slope between a minimum frequency within the passband and a left adjacent band of the passband (a frequency in the left adjacent band is less than a frequency in the passband), and a roll-off slope between a maximum frequency within the passband and a right adjacent band of the passband (a frequency in the right adjacent band is greater than a frequency in the passband). An adjacent band may refer to a frequency band above or below the passband, and a transition band between the adjacent band and the passband may be 0 MHz to tens of MHz. As an example, a bandwidth of the adjacent band indicates a frequency band ranges over 10% of a central frequency of the passband.

(21) At least one acoustic resonance unit **10** each includes a first acoustic resonator **111** and a second acoustic resonator **112**. In a case that the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, the first resonator **111** is connected in series between the input terminal of the band-pass filter circuit and the input terminal of the electromagnetic LC filter circuit. In a case that the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, the first acoustic resonator **111** is connected in series between the output terminal of the band-pass filter circuit and the output terminal of the electromagnetic LC filter circuit. Reference is made to FIG. **1**. In an example, an acoustic resonator unit **10** includes a first acoustic resonator **111** and a second acoustic resonator **112**. The first resonator **111** is connected in series between the output terminal of the band-pass filter circuit and the output terminal of the electromagnetic LC filter circuit. The second acoustic resonator **112** is connected to a terminal of the first resonator **111**, so that the second acoustic resonator **112** serves as a branch between the input terminal of the band-pass filter circuit and the output terminal of the band-pass filter circuit. Hence, the first acoustic resonator **111** and the second acoustic resonator **112** can form a transmission zero within the adjacent band of the passband. Thereby, an effect of adjacent band suppression of the band-pass filter circuit is improved. Another terminal of the second acoustic resonator **112** is not connected to the first resonator **111**, and may be connected to a ground or another circuit. A series resonant frequency of the second acoustic resonator **112** may be set out of the passband of the band-pass filter circuit, or a parallel resonant

frequency of the second acoustic resonator **112** may be set within the passband of the band-pass filter circuit. Hence, a signal within the passband is prevented from being outputted from the second acoustic resonator **112** to another circuit or the ground, and thereby a signal loss in a band-pass filter circuit is reduced. In a case that the series resonant frequency of the second acoustic resonator **112** is out of the passband of the band-pass filter circuit, for example, the series resonant frequency of the second acoustic resonator **112** may be within the adjacent band, so that a noise signal within the adjacent frequency band may be outputted from the second acoustic resonator **112** to another circuit or the ground. Hence, the noise signal within the adjacent frequency band in the band-pass filter circuit is effectively suppressed, and thereby the filtering effect of the band-pass filter circuit is improved. A parallel resonant frequency of the first acoustic resonator **111** is within a stopband of the band-pass filter circuit, and the parallel resonance frequency of the second acoustic resonator **112** is within the passband of the band-pass filter circuit. Thereby, the roll-off slope on both sides of the passband is increased, and the filtering efficiency of the band-pass filter is improved.

(22) In the technical solution of the embodiment of the present disclosure, both the input side and the output side of the electromagnetic LC filter circuit are provided with the acoustic resonant units. The acoustic resonator in the acoustic resonant units has a high quality factor. Therefore, the acoustic resonant units has a large roll-off slope in the frequency transition region, so that the roll-off slope on both sides of the passband of the band-pass filter circuit is increased. Hence, the band-pass filter circuit realizes a steep roll-off characteristic while maintaining a wide passband of the electromagnetic LC filter circuit. Furthermore, the acoustic resonator can form a transmission zero in the adjacent band, so that the suppression effect of the adjacent band is improved, and thereby the filtering effect of the band-pass filter circuit is improved.

(23) In addition, FIG. 1 exemplarily shows that the band-pass filter circuit includes two acoustic resonance units **10**. One of the acoustic resonance units **10** is connected, in series, to the input side of the electromagnetic LC filter circuit **00**. The other one of the acoustic resonance units **10** is connected, in series, to the output side of the output terminal of the electromagnetic LC filter circuit **00**. The band-pass filter circuit may include multiple acoustic resonance units **10**. In a case that multiple acoustic resonance units **10** are connected on the input side of the electromagnetic LC filter circuit **00**, the multiple acoustic resonance units **10** may be connected to each other in series, and then connected to the input terminal of the electromagnetic LC filter circuit **00**. Alternatively, the multiple acoustic resonance units **10** may be connected to each other in parallel, and then connected to the input terminal of the electromagnetic LC filter circuit **00**. In a case that multiple acoustic resonance units **10** are connected on the output side of the electromagnetic LC filter circuit **00**, the multiple acoustic resonance units **10** may be connected to each other in series, and then connected to the output terminal of the electromagnetic LC filter circuit **00**. Alternatively, the multiple acoustic resonance units **10** may be connected to each other in parallel, and then connected to the output terminal of the electromagnetic LC filter circuit **00**.

(24) FIG. 2 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. Reference is made to FIG. 2. At least one acoustic resonance unit **10** each includes one acoustic resonator **11**. The acoustic resonator **11** is connected in series between a second terminal of the band-pass filter circuit and a second terminal of the electromagnetic LC filter circuit **00**. Alternatively, the acoustic resonator **11** is connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. A first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and a first terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**; and the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**. Alternatively, the first terminal of the band-pass filter circuit

serves as the output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as the output terminal of the electromagnetic LC filter circuit **00**; and the second terminal of the band-pass filter circuit serves as the input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as the input terminal of the electromagnetic LC filter circuit **00**.

(25) FIG. 2 exemplarily shows that there is one acoustic resonance unit **10** includes one acoustic resonator **11**. The acoustic resonator **11** is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. In this case, the second terminal of the band-pass filter circuit serves as the input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as the input terminal of the electromagnetic LC filter circuit **00**. The acoustic resonator **11** is connected in series on the input side of the electromagnetic LC filter circuit **00**, so that a transmission zero may be formed in a right adjacent band of the passband. Thereby, a roll-off slope between a maximum frequency in the passband of the electromagnetic LC filter circuit **00** and the right adjacent band (a frequency in the right adjacent band is greater than a frequency in the passband) is increased, an output amplitude of a noise signal within the right adjacent band is reduced, and a suppression effect of the adjacent band of the band-pass filter circuit is improved.

(26) In an embodiment, the acoustic resonator **11** may be connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. Here, the second terminal of the band-pass filter circuit serves as the output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as the output terminal of the electromagnetic LC filter circuit **00**. In this case, the roll-off slope of the passband of the electromagnetic LC filter circuit **00** is increased, and the suppression effect of the adjacent band of the band-pass filter circuit is improved.

(27) In a further embodiment, there are multiple acoustic resonance units **10** each including one acoustic resonator **11**. Some of the multiple acoustic resonance units **10** are connected on the input side of the electromagnetic LC filter circuit **00**, and the other of the multiple acoustic resonance units **10** are connected on the output side of the electromagnetic LC filter circuit **00**. The above-mentioned effects can also be achieved in this embodiment and are not repeated here.

(28) FIG. 3 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. Reference is made to FIG. 3. In an embodiment, the acoustic resonator **11** may be connected in parallel between a second terminal of the band-pass filter circuit and a second terminal of the electromagnetic LC filter circuit **00**. In this case, the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**. The acoustic resonator **11** is connected in parallel on the input side of the electromagnetic LC filter circuit **00**, so that a transmission zero can be formed within a left adjacent band. Thereby, a roll-off slope between a minimum frequency within the passband of the electromagnetic LC filter circuit **00** and the left adjacent band (a frequency in the left adjacent band is less than a frequency in the passband) is increased, an output amplitude of a noise signal within the left adjacent band is reduced, and a suppression effect of the adjacent band of the band-pass filter circuit is improved.

(29) In an embodiment, the acoustic resonator **11** may be connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. Here, the second terminal of the band-pass filter circuit serves as the output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as the output terminal of the electromagnetic LC filter circuit **00**. In this case, the roll-off slope of the passband of the electromagnetic LC filter circuit **00** is increased, and the suppression effect of the adjacent band of the band-pass filter circuit is improved.

(30) In a further embodiment, there are multiple acoustic resonance units **10** each including one

acoustic resonator **11**. Some of the multiple acoustic resonance units **10** are connected on the input side of the electromagnetic LC filter circuit **00**, and the other of the multiple acoustic resonance units **10** are connected on the output side of the electromagnetic LC filter circuit **00**. The above-mentioned effects can also be achieved in this embodiment and are not repeated here.

(31) In a case that the acoustic resonator **11** is connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**, a terminal of the acoustic resonator **11** is not connected to the band-pass filter circuit, and may be connected to another circuit or ground. For example, the terminal of the acoustic resonator **11** not connected to the band-pass filter circuit may be connected to at least one of a capacitor, an inductor, or the like.

(32) FIG. 4 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. Reference is made to FIG. 4. At least one acoustic resonance unit **10** each includes one first port C1, one second port C2, and three acoustic resonators **11**. The three acoustic resonators **11** consist of two first acoustic resonators **111** and one second acoustic resonator **112**. The two first acoustic resonators **111** are connected in series between the first port C1 and the second port C2. The second acoustic resonator **112** is connected to a terminal of each of the two first acoustic resonators **111**. The at least one acoustic resonance unit **10** is connected in series between a first terminal of the band-pass filter circuit and a first terminal of the electromagnetic LC filter circuit **00**. The first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**. Alternatively, the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**.

(33) FIG. 4 exemplarily shows that the acoustic resonance unit **10** includes the first port C1, the second port C2 and the three acoustic resonators **11**. The three acoustic resonators **11** are connected in a T-shaped pattern. The two first acoustic resonators **111** are connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**. A series resonant frequency of each of the first acoustic resonators **111** is within in the passband, and a transmission zero may be formed in a right adjacent band of the passband. Hence, a roll-off slope on the right side of the passband of the band-pass filter circuit is increased, and a suppression effect of the adjacent band of the band-pass filter circuit is improved. In addition, the second acoustic resonator **112** is connected to a terminal of each of the first acoustic resonators **111**. A series resonant frequency of the second acoustic resonator **112** is set out of the passband of the band-pass filter circuit, or a parallel resonant frequency of the second acoustic resonator **112** is set within the passband of the band-pass filter circuit. Therefore, a signal within the passband is prevented from being outputted from the second acoustic resonator **112** to another circuit or the ground. Hence, a signal loss of the band-pass filter circuit is reduced, a transmission zero can be formed within a left adjacent band of the passband, and the suppression effect of the adjacent band of the band-pass filter circuit is improved. A terminal of the second acoustic resonator **112** is not connected to the first acoustic resonator **111**, and may be connected to the ground or another circuit. Thereby, a noise signal within the adjacent band can be outputted from the second acoustic resonator **112** to another circuit or the ground. Hence, the noise signal within the adjacent band in the band-pass filter circuit is effectively suppressed, and a filtering effect of the band-pass filter circuit is improved.

(34) FIG. 4 exemplarily shows that the acoustic resonance unit **10** is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**. Here, the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**. In another embodiment, the

acoustic resonance unit **10** may be connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**. Here, the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**.

(35) In addition, the terminal of the second acoustic resonator **112** not connected to the first acoustic resonator **111** may be connected to a ground or another circuit. For example, the terminal of the acoustic resonator **11** not connected to the first acoustic resonator **111** may be connected to at least one of a capacitor or an inductor. An overall resonant frequency of the second acoustic resonator **112** and other circuits may be adjusted so that the series resonant frequency of a branch where the second acoustic resonator **112** is located is out of the passband of the band-pass filter circuit, or the parallel resonant frequency of the branch where the second acoustic resonator **112** is located is within the passband of the band-pass filter circuit. Hence, the signal whose frequency is within the passband can be prevented from being outputted from the second acoustic resonator **112** to another circuit, and thereby a loss of the band-pass filter circuit is reduced.

(36) FIG. 5 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. Reference is made to FIG. 5. Multiple acoustic resonance units **10** are connected on one side of the electromagnetic LC filter circuit **00**. Each of the acoustic resonance units **10** includes three acoustic resonators **11**. The acoustic resonance units **10** may be connected in series to each other, and adjacent ones of the acoustic resonance units **10** may share one first acoustic resonator **111**, so as to form multiple T-shaped connections. With the multiple acoustic resonance units **10**, a filtering effect of the acoustic resonance units **10** can be further improved. In addition, each acoustic resonance unit **10** includes multiple transmission zeros within an adjacent frequency band. In a case that the band-pass filter circuit has multiple acoustic resonance units **10**, the band-pass filter circuit has more transmission zeros within the adjacent frequency band. Therefore, the output amplitude of a noise signal within the adjacent frequency band can be further reduced, and the suppression effect of the adjacent band of the band-pass filter circuit is improved.

(37) In a case that at least one acoustic resonance unit **10** each includes an acoustic resonator **11**, the at least one acoustic resonance unit **10** may be disposed on one of the input side and the output side of the electromagnetic LC filter circuit **00**, and the acoustic resonance units **10** each including three acoustic resonators **11** may be disposed on the other one of the input side and the output side of the electromagnetic LC filter circuit **00**, which is not repeated here.

(38) FIG. 6 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. 6, the band-pass filter circuit further includes at least one first circuit element **20**. For each first circuit element, a first terminal of the first circuit element **20** is connected to a first port C1 of an acoustic resonance unit, and a second terminal of the first circuit element **20** is connected to a second port C2 of the acoustic resonance unit. Alternatively or additionally, the at least one first circuit element **20** is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**.

(39) The first circuit element **20** includes an inductor or a capacitor. FIG. 6 exemplarily shows that the first circuit element **20** is a capacitor. The first circuit element **20** is connected between the first port C1 and the second port C2, that is, the capacitor is connected to two first acoustic resonators **111** in parallel. A resonant frequency of the first acoustic resonators **111** can be controlled through the capacitor so that a resonant frequency of the parallel structure formed by the capacitor and the first acoustic resonators **111** is out of the passband of the band-pass filter circuit. Hence, a noise signal out of the passband of the band-pass filter circuit is suppressed, and a filtering effect of the band-pass filter circuit is improved.

(40) In an embodiment, the first circuit element **20** is an inductor. The first circuit element **20** may

be connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**. Thereby, the filtering function of the band-pass filter circuit is realized.

(41) In an embodiment, multiple first circuit elements **20** are included. Reference is made to FIG. 7, which is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. FIG. 7 exemplarily shows that two first circuit elements **20** are included. One of the first circuit elements **20** is a capacitor. The capacitor is connected in parallel between a first port C1 and a second port C2. The other one of the first circuit elements **20** is an inductor. The inductor is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit **00**. The multiple first circuit elements **20** are disposed, so that the filtering function of the band-pass filter can be further improved.

(42) FIG. 8 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. Reference is made to FIG. 8. At least one acoustic resonance unit **10** each includes one first port C1, one second port C2, and at least three acoustic resonators **11**. The at least three acoustic resonators **11** consist of at least one first acoustic resonator **111** and at least two second acoustic resonators **112**. The first acoustic resonator **111** is connected in series between the first port C1 and the second port C2. The second acoustic resonators **112** are connected to a terminal of the first acoustic resonator **111**. The acoustic resonance unit **10** is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. The first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**, the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**. Alternatively, the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit **00** serves as an input terminal of the electromagnetic LC filter circuit **00**, the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**.

(43) FIG. 8 exemplarily shows that the acoustic resonator unit **10** includes three acoustic resonators **11**. The three acoustic resonators **11** are connected in a π -shaped pattern. The first acoustic resonator **111** is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. A series resonant frequency of the first acoustic resonator **111** is within the passband, and a transmission zero can be formed in an adjacent band of the passband. A roll-off slope on both sides of the passband of the band-pass filter circuit is increased, and the suppression effect of an adjacent band of the band-pass filter circuit is improved. In addition, one of the second acoustic resonators **112** is connected to a terminal of the first acoustic resonator **111**, and the other one of the second acoustic resonators **112** is connected to another terminal of the first acoustic resonator **111**. Hence, a transmission zero can be formed in the left adjacent band of the passband, so that the suppression effect of the adjacent band of the band-pass filter circuit is further improved. For each of the second acoustic resonators **112**, a terminal of the second acoustic resonator **112** is not connected to the first acoustic resonator **111**, and may be connected to the ground or another circuit. A series resonant frequency of the second acoustic resonator **112** may be set out of the passband of the band-pass filter circuit, or a parallel resonant frequency of the second acoustic resonator **112** is set within the passband of the band-pass filter circuit. Hence, a signal in the passband is prevented from being outputted from the second acoustic resonator **112** to another circuit or the ground, and a signal loss of the band-pass filter circuit is reduced. In a case that the series resonant frequency of the second acoustic resonator **112** is out of

the passband of the band-pass filter circuit, for example, the series resonant frequency of the second acoustic resonator **112** may be within the adjacent band. Thereby, a noise signal within the adjacent band can be prevented from being outputted from the second acoustic resonator **112** to another circuit or the ground. Hence, the noise signal within the adjacent band in the band-pass filter circuit is effectively suppressed, and a filtering effect of the band-pass filter circuit is improved.

(44) FIG. **8** exemplarily shows that the acoustic resonance unit **10** is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. here, the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, the second terminal of the electromagnetic LC filter circuit **00** serves as an output terminal of the electromagnetic LC filter circuit **00**. In another embodiment, the acoustic resonance unit **10** may be connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**. Here, the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit **00** serves as input terminal of the electromagnetic LC filter circuit **00**.

(45) In addition, the terminal of the second acoustic resonator **112** not connected to the first acoustic resonator **11** may be connected to a ground terminal or another circuit. For example, the terminal of the acoustic resonator **11** not connected to the first acoustic resonator **111** may be connected to at least one of a capacitor or an inductor. An overall resonant frequency of the second acoustic resonator **112** and other circuits may be adjusted so that the series resonant frequency of a branch where the second acoustic resonator **112** is located is out of the passband of the band-pass filter circuit, or the parallel resonant frequency of the branch where the second acoustic resonator **112** is located is within the passband of the band-pass filter circuit. Hence, the signal whose frequency is within the passband can be prevented from being outputted from the second acoustic resonator **112** to another circuit, and thereby a loss of the band-pass filter circuit is reduced.

(46) FIG. **9** is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. **9**, at least one acoustic resonance unit **10** each further includes a second circuit element **30**. The second circuit element **30** is connected in series between a first port C1 and a second port C2. The second circuit element **30** includes an inductor or a capacitor.

(47) The second circuit element **30** is connected in series between the first port C1 and the second port C2 of an acoustic resonator unit **10**. Hence, the second circuit element **30** is connected with at least one first acoustic resonator **111** in parallel. The second circuit element **30** includes an inductor or a capacitor. A passband of the band-pass filter circuit may be adjusted by adjusting an electrical parameter of a parallel structure of the second circuit element **30** and the first acoustic resonator **111**. By adjusting the electrical parameter of an integral structure of the first acoustic resonator **111** and the second circuit element **30**, a position of the transmission zero of the acoustic resonance unit can be optimized, an output amplitude of a noise signal within an adjacent frequency band can be reduced, and a suppression effect of the adjacent frequency band of the band-pass filter circuit is improved.

(48) FIG. **10** is a schematic diagram showing a performance of a band-pass filter circuit as shown in FIG. **9**. In FIG. **10**, an abscissa represents a frequency, and an ordinate is the insertion loss. Curve **1** shows a frequency of the electromagnetic LC filter circuit vs. an insertion loss of the electromagnetic LC filter circuit. Curve **2** shows a frequency of a band-pass filter circuit as shown in Figure vs. an insertion loss of the band-pass filter circuit as shown in FIG. **9**. Reference is made to FIG. **10**. The curve **2** indicates a passband much greater than 200 MHz. A roll-off slope of a frequency attenuation region of curve **2** is greater than a roll-off slope of a frequency attenuation region of curve **1**. As can be seen, the band-pass filter circuit in the present disclosure has both a wide passband and a steep roll-off slope, so that the filtering effect of the band-pass filter circuit is

improved. In addition, a first acoustic resonator **111** is connected to an inductor in parallel, and the first acoustic resonator **111** and the inductor are connected in series to the input side of the electromagnetic LC filter circuit **00**. A first acoustic resonator **111** is connected to a capacitor in parallel, and the first acoustic resonator **111** and the capacitor are connected in series to an output side of the electromagnetic LC filter circuit **00**. Multiple second acoustic resonators **112** are connected in parallel to the input side and the output side of the electromagnetic LC filter circuit **00**. Therefore, transmission zeroes **101** are formed within an adjacent band on either side of the passband of the band-pass filter circuit. Hence, the output amplitude of a noise signal within the adjacent band is reduced, the suppression effect of the adjacent band of the band pass filter circuit is improved, and the filtering effect of the band-pass filter circuit is effectively improved. In a case that a parallel resonator frequency of the second acoustic resonator **112** is within the passband, the second acoustic resonator **112** can block a signal whose frequency is within the passband. Hence, an attenuation of the signal whose frequency is within the passband is reduced and the filtering effect of the band-pass filter circuit is improved. Reference is further made to FIG. **10**. Compared with curve **1**, the adjacent band shown by curve **2** is a wideband, that is, a bandwidth of curve **2** for frequency suppression of the adjacent band is greater than 200 MHz. Hence, a wideband suppression of the adjacent band is realized and the filtering effect of the band-pass filter circuit is improved.

(49) Based on the above technical solutions, in a case that at least two acoustic resonance units **10** are connected between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit **00**, adjacent ones of the acoustic resonance units **10** share one second acoustic resonator **11**.

(50) In a case that multiple acoustic resonance units **10** are disposed on one side of the electromagnetic LC filter circuit **00** and each of the acoustic resonance units **10** includes three acoustic resonators **11**, the acoustic resonance units **10** may be connected in series, and adjacent ones of the acoustic resonance units **10** may share one second acoustic resonator **11**, so as to form multiple π -shaped connections. The multiple acoustic resonance units **10** are disposed, so that the filtering effect of the acoustic resonance units **10** is further improved. In addition, each of the acoustic resonance units **10** includes transmission zeros in multiple adjacent bands. With the multiple acoustic resonance units **10**, the band-pass filter circuit has more transmission zeros in adjacent bands. Hence, an output amplitude of a noise signal within an adjacent band is further reduced, and the suppression effect of the adjacent band of the band-pass filter circuit is improved.

(51) FIG. **11** is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. **11**, the band-pass filter circuit further includes a substrate **40** and at least one chip **60**. The electromagnetic LC filter circuit **00** includes at least one inductor **L1** and at least one capacitor **Cs1**. The at least one chip **60** is disposed on one side of the substrate **40**. Both the at least one acoustic resonator **11** and the at least one capacitor **Cs1** are disposed on the chip **60**. The at least one inductor **L1** is disposed in the substrate **40**.

(52) A conductive layer **50** is disposed within the substrate **40**, for forming the inductor **L1**. In a case that the conductive layer **50** includes multiple layers, the inductor **L1** may be of a three-dimensional inductor structure. Hence, an area for the inductor **L1** may be reduced while ensuring an inductance of the inductor **L1** and a quality factor of the inductor, which is beneficial to reducing an area occupied by the band-pass filter circuit. The acoustic resonator **11** may be at least one of the first acoustic resonator **111** or the second acoustic resonator **112**. The acoustic resonator **11** may be integrated on the chip **60** through a chip integration process, so as to ensure a performance of the acoustic resonator **11**. An electrical connection between the acoustic resonator **11** on the chip **60** and the inductor **L1** in the substrate **40** may be realized through a solder ball, a copper pillar, metal bonding, and other methods.

(53) The capacitor **Cs1** is disposed on the chip **60**, so that the capacitor **Cs1** has a high quality factor and consistency, which is beneficial to improving the filtering performance of the band-pass

filter circuit. The consistency refers to that capacitors Cs1 from different batches are the same or slightly different in terms of an electrical performance, or capacitors Cs1 at different positions on a same wafer are the same or slightly different in terms of the electrical performance. A relatively large capacitance may be generated with a relatively small occupied space. An occupied space of the capacitor Cs1 is reduced while ensuring the quality factor of the capacitor Cs1, which is beneficial to reducing an occupied space of the band-pass filter circuit. FIG. 11 exemplarily shows that the capacitor Cs1 and the acoustic resonator 11 are disposed on a same chip 60.

(54) FIG. 12 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. 12, the band-pass filter circuit further includes a substrate 40 and at least two chips 60. The electromagnetic LC filter circuit 00 includes at least one of an inductor L1 or a capacitor Cs1. The at least two chips 60 are arranged on one side of the substrate 40. At least one acoustic resonator 11 is disposed on one of the chips 60. The at least one of the capacitor Cs1 or the inductor L1 is disposed on one of the chips 60 other than the chip disposed with the acoustic resonator 11.

(55) FIG. 12 exemplarily shows that the electromagnetic LC filter circuit 00 includes two chips 60 and one capacitor Cs1. The acoustic resonator 11 is disposed on one of the chips 60. The capacitor Cs1 is disposed on the other of the chips 60. By forming different elements on different chips 60, a yield of the element can be better controlled. Hence, a yield of the band-pass filter circuit formed after the acoustic resonator 11 and the electromagnetic LC filter circuit 00 are connected to each other is improved, which is beneficial to reducing a cost of the band-pass filter circuit.

(56) FIG. 12 exemplarily shows that only the capacitor Cs1 is disposed on the chip 60. In another embodiment, an inductor in the electromagnetic LC filter circuit may be disposed on the chip 60, so as to reduce provision of the inductor in the substrate 40.

(57) FIG. 13 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. 13, the band-pass filter circuit further includes a substrate 40 and at least one chip 60, and the electromagnetic LC filter circuit 00 includes at least one of an inductor L1 or a capacitor Cs1. The at least one chip 60 is disposed on one side of the substrate 40. At least one acoustic resonator 11 is disposed on the chip 60, and the at least one of a capacitor Cs1 or an inductor L1 is disposed in the substrate 40.

(58) FIG. 13 exemplarily shows that the band-pass filter circuit includes one chip 60, and the electromagnetic LC filter circuit 00 includes one inductor L1 and one capacitor Cs1. The acoustic resonator 11 may be at least one of a first acoustic resonator 111 or a second acoustic resonator 112. The acoustic resonator 11 is disposed on the chip 60, so as to ensure a performance of the acoustic resonator 11. A multi-layer conductive layer 50 may be included in the substrate 40, and dielectric layers are filled between layers of the conductive layer 50. In a case that the inductor L1 and the capacitor Cs1 are disposed in the substrate 40, the inductor L1 may be formed in a three-dimensional structure through the multi-layer conductive layer 50. Hence, an area for the inductor L1 may be reduced, while ensuring an inductance of the inductor L1 and a quality factor of the inductor, which is beneficial to reducing an occupied area of the band-pass filter circuit. In addition, multiple capacitors Cs1 may be connected to each other in series or in parallel.

(59) FIG. 14 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. 14, the band-pass filter circuit further includes an encapsulation layer 70, a conductive layer 80, and at least two chips 90. The electromagnetic LC filter circuit 00 includes at least one inductor L1 and at least one capacitor Cs1. The conductive layer 80 is formed as at least one inductor L1 and a connector T1. At least one acoustic resonator 11 is disposed on the chip 90. The at least one capacitor Cs1 is disposed on another chip 90. The encapsulation layer 70 covers the chips 90 and the conductive layer 80, and exposes the connector T1.

(60) The conductive layer 80 may form an inductor L1. In a case that the conductive layer 80 includes multiple layers, the inductor L1 may be of a three-dimensional structure. Hence, an area

for the inductor L1 may be reduced while ensuring an inductance of the inductor L1 and a quality factor of the inductor, which is beneficial to reducing an occupied area of the band-pass filter circuit. The encapsulation layer 70 covers the conductive layer 80, so that the inductor L1 is embedded within the encapsulation layer 70. Therefore, a high quality factor of the inductor L1 is ensured. FIG. 14 exemplarily shows that the band-pass filter circuit includes two chips 90. One of the chips 90 is disposed with the acoustic resonator 11, so as to ensure a performance of the acoustic resonator 11. The other one of the chips 90 is disposed with the capacitor Cs1, so that the capacitor Cs1 has a high quality factor and better consistency, which is beneficial to improving a filtering performance of the band-pass filter circuit. A relatively large capacitance may be generated with a relatively small occupied space. An occupied space of the capacitor Cs1 is reduced while ensuring the quality factor of the capacitor Cs1, which is beneficial to reducing an occupied space of the band-pass filter circuit. The encapsulation layer 70 covers the chips 90 and the conductive layer 80, so that the band-pass filter circuit has an integrated encapsulation layer 70. The connector T1 is exposed, forming a fan-out packaging. Thereby, an integration and reliability of modules of the band-pass filter circuit is improved.

(61) In another embodiment, the capacitor Cs1 and the acoustic resonator 11 may be disposed on a same chip 90. FIG. 15 is a schematic structural diagram of a band-pass filter circuit according to another embodiment of the present disclosure. As shown in FIG. 15, the electromagnetic LC filter circuit 00 includes two capacitors Cs1. One capacitor Cs1 is independently disposed on a chip 90. The other capacitor Cs1 and the acoustic resonator 11 are both disposed on another chip 90. In addition, in a case that the electromagnetic LC filter circuit 00 includes multiple capacitors Cs1 and the band-pass filter circuit includes multiple acoustic resonators 11, the band-pass filter circuit may include multiple chips 90. For each of the chips 90, the chip may be disposed with merely an capacitor Cs1, forming a capacitor chip; or the chip may be disposed with merely an acoustic resonator 11, forming an acoustic resonator chip; or the chip may be disposed with both the capacitor Cs1 and the acoustic resonator 11, forming a hybrid chip, which depends on a requirement and is not limited here.

(62) A multiplexer is further provided according to an embodiment of the present disclosure. FIG. 16 is a schematic structural diagram of a multiplexer according to an embodiment of the present disclosure. As shown in FIG. 16, the multiplexer includes a band-pass filter circuit 210 according to any of the embodiments of the present disclosure.

(63) Reference is further made to FIG. 16. The multiplexer includes a first terminal IN and at least two second terminals. Each band-pass filter circuit 210 is connected in series between the first terminal IN and one of the second terminals of the multiplexer.

(64) FIG. 16 exemplarily shows that the multiplexer includes one first terminal IN and n second terminals. The second terminals are noted as OUT1, OUT2 . . . OUTn, respectively. Each band-pass filter circuit 210 is connected in series between the first terminal IN and one of the second terminals. For example, a first band-pass filter circuit 210 is connected in series between the first terminal IN and a first one of the second terminal, OUT1; a second band-pass filter circuit 210 is connected in series between the first terminal IN and a second one of the second terminals, OUT2; and the like. The multiplexer includes the band-pass filter circuit 210 according to any one of the embodiments of the present disclosure, and therefore has the effect of the band-pass filter circuit. The multiplexer has a high roll-off slope, so that a suppression of a steep transition band can be realized. In addition, the suppression effect of an adjacent band of the band-pass filter circuit can be improved, so that a wideband suppression of the adjacent band is realized. Hence, the filtering effect of the band-pass filter circuit is improved.

(65) It should be noted that the multiplexer may further include a filter circuit other than the band-pass filter circuit described above. The filter circuit is connected in series between the first terminal IN and any one of the second terminals. The filter circuit may be a low-pass filter circuit, a high-pass filter circuit, or a band-pass filter circuits, which is not limited here.

Claims

1. A band-pass filter circuit, comprising an electromagnetic LC filter circuit and acoustic resonance circuits, wherein at least one first acoustic resonance circuit of the acoustic resonance circuits each comprises at least one first acoustic resonator and at least one second acoustic resonator; the at least one first acoustic resonator is connected in series between a first terminal of the band-pass filter circuit and a first terminal of the electromagnetic LC filter circuit; each of the at least one second acoustic resonator is connected to a terminal of the at least one first acoustic resonator, wherein the first terminal of the band-pass filter circuit serves as an input terminal or output terminal of the band-pass filter circuit; one or more of the acoustic resonance circuits are connected on an input side of the electromagnetic LC filter circuit; and the remaining one or more of the acoustic resonance circuits are connected on an output side of the electromagnetic LC filter circuit.
2. The band-pass filter circuit according to claim 1, wherein each acoustic resonance circuit other than the at least one first acoustic resonance circuit comprises only one acoustic resonator; and one or more acoustic resonators comprised in an acoustic resonance circuit other than the at least one first acoustic resonator circuit are all connected in series between a second terminal of the band-pass filter circuit and a second terminal of the electromagnetic LC filter circuit, or the one or more acoustic resonators comprised in an acoustic resonance circuit other than the at least one first acoustic resonator circuit are connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit, wherein the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit, or the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.
3. The band-pass filter circuit according to claim 1, wherein the at least one first acoustic resonance circuit each comprises a first port, a second port, and three acoustic resonators; the three acoustic resonators comprise two first acoustic resonators and one second acoustic resonator; the two first acoustic resonators are connected in series between the first port and the second port, the second acoustic resonator is connected to a terminal of the at least one first acoustic resonator; and the at least one first acoustic resonance circuit is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit; wherein the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.
4. The band-pass filter circuit according to claim 3, further comprising one or both of: at least one first circuit element, each of which comprises a first terminal connected to the first port of one of the at least one first acoustic resonance circuit, and a second terminal connected to the second port of the first acoustic resonance circuit; and at least one first circuit element, connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit.
5. The band-pass filter circuit according to claim 1, wherein at least one second acoustic resonance circuit other than the at least one first acoustic resonance circuit each comprises one first port, one second port, and at least three acoustic resonators; the at least three acoustic resonators comprise at least one first acoustic resonator and at least two second acoustic resonators; the at least one first acoustic resonator is connected in series between the first port and the second port, each of the at least two second acoustic resonators is connected to a terminal of the at least one first acoustic

resonator; and the at least one second acoustic resonance circuit is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit; wherein the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

6. The band-pass filter circuit according to claim 5, wherein the at least one second acoustic resonance circuit other than the at least one first acoustic resonance circuit each further comprises a second circuit element, and the second circuit element is connected in parallel with the at least one first acoustic resonator of the at least one second acoustic resonance circuit, and is connected between the first port and the second port; wherein the second circuit element comprise an inductor or a capacitor.

7. The band-pass filter circuit according to claim 5, wherein a quantity of second acoustic resonance circuits connected between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit is two or more, and adjacent ones of the second acoustic resonance circuits share one of the at least two second acoustic resonators.

8. The band-pass filter circuit according to claim 1, further comprising a substrate and one chip, wherein the electromagnetic LC filter circuit comprises at least one inductor and at least one capacitor; the chip is disposed on a side of the substrate; all acoustic resonators in the acoustic resonance circuits are disposed on the chip; the at least one capacitor is disposed on the chip; and the at least one inductor is disposed in the substrate.

9. The band-pass filter circuit according to claim 1, further comprising a substrate and at least two chips, wherein the electromagnetic LC filter circuit comprises at least one inductor or at least one capacitor; the at least two chips are disposed on a side of the substrate; all acoustic resonators in the acoustic resonance circuits are disposed on one of the at least two chips, and the at least one inductor or the at least one capacitor is disposed on another of the at least two chips.

10. The band-pass filter circuit according to claim 1, further comprising a substrate and at least one chip, wherein the electromagnetic LC filter circuit comprises at least one inductor or at least one capacitor; the at least one chip is disposed on a side of the substrate; all acoustic resonators in the acoustic resonance circuits are disposed on the at least one chip, and the at least one inductor or the at least one capacitor is disposed in the substrate.

11. The band-pass filter circuit according to claim 1, further comprising an encapsulation layer, a conductive layer, and at least two chips, wherein the electromagnetic LC filter circuit comprises at least one inductor and at least one capacitor; the at least one inductor and a connector is located in the conductive layer, all acoustic resonators in the acoustic resonance circuits are disposed on one of the at least two chips, the at least one capacitor is disposed on another of the at least two chips, and the encapsulation layer covers the at least two chips and the conductive layer, and exposes the connector.

12. A multiplexer, comprising a band-pass filter circuit, wherein the band-pass filter circuit comprises an electromagnetic LC filter circuit and acoustic resonance circuits; at least one first acoustic resonance circuit of the acoustic resonance circuits each comprises at least one first acoustic resonator and at least one second acoustic resonator; the at least one first acoustic resonator is connected in series between a first terminal of the band-pass filter circuit and a first terminal of the electromagnetic LC filter circuit; each of the at least one second acoustic resonator

is connected to a terminal of the at least one first acoustic resonator, wherein the first terminal of the band-pass filter circuit serves as an input terminal or output terminal of the band-pass filter circuit; one or more of the acoustic resonance circuits are connected on an input side of the electromagnetic LC filter circuit; and the remaining one or more of the acoustic resonance circuits are connected on an output side of the electromagnetic LC filter circuit.

13. The multiplexer according to claim 12, wherein in the band-pass filter circuit, each acoustic resonance circuit other than the at least one first acoustic resonance circuit comprises only one acoustic resonator; and one or more acoustic resonators comprised in an acoustic resonance circuit other than the at least one first acoustic resonator circuit are all connected in series between a second terminal of the band-pass filter circuit and a second terminal of the electromagnetic LC filter circuit, or the one or more acoustic resonators comprised in an acoustic resonance circuit other than the at least one first acoustic resonator circuit are connected in parallel between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit, wherein the second terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit, or the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

14. The multiplexer according to claim 12, wherein in the band-pass filter circuit, the at least one first acoustic resonance circuit each comprises a first port, a second port, and three acoustic resonators; the three acoustic resonators comprise two first acoustic resonators and one second acoustic resonator; the two first acoustic resonators are connected in series between the first port and the second port, the second acoustic resonator is connected to a terminal of the at least one first acoustic resonator; and the at least one first acoustic resonance circuit is connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit; wherein the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the first terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

15. The multiplexer according to claim 14, wherein the band-pass filter circuit further comprises one or both of: at least one first circuit element, each of which comprises a first terminal connected to the first port of one of the at least one first acoustic resonance circuit, and a second terminal connected to the second port of the first acoustic resonance circuit; and at least one first circuit element, connected in series between the first terminal of the band-pass filter circuit and the first terminal of the electromagnetic LC filter circuit.

16. The multiplexer according to claim 12, wherein in the band-pass filter circuit, at least one second acoustic resonance circuit other than the at least one first acoustic resonance circuit each comprises one first port, one second port, and at least three acoustic resonators; the at least three acoustic resonators comprise at least one first acoustic resonator and at least two second acoustic resonators; the at least one first acoustic resonator is connected in series between the first port and the second port, each of the at least two second acoustic resonators is connected to a terminal of the at least one first acoustic resonator; and the at least one second acoustic resonance circuit is connected in series between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit; wherein the first terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an input terminal of the band-

pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit; or the first terminal of the band-pass filter circuit serves as an input terminal of the band-pass filter circuit, the first terminal of the electromagnetic LC filter circuit serves as an input terminal of the electromagnetic LC filter circuit, the second terminal of the band-pass filter circuit serves as an output terminal of the band-pass filter circuit, and the second terminal of the electromagnetic LC filter circuit serves as an output terminal of the electromagnetic LC filter circuit.

17. The multiplexer according to claim 16, wherein in the band-pass filter circuit, the at least one second acoustic resonance circuit other than the at least one first acoustic resonance circuit each further comprises a second circuit element, and the second circuit element is connected in parallel with the at least one first acoustic resonator of the at least one second acoustic resonance circuit, and is connected between the first port and the second port; wherein the second circuit element comprise an inductor or a capacitor.

18. The multiplexer according to claim 16, wherein in the band-pass filter circuit, a quantity of second acoustic resonance circuits connected between the second terminal of the band-pass filter circuit and the second terminal of the electromagnetic LC filter circuit is two or more, and adjacent ones of the second acoustic resonance circuits share one of the at least two second acoustic resonators.

19. The multiplexer according to claim 12, wherein the band-pass filter circuit further comprises a substrate and at least one chip, and wherein the electromagnetic LC filter circuit comprises at least one inductor or at least one capacitor; the at least one chip is disposed on a side of the substrate; all acoustic resonators in the acoustic resonance circuits are disposed on the at least one chip, and the at least one inductor or the at least one capacitor is disposed in the substrate.

20. The multiplexer according to claim 12, wherein the band-pass filter circuit further comprises an encapsulation layer, a conductive layer, and at least two chips, and wherein the electromagnetic LC filter circuit comprises at least one inductor and at least one capacitor; the at least one inductor and a connector is located in the conductive layer, all acoustic resonators in the acoustic resonance circuits are disposed on one of the at least two chips, the at least one capacitor is disposed on another of the at least two chips, and the encapsulation layer covers the at least two chips and the conductive layer, and exposes the interface.
