

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                    |
|----------------------|--------------------|
| United States Patent | 12407859           |
| Kind Code            | B2                 |
| Date of Patent       | September 02, 2025 |
| Inventor(s)          | Koo; Moonmo et al. |

---

### Method for processing image on basis of transform and device therefor

---

#### Abstract

Embodiments of the present disclosure provide a method and apparatus for processing a video signal. A method for decoding a video signal according to an embodiment of the present disclosure includes obtaining a sub-block transform (SBT) flag indicating whether an SBT is applied, wherein the SBT represents a transform applied to one of sub-blocks split from a coding unit, determining a transform unit from the coding unit based on the SBT flag, determining a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value and determining the size value as a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value, obtaining transform coefficients based on the size value, and performing an inverse transform on the transform coefficients. A data processing time and the amount of data necessary for a transform can be reduced by performing coding in consideration of a region reduced according to a block size.

---

|                              |                                                                                      |
|------------------------------|--------------------------------------------------------------------------------------|
| <b>Inventors:</b>            | <b>Koo; Moonmo (Seoul, KR), Lim; Jaehyun (Seoul, KR), Kim; Seunghwan (Seoul, KR)</b> |
| <b>Applicant:</b>            | <b>LG ELECTRONICS INC. (Seoul, KR)</b>                                               |
| <b>Family ID:</b>            | <b>72045004</b>                                                                      |
| <b>Assignee:</b>             | <b>LG Electronics Inc. (Seoul, KR)</b>                                               |
| <b>Appl. No.:</b>            | <b>17/430496</b>                                                                     |
| <b>Filed (or PCT Filed):</b> | <b>February 12, 2020</b>                                                             |
| <b>PCT No.:</b>              | <b>PCT/KR2020/001986</b>                                                             |
| <b>PCT Pub. No.:</b>         | <b>WO2020/166977</b>                                                                 |

**PCT Pub. Date:** August 20, 2020

## Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20220086490 A1   | Mar. 17, 2022    |

## Related U.S. Application Data

us-provisional-application US 62804752 20190212

---

## Publication Classification

**Int. Cl.:** H04N19/61 (20140101); H04N19/176 (20140101); H04N19/46 (20140101);  
H04N19/625 (20140101); H04N19/70 (20140101)

**U.S. Cl.:**

**CPC** H04N19/61 (20141101); H04N19/176 (20141101); H04N19/46 (20141101);  
H04N19/625 (20141101); H04N19/70 (20141101);

## Field of Classification Search

**USPC:** None

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl. | CPC         |
|--------------|-------------|---------------|----------|-------------|
| 2020/0186838 | 12/2019     | Zhao          | N/A      | H04N 19/119 |
| 2020/0228832 | 12/2019     | Tsai          | N/A      | H04N 19/176 |
| 2021/0227208 | 12/2020     | Lee           | N/A      | H04N 19/159 |
| 2021/0266581 | 12/2020     | Jung          | N/A      | H04N 19/46  |
| 2021/0360240 | 12/2020     | Lee           | N/A      | H04N 19/619 |

### FOREIGN PATENT DOCUMENTS

| Patent No.   | Application Date | Country | CPC |
|--------------|------------------|---------|-----|
| 20160038063  | 12/2015          | KR      | N/A |
| 20180096194  | 12/2017          | KR      | N/A |
| WO2018190594 | 12/2017          | WO      | N/A |

### OTHER PUBLICATIONS

Versatile Video Coding (Draft 4), JVET-M1001-v7 (Year: 2019). cited by examiner  
PCT International Search Report in International Application No. PCT/KR2020/001986, dated May 26, 2020, 5 pages. cited by applicant  
Zhao et al., "CE6: Sub-block transform for inter blocks (CE6.4.1)," JVET-M0140-v3, Presented at Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 13th Meeting: Marrakech, MA, Jan. 9-18, 2019, 19 pages. cited by applicant  
Koo et al., "CE6-related: 32 point MTS based on skipping high frequency coefficients," JVET-

*Primary Examiner:* Jebari; Mohammed

*Attorney, Agent or Firm:* Fish & Richardson P.C.

---

## **Background/Summary**

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a National Stage application under 35 U.S.C. § 371 of International Application No. PCT/KR2020/001986, filed on Feb. 12, 2020, which claims the benefit of U.S. Provisional Application No. 62/804,752, filed on Feb. 12, 2019. The disclosures of the prior application are incorporated by reference in their entirety.

### **TECHNICAL FIELD**

(1) Embodiments of the present disclosure relate to a video coding system and, more specifically, to a method and device for encoding and decoding a video signal using a reduced transform.

### **BACKGROUND ART**

(2) Compression coding refers to a signal processing technique for transmitting digitalized information through a communication line or storing the same in an appropriate form in a storage medium. Media such as video, images and audio can be objects of compression coding and, particularly, a technique of performing compression coding on images is called video image compression.

(3) Next-generation video content will have features of a high spatial resolution, a high frame rate and high dimensionality of scene representation. To process such content, memory storage, a memory access rate and processing power will significantly increase.

(4) Accordingly, there is a need to design a coding tool for processing more efficiently next-generation video content. In particular, a scheme for efficiently performing a transform is required.

### **DISCLOSURE**

#### **Technical Problem**

(5) Embodiments of the present disclosure provide a method and an apparatus for coding information related to a transform in consideration of zero-out that regards some regions as 0 when a sub-block transform (SBT) is used to reduce the amount of data and to increase a processing speed in a video signal encoding or decoding process.

(6) Technical objects to be achieved in embodiments of the present disclosure are not limited to the aforementioned technical objects, and other technical objects not described above may be evidently understood by a person having ordinary knowledge in the art to which the present disclosure pertains from the following description.

#### **Technical Solution**

(7) Embodiments of the present disclosure provide a method and apparatus for processing a video signal.

(8) A method for decoding a video signal according to an embodiment of the present disclosure includes obtaining a sub-block transform (SBT) flag indicating whether an SBT is applied, wherein the SBT represents a transform applied to one of sub-blocks split from a coding unit, determining a transform unit from the coding unit based on the SBT flag, determining a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value and determining the size value as

a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value, obtaining transform coefficients based on the size value, and performing an inverse transform on the transform coefficients.

(9) In an embodiment, the first reference value may be 4, the second reference value may be 5, and the third reference value may be 6.

(10) In an embodiment, the determining of the size value of the transform unit may include: reducing a width value of the transform unit to 4 if DST-7 or DCT-8 is applied and the width value of the transform unit is 5 and reducing the width value to 5 if DCT-2 is applied and the size value is equal to or greater than 6; and reducing a height value of the transform unit to 4 if DST-7 or DCT-8 is applied and the height value of the transform unit is 5 and reducing the height value to 5 if DCT-2 is applied and the size value is equal to or greater than 6, wherein the width value may be obtained by applying logarithm with a base of 2 to the width of the transform unit and the height value may be obtained by applying logarithm with a base of 2 to the height of the transform unit.

(11) In an embodiment, the determining of the transform unit may include: splitting the coding unit into a plurality of sub-blocks based on an SBT direction flag indicating a splitting direction of a coding unit and an SBT size flag indicating a size of sub-blocks split from the coding unit when the SBT is applied; and determining one of the sub-blocks as the transform unit based on an SBT position flag indicating a position of a sub-block to which a transform is applied among the sub-blocks.

(12) In an embodiment, the performing of the inverse transform may include applying a horizontal inverse transform and a vertical inverse transform to a transform block including the transform coefficients, wherein a horizontal transform kernel for the horizontal inverse transform and a vertical transform kernel for the vertical inverse transform may be determined based on the SBT direction flag and the SBT position flag.

(13) In an embodiment, the horizontal transform kernel and the vertical transform kernel may be DST-7 or DCT-8.

(14) In an embodiment, the SBT direction flag may indicate that the coding unit is split in the vertical direction or the horizontal direction

(15) In an embodiment the SBT size flag may indicate that a sub-block split from the coding unit has a size half or quarter the coding unit.

(16) An apparatus for decoding a video signal according to another embodiment of the present disclosure includes a memory configured to store the video signal and a processor combined with the memory and configured to process the video signal. The processor is configured to obtain a sub-block transform (SBT) flag indicating whether an SBT is applied, wherein the SBT represents a transform applied to one of sub-blocks split from a coding unit, to determine a transform unit from the coding unit based on the SBT flag, to determine a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value and determining the size value as a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value, to obtain transform coefficients based on the size value, and to perform an inverse transform on the transform coefficients.

(17) A non-transitory computer-readable medium storing one or more commands according to another embodiment of the present disclosure is provided. The one or more commands executed by one or more processors control a video signal processing apparatus to: obtain a sub-block transform (SBT) flag indicating whether an SBT is applied, wherein the SBT represents a transform applied

to one of sub-blocks split from a coding unit; determine a transform unit from the coding unit based on the SBT flag; determine a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value and determining the size value as a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value; obtain transform coefficients based on the size value; and perform an inverse transform on the transform coefficients.

#### Advantageous Effects

(18) According to embodiments of the present disclosure, it is possible to reduce the amount of data necessary for a transform and a transformation time by coding information related to the transform in consideration of zero-out when an encoder splits a coding unit into sub-blocks in an optimal form and then performs the transform.

(19) Effects that can be achieved by embodiments of the present disclosure are not limited to effects that have been described hereinabove merely by way of example, and other effects and advantages of the present disclosure will be more clearly understood from the following description by a person skilled in the art to which the present disclosure pertains.

---

## Description

### DESCRIPTION OF DRAWINGS

(1) The accompanying drawings, which are included to provide a further understanding of the present disclosure and are incorporated on and constitute a part of this specification illustrate embodiments of the present disclosure and together with the description serve to explain the principles of the present disclosure.

(2) FIG. 1 shows an example of a video coding system as an embodiment to which the present disclosure is applied.

(3) FIG. 2 is a schematic block diagram of an encoding apparatus which encodes video/image signals as an embodiment to which the present disclosure is applied.

(4) FIG. 3 is a schematic block diagram of a decoding apparatus which decodes image signals as an embodiment to which the present disclosure is applied.

(5) FIG. 4 is a configuration diagram of a content streaming system an embodiment to which the present disclosure is applied.

(6) FIGS. 5a to 5d show embodiments to which the present disclosure is applicable, FIG. 5A is a diagram for describing a block segmentation structure according to QT (Quad Tree), FIG. 5B is a diagram for describing a block segmentation structure according to BT (Binary Tree), FIG. 5C is a diagram for describing a block segmentation structure according to TT (Ternary Tree), and FIG. 5D is a diagram for describing a block segmentation structure according to AT (Asymmetric Tree).

(7) FIG. 6 is a schematic block diagram of a transform and quantization unit, and a dequantization and inverse transform unit in an encoding apparatus.

(8) FIG. 7 is a schematic block diagram of a dequantization and inverse transform unit in a decoding apparatus.

(9) FIG. 8 illustrates an example of a flow chart for a transform when encoding a video signal according to an embodiment of the present disclosure.

(10) FIG. 9 illustrates an example of a flow chart for a transform in a decoding process of a video signal according to an embodiment of the present disclosure.

(11) FIG. 10 illustrates an example of a flow chart for performing a transform through multiple transform selection in an encoding process of a video signal according to an embodiment of the

present disclosure.

(12) FIG. 11 illustrates an example of a flow chart for performing a transform through multiple transform selection in a decoding process of a video signal according to an embodiment of the present disclosure.

(13) FIGS. 12a and 12b illustrate an example where a separable transform according to an embodiment of the present disclosure is applied, and more specifically, FIG. 12a illustrates an area where a significant coefficient is present and an area where zero-out is applied upon forward transform, and FIG. 12b illustrates an area where a significant coefficient is present and an area where zero-out is applied upon inverse transform.

(14) FIGS. 13a and 13b illustrate an example of a transform for subblocks of a block, to which a symmetric vertical split is applied, according to an embodiment of the present disclosure.

(15) FIGS. 14a and 14b illustrate an example of a transform for subblocks of a block, to which a symmetric horizontal split is applied, according to an embodiment of the present disclosure.

(16) FIGS. 15a and 15b illustrate an example of a transform for subblocks of a block, to which an asymmetric vertical split is applied, according to an embodiment of the present disclosure.

(17) FIGS. 16a and 16b illustrate an example of a transform for subblocks of a block, to which an asymmetric horizontal split is applied, according to an embodiment of the present disclosure.

(18) FIGS. 17a to 17d illustrate examples of transforms to which zero-out is applied in subblocks of a block, to which a symmetric split is applied, according to an embodiment of the present disclosure.

(19) FIGS. 18a to 18d illustrate examples of transforms to which zero-out is applied in subblocks of a block, to which an asymmetric split is applied, according to an embodiment of the present disclosure.

(20) FIG. 19 is a flowchart of a process for decoding a coding unit based on a coding unit syntax according to an embodiment of the present disclosure.

(21) FIG. 20 is a flowchart of a process for decoding the transform tree syntax based on the coding unit syntax according to an embodiment of the present disclosure.

(22) FIG. 21 is a flowchart of a process for decoding the transform tree syntax based on the coding unit syntax according to an embodiment of the present disclosure.

(23) FIG. 22 is a flowchart of a decoding operation based on a residual coding syntax according to an embodiment of the present disclosure.

(24) FIG. 23 is a flowchart of encoding a video signal according to an embodiment of the present disclosure.

(25) FIG. 24 is a flowchart of decoding a video signal according to an embodiment of the present disclosure.

(26) FIG. 25 is a block diagram of an apparatus for processing a video signal as an embodiment to which the present disclosure is applied.

## MODE FOR DISCLOSURE

(27) Hereinafter, preferred embodiments of the present disclosure will be described in detail. Some embodiments of the present disclosure are described in detail with reference to the accompanying drawings. A detailed description to be disclosed along with the accompanying drawings are intended to describe some embodiments of the present disclosure and are not intended to describe a sole embodiment of the present disclosure. The following detailed description includes more details in order to provide full understanding of the present disclosure. However, those skilled in the art will understand that the present disclosure may be implemented without such more details.

(28) In some cases, in order to avoid that the concept of the present disclosure becomes vague, known structures and devices are omitted or may be shown in a block diagram form based on the core functions of each structure and device.

(29) Although most terms used in the present disclosure have been selected from general ones widely used in the art, some terms have been arbitrarily selected by the applicant and their

meanings are explained in detail in the following description as needed. Thus, the present disclosure should be understood with the intended meanings of the terms rather than their simple names or meanings.

(30) Specific terms used in the following description have been provided to help understanding of the present disclosure, and the use of such specific terms may be changed in various forms without departing from the technical spirit of the present disclosure. For example, signals, data, samples, pictures, frames, blocks and the like may be appropriately replaced and interpreted in each coding process.

(31) In the present description, a “processing unit” refers to a unit in which an encoding/decoding process such as prediction, transform and/or quantization is performed. Further, the processing unit may be interpreted into the meaning including a unit for a luma component and a unit for a chroma component. For example, the processing unit may correspond to a block, a coding unit (CU), a prediction unit (PU) or a transform unit (TU).

(32) In addition, the processing unit may be interpreted into a unit for a luma component or a unit for a chroma component. For example, the processing unit may correspond to a coding tree block (CTB), a coding block (CB), a PU or a transform block (TB) for the luma component. Further, the processing unit may correspond to a CTB, a CB, a PU or a TB for the chroma component. Moreover, the processing unit is not limited thereto and may be interpreted into the meaning including a unit for the luma component and a unit for the chroma component.

(33) In addition, the processing unit is not necessarily limited to a square block and may be configured as a polygonal shape having three or more vertexes.

(34) Furthermore, in the present description, a pixel is called a sample. In addition, using a sample may mean using a pixel value or the like.

(35) FIG. 1 shows an example of a video coding system as an embodiment to which the present disclosure is applied. The video coding system may include a source device **10** and a receive device **20**. The source device **10** can transmit encoded video/image information or data to the receive device **20** in the form of a file or streaming through a digital storage medium or a network.

(36) The source device **10** may include a video source **11**, an encoding apparatus **12**, and a transmitter **13**. The receive device **20** may include a receiver, a decoding apparatus **22** and a renderer **23**. The encoding apparatus **12** may be called a video/image encoding apparatus and the decoding apparatus **20** may be called a video/image decoding apparatus. The transmitter **13** may be included in the encoding apparatus **12**. The receiver **21** may be included in the decoding apparatus **22**. The renderer **23** may include a display and the display may be configured as a separate device or an external component.

(37) The video source can acquire a video/image through video/image capturing, combining or generating process. The video source may include a video/image capture device and/or a video/image generation device. The video/image capture device may include, for example, one or more cameras, a video/image archive including previously captured videos/images, and the like. The video/image generation device may include, for example, a computer, a tablet, a smartphone, and the like and (electronically) generate a video/image. For example, a virtual video/image can be generated through a computer or the like and, in this case, a video/image capture process may be replaced with a related data generation process.

(38) The encoding apparatus **12** can encode an input video/image. The encoding apparatus **12** can perform a series of procedures such as prediction, transform and quantization for compression and coding efficiency. Encoded data (encoded video/image information) can be output in the form of a bitstream.

(39) The transmitter **13** can transmit encoded video/image information or data output in the form of a bitstream to the receiver of the receive device in the form of a file or streaming through a digital storage medium or a network. The digital storage medium may include various storage media such as a USB (universal serial bus), an SD card (secure digital card), a CD (compact disc), a DVD

(digital versatile disc), Blu-ray Disc (blu-ray disc), an HDD (hard disk drive), and an SSD (solid state drive). The transmitter **13** may include an element for generating a media file through a predetermined file format and an element for transmission through a broadcast/communication network. The receiver **21** can extract a bitstream and transmit the bitstream to the decoding apparatus **22**.

(40) The decoding apparatus **22** can decode a video/image by performing a series of procedures such as inverse quantization, inverse transform and prediction corresponding to operation of the encoding apparatus **12**.

(41) The renderer **23** can render the decoded video/image. The rendered video/image can be display through a display.

(42) FIG. **2** illustrates a schematic block diagram of an encoding apparatus encoding a video signal according to an embodiment of the present disclosure. An encoding apparatus **100** of FIG. **2** may correspond to the encoding apparatus **12** of FIG. **1**.

(43) An image partitioning module **110** may partition an input image (or a picture or a frame) input to the encoding apparatus **100** into one or more processing units. For example, the processing unit may be called a coding unit (CU). In this case, the coding unit may be recursively partitioned from a coding tree unit (CTU) or a largest coding unit (LCU) according to a quad-tree binary-tree (QTBT) structure. For example, one coding unit may be partitioned into a plurality of coding units with a deeper depth based on the quad-tree structure and/or the binary tree structure. In this case, for example, the quad-tree structure may be first applied, and then the binary tree structure may be applied. Alternatively, the binary tree structure may be first applied. A coding procedure according to an embodiment of the present disclosure may be performed based on a final coding unit that is no longer partitioned. In this case, a largest coding unit may be directly used as the final coding unit based on coding efficiency according to image characteristics. Alternatively, the coding unit may be recursively partitioned into coding units with a deeper depth, and thus a coding unit with an optimal size may be used as the final coding unit, if necessary or desired. Here, the coding procedure may include procedures such as prediction, transform and reconstruction which will be described later. As another example, the processing unit may further include a prediction unit (PU) or a transform unit (TU). In this case, the prediction unit and the transform unit may be partitioned from the above-described coding unit. The prediction unit may be a unit of sample prediction, and the transform unit may be a unit of deriving a transform coefficient or a unit of deriving a residual signal from a transform coefficient.

(44) The term ‘unit’ used in the present disclosure may be interchangeably used with the term ‘block’ or ‘area’, if necessary or desired. In the present disclosure, an  $M \times N$  block may represent a set of samples or transform coefficients consisting of  $M$  columns and  $N$  rows. A sample may generally represent a pixel or a pixel value, and may represent a pixel/pixel value of a luma component or represent a pixel/pixel value of a chroma component. The sample may be used as a term for corresponding one picture (or image) to a pixel or a pel.

(45) The encoding apparatus **100** may subtract a predicted signal (a predicted block or a predicted sample array) output from an inter-prediction module **180** or an intra-prediction module **185** from an input video signal (an original block or an original sample array) to generate a residual signal (a residual block or a residual sample array). The generated residual signal may be transmitted to the transform module **120**. In this case, as shown, a unit which subtracts the predicted signal (predicted block or predicted sample array) from the input video signal (original block or original sample array) in the encoding apparatus **100** may be called a subtraction module **115**. A prediction module may perform prediction on a processing target block (hereinafter, referred to as a current block) and generate a predicted block including predicted samples for the current block. The prediction module may determine whether to apply intra-prediction or inter-prediction on a per CU basis. The prediction module may generate various types of information on prediction, such as prediction mode information, and transmit the information on prediction to an entropy encoding module **190**.

as described later in description of each prediction mode. The information on prediction may be encoded in the entropy encoding module **190** and output in the form of a bitstream.

(46) The intra-prediction module **185** may predict the current block with reference to samples in a current picture. Referred samples may neighbor the current block or may be separated therefrom according to a prediction mode. In intra-prediction, prediction modes may include a plurality of nondirectional modes and a plurality of directional modes. The nondirectional modes may include, for example, a DC mode and a planar mode. The directional modes may include, for example, 33 directional prediction modes or 65 directional prediction modes according to a degree of minuteness of prediction direction. However, this is merely an example, and a number of directional prediction modes equal to or greater than 65 or equal to or less than 33 may be used according to settings. The intra-prediction module **185** may determine a prediction mode to be applied to the current block using a prediction mode applied to neighbor blocks.

(47) The inter-prediction module **180** may derive a predicted block for the current block based on a reference block (reference sample array) specified by a motion vector on a reference picture. To reduce an amount of motion information transmitted in an inter-prediction mode, the inter-prediction module **180** may predict motion information based on correlation of motion information between a neighboring block and the current block on a per block, subblock or sample basis. The motion information may include a motion vector and a reference picture index. The motion information may further include inter-prediction direction (L0 prediction, L1 prediction, Bi prediction, etc.) information. In the case of inter-prediction, neighboring blocks may include a spatial neighboring block present in a current picture and a temporal neighboring block present in a reference picture. The reference picture including the reference block may be the same as or different from the reference picture including the temporal neighboring block. The temporal neighboring block may be called a collocated reference block or a collocated CU (colCU), and the reference picture including the temporal neighboring block may be called a collocated picture (colPic). For example, the inter-prediction module **180** may construct a motion information candidate list based on motion information of neighboring blocks and generate information indicating which candidate is used to derive a motion vector and/or a reference picture index of the current block. The inter-prediction may be performed based on various prediction modes. For example, in the case of a skip mode and a merge mode, the inter-prediction module **180** may use motion information of a neighboring block as motion information of the current block. In the skip mode, a residual signal is not be transmitted, unlike the merge mode. In a motion vector prediction (MVP) mode, the motion vector of the current block may be indicated by using a motion vector of a neighboring block as a motion vector predictor and signaling a motion vector difference (MVD).

(48) A predicted signal generated by the inter-prediction module **180** or the intra-prediction module **185** may be used to generate a reconstructed signal or a residual signal.

(49) The transform module **120** may apply a transform technique to a residual signal to generate transform coefficients. For example, the transform technique may include at least one of discrete cosine transform (DCT), discrete sine transform (DST), Karhunen-Loeve transform (KLT), graph-based transform (GBT), and conditionally non-linear transform (CNT). The GBT refers to transform obtained from a graph representing information on a relationship between pixels. The CNT refers to transform obtained based on a predicted signal generated using all previously reconstructed pixels. Further, the transform process may be applied to square pixel blocks with the same size, or applied to non-square blocks or blocks with variable sizes.

(50) A quantization module **130** may quantize transform coefficients and transmit the quantized transform coefficients to the entropy encoding module **190**. The entropy encoding module **190** may encode a quantized signal (information on the quantized transform coefficients) and output the encoded signal as a bitstream. The information on the quantized transform coefficients may be called residual information. The quantization module **130** may rearrange the quantized transform coefficients of the block form in the form of one-dimensional (1D) vector based on a coefficient

scan order and generate information about the quantized transform coefficients based on characteristics of the quantized transform coefficients of the one-dimensional vector form. The entropy encoding module **190** may perform various encoding schemes such as exponential Golomb, context-adaptive variable length coding (CAVLC), and context-adaptive binary arithmetic coding (CABAC). The entropy encoding module **190** may encode information necessary for video/image reconstruction (e.g., values of syntax elements) along with or separately from the quantized transform coefficients. Encoded information (e.g., video/image information) may be transmitted or stored in the form of a bitstream in network abstraction layer (NAL) unit. The bitstream may be transmitted through a network or stored in a digital storage medium. Here, the network may include a broadcast network and/or a communication network, and the digital storage medium may include various storage media such as USB, SD, CD, DVD, Blu-ray, HDD and SSD. A transmitter (not shown) which transmits the signal output from the entropy encoding module **190** and/or a storage (not shown) which stores the signal may be configured as internal/external elements of the encoding apparatus **100**, or the transmitter may be a component of the entropy encoding module **190**.

(51) The quantized transform coefficients output from the quantization module **130** may be used to generate a reconstructed signal. For example, a residual signal can be reconstructed by applying dequantization and inverse transform to the quantized transform coefficients through a dequantization module **140** and an inverse transform module **150** in the loop. An addition module **155** may add the reconstructed residual signal to the predicted signal output from the inter-prediction module **180** or the intra-prediction module **185** to generate a reconstructed signal (reconstructed picture, reconstructed block or reconstructed sample array). When there is no residual signal for a processing target block as in a case in which the skip mode is applied, a predicted block may be used as a reconstructed block. The addition module **155** may also be called a reconstruction unit or a reconstructed block generator. The generated reconstructed signal can be used for intra-prediction of the next processing target block in the current picture or used for inter-prediction of the next picture through filtering which will be described later.

(52) A filtering module **160** can improve subjective/objective picture quality by applying filtering to the reconstructed signal. For example, the filtering module **160** may generate a modified reconstructed picture by applying various filtering methods to the reconstructed picture and transmit the modified reconstructed picture to a decoded picture buffer (DPB) **170**. Examples of the various filtering methods may include deblocking filtering, sample adaptive offset (SAO), adaptive loop filtering (ALF), and bilateral filtering. The filtering module **160** may generate information on filtering and transmit the information on filtering to the entropy encoding module **190** as will be described later in description of each filtering method. The information on filtering may be output in the form of a bitstream through entropy encoding in the entropy encoding module **190**.

(53) The modified reconstructed picture transmitted to the decoded picture buffer **170** may be used as a reference picture in the inter-prediction module **180**. When inter-prediction is applied, the encoding apparatus **100** can avoid mismatch between the encoding apparatus **100** and the decoding apparatus **200** using the modified reconstructed picture and improve encoding efficiency. The decoded picture buffer **170** may store the modified reconstructed picture such that the modified reconstructed picture is used as a reference picture in the inter-prediction module **180**.

(54) FIG. 3 is a schematic block diagram of a decoding apparatus which performs decoding of a video signal according to an embodiment of the present disclosure. The decoding apparatus **200** of FIG. 3 corresponds to the decoding apparatus **22** of FIG. 1.

(55) Referring to FIG. 3, the decoding apparatus **200** may include an entropy decoding module **210**, a dequantization module **220**, an inverse transform module **230**, an addition module **235**, a filtering module **240**, a decoded picture buffer (DPB) **250**, an inter-prediction module **260**, and an intra-prediction module **265**. The inter-prediction module **260** and the intra-prediction module **265** may be collectively called a prediction module. That is, the prediction module may include the

inter-prediction module **180** and the intra-prediction module **185**. The dequantization module **220** and the inverse transform module **230** may be collectively called a residual processing module. That is, the residual processing module may include the dequantization module **220** and the inverse transform module **230**. In some embodiments, the entropy decoding module **210**, the dequantization module **220**, the inverse transform module **230**, the addition module **235**, the filtering module **240**, the inter-prediction module **260**, and the intra-prediction module **265** described above may be configured as a single hardware component (e.g., a decoder or a processor). In some embodiments, the decoded picture buffer **250** may be configured as a single hardware component (e.g., a memory or a digital storage medium).

(56) When a bitstream including video/image information is input, the decoding apparatus **200** may reconstruct an image through a process corresponding to the process of processing the video/image information in the encoding apparatus **100** of FIG. 2. For example, the decoding apparatus **200** may perform decoding using a processing unit applied in the encoding apparatus **100**. Thus, a processing unit upon the decoding may be a coding unit, for example, and the coding unit may be partitioned from a coding tree unit or a largest coding unit according to a quadtree structure and/or a binary tree structure. In addition, a reconstructed video signal decoded and output by the decoding apparatus **200** may be reproduced through a reproduction apparatus.

(57) The decoding apparatus **200** may receive a signal output from the encoding apparatus **100** of FIG. 2 in the form of a bitstream, and the received signal may be decoded through the entropy decoding module **210**. For example, the entropy decoding module **210** may parse the bitstream to derive information (e.g., video/image information) necessary for image reconstruction (or picture reconstruction). For example, the entropy decoding module **210** may obtain information in the bitstream using a coding scheme such as exponential Golomb, CAVLC or CABAC, and output a syntax element value necessary for image reconstruction and a quantized value of transform coefficients for residual. More specifically, the CABAC entropy decoding method may receive a bin corresponding to each syntax element in the bitstream, determine a context model using decoding target syntax element information and decoding information of neighboring and decoding target blocks or information on symbols/bins decoded in a previous stage, predict the probability of generation of the bin according to the determined context model, and perform arithmetic decoding of bins to thereby generate a symbol corresponding to each syntax element value. The CABAC entropy decoding method can update the context model using information on symbols/bins decoded for the next symbol/bin context model after the context model is determined. Information about prediction among the information decoded in the entropy decoding module **210** may be provided to the prediction module (the inter-prediction module **260** and the intra-prediction module **265**), and residual values, on which entropy decoding has been performed in the entropy decoding module **210**, that is, quantized transform coefficients and related parameter information may be input to the dequantization module **220**. Further, information on filtering among the information decoded in the entropy decoding module **210** may be provided to the filtering module **240**. A receiver (not shown) receiving a signal output from the encoding apparatus **100** may be additionally configured as an internal/external element of the decoding apparatus **200**, or the receiver may be a component of the entropy decoding module **210**.

(58) The dequantization module **220** may output transform coefficients through dequantization of the quantized transform coefficients. The dequantization module **220** may rearrange the quantized transform coefficients in the form of a two-dimensional (2D) block. In this case, rearrangement may be performed based on the coefficient scan order performed in the encoding apparatus **100**. The dequantization module **220** may perform dequantization on the quantized transform coefficients using a quantization parameter (e.g., quantization step size information) and obtain transform coefficients.

(59) The inverse transform module **230** inversely transforms the transform coefficients to obtain a residual signal (residual block or residual sample array).

(60) The prediction module may perform prediction on a current block and generate a predicted block including predicted samples for the current block. The prediction module may determine whether intra-prediction or inter-prediction is applied to the current block based on information on prediction output from the entropy decoding module **210**, and determine a specific intra/inter-prediction mode.

(61) The intra-prediction module **265** may predict the current block with reference to samples in a current picture. The referred samples may neighbor the current block or may be separated from the current block according to a prediction mode. In intra-prediction, prediction modes may include a plurality of nondirectional modes and a plurality of directional modes. The intra-prediction **265** may determine a prediction mode applied to the current block using a prediction mode applied to neighboring blocks.

(62) The inter-prediction module **260** may derive a predicted block for the current block based on a reference block (reference sample array) specified by a motion vector on a reference picture. To reduce an amount of motion information transmitted in the inter-prediction mode, the motion information may be predicted based on correlation of motion information between a neighboring block and the current block on a per block, subblock or sample basis. The motion information may include a motion vector and a reference picture index. The motion information may further include inter-prediction direction (L0 prediction, L1 prediction, Bi prediction) information. In the case of inter-prediction, the neighboring blocks may include a spatial neighboring block present in a current picture and a temporal neighboring block present in a reference picture. For example, the inter-prediction module **260** may construct a motion information candidate list based on neighboring blocks and derive the motion vector and/or the reference picture index of the current block based on received candidate selection information. The inter-prediction may be performed based on various prediction modes, and information on prediction may include information indicating the inter-prediction mode for the current block.

(63) The addition module **235** can generate a reconstructed signal (reconstructed picture, reconstructed block or reconstructed sample array) by adding the obtained residual signal to the predicted signal (predicted block or predicted sample array) output from the inter-prediction module **260** or the intra-prediction module **265**. When there is no residual for the processing target block as in a case in which the skip mode is applied, the predicted block may be used as a reconstructed block.

(64) The addition module **235** may also be called a reconstruction unit or a reconstructed block generator. The generated reconstructed signal may be used for intra-prediction of a next processing target block in the current picture or used for inter-prediction of a next picture through filtering which will be described later.

(65) The filtering module **240** can improve subjective/objective picture quality by applying filtering to the reconstructed signal. For example, the filtering module **240** may generate a modified reconstructed picture by applying various filtering methods to the reconstructed picture, and transmit the modified reconstructed picture to a decoded picture buffer **250**. Examples of the various filtering methods may include deblocking filtering, sample adaptive offset, adaptive loop filtering, and bilateral filtering.

(66) The modified reconstructed picture transmitted to the decoded picture buffer **250** may be used as a reference picture by the inter-prediction module **260**.

(67) In the present disclosure, implementations described in the filtering module **160**, the inter-prediction module **180**, and the intra-prediction module **185** of the encoding apparatus **100** can be applied to the filtering module **240**, the inter-prediction module **260** and the intra-prediction module **265** of the decoding apparatus equally or in a corresponding manner.

(68) FIG. **4** is a configuration diagram of a content streaming system according to an embodiment of the present disclosure.

(69) A content streaming system to which an embodiment of the present disclosure is applied may

roughly include an encoding server **410**, a streaming server **420**, a web server **430**, a media storage **440**, a user equipment **450**, and a multimedia input device **460**.

(70) The encoding server **410** compresses content input from a multimedia input device **460** such as a smartphone, a camera, and a camcorder into digital data to generate a bitstream, and transmits the generated bitstream to the streaming server **420**. As another example, when the multimedia input device **460** such as a smartphone, a camera and a camcorder directly generates the bitstream, the encoding server **410** may be omitted.

(71) The bitstream may be generated by an encoding method or a bitstream generation method to which an embodiment of the present disclosure is applied, and the streaming server **420** may temporarily store the bitstream in the process of transmitting or receiving the bitstream.

(72) The streaming server **420** transmits multimedia data to the user equipment **450** based on a user request via the web server **430**, and the web server **430** serves as a medium that informs a user of types of services. If the user sends a request for a desired service to the web server **430**, the web server **430** sends information on the requested service to the streaming server **420**, and the streaming server **420** transmits multimedia data to the user. The content streaming system may include a separate control server, and in this case, the control server serves to control commands/responses between the respective devices in the content streaming system.

(73) The streaming server **420** may receive content from the media storage **440** and/or the encoding server **410**. For example, if content is received from the encoding server **410**, the streaming server **420** may receive the content in real time. In this case, the streaming server **420** may store a bitstream for a predetermined time in order to provide a smooth streaming service.

(74) Examples of the user equipment **450** may include a cellular phone, a smartphone, a laptop computer, a digital broadcast terminal, a personal digital assistant (PDA), a portable multimedia player (PMP), a navigation, a slate PC, a tablet PC, an ultrabook, a wearable device (e.g., a smartwatch, a smart glass, and a head mounted display (HMD)), a digital TV, a desktop computer, and a digital signage.

(75) Each server in the content streaming system may be operated as a distributed server, and in this case, data received by each server may be distributed and processed.

(76) FIG. 5a to 5d illustrate examples of a block partitioning structure according to an embodiment of the present disclosure. More particularly, FIG. 5a illustrates an example of a block partitioning structure according to quadtree (QT), FIG. 5b illustrates an example of a block partitioning structure according to binary tree (BT), FIG. 5c illustrates an example of a block partitioning structure according to ternary tree (TT), and FIG. 5d illustrates an example of a block partitioning structure according to asymmetric tree (AT).

(77) In the video coding system, one block may be partitioned based on a QT partitioning scheme. One subblock partitioned using the QT partitioning scheme may be further recursively partitioned according to the QT partitioning scheme. A leaf block that is no longer partitioned by the QT partitioning scheme may be partitioned using at least one of BT, TT, or AT partitioning scheme. BT may have two types of partitions such as horizontal BT ( $2N \times N$ ,  $2N \times N$ ) and vertical BT ( $N \times 2N$ ,  $N \times 2N$ ). TT may have two types of partitions such as horizontal TT ( $2N \times 1/2N$ ,  $2N \times N$ ,  $2N \times 1/2N$ ) and vertical TT ( $1/2N \times 2N$ ,  $N \times 2N$ ,  $1/2N \times 2N$ ). AT may have four types of partitions such as horizontal-up AT ( $2N \times 1/2N$ ,  $2N \times 3/2N$ ), horizontal-down AT ( $2N \times 3/2N$ ,  $2N \times 1/2N$ ), vertical-left AT ( $1/2N \times 2N$ ,  $3/2N \times 2N$ ), and vertical-right AT ( $3/2N \times 2N$ ,  $1/2N \times 2N$ ). Each of BT, TT and AT may be further recursively partitioned using BT, TT and AT.

(78) FIG. 5a illustrates an example of QT partition. A block A may be partitioned into four subblocks A0, A1, A2 and A3 by QT. The subblock A1 may be further partitioned into four subblocks B0, B1, B2 and B3 by QT.

(79) FIG. 5b illustrates an example of BT partition. The block B3 that is no longer partitioned by QT may be partitioned by vertical BT (C0, C1) or horizontal BT (D0, D1). Each subblock such as the block C0 may be further recursively partitioned as in the form of horizontal BT (E0, E1) or

vertical BT (F0, F1).

(80) FIG. 5c illustrates an example of TT partition. The block B3 that is no longer partitioned by QT may be partitioned into vertical TT (C0, C1, C2) or horizontal TT (D0, D1, D2). Each subblock such as the block C1 may be further recursively partitioned as in the form of horizontal TT (E0, E1, E2) or vertical TT (F0, F1, F2).

(81) FIG. 5d illustrates an example of AT partition. The block B3 that is no longer partitioned by QT may be partitioned into vertical AT (C0, C1) or horizontal AT (D0, D1). Each subblock such as the block C1 may be further recursively partitioned as in the form of horizontal AT (E0, E1) or vertical TT (F0, F1).

(82) BT, TT and AT partitions may be applied to one block together. For example, a subblock partitioned by BT may be partitioned by TT or AT. Further, a subblock partitioned by TT may be partitioned by BT or AT. A subblock partitioned by AT may be partitioned by BT or TT. For example, after horizontal BT partition, each subblock may be partitioned by vertical BT. After vertical BT partition, each subblock may also be partitioned by horizontal BT. In this case, partition orders are different, but finally partitioned shapes are the same.

(83) If a block is partitioned, a block search order may be variously defined. In general, search is performed from left to right and from top to bottom, and searching the block may mean the order of determining whether each partitioned subblock is additionally partitioned, or mean an encoding order of each subblock when the block is no longer partitioned, or mean a search order when a subblock refers to information of other neighboring block.

(84) The transform may be performed per processing unit (or transform block) partitioned by the partition structures as illustrated in FIGS. 5a to 5d, and in particular, a transform matrix may be applied by performing the partition in a row direction and a column direction. According to an embodiment of the present disclosure, different transform types may be used depending on a length of the processing unit (or transform block) in the row direction or the column direction.

(85) The transform is applied to residual blocks, and this is to decorrelate the residual blocks as much as possible, concentrate coefficients at a low frequency, and generate a zero tail at an end of a block. A transform scheme according to an embodiment of the present disclosure may include two stage of transforms (primary transform and secondary transform). The primary transform (or core transform) may be composed of DCT or DST transform families applied to all rows and columns of a residual block. Thereafter, the secondary transform may be additionally applied to a top left corner of an output of the core transform. Similarly, an inverse transform may be applied in the order of an inverse secondary transform and an inverse core transform. The inverse secondary transform may be first applied to a top left corner of a coefficient block. Then, the inverse core transform may be applied to the output of the inverse secondary transform.

(86) FIG. 6 is a schematic block diagram of the transform and quantization module **120/130** and the dequantization and inverse transform module **140/150** in the encoding apparatus **100** illustrated in FIG. 2, and FIG. 7 is a schematic block diagram of the dequantization and inverse transform module **220/230** in the decoding apparatus **200**.

(87) Referring to FIG. 6, the transform and quantization module **120/130** may include a primary transform module **121**, a secondary transform module **122**, and a quantization module **130**. The dequantization and inverse transform module **140/150** may include a dequantization module **140**, an inverse secondary transform module **151**, and an inverse primary transform module **152**.

(88) Referring to FIG. 7, the dequantization and inverse transform module **220/230** may include a dequantization module **220**, an inverse secondary transform module **231**, and an inverse primary transform module **232**. According to an embodiment of the present disclosure, a transform may be performed through a plurality of stages. For example, as illustrated in FIG. 6, two states of a primary transform and a secondary transform may be applied, or more than two transform stages may be used according to algorithms. As described above, the primary transform may be referred to as a core transform.

(89) The primary transform module **121** may apply the primary transform to a residual signal, and the primary transform may be predefined as a table in an encoder and/or a decoder. The secondary transform module **122** may apply the secondary transform to a primarily transformed signal, and the secondary transform may be predefined as a table in the encoder and/or the decoder.

(90) In an embodiment, a non-separable transform may be conditionally applied as the secondary transform. For example, the secondary transform may be applied only to the case of intra-prediction blocks, and may have an applicable transform set for each prediction mode group.

(91) The prediction mode group may be set based on symmetry with respect to a prediction direction. For example, since prediction mode **52** and prediction mode **16** are symmetrical based on prediction mode **34** (diagonal direction), one group may be formed and the same transform set may be applied thereto. When transform for prediction mode **52** is applied, transposed input data is applied, and this is because a transform set of prediction mode **52** is the same as that of prediction mode **16**.

(92) In the planar mode and the DC mode, since there is no symmetry with respect to the direction, a different transform set is applied, and a corresponding transform set may include two transforms. Each transform set may include three transforms in remaining directional modes.

(93) The quantization module **130** may perform quantization on a secondarily transformed signal. The dequantization and inverse transform module **140/150** performs the reverse of the aforementioned procedure, and redundant description is omitted.

(94) FIG. 7 is a schematic block diagram of the dequantization and inverse transform module **220/230** in the decoding apparatus **200**. Referring to FIG. 7, the dequantization and inverse transform module **220/230** may include the dequantization module **220**, the inverse secondary transform module **231**, and the inverse primary transform module **232**.

(95) The dequantization module **220** obtains transform coefficients from an entropy-decoded signal using quantization step size information. The inverse secondary transform module **231** performs an inverse secondary transform on the transform coefficients. Here, the inverse secondary transform refers to an inverse transform of the secondary transform described with reference to FIG. 6. The inverse primary transform module **232** performs an inverse primary transform on the inversely secondarily transformed signal (or block) and obtains a residual signal. Here, the inverse primary transform refers to an inverse transform of the primary transform described with reference to FIG. 6.

(96) FIG. 8 illustrates an example of a flow chart for a transform when encoding a video signal according to an embodiment of the present disclosure.

(97) In step **S810**, the encoding apparatus **100** performs a primary transform on a residual block. The primary transform may be referred to as a core transform. In an embodiment, the encoding apparatus **100** may perform a primary transform using a transform kernel determined depending on multiple transform selection (MTS) to be described later. Further, the encoding apparatus **100** may transmit, to the decoding apparatus **200**, an MTS index indicating a specific MTS among MTS candidates. The MTS candidates may be determined based on an intra-prediction mode of a current block. The encoding apparatus **100** may transmit residual data in a state of omitting a transform. If the transform is omitted, the encoding apparatus **100** may encode a syntax element (e.g., transform skip flag) indicating that the transform is omitted, and include the corresponding syntax element in a bitstream.

(98) The encoding apparatus **100** determines whether to apply a secondary transform, in **S820**. For example, the encoding apparatus **100** may determine whether the secondary transform is applied to a primarily transformed residual transform coefficient. For example, the secondary transform is a non-separable transform applied to coefficients located in a top left area (e.g., 4×4 or 8×8 top left area) in a block, and may be referred to a low frequency non-separable transform (LFNST). The secondary transform may be applied to a block to which an intra-prediction is applied.

(99) The encoding apparatus **100** determines the secondary transform, in **S830**. The encoding

apparatus **100** determines the secondary transform based on a secondary transform set designated depending on the intra-prediction mode. Before the step **S830**, the encoding apparatus **100** may determine an area, to which the secondary transform is applied based on a size of the current block, and an output size according to the transform. The encoding apparatus **100** performs the secondary transform using the secondary transform determined in the step **S830**, in **S840**.

(100) FIG. **9** illustrates an example of a flow chart for a transform in a decoding process of a video signal according to an embodiment of the present disclosure.

(101) The decoding apparatus **200** determines whether to apply an inverse secondary transform, in **S910**. For example, the inverse secondary transform may be a non-separable transform applied for a top left area (e.g., 4×4 or 8×8 top left area) of a block including transform coefficients. For example, the decoding apparatus **200** may determine whether to apply the inverse secondary transform based on a syntax element (e.g., secondary transform flag) indicating whether to apply the secondary transform from the encoding apparatus **100**.

(102) The decoding apparatus **200** determines the inverse secondary transform, in **S920**. The decoding apparatus **200** may determine the inverse secondary transform applied to a current block based on a transform set designated depending on an intra-prediction mode. Before the step **S920**, the decoding apparatus **200** may determine an area to which the inverse secondary transform is applied based on a size of the current block. The decoding apparatus **200** performs the inverse secondary transform on a dequantized residual block using the inverse secondary transform determined in the step **S920**, in **S930**.

(103) The decoding apparatus **200** performs an inverse primary transform on an inverse secondary transformed residual block, in **S940**. The inverse primary transform may be referred to as an inverse core transform. In an embodiment, the decoding apparatus **200** may perform the inverse primary transform using a transform kernel determined depending on MTS to be described later. Before the step **S940**, the decoding apparatus **200** may determine whether the MTS is applied to the current block. In this case, a step of determining whether the MTS is applied may be further included in the flow chart of the decoding illustrated in FIG. **9**.

(104) In an embodiment, if the MTS is applied to the current block (e.g., if a MTS flag of a CU level is 1), the decoding apparatus **200** may construct MTS candidates based on the intra-prediction mode of the current block. In this case, a step of constructing the MTS candidates may be further included in the flow chart of the decoding illustrated in FIG. **9**. The decoding apparatus **200** may determine the inverse primary transform applied to the current block using an index indicating a specific MTS among the constructed MTS candidates. The decoding apparatus **200** may determine a transform kernel corresponding to the MTS index with reference to a table defining a relationship between the MTS index and the transform kernel.

(105) In addition to DCT-2 and 4×4 DST-7 applied to HEVC, an adaptive (or explicit) multiple transform selection (MTS) scheme may be used for residual coding for inter- and intra-coded blocks. The MTS may be referred to as an adaptive multiple transform (AMT) or an explicit multiple transform (EMT). For example, as a transform according to an embodiment of the present disclosure, transforms selected from DCT/DST families may be used. For example, additional matrixes other than DCT-2 may include DST-7, DCT-8, DST-1, and DCT-5. The following Table 1 represents basic functions of selected DST/DCT.

(106) TABLE-US-00001 TABLE 1 Transform Type Basis function  $T_{sub.i}(j)$ ,  $i, j = 0, 1, \dots, N - 1$

$$\text{DCT-II } T_i(j) = \begin{cases} 0 & i = 0 \\ \frac{1}{\sqrt{N}} \cdot \text{Math.} \cos\left(\frac{\text{Math. } i \cdot \text{Math. } (2j + 1)}{2N}\right) & i \neq 0 \end{cases} \text{ where } \begin{cases} \frac{\sqrt{2}}{N} & i = 0 \\ 1 & i \neq 0 \end{cases} \text{ DCT-V}$$

$$T_i(j) = \begin{cases} 0 & i = 0 \\ \frac{1}{\sqrt{2N-1}} \cdot \text{Math.} \cos\left(\frac{2 \cdot \text{Math. } i \cdot \text{Math. } j}{2N-1}\right) & i \neq 0 \end{cases}$$

$$\text{where } \begin{cases} \frac{\sqrt{2}}{N} & i = 0 \\ 1 & i \neq 0 \end{cases}, \begin{cases} \frac{\sqrt{2}}{N} & j = 0 \\ 1 & j \neq 0 \end{cases} \text{ DCT-VIII}$$

$$T_i(j) = \frac{1}{\sqrt{4N+1}} \cdot \text{Math.} \cos\left(\frac{\text{Math. } (2i + 1) \cdot \text{Math. } (2j + 1)}{4N+2}\right) \text{ DST-I}$$

$$T_i(j) = \sqrt{\frac{2}{N+1}} \cdot \text{Math. sin}\left(\frac{\text{Math.}(i+1) \cdot \text{Math.}(j+1)}{N+1}\right) \text{ DST-VII}$$

$$T_i(j) = \sqrt{\frac{4}{2N+1}} \cdot \text{Math. sin}\left(\frac{\text{Math.}(2i+1) \cdot \text{Math.}(j+1)}{2N+1}\right)$$

(107) The MTS may be applied to CUs having a width and a height that are less than or equal to 64, and whether the MTS is applied may be controlled by a flag of a per CU basis (e.g., cu\_mts\_flag). If a CU level flag is 0, DCT-2 is applied to the CU in order to encode a residue. A luma coding block in the CU to which the MTS is applied may be signaled in order to identify horizontal and vertical transforms in which two additional flags will be used. If a transform skip mode is applied, a transform for residual samples of the block may be omitted. For coding (intra-residual coding) of the residual samples to which intra-prediction is applied, a mode-dependent transform candidate selection process may be used. Three transform subsets may be defined as in the following Table 2, and a transform subset may be selected based on an intra-prediction mode as shown in Table 3 below.

(108) TABLE-US-00002 TABLE 2 Transform Set Transform Candidates 0 DST-VII, DCT-VIII 1 DST-VII, DST-I 2 DST-VII, DCT-VIII

(109) Along with a subset concept, a transform subset is initially confirmed based on Table 2 by using the intra-prediction mode of a CU having a CU-level MTS flag of 1. Thereafter, for each of a horizontal transform (indicated by EMT\_TU\_horizontal\_flag) and a vertical transform (indicated by EMT\_TU\_vertical\_flag), one of two transform candidates in the confirmed transform subset may be selected based on explicit signaling using flags according to Table 3.

(110) TABLE-US-00003 TABLE 3 Intra Mode 0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 V 2 1 0 1 0 1 0 1 0 1 0 1 0 0 0 0 H 2 1 0 1 0 1 0 1 0 1 0 1 0 1 2 2 2 2 Intra Mode 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 V 0 0 0 0 0 1 0 1 0 1 0 1 0 1 0 1 0 H 2 2 2 2 2 1 0 1 0 1 0 1 0 1 0 Intra Mode 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 V 1 0 1 0 1 0 1 0 1 0 1 2 2 2 2 2 2 2 H 1 0 1 0 1 0 1 0 1 0 1 0 0 0 0 0 0 0 Intra Mode 53 54 55 56 57 58 59 60 61 62 63 64 65 66 V 2 2 1 0 1 0 1 0 1 0 1 0 1 0 H 0 0 1 0 1 0 1 0 1 0 1 0 1 0

(111) In Table 3, 'Intra Mode' denotes the intra-prediction mode (67 mode basis) applied to the CU, 'V' denotes an index indicating a transform set for a vertical transform, and 'H' denotes an index indicating a transform set for a horizontal transform. As shown in Table 3, a transform set that can be applied per intra-prediction mode is configured, and

EMT\_TU\_horizontal\_flag/EMT\_TU\_vertical\_flag indicates a transform kernel for horizontal/vertical transform in each horizontal/vertical transform set among transform candidates (Table 2) constituting horizontal/vertical transform sets (H/V) corresponding to the prediction mode.

(112) TABLE-US-00004 TABLE 4 Hori- Hori- zontal zontal 35 Intra 67 Intra Configuration (row) (column) Prediction Prediction group transform transform modes modes Group 0 DST7 DST7 0 0 0 (G0) 1 DCT5 DST7 2 DST7 DCT5 3 DCT5 DCT5 Group 0 DST7 DST7 1, 3, 5, 7, 13, 1, 3, 5, 7, 9, 1 (G1) 1 DST1 DST7 15, 17, 19, 21, 11, 13, 23, 25, 2 DST7 DST1 23, 29, 31, 33 27, 29, 31, 33, 3 DST1 DST1 35, 37, 39, 41, 43, 45, 55, 57, 59, 61, 63, 65 Group 0 DST7 DST7 2, 4, 6, 14, 16, 2, 4, 6, 8, 10, 2 (G2) 1 DCT8 DST7 18, 20, 22, 30, 12, 24, 26, 28, 2 DST7 DCT8 32, 34 30, 32, 34, 36, 3 DCT8 DCT8 38, 40, 42, 44, 56, 58, 60, 54, 66 Group 0 DST7 DST7 8, 9, 10, 11, 12 14, 15, 16, 17, 3 (G3) 1 DCT5 DST7 (Neighboring 18, 19, 20, 21, 2 DST7 DCT8 angles to 22 3 DCT5 DCT8 horizontal (Neighboring directions) angles to horizontal directions) Group 0 DST7 DST7 24, 25, 26, 27, 46, 47, 48, 49, 4 (G4) 1 DCT8 DST7 28 50, 51, 52, 53, 2 DST7 DCT5 (Neighboring 54 3 DCT8 DCT5 angles to (Neighboring vertical angles to directions) vertical directions Group 0 DCT8 DCT8 Inter Inter 5 (G5) 1 DST7 DCT8 prediction prediction 2 DCT8 DST7 3 DST7 DST7

(113) Table 4 illustrates an example of a transform configuration group, to which MTS is applied, as an embodiment to which the present disclosure is applied.

(114) Referring to Table 4, transform configuration groups may be determined based on a prediction mode, and the number of groups may be 6 (G0 to G5). In addition, G0 to G4 correspond to a case to which intra-prediction is applied, and G5 represents transform combinations (or

transform set or transform combination set) applied to a residual block generated by inter-prediction.

(115) One transform combination may consist of a horizontal transform (or row transform) applied to rows of a corresponding 2D block and a vertical transform (or column transform) applied to columns thereof.

(116) Each of the transform configuration groups may have four transform combination candidates. The four transform combination candidates may be selected or determined using transform combination indexes 0 to 3, and a transform combination index may be encoded and transmitted from an encoder to a decoder.

(117) In an embodiment, residual data (or residual signal) obtained through intra-prediction may have different statistical characteristics depending on the intra-prediction mode. Thus, as shown in Table 4, transforms other than a normal cosine transform (e.g., DCT-2) may be applied per intra-prediction. In the present disclosure, a transform type may be represented as DCT-Type 2, DCT-II, and DCT-2, for example.

(118) Referring to Table 4, a case of using 35 intra-prediction modes and a case of using 67 intra-prediction modes are shown. A plurality of transform combinations may be applied for each transform configuration group divided from each intra-prediction mode column. For example, a plurality of transform combinations may consist of four transform combinations. As a specific example, DST-7 and DCT-5 can be applied to group 0 in both the row (horizontal) direction and the column (vertical) direction, and thus a total of four combinations can be applied.

(119) Since a total of four transform kernel combinations can be applied to each intra-prediction mode, a transform combination index for selecting one from among them can be transmitted per transform unit. In the present disclosure, the transform combination index may be referred to as an MTS index and may be represented by `mts_idx`.

(120) Furthermore, there may occur a case in which DCT-2 is optimal for both the row direction and the column direction due to characteristics of a residual signal, in addition to the transform kernels shown in Table 4. Thus, a transform can be adaptively applied by defining an MTS flag for each coding unit. If the MTS flag is 0, DCT-2 may be applied for both the row direction and the column direction, and if the MTS flag is 1, one of four combinations may be selected or determined through an MTS index.

(121) In an embodiment, if the number of transform coefficients is less than a specific value (e.g., 3) for one transform unit even if the MTS flag is 1, the transform kernels of Table 4 is not applied and the same transform kernel (e.g., DST-7) may be applied for both the row direction and the column direction.

(122) In an embodiment, if transform coefficient values are previously parsed and the number of transform coefficients is less than a specific value (e.g., 3), an MTS index is not parsed and a specific transform kernel (e.g., DST-7) may be applied. Hence, an amount of transmission of additional information can be reduced.

(123) In an embodiment, MTS may be applied only if a width or a height of the transform unit is equal to or less than a reference size (e.g., 32), or MTS may be applied only when both the width and the height of the transform unit is equal to or less than the reference size (e.g., 32).

(124) In an embodiment, the transform configuration groups as shown in Table 4 may be pre-configured through off-line training.

(125) In an embodiment, the MTS index may be defined as one index that can simultaneously indicate a combination of the horizontal transform and the vertical transform. Further, the MTS index may be defined as each of a separate horizontal transform index and a separate vertical transform index.

(126) FIG. 10 illustrates an example of a flow chart for performing a transform through multiple transform selection in an encoding process of a video signal according to an embodiment of the present disclosure.

- (127) Although the present disclosure basically describes an embodiment for a separable transform in which a transform is applied by being separated in the horizontal direction and the vertical direction, a transform combination may consist of non-separable transforms.
- (128) Alternatively, a transform combination may be configured as a mixture of separable transforms and non-separable transforms. In this case, if the non-separable transform is used, transform selection per row/column or selection per the horizontal/vertical direction is unnecessary, and the transform combinations of Table 4 can be used only when separable transform is selected.
- (129) In addition, methods described in the present disclosure can be applied irrespective of the primary transform or the secondary transform. That is, there is no limit in which the methods shall be applied only to one of the two transforms, and the methods can be applied to all the two transforms. The primary transform may refer to a transform for first transforming a residual block, and the secondary transform may refer to a transform for applying a transform to a block generated as a result of the primary transform.
- (130) First, the encoding apparatus **100** may determine a transform group corresponding to a current block, in **S1010**. The transform group may refer to a transform group of Table 4, but the present disclosure is not limited thereto. For example, the transform group may consist of other transform combinations.
- (131) The encoding apparatus **100** may perform a transform on available candidate transform combinations in the transform group, in **S1020**. As a result of the transform, the encoding apparatus **100** may determine or select a transform combination with the lowest rate distortion (RD) cost, in **S1030**. The encoding apparatus **100** may encode a transform combination index corresponding to the selected transform combination in **S1040**.
- (132) FIG. **11** illustrates an example of a flow chart for performing a transform through multiple transform selection in a decoding process of a video signal according to an embodiment of the present disclosure. First, the decoding apparatus **200** may determine a transform group for a current block, in **S1110**. The decoding apparatus **200** may parse a transform combination index, and the transform combination index may correspond to one of a plurality of transform combinations in the transform group, in **S1120**. The decoding apparatus **200** may derive a transform combination corresponding to the transform combination index, in **S1130**. Although the transform combination may refer to a transform combination described in Table 4, the present disclosure is not limited thereto. That is, the transform combination may be configured as other transform combinations.
- (133) The decoding apparatus **200** may perform an inverse transform on the current block based on the transform combination, in **S1140**. When the transform combination consists of a row transform and a column transform, the column transform may be first applied, and then the row transform may be applied. However, the present disclosure is not limited thereto, and the row transform may be applied and then the column transform may be applied. Alternatively, when the transform combination consists of non-separable transforms, a non-separable transform may be immediately applied. In some embodiments, a process of determining a transform group and a process of parsing a transform combination index may be performed at the same time.
- (134) In an embodiment of the present disclosure, as described below, two MTS candidates may be used for directional modes, and four MTS candidates may be used for nondirectional modes.
- (135) A) Nondirectional Modes (DC and Planar)
- (136) When MTS index is 0, DST-7 is used for horizontal and vertical transforms
- (137) When MTS index is 1, DST-7 is used for vertical transform and DCT-8 is used for horizontal transform
- (138) When MTS index is 2, DCT-8 is used for vertical transform and DST-7 is used for horizontal transform
- (139) When MTS index is 3, DCT-8 is used for horizontal and vertical transforms
- (140) B) Modes Belonging to Horizontal Group Modes
- (141) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(142) When MTS index is 1, DCT-8 is used for vertical transform and DST-7 is used for horizontal transform

(143) C) Modes Belonging to Vertical Group Modes

(144) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(145) When MTS index is 1, DST-7 is used for vertical transform and DCT-8 is used for horizontal transform

(146) Here (in the case where 67 intra-prediction modes are used), horizontal group modes include intra-prediction modes of Nos. 2 to 34, and vertical modes include intra-prediction modes of Nos. 35 to 66.

(147) In another embodiment of the present disclosure, three MTS candidates may be used for all the intra-prediction modes.

(148) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(149) When MTS index is 1, DST-7 is used for vertical transform and DCT-8 is used for horizontal transform

(150) When MTS index is 2, DCT-8 is used for vertical transform and DST-7 is used for horizontal transform

(151) In another embodiment of the present disclosure, two MTS candidates may be used for directional prediction modes, and three MTS candidates may be used for nondirectional modes.

(152) A) Nondirectional Modes (DC and Planar)

(153) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(154) When MTS index is 1, DST-7 is used for vertical transform and DCT-8 is used for horizontal transform

(155) When MTS index is 2, DCT-8 is used for vertical transform and DST-7 is used for horizontal transform

(156) B) Prediction Modes Corresponding to Horizontal Group Modes

(157) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(158) When MTS index is 1, DCT-8 is used for vertical transform and DST-7 is used for horizontal transform

(159) C) Prediction Modes Corresponding to Vertical Group Modes

(160) When MTS index is 0, DST-7 is used for horizontal and vertical transforms

(161) When MTS index is 1, DST-7 is used for vertical transform and DCT-8 is used for horizontal transform

(162) In another embodiment of the present disclosure, one MTS candidate (e.g., DST-7) may be used for all the intra-modes. In this case, encoding time can be reduced by 40% along with a minor coding loss. In addition, one flag may be used to indicate one of DCT-2 and DST-7.

(163) A method for performing the decoding based on information related to MTS of the encoding apparatus **100** according to an embodiment of the present disclosure is as follows.

(164) The decoding apparatus **200** according to an embodiment of the present disclosure may obtain a flag `sps_mts_intra_enabled_flag` indicating whether a flag `cu_mts_flag` indicating whether to apply MTS is present in a residual coding syntax of an intra-coding unit, or a flag `sps_mts_inter_enabled_flag` indicating whether a flag `cu_mts_flag` indicating whether to apply MTS is present in a residual coding syntax of an inter-coding unit. For example, if `sps_mts_intra_enabled_flag=0`, `cu_mts_flag` is not present in the residual coding syntax of the intra-coding unit, and if `sps_mts_intra_enabled_flag=1`, `cu_mts_flag` is present in the residual coding syntax of the intra-coding unit. In addition, `sps_mts_inter_enabled_flag` indicates whether `cu_mts_flag` is present in the residual coding syntax of the inter-coding unit. For example, if `sps_mts_inter_enabled_flag=0`, `cu_mts_flag` is not present in the residual coding syntax of the inter-coding unit, and if `sps_mts_inter_enabled_flag=1`, `cu_mts_flag` is present in the residual coding syntax of the inter-coding unit.

(165) The decoding apparatus **200** may obtain `cu_mts_flag` based on `sps_mts_intra_enabled_flag`

or `sps_mts_inter_enabled_flag`. For example, when `sps_mts_intra_enabled_flag=1` or `sps_mts_inter_enabled_flag=1`, the decoding apparatus **200** may obtain `cu_mts_flag`. Here, `cu_mts_flag` indicates whether MTS is applied to a residual sample of a luma transform block. For example, if `cu_mts_flag=0`, MTS is not applied to the residual sample of the luma transform block, and if `cu_mts_flag=1`, MTS is applied to the residual sample of the luma transform block.

(166) The decoding apparatus **200** may obtain an MTS index `mts_idx` based on `cu_mts_flag`. For example, when `cu_mts_flag=1`, the decoding apparatus **200** may obtain `mts_idx`. Here, `mts_idx` indicates which transform kernel is applied to luma residual samples of a current transform block in the horizontal direction and/or the vertical direction. For example, at least one of embodiments described in the present disclosure may be applied for `mts_idx`.

(167) The decoding apparatus **200** may derive a transform kernel corresponding to `mts_idx`. For example, the transform kernel corresponding to `mts_idx` may be defined by being divided into a horizontal transform and a vertical transform.

(168) For example, if MTS is applied to the current block (i.e., `cu_mts_flag=1`), the decoding apparatus **200** may construct MTS candidates based on the intra-prediction mode of the current block. Further, the decoding apparatus **200** may determine an MTS candidate applied to the current block from among the constructed MTS candidates using `mts_idx`.

(169) As another example, different transform kernels may be applied to the horizontal transform and the vertical transform. However, the present disclosure is not limited thereto, and the same transform kernel may be applied to the horizontal transform and the vertical transform.

(170) The decoding apparatus **200** may perform an inverse transform based on the transform kernel.

(171) Furthermore, in the present disclosure, MTS may be represented as AMT or EMT, and `mts_idx` may be represented as `AMT_idx`, `EMT_idx`, `AMT_TU_idx`, `EMT_TU_idx`, or the like, in the same manner. The present disclosure is not limited thereto.

(172) The present disclosure is described by being divided into a case, in which the MTS is applied, and a case, in which the MTS is not applied, based on the MTS flag, but embodiments of the present disclosure are not limited to such an expression. For example, whether to apply the MTS may be the same meaning as whether to use other transform types (or transform kernels) other than a predefined specific transform type (which may be referred to as a basic transform type, a default transform type, etc.). If the MTS is applied, a transform type (e.g., any one transform type or a combined transform type of two or more transform types among a plurality of transform types) other than a basic transform type may be used for a transform. Further, if the MTS is not applied, the basic transform type may be used for the transform. In an embodiment, the basic transform type may be configured (or defined) as DCT-2.

(173) As an example, when an MTS flag syntax indicating whether the MTS is applied to a current transform block, and an MTS index syntax indicating a transform type applied to the current transform block if the MTS are applied may also be individually transmitted from the encoding apparatus **100** to the decoding apparatus **200**. As another example, when whether the MTS is applied to a current transform block, and a syntax (e.g., MTS index) including all the transform types applied to the current transform block if the MTS are applied may also be transmitted from the encoding apparatus **100** to the decoding apparatus **200**. That is, in the latter example, a syntax (or syntax element) indicating a transform type applied to the current transform block (or unit) may be transmitted from the encoding apparatus **100** to the decoding apparatus **200** within all of transform type groups (or transform type sets) including the above-described basic transform type.

(174) Accordingly, the MTS index may represent together a transform type applied to the current transform block and whether to apply MTS. In other words, in the latter embodiment, only an MTS index may be signaled without an MTS flag. In this case, DCT-2 may be interpreted as being included in MTS. However, in the present disclosure, a case where DCT-2 is applied may be described as a case where MTS is not applied. Nevertheless, a technical range related to MTS is not

limited to corresponding defined contents.

(175) A method for the decoding apparatus **200** to generate a block including residual samples from a transform block through an inverse transform may be as follows.

(176) Input to this process is as follows: luma position (xTbY, yTbY) indicating a top left sample of a current luma transform block for a top left luma sample of a current picture, a variable nTbW indicating a width of a current transform block, a variable nTbH indicating a height of the current transform block, a variable cIdx indicating a chroma component of a current block, (nTbW)×(nTbH) array d[x][y] of scaled transform coefficients for x=0 . . . nTbW-1, and y=0 . . . nTbH-1.

(177) Output from this process is (nTbW)×(nTbH) array r[x][y] of residual samples for x=0 . . . nTbW-1, and y=0 . . . nTbH-1.

(178) A variable trTypeHor indicating a horizontal transform kernel and a variable trTypeVer indicating a vertical transform kernel may be derived based on mts\_idx[x][y] and CuPredMode[x][y] of Table 5.

(179) The (nTbW)×(nTbH) array of the residual samples may be derived as follows: 1. A (vertical) column of each scaled transform coefficient d[x][y] (x=0 . . . nTbW-1, y=0 . . . nTbH-1) is transformed into e[x][y] (x=0 . . . nTbW-1, y=0 . . . nTbH-1) by an one-dimensional transform process for a column x=0 . . . nTbW-1. In this case, an input is a transform type variable trType which is set to be same as the height nTbH of the transform block, the list d[x][y] (y=0 . . . nTbH-1), and trTypeVer, and the list e[x][y] (y=0 . . . nTbH-1) is output. 2. Intermediate sample values g[x][y] (x=0 . . . nTbW-1, y=0 . . . nTbH-1) are derived as in Equation 4 below.

$g[x][y] = \text{Clip3}(\text{CoeffMin}, \text{CoeffMax}, (e[x][y] + 256) \gg 9)$  3. A (horizontal) row of each intermediate array g[x][y] (x=0 . . . nTbW-1, y=0 . . . nTbH-1) is transformed into r[x][y] (x=0 . . . nTbW-1, y=0 . . . nTbH-1) by an one-dimensional (1D) transform process for each row y=0 . . . nTbH-1. In this case, an input is a transform type variable trType which is set to be same as the width nTbW of the transform block, the list g[x][y] (x=0 . . . nTbW-1), and trTypeHor, and the list r[x][y] (x=0 . . . nTbW-1) is output.

(180) Considering a non-zero width (nonZeroW) and a non-zero height (nonZeroH) by zero-out described below, a process of deriving a residual sample array may be represented again as follows.

(181) 1. For each column of a scaled (nonZeroW)×(nonZeroH) array transform coefficient block d[x][y] (where x=0 . . . nonZeroW-1, y=0 . . . nonZeroH-1) (each column is distinguished by x=0 . . . nonZeroW-1), the corresponding 1D transform process is called (by a total of nonZeroW calls), and thus (nonZeroW)×(nTbH) array block e[x][y] is obtained as an output, where x=0 . . . nonZeroW-1, y=0 . . . nTbH-1. When the corresponding 1 D transform process for x-th column is called, a length nTbH of the transform, a scaled transform coefficient vector length nonZeroH, a scaled transform coefficient vector d[x][y] (where x value denotes x-th column, y=0 . . . nonZeroH-1), and trTypeVer denoting a transform type (transferred to parameter trType) are transferred as input factors, and vector (list) e[x][y] is obtained as an output of the corresponding 1 D transform process (where x value denotes x-th column, y=0 . . . nTbH-1)

(182) 2. Intermediate sample values g[x][y] (x=0 . . . nonZeroW-1, y=0 . . . nTbH-1) are derived as in Equation 4 below.

$g[x][y] = \text{Clip3}(\text{CoeffMin}, \text{CoeffMax}, (e[x][y] + 64) \gg 7)$

(183) 3. For each row of (nonZeroW)×(nTbH) array block g[x][y] (where x=0 . . . nonZeroW-1, y=0 . . . nTbH-1) (each row is distinguished by y=0 . . . nTbH-1), the corresponding 1 D transform process is called (by a total of nTbH calls), and thus the (nTbW)×(nTbH) array block r[x][y] is obtained as an output (where x=0 . . . nTbW-1, y=0 . . . nTbH-1). When the corresponding 1 D transform process for y-th row is called, a length nTbW of the transform, an input vector length nonZeroW, an input vector g[x][y] (where y value denotes the y-th row, x=0 . . . nonZeroW-1), and trTypeHor denoting a transform type (transferred to parameter trType) are transferred as input factors, and vector (list) r[x][y] (where y value denotes the y-th row, x=0 . . . nTbW-1) is obtained

as an output of the corresponding 1D transform process (where y value denotes the y-th row, x=0 . . . nTbW-1).

(184) TABLE-US-00005 TABLE 5 CuPredMode[ x ][ y ] == CuPredMode[ x ][ y ] ==  
MODE\_INTRA MODE\_INTER mts\_idx[ x ][ y ] trTypeHor trTypeVer trTypeHor trTypeVer -1  
(inferred) 0 0 0 0 0 (00) 1 1 2 2 1 (01) 2 1 1 2 2 (10) 1 2 2 1 3 (11) 2 2 1 1

(185) In Table 5, CuPredMode denotes a prediction mode applied to a current CU, trTypeHor denotes a type of a transform kernel for a horizontal transform, and trTypeVer denotes a type of a transform kernel for a vertical transform.

(186) Embodiments of the present disclosure provide a syntax element for MTS. A sequence parameter set according to an embodiment of the present disclosure may include a flag (sps\_mts\_intra\_enabled\_flag) indicating whether an MTS flag or an MTS index is present in a low level syntax for an intra-coding unit (e.g., residual coding syntax, transform unit syntax), and a flag (sps\_mts\_inter\_enabled\_flag) indicating whether the MTS flag or the MTS index is present in a low level syntax for an inter-coding unit.

(187) According to a syntax structure for decoding of a transform unit according to an embodiment of the present disclosure, if specific condition is satisfied, the decoding apparatus **200** may parse an MTS flag (cu\_mts\_flag). For example, the condition for parsing the MTS flag may include a case in which sps\_mts\_intra\_enabled\_flag is 1 while a prediction mode of a current coding unit is an intra-prediction mode or sps\_mts\_inter\_enabled\_flag is 1 while the prediction mode of the current coding unit is an inter-prediction mode, there is a non-zero transform coefficient for a luma component, a current tree type is not a dual tree for a chroma component, and each of a width and a height of a transform block is less than or equal to a specific length (e.g., 32).

(188) After the MTS index (cu\_mts\_flag) is obtained, for example, if cu\_mts\_flag=0, MTS is not applied to a residual sample of a luma transform block, and if cu\_mts\_flag=1, MTS may be applied to the residual sample of the luma transform block.

(189) As described above, the present disclosure dividedly describes a case of applying the MTS and a case of not applying the MTS based on the MTS flag, but the present disclosure is not limited thereto. For example, whether to apply the MTS may mean whether to use transform types (or transform kernels) other than a predefined specific transform type (which may be referred to as a basic transform type, a default transform type, etc.). If the MTS is applied, a transform type (e.g., any one of a plurality of transform types or a combination of two or more transform types) other than the basic transform type may be used for the transform, and if the MTS is not applied, the basic transform type may be used for the transform. In an embodiment, the basic transform type may be configured (or defined) as DCT-2.

(190) For example, an MTS flag syntax indicating whether MTS is applied to a current transform block, and an MTS index syntax indicating a transform type applied to the current block when MTS is applied may be individually transmitted from the encoding apparatus **100** to the decoding apparatus **200**. As another example, a syntax (e.g., MTS index) including both information about whether MTS is applied to the current transform block and a transform type applied to the current block when MTS is applied may be transmitted from the encoding apparatus **100** to the decoding apparatus **200**. That is, in the latter embodiment, a syntax (or syntax element) indicating a transform type applied to the current transform block (or unit) in all of transform type groups (or transform type set) including the aforementioned basic transform type may be transmitted from the encoding apparatus **100** to the decoding apparatus **200**.

(191) Accordingly, despite the expression, a syntax (MTS index) indicating the transform type applied to the current transform block may include information about whether MTS is applied. In other words, in the latter embodiment, only an MTS index may be signaled without an MTS flag. In this case, DCT-2 may be interpreted as being included in MTS. However, the present disclosure may describe a case of applying DCT-2 as a case of not applying the MTS. Nevertheless, a technical range related to the MTS is not limited to corresponding defined contents.

(192) According to an embodiment of the present disclosure, flag (transform\_skip\_flag) indicating whether there is a transform skip, and the MTS index (mts\_idx) may be signaled via a residual syntax. However, this is merely an example, and the present disclosure is not limited thereto. For example, transform\_skip\_flag and/or mts\_idx syntax may be signaled via a transform unit syntax.

(193) Hereinafter, a method is proposed to improve complexity by applying a primary transform only to a predefined area. When combinations of various transforms (or transform kernels) such as MTS (e.g., DCT-2, DST-7, DCT-8, DST-1, DCT-5, etc.) are selectively applied to the primary transform, complexity may increase. Particularly, various transforms need to be considered as a size of a coding block (or transform block) increases, which may considerably increase complexity.

(194) Accordingly, an embodiment of the present disclosure proposes a method for performing a transform only on a predefined area according to specific conditions, instead of performing (or applying) the transform on all the areas in order to reduce complexity.

(195) In an embodiment, according to a reduced transform (RT) method, the encoding apparatus **100** may obtain an encoder may obtain an  $R \times R$  transform block instead of an  $M \times M$  transform block by applying a forward primary transform to an  $M \times M$  pixel block (luma block). For example, an  $R \times R$  area may be a top-left  $R \times R$  area in a current block (coding block, transform block). The decoding apparatus **200** may obtain an  $M \times M$  transform block by performing an inverse primary transform only on an  $R \times R$  ( $M \geq R$ ) area.

(196) Consequently, non-zero coefficients may be present only in the  $R \times R$  area. For example, in this case, the decoding apparatus **200** may zero-out coefficients present in areas other than the  $R \times R$  area without performing calculation therefor. The encoding apparatus **100** may perform a forward transform so that only the  $R \times R$  area remains (so that non-zero coefficients are present only in the  $R \times R$  area).

(197) Further, the decoding apparatus **200** may apply a primary transform (i.e., inverse transform) only to a predefined area determined depending on a size of a coding block (or transform block) and/or transform (or transform kernel) type. The following table 6 shows an example of a reduced adaptive multiple transform (RAMT) using a predefined  $R$  (which may be referred to as a reduced factor, a reduced transform factor, etc.) value depending on a size of a transform (or a size of a transform block). In the present disclosure, the RAMT representing a reduced transform adaptively determined depending on a block size may be referred to as a reduced MTS, a reduced explicit multiple transform, a reduced primary transform, etc.

(198) TABLE-US-00006

| TABLE 6        | Transform      | Reduced        | Reduced          | Reduced        | Reduced size   | transform 1    |
|----------------|----------------|----------------|------------------|----------------|----------------|----------------|
| transform 2    | transform 3    | $8 \times 8$   | $4 \times 4$     | $6 \times 6$   | $6 \times 6$   | $16 \times 16$ |
| $8 \times 8$   | $12 \times 12$ | $8 \times 8$   | $32 \times 32$   | $16 \times 16$ | $16 \times 16$ | $64 \times 64$ |
| $32 \times 32$ | $16 \times 16$ | $16 \times 16$ | $128 \times 128$ | $32 \times 32$ | $16 \times 16$ | $16 \times 16$ |

(199) Referring to Table 6, at least one reduced transform may be defined depending on a size of a transform (or a size of a transform block). In an embodiment, which reduced transform from among reduced transforms illustrated in Table 6 is used may be determined according to a transform (or transform kernel) applied to a current block (coding block or transform block). Although Table 6 assumes that three reduced transforms are used, the present disclosure is not limited thereto. One or more various reduced transforms may be predefined depending on the size of the transform.

(200) Further, in an embodiment of the present disclosure, a reduced transform factor ( $R$ ) may be determined depending on the primary transform in application of the aforementioned reduced adaptive multiple transform. For example, if the primary transform is DCT-2, a reduction of coding performance can be minimized by not using the reduced transform for a small-sized block or by using a relatively large  $R$  value because computational complexity of DCT-2 is relatively lower than those of other primary transforms (e.g., a combination of DST-7 and/or DCT-8). The following Table 7 shows an example of an RAMT using a predefined  $R$  value depending on a size of a transform (or a size of a transform block) and a transform kernel.

(201) TABLE-US-00007

| TABLE 7 | Transform | Reduced transform | Reduced transform size for |
|---------|-----------|-------------------|----------------------------|
|---------|-----------|-------------------|----------------------------|

DCT2 except DCT2  $8 \times 8$   $8 \times 8$   $4 \times 16$   $16 \times 16$   $8 \times 8$   $32 \times 32$   $32 \times 32$   $16 \times 16$   $64 \times 64$   $32 \times 32$   $32 \times 32$   $128 \times 128$   $32 \times 32$   $32 \times 32$

(202) Referring to Table 7, if a transform applied to the primary transform is DCT-2 and if the transform applied to the primary transform is a transform other than DCT-2 (e.g., combination of DST7 and/or DCT8), different reduced transform factors may be used.

(203) An operation of the encoding apparatus **100** for applying a reduced transform according to an embodiment of the present disclosure is as below. First, the encoding apparatus **100** determines whether to apply a transform to a current block. The encoding apparatus **100** may encode a transform skip flag depending on the determined result. In this case, the encoding apparatus **100** may encode the transform skip flag.

(204) If the transform is applied to the current block, the encoding apparatus **100** determines a transform kernel to be applied to a primary transform of the current block. The encoding apparatus **100** may encode a transform index indicating the determined transform kernel. The encoding apparatus **100** determines an area, in which a significant coefficient is present in the current block, based on the transform kernel applied to the primary transform of the current block and a size of the current block.

(205) In an embodiment, if a transform kernel indicated by a transform index is a predefined transform and a width and/or a height of a current block are greater than a predefined size, the encoding apparatus **100** may determine an area having a width and/or a height of the predefined size as an area in which the significant coefficient is present.

(206) For example, the predefined transform may be one of a plurality of transform combinations consisting of combinations of DST-7 and/or DCT-8, and the predefined size may be 16.

Alternatively, the predefined transform may be a transform except DCT-2. As an example, if a transform kernel indicated by a transform index is DCT-2 and a width and/or a height of a current block are greater than 32, the encoding apparatus **100** may determine an area having the width and/or the height of 32 as an area to which the primary transform is applied, and may include a non-zero transform coefficient in a reduced area having the width or the height of 16 when expressing an output according to a transform in two-dimensional form.

(207) Further, in an embodiment, if a transform kernel indicated by a transform index belongs to a first transform group, the encoding apparatus **100** may determine a smaller value of a width of a current block and a first threshold value as a width of an area in which a significant coefficient (non-zero coefficient) according to the primary transform is present, and may determine a smaller value of a height of the current block and the first threshold value as a height of an area in which the significant coefficient is present. For example, the first threshold value may be 32, but the present disclosure is not limited thereto. For example, the first threshold value may be 4, 8, or 16 as shown in Table 6 or Table 7.

(208) In addition, if the transform kernel indicated by the transform index belongs to a second transform group, the encoding apparatus **100** may determine a smaller value of the width of the current block and a second threshold value as a width of an area to which the primary transform is applied, and may determine a smaller value of the height of the current block and the second threshold value as the height of the area in which the significant coefficient is present. For example, the second threshold value may be 16, but the present disclosure is not limited thereto. For example, the second threshold value may be 4, 6, 8, 12, or 32 as shown in Table 6 or Table 7.

(209) In an embodiment, the first transform group may include DCT-2, and the second transform group may include a plurality of transform combinations consisting of combinations of DST-7 and/or DCT-8.

(210) The encoding apparatus **100** performs a forward primary transform using the transform kernel applied to the primary transform of the current block. The encoding apparatus **100** may a primarily transformed transform coefficients in the area in which the significant coefficient is present by performing the forward primary transform. In an embodiment, the encoding apparatus

**100** may apply a secondary transform to the primarily transformed transform coefficient.

(211) An operation of the decoding apparatus **200** for applying a reduced transform according to an embodiment of the present disclosure is as below. The decoding apparatus **200** checks whether a transform skip is applied to a current block. If the transform skip is not applied to the current block, the decoding apparatus **200** obtains, from a video signal, a transform index indicating a transform kernel applied to the current block.

(212) The decoding apparatus **200** determines an area, in which a primary transform (i.e., inverse primary transform) is applied to the current block, based on the transform kernel indicated by the transform index and a size (i.e., width and/or height) of the current block. In an embodiment, the decoding apparatus **200** may consider coefficients of a remaining area other than the area, to which the primary transform is applied, as zero in the current block. In addition, if the transform kernel indicated by the transform index is a predefined transform and the width and/or the height of the current block are greater than a predefined size, the decoding apparatus **200** may determine an area having a width and/or a height of the predefined size as the area to which the primary transform is applied.

(213) For example, the predefined transform may be any one of a plurality of transform combinations consisting of combinations of DST-7 and/or DCT-8, and the predefined size may be 16. Alternatively, the predefined transform may be a transform except DCT-2. For example, if the transform kernel indicated by the transform index is DCT-2 and the width and/or the height of the current block are greater than 32, the decoding apparatus **200** may determine an area having a width and/or a height of 32 as the area to which the primary transform is applied.

(214) Furthermore, in an embodiment, if a transform kernel indicated by a transform index belongs to a first transform group, the decoding apparatus **200** may determine a smaller value of the width of the current block and a first threshold value as a width of an area to which the primary transform is applied, and may determine a smaller value of the height of the current block and the first threshold value as a height of an area to which the primary transform is applied. For example, the first threshold value may be 32, but the present disclosure is not limited thereto. For example, the first threshold value may be 4, 8, or 16 as shown in Table 6 or Table 7.

(215) In addition, if the transform kernel indicated by the transform index belongs to a second transform group, the decoding apparatus **200** may determine a smaller value of the width of the current block and a second threshold value as the width of the area to which the primary transform is applied, and may determine a smaller value of the height of the current block and the second threshold value as the height of the area to which the primary transform is applied. For example, the second threshold value may be 16, but the present disclosure is not limited thereto. For example, the second threshold value may be 4, 6, 8, 12, or 32 as shown in Table 6 or Table 7.

(216) In an embodiment, the first transform group may include DCT-2, and the second transform group may include a plurality of transform combinations consisting of combinations of DST-7 and/or DCT-8.

(217) The decoding apparatus **200** performs an inverse primary transform on the area, to which the inverse primary transform is applied, using the transform kernel indicated by the transform index. The decoding apparatus **200** may obtain inverse primary transformed transform coefficients by performing the inverse primary transform. In an embodiment, the decoding apparatus **200** may apply an inverse secondary transform to a dequantized transform coefficient before performing the inverse primary transform.

#### First Embodiment

(218) According to an embodiment of the present disclosure, worst case complexity can be considerably reduced by performing a transform only on a predefined area according to specific conditions.

(219) In addition, in an embodiment of the present disclosure, if an MTS (EMT or AMT) flag is 0 (i.e., if DCT-2 transform is applied in both a horizontal (lateral) direction and a vertical

(longitudinal) direction), the decoding apparatus **200** may leave only 32 coefficients from each of the left side and the upper side in the horizontal and vertical directions and perform zero-out for a high frequency component (i.e., consider or set the high frequency component as 0). Although this embodiment is referred to as the first embodiment for convenience of explanation in embodiments to be described later, embodiments of the present disclosure are not limited thereto.

(220) For example, for a  $64 \times 64$  TU (or CU), the decoding apparatus **200** may leave transform coefficients only for a  $32 \times 32$  top left area and perform zero-out for coefficients of a remaining area. Further, for a  $64 \times 16$  TU, the decoding apparatus **200** may leave transform coefficients only for a  $32 \times 16$  top left area and perform zero-out for coefficients of a remaining area. In addition, for an  $8 \times 64$  TU, the encoding apparatus **100**/decoding apparatus **200** may leave transform coefficients only for a  $8 \times 32$  top left area and perform zero-out for coefficients of a remaining area. That is, it may be configured so that transform coefficients are present only for a maximum length of 32 in both the horizontal and vertical directions, which can improve transform efficiency.

(221) In an embodiment, such a zero-out method may be applied only to a residual signal to which intra-prediction is applied, or may be applied only to a residual signal to which inter-prediction is applied, or applied to both a residual signal to which intra-prediction is applied and a residual signal to which inter-prediction is applied.

### Second Embodiment

(222) In an embodiment of the present disclosure, if an MTS flag is 1 (i.e., if a transform (e.g., DST-7 or DCT-8) other than DCT-2 transform is applicable in the horizontal direction and the vertical direction), the decoding apparatus **200** may leave coefficients of a specific top-left area and perform zero-out for a remaining high frequency component (i.e., consider or set the high frequency component as 0). Although this embodiment is referred to as the second embodiment for convenience of explanation in embodiments to be described later, embodiments of the present disclosure are not limited thereto.

(223) In an embodiment, the decoding apparatus **200** may be configured to leave only a transform coefficient area of a part of the top-left area as in the following example. That is, the encoding apparatus **100** may leave coefficients of a predefined top-left area and perform zero-out for a remaining high frequency component, and the decoding apparatus **200** may preset the length (or the number) of transform coefficients in the horizontal and/or vertical directions to which a primary transform is applied depending on a width and/or a height. For example, coefficients outside the length to which an inverse primary transform is applied may be zero-out. If a width (w) is equal to or greater than  $2 \cdot \sup.n$ , transform coefficients only for a length of  $w/2 \cdot \sup.p$  from the left side may be left, and transform coefficients of a remaining area may be fixed (or set or consider) to 0 (zero-out). If a height (h) is equal to or greater than  $2 \cdot \sup.n$ , transform coefficients may be left only for a length of  $h/2 \cdot \sup.q$  from the top, and transform coefficients of a remaining area may be fixed to a value of 0.

(224) For example, values m, n, p, and q may be predefined as various values. For example, the values m, n, p, and q may be set to integer values equal to or greater than 0. Alternatively, they may be set as in the following examples. 1) (m, n, p, q)=(5, 5, 1, 1) 2) (m, n, p, q)=(4, 4, 1, 1)

(225) For example, if they are predefined as the example of 1), transform coefficients may be left only for a  $16 \times 16$  top left area in a  $32 \times 16$  TU, and transform coefficients may be left only for a  $8 \times 16$  top left area in an  $8 \times 32$  TU.

(226) In an embodiment, such a zero-out method may be applied only to a residual signal to which intra-prediction is applied, or may be applied only to a residual signal to which inter-prediction is applied, or applied to both a residual signal to which intra-prediction is applied and a residual signal to which inter-prediction is applied.

### Third Embodiment

(227) In another embodiment of the present disclosure, when an MTS flag is 1 (i.e., if a transform (e.g., DST-7 or DCT-8) other than DCT-2 transform is applicable in the horizontal direction and the

vertical direction), the decoding apparatus **200** may leave coefficients of a specific top-left area and perform zero-out for a remaining high frequency component (i.e., consider or set the high frequency component as 0). Alternatively, more specifically, the encoding apparatus **100** may leave coefficients of a predefined top-left area and perform zero-out for a remaining high frequency component, and the decoding apparatus **200** may previously recognize a zero-out area and perform decoding using coefficients of the non-zero-out area. However, embodiments of the present disclosure are not limited thereto, and the zero-out process from a decoder perspective may be understood as a process of considering (or recognizing or setting) a zero-out area as 0. Although this embodiment is referred to as the third embodiment for convenience of explanation in embodiments to be described later, embodiments of the present disclosure are not limited thereto. (228) In an embodiment, the decoding apparatus **200** may be configured to leave only a transform coefficient area of a part of the top-left area as in the following example. That is, the encoding apparatus **100**/decoding apparatus **200** may preset the length (or the number) of transform coefficients in the horizontal and/or vertical directions to which an inverse primary transform is applied depending on a width and/or a height. For example, coefficients outside the length to which the inverse primary transform is applied may be zero-out. When the height (h) is equal to or greater than the width (w) and is equal to or greater than  $2 \cdot \sup.n$ , only a  $w \times (h/2 \cdot \sup.p)$  top-left area may leave a transform coefficient, and a transform coefficient of a remaining area may be fixed (or set or consider) to zero. When the width (w) is greater than the height (h) and is equal to or greater than  $2 \cdot \sup.m$ , only a  $(w/2 \cdot \sup.q) \times h$  top-left area may leave a transform coefficient, and a transform coefficient of a remaining area may be fixed to zero.

(229) Although the above-described example describes that the length in the vertical direction is reduced to  $(h/2 \cdot \sup.p)$  when the height (h) is equal to the width (w), the length in the horizontal direction may be configured to be reduced to  $(w/2q)$ .

(230) For example, values m, n, p, and q may be predefined as various values. For example, the values m, n, p, and q may be set to integer values equal to or greater than 0. Alternatively, more specifically, they may be set as in the following examples. 1) (m, n, p, q)=(4, 4, 1, 1) 2) (m, n, p, q)=(5, 5, 1, 1)

(231) For example, if they are predefined as the example of 1), transform coefficients may be left only for a  $16 \times 16$  top left area in a  $32 \times 16$  TU, and transform coefficients may be left only for a  $8 \times 8$  top left area in an  $8 \times 16$  TU.

(232) In an embodiment, such a zero-out method may be applied only to a residual signal to which intra-prediction is applied, or may be applied only to a residual signal to which inter-prediction is applied, or applied to both a residual signal to which intra-prediction is applied and a residual signal to which inter-prediction is applied.

(233) The first embodiment relating to a method of limiting a transform coefficient area when the MTS flag is 0, and the second and third embodiments relating to a method of limiting a transform coefficient area when the MTS flag is 1 may be individually applied or may be combined and applied.

(234) In an embodiment, the following combined configurations may be applied. 1) First embodiment+Second embodiment 2) First embodiment+Third embodiment

(235) As mentioned in the second and third embodiments, as an embodiment, the zero-out method may be applied only to a residual signal to which intra-prediction is applied, or may be applied only to a residual signal to which inter-prediction is applied, or may be applied to both a residual signal to which intra-prediction is applied and a residual signal to which inter-prediction is applied.

Accordingly, the following combined configurations may be applied when the MTS flag is 1. In this instance, the first embodiment may be applied when the MTS flag is 0.

(236) TABLE-US-00008 TABLE 8 Config. Intra-prediction Inter-prediction index residual signal residual signal 1 Zero-out is not applied Zero-out is not applied 2 Zero-out is not applied First embodiment 3 Zero-out is not applied Second embodiment 4 First embodiment Zero-out is not

applied 5 First embodiment First embodiment 6 First embodiment Second embodiment 7 Second embodiment Zero-out is not applied 8 Second embodiment First embodiment 9 Second embodiment Second embodiment

(237) In an embodiment of the present disclosure, the encoding apparatus **100**/decoding apparatus **200** may not perform a residual coding on an area that is regarded as an area having a transform coefficient of 0 according to zero-out of the above-described embodiments. That is, the encoding apparatus **100**/decoding apparatus **200** may define to perform the residual coding only on areas other than a zero-out area.

(238) In the above-described first, second and third embodiments, an area (or coefficient) that can only have a value of 0 in a TU is obviously determined. That is, areas other than the top left area in which presence of transform coefficients is permitted are zero-out. Thus, in an entropy coding (or residual coding) process, the encoding apparatus **100**/decoding apparatus **200** may be configured to bypass an area guaranteed to have a value of 0 without performing residual coding on the area.

(239) In an embodiment, the encoding apparatus **100**/decoding apparatus **200** may code a flag (referred to as a coded block flag (CBF)) (or a syntax or a syntax element) indicating presence or absence of a non-zero transform coefficient in a coefficient group (CG). Here, the CG is a subblock of a TU and may be configured as a 4×4 or 2×2 block depending on a shape of a TU block and/or whether the TU is a chroma/luma component.

(240) In this instance, the encoding apparatus **100**/decoding apparatus **200** may scan the inside of the corresponding CG to code coefficient values (or coefficient level values) only when the CBF is 1. Thus, the encoding apparatus **100**/decoding apparatus **200** does not perform CBF coding on CGs belonging to an area zeroed out to zero and may configure so that the CGs have a value of zero by default.

(241) In an embodiment, the encoding apparatus **100** may first code a position of a coefficient that is last located in the forward scan order (or a syntax or a syntax element indicating a position of a last significant coefficient). For example, the encoding apparatus **100** may code last\_coefficient position\_x that is a horizontal position, and last\_coefficient position\_y that is a vertical position. In the present disclosure, the last significant coefficient is a non-zero transform coefficient that is last disposed when transform coefficients are disposed according to the scan order from a top left position in one transform block. A position after the last significant coefficient in the scan order is filled with zero (considered to be zero).

(242) Maximum values of available values of last\_coefficient position\_x and last\_coefficient position\_y may be respectively determined as (width-1) and (height-1) of a TU. However, when an area in which non-zero coefficients can be present is limited by zero-out, the maximum values of available values of last\_coefficient position\_x and last\_coefficient\_position\_y may also be limited.

(243) Accordingly, the encoding apparatus **100**/decoding apparatus **200** may limit the maximum values of available values of last\_coefficient position\_x and last\_coefficient position\_y in consideration of zero-out, and then code them. For example, when a binarization method applied to last\_coefficient position\_x and last\_coefficient position\_y is a (truncated unary (or truncated rice (TR) or truncated binary (TB)) binarization method, the encoding apparatus **100**/decoding apparatus **200** may control (reduce) so that a maximum length of a truncated unary code corresponds to an adjusted maximum value (i.e., available maximum values of last\_coefficient position\_x and last\_coefficient\_position\_y).

(244) FIGS. **12a** and **12b** illustrate an example where a separable transform according to an embodiment of the present disclosure is applied. More specifically, FIG. **12a** illustrates an area where a significant coefficient is present and an area where zero-out is applied upon forward transform (upon encoding), and FIG. **12b** illustrates an area where a significant coefficient is present and an area where zero-out is applied upon inverse transform (upon decoding).

(245) A scheme for leaving only coefficients of a low frequency area (e.g., a 16×16 top left area in

a  $32 \times 32$  block) for a block to which MTS is applied based on a forward transform and applying zero-out (filled with 0 or derived as 0) to a remainder may be referred to as reduced multiple transform selection (RMTS). For example, in FIG. 12a, if the size of a block **1210** including residual sample values is  $32 \times 32$  and a  $16 \times 16$  reduced block is output by the application of the RMTS, only coefficients (16 coefficients from the left) disposed in a left area **1220** in a row direction among coefficients generated by the application of a horizontal transform are left, and a right area **1225** is considered to have a coefficient of 0. Thereafter, only coefficients (16 coefficients from the top) disposed in a top area **1230** in a column direction among coefficients generated by the application of a vertical transform are left, and a remaining area **1235** is considered to have a coefficient of 0.

(246) Referring to FIG. 12b, the size of a transform block **1255** including transform coefficients is  $32 \times 32$ , a transform is applied to a  $16 \times 16$  top left area **1250** by the application of the RMTS, and a remaining area is considered to have a coefficient of 0. Since a vertical inverse transform is applied to the  $16 \times 16$  area, significant coefficients are generated in a left area **1260** of the transform block, and a right area **1265** is still considered to have a coefficient of 0. Thereafter, since a horizontal inverse transform is applied to the left area **1260**, significant coefficients may be present for the entire  $32 \times 32$  area of the transform block.

(247) In an embodiment of the present disclosure, there is proposed reduced 32-point MTS (RMTS32) in which a transform for high frequency coefficients is omitted. The 32-point MTS represents a method of applying a transform to a row or a column with a length of 32. The 32-point MTS can require up to 64 multiplication operations per output sample by considering the worst computational complexity, and thus the RMTS32 can reduce the computational complexity and also reduce memory usage.

(248) According to the RMTS32, when an MTS flag is 1 (or when an MTS index is greater than 0) and a block width (height) is greater than or equal to 32, a remaining area is considered to be 0 (zero-out) while a maximum  $16 \times 16$  top left area is maintained, and up to left (top) 16 coefficients are maintained. Since zero-out is independently applied in the horizontal and vertical directions, the RMTS may be applied to all block shapes. Assuming that RMTS is applied to a 32-length, a  $16 \times 16$  top left area may be maintained for a  $32 \times 32$  transform block, a  $16 \times 8$  top left area may be maintained for a  $32 \times 8$  transform block, and a  $16 \times 16$  top left area may be maintained for a  $16 \times 32$  transform block.

(249) The computational complexity of 32-point MTS can be reduced to a half by using the RMTS32 from a perspective of an operation count. In this case, the 32-point MTS is a transform matrix applied to a row or a column with a length 32 of a block (when an MTS index is greater than 0 while only an MTS index is used for deriving a transform combination). Furthermore, from a perspective of memory usage, only a half the transform basis vectors of 32-point MTS matrices needs to be stored. With respect to an area considered to be zero, residual coding may be omitted because a related subblock flag is implicitly derived as 0, and a parameter for truncated unary binarization of the last coefficient position may be adjusted depending on a position at which a sufficient transform coefficient can be present.

(250) From a perspective of memory usage, the RMTS32 proposed in this embodiment generates 16 coefficients for a row or a column with a 32-length. Hence, in  $32 \times 32$  DST-7/DCT-8, only the first 16 transform basis vectors need to be stored, and the memory usage for storing 32-length DST-7/DCT-8 can be reduced to a half (e.g., from 2 KB to 1 KB).

(251) For example, a residual coding syntax for implementing the above-described RMTS32 may be configured as in the following Table 9.

(252) TABLE-US-00009 TABLE 9 Descriptor residual\_coding( x0, y0, log2TbWidth, log2TbHeight, cIdx ) { if( transform\_skip\_enabled\_flag && ( cIdx != 0 || tu\_mts\_flag[ x0 ][ y0 ] == 0 ) && ( log2TbWidth <= 2 ) && ( log2TbHeight <= 2 ) ) transform\_skip\_flag[ x0 ][ y0 ][ cIdx ] ae(v) last\_sig\_coeff\_x\_prefix ae(v) last\_sig\_coeff\_y\_prefix ae(v) if(

```

last_sig_coeff_x_prefix > 3 ) last_sig_coeff_x_suffix ae(v)    if( last_sig_coeff_y_prefix > 3 )
last_sig_coeff_y_suffix ae(v)    ...    for( i = lastSubBlock; i >= 0; i-- ) { ... if( ( i <
lastSubBlock ) && ( i > 0 ) ) {    if( transform_skip_flag[ x0 ][ y0 ][ cIdx ] == 1 || ( tu_mts_flag[
x0 ][ y0 ] == 0 && ( xS << log2SbSize ) < 32 && ( yS << log2SbSize ) < 32 ) || ( tu_mts_flag[ x0
][ y0 ] == 1 && ( cIdx != 0 || ( ( xS << log2SbSize ) < 16 ) && ( ( yS << log2SbSize ) < 16 ) ) )
) coded_sub_block_flag[ xS ][ yS ] ae(v) inferSbDcSigCoeffFlag = 1 } ...    }    if( tu_mts_flag[
x0 ][ y0 ] && ( cIdx == 0 ) ) mts_idx[ x0 ][ y0 ][ cIdx ] ae(v) }

```

(253) Furthermore, a non-zero width (nonZeroW) and a non-zero height (nonZeroH) of an area to which a transform is applied in a transform block may be determined as follows.

nonZeroW=Min(nTbW,trTypeHor==0?32:16)

nonZeroH=Min(nTbH,trTypeVer==0?32:16)

(254) Here, nTbW denotes a width of a current block (transform block), nTbH denotes a height of the current block (transform block), and trTypeHor and trTypeVer denote a type of horizontal transform kernel and a type of vertical transform kernel, respectively. Min(A, B) is a function for outputting a smaller value of A and B.

(255) For example, trTypeHor and trTypeVer may be determined as in the following Table 10 based on an MTS index (mts\_idx) that is an index indicating a transform type.

(256) TABLE-US-00010 TABLE 10 mts\_idx trTypeHor trTypeVer 0 0 0 1 1 1 2 2 1 3 1 2 4 2 2

(257) Here, values of trTypeHor and trTypeVer denote one of types of transform kernel. For example, 0 may denote DCT-2, 1 may denote DST-7, and 2 may denote DCT-8. In Table 10, if mts\_idx is 0, trTypeHor and trTypeVer are also determined as 0. If mts\_idx is not 0 (if it is greater than 0), trTypeHor and trTypeVer are also determined as a non-zero value (greater than 0).

(258) In other words, the non-zero width (nonZeroW) of an area to which a transform is applied may be determined as a smaller value of a width (nTbW) of a current block (transform block) and 16 if a transform index (trTypeHor) is greater than a threshold value (e.g., 0) (i.e., if trTypeHor is not 0), and may be determined a smaller value of the width of the current block and 32 if the transform index (trTypeHor) is not greater than the threshold value (e.g., 0) (i.e., if trTypeHor is 0).

(259) Furthermore, the non-zero height (nonZeroH) of the area to which the transform is applied may be determined as a smaller value of the height (nTbH) of the current block (transform block) and 16 if a vertical transform type index (trTypeVer) is greater than the threshold value (e.g., 0), and may be determined as a smaller value of the height (nTbH) of the current block (transform block) and 32 if the vertical transform type index (trTypeVer) is not greater than the threshold value (e.g., 0).

(260) According to an embodiment of the present disclosure, only a half the 32-length DST-7/DCT-8 may be stored in the memory as follows.

(261) For example, if a (horizontal or vertical) transform type index (trType) is 1 (e.g., DST-7) and the number of samples (nTbs) of a row or column of a transform target block is 32, a transform matrix may be derived as in the following Tables 11 and 12. Matrices of Tables 11 and 12 are horizontally concatenated to constitute one matrix. In [m][n], m is a transverse index, and n is a longitudinal index. If the matrix of Table 11 and the matrix of Table 12 are concatenated, a 16×32 matrix is derived, and the corresponding matrix becomes a matrix for a forward transform. An inverse transform may be performed through the matrix configured by Tables 11 and 12 and proper indexing. Furthermore, in Tables 11 and 12, the strike-out for 16 rows below means that the 16 rows are deleted because they are unnecessary by the application of a reduced transform.

(262) TABLE-US-00011 TABLE 11 transMatrix[ m ][ n ] = transMatrixCol0to15[ m ][ n ] with m = 0..15, n = 0..15 transMatrixCol0to15 = { { 4 9 13 17 21 26 30 34 38 42 45 50 53 56 60 63 } { 13 26 38 50 60 68 77 82 86 89 90 88 85 80 74 66 } { 21 42 60 74 84 89 89 84 74 60 42 21 0 -21 -42 -60 } { 30 56 77 88 89 80 63 38 9 -21 -50 -72 -85 -90 -84 -68 } { 38 68 86 88 74 45 9 -30 -63 -84 -90 -78 -53 -17 21 56 } { 45 78 90 77 42 -4 -50 -80 -90 -74 -38 9 53 82 89 72 } { 53 85 85 53 0 -53 -85 -85 -53 0 53 85 85 53 0 -53 } { 60 89 74 21 -42 -84 -84 -42 21 74 89 60 0 -60

-89 -74 } { 66 90 56 -13 -74 -88 -45 26 80 84 34 -38 -85 -78 -21 50 } { 72 86 34 -45 -89 -63 13 78 82 21 -56 -90 -53 26 84 77 } { 77 80 9 -72 -84 -17 66 86 26 -60 -88 -34 53 90 42 -45 } { 80 72 -17 -86 -60 34 90 45 -50 -89 -30 63 85 13 -74 -78 } { 84 60 -42 -89 -21 74 74 -21 -89 -42 60 84 0 -84 -60 42 } { 86 45 -63 -78 21 90 26 -77 -66 42 88 4 -85 -50 60 80 } { 88 30 -78 -56 60 77 -34 -88 4 89 26 -80 -53 63 74 -38 } { 90 13 -88 -26 84 38 -78 -50 72 60 -63 -68 53 77 -42 -82 } },

(263) TABLE-US-00012 TABLE 12 transMatrix[ m ][ n ] = transMatrixCol16to31 [ m - 16 ][ n ] with m = 16..31, n = 0..15 transMatrixCol16to31 = { { 66 68 72 74 77 78 80 82 84 85 86 88 88 89 90 90 } { 56 45 34 21 9 -4 -17 -30 -42 -53 -63 -72 -78 -84 -88 -90 } { -74 -84 -89 -89 -84 -74 -60 -42 -21 0 21 42 60 74 84 89 } { -45 -17 13 42 66 82 90 86 74 53 26 -4 -34 -60 -78 -88 } { 80 90 82 60 26 -13 -50 -77 -89 -85 -66 -34 4 42 72 88 } { 34 -13 -56 -84 -88 -68 -30 17 60 85 88 66 26 -21 -63 -86 } { -85 -85 -53 0 53 85 85 53 0 -53 -85 -85 -53 0 53 85 } { -21 42 84 84 42 -21 -74 -89 -60 0 60 89 74 21 -42 -84 } { 88 72 9 -60 -90 -63 4 68 89 53 -17 -77 -86 -42 30 82 } { 9 -66 -88 -42 38 88 68 -4 -74 -85 -30 50 90 60 -17 -80 } { -90 -50 38 89 56 -30 -88 -63 21 85 68 -13 -82 -74 4 78 } { 4 82 68 -21 -88 -56 38 90 42 -53 -88 -26 66 84 9 -77 } { 89 21 -74 -74 21 89 42 -60 -84 0 84 60 -42 -89 -21 74 } { -17 -90 -30 74 68 -38 -88 -9 84 53 -56 -82 13 89 34 -72 } { -86 9 90 21 -82 -50 66 72 -42 -85 13 90 17 -84 -45 68 } { 30 86 -17 -89 4 90 9 -88 -21 85 34 -80 -45 74 56 -66 } },

(264) Furthermore, if a (horizontal or vertical) transform type index (trType) is 2 (e.g., DCT-8) and the number of samples (nTbs) of a row or column of a transform target block is 32, a transform matrix may be derived as in the following Tables 13 and 14. Matrices of Tables 13 and 14 are horizontally concatenated to constitute one matrix. In [m][n], m is a transverse index, and n is a longitudinal index. If the matrix of Table 13 and the matrix of Table 14 are concatenated, a 16×32 matrix is derived, and the corresponding matrix becomes a matrix for a forward transform. An inverse transform may be performed through the matrix configured by Tables 13 and 14 and proper indexing. Furthermore, in Tables 13 and 14, the strike-out for 16 rows below means that the 16 rows are deleted because they are unnecessary by the application of a reduced transform.

(265) TABLE-US-00013 TABLE 13 transMatrix[ m ][ n ] = transMatrixCol0to15[ m ][ n ] with m = 0..15, n = 0..15 transMatrixCol0to15 = { { 90 90 89 88 88 86 85 84 82 80 78 77 74 72 68 66 } { 90 88 84 78 72 63 53 42 30 17 4 -9 -21 -34 -45 -56 } { 89 84 74 60 42 21 0 -21 -42 -60 -74 -84 -89 -89 -84 -74 } { 88 78 60 34 4 -26 -53 -74 -86 -90 -82 -66 -42 -13 17 45 } { 88 72 42 4 -34 -66 -85 -89 -77 -50 -13 26 60 82 90 80 } { 86 63 21 -26 -66 -88 -85 -60 -17 30 68 88 84 56 13 -34 } { 85 53 0 -53 -85 -85 -53 0 53 85 85 53 0 -53 -85 -85 } { 84 42 -21 -74 -89 -60 0 60 89 74 21 -42 -84 -84 -42 21 } { 82 30 -42 -86 -77 -17 53 89 68 4 -63 -90 -60 9 72 88 } { 80 17 -60 -90 -50 30 85 74 4 -68 -88 -38 42 88 66 -9 } { 78 4 -74 -82 -13 68 85 21 -63 -88 -30 56 89 38 -50 -90 } { 77 -9 -84 -66 26 88 53 -42 -90 -38 56 88 21 -68 -82 -4 } { 74 -21 -89 -42 60 84 0 -84 -60 42 89 21 -74 -74 21 89 } { 72 -34 -89 -13 82 56 -53 -84 9 88 38 -68 -74 30 90 17 } { 68 -45 -84 17 90 13 -85 -42 72 66 -50 -82 21 90 9 -86 } { 66 -56 -74 45 80 -34 -85 21 88 -9 -90 -4 89 17 -86 -30 } },

(266) TABLE-US-00014 TABLE 14 transMatrix[ m ][ n ] = transMatrixCol16to31 [ m - 16 ][ n ] with m = 16..31, n = 0..15 transMatrixCol16to31 = { { 63 60 56 53 50 45 42 38 34 30 26 21 17 13 9 4 } { -66 -74 -80 -85 -88 90 -89 -86 -82 -77 -68 -60 -50 -38 -26 -13 } { -60 -42 -21 0 21 42 60 74 84 89 89 84 74 60 42 21 } { 68 84 90 85 72 50 21 -9 -38 -63 -80 -89 -88 -77 -56 -30 } { 56 21 -17 -53 -78 -90 -84 -63 -30 9 45 74 88 86 68 38 } { -72 -89 -82 -53 -9 38 74 90 80 50 4 -42 -77 -90 -78 -45 } { -53 0 53 85 85 53 0 -53 -85 -85 -53 0 53 85 85 53 } { 74 89 60 0 -60 -89 -74 -21 42 84 84 42 -21 -74 -89 -60 } { 50 -21 -78 -85 -38 34 84 80 26 -45 -88 -74 -13 56 90 66 } { -77 -84 -26 53 90 56 -21 -82 -78 -13 63 89 45 -34 -86 -72 } { -45 42 90 53 -34 -88 -60 26 86 66 -17 -84 -72 9 80 77 } { 78 74 -13 -85 -63 30 89 50 -45 -90 -34 60 86 17 -72 -80 } { 42 -60 -84 0 84 60 -42 -89 -21 74 74 -21 -89 -42 60 84 } { -80 -60 50 85 -4 -88 -42 66 77 -26 -90 -21 78 63 -45 -86 } { -38 74 63 -53 -80 26 89 4 -88 -34 77

60 -56 -78 30 88 } { 82 42 -77 -53 68 63 -60 -72 50 78 -38 -84 26 88 -13 -90 } },

(267) By constructing a transform matrix for generating an output vector including 16 sample values for an input vector including 32 residual signal samples (upon forward transform) as in Tables 11 and 12 or Tables 13 and 14 and performing an inverse transform that outputs an output vector including 32 residual signal samples for an input vector including 16 values using the matrices of Tables 11 and 12 or Tables 13 and 14 and using the indexing for an inverse transform (upon inverse transform), computational complexity and memory usage can be reduced. For example, when a  $16 \times 32$  matrix derived by concatenating Tables 11 and 12 (or Tables 13 and 14) in the horizontal direction is left as a forward transform matrix, a matrix derived by transposing the forward transform matrix is an inverse transform matrix, and therefore the decoding apparatus **200** may perform an inverse transform through the indexing corresponding to a transpose operation on each component of the forward transform matrix.

(268) Another embodiment of the present disclosure provides a method for residual coding for RMTS32. In the present embodiment, coefficients may be scanned only in an area in which non-zero coefficients may be present. In other words, a zero-out area is not scanned and may be considered to be filled with values of 0. In the zero-out case of the RMTS32, a scanned area may be a  $16 \times 16$  top left area, and the same scan order as  $16 \times 16$  TU may be applied to the  $16 \times 16$  top left area. Furthermore, truncated unary binarization at the last coefficient position may be adjusted by considering a maximum possible position.

(269) Although some of the above-described embodiments of the present disclosure are described as separate embodiments, the present disclosure is not limited thereto. That is, the above-described embodiments may be independently performed or one or more embodiments may be performed in a combined manner.

(270) An embodiment which will be described below provides a method for partitioning a block into sub-blocks and applying a transform to the partitioned sub-blocks. A transform technique applied to each sub-block partitioned from a block corresponding to a transform unit may be called a sub-block transform (SBT).

(271) RMTS32 proposed above may be applied to all cases in which 32-point DST-7 or 32-point DCT-8 is applied as well as cases in which MTS is applied. For example, a transform may be applied as illustrated in FIG. **13a** to FIG. **18d**.

(272) Although DST-7 or DCT-8 may be applied to components of each sub-block as illustrated in FIG. **13a** to FIG. **18d**, a transform pair applied in the horizontal direction and the vertical direction is not limited to example of FIG. **13a** to FIG. **18d** and various transform pairs may be applied. For example, a transform pair applied to each sub-block may be indicated by an index (e.g., MTS index) or may be implicitly determined according to a block partitioned form and the position of a sub-block to which a transform is applied.

(273) In FIG. **13a** to FIG. **18d**, the width and the height of a block (e.g., coding unit) are represented by  $w$  and  $h$ . When the width and the height of a sub-block to which a separable transform is actually applied are represented as a pair of (width, height), the transform may be applied to sub-blocks having sizes of  $(w_1, h)$ ,  $(w-w_1, h)$ ,  $(w, h_1)$ , and  $(w, h-h_1)$ . Here,  $w_1$  may be  $\frac{1}{4}$ ,  $\frac{1}{2}$ ,  $\frac{3}{4}$ , or  $p/m$  width  $w$ , and  $h_1$  may be  $\frac{1}{4}$ ,  $\frac{1}{2}$ ,  $\frac{3}{4}$ , or  $q/n$  height  $h$ .

(274) A sub-block to which the transform is applied may be positioned on the left or right of a block when the block is partitioned in the vertical direction as illustrated in FIGS. **13a**, **13b**, **15a**, and **15b** and may be positioned on the top or bottom of the block as illustrated in FIGS. **14a**, **14b**, **16a**, and **16b**. The sub-block transform may be applied to a residual signal of a block to which an inter-prediction is applied, as illustrated in FIG. **13a** to FIG. **18d**.

(275) A flag (sub-block transform (SBT) flag) for indicating whether a block including a corresponding residual signal is partitioned and a transform is applied to one sub-block may be signaled. When the SBT flag is 1, the block is partitioned into a plurality of sub-blocks and a transform is performed. When the SBT flag is 0, the block is not additionally partitioned. In the

present specification, SBT represents a method of applying a transform to only one of sub-blocks (transform units) partitioned from a coding unit.

(276) When the SBT flag is 1, a flag (SBT horizontal flag) indicating a partitioning direction (vertical direction or horizontal direction) of the block may be signaled. Here, when the SBT horizontal flag is 0, the block may be partitioned in the vertical direction as illustrated in FIG. **13a** or **13b**. When the SBT horizontal flag is 1, the block may be partitioned in the horizontal direction as illustrated in FIG. **14a** or **14b**.

(277) In addition, when the SBT flag is 1, a flag (SBT position flag) indicating the position of a sub-block to which a transform is actually applied among sub-blocks partitioned from the horizontal block may be signaled. For example, a transform may be applied to a first sub-block (left or upper sub-block) when the SBT position flag is 0 and the transform may be applied to a second sub-block (right or lower sub-block) when the SBT position flag is 1.

(278) Furthermore, a block may be partitioned based on  $\frac{1}{2}$  or  $\frac{1}{4}$  the width (w) or the height (h) thereof, and a flag (SBT quad flag) indicating a point at the width or the height may be signaled. The block may be partitioned based on  $\frac{1}{2}$  the width or the height thereof as illustrated in FIG. **13a**, **13b**, **14a**, or **14b** when the SBT quad block flag is 0 and may be partitioned based on  $\frac{1}{4}$  the width or the height thereof as illustrated in FIG. **15a**, **15b**, **16a**, or **16b** when the SBT quad block flag is 1.

(279) FIGS. **13a** and **13b** illustrate an example of a transform for subblocks of a block, to which a symmetric vertical partitioning is applied, according to an embodiment of the present disclosure. When the flag (SBT horizontal flag) indicating a partitioning direction of a block **1310** is 0, the block may be partitioned in the vertical direction as illustrated in FIGS. **13a** and **13b**. When the flag (SBT horizontal flag) indicating a partitioning direction of a block **1310** is 0, the block (e.g., coding unit) **1310** is partitioned into a first sub-block **1320** positioned on the left and a second sub-block **1330** positioned on the right based on the vertical boundary, as illustrated in FIGS. **13a** and **13b**. In the FIGS. **13a** and **13b**, the block **1310** may be partitioned into the first sub-block **1320** and the second sub-block **1330** based on  $\frac{1}{2}$  the width of the block ( $w_1 = \frac{1}{2} * w$ ) when the width of the block **1510** is w.

(280) When the block **1310** is partitioned as illustrated in FIGS. **13a** and **13b**, a sub-block to which a transform is applied between the sub-blocks **1320** and **1330** may be determined based on the flag (SBT position flag) indicating a sub-block to which a transform is applied. A transform may be applied to the first sub-block **1320** positioned on the left, as illustrated in FIG. **13a**, when the SBT position flag is 0 and the transform may be applied to the second sub-block **1330** positioned on the right, as illustrated in FIG. **13b**, when the SBT position flag is 1.

(281) FIGS. **14a** and **14b** illustrate an example of a transform for subblocks of a block, to which a symmetric horizontal partitioning is applied, according to an embodiment of the present disclosure. When the flag (SBT horizontal flag) indicating a partitioning direction of a block **1410** is 1, the block **1410** may be partitioned in the horizontal direction as illustrated in FIGS. **14a** and **14b**. The block (e.g., coding unit) **1410** is partitioned into a first sub-block **1420** positioned in the upper part and a second sub-block **1430** positioned in the lower part based on the horizontal boundary, as illustrated in FIGS. **14a** and **14b**. When the flag (SBT horizontal flag) indicating a partitioning direction of the block **1410** is 1, the block **1410** may be partitioned into the first sub-block **1420** and the second sub-block **1430** based on  $\frac{1}{2}$  the height of the block **1410** ( $h_1 = \frac{1}{2} * h$ ) when the height of the block **1510** is h, as illustrated in FIGS. **14a** and **14b**.

(282) When the block **1410** is partitioned as illustrated in FIGS. **14a** and **14b**, a sub-block to which a transform is applied between the sub-blocks **1420** and **1430** may be determined based on the flag (SBT position flag) indicating a sub-block to which a transform is applied. A transform may be applied to the first sub-block **1420** positioned in the upper part, as illustrated in FIG. **14a**, when the SBT position flag is 0 and the transform may be applied to the second sub-block **1430** positioned in the lower part, as illustrated in FIG. **14b**, when the SBT position flag is 1.

(283) FIGS. **15a** and **15b** illustrate an example of a transform for subblocks of a block, to which an

asymmetric vertical partitioning is applied, according to an embodiment of the present disclosure. When the flag (SBT horizontal flag) indicating a partitioning direction of a block **1510** is 0, the block **1510** may be partitioned in the vertical direction as illustrated in FIGS. **15a** and **15b**. The block (e.g., coding unit) **1510** is partitioned into a left sub-block and a right sub-block based on the vertical boundary, as illustrated in FIGS. **15a** and **15b**. The block **1510** may be partitioned based on  $\frac{1}{4}$  the width of the block **1510** ( $w_1 = \frac{1}{4} * w$ ) and a transform may be applied to the first sub-block **1520** corresponding to the left region corresponding to  $\frac{1}{4}$  the width when the width of the block **1510** is  $w$ , as illustrated in FIG. **15a**, or the block **1510** may be partitioned based on  $\frac{3}{4}$  the width of the block **1510** ( $w_1 = \frac{3}{4} * w$ ) and a transform may be applied to the second sub-block **1530** corresponding to the right region corresponding to  $\frac{1}{4}$  the width when the width of the block **1510** is  $w$ , as illustrated in FIG. **15b**.

(284) When the block **1510** is partitioned as illustrated in FIGS. **15a** and **15b**, a sub-block to which a transform is applied between the sub-blocks **1520** and **1530** may be determined based on the flag (SBT position flag) indicating a sub-block to which a transform is applied. A transform may be applied to the first sub-block **1520** corresponding to the  $\frac{1}{4}$  left region, as illustrated in FIG. **15a**, when the SBT position flag is 0 and the transform may be applied to the second sub-block **1530** corresponding to the  $\frac{1}{4}$  right region, as illustrated in FIG. **15b**, when the SBT position flag is 1.

(285) FIGS. **16a** and **16b** illustrate an example of a transform for subblocks of a block, to which an asymmetric horizontal partitioning is applied, according to an embodiment of the present disclosure. When the flag (SBT horizontal flag) indicating a partitioning direction of a block **1610** is 1, the block **1610** may be partitioned in the horizontal direction as illustrated in FIGS. **16a** and **16b**. The block (e.g., coding unit) **1610** may be partitioned into an upper sub-block and a lower sub-block based on the horizontal boundary, as illustrated in FIGS. **16a** and **16b**. The block **1610** may be partitioned based on  $\frac{1}{4}$  the height of the block **1610** ( $h_1 = \frac{1}{4} * h$ ) and a transform may be applied to the first sub-block **1620** corresponding to the  $\frac{1}{4}$  upper region when the height of the block **1610** is  $h$ , as illustrated in FIG. **16a**, or the block **1610** may be partitioned based on  $\frac{3}{4}$  the height of the block **1610** ( $h_1 = \frac{3}{4} * h$ ) and a transform may be applied to the second sub-block **1630** corresponding to the  $\frac{1}{4}$  lower region when the height of the block **1610** is  $h$ , as illustrated in FIG. **16b**.

(286) When the block **1610** is partitioned as illustrated in FIGS. **16a** and **16b**, a sub-block to which a transform is applied between the sub-blocks **1620** and **1630** may be determined based on the flag (SBT position flag) indicating a sub-block to which a transform is applied. A transform may be applied to the first sub-block **1620** corresponding to the  $\frac{1}{4}$  upper region, as illustrated in FIG. **16a**, when the SBT position flag is 0 and the transform may be applied to the second sub-block **1630** corresponding to the  $\frac{1}{4}$  lower region, as illustrated in FIG. **16b**, when the SBT position flag is 1.

(287) When a horizontal transform and a vertical transform are determined for a specific block (without designating a horizontal transform and a vertical transform through MTS signaling) as illustrated in FIGS. **13a** to **18d**, the above-described RMTS32 may be applied if the width or the height of the block is **32**. When SBT is applied as illustrated in FIGS. **13a** to **18d**, DST-7 or DCT-8 may be used as a transform kernel for the horizontal transform and the vertical transform. When RMTS32 is applied, residual coding may be omitted for a region to which zero-out is applied. Alternatively, scanning and residual coding may be applied to only a region to which zero-out is not applied. Sub-blocks according to symmetric partitioning for a residual block may have (width, height) of ( $w/2$ ,  $h$ ) or ( $w$ ,  $h/2$ ), as illustrated in FIGS. **17a** to **17d**, and zero-out may be applied to a sub-block having a side of a reference length (e.g., **32**) or longer. Further, sub-blocks according to asymmetric partitioning for a residual block may have (width, height) of ( $w/4$ ,  $h$ ) or ( $w$ ,  $h/4$ ), as illustrated in FIGS. **18a** to **18d**, and zero-out may be applied to a sub-block having a side of a reference length (e.g., **16**) or longer.

(288) When a block is symmetrically partitioned and the width  $w$  or the height  $h$  thereof is equal to or greater than a predefined first length (e.g., **32**) in FIGS. **17a** to **17d**, the width nonZeroW or the

height nonZeroH of a transform target region is reduced to a second length (e.g., 16) less than the first length. For example, when a block **1710** is partitioned into a left sub-block and a right sub-block based on the vertical boundary, an upper region **1720** of the left sub-block may be determined as a transform target region, as illustrated in FIG. **17a**, or an upper region **1730** of the right sub-block may be determined as a transform target region, as illustrated in FIG. **17b**. Furthermore, when a block **1710** is partitioned into an upper sub-block and a lower sub-block based on the horizontal boundary, a left region **1740** of the upper sub-block may be determined as a transform target region, as illustrated in FIG. **17c**, or a left region **1750** of the lower sub-block may be determined as a transform target region, as illustrated in FIG. **17d**. In the present specification, a transform target region is a region in which a non-zero transform coefficient may be present when a decoder performs an (inverse) transform and may be substituted with an inverse transform target region.

(289) When a block is partitioned at a point corresponding to  $\frac{1}{4}$  or  $\frac{3}{4}$  the width  $w$  therein in the vertical direction, as illustrated in FIGS. **15a** and **15b**, and the width  $w$  or the height  $h$  thereof is equal to or greater than the predefined first length (e.g., 32) in FIGS. **18a** to **18d**, the width nonZeroW or the height nonZeroH of a transform target region is reduced to the second length (e.g., 16) less than the first length. For example, an upper region **1820** of the  $\frac{1}{4}$  left region may be determined as a transform target region, as illustrated in FIG. **18a**, when a block **1810** is partitioned based on  $\frac{1}{4}$  the width  $w$  ( $w_1 = \frac{1}{4} * w$ ) and an upper region **1830** of the  $\frac{1}{4}$  right region may be determined as a transform target region, as illustrated in FIG. **18b**, when the block **1810** is partitioned based on  $\frac{3}{4}$  the width  $w$  ( $w_1 = \frac{3}{4} * w$ ). Furthermore, a left region **1840** of the  $\frac{1}{4}$  upper region may be determined as a transform target region, as illustrated in FIG. **18c**, when the block **1810** is partitioned based on  $\frac{1}{4}$  the height  $h$  thereof ( $h_1 = \frac{1}{4} * h$ ) and a left region **1850** of the  $\frac{1}{4}$  lower region may be determined as a transform target region, as illustrated in FIG. **18d**, when the block **1810** is partitioned based on  $\frac{3}{4}$  the height  $h$  thereof ( $h_1 = \frac{3}{4} * h$ ). Although FIG. **17a** to FIG. **18d** show that (inverse) transform is applied to a region (a region where a non-zero transform coefficient may be present) reduced according to zero-out based on the decoder, transform may be applied to an entire region (a region to which SBT is applied) where residual samples are present before zero-out, as shown in FIG. **13a** to FIG. **16b**, based on the encoder.

(290) The following embodiment provides a more specific method for realizing partitioning and transform per sub-block.

(291) A residual signal block may be partitioned into a plurality of sub-blocks by applying SBT and a transform (horizontal transform and vertical transform) may be applied to one of the partitioned sub-blocks. DCT-2 may be applied in both the horizontal and vertical direction if any of the width and the height of a sub-block to which the transform is applied is equal to or greater than a reference value (e.g., 64) and DCT-8 may be applied if not. For example, a transform combination applied to a sub-block to which a transform is applied may be determined based on a partitioning direction and the position of the sub-block to which the transform is applied as shown in Table 22 below. Accordingly, when SBT is applied, the aforementioned reduced transform RMTS32 may be applied to perform zero-out if both the width and the height of a sub-block to which a transform is applied is the reference value (e.g., 32) or less.

(292) That is, in the case of forward transform, the encoding apparatus **100** may apply length-M DST-7 or DCT-8 to  $M$  (e.g., 32) residual samples arranged in the row or column direction and output  $R$  (e.g., 16) ( $R < M$ ) transform coefficients. On the other hand, in the case of reverse transform, the decoding **200** may apply reverse transform to only  $R$  transform coefficients corresponding to some of  $M$  transform coefficients arranged in the row or column direction and regard the remaining transform coefficients as 0.

(293) A partitioning form of a transform unit to which SBT is applied may be determined by the following four syntax elements.

(294) An SBT flag `cu_sbt_flag` indicates whether a current CU is partitioned into a plurality of sub-

blocks (whether SBT is applied to a CU). For example, SBT is not applied to the current CU if the SBT flag `cu_sbt_flag` is 0 and SBT is applied to the current CU if the SBT flag `cu_sbt_flag` is 1. (295) An SBT size flag `cu_sbt_quad_flag` is parsed when SBT is applied and indicates the size of each sub-block. For example, a sub-block partitioned from a CU is  $\frac{1}{2}$  the size of the current CU if the SBT size flag `cu_sbt_quad_flag` is 0 and is  $\frac{1}{4}$  the size of the current CU if the SBT size flag `cu_sbt_quad_flag` is 1. In other words, the CU is partitioned based on  $\frac{1}{2}$  the width or the height of the current CU, as illustrated in FIGS. **13a** to **14b**, if the SBT size flag `cu_sbt_quad_flag` is 0 and is partitioned based on  $\frac{1}{4}$  or  $\frac{3}{4}$  the width or the height of the current CU, as illustrated in FIGS. **15a** to **16b**, if the SBT size flag `cu_sbt_quad_flag` is 1.

(296) An SBT direction flag `cu_sbt_horizontal_flag` is parsed when SBT is applied and indicates a partitioning direction of the current CU. Here, the partitioning direction may include the vertical direction and the horizontal direction. For example, the current CU is partitioned in the vertical direction, as illustrated in FIGS. **13a** and **13b** or FIGS. **15a** and **15b**, if the SBT direction flag `cu_sbt_horizontal_flag` is 0 and is partitioned in the horizontal direction, as illustrated in FIGS. **14a** and **14b** or FIGS. **16a** and **16b**, if the SBT direction flag `cu_sbt_horizontal_flag` is 1.

(297) An SBT position flag `cu_sbt_pos_flag` indicates a sub-block having CBF indicating whether a valid transform coefficient is present in sub-blocks partitioned from the current CU based on the SBT size flag `cu_sbt_quad_flag` and the SBT direction flag `cu_sbt_horizontal_flag`. That is, the SBT position flag `cu_sbt_pos_flag` indicates a sub-block (transform unit) that may include a non-zero transform coefficient in the current CU. For example, the current CU is partitioned based on  $\frac{1}{2}$  the width thereof in the vertical direction, as illustrated in FIGS. **13a** and **13b**, if the SBT size flag `cu_sbt_quad_flag` is 0 and the SBT direction flag `cu_sbt_horizontal_flag` is 0, the transform is applied to the left sub-block **1320** if the SBT position flag `cu_sbt_pos_flag` is 0, and the transform is applied to the right sub-block **1330** if the SBT position flag `cu_sbt_pos_flag` is 1. The current CU is partitioned based on  $\frac{1}{2}$  the height thereof in the horizontal direction, as illustrated in FIGS. **14a** and **14b**, if the SBT size flag `cu_sbt_quad_flag` is 0 and the SBT direction flag `cu_sbt_horizontal_flag` is 1, the transform is applied to the upper sub-block **1420** if the SBT position flag `cu_sbt_pos_flag` is 0, and the transform is applied to the lower sub-block **1430** if the SBT position flag `cu_sbt_pos_flag` is 1. The current CU is partitioned based on  $\frac{1}{4}$  the width thereof in the vertical direction, as illustrated in FIGS. **15a** and **15b**, if the SBT size flag `cu_sbt_quad_flag` is 1 and the SBT direction flag `cu_sbt_horizontal_flag` is 0, the transform is applied to the left sub-block **1520** if the SBT position flag `cu_sbt_pos_flag` is 0, and the transform is applied to the right sub-block **1530** if the SBT position flag `cu_sbt_pos_flag` is 1. The current CU is partitioned based on  $\frac{1}{4}$  the height thereof in the horizontal direction, as illustrated in FIGS. **16a** and **16b**, if the SBT size flag `cu_sbt_quad_flag` is 1 and the SBT direction flag `cu_sbt_horizontal_flag` is 1, the transform is applied to the upper sub-block **1620** if the SBT position flag `cu_sbt_pos_flag` is 0, and the transform is applied to the lower sub-block **1630** if the SBT position flag `cu_sbt_pos_flag` is 1. (298) According to embodiments of the present disclosure, when a reduced transform is used, the width and the height of a transform unit are not used, and the original width and the height of a region that does not zero out (a region where non-zero transform coefficients may present) may be regarded as (changed to) the width and height of the transform unit and coding may be performed thereon. For example, if the original width and height of a transform unit are  $32 \times 16$ , non-zero transform coefficients are present only in a top left  $16 \times 16$  region due to zero-out when the reduced transform is applied. Accordingly, the width and the height of the transform unit may be set to 16 and 16 and coding may be performed on syntax elements (e.g., `last_sig_coeff_x_prefix` and `last_sig_coeff_y_prefix`). In Table 20 which will be described later, the decoding apparatus **200** may change the width and the height of a transform unit by changing size variables `log2TbWidth` and `log2TbHeight` of the transform unit before position information of the last significant coefficient, `last_sig_coeff_x_prefix` and `last_sig_coeff_y_prefix`, is coded and code subsequent syntax elements according to the changed values. Further, parameters `cMax` of `last_sig_coeff_x_prefix` and `last`

sig\_coeff\_y\_prefix are set in consideration of the changed size variables log 2TbWidth and log 2TbWidth as shown in Table 28. Consequently, the decoding apparatus **200** may set a region where non-zero transform coefficients are present (a region other than a zero-out region) as a new transform unit at the time of residual coding.

(299) Syntax structures for realizing an embodiment of the present disclosure may be configured as shown in Table 15 to Table 19 below. Each syntax is merely an example and may be modified in various manners. Further, syntax elements less related to the embodiment of the present disclosure are omitted for simplification of description.

(300) Table 15 shows an example of a sequence parameter set raw byte sequence payload (RBSP) syntax seq\_parameter\_set\_rbsp according to an embodiment of the present disclosure.

(301) TABLE-US-00015 TABLE 15 Descriptor seq\_parameter\_set\_rbsp( ) { . . . u(1)  
sps\_mts\_enabled\_flag u(1) if( sps\_mts\_enabled\_flag ) { sps\_explicit\_mts\_intra\_enabled\_flag u(1)  
sps\_explicit\_mts\_inter\_enabled\_flag u(1) } sps\_sbt\_enabled\_flag u(1) if( sps\_sbt\_enabled\_flag )  
sps\_sbt\_max\_size\_64\_flag u(1) . . . }

(302) In Table 15, sps\_mts\_enabled\_flag indicates whether the sequence set RBSP syntax includes sps\_explicit\_mts\_intra\_enabled\_flag and sps\_explicit\_mts\_inter\_enabled\_flag. For example, the sequence parameter set RBSP syntax includes sps\_explicit\_mts\_intra\_enabled\_flag and sps\_explicit\_mts\_inter\_enabled\_flag if sps\_mts\_enabled\_flag is 1 and the sequence parameter set RBSP syntax does not include sps\_explicit\_mts\_intra\_enabled\_flag and sps\_explicit\_mts\_inter\_enabled\_flag if sps\_mts\_enabled\_flag is 0.

(303) sps\_explicit\_mts\_intra\_enabled\_flag indicates whether a transform unit syntax for intra coding units includes tu\_mts\_idx. For example, the transform unit syntax for intra coding units includes tu\_mts\_idx if sps\_explicit\_mts\_intra\_enabled\_flag is 1 and the transform unit syntax for intra coding units does not include tu\_mts\_idx if sps\_explicit\_mts\_intra\_enabled\_flag is 0. If sps\_explicit\_mts\_intra\_enabled\_flag is not included, sps\_explicit\_mts\_intra\_enabled\_flag is inferred as 0.

(304) sps\_explicit\_mts\_inter\_enabled\_flag indicates whether a transform unit syntax for intra coding units includes tu\_mts\_idx. For example, the transform unit syntax for intra coding units includes tu\_mts\_idx if sps\_explicit\_mts\_inter\_enabled\_flag is 1 and the transform unit syntax for intra coding units does not include tu\_mts\_idx if sps\_explicit\_mts\_inter\_enabled\_flag is 0. If sps\_explicit\_mts\_inter\_enabled\_flag is not included, sps\_explicit\_mts\_inter\_enabled\_flag is inferred as 0.

(305) sps\_sbt\_enabled\_flag indicates whether sub-block transform (SBT) is applicable to inter-predicted CUs. For example, SBT is disabled for inter-predicted CUs if sps\_sbt\_enabled\_flag is 0 and SBT is enabled for the inter-predicted CUs if sps\_sbt\_enabled\_flag is 1.

(306) sps\_sbt\_max\_size\_64\_flag indicates a maximum CU width and height that allow SBT. For example, the maximum CU width and height that allow SBT are 32 luma samples if sps\_sbt\_max\_size\_64\_flag is 0 and the maximum CU width and height that allow SBT are 64 luma samples if sps\_sbt\_max\_size\_64\_flag is 1. A maximum size MaxSbtSize that allows SBT may be determined based on sps\_sbt\_max\_size\_64\_flag as follows.

MaxSbtSize=sps\_sbt\_max\_size\_64\_flag?64:32

(307) Table 16 shows an example of a picture parameter set RBSP syntax pic\_parameter\_set\_rbsp according to an embodiment of the present disclosure.

(308) TABLE-US-00016 TABLE 16 Descriptor pic\_parameter\_set\_rbsp( ) { . . . se(v)  
transform\_skip\_enabled\_flag u(1) if( transform\_skip\_enabled\_flag )  
log2\_transform\_skip\_max\_size\_minus2 ue(v) . . . }

(309) In Table 16, transform\_skip\_enabled\_flag indicates whether the transform unit syntax can include transform\_skip\_flag. For example, the transform unit syntax includes transform\_skip\_flag if transform\_skip\_enabled\_flag is 1 and the transform unit syntax does not include transform\_skip\_flag if transform\_skip\_enabled\_flag is 0.

(310)  $\log 2\_transform\_skip\_max\_size\_minus2$  indicates a maximum block size for which transform skip is used and may have a value in the range of 0 to 3. If  $\log 2\_transform\_skip\_max\_size\_minus2$  is not present,  $\log 2\_transform\_skip\_max\_size\_minus2$  is inferred as 0. A variable  $MaxTsSize$  indicating the maximum block size for which transform skip can be applied may be set to  $1 \ll (\log 2\_transform\_skip\_max\_size\_minus2 + 2)$ .

(311) Table 17 shows an example of a coding unit syntax `coding_unit` according to an embodiment of the present disclosure.

(312) TABLE-US-00017 TABLE 17 Descriptor `coding_unit( x0, y0, cbWidth, cbHeight, treeType )`  

```

{ ... if( !pcm_flag[ x0 ][ y0 ] ) { if( CuPredMode[ x0 ][ y0 ] != MODE_INTRA && cu_skip_flag[ x0 ][ y0 ] == 0 ) cu_cbf ae(v) if( cu_cbf ) { if( CuPredMode[ x0 ][ y0 ] != MODE_INTRA && sps_sbt_enabled_flag && !ciip_flag[ x0 ][ y0 ] ) { if( cbWidth <= MaxSbtSize && cbHeight <= MaxSbtSize ) { allowSbtVerH = cbWidth >= 8 allowSbtVerQ = cbWidth >= 16 allowSbtHorH = cbHeight >= 8 allowSbtHorQ = cbHeight >= 16 if( allowSbtVerH || allowSbtHorH || allowSbtVerQ || allowSbtHorQ ) cu_sbt_flag ae(v) } if( cu_sbt_flag ) { if( ( allowSbtVerH || allowSbtHorH ) && ( allowSbtVerQ || allowSbtHorQ ) ) cu_sbt_quad_flag ae(v) if( ( cu_sbt_quad_flag && allowSbtVerQ && allowSbtHorQ ) || ( !cu_sbt_quad_flag && allowSbtVerH && allowSbtHorH ) ) cu_sbt_horizontal_flag ae(v) cu_sbt_pos_flag ae(v) } } transform_tree( x0, y0, cbWidth, cbHeight, treeType ) } } }

```

(313) In Table 17, `cu_sbt_flag` indicates whether SBT is used for the current coding unit. For example, SBT is used for the current coding unit if `cu_sbt_flag` is 1 and SBT is not used for the current coding unit if `cu_sbt_flag` is 0. When SBT is used, a coding unit is partitioned into two transform units, one transform unit includes residual data, and the other transform unit does not include residual data.

(314) `cu_sbt_quad_flag` indicates the size of a sub-block partitioned from the current coding unit. For example, a sub-block includes a transform unit that is  $\frac{1}{4}$  the size of the current coding unit for the current coding unit if `cu_sbt_quad_flag` is 1 and the sub-block includes a transform unit that is  $\frac{1}{2}$  the size of the current coding unit for the current coding unit if `cu_sbt_quad_flag` is 0. If `cu_sbt_quad_flag` is not present, the value thereof is inferred as 0.

(315) `cu_sbt_horizontal_flag` indicates a partitioning direction of the current coding unit. For example, the current coding unit is horizontally partitioned into two transform units if `cu_sbt_horizontal_flag` is 1 and the current coding unit is vertically partitioned into two transform units if `cu_sbt_horizontal_flag` is 0.

(316) If `cu_sbt_horizontal_flag` is not present, the value thereof may be derived as follows. If `cu_sbt_quad_flag` is 1, `cu_sbt_horizontal_flag` is set to be the same as `allowSbtHorQ`. If not (if `cu_sbt_quad_flag` is 0), `cu_sbt_horizontal_flag` is set to be the same as `allowSbtHorH`.

(317) `cu_sbt_pos_flag` indicates the position of a transform unit in which CBF flag `tu_cbf_luma`, `tu_cbf_cb`, and `tu_cbf_cr` is present in the current coding unit. For example, CBF flag `tu_cbf_luma`, `tu_cbf_cb`, and `tu_cbf_cr` of a first transform unit is not present in the current coding unit if `cu_sbt_pos_flag` is 1 and CBF flag `tu_cbf_luma`, `tu_cbf_cb`, and `tu_cbf_cr` of a second transform unit is not present in the current coding unit if `cu_sbt_pos_flag` is 0. A variable `SbtNumFourthsTb0` may be derived as follows.

$sbtMinNumFourths = cu\_sbt\_quad\_flag ? 1 : 2$   
 $SbtNumFourthsTb0 = cu\_sbt\_pos\_flag ? (4 - sbtMinNumFourths) : sbtMinNumFourths$

(318) FIG. 19 is a flowchart of a process for decoding a coding unit based on a coding unit syntax according to an embodiment of the present disclosure. The flowchart of FIG. 19 schematically illustrates the operation of the decoding apparatus 200 according to Table 17.

(319) The decoding apparatus 200 checks whether the current CU includes a non-zero transform coefficient (whether `CU_CBF` is 1) (S1905). If `CU_CBF` is 1, the decoding apparatus 200 checks i) whether a prediction mode of the current CU is not the intra-prediction mode (`CuPredMode != MODE_INTRA`) (or the prediction mode of the current CU is the inter-prediction mode

(CuPredMode=MODE\_INTER)), ii) whether SBT is enabled for the current CU (sps\_sbt\_enabled\_flag), and iii) whether prediction according to a combination of inter-prediction and intra-prediction is not applied (!ciip\_flag) in step **S1910**. If the conditions of step **S1910** are satisfied, the decoding apparatus **200** checks whether the width and the height of the current coding unit are equal to or less than a maximum SBT size in step **S1915**.

(320) If the condition of step **S1915** is satisfied, values of variables allowSbtVerH, allowSbtVerQ, allowSbtHorH, and allowSbtHorQ for determining whether to allow SBT are determined based on the width and the height of the current coding unit in step **S1920**. allowSbtVerH is determined to be 1 if the width cbWidth of the current coding unit is equal to or greater than 8 (0 if not), allowSbtVerQ is determined to be 1 if the width cbWidth of the current coding unit is equal to or greater than 16 (0 if not), allowSbtHorH is determined to be 1 if the height cbHeight of the current coding unit is equal to or greater than 8 (0 if not), and allowSbtHorQ is determined to be 1 if the height cbHeight of the current coding unit is equal to or greater than 16 (0 if not). Thereafter, it is determined whether at least one of i) allowSbtVerH, allowSbtHorH, allowSbtVerQ, and allowSbtHorQ is 1 in step **S1925**. If the condition of step **S1925** is satisfied, the decoding apparatus **200** parses cu\_sbt flag (**S1930**) and checks whether cu\_sbt\_flag is 1 (i.e., whether SBT is applied to the current coding unit) (**S1935**).

(321) If cu\_sbt\_flag is 1, the decoding apparatus **200** determines i) whether allowSbtVerH or allowSbtHorH is 1 and ii) allowSbtVerQ or allowSbtHorQ is 1 in step **S1940**. If the conditions of step **S1940** are satisfied, the decoding apparatus **200** parses cu\_sbt\_quad\_flag (**S1945**). The decoding apparatus **200** checks i) whether cu\_sbt\_quad\_flag is 1 (CU is partitioned into  $\frac{1}{4}$  size) and allowSbtVerQ and allowSbtHorQ are 1 or ii) whether cu\_sbt\_quad\_flag is 0 (CU is partitioned into  $\frac{1}{2}$  size) and allowSbtVerH and allowSbtHorH is 1 in step **S1950**. If the conditions of step **S1950** are satisfied, the decoding apparatus **200** parses cu\_sbt\_horizontal\_flag (**S1955**). Thereafter, the decoding apparatus **200** parses cu\_sbt\_pos\_flag (irrespective of the conditions of **S1950**) (**S1960**). Thereafter, the decoding apparatus **200** calls a transform tree syntax (**S1965**). When the transform tree syntax is called, the width cbWidth and the height cbHeight of the current coding unit are input as the width tbWidth and the height tbHeight of a transform unit.

(322) Table 18 shows an example of the transform tree syntax transform\_tree according to an embodiment of the present disclosure.

(323) TABLE-US-00018 TABLE 18 Descriptor transform\_tree( x0, y0, tbWidth, tbHeight, treeType ) { InferTuCbfLuma = 1 if( IntraSubPartSplitType == NO\_ISP\_SPLIT ) { if( tbWidth > MaxTbSizeY || tbHeight > MaxTbSizeY ) { trafoWidth = ( tbWidth > MaxTbSizeY ) ? (tbWidth / 2) : tbWidth trafoHeight = ( tbHeight > MaxTbSizeY ) ? (tbHeight / 2) : tbHeight transform\_tree( x0, y0, trafoWidth, trafoHeight ) if( tbWidth > MaxTbSizeY ) transform\_tree( x0 + trafoWidth, y0, trafoWidth, trafoHeight, treeType ) if( tbHeight > MaxTbSizeY ) transform\_tree( x0, y0 + trafoHeight, trafoWidth, trafoHeight, treeType ) if( tbWidth > MaxTbSizeY && tbHeight > MaxTbSizeY ) transform\_tree( x0 + trafoWidth, y0 + trafoHeight, trafoWidth, trafoHeight, treeType ) } else { transform\_unit( x0, y0, tbWidth, tbHeight, treeType, 0 ) } } else if( cu\_sbt\_flag ) { if( !cu\_sbt\_horizontal\_flag ) { trafoWidth = tbWidth \* SbtNumFourthsTb0 / 4 transform\_unit( x0, y0, trafoWidth, tbHeight, treeType , 0 ) transform\_unit( x0 + trafoWidth, y0, tbWidth - trafoWidth , tbHeight, treeType , 1 ) } else { trafoHeight = tbHeight \* SbtNumFourthsTb0 / 4 transform\_unit( x0, y0, tbWidth, trafoHeight, treeType , 0 ) transform\_unit( x0, y0 + trafoHeight, tbWidth, tbHeight - trafoHeight, treeType , 1 ) } } else if( IntraSubPartitionsSplitType == ISP\_HOR\_SPLIT ) { trafoHeight = tbHeight / NumIntraSubPartitions for( partIdx = 0; partIdx < NumIntraSubPartitions; partIdx++ ) transform\_unit( x0, y0 + trafoHeight \* partIdx, tbWidth, trafoHeight, treeType, partIdx ) } else if( IntraSubPartitionsSplitType == ISP\_VER\_SPLIT ) { trafoWidth = tbWidth / NumIntraSubPartitions for( partIdx = 0; partIdx < NumIntraSubPartitions; partIdx++ ) transform\_unit( x0 + trafoWidth \* partIdx, y0, trafoWidth, tbHeight, treeType, partIdx ) } }

(324) FIG. 20 is a flowchart of a process for decoding the transform tree syntax based on the coding unit syntax according to an embodiment of the present disclosure. The flowchart of FIG. 20 schematically illustrates the operation of the decoding apparatus 200 according to Table 18.

(325) In step S2005, the decoding apparatus 200 checks whether cu\_sbt\_flag is 1 (whether SBT is applied to the current coding unit). If cu\_sbt\_flag is 1, the decoding apparatus 200 checks whether cu\_sbt\_horizontal\_flag is 0 in step S2010. If cu\_sbt\_horizontal\_flag is 0 (if the current coding unit is vertically partitioned), the decoding apparatus 200 determines a variable trafoWidth to be  $tbWidth * SbtNumFourthsTb0/4$  in step S2015. Thereafter, the decoding apparatus 200 calls a transform unit syntax for a first sub-block and calls a transform unit syntax for a second sub-block.

(326) If cu\_sbt\_horizontal\_flag is 1 (if the current coding unit is horizontally partitioned), the decoding apparatus 200 determines a variable trafoHeight to be  $tbHeight * SbtNumFourthsTb0/4$  in step S2020. Thereafter, the decoding apparatus 200 calls the transform unit syntax for the first sub-block and calls the transform unit syntax for the second sub-block.

(327) Table 19 shows an example of a transform unit syntax according to an embodiment of the present disclosure.

(328) TABLE-US-00019 TABLE 19 Descriptor transform \_unit( x0, y0, tbWidth, tbHeight, treeType, subTuIndex ) { if( treeType == SINGLE\_TREE || treeType == DUAL\_TREE\_LUMA ) { if( ( IntraSubPartitionsSplitType == ISP\_NO\_SPLIT && !( cu\_sbt\_flag && ( subTuIndex == 0 && cu\_sbt\_horizontal\_flag ) ) || ( subTuIndex == 1 && !cu\_sbt\_horizontal\_flag ) ) ) || ( IntraSubPartitionsSplitType != ISP\_NO\_SPLIT && ( subTuIndex < NumIntraSubPartitions - 1 || !InferTuCbfLuma ) ) ) tu\_cbf\_luma[ x0 ][ y0 ] ae(v) if( IntraSubPartitionsSplitType != ISP\_NO\_SPLIT ) InferTuCbfLuma = InferTuCbfLuma && !tu\_cbf\_luma[ x0 ][ y0 ] } if( ( treeType == SINGLE\_TREE || treeType == DUAL\_TREE\_CHROMA ) { if( ( IntraSubPartitionsSplitType == ISP\_NO\_SPLIT && !( cu\_sbt\_flag && ( subTuIndex == 0 && cu\_sbt\_pos\_flag ) || ( subTuIndex == 1 && !cu\_sbt\_pos\_flag ) ) ) || ( IntraSubPartitionsSplitType != ISP\_NO\_SPLIT && ( subTuIndex == NumIntraSubPartitions - 1 ) ) ) { tu\_cbf\_cb[ x0 ][ y0 ] ae(v) tu\_cbf\_cr[ x0 ][ y0 ] ae(v) } } if( IntraSubPartitionsSplitType != ISP\_NO\_SPLIT && treeType == SINGLE\_TREE && subTuIndex == NumIntraSubPartitions - 1 ) xC = CbPosX[ x0 ][ y0 ] yC = CbPosY[ x0 ][ y0 ] wC = CbWidth[ x0 ][ y0 ] / 2 hC = CbHeight[ x0 ][ y0 ] / 2 } else xC = x0 yC = y0 wC = tbWidth / SubWidthC hC = tbHeight / SubHeightC } if( ( tu\_cbf\_luma[ x0 ][ y0 ] || tu\_cbf\_cb[ x0 ][ y0 ] || tu\_cbf\_cr[ x0 ][ y0 ] ) && treeType != DUAL\_TREE\_CHROMA ) { if( cu\_qp\_delta\_enabled\_flag && !IsCuQpDeltaCoded ) { cu\_qp\_delta\_abs ae(v) if( cu\_qp\_delta\_abs ) cu\_qp\_delta\_sign\_flag ae(v) } } if( tu\_cbf\_luma[ x0 ][ y0 ] && treeType != DUAL\_TREE\_CHROMA && ( tbWidth <= 32 ) && ( tbHeight <= 32 ) && ( IntraSubPartitionsSplit[ x0 ][ y0 ] == ISP\_NO\_SPLIT ) && ( !cu\_sbt\_flag ) ) { if( transform\_skip\_enabled\_flag && log2TbWidth <= MaxTsSize && log2TbHeight <= MaxTsSize ) transform\_skip\_flag[ x0 ][ y0 ] ae(v) if( ( CuPredMode[ x0 ][ y0 ] == MODE\_INTER && sps\_mts\_inter\_enabled\_flag ) || ( CuPredMode[ x0 ][ y0 ] == MODE\_INTRA && sps\_mts\_intra\_enabled\_flag ) && ( tbWidth <= 32 ) && ( tbHeight <= 32 ) && ( !transform\_skip\_flag[ x0 ][ y0 ] ) ) tu\_mts\_idx[ x0 ][ y0 ] ae(v) } if( tu\_cbf\_luma[ x0 ][ y0 ] ) residual\_coding( x0, y0, Log2( tbWidth ), Log2( tbHeight ), 0 ) if( tu\_cbf\_cb[ x0 ][ y0 ] ) residual\_coding( xC, yC, Log2( wC ), Log2( hC ), 1 ) if( tu\_cbf\_cr[ x0 ][ y0 ] ) residual\_coding( xC, yC, Log2( wC ), Log2( hC ), 2 ) }

(329) In Table 19, transform\_skip\_flag[x0][y0] indicates whether a transform is applied to a luma transform block. Array indexes x0 and y0 indicate the position (x0, y0) of a top left luma sample of a transform block with respect to a top left luma sample of a picture. For example, a transform is not applied to the luma transform block if transform\_skip\_flag[x0][y0] is 1, and another syntax element determines whether a transform is applied to the luma transform block if transform\_skip\_flag[x0][y0] is 0. If transform\_skip\_flag[x0][y0] is not present, the value thereof is

inferred as 0.

(330) tu\_mts\_idx[x0][y0] indicates transform kernels applied to residual samples in the horizontal and vertical directions of a related luma transform block. Array indexes x0 and y0 indicate the position (x0, y0) of a top left luma sample with respect to a top left luma sample of a picture. If tu\_mts\_idx[x0][y0] is not present, the value thereof is inferred as 0.

(331) FIG. 21 is a flowchart of a process for decoding the transform tree syntax based on the coding unit syntax according to an embodiment of the present disclosure. The flowchart of FIG. 21 schematically illustrates the operation of the decoding apparatus 200 according to Table 19.

(332) In step S2105, the decoding apparatus 200 checks whether conditions for parsing CBF of a transform unit are satisfied. CBF may be parsed if one of the following conditions (1) and (2) is satisfied.

(333) Condition (1): When both (1)-1 and (1)-2 are satisfied

(334) (1)-1. ISP (intra subpartitions) are not applied

(IntraSubPartitionsSplitType==ISP\_NO\_SPLIT)

(335) (1)-2. A case in which a transform is applied to the current sub-block when SBT is not applied (!cu\_sbt\_flag) or when SBT is applied (cu\_sbt\_flag). Here, a case in which a transform is applied refers to a case in which subTuIndex is 0 and cu\_sbt\_pos\_flag is 0 (subTuIndex==0 && !cu\_sbt\_pos\_flag), or (ii) a case in which subTuIndex is 1 and cu\_sbt\_pos\_flag is 1 (subTuIndex==1 && cu\_sbt\_pos\_flag).

(336) Condition (2): Both (2)-1 and (2)-2 are satisfied

(337) (2)-1. ISP is applied (IntraSubPartitionsSplitType !=ISP\_NO\_SPLIT)

(338) (2)-2. (i) A block indicated by subTuldex is not the last ISP partition block

(subTuIndex<NumIntraSubPartitions-1), or (ii) InferTuCbfLuma is 0 (!InferTuCbfLuma)

(339) InferTuCbfLuma is a variable for inferring a corresponding CBF as 1 without parsing CBF of the last sub-block when CBF for previous sub-blocks is 0. InferTuCbfLuma is initially set to 1 and is updated after CBF parsing of each sub-block. InferTuCbfLuma is maintained if CBF of the current sub-block is 0 and set to 1 if CBF of the current sub-block is 1

(InferTuCbfLuma=InferTuCbfLuma && !tu\_cbf\_luma[x0][y0]).

(340) If the condition of step S2105 is satisfied, the decoding apparatus 200 parses CBF (tu\_cbf\_luma) of the current transform unit (S2110). Thereafter, the decoding apparatus 200 checks whether tu\_cbf\_luma is 1 and performs residual coding (S2120).

(341) Table 20 shows an example of a residual coding syntax according to an embodiment of the present disclosure.

(342) TABLE-US-00020 TABLE 20 Descriptor residual\_coding( x0, y0, log2TbWidth, log2TbHeight, cIdx ) { if( ( tu\_mts\_idx[ x0 ][ y0 ] > 0 || ( cu\_sbt\_flag && log2TbHeight < 6 && log2TbWidth < 6 ) ) && cIdx == 0 && log2TbWidth > 4 ) log2TbWidth = 4 else log2TbWidth = Min( log2TbWidth, 5 ) if( ( tu\_mts\_idx[ x0 ][ y0 ] > 0 || ( cu\_sbt\_flag && log2TbHeight < 6 && log2TbWidth < 6 ) ) && cIdx == 0 && log2TbHeight > 4 ) log2TbHeight = 4 else log2TbHeight = Min( log2TbHeight, 5 ) if( log2TbWidth > 0 ) last\_sig\_coeff\_x\_prefix ae(v) if( log2TbHeight > 0 ) last\_sig\_coeff\_y\_prefix ae(v) if( last\_sig\_coeff\_x\_prefix > 3 ) last\_sig\_coeff\_x\_suffix ae(v) if( last\_sig\_coeff\_y\_prefix > 3 ) last\_sig\_coeff\_y\_suffix ae(v) log2SbW = ( Min( log2TbWidth, log2TbHeight ) < 2 ? 1 : 2 ) log2SbH = log2SbW if ( log2TbWidth < 2 && cIdx == 0 ) { log2SbW = log2TbWidth log2SbH = 4 - log2SbW } else if ( log2TbHeight < 2 && cIdx == 0 ) { log2SbH = log2TbHeight log2SbW = 4 - log2SbH } numSbCoeff = 1 << ( log2SbW + log2SbH ) lastScanPos = numSbCoeff lastSubBlock = ( 1 << ( log2TbWidth + log2TbHeight - ( log2SbW + log2SbH ) ) ) - 1 do { if( lastScanPos == 0 ) { lastScanPos = numSbCoeff lastSubBlock-- } lastScanPos-- xS = DiagScanOrder[ log2TbWidth - log2SbW ][ log2TbHeight - log2SbH ][ lastSubBlock ][ 0 ] yS = DiagScanOrder[ log2TbWidth - log2SbW ][ log2TbHeight - log2SbH ][ lastSubBlock ][ 1 ] xC = ( xS << log2SbW ) + DiagScanOrder[ log2SbW ][ log2SbH ][ lastScanPos ][ 0 ] yC = ( yS <<



last significant coefficient in a transform block in scan order. The value of last\_sig\_coeff\_x\_prefix may fall within the range of 0 to  $(\log 2TbWidth < 1) - 1$ . If last\_sig\_coeff\_x\_prefix is not present, the value thereof is inferred as 0. Since last\_sig\_coeff\_x\_prefix is coded based on the variable log 2ZoTbWidth in an embodiment of the present disclosure, the value of last\_sig\_coeff\_x\_prefix may also fall within the range of 0 to  $(\log 2ZoTbWidth < 1) - 1$ .

(344) last\_sig\_coeff\_y\_prefix indicates a prefix of the row position of the last significant coefficient in the transform block in scan order. The value of last\_sig\_coeff\_y\_prefix may fall within the range of 0 to  $(\log 2TbHeight < 1) - 1$ . If last\_sig\_coeff\_y\_prefix is not present, the value thereof is inferred as 0.

(345) FIG. 22 is a flowchart of a decoding operation based on a residual coding syntax according to an embodiment of the present disclosure. The flowchart of FIG. 22 illustrates the operation of the decoding apparatus 200 according to Table 20.

(346) In step S2205, the decoding apparatus 200 checks i) whether MTS is applied to a current transform unit ( $tu\_mts\_idx[x0][y0] > 0$ ) or ii) whether SBT is applied to the current transform unit and the width and the height of the current transform unit are less than a reference size ( $cu\_sbt\_flag \&\& \log 2TbHeight < 6 \&\& \log 2TbWidth < 6$ ), and whether the width of the current transform unit is greater than a reference size ( $\log 2TbWidth > 4$ ). Here, log 2TbWidth and log 2TbHeight represent values obtained by applying logarithm with a base of 2 to the width and the height of the current transform unit. That is, the decoding apparatus 200 checks whether the width of the current transform unit is greater than 16. If MTS is applied or both the width and the height of the transform unit are less than 64 when SBT is applied, the decoding apparatus 200 checks whether DST-7 or DCT-8 is applied and the width of the transform unit is greater than 16 because DST-7 or DCT-8 is applied as a transform kernel.

(347) log 2TbWidth is determined to be 4 (S2210) if the condition of step S2205 is satisfied and determined to be a smaller value  $\text{Min}(\log 2TbWidth, 5)$  between log 2TbWidth and 5 if the condition of step S2205 is not satisfied (S2215).  $\text{Min}(A, B)$  represents a function of outputting a smaller value between A and B. For example, if any of the width and the height of the transform unit is 64 when MTS is not applied and SBT is applied, DCT-2 is applied. Accordingly, if DCT-2 is applied and the width or the height of the transform unit is 64 ( $\log 2TbWidth$  or  $\log 2TbHeight$  is 6), log 2TbWidth is determined to be 5. That is, the decoding apparatus 200 may determine a region having a width and/or a height of 32 as a region to which the primary transform is applied if DCT-2 is applied and the width and/or the height of the current block is greater than 32.

(348) In step S2220, the decoding apparatus 200 checks whether a condition similar to that of step S2205 is satisfied for the height of the current transform unit (whether DST-7 or DCT-8 is applied and the height of the current transform unit is greater than 16). log 2TbHeight is determined to be 4 (S2225) if the condition of step S2220 is satisfied and determined to be a smaller value  $\text{Min}(\log 2TbHeight, 5)$  between log 2TbHeight and 5 if the condition of step S2220 is not satisfied (S2215).

(349) In another embodiment of the present disclosure, temporary variables log 2ZoTbWidth and log 2ZoTbHeight in consideration of zero-out may be used instead of log 2TbWidth and log 2TbHeight indicating the width and the height of a transform unit. In this case, step S2210 may be modified into  $\log 2TbZoWidth = 4$ , step S2215 may be modified into  $\log 2TbZoWidth = \text{Min}(\log 2ZoTbWidth, 5)$ , step S2225 may be modified into  $\log 2TbZoHeight = 4$ , and step S2230 may be modified into  $\log 2TbZoHeight = \text{Min}(\log 2ZoTbHeight, 5)$ . Thereafter, variables in which zero-out is reflected may be input as variables indicating size values (width value, height value) ( $\log 2TbWidth = \log 2ZoTbWidth$ ,  $\log 2TbHeight = \log 2TbZoHeight$ ).

(350) Thereafter, the decoding apparatus 200 parses position information last\_sig\_coeff\_x\_prefix and last\_sig\_coeff\_y\_prefix of the last significant coefficient in the transform unit in scan order.

(351) A transform process for scaled transform coefficients according to an embodiment of the present disclosure may be as follows.

(352) Transformation for scaled transform coefficients

(353) General

(354) Inputs to this process include the following. A luminance position (xTbY, yTbY) indicating a top left sample of a current transform block with respect to a top left luminance sample of a current picture, a variable nTbW indicating the width of the current transform block, a variable nTbH indicating the height of the current transform block, a variable cIdx indicating a color component of the current block, and an (nTbW)×(nTbH) array d[x][y] of scaled transform coefficients x=0 . . . nTbW-1 and y=0 . . . nTbH-1.

(355) The output of this process is an (nTbW)×(nTbH) array r[x][y] of residual samples x=0 . . . nTbW-1 and y=0 . . . nTbH-1.

(356) A variable implicitMtsEnabled is derived as follows. If sps\_mts\_enabled\_flag is 1 and one of the following conditions is true, implicitMtsEnabled is set to 1. IntraSubPartitionsSplitType is not ISP\_NO\_SPLIT (i.e., ISP is applied). cu\_sbt\_flag is 1 (i.e., SBT is applied) and Max(nTbW, nTbH) is equal to or less than 32 (both the width and the height of a transform block are equal to or less than 32) Both sps\_explicit\_mts\_intra\_enabled\_flag and sps\_explicit\_mts\_inter\_enabled\_flag are 0 and CuPredMode[xTbY][yTbY] is MODE\_INTRA (the current block is coded in the intra-prediction mode) If not, implicitMtsEnabled is set to 0.

(357) A variable trTypeHor indicating a horizontal transform kernel and a variable trTypeVer indicating a vertical transform kernel are derived as follows. If cIdx is greater than 0, both trTypeHor and trTypeVer are set to 0 (cIdx indicates the color component of the current block and cIdx indicates the luma component of the current block, and the current block indicates a chroma component Cb if cIdx is 1 and indicates chroma component Cr if cIdx is 2). If not, the following is applied if implicitMtsEnabled is 1. If IntraSubPartitionsSplitType is not ISP\_NO\_SPLIT (if ISP is applied), trTypeHor and trTypeVer are determined based on the intraPredMode as shown in Table 21.

(358) TABLE-US-00021 TABLE 21 predModeIntra trTypeHor trTypeVer INTRA\_PLANAR, (nTbW >= 4 && (nTbH >= 4 && INTRA\_ANGULAR31, nTbW <= 16) ? nTbH <= 16) ? INTRA\_ANGULAR32, 1:0 1:0 INTRA\_ANGULAR34, INTRA\_ANGULAR36, INTRA\_ANGULAR37 INTRA\_ANGULAR33, 0 0 INTRA\_ANGULAR35 INTRA\_ANGULAR2, (nTbW >= 4 && 0 INTRA\_ANGULAR4, . . . , nTbW <= 16) ? INTRA\_ANGULAR28, 1:0 INTRA\_ANGULAR30, INTRA\_ANGULAR39, INTRA\_ANGULAR41, . . . , INTRA\_ANGULAR63, INTRA\_ANGULAR65 INTRA\_ANGULAR3, 0 (nTbH >= 4 && INTRA\_ANGULAR5, . . . , nTbH <= 16) ? INTRA\_ANGULAR27, 1:0 INTRA\_ANGULAR29, INTRA\_ANGULAR38, INTRA\_ANGULAR40, . . . , INTRA\_ANGULAR64, INTRA\_ANGULAR66 If not (if ISP is not applied), trTypeHor and trTypeVer are determined based on cu\_sbt\_horizontal\_flag and cu\_sbt\_pos\_flag as shown in Table 22 when cu\_sbt\_flag is 1 (when SBT is applied). In Table 22, DST-7 is applied if trTypeHor or trTypeVer is 1 and DCT-8 is applied if trTypeHor or trTypeVer is 2. That is, DST-7 or DCT-8 may be applied for a block to which SBT has been applied.

(359) TABLE-US-00022 TABLE 22 cu\_sbt\_horizontal\_flag cu\_sbt\_pos\_flag trTypeHor trTypeVer 0 0 2 1 0 1 1 1 0 1 2 1 1 1 If not (sps\_explicit\_mts\_intra\_enabled\_flag and sps\_explicit\_mts\_inter\_enabled\_flag are 0), trTypeHor and trTypeVer are derived as follows.

(360) trTypeHor=(nTbW>=4 && nTbW<=16 && nTbW<=nTbH)? 1:0

(361) trTypeVer=(nTbH>=4 && nTbH<=16 && nTbH<=nTbW)? 1:0 If not, trTypeHor and trTypeVer are determined based on tu\_mts\_idx[xTbY][yTbY] as shown in Table 23.

(362) TABLE-US-00023 TABLE 23 tu\_mts\_idx[ x0 ][ y0 ] 0 1 2 3 4 trTypeHor 0 1 2 1 2 trTypeVer 0 1 1 2 2

(363) Variables nonZeroW and nonZeroH are derived as follows.

nonZeroW=Min(nTbW,(trTypeHor>0)?16:32)

nonZeroH=Min(nTbH,(trTypeVer>0)?16:32)

(364) The (nTbW)×(nTbH) array of residual samples are derived as follows.

(365) 1. When nTbH is greater than 1, each (vertical) column of scaled transform coefficients d[x][y] for x=0 . . . nonZeroW-1 and y=0 . . . nonZeroH-1 is transformed into e[x][y] for x=0 . . . nonZeroW-1 and y=0 . . . nTbH-1. To apply a transform for the length corresponding to the height nTbH of a transform block to each column x=0 . . . nonZeroW-1, a one-dimensional transform process is called for each column, a non-zero height nonZeroH of the scaled transform coefficients, a list d[x][y] for y=0 . . . nonZeroH-1, and a transform type variable trType set to the same value as trTypeVer are input as factors for calling the one-dimensional transform process, and a list e[x][y] for y=0 . . . nTbH-1 is output.

(366) 2. When both nTbH and nTbW are greater than 1, intermediate sample values g[x][y] for x=0 . . . nonZeroW-1 and y=0 . . . nTbH-1 may be derived as follows.

$g[x][y] = \text{Clip3}(\text{CoeffMin}, \text{CoeffMax}, (e[x][y] + 64) >> 7)$

(367) Here, the function Clip3(Min, Max, X) is a function that outputs X if X is a value between Min and Max, outputs Min if X is less than Min, and outputs Max if X is greater than Max.

(368) 3. When nTbW is greater than 1, each (horizontal) row of a resulting array g[x][y] for x=0 . . . nonZeroW-1 and y=0 . . . nTbH-1 is transformed into r[x][y] for x=0 . . . nTbW-1 and y=0 . . . nTbH-1. To apply a transform for the length corresponding to the width nTbW of a transform block to each row y=0 . . . nTbH-1, a one-dimensional transform process is called for each row, a non-zero width nonZeroW of the resulting array g[x][y], a list g[x][y] for x=0 . . . nonZeroW-1, and a transform type variable trType set to the same value as trTypeHor are input as factors for calling the one-dimensional transform process, and a list r[x][y] for x=0 . . . nTbW-1 is output.

(369) Transformation Process

(370) Inputs of this process include the following. A variable nTbS indicating a horizontal sample size of transformed samples, a variable nonZeroS indicating a horizontal sample size of a non-zero scaled transform coefficients, a list x[j] (j=0 . . . nonZeroS-1) of scaled transform coefficients, and a transform kernel type variable trType.

(371) The output of this process is a list of transformed samples y[i].

(372) A transform matrix derivation process is called, the transform size nTbS and the transform kernel type trType are input, and a transform matrix transMatrix is output.

(373) A transform is performed based on the value of trType, and a list y[i] (i=0 . . . nTbS-1) of transformed samples is derived as follows. If trType is 0, a transform matrix multiplication as represented by Formula 1 is applied.

$y[i] = \sum_{j=0}^{\text{sup.nonZeroS}-1} \text{transMatrix}[i][j] * 2^{\text{sup.6-Log 2(nTbS)}} * x[j]$  with  $i=0 \dots nTbS-1$  [Formula 1] If not (if trType is 1 or 2), a transform matrix multiplication as

represented by Formula 2 is applied.

$y[i] = \sum_{j=0}^{\text{sup.nonZeroS}-1} \text{transMatrix}[i][j] * x[j]$  with  $i=0 \dots nTbS-1$  [Formula 2]

Transform Matrix Derivation Process

(374) Inputs of this process include the following. A variable nTbS indicating a horizontal sample size of scaled transform coefficients, and a transform kernel type trType.

(375) The output of this process is a transform matrix transMatrix.

(376) The transform matrix transMatrix is derived based on trType and nTbS. If trType is 1 and nTbS is 32, the transform matrix transMatrix is derived as shown in Table 24 and Table 25.

(377) Matrices of Table 24 and Table 25 are concatenated in the horizontal direction to constitute one matrix, m in [m][n] is a horizontal index and n is a vertical index. When the matrix of Table 24 and the matrix of Table 25 are concatenated, a 16×32 matrix is derived and becomes a matrix for forward transform. Inverse transform may be performed through the matrix composed of Table 24 and Table 25 and appropriate indexing. For example, when the 16×32 matrix derived by concatenating the matrices of Table 24 and Table 25 (Table 26 and Table 27 if trType is 2 and nTbs is 32) in the horizontal direction is set to a forward transform matrix, a matrix derived by transposing the forward transform matrix becomes a reverse transform matrix, the decoding apparatus 200 can perform inverse transform through indexing corresponding to a transposition

operation for each component of the forward transform matrix.

(378) TABLE-US-00024 TABLE 24 transMatrix[ m ][ n ] = transMatrixCol0to15[ m ][ n ] with m = 0..15, n = 0..15 transMatrixCol0to15 = { { 4 9 13 17 21 26 30 34 38 42 46 50 53 56 60 63 } { 13 26 38 50 60 68 77 82 86 89 90 88 85 80 74 66 } { 21 42 60 74 84 89 89 84 74 60 42 21 0 -21 -42 -60 } { 30 56 77 87 89 80 63 38 9 -21 -50 -72 -85 -90 -84 -68 } { 38 68 86 88 74 46 9 -30 -63 -84 -90 -78 -53 -17 21 56 } { 46 78 90 77 42 -4 -50 -80 -90 -74 -38 9 53 82 89 72 } { 53 85 85 53 0 -53 -85 -85 -53 0 53 85 85 53 0 -53 } { 60 89 74 21 -42 -84 -84 -42 21 74 89 60 0 -60 -89 -74 } { 66 90 56 -13 -74 -87 -46 26 80 84 34 -38 -85 -78 -21 50 } { 72 86 34 -46 -89 -63 13 78 82 21 -56 -90 -53 26 84 77 } { 77 80 9 -72 -84 -17 66 86 26 -60 -88 -34 53 90 42 -46 } { 80 72 -17 -86 -60 34 90 46 -50 -89 -30 63 85 13 -74 -78 } { 84 60 -42 -89 -21 74 74 -21 -89 -42 60 84 0 -84 -60 42 } { 86 46 -63 -78 21 90 26 -77 -66 42 87 4 -85 -50 60 80 } { 88 30 -78 -56 60 77 -34 -87 4 89 26 -80 -53 63 74 -38 } { 90 13 -87 -26 84 38 -78 -50 72 60 -63 -68 53 77 -42 -82 } },

(379) TABLE-US-00025 TABLE 25 transMatrix[ m ][ n ] = transMatrixCol16to31[ m - 16 ][ n ] with m = 16..31, n = 0..15 transMatrixCol16to31 = { { 66 68 72 74 77 78 80 82 84 85 86 87 88 89 90 90 } { 56 46 34 21 9 -4 -17 -30 -42 -53 -63 -72 -78 -84 -87 -90 } { -74 -84 -89 -89 -84 -74 -60 -42 -21 0 21 42 60 74 84 89 } { -46 -17 13 42 66 82 90 86 74 53 26 -4 -34 -60 -78 -88 } { 80 90 82 60 26 -13 -50 -77 -89 -85 -66 -34 4 42 72 87 } { 34 -13 -56 -84 -88 -68 -30 17 60 85 87 66 26 -21 -63 -86 } { -85 -85 -53 0 53 85 85 53 0 -53 -85 -85 -53 0 53 85 } { -21 42 84 84 42 -21 -74 -89 -60 0 60 89 74 21 -42 -84 } { 88 72 9 -60 -90 -63 4 68 89 53 -17 -77 -86 -42 30 82 } { 9 -66 -88 -42 38 87 68 -4 -74 -85 -30 50 90 60 -17 -80 } { -90 -50 38 89 56 -30 -87 -63 21 85 68 -13 -82 -74 4 78 } { 4 82 68 -21 -87 -56 38 90 42 -53 -88 -26 66 84 9 -77 } { 89 21 -74 -74 21 89 42 -60 -84 0 84 60 -42 -89 -21 74 } { -17 -90 -30 74 68 -38 -88 -9 84 53 -56 -82 13 89 34 -72 } { -86 9 90 21 -82 -50 66 72 -42 -85 13 90 17 -84 -46 68 } { 30 86 -17 -89 4 90 9 -88 -21 85 34 -80 -46 74 56 -66 } }, If trType is 2 and nTbS is 32, a transform matrix transMatrix as shown in Table 26 and 27 is derived.

(380) TABLE-US-00026 TABLE 26 transMatrix[ m ][ n ] = transMatrixCol0to15[ m ][ n ] with m = 0..15, n = 0..15 transMatrixCol0to15 = { { 90 90 89 88 87 86 85 84 82 80 78 77 74 72 68 66 } { 90 87 84 78 72 63 53 42 30 17 4 -9 -21 -34 -46 -56 } { 89 84 74 60 42 21 0 -21 -42 -60 -74 -84 -89 -89 -84 -74 } { 88 78 60 34 4 -26 -53 -74 -86 -90 -82 -66 -42 -13 17 46 } { 87 72 42 4 -34 -66 -85 -89 -77 -50 -13 26 60 82 90 80 } { 86 63 21 -26 -66 -87 -85 -60 -17 30 68 88 84 56 13 -34 } { 85 53 0 -53 -85 -85 -53 0 53 85 85 53 0 -53 -85 -85 } { 84 42 -21 -74 -89 -60 0 60 89 74 21 -42 -84 -84 -42 21 } { 82 30 -42 -86 -77 -17 53 89 68 4 -63 -90 -60 9 72 88 } { 80 17 -60 -90 -50 30 85 74 4 -68 -87 -38 42 88 66 -9 } { 78 4 -74 -82 -13 68 85 21 -63 -87 -30 56 89 38 -50 -90 } { 77 -9 -84 -66 26 88 53 -42 -90 -38 56 87 21 -68 -82 -4 } { 74 -21 -89 -42 60 84 0 -84 -60 42 89 21 -74 -74 21 89 } { 72 -34 -89 -13 82 56 -53 -84 9 88 38 -68 -74 30 90 17 } { 68 -46 -84 17 90 13 -85 -42 72 66 -50 -82 21 90 9 -86 } { 66 -56 -74 46 80 -34 -85 21 88 -9 -90 -4 89 17 -86 -30 } },

(381) TABLE-US-00027 TABLE 27 transMatrix[ m ][ n ] = transMatrixCol16to31[ m - 16 ][ n ] with m = 16..31, n = 0..15 transMatrixCol16to31 = { { 63 60 56 53 50 46 42 38 34 30 26 21 17 13 9 4 } { -66 -74 -80 -85 -88 -90 -89 -86 -82 -77 -68 -60 -50 -38 -26 -13 } { -60 -42 -21 0 21 42 60 74 84 89 89 84 74 60 42 21 } { 68 84 90 85 72 50 21 -9 -38 -63 -80 -89 -87 -77 -56 -30 } { 56 21 -17 -53 -78 -90 -84 -63 -30 9 46 74 88 86 68 38 } { -72 -89 -82 -53 -9 38 74 90 80 50 4 -42 -77 -90 -78 -46 } { -53 0 53 85 85 53 0 -53 -85 -85 -53 0 53 85 85 53 } { 74 89 60 0 -60 -89 -74 -21 42 84 84 42 -21 -74 -89 -60 } { 50 -21 -78 -85 -38 34 84 80 26 -46 -87 -74 -13 56 90 66 } { -77 -84 -26 53 90 56 -21 -82 -78 -13 63 89 46 -34 -86 -72 } { -46 42 90 53 -34 -88 -60 26 86 66 -17 -84 -72 9 80 77 } { 78 74 -13 -85 -63 30 89 50 -46 -90 -34 60 86 17 -72 -80 } { 42 -60 -84 0 84 60 -42 -89 -21 74 74 -21 -89 -42 60 84 } { -80 -60 50 85 -4 -87 -42 66 77 -26 -90 -21 78 63 -46 -86 } { -38 74 63 -53 -80 26 89 4 -87 -34 77 60 -56 -78 30 88 } { 82 42 -77 -53 68 63 -60 -72 50 78 -38 -84 26 87 -13 -90 } },

## Binarization Process

(382) A binarization process in a CABAC parsing process for tile group data according to an embodiment of the present disclosure may be as follows. The input of this process is a request for a syntax element. The output of this process is binarization of the requested syntax element. Table 28 below shows a binarization process type and inputs related to each syntax element. A TR (truncated rice) binarization process, a TB (truncated binary) binarization process, an EGk (k-th order Exp-Golomb) binarization process, and an FL (fixed length) binarization process may be performed through processes known to those skilled in the art.

(383) TABLE-US-00028 TABLE 28 Syntax Binarization structure Syntax element Process Input parameters . . . . . coding\_unit( ) . . . . . cu\_sbt\_flag[ ][ ] FL cMax = 1 cu\_sbt\_quad\_flag[ ][ ] FL cMax = 1 cu\_sbt\_horizontal\_flag[ ][ ] FL cMax = 1 cu\_sbt\_pos\_flag[ ][ ] FL cMax = 1 . . . . . transform\_unit( ) . . . . . transform\_skip\_flag[ ][ ] FL cMax = 1 tu\_mts\_idx[ ][ ] TR cMax = 4, cRiceParam = 0 residual\_coding( ) last\_sig\_coeff\_x\_prefix TR cMax = (  $\log_2 \text{TbWidth} \ll 1$  ) - 1, cRiceParam = 0 last\_sig\_coeff\_y\_prefix TR cMax = (  $\log_2 \text{TbHeight} \ll 1$  ) - 1, cRiceParam = 0 last\_sig\_coeff\_x\_suffix FL cMax = ( 1 << ( ( last\_sig\_coeff\_x\_prefix >> 1 ) - 1 ) - 1 ) last\_sig\_coeff\_y\_suffix FL cMax = ( 1 << ( ( last\_sig\_coeff\_y\_prefix >> 1 ) - 1 ) - 1 ) . . . . .

(384) Process in Table 28 is an item indicating a binarization type, and TR indicates a truncated rice (or truncated unary) binarization method, and FL indicates a fixed length binarization method. Further, cMax and cRiceParam are parameters for determining the length of a bin string for unary binarization, and the length of the bin string may be determined as  $\text{cMax} > \text{cRiceParam}$ .

(385) In Table 28, syntax elements last\_sig\_coeff\_x\_prefix and last\_sig\_coeff\_y\_prefix related to the position of the last significant coefficient in a block are determined based on variables  $\log_2 \text{TbWidth}$  and  $\log_2 \text{TbHeight}$  with respect to a significant width and a significant height in consideration of zero-out. That is, position information last\_sig\_coeff\_x\_prefix and last\_sig\_coeff\_y\_prefix of the last significant coefficient is coded based on the variables  $\log_2 \text{TbWidth}$  and  $\log_2 \text{TbHeight}$  with respect to a transform target region.

(386) last\_sig\_coeff\_x\_prefix indicates a prefix of the column position of the last significant coefficient in the transform block in scan order and last\_sig\_coeff\_y\_prefix indicates a prefix of the row position of the last significant coefficient in the transform block in scan order. For example, an input parameter cMax for binarization of last\_sig\_coeff\_x\_prefix may be determined based on  $\log_2 \text{TbWidth}$  ( $\text{cMax} = (\log_2 \text{TbWidth} \ll 1) - 1$ ) and an input parameter  $\log_2 \text{TbHeight}$  for binarization of last\_sig\_coeff\_y\_prefix may be determined based on  $\log_2 \text{TbHeight}$  ( $\text{cMax} = (\log_2 \text{TbHeight} \ll 1) - 1$ ), as shown in Table 28.

(387) The position of the last significant coefficient in the transform block may be derived using last\_sig\_coeff\_x\_prefix and last\_sig\_coeff\_y\_prefix derived as above, and scanning or transformation for the transform block may be performed based on the position of the last significant coefficient.

(388) Furthermore, a suffix for determining the position of the last significant coefficient may be additionally used. Referring to Table 20, if last\_sig\_coeff\_x\_prefix is greater than a reference value (3), a suffix last\_sig\_coeff\_x\_suffix related to the column position of the last significant coefficient may be obtained. Further, if last\_sig\_coeff\_y\_prefix is greater than the reference value (3), a suffix last\_sig\_coeff\_y\_suffix related to the row position of the last significant coefficient may be obtained. If last\_sig\_coeff\_x\_suffix is present, the column position LastSignificantCoeffX of the last significant coefficient may be determined based on last\_sig\_coeff\_x\_prefix and last\_sig\_coeff\_x\_suffix. Further, if last\_sig\_coeff\_y\_suffix is present, the column position LastSignificantCoeffY of the last significant coefficient may be determined based on last\_sig\_coeff\_y\_prefix and last\_sig\_coeff\_y\_suffix.

(389) Derivation Process for ctxTable, ctxIdx, and bypassFlag

(390) The input of this process is the position of a current bin, binIdx, in a bin string. The output of

this process is ctxTable, ctxIdx, and bypassFlag. Values of ctxTable, ctxIdx, and bypassFlag are derived based on entry for binIdx of a corresponding syntax element in Table 29.

(391) TABLE-US-00029 TABLE 29 binIdx Syntax element 0 1 2 3 4 >=5 . . . . .  
. cu\_sbt\_flag[ ][ ] 0 na na na na na cu\_sbt\_quad\_flag[ ][ ] 0 na na na na na cu\_sbt\_horizontal\_flag[ ][ ] (cbWidth \* na na na na na cbHeight < 256) ? 1:0 cu\_sbt\_pos\_flag[ ][ ] 0 na na na na na . . . . .  
. . . . . transform\_skip\_flag[ ][ ] 0 na na na na na tu\_mts\_idx[ ][ ] cqtDepth 6 7 8 na na  
last\_sig\_coeff\_x\_prefix 0 . . . 23 last\_sig\_coeff\_y\_prefix 0 . . . 23 last\_sig\_coeff\_x\_suffix Bypass  
bypass bypass bypass bypass bypass last\_sig\_coeff\_y\_suffix Bypass bypass bypass bypass bypass  
bypass . . . . . If the entry in Table 29 is not “bypass”, “terminate”, or “na”, values of binIdx are decoded through DecodeDecision process as follows. ctxTable is indicated in XXX (another process). A variable ctxIdxOffset is indicated by the lowest value of ctxIdx in XXX (other process) based on the current value of initType. ctxIdx is set to be equal to the sum of ctxInc and ctxIdxOffset. bypassFlag is set to 0.

(392) In Table 29, ctxInc for last\_sig\_coeff\_x\_prefix and last sig\_coeff\_y\_prefix is determined by “derivation process of ctxInc for syntax elements last sig\_coeff\_x\_prefix and lasg\_sig\_coeff\_y\_prefix” which will be described later. If the entry in Table 29 is “bypass”, the values of binIdx are decoded through DecodeBypass process as follows. ctxTable is set to 0. ctxIdx is set to 0. bypassFlag is set to 1. If the entry in Table 29 is “terminate”, the values of binIdx are decoded through DecodeTerminate process as follows. ctxTable is set to 0. ctxIdx is set to 0. bypassFlag is set to 0. If the entry in Table 29 is “na”, the values of binIdx are not generated for the corresponding syntax element.

(393) Derivation process of ctxInc for the syntax elements last\_sig\_coeff\_x\_prefix and lasg\_sit\_coeff\_y\_prefix

(394) The input of this process is the variable binIdx, color component index cIdx, and binary logarithms log 2TbWidth and log 2TbHeight of a transform block width and a transform block height. The output of this process is the variable ctxInc.

(395) A variable log 2TbSize is derived as follows.

(396) If a parsed syntax element is last\_sig\_coeff\_x prefix, log 2TbSize is set to the same as log 2TbWidth. If not (if the parsed syntax element is last sig\_coeff\_y\_prefix), log 2TbSize is set to be the same as log 2TbHeight.

(397) Variables ctxOffset and ctxShift are derived as follows. If cIdx is 0, ctxOffset is set to  $3 * (\log 2TbSize - 2) + ((\log 2TbSize - 1) >> 2)$  and ctxShift is set to  $(\log 2TbSize + 1) >> 2$ . If not (if cIdx is greater than 0), ctxOffset is set to 21 and ctxShift is set to  $\text{Clip3}(0, 2, 2.\text{sup}.\log 2TbSize >> 3)$

(398) The variable ctxInc is derived as follows.

$\text{ctxInc} = (\text{binIdx} >> \text{ctxShift}) + \text{ctxOffset}$

(399) FIG. 23 illustrates an example of a video signal encoding method according to an embodiment of the present disclosure. Operations of FIG. 23 may be performed by the encoding apparatus 100.

(400) The encoding apparatus 100 determines whether to apply SBT (S2310) and determines a transform unit according to whether SBT is applied (S2320). For example, the encoding apparatus 100 may determine that SBT is applied to only a part of a transform unit in consideration of RD cost and determine transform forms (splitting direction and sub-block size) as shown in FIG. 13a to FIG. 16b.

(401) For example, a splitting direction may include a vertical direction as shown in FIGS. 13a, 13b, 15a, and 15b or a horizontal direction as shown in FIGS. 14a, 14b, 16a, and 16b. Further, a coding unit may be split into regions each having a size half the coding unit, as shown in FIGS. 13a, 13b, 14a, and 14b, or split into regions each having a size quarter the coding unit, as shown in FIGS. 15a, 15b, 16a, and 16b.

(402) In step S2330, the encoding apparatus 100 applies a transform to the transform unit. In an embodiment, the encoding apparatus 100 may apply a horizontal transform and a vertical transform

to the transform unit. When SBT is applied, a transform kernel for the horizontal transform and the vertical transform may be DST-7 or DCT-8 and may be determined based on a splitting direction of the coding unit and the position of a sub-block to which the transform is applied.

(403) For example, if the coding unit is split in the vertical direction and the transform is applied to the left sub-block **1320**, as shown in FIG. **13a**, DCT-8 may be applied as the horizontal transform and DST-7 may be applied as the vertical transform. If the coding unit is split in the vertical direction and the transform is applied to the right sub-block **1330**, as shown in FIG. **13b**, DST-7 may be applied as the horizontal transform and the vertical transform. If the coding unit is split in the horizontal direction and the transform is applied to the upper sub-block **1420**, as shown in FIG. **14a**, DST-7 may be applied as the horizontal transform and DCT-8 may be applied as the vertical transform. If the coding unit is split in the horizontal direction and the transform is applied to the lower sub-block **1430**, as shown in FIG. **14b**, DST-7 may be applied as the horizontal transform and the vertical transform.

(404) According to the embodiment of the present disclosure, if the size (width and height) of the transform unit is greater than a reference size when SBT is applied, the size (width and height) of a region where non-zero transform coefficients are present in the transform unit is set to the reference size. For example, when a reference width is 16, the width of a region where non-zero transform coefficients are present is reduced to 16 if the width of the transform unit is 32. Further, when a reference height is 16, the height of the region where non-zero transform coefficients are present is reduced to 16 if the height of the transform unit is 32. A decoder can reduce the amount of data and a processing time necessary for a transform by setting only the region where significant (non-zero) transform coefficients are present instead of the entire transform unit as a transform target region and applying the transform thereto.

(405) In step **S2340**, the encoding apparatus **100** encodes information related to the transform. Here, the information related to the transform may include information about SBT. The information about SBT includes an SBT flag `cu_sbt_flag` indicating whether SBT is applied, an SBT direction flag `cu_sbt_horizontal_flag` indicating a splitting direction of a coding unit, an SBT size flag `cu_sbt_quad_flag` indicating a size of a sub-block split into a coding block, and an SBT position flag `cu_sbt_pos_flag` indicating a position of a sub-block to which the transform is applied among sub-blocks. Further, the information related to the transform may include position information (e.g., `last_sig_coeff_x_prefix` and `last_sig_coeff_y_prefix`) of the last significant coefficient in the transform unit in scan order.

(406) FIG. **24** is a flowchart of a process of decoding a video signal according to an embodiment of the present disclosure. Operations in FIG. **24** may be performed by the decoding apparatus **200**.

(407) In step **S2410**, the decoding apparatus **200** obtains an SBT flag `cu_sbt_flag` indicating whether SBT is applied. Here, SBT refers to a transform applied to one of sub-blocks split from a coding unit.

(408) When the SBT is applied, the decoding apparatus **200** splits the coding unit into a plurality of sub-blocks based on the SBT direction flag `cu_sbt_horizontal_flag` indicating a splitting direction of the coding unit and the SBT size flag `cu_sbt_quad_flag` indicating a size of a sub-block split from the coding unit.

(409) In an embodiment, the SBT direction flag `cu_sbt_horizontal_flag` may indicate that the coding unit is split in the vertical or horizontal direction. For example, the coding unit may be split in the vertical direction, as shown in FIGS. **13a**, **13b**, **15a**, and **15b**, or split in the horizontal direction, as shown in FIGS. **14a**, **14b**, **16a**, and **16b**.

(410) In an embodiment, the SBT size flag `cu_sbt_quad_flag` may indicate that a sub-block split from the coding unit has a size half or quarter the coding unit. For example, the coding unit may be split into sub-blocks each having a size half the coding unit, as shown in FIGS. **13a**, **13b**, **14a**, and **14b**, or split into sub-blocks each having a size quarter the coding unit, as shown in FIGS. **15a**, **15b**, **16a**, and **16b**.

(411) In step **S2420**, the decoding apparatus **200** determines a transform unit to which (inverse) transform will be applied from the coding unit. When the SBT is applied, the decoding apparatus **200** determines one of the sub-blocks as a transform unit based on the SBT position flag `cu_sbt_pos_flag` indicating the position of a sub-block to which the transform will be applied from the sub-blocks.

(412) In step **S2430**, the decoding apparatus **200** determines a size value  $\log 2TbWidth$  or  $\log 2TbHeight$  of the transform unit as a first reference value (e.g., 4) if the size value  $\log 2TbWidth$  or  $\log 2TbHeight$  of the transform unit is greater than the first reference value (e.g., 4) and less than a third reference value (e.g., 6) when DST-7 or DCT-8 is applied (i.e., in a case where DST-7 or DCT-8 is applied to the entire block when SBT is not applied or DST-7 or DCT-8 is applied to the sub-block to which the transform is applied when SBT is applied) and determines the size value  $\log 2TbWidth$  or  $\log 2TbHeight$  as a second reference value (e.g., 5) if DCT-2 is applied (e.g., if SBT is not applied and DCT-2 is applied to the entire transform block) and the size value is equal to or greater than the third reference value (e.g., 6). Here, the third reference value is greater than the second reference value, and the second reference value is greater than the first reference value.

(413) In an embodiment, the first reference value may be 4, the second reference value may be 5, and the third reference value may be 6.

(414) For example, if DST-7 or DCT-8 is applied and the width value  $\log 2TbWidth$  corresponding to the width of the transform unit is 5, as shown in Table 20 and FIG. 22, the width value  $\log 2TbWidth$  is determined as 4 (reduced). If DCT-2 is applied and the width value  $\log 2TbWidth$  is equal to or greater than 6, the width value  $\log 2TbWidth$  is determined as the second reference value (5). Here, the width value  $\log 2TbWidth$  is a value obtained by applying logarithm with a base of 2 to the width of the transform unit.

(415) If DST-7 or DCT-8 is applied and the height value  $\log 2TbHeight$  corresponding to the height of the transform unit is 5, the height value  $\log 2TbHeight$  is determined as 4 (reduced). If DCT-2 is applied and the height value  $\log 2TbHeight$  is equal to or greater than 6, the height value  $\log 2TbHeight$  is determined as the second reference value (5). Here, the height value  $\log 2TbHeight$  is a value obtained by applying logarithm with a base of 2 to the height of the transform unit.

(416) In step **S2440**, the decoding apparatus **200** obtains transform coefficients based on the determined size values. For example, the decoding apparatus **200** may obtain position information (e.g., `last_sig_coeff_x_prefix` and `last_sig_coeff_y_prefix`) of the last significant coefficient in consideration of the determined size values  $\log 2TbWidth$  and  $\log 2TbHeight$ , as shown in Table 20 and FIG. 22, and obtain transform coefficients through a transform coefficient scanning operation.

(417) In step **S2450**, the decoding apparatus **200** performs inverse transform on the obtained transform coefficients.

(418) In an embodiment, the decoding apparatus **200** may apply horizontal inverse transform and vertical inverse transform to a transform unit including the transform coefficients, and a horizontal transform kernel for the horizontal inverse transform and a vertical transform kernel for the vertical inverse transform may be determined based on the SBT direction flag `cu_sbt_horizontal_flag` and the SBT position flag `cu_sbt_pos_flag`. For example, a horizontal transform type `trTypeHor` and a vertical transform type `trTypeVer` may be determined according to the SBT direction flag `cu_sbt_horizontal_flag` and the SBT position flag `cu_sbt_pos_flag`, as shown in Table 22, and the horizontal transform type `trTypeHor` and the vertical transform type `trTypeVer` may be determined between DST-7 and DCT-8.

(419) More specifically, if the coding unit is split in the vertical direction and the transform is applied to the left sub-block **1320**, as shown in FIG. 13a, DCT-8 may be applied as the horizontal transform and DST-7 may be applied as the vertical transform. If the coding unit is split in the vertical direction and the transform is applied to the right sub-block **1330**, as shown in FIG. 13b, DST-7 may be applied as the horizontal transform and the vertical transform. Further, if the coding unit is split in the horizontal direction and the transform is applied to the upper sub-block **1420**, as

shown in FIG. 14a, DST-7 may be applied as the horizontal transform and DCT-8 may be applied as the vertical transform. If the coding unit is split in the horizontal direction and the transform is applied to the lower sub-block 1430, as shown in FIG. 14b, DST-7 may be applied as the horizontal transform and the vertical transform.

(420) In an embodiment, if the width or the height of the transform unit is greater than a reference width or height (e.g., 16), inverse transform is not applied to the entire transform unit and may be applied to a reduced region. For example, the size of the transform unit is  $32 \times 16$  (or  $16 \times 32$ ), a top left  $16 \times 16$  region may be determined as a transform target region (a region where non-zero transform coefficients are present) and inverse transform may be applied to the transform target region. In addition, the decoding apparatus 200 may regard the transform target region instead of the original transform unit as a transform unit and apply inverse transform to the changed transform unit.

(421) FIG. 25 is a block diagram of an apparatus for processing a video signal according to an embodiment of the present disclosure. The video signal processing apparatus of FIG. 25 may correspond to the encoding apparatus 100 of FIG. 1 or the decoding apparatus 200 of FIG. 2.

(422) The video signal processing apparatus 2500 for processing a video signal includes a memory 2520 storing a video signal and a processor 2510 combined with the memory and configured to process a video signal. The processor 2510 according to an embodiment of the present disclosure may be configured as at least one processing circuit for processing a video signal and may process a video signal by executing commands for encoding or decoding. That is, the processor 2510 may encode original video data or decode an encoded video signal by executing the above-described encoding or decoding method.

(423) The processor 2510 according to the embodiment of the present disclosure may be configured, for encoding a video signal, to split a coding unit into a plurality of sub-blocks, to determine one of the sub-blocks as a transform unit, to apply a transform to the transform unit, wherein, if the size of the transform unit is greater than a reference size, the size of a region where non-zero transform coefficients are present in the transform unit is set to the reference size, and to encode information related to the transform.

(424) In an embodiment, the reference width and reference height may be 16.

(425) In an embodiment, the processor 2510 may apply the horizontal transform and the vertical transform to the transform unit, and a horizontal transform kernel for the horizontal transform and a vertical transform kernel for the vertical transform may be determined based on a splitting direction of the coding unit and the position of the sub-block to which the transform is applied.

(426) In an embodiment, the splitting direction of the coding unit may include the horizontal direction or the vertical direction.

(427) In an embodiment, the transform unit may have a size half or quarter the coding unit.

(428) To decode a video signal, the processor 2510 according to an embodiment of the present disclosure may be configured

(429) to obtain a sub-block transform (SBT) flag indicating whether SBT is applied, wherein the SBT represents a transform applied to one of sub-blocks split from a coding unit, to determine a transform unit from the coding unit based on the SBT flag, to determine a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value, to determine the size value as a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value, to obtain transform coefficients based on the size value, and to perform inverse transform on the transform coefficients.

(430) In an embodiment, the first reference value may be 4, the second reference value may be 5,

and the third reference value may be 6.

(431) In an embodiment, the processor **2510** may be configured to reduce a width value of the transform unit to 4 if DST-7 or DCT-8 is applied and the width value of the transform unit is 5, to determine a size value as a smaller value between the width value and 5 if DCT-2 is applied and the size value is equal to or greater than 6, to reduce a height value of the transform unit to 4 if DST-7 or DCT-8 is applied and the height value of the transform unit is 5, and to determine the height value as 5 if DCT-2 is applied and the size value is equal to or greater than 6. Here, the width value is obtained by applying logarithm with a base of 2 to the width of the transform unit and the height value is obtained by applying logarithm with a base of 2 to the height of the transform unit.

(432) In an embodiment, the processor **2510** may be configured to split the coding unit into a plurality of sub-blocks based on an SBT direction flag indicating a splitting direction of a coding unit and an SBT side flag indicating a size of sub-blocks split from the coding unit when the SBT is applied, and to determine one of the sub-blocks as the transform unit based on an SBT position flag indicating a position of a sub-block to which a transform is applied among the sub-blocks.

(433) In an embodiment, the processor **2510** may be configured, for performing an inverse transform, to apply a horizontal inverse transform and a vertical inverse transform to a transform block including the transform coefficients, wherein a horizontal transform kernel for the horizontal inverse transform and a vertical transform kernel for the vertical inverse transform may be determined based on the SBT direction flag and the SBT position flag.

(434) In an embodiment, the horizontal transform kernel and the vertical transform kernel may be DST-7 or DCT-8.

(435) In an embodiment, the SBT direction flag may indicate that the coding unit is split in the vertical direction or the horizontal direction.

(436) In an embodiment, the SBT size flag may indicate that a sub-block split from the coding unit has a size half or quarter the coding unit.

(437) The processing methods to which the present disclosure is applied may be manufactured in the form of a program executed by a computer and may be stored in computer-readable recording media. Multimedia data with a data structure according to the present disclosure may also be stored in computer-readable recording media. The computer-readable recording media include all types of storage devices and distributed storage devices in which data readable by a computer is stored. The computer-readable recording media may include a Blue-ray disk (BD), a universal serial bus (USB), a ROM, a PROM, an EEPROM, a RAM, a CD-ROM, a magnetictape, a floppy disk, and an optical data storage device, for example. Furthermore, the computer-readable recording media includes media implemented in the form of carrier waves (e.g., transmission through the Internet). Furthermore, a bitstream generated by the encoding method may be stored in a computer-readable recording medium or may be transmitted over wired/wireless communication networks.

(438) Embodiments of the present disclosure can be implemented as computer program products by program codes, and the program codes can be executed in a computer according to embodiments of the present disclosure. The program codes may be stored on computer-readable carriers.

(439) A non-transitory computer-readable medium according to an embodiment of the present disclosure stores one or more commands executed by one or more processors. The one or more commands control the video signal processing apparatus **2500** (or the encoding device **100**) to split a coding unit into a plurality of sub-blocks, to determine one of the sub-blocks as a transform unit, to apply a transform to the transform unit, wherein, if the size of the transform unit is greater than a reference size, the size of a region where non-zero transform coefficients are present in the transform unit is set to the reference size, and to encode information related to the transform.

(440) In an embodiment, the reference width and reference height may be 16.

(441) In an embodiment, the processor **2510** may apply the horizontal transform and the vertical transform to the transform unit, and a horizontal transform kernel for the horizontal transform and a

vertical transform kernel for the vertical transform may be determined based on a splitting direction of the coding unit and the position of the sub-block to which the transform is applied.

(442) In an embodiment, the splitting direction of the coding unit may include the horizontal direction or the vertical direction.

(443) In an embodiment, the transform unit may have a size half or quarter the coding unit.

(444) One or more commands stored in a non-transitory computer-readable medium according to another embodiment of the present disclosure control the video signal processing apparatus **2500** (or the decoding apparatus **200**), for decoding a video signal, to obtain a sub-block transform (SBT) flag indicating whether SBT is applied, wherein the SBT represents a transform applied to one of sub-blocks split from a coding unit, to determine a transform unit from the coding unit based on the SBT flag, to determine a size value of the transform unit as a first reference value if DST-7 (Discrete Sine Transform type 7) or DCT-8 (Discrete Cosine Transform type 8) is applied and the size value of the transform unit is greater than the first reference value and less than a third reference value, to determine the size value as a second reference value if DCT-2 (Discrete Cosine Transform type 2) is applied and the size value is equal to or greater than the third reference value, wherein the third reference value is greater than the second reference value and the second reference value is greater than the first reference value, to obtain transform coefficients based on the size value, and to perform inverse transform on the transform coefficients.

(445) In an embodiment, the first reference value may be 4, the second reference value may be 5, and the third reference value may be 6.

(446) In an embodiment, the one or more commands may reduce a width value of the transform unit to 4 if DST-7 or DCT-8 is applied and the width value of the transform unit is 5, reduce the width value to 5 if DCT-2 is applied and the size value is equal to or greater than 6, reduce a height value of the transform unit to 4 if the SBT is applied or DST-7 or DCT-8 is applied and the height value of the transform unit is greater than 4, and determine the height value as 5 if DCT-2 is applied and the size value is equal to or greater than 6. Here, the width value is obtained by applying logarithm with a base of 2 to the width of the transform unit and the height value is obtained by applying logarithm with a base of 2 to the height of the transform unit.

(447) In an embodiment, to determine the transform unit, the one or more commands may split the coding unit into a plurality of sub-blocks based on an SBT direction flag indicating a splitting direction of a coding unit and an SBT size flag indicating a size of sub-blocks split from the coding unit when the SBT is applied, and determine one of the sub-blocks as the transform unit based on an SBT position flag indicating a position of a sub-block to which a transform is applied among the sub-blocks.

(448) In an embodiment, the horizontal transform kernel and the vertical transform kernel may be DST-7 or DCT-8.

(449) In an embodiment, the SBT direction flag may indicate that the coding unit is split in the vertical direction or the horizontal direction.

(450) In an embodiment, the SBT size flag may indicate that a sub-block split from the coding unit has a size half or quarter the coding unit.

(451) As described above, embodiments of the present disclosure can be implemented and executed on a processor, a microprocessor, a controller or a chip. For example, functional units shown in each figure can be implemented and executed on a computer, a processor, a microprocessor, a controller or a chip.

(452) The decoder and the encoder to which the present disclosure is applied may be included in multimedia broadcast transmission/reception apparatuses, mobile communication terminals, home cinema video systems, digital cinema video systems, monitoring cameras, video conversation apparatuses, real-time communication apparatuses such as video communication, mobile streaming devices, storage media, camcorders, video-on-demand (VoD) service providing apparatuses, over the top video (OTT) video systems, Internet streaming service providing apparatuses, 3D video

systems, video phone video systems, medical video systems, etc., and may be used to process video signals or data signals. For example, OTT video systems may include game consoles, Blue-ray players, Internet access TVs, home theater systems, smartphones, tablet PCs, digital video recorders (DVRs), etc.

(453) Embodiments described above are combinations of elements and features of the present disclosure. The elements or features may be considered selective unless otherwise mentioned. Each element or feature may be practiced without being combined with other elements or features. Further, an embodiment of the present disclosure may be constructed by combining parts of the elements and/or features. Operation orders described in embodiments of the present disclosure may be rearranged. Some constructions of any one embodiment may be included in another embodiment and may be replaced with corresponding constructions of another embodiment. It is obvious to those skilled in the art that claims that are not explicitly cited in each other in the appended claims may be presented in combination as an exemplary embodiment or included as a new claim by a subsequent amendment after the application is filed.

(454) The implementations of the present disclosure may be achieved by various means, for example, hardware, firmware, software, or a combination thereof. In a hardware configuration, the methods according to the implementations of the present disclosure may be achieved by one or more application specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), processors, controllers, microcontrollers, microprocessors, etc.

(455) In a firmware or software configuration, the implementations of the present disclosure may be implemented in the form of a module, a procedure, a function, etc. Software code may be stored in the memory and executed by the processor. The memory may be located at the interior or exterior of the processor and may transmit data to and receive data from the processor via various known means.

(456) Those skilled in the art will appreciate that the present disclosure may be carried out in other specific ways than those set forth herein without departing from the spirit and essential characteristics of the present disclosure. Accordingly, the above embodiments are therefore to be construed in all aspects as illustrative and not restrictive. The scope of the present disclosure should be determined by the appended claims and their legal equivalents, not by the above description, and all changes coming within the meaning and equivalency range of the appended claims are intended to be embraced therein

## INDUSTRIAL APPLICABILITY

(457) Although exemplary aspects of the present disclosure have been described for illustrative purposes, those skilled in the art will appreciate that various modifications, additions and substitutions are possible, without departing from essential characteristics of the disclosure.

## Claims

1. A method for decoding a video signal, comprising: obtaining a sub-block transform (SBT) flag indicating whether a SBT is applied, wherein the SBT represents a transform applied to a transform unit corresponding to one of subblocks split from a coding unit; checking whether a condition related to a width and a height of the transform unit is satisfied; determining a width variable and a height variable related to a transform target region based on the SBT flag and the condition; and performing an inverse-transform on the transform target region based on the width variable and the height variable related to the transform target region, wherein, based on the SBT flag indicating that the SBT is applied to the transform unit and the condition being satisfied, the width variable related to the transform target region is determined as a first reference value, wherein, based on the SBT flag indicating that the SBT is not applied to the transform unit or the condition not being satisfied, the width variable related to the transform target region is determined as a smaller value

among the width of the transform unit and a second reference value, wherein, based on the SBT flag indicating that the SBT is applied to the transform unit and the condition being satisfied, the height variable related to the transform target region is determined as the first reference value, wherein, based on the SBT flag indicating that the SBT is not applied to the transform unit or the condition not being satisfied, the height variable related to the transform target region is determined as a smaller value among the height of the transform unit and the second reference value, wherein the inverse-transform on the transform target region comprises a horizontal direction transform and a vertical direction transform on a non-zero region in the transform unit, wherein a horizontal transform kernel index indicating a type of a horizontal transform kernel for the horizontal direction transform is derived based on the SBT flag, wherein a vertical transform kernel index indicating a type of a vertical transform kernel for the vertical direction transform is derived based on the SBT flag, wherein a width of the non-zero region is determined as a smaller value among the width of the transform unit and 16, based on the horizontal transform kernel index being greater than zero, and wherein a height of the non-zero region is determined as a smaller value among the height of the transform unit and 16, based on the vertical transform kernel index being greater than zero.

2. A method for encoding a video signal, the method comprising: checking whether a condition related to a width and a height of a transform unit is satisfied; determining a width variable and a height variable related to a transform target region based on whether a sub-block transform (SBT) is applied and the condition; performing a transform on the transform unit based on the width variable and the height variable related to the transform target region; and generating a SBT flag indicating whether the SBT is applied, wherein the SBT represents a transform applied to the transform unit corresponding to one of subblocks split from a coding unit, wherein, based on the SBT being applied to the transform unit and the condition being satisfied, the width variable related to the transform target region is determined as a first reference value, wherein, based on the SBT not being applied to the transform unit or the condition not being satisfied, the width variable related to the transform target region is determined as a smaller value among the width of the transform unit and a second reference value, and wherein, based on the SBT being applied to the transform unit and the condition being satisfied, the height variable related to the transform target region is determined as the first reference value, wherein, based on the SBT not being applied to the transform unit or the condition not being satisfied, the height variable related to the transform target region is determined as a smaller value among the height of the transform unit and the second reference value, wherein the transform on the transform unit comprises a horizontal direction transform and a vertical direction transform on the transform unit, wherein a horizontal transform kernel index indicating a type of a horizontal transform kernel for the horizontal direction transform is derived based on the SBT flag, wherein a vertical transform kernel index indicating a type of a vertical transform kernel for the vertical direction transform is derived based on the SBT flag, wherein a width of an area, in which a non-zero transform coefficient is present, is determined as a smaller value among the width of the transform unit and 16, based on the horizontal transform kernel index being greater than zero, and wherein a height of the area, in which the non-zero transform coefficient is present, is determined as a smaller value among the height of the transform unit and 16, based on the vertical transform kernel index being greater than zero.

3. A method comprising: generating a bitstream for image information including a sub-block transform (SBT) flag indicating whether a SBT is applied, wherein the SBT represents a transform applied to a transform unit corresponding to one of subblocks split from a coding unit; and transmitting data including the bitstream, wherein whether a condition related to a width and a height of the transform unit is satisfied is checked, wherein a width variable and a height variable related to a transform target region is determined based on whether the SBT is applied and the condition, wherein a transform on the transform unit is performed based on the width variable and

the height variable related to the transform target region, wherein, based on the SBT being applied to the transform unit and the condition being satisfied, the width variable related to the transform target region is determined as a first reference value, wherein, based on the SBT not being applied to the transform unit or the condition not being satisfied, the width variable related to the transform target region is determined as a smaller value among the width of the transform unit and a second reference value, and wherein, based on the SBT being applied to the transform unit and the condition being satisfied, the height variable related to the transform target region is determined as the first reference value, wherein, based on the SBT not being applied to the transform unit or the condition not being satisfied, the height variable related to the transform target region is determined as a smaller value among the height of the transform unit and the second reference value, wherein the transform on the transform unit comprises a horizontal direction transform and a vertical direction transform on the transform unit, wherein a horizontal transform kernel index indicating a type of a horizontal transform kernel for the horizontal direction transform is derived based on the SBT flag, wherein a vertical transform kernel index indicating a type of a vertical transform kernel for the vertical direction transform is derived based on the SBT flag, wherein a width of an area, in which a non-zero transform coefficient is present, is determined as a smaller value among the width of the transform unit and 16, based on the horizontal transform kernel index being greater than zero, and wherein a height of the area, in which the non-zero transform coefficient is present, is determined as a smaller value among the height of the transform unit and 16, based on the vertical transform kernel index being greater than zero.

---