

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12408229

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Vargas; Jose Edson et al.

Establishing radio bearers on millimeter wave frequencies for device-to-device communications

Abstract

Disclosed are techniques for wireless communication. In an aspect, a first user equipment (UE) establishes a radio resource control (RRC) connection for a communication session with a second UE, establishes a signaling radio bearer (SRB) for the communication session with the second UE on a first frequency band, sends, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and configures the DRB on the second frequency band based on the one or more parameters in the first RRC message and/or a device-to-device discovery procedure performed in the first frequency band.

Inventors: Vargas; Jose Edson (San Diego, CA), Wu; Zhibin (Los Altos, CA), Gulati; Kapil (Belle Mead, NJ), Li; Junyi (Fairless Hills, PA), Baghel; Sudhir Kumar (Fremont, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 72663320

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/951442

Filed: September 23, 2022

Prior Publication Data

Document Identifier

US 20230017902 A1

Publication Date

Jan. 19, 2023

Related U.S. Application Data

Publication Classification

Int. Cl.: H04W76/27 (20180101); H04B1/00 (20060101); H04W8/00 (20090101); H04W28/02 (20090101); H04W76/15 (20180101); H04W76/19 (20180101)

U.S. Cl.:

CPC H04W76/27 (20180201); H04B1/0064 (20130101); H04W8/005 (20130101); H04W28/0268 (20130101); H04W76/15 (20180201); H04W76/19 (20180201);

Field of Classification Search

CPC: H04W (76/27); H04W (76/19); H04W (76/15); H04W (8/005); H04W (28/0268); H04B (1/0064)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9832754	12/2016	Akkarakaran et al.	N/A	N/A
10771961	12/2019	Lee et al.	N/A	N/A
11102839	12/2020	Wu et al.	N/A	N/A
11464066	12/2021	Vargas et al.	N/A	N/A
11540106	12/2021	Vargas et al.	N/A	N/A
2003/0061623	12/2002	Denney	348/192	H04L 47/6215
2005/0094640	12/2004	Howe	370/474	H04L 47/2416
2007/0112996	12/2006	Manula	710/310	G06F 13/423
2011/0206143	12/2010	Reinhardt	375/259	H04W 88/06
2012/0250601	12/2011	Choi	370/329	H04W 88/04
2013/0219091	12/2012	Stark	29/829	H04L 45/50
2014/0181319	12/2013	Chen	709/234	G06F 13/385
2014/0295868	12/2013	Lee	N/A	N/A
2014/0328329	12/2013	Novlan et al.	N/A	N/A
2015/0263945	12/2014	Blessing	370/392	H04L 49/252
2016/0135220	12/2015	Jha	455/434	H04W 72/0453
2016/0226725	12/2015	Lizuka	N/A	H04L 43/028
2016/0277198	12/2015	Kwak	N/A	H04N 21/6162
2017/0048906	12/2016	Lee et al.	N/A	N/A
2017/0118766	12/2016	Baek et al.	N/A	N/A
2017/0181206	12/2016	Lee et al.	N/A	N/A

2017/0215183	12/2016	Gulati et al.	N/A	N/A
2017/0367003	12/2016	Zhang et al.	N/A	N/A
2017/0373740	12/2016	Guo et al.	N/A	N/A
2017/0373916	12/2016	Oh	N/A	H04L 69/22
2018/0070111	12/2017	Kwon	N/A	H04L 69/04
2018/0132304	12/2017	Lee et al.	N/A	N/A
2018/0242190	12/2017	Khoryaev et al.	N/A	N/A
2018/0279134	12/2017	Malik et al.	N/A	N/A
2018/0310305	12/2017	Shao	N/A	H04W 24/10
2019/0037461	12/2018	Li et al.	N/A	N/A
2019/0090156	12/2018	Kim	N/A	H04W 80/08
2019/0097712	12/2018	Singh et al.	N/A	N/A
2019/0110281	12/2018	Zhou et al.	N/A	N/A
2019/0191452	12/2018	Pelletier et al.	N/A	N/A
2019/0349730	12/2018	Kim et al.	N/A	N/A
2019/0379441	12/2018	Priyanto et al.	N/A	N/A
2020/0067650	12/2019	Kim et al.	N/A	N/A
2020/0092685	12/2019	Fehrenbach et al.	N/A	N/A
2020/0120458	12/2019	Aldana et al.	N/A	N/A
2020/0128597	12/2019	Shimizu et al.	N/A	N/A
2020/0146048	12/2019	Lee et al.	N/A	N/A
2020/0178221	12/2019	Byun et al.	N/A	N/A
2020/0229007	12/2019	Jung et al.	N/A	N/A
2020/0259896	12/2019	Sachs	N/A	H04L 67/12
2020/0267790	12/2019	Kim et al.	N/A	N/A
2020/0313999	12/2019	Lee	N/A	H04L 43/0847
2021/0028850	12/2020	Elliott et al.	N/A	N/A
2021/0045103	12/2020	Kim et al.	N/A	N/A
2021/0099847	12/2020	Uchiyama et al.	N/A	N/A
2021/0168862	12/2020	Murray et al.	N/A	N/A
2021/0306420	12/2020	Chintada	N/A	H04L 67/61
2021/0321267	12/2020	Kim	N/A	N/A
2021/0329730	12/2020	Wu et al.	N/A	N/A
2022/0021756	12/2021	Fuller	N/A	H04L 1/0061
2022/0039080	12/2021	Khoryaev et al.	N/A	N/A
2023/0122993	12/2022	Vargas et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
103875196	12/2013	CN	N/A
107079280	12/2016	CN	N/A
107548158	12/2017	CN	N/A
107925906	12/2017	CN	N/A
108633074	12/2017	CN	N/A
3148283	12/2016	EP	N/A
2548374	12/2016	GB	N/A
20170093071	12/2016	KR	N/A
WO-2013162193	12/2012	WO	N/A

WO-2017099833	12/2016	WO	N/A
2017204906	12/2016	WO	N/A
2018064068	12/2017	WO	N/A
WO-2019036578	12/2018	WO	N/A

OTHER PUBLICATIONS

Huawei, NPL document, Further views on Rel-17 work area on NR sidelink enhancements for V2X and other use cases (Year: 2019). cited by examiner

Huawei 1, NPL document, beamforming for v2X sidelink for FR1 and FR2 (Year: 2019). cited by examiner

LG, NPL document, Summary of emails discussion on Rel-17 sidelink enhancement (Year: 2019). cited by examiner

CATT: “Discussion on Unicast Connection Setup Procedure”, 3GPP TSG-RAN WG2 Meeting #107, 3GPP Draft; R2-1908737, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG2. No. Prague, Czech Republic; Aug. 26, 2019-Aug. 30, 2019, Aug. 16, 2019 (Aug. 16, 2019), 9 Pages, XP051766559, Sections 1.-4., Appendices A, B. cited by applicant

International Search Report and Written Opinion—PCT/US2020/024031—ISA/EPO—dated Sep. 17, 2020. cited by applicant

VIVO: “Consideration on PC5 L3 Protocol Design”, 3GPP TSG-RAN WG2 Meeting #103bis, 3GPP Draft; R2-1813923 Consideration on PC5 L3 Protocol Design, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles ; F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG2, No. Chengdu, CN; Oct. 8, 2018-Oct. 12, 2018, Sep. 28, 2018 (Sep. 28, 2018), 3 Pages, XP051523393, Sections 1.-3. cited by applicant

Huawei, et al., “Beamforming for V2X Sidelink for FR1 and FR2”, 3GPP TSG AN WG1 Meeting #96, R1-1903075, Athens, Greece, , Feb. 25-Mar. 1, 2019, 4 pages. cited by applicant

Primary Examiner: Ambaye; Mewale A

Attorney, Agent or Firm: Muncy, Geissler, Olds & Lowe, P.C./QUALCOMM Incorporated

Background/Summary

PRIORITY (1) The present Application for Patent is a continuation of U.S. patent application Ser. No. 16/824,649, entitled “ESTABLISHING RADIO BEARERS ON MILLIMETER WAVE FREQUENCIES FOR DEVICE-TO-DEVICE COMMUNICATIONS,” filed Mar. 19, 2020, which claims the benefit of U.S. Provisional Application No. 62/830,226, entitled “ESTABLISHING RADIO BEARERS ON MILLIMETER WAVE FREQUENCIES FOR DEVICE-TO-DEVICE COMMUNICATIONS,” filed Apr. 5, 2019, assigned to the assignee hereof, and expressly incorporated herein by reference in its entirety.

INTRODUCTION

(1) Various aspects described herein generally relate to wireless communication systems, and more specifically to device-to-device communications over sidelink.

(2) Wireless communication systems have developed through various generations, including a first-generation analog wireless phone service (1G), a second-generation (2G) digital wireless phone service (including interim 2.5G networks), a third-generation (3G) high speed data, Internet-capable wireless service and a fourth-generation (4G) service (e.g., LTE or WiMax). There are presently many different types of wireless communication systems in use, including cellular and

personal communications service (PCS) systems. Examples of known cellular systems include the cellular analog advanced mobile phone system (AMPS), and digital cellular systems based on code division multiple access (CDMA), frequency division multiple access (FDMA), time division multiple access (TDMA), the global system for mobile access (GSM) variation of TDMA, etc.

(3) A fifth generation (5G) wireless standard, referred to as New Radio (NR), enables higher data transfer speeds, greater numbers of connections, and better coverage, among other improvements. The NR standard, according to the Next Generation Mobile Networks Alliance, is designed to provide data rates of several tens of megabits per second to each of tens of thousands of users, with 1 gigabit per second to tens of workers on an office floor. Several hundreds of thousands of simultaneous connections should be supported in order to support large wireless sensor deployments. Consequently, the spectral efficiency of NR mobile communications should be significantly enhanced compared to the current 4G standard. Furthermore, signaling efficiencies should be enhanced and latency should be substantially reduced compared to current standards.

(4) Leveraging the increased data rates and decreased latency of 5G, among other things, vehicle-to-everything (V2X) communication technologies are being implemented to support autonomous driving applications, such as wireless communications between vehicles, between vehicles and the roadside infrastructure, between vehicles and pedestrians, etc.

SUMMARY

(5) This summary identifies features of some example aspects, and is not an exclusive or exhaustive description of the disclosed subject matter. Whether features or aspects are included in, or omitted from this summary is not intended as indicative of relative importance of such features. Additional features and aspects are described, and will become apparent to persons skilled in the art upon reading the following detailed description and viewing the drawings that form a part thereof.

(6) In an aspect, a method for wireless communication at a first user equipment (UE) includes establishing a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection, sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, and configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(7) In an aspect, a method for wireless communication at a first UE includes establishing an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(8) In an aspect, a method for wireless communication at a second UE includes establishing an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, receiving, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(9) In an aspect, a method for wireless communication at a second UE includes establishing an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, receiving, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(10) In an aspect, a first UE includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to establish an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(11) In an aspect, a first UE includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to establish an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(12) In an aspect, a second UE includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to establish an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(13) In an aspect, a second UE includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to establish an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(14) In an aspect, a first UE includes means for establishing an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, means for sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and means for configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(15) In an aspect, a first UE includes means for establishing an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, means for sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and means for configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(16) In an aspect, a second UE includes means for establishing an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, means for receiving, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and means for configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(17) In an aspect, a second UE includes means for establishing an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, means for receiving,

from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and means for configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(18) In an aspect, a non-transitory computer-readable medium storing computer-executable instructions includes computer-executable instructions comprising at least one instruction instructing a first UE to establish an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, at least one instruction instructing the first UE to send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and at least one instruction instructing the first UE to configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(19) In an aspect, a non-transitory computer-readable medium storing computer-executable instructions includes computer-executable instructions comprising at least one instruction instructing a first UE to establish an SRB for a communication session with a second UE on a first frequency band based on an RRC connection, at least one instruction instructing the first UE to send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and at least one instruction instructing the first UE to configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(20) In an aspect, a non-transitory computer-readable medium storing computer-executable instructions includes computer-executable instructions comprising at least one instruction instructing a second UE to establish an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, at least one instruction instructing the second UE to receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, and at least one instruction instructing the second UE to configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(21) In an aspect, a non-transitory computer-readable medium storing computer-executable instructions includes computer-executable instructions comprising at least one instruction instructing a second UE to establish an SRB for a communication session with a first UE on a first frequency band based on an RRC connection, at least one instruction instructing the second UE to receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band, and at least one instruction instructing the second UE to configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(22) Other objects and advantages associated with the aspects disclosed herein will be apparent to those skilled in the art based on the accompanying drawings and detailed description.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The accompanying drawings are presented to aid in the description of examples of one or more aspects of the disclosed subject matter and are provided solely for illustration of the examples and

not limitation thereof:

- (2) FIG. 1 illustrates an exemplary wireless communications system in accordance with one or more aspects of the disclosure.
- (3) FIGS. 2A and 2B illustrate example wireless network structures, according to various aspects.
- (4) FIG. 3 illustrates an example of a wireless communications system that supports unicast sidelink establishment in accordance with aspects of the disclosure.
- (5) FIG. 4 is a block diagram illustrating various components of an exemplary UE according to at least one aspect of the disclosure.
- (6) FIG. 5 illustrates an exemplary flow between an initiator device and a target device, according to aspects of the disclosure.
- (7) FIGS. 6 to 9 illustrate exemplary flows for wireless communication, according to aspects of the disclosure.
- (8) FIGS. 10 to 15 illustrate exemplary apparatuses for wireless communication, according to aspects of the disclosure.

DETAILED DESCRIPTION

(9) Disclosed are techniques for establishing a device-to-device unicast sidelink between an initiator device and a target device in a millimeter wave (mmW) frequency band. In an aspect, the devices may obtain connection setup parameters for the mmW unicast sidelink from a previously established non-mmW link between the devices or between at least one of the devices and a base station. The connection setup parameters may include the locations of the devices, a requested quality of service (QoS) for the mmW unicast sidelink, the number of transmit beams used by the initiator device for the mmW unicast sidelink, periodicity of the transmit beams, and the beam response and/or physical random access channel (PRACH) configuration for the transmit beams. By using the previously established non-mmW link to obtain the connection setup parameters for the mmW unicast sidelink, beam pair link (BPL) acquisition and resource utilization are sped up in the for the mmW unicast sidelink. Once the mmW unicast sidelink is established from the initiator device to the target device, the initiator device can transmit data to the target device over the mmW unicast link. In addition, if desired, the target device can transmit data to the initiator device with support of, for example, reflective QoS.

(10) These and other aspects of the subject matter are provided in the following description and related drawings directed to specific examples of the disclosed subject matter. Alternates may be devised without departing from the scope of the disclosed subject matter. Additionally, well-known elements will not be described in detail or will be omitted so as not to obscure the relevant details of the disclosure.

(11) The words “exemplary” and/or “example” are used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” and/or “example” is not necessarily to be construed as preferred or advantageous over other aspects. Likewise, the term “aspects of the disclosure” does not require that all aspects of the disclosure include the discussed feature, advantage or mode of operation.

(12) Those of skill in the art will appreciate that the information and signals described below may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description below may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof, depending in part on the particular application, in part on the desired design, in part on the corresponding technology, etc.

(13) Further, many aspects are described in terms of sequences of actions to be performed by, for example, elements of a computing device. It will be recognized that various actions described herein can be performed by specific circuits (e.g., application specific integrated circuits (ASICs)), by program instructions being executed by one or more processors, or by a combination of both.

Additionally, the sequence(s) of actions described herein can be considered to be embodied entirely within any form of non-transitory computer-readable storage medium having stored therein a corresponding set of computer instructions that, upon execution, would cause or instruct an associated processor of a device to perform the functionality described herein. Thus, the various aspects of the disclosure may be embodied in a number of different forms, all of which have been contemplated to be within the scope of the claimed subject matter. In addition, for each of the aspects described herein, the corresponding form of any such aspects may be described herein as, for example, “logic configured to” perform the described action.

(14) As used herein, the terms “user equipment” (UE), “vehicle UE” (V-UE), “pedestrian UE” (P-UE), and “base station” are not intended to be specific or otherwise limited to any particular radio access technology (RAT), unless otherwise noted. In general, a UE may be any wireless communication device (e.g., vehicle on-board computer, vehicle navigation device, mobile phone, router, tablet computer, laptop computer, tracking device, wearable (e.g., smartwatch, glasses, augmented reality (AR)/virtual reality (VR) headset, etc.), vehicle (e.g., automobile, motorcycle, bicycle, etc.), Internet of Things (IoT) device, etc.) used by a user to communicate over a wireless communications network. A UE may be mobile or may (e.g., at certain times) be stationary, and may communicate with a radio access network (RAN). As used herein, the term “UE” may be referred to interchangeably as an “access terminal” or “AT,” a “client device,” a “wireless device,” a “subscriber device,” a “subscriber terminal,” a “subscriber station,” a “user terminal” or UT, a “mobile terminal,” a “mobile station,” or variations thereof.

(15) A V-UE is a type of UE and may be any in-vehicle wireless communication device, such as a navigation system, a warning system, a heads-up display (HUD), an on-board computer, etc. Alternatively, a V-UE may be a portable wireless communication device (e.g., a cell phone, tablet computer, etc.) that is carried by the driver of the vehicle or a passenger in the vehicle. The term “V-UE” may refer to the in-vehicle wireless communication device or the vehicle itself, depending on the context. A P-UE is a type of UE and may be a portable wireless communication device that is carried by a pedestrian (i.e., a user that is not driving or riding in a vehicle). Generally, UEs can communicate with a core network via a RAN, and through the core network the UEs can be connected with external networks such as the Internet and with other UEs. Of course, other mechanisms of connecting to the core network and/or the Internet are also possible for the UEs, such as over wired access networks, wireless local area network (WLAN) networks (e.g., based on IEEE 802.11, etc.) and so on.

(16) A base station may operate according to one of several RATs in communication with UEs depending on the network in which it is deployed, and may be alternatively referred to as an access point (AP), a network node, a NodeB, an evolved NodeB (eNB), a New Radio (NR) Node B (also referred to as a gNB or gNodeB), etc. In addition, in some systems a base station may provide purely edge node signaling functions while in other systems it may provide additional control and/or network management functions. A communication link through which UEs can send signals to a base station is called an uplink (UL) channel (e.g., a reverse traffic channel, a reverse control channel, an access channel, etc.). A communication link through which the base station can send signals to UEs is called a downlink (DL) or forward link channel (e.g., a paging channel, a control channel, a broadcast channel, a forward traffic channel, etc.). As used herein the term traffic channel (TCH) can refer to either an UL/reverse or DL/forward traffic channel.

(17) The term “base station” may refer to a single physical transmission-reception point (TRP) or to multiple physical TRPs that may or may not be co-located. For example, where the term “base station” refers to a single physical TRP, the physical TRP may be an antenna of the base station corresponding to a cell of the base station. Where the term “base station” refers to multiple co-located physical TRPs, the physical TRPs may be an array of antennas (e.g., as in a multiple-input multiple-output (MIMO) system or where the base station employs beamforming) of the base station. Where the term “base station” refers to multiple non-co-located physical TRPs, the physical

TRPs may be a distributed antenna system (DAS) (a network of spatially separated antennas connected to a common source via a transport medium) or a remote radio head (RRH) (a remote base station connected to a serving base station). Alternatively, the non-co-located physical TRPs may be the serving base station receiving the measurement report from the UE and a neighbor base station whose reference RF signals the UE is measuring. Because a TRP is the point from which a base station transmits and receives wireless signals, as used herein, references to transmission from or reception at a base station are to be understood as referring to a particular TRP of the base station.

(18) An “RF signal” comprises an electromagnetic wave of a given frequency that transports information through the space between a transmitter and a receiver. As used herein, a transmitter may transmit a single “RF signal” or multiple “RF signals” to a receiver. However, the receiver may receive multiple “RF signals” corresponding to each transmitted RF signal due to the propagation characteristics of RF signals through multipath channels. The same transmitted RF signal on different paths between the transmitter and receiver may be referred to as a “multipath” RF signal.

(19) According to various aspects, FIG. 1 illustrates an exemplary wireless communications system **100**. The wireless communications system **100** (which may also be referred to as a wireless wide area network (WWAN)) may include various base stations **102** (labelled “BS”) and various UEs **104**. The base stations **102** may include macro cell base stations (high power cellular base stations) and/or small cell base stations (low power cellular base stations). In an aspect, the macro cell base stations **102** may include eNBs where the wireless communications system **100** corresponds to an LTE network, or gNBs where the wireless communications system **100** corresponds to a NR network, or a combination of both, and the small cell base stations may include femtocells, picocells, microcells, etc.

(20) The base stations **102** may collectively form a RAN and interface with a core network **174** (e.g., an evolved packet core (EPC) or next generation core (NGC)) through backhaul links **122**, and through the core network **174** to one or more location servers **172**. In addition to other functions, the base stations **102** may perform functions that relate to one or more of transferring user data, radio channel ciphering and deciphering, integrity protection, header compression, mobility control functions (e.g., handover, dual connectivity), inter-cell interference coordination, connection setup and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, RAN sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate with each other directly or indirectly (e.g., through the EPC/NGC) over backhaul links **134**, which may be wired or wireless.

(21) The base stations **102** may wirelessly communicate with the UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. In an aspect, one or more cells may be supported by a base station **102** in each geographic coverage area **110**. A “cell” is a logical communication entity used for communication with a base station (e.g., over some frequency resource, referred to as a carrier frequency, component carrier, carrier, band, or the like), and may be associated with an identifier (e.g., a physical cell identifier (PCI), an enhanced cell identifier (ECI), a virtual cell identifier (VCI), etc.) for distinguishing cells operating via the same or a different carrier frequency. In some cases, different cells may be configured according to different protocol types (e.g., machine-type communication (MTC), narrowband IoT (NB-IoT), enhanced mobile broadband (eMBB), or others) that may provide access for different types of UEs. Because a cell is supported by a specific base station, the term “cell” may refer to either or both the logical communication entity and the base station that supports it, depending on the context. In some cases, the term “cell” may also refer to a geographic coverage area of a base station (e.g., a sector), insofar as a carrier frequency can be detected and used for communication

within some portion of geographic coverage areas **110**.

(22) While neighboring macro cell base station **102** geographic coverage areas **110** may partially overlap (e.g., in a handover region), some of the geographic coverage areas **110** may be substantially overlapped by a larger geographic coverage area **110**. For example, a small cell base station **102'** (labelled "SC" for "small cell") may have a coverage area **110'** that substantially overlaps with the geographic coverage area **110** of one or more macro cell base stations **102**. A network that includes both small cell and macro cell base stations may be known as a heterogeneous network. A heterogeneous network may also include home eNBs (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG).

(23) The communication links **120** between the base stations **102** and the UEs **104** may include UL (also referred to as reverse link) transmissions from a UE **104** to a base station **102** and/or downlink (DL) (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **120** may use MIMO antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links **120** may be through one or more carrier frequencies. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or less carriers may be allocated for DL than for UL).

(24) The wireless communications system **100** may further include a wireless local area network (WLAN) access point (AP) **150** in communication with WLAN stations (STAs) **152** via communication links **154** in an unlicensed frequency spectrum (e.g., 5 GHz). When communicating in an unlicensed frequency spectrum, the WLAN STAs **152** and/or the WLAN AP **150** may perform a clear channel assessment (CCA) or listen before talk (LBT) procedure prior to communicating in order to determine whether the channel is available.

(25) The small cell base station **102'** may operate in a licensed and/or an unlicensed frequency spectrum. When operating in an unlicensed frequency spectrum, the small cell base station **102'** may employ LTE or NR technology and use the same 5 GHz unlicensed frequency spectrum as used by the WLAN AP **150**. The small cell base station **102'**, employing LTE/5G in an unlicensed frequency spectrum, may boost coverage to and/or increase capacity of the access network. NR in unlicensed spectrum may be referred to as NR-U. LTE in an unlicensed spectrum may be referred to as LTE-U, licensed assisted access (LAA), or MulteFire.

(26) The wireless communications system **100** may further include a millimeter wave (mmW) base station **180** that may operate in mmW frequencies and/or near mmW frequencies in communication with a UE **182**. Extremely high frequency (EHF) is part of the RF in the electromagnetic spectrum. EHF has a range of 30 GHz to 300 GHz and a wavelength between 1 millimeter and 10 millimeters. Radio waves in this band may be referred to as a millimeter wave. Near mmW may extend down to a frequency of 3 GHz with a wavelength of 100 millimeters. The super high frequency (SHF) band extends between 3 GHz and 30 GHz, also referred to as centimeter wave. Communications using the mmW/near mmW radio frequency band have high path loss and a relatively short range. The mmW base station **180** and the UE **182** may utilize beamforming (transmit and/or receive) over a mmW communication link **184** to compensate for the extremely high path loss and short range. Further, it will be appreciated that in alternative configurations, one or more base stations **102** may also transmit using mmW or near mmW and beamforming. Accordingly, it will be appreciated that the foregoing illustrations are merely examples and should not be construed to limit the various aspects disclosed herein.

(27) Transmit beamforming is a technique for focusing an RF signal in a specific direction. Traditionally, when a network node (e.g., a base station) broadcasts an RF signal, it broadcasts the signal in all directions (omni-directionally). With transmit beamforming, the network node determines where a given target device (e.g., a UE) is located (relative to the transmitting network node) and projects a stronger downlink RF signal in that specific direction, thereby providing a faster (in terms of data rate) and stronger RF signal for the receiving device(s). To change the directionality of the RF signal when transmitting, a network node can control the phase and relative

amplitude of the RF signal at each of the one or more transmitters that are broadcasting the RF signal. For example, a network node may use an array of antennas (referred to as a “phased array” or an “antenna array”) that creates a beam of RF waves that can be “steered” to point in different directions, without actually moving the antennas. Specifically, the RF current from the transmitter is fed to the individual antennas with the correct phase relationship so that the radio waves from the separate antennas add together to increase the radiation in a desired direction, while cancelling to suppress radiation in undesired directions.

(28) Transmit beams may be quasi-collocated, meaning that they appear to the receiver (e.g., a UE) as having the same parameters, regardless of whether or not the transmitting antennas of the network node themselves are physically collocated. In NR, there are four types of quasi-collocation (QCL) relations. Specifically, a QCL relation of a given type means that certain parameters about a second reference RF signal on a second beam can be derived from information about a source reference RF signal on a source beam. Thus, if the source reference RF signal is QCL Type A, the receiver can use the source reference RF signal to estimate the Doppler shift, Doppler spread, average delay, and delay spread of a second reference RF signal transmitted on the same channel. If the source reference RF signal is QCL Type B, the receiver can use the source reference RF signal to estimate the Doppler shift and Doppler spread of a second reference RF signal transmitted on the same channel. If the source reference RF signal is QCL Type C, the receiver can use the source reference RF signal to estimate the Doppler shift and average delay of a second reference RF signal transmitted on the same channel. If the source reference RF signal is QCL Type D, the receiver can use the source reference RF signal to estimate the spatial receive parameter of a second reference RF signal transmitted on the same channel.

(29) In receive beamforming, the receiver uses a receive beam to amplify RF signals detected on a given channel. For example, the receiver can increase the gain setting and/or adjust the phase setting of an array of antennas in a particular direction to amplify (e.g., to increase the gain level of) the RF signals received from that direction. Thus, when a receiver is said to beamform in a certain direction, it means the beam gain in that direction is high relative to the beam gain along other directions, or the beam gain in that direction is the highest compared to the beam gain in that direction of all other receive beams available to the receiver. This results in a stronger received signal strength (e.g., reference signal received power (RSRP), reference signal received quality (RSRQ), signal-to-interference-plus-noise ratio (SINR), etc.) of the RF signals received from that direction.

(30) Transmit and receive beams may be spatially related. A spatial relation means that parameters for a second beam (e.g., a transmit or receive beam) for a second reference signal can be derived from information about a first beam (e.g., a receive beam or a transmit beam) for a first reference signal. For example, a UE may use a particular receive beam to receive a reference downlink reference signal (e.g., synchronization signal block (SSB)) from a base station. The UE can then form a transmit beam for sending an uplink reference signal (e.g., sounding reference signal (SRS)) to that base station based on the parameters of the receive beam.

(31) Note that a “downlink” beam may be either a transmit beam or a receive beam, depending on the entity forming it. For example, if a base station is forming the downlink beam to transmit a reference signal to a UE, the downlink beam is a transmit beam. If the UE is forming the downlink beam, however, it is a receive beam to receive the downlink reference signal. Similarly, an “uplink” beam may be either a transmit beam or a receive beam, depending on the entity forming it. For example, if a base station is forming the uplink beam, it is an uplink receive beam, and if a UE is forming the uplink beam, it is an uplink transmit beam.

(32) In 5G, the frequency spectrum in which wireless nodes (e.g., base stations **102/180**, UEs **104/182**) operate is divided into multiple frequency ranges, FR1 (from 450 to 6000 MHz), FR2 (from 24250 to 52600 MHz), FR3 (above 52600 MHz), and FR4 (between FR1 and FR2). In a multi-carrier system, such as 5G, one of the carrier frequencies is referred to as the “primary

carrier” or “anchor carrier” or “primary serving cell” or “PCell,” and the remaining carrier frequencies are referred to as “secondary carriers” or “secondary serving cells” or “SCells.” In carrier aggregation, the anchor carrier is the carrier operating on the primary frequency (e.g., FR1) utilized by a UE **104/182** and the cell in which the UE **104/182** either performs the initial radio resource control (RRC) connection establishment procedure or initiates the RRC connection re-establishment procedure. The primary carrier carries all common and UE-specific control channels, and may be a carrier in a licensed frequency (however, this is not always the case). A secondary carrier is a carrier operating on a second frequency (e.g., FR2) that may be configured once the RRC connection is established between the UE **104** and the anchor carrier and that may be used to provide additional radio resources. In some cases, the secondary carrier may be a carrier in an unlicensed frequency. The secondary carrier may contain only necessary signaling information and signals, for example, those that are UE-specific may not be present in the secondary carrier, since both primary uplink and downlink carriers are typically UE-specific. This means that different UEs **104/182** in a cell may have different downlink primary carriers. The same is true for the uplink primary carriers. The network is able to change the primary carrier of any UE **104/182** at any time. This is done, for example, to balance the load on different carriers. Because a “serving cell” (whether a PCell or an SCell) corresponds to a carrier frequency/component carrier over which some base station is communicating, the term “cell,” “serving cell,” “component carrier,” “carrier frequency,” and the like can be used interchangeably.

(33) For example, still referring to FIG. **1**, one of the frequencies utilized by the macro cell base stations **102** may be an anchor carrier (or “PCell”) and other frequencies utilized by the macro cell base stations **102** and/or the mmW base station **180** may be secondary carriers (“SCells”). The simultaneous transmission and/or reception of multiple carriers enables the UE **104/182** to significantly increase its data transmission and/or reception rates. For example, two 20 MHz aggregated carriers in a multi-carrier system would theoretically lead to a two-fold increase in data rate (i.e., 40 MHz), compared to that attained by a single 20 MHz carrier.

(34) The wireless communications system **100** may further include one or more UEs, such as UE **190**, that connects indirectly to one or more communication networks via one or more device-to-device (D2D) peer-to-peer (P2P) links. In the example of FIG. **1**, UE **190** has a D2D P2P link **192** with one of the UEs **104** connected to one of the base stations **102** (e.g., through which UE **190** may indirectly obtain cellular connectivity) and a D2D P2P link **194** with WLAN STA **152** connected to the WLAN AP **150** (through which UE **190** may indirectly obtain WLAN-based Internet connectivity). In an example, the D2D P2P links **192** and **194** may be supported with any well-known D2D RAT, such as LTE Direct (LTE-D), WiFi Direct (WiFi-D), Bluetooth®, and so on.

(35) Leveraging the increased data rates and decreased latency of NR, among other things, vehicle-to-everything (V2X) communication technologies are being implemented to support intelligent transportation systems (ITS) applications, such as wireless communications between vehicles (vehicle-to-vehicle (V2V)), between vehicles and the roadside infrastructure (vehicle-to-infrastructure (V2I)), and between vehicles and pedestrians (vehicle-to-pedestrian (V2P)). The goal is for vehicles to be able to sense the environment around them and communicate that information to other vehicles, infrastructure, and personal mobile devices. Such vehicle communication will enable safety, mobility, and environmental advancements that current technologies are unable to provide. Once fully implemented, the technology is expected to reduce unimpaired vehicle crashes by 80%.

(36) Still referring to FIG. **1**, the wireless communications system **100** may include multiple V-UEs **160** that may communicate with base stations **102** over communication links **120** (e.g., using the Uu interface). V-UEs **160** may also communicate directly with each other over a wireless unicast sidelink **162**, with a roadside access point **164** over a sidelink **166**, or with UEs **104** over a sidelink **168** using P2P/D2D protocols (e.g., “PC5,” an LTE V2X D2D interface) or ProSe direct communications. Sidelink communication may be used for D2D media-sharing, V2V

communication, V2X communication (e.g., cellular V2X (cV2X) communication, enhanced V2X (eV2X) communication, etc.), emergency rescue applications, etc. One or more of a group of V-UEs **160** utilizing D2D communications may be within the geographic coverage area **110** of a base station **102**. Other V-UEs **160** in such a group may be outside the geographic coverage area **110** of a base station **102** or be otherwise unable to receive transmissions from a base station **102**. In some cases, groups of V-UEs **160** communicating via D2D communications may utilize a one-to-many (1:M) system in which each V-UE **160** transmits to every other V-UE **160** in the group. In some cases, a base station **102** facilitates the scheduling of resources for D2D communications. In other cases, D2D communications are carried out between V-UEs **160** without the involvement of a base station **102**.

(37) In an aspect, the V-UEs **160**, and any other UE illustrated in FIG. **1**, may have a sidelink manager **170**. The sidelink manager **170** may be a hardware, software, or firmware component that, when executed, causes the V-UE **160** to perform the operations described herein. For example, the sidelink manager **170** may be a software module stored in a memory of the V-UE **160** and executable by a processor of the V-UE **160**. As another example, the sidelink manager **170** may be a hardware circuit (e.g., an ASIC, a field programmable gate array (FPGA), etc.) within the V-UE **160**. Note that although only one UE (V-UE **160**) is illustrated as including a sidelink manager **170**, any of the illustrated UEs may include a sidelink manager **170**.

(38) In an aspect, the sidelinks **162**, **166**, **168** may operate over a communication medium of interest, which may be shared with other communications between other vehicles and/or infrastructure access points, as well as other RATs. A “medium” may be composed of one or more frequency, time, and/or space communication resources (e.g., encompassing one or more channels across one or more carriers) associated with communication between one or more transmitter/receiver pairs.

(39) In an aspect, the sidelinks **162**, **166**, **168** may be cV2X links. A first generation of cV2X has been standardized in LTE, and the next generation is expected to be defined in NR. cV2X is a cellular technology that also enables device-to-device communications. In the U.S. and Europe, cV2X is expected to operate in the licensed ITS band in sub-6 GHz. Other bands may be allocated in other countries. Thus, as a particular example, the medium of interest utilized by sidelinks **162**, **166**, **168** may correspond to at least a portion of the licensed ITS frequency band of sub-6 GHz. However, the present disclosure is not limited to this frequency band or cellular technology.

(40) In an aspect, the sidelinks **162**, **166**, **168** may be dedicated short-range communications (DSRC) links. DSRC is a one-way or two-way short-range to medium-range wireless communication protocol that uses the wireless access for vehicular environments (WAVE) protocol, also known as IEEE 802.11p, for V2V, V2I, and V2P communications. IEEE 802.11p is an approved amendment to the IEEE 802.11 standard and operates in the licensed ITS band of 5.9 GHz (5.85-5.925 GHz) in the U.S. In Europe, IEEE 802.11p operates in the ITS G5A band (5.875-5.905 MHz). Other bands may be allocated in other countries. The V2V communications briefly described above occur on the Safety Channel, which in the U.S. is typically a 10 MHz channel that is dedicated to the purpose of safety. The remainder of the DSRC band (the total bandwidth is 75 MHz) is intended for other services of interest to drivers, such as road rules, tolling, parking automation, etc. Thus, as a particular example, the mediums of interest utilized by sidelinks **162**, **166**, **168** may correspond to at least a portion of the licensed ITS frequency band of 5.9 GHz.

(41) Alternatively, the medium of interest may correspond to at least a portion of an unlicensed frequency band shared among various RATs. Although different licensed frequency bands have been reserved for certain communication systems (e.g., by a government entity such as the Federal Communications Commission (FCC) in the United States), these systems, in particular those employing small cell access points, have recently extended operation into unlicensed frequency bands such as the Unlicensed National Information Infrastructure (U-NII) band used by wireless local area network (WLAN) technologies, most notably IEEE 802.11x WLAN technologies

generally referred to as “Wi-Fi.” Example systems of this type include different variants of CDMA systems, TDMA systems, FDMA systems, orthogonal FDMA (OFDMA) systems, single-carrier FDMA (SC-FDMA) systems, and so on.

(42) Communications between the V-UEs **160** are referred to as V2V communications, communications between the V-UEs **160** and the one or more roadside access points **164** are referred to as V2I communications, and communications between the V-UEs **160** and one or more UEs **104** (where the UEs **104** are P-UEs) are referred to as V2P communications. The V2V communications between V-UEs **160** may include, for example, information about the position, speed, acceleration, heading, and other vehicle data of the V-UEs **160**. The V2I information received at a V-UE **160** from the one or more roadside access points **164** may include, for example, road rules, parking automation information, etc. The V2P communications between a V-UE **160** and a UE **104** may include information about, for example, the position, speed, acceleration, and heading of the V-UE **160** and the position, speed (e.g., where the UE **104** is carried by a user on a bicycle), and heading of the UE **104**.

(43) Note that although FIG. **1** only illustrates two of the UEs as V-UEs (V-UEs **160**), any of the illustrated UEs (e.g., UEs **104**, **152**, **182**, **190**) may be V-UEs. In addition, although only UE **182** was described as being capable of beam forming, any of the illustrated UEs, including V-UEs **160**, may be capable of beam forming. Where V-UEs **160** are capable of beam forming, they may beam form towards each other (i.e., towards other V-UEs **160**), towards roadside access points **164**, towards other UEs (e.g., UEs **104**, **152**, **182**, **190**), etc. Thus, in some cases, V-UEs **160** may utilize beamforming over sidelinks **162**, **166**, and **168**.

(44) According to various aspects, FIG. **2A** illustrates an exemplary wireless network structure **200**. For example, an NGC **210** (also referred to as a “5GC”) can be viewed functionally as control plane functions (C-plane) **214** (e.g., UE registration, authentication, network access, gateway selection, etc.) and user plane functions (U-plane) **212** (e.g., UE gateway function, access to data networks, IP routing, etc.), which operate cooperatively to form the core network. User plane interface (NG-U) **213** and control plane interface (NG-C) **215** connect the gNB **222** to the NGC **210** and specifically to the user plane functions **212** and control plane functions **214**, respectively. In an additional configuration, an eNB **224** may also be connected to the NGC **210** via NG-C **215** to the control plane functions **214** and NG-U **213** to user plane functions **212**. Further, eNB **224** may directly communicate with gNB **222** via a backhaul connection **223**. In some configurations, the New RAN **220** may only have one or more gNBs **222**, while other configurations include one or more of both eNBs **224** and gNBs **222**. Either gNB **222** or eNB **224** may communicate with UEs **204** (e.g., any of the UEs depicted in FIG. **1**). In an aspect, two UEs **204** may communicate with each other over a wireless unicast sidelink **242**, which may correspond to wireless unicast sidelink **162** in FIG. **1**.

(45) Another optional aspect may include location server **230**, which may be in communication with the NGC **210** to provide location assistance for UEs **204**. The location server **230** can be implemented as a plurality of separate servers (e.g., physically separate servers, different software modules on a single server, different software modules spread across multiple physical servers, etc.), or alternately may each correspond to a single server. The location server **230** can be configured to support one or more location services for UEs **204** that can connect to the location server **230** via the core network, NGC **210**, and/or via the Internet (not illustrated). Further, the location server **230** may be integrated into a component of the core network, or alternatively may be external to the core network.

(46) According to various aspects, FIG. **2B** illustrates another exemplary wireless network structure **250**. For example, an NGC **260** (also referred to as a “5GC”) can be viewed functionally as control plane functions, provided by an access and mobility management function (AMF)/user plane function (UPF) **264**, and user plane functions, provided by a session management function (SMF) **262**, which operate cooperatively to form the core network (i.e., NGC **260**). User plane interface

263 and control plane interface **265** connect the eNB **224** to the NGC **260** and specifically to SMF **262** and AMF/UPF **264**, respectively. In an additional configuration, a gNB **222** may also be connected to the NGC **260** via control plane interface **265** to AMF/UPF **264** and user plane interface **263** to SMF **262**. Further, eNB **224** may directly communicate with gNB **222** via the backhaul connection **223**, with or without gNB direct connectivity to the NGC **260**. In some configurations, the New RAN **220** may only have one or more gNBs **222**, while other configurations include one or more of both eNBs **224** and gNBs **222**. Either gNB **222** or eNB **224** may communicate with UEs **204** (e.g., any of the UEs depicted in FIG. **1**). The base stations of the New RAN **220** communicate with the AMF-side of the AMF/UPF **264** over the N2 interface and the UPF-side of the AMF/UPF **264** over the N3 interface. In an aspect, two UEs **204** may communicate with each other over a wireless unicast sidelink **242**, which may correspond to wireless unicast sidelink **162** in FIG. **1**.

(47) The functions of the AMF include registration management, connection management, reachability management, mobility management, lawful interception, transport for session management (SM) messages between the UE **204** and the SMF **262**, transparent proxy services for routing SM messages, access authentication and access authorization, transport for short message service (SMS) messages between the UE **204** and the short message service function (SMSF) (not shown), and security anchor functionality (SEAF). The AMF also interacts with the authentication server function (AUSF) (not shown) and the UE **204**, and receives the intermediate key that was established as a result of the UE **204** authentication process. In the case of authentication based on a UMTS (universal mobile telecommunications system) subscriber identity module (USIM), the AMF retrieves the security material from the AUSF. The functions of the AMF also include security context management (SCM). The SCM receives a key from the SEAF that it uses to derive access-network specific keys. The functionality of the AMF also includes location services management for regulatory services, transport for location services messages between the UE **204** and the location management function (LMF) **270**, as well as between the New RAN **220** and the LMF **270**, evolved packet system (EPS) bearer identifier allocation for interworking with the EPS, and UE **204** mobility event notification. In addition, the AMF also supports functionalities for non-3GPP access networks.

(48) Functions of the UPF include acting as an anchor point for intra-/inter-RAT mobility (when applicable), acting as an external protocol data unit (PDU) session point of interconnect to the data network (not shown), providing packet routing and forwarding, packet inspection, user plane policy rule enforcement (e.g., gating, redirection, traffic steering), lawful interception (user plane collection), traffic usage reporting, quality of service (QoS) handling for the user plane (e.g., uplink/downlink rate enforcement, reflective QoS marking in the downlink), uplink traffic verification (service data flow (SDF) to QoS flow mapping), transport level packet marking in the uplink and downlink, downlink packet buffering and downlink data notification triggering, and sending and forwarding of one or more “end markers” to the source RAN node.

(49) The functions of the SMF **262** include session management, UE Internet protocol (IP) address allocation and management, selection and control of user plane functions, configuration of traffic steering at the UPF to route traffic to the proper destination, control of part of policy enforcement and QoS, and downlink data notification. The interface over which the SMF **262** communicates with the AMF-side of the AMF/UPF **264** is referred to as the N11 interface.

(50) Another optional aspect may include a LMF **270**, which may be in communication with the NGC **260** to provide location assistance for UEs **204**. The LMF **270** can be implemented as a plurality of separate servers (e.g., physically separate servers, different software modules on a single server, different software modules spread across multiple physical servers, etc.), or alternately may each correspond to a single server. The LMF **270** can be configured to support one or more location services for UEs **204** that can connect to the LMF **270** via the core network, NGC **260**, and/or via the Internet (not illustrated).

(51) FIG. 3 illustrates an example of a wireless communications system 300 that supports unicast sidelink establishment in accordance with aspects of the disclosure. In some examples, wireless communications system 300 may implement aspects of wireless communications systems 100, 200, and 250. Wireless communications system 300 may include a first UE 302 and a second UE 304, which may be examples of any of the UEs described herein. As a specific example, UEs 302 and 304 may correspond to V-UEs 160 in FIG. 1. In the example of FIG. 3, the UE 302 may attempt to establish a unicast connection over a sidelink with UE 304, which may be a V2X communication link between UE 302 and UE 304. Additionally or alternatively, the unicast connection over the sidelink may generally be used for sidelink communications between any two UEs. Thus, the established sidelink connection may correspond to sidelinks 162 and/or 168 in FIG. 1 and/or wireless unicast sidelink 242 in FIGS. 2A and 2B. The sidelink connection may be established for signaling in an omni-directional frequency range (e.g., FR1) as shown in the upper part of the FIG. 3, and a mmW frequency range (e.g., FR2) for data transmission as shown in the lower part of FIG. 3. In some cases, UE 302 may be referred to as an initiating UE that initiates the unicast connection procedure, and UE 304 may be referred to as a target UE that is targeted for the unicast connection procedure by the initiating UE.

(52) For establishing the unicast connection, access stratum (AS) (a functional layer in the UMTS and LTE protocol stacks between the RAN and the UE that is responsible for transporting data over wireless links and managing radio resources, also referred to as “Layer 2” or “L2”) parameters may be configured and negotiated between UE 302 and UE 304. For example, a transmission and reception capability matching may be negotiated between UE 302 and UE 304. Each UE may have different capabilities (e.g., transmission and reception capabilities, 64 quadrature amplitude modulation (QAM), transmission diversity, carrier aggregation (CA) capabilities, supported communications frequency band(s), etc.). In some cases, different services may be supported at the upper layers of corresponding protocol stacks for UE 302 and UE 304. Additionally, a security association may be established between UE 302 and UE 304 for the unicast connection. Unicast traffic may benefit from security protection at a link level (e.g., integrity protection). Security requirements may differ for different wireless communications systems. For example, V2X and Uu systems may have different security requirements (e.g., Uu security does not include confidentiality protection). Additionally, IP configurations (e.g., IP versions, addresses, etc.) may be negotiated for the unicast connection between UE 302 and UE 304.

(53) In some cases, UE 304 may create a service announcement (e.g., a service capability message) to transmit over a cellular network (e.g., cV2X) to assist the unicast connection establishment. Conventionally, UE 302 may identify and locate candidates for unicast communications based on a basic service message (BSM) broadcasted unencrypted by nearby UEs (e.g., UE 304). The BSM may include location information, security and identity information, and vehicle information (e.g., speed, maneuver, size, etc.) for the corresponding UE. However, for different wireless communications systems (e.g., D2D or V2X communications), a discovery channel may not be configured so that UE 302 is able to detect the BSM(s). Accordingly, the service announcement transmitted by UE 304 and other nearby UEs (e.g., a discovery signal) may be an upper layer signal and broadcasted (e.g., in a NR sidelink broadcast). In some cases, UE 304 may include one or more parameters for itself in the service announcement, including connection parameters and/or capabilities it possesses. UE 302 may then monitor for and receive the broadcasted service announcement to identify potential UEs for corresponding unicast connections. In some cases, UE 302 may identify the potential UEs based on the capabilities each UE indicates in their respective service announcements.

(54) The service announcement may include information to assist UE 302 (e.g., or any initiating UE) to identify the UE transmitting the service announcement (UE 304 in the example of FIG. 3). For example, the service announcement may include channel information where direct communication requests may be sent. In some cases, the channel information may be specific to

RAT (e.g., LTE or NR) and may include a resource pool within which UE 302 transmits the communication request. Additionally, the service announcement may include a specific destination address for the UE (e.g., a Layer 2 destination address) if the destination address is different from the current address (e.g., the address of the streaming provider or UE transmitting the service announcement). The service announcement may also include a network or transport layer for UE 302 to transmit a communication request on. For example, the network layer (also referred to as “Layer 3” or “L3”) or the transport layer (also referred to as “Layer 4” or “L4”) may indicate a port number of an application for the UE transmitting the service announcement. In some cases, no IP addressing may be needed if the signaling (e.g., PC5 signaling) carries a protocol (e.g., a real-time transport protocol (RTP)) directly or gives a locally-generated random protocol. Additionally, the service announcement may include a type of protocol for credential establishment and QoS-related parameters.

(55) After identifying a potential unicast connection target (UE 304 in the example of FIG. 3), the initiating UE (UE 302 in the example of FIG. 3) may transmit a connection request 315 to the identified target UE 304. In some cases, the connection request 315 may be a first RRC message transmitted by UE 302 to request a unicast connection with UE 304 (e.g., an RRCDirectConnectionSetupRequest message). For example, the unicast connection may utilize the PC5 interface for the unicast link, and the connection request 315 may be an RRC connection setup request message. Additionally, UE 302 may use a sidelink signaling radio bearer 305 to transport the connection request 315.

(56) After receiving the connection request 315, UE 304 may determine whether to accept or reject the connection request 315. UE 304 may base this determination on a transmission/reception capability, an ability to accommodate the unicast connection over the sidelink, a particular service indicated for the unicast connection, the contents to be transmitted over the unicast connection, or a combination thereof. For example, if UE 302 wants to use a first RAT to transmit or receive data, but UE 304 does not support the first RAT, then UE 304 may reject the connection request 315. Additionally or alternatively, UE 304 may reject the connection request 315 based on being unable to accommodate the unicast connection over the sidelink due to a limited radio resource, a scheduling issue, etc. Accordingly, UE 304 may transmit an indication of whether the request is accepted or rejected in a connection response 320. Similar to UE 302 and the connection request 315, UE 304 may use a sidelink signaling radio bearer 310 to transport the connection response 320. Additionally, the connection response 320 may be a second RRC message transmitted by UE 304 in response to the connection request 315 (e.g., an RRCDirectConnectionResponse message).

(57) In some cases, sidelink signaling radio bearers 305 and 310 may be the same sidelink radio signal bearer or may be separate sidelink signaling radio bearers. Accordingly, a radio link control (RLC) layer acknowledged mode (AM) may be used for sidelink signaling radio bearers 305 and 310. A UE that supports the unicast connection may listen on a logical channel associated with the sidelink signaling radio bearers. In some cases, the AS layer (i.e., Layer 2) may pass information directly through RRC signaling (e.g., control plane) instead of a V2X layer (e.g., data plane).

(58) If the connection response 320 indicates that UE 304 accepted the connection request 315, UE 302 may then transmit a connection establishment 325 message on the sidelink signaling radio bearer 305 to indicate that the unicast connection setup is complete. In some cases, the connection establishment 325 may be a third RRC message (e.g., an RRCDirectConnectionSetupComplete message). Each of the connection request 315, the connection response 320, and the connection establishment 325 may use a basic capability when being transported from one UE to the other UE to enable each UE to be able to receive and decode the corresponding transmission (e.g., RRC message).

(59) Additionally, identifiers may be used for each of the connection request 315, the connection response 320, and the connection establishment 325 (e.g., the RRC signaling). For example, the identifiers may indicate which UE 302/304 is transmitting which message and/or which UE

302/304 the message is intended for. For physical (PHY) channels, the RRC signaling and any subsequent data transmissions may use the same identifier (e.g., Layer 2 IDs). However, for logical channels, the identifiers may be separate for the RRC signaling and for the data transmissions. For example, on the logical channels, the RRC signaling and the data transmissions may be treated differently and have different acknowledgement (ACK) feedback messaging. In some cases, for the RRC messaging, a physical (PHY) layer ACK may be used for ensuring the corresponding messages are transmitted and received properly.

(60) One or more information elements may be included in the connection request **315** and/or the connection response **320** for UE **302** and/or UE **304**, respectively, to enable negotiation of corresponding AS layer parameters for the unicast connection. For example, UE **302** and/or UE **304** may include packet data convergence protocol (PDCP) parameters in a corresponding unicast connection setup message to set a PDCP context for the unicast connection. In some cases, the PDCP context may indicate whether or not PDCP duplication is utilized for the unicast connection. Additionally, UE **302** and/or UE **304** may include RLC parameters when establishing the unicast connection to set an RLC context of the unicast connection. For example, the RLC context may indicate whether an AM (e.g., a reordering timer (t-reordering) is used) or an unacknowledged mode (UM) is used for the RLC layer of the unicast communications.

(61) Additionally, UE **302** and/or UE **304** may include medium access control (MAC) parameters to set a MAC context for the unicast connection. In some cases, the MAC context may enable resource selection algorithms, a hybrid automatic repeat request (HARQ) feedback scheme (e.g., ACK or negative ACK (NACK) feedback), parameters for the HARQ feedback scheme, carrier aggregation, or a combination thereof for the unicast connection. Additionally, UE **302** and/or UE **304** may include PHY layer parameters when establishing the unicast connection to set a PHY layer context for the unicast connection. For example, the PHY layer context may indicate a transmission format (unless transmission profiles are included for each UE **302/304**) and a radio resource configuration (e.g., bandwidth part (BWP), numerology, etc.) for the unicast connection. These information elements may be supported for different frequency range configurations (e.g., FR1 and FR2).

(62) In some cases, a security context may also be set for the unicast connection (e.g., after the connection establishment **325** message is transmitted). Before a security association (e.g., security context) is established between UE **302** and UE **304**, the sidelink signaling radio bearers **305** and **310** may not be protected. After a security association is established, the sidelink signaling radio bearers **305** and **310** may be protected. Accordingly, the security context may enable secure data transmissions over the unicast connection and the sidelink signaling radio bearers **305** and **310**. Additionally, IP layer parameters (e.g., link-local IPv4 or IPv6 addresses) may also be negotiated. In some cases, the IP layer parameters may be negotiated by an upper layer control protocol running after RRC signaling is established (e.g., the unicast connection is established). As noted above, UE **304** may base its decision on whether to accept or reject the connection request **315** on a particular service indicated for the unicast connection and/or the contents to be transmitted over the unicast connection (e.g., upper layer information). The particular service and/or contents may be also indicated by an upper layer control protocol running after RRC signaling is established.

(63) After the unicast connection is established, UE **302** and UE **304** may communicate using the unicast connection over a sidelink **330**, where sidelink data **335** is transmitted between the two UEs **302** and **304**. The sidelink **330** may correspond to sidelinks **162** and/or **168** in FIG. **1** and/or wireless unicast sidelink **242** in FIGS. **2A** and **2B**. In some cases, the sidelink data **335** may include RRC messages transmitted between the two UEs **302** and **304**. To maintain this unicast connection on sidelink **330**, UE **302** and/or UE **304** may transmit a keep alive message (e.g., RRCDirectLinkAlive message, a fourth RRC message, etc.). In some cases, the keep alive message may be triggered periodically or on-demand (e.g., event-triggered). Accordingly, the triggering and transmission of the keep alive message may be invoked by UE **302** or by both UE **302** and UE **304**.

Additionally or alternatively, a MAC control element (CE) (e.g., defined over sidelink 330) may be used to monitor the status of the unicast connection on sidelink 330 and maintain the connection. When the unicast connection is no longer needed (e.g., UE 302 travels far enough away from UE 304), either UE 302 and/or UE 304 may start a release procedure to drop the unicast connection over sidelink 330. Accordingly, subsequent RRC messages may not be transmitted between UE 302 and UE 304 on the unicast connection.

(64) FIG. 4 is a block diagram illustrating various components of an exemplary UE 400, according to aspects of the disclosure. In an aspect, the UE 400 may correspond to any of the UEs described herein. As a specific example, the UE 400 may be a V-UE, such as V-UE 160 in FIG. 1. For the sake of simplicity, the various features and functions illustrated in the block diagram of FIG. 4 are connected together using a common data bus that is meant to represent that these various features and functions are operatively coupled together. Those skilled in the art will recognize that other connections, mechanisms, features, functions, or the like, may be provided and adapted as necessary to operatively couple and configure an actual UE. Further, it is also recognized that one or more of the features or functions illustrated in the example of FIG. 4 may be further subdivided, or two or more of the features or functions illustrated in FIG. 4 may be combined.

(65) The UE 400 may include at least one transceiver 404 connected to one or more antennas 402 for communicating with other network nodes, such as V-UEs (e.g., V-UEs 160), infrastructure access points (e.g., roadside access point 164), P-UEs (e.g., UEs 104), base stations (e.g., base stations 102), etc., via at least one designated RAT (e.g., C-V2X or IEEE 802.11p) over one or more communication links (e.g., communication links 120, sidelinks 162, 166, 168, mmW communication link 184). The transceiver 404 may be variously configured for transmitting and encoding signals (e.g., messages, indications, information, and so on), and, conversely, for receiving and decoding signals (e.g., messages, indications, information, pilots, and so on) in accordance with the designated RAT.

(66) As used herein, a “transceiver” may include at least one transmitter and at least one receiver in an integrated device (e.g., embodied as a transmitter circuit and a receiver circuit of a single communication device) in some implementations, may comprise a separate transmitter device and a separate receiver device in some implementations, or may be embodied in other ways in other implementations. In an aspect, a transmitter may include or be coupled to a plurality of antennas (e.g., antenna(s) 402), such as an antenna array, that permits the UE 400 to perform transmit “beamforming,” as described herein. Similarly, a receiver may include or be coupled to a plurality of antennas (e.g., antenna(s) 402), such as an antenna array, that permits the UE 400 to perform receive beamforming, as described herein. In an aspect, the transmitter(s) and receiver(s) may share the same plurality of antennas (e.g., antenna(s) 402), such that the UE 400 can only receive or transmit at a given time, not both at the same time. In some cases, a transceiver may not provide both transmit and receive functionalities. For example, a low functionality receiver circuit may be employed in some designs to reduce costs when providing full communication is not necessary (e.g., a receiver chip or similar circuitry simply providing low-level sniffing).

(67) The UE 400 may also include a satellite positioning service (SPS) receiver 406. The SPS receiver 406 may be connected to the one or more antennas 402 for receiving satellite signals. The SPS receiver 406 may comprise any suitable hardware and/or software for receiving and processing SPS signals, such as global positioning system (GPS) signals. The SPS receiver 406 requests information and operations as appropriate from the other systems, and performs the calculations necessary to determine the UE's 400 position using measurements obtained by any suitable SPS algorithm.

(68) One or more sensors 408 may be coupled to a processing system 410 to provide information related to the state and/or environment of the UE 400, such as speed, heading (e.g., compass heading), headlight status, gas mileage, etc. By way of example, the one or more sensors 408 may include a speedometer, a tachometer, an accelerometer (e.g., a microelectromechanical systems

(MEMS) device), a gyroscope, a geomagnetic sensor (e.g., a compass), an altimeter (e.g., a barometric pressure altimeter), etc.

(69) The processing system **410** may include one or more microprocessors, microcontrollers, ASICs, processing cores, digital signal processors, or the like that provide processing functions, as well as other calculation and control functionality. The processing system **410** may include any form of logic suitable for performing, or causing the components of the UE **400** to perform, at least the techniques provided herein.

(70) The processing system **410** may also be coupled to a memory **414** for storing data and software instructions for executing programmed functionality within the UE **400**. The memory **414** may be on-board the processing system **410** (e.g., within the same integrated circuit (IC) package), and/or the memory **414** may be external to the processing system **410** and functionally coupled over a data bus.

(71) The UE **400** may include a user interface **450** that provides any suitable interface systems, such as a microphone/speaker **452**, keypad **454**, and display **456** that allow user interaction with the UE **400**. The microphone/speaker **452** provides for voice communication services with the UE **400**. The keypad **454** comprises any suitable buttons for user input to the UE **400**. The display **456** comprises any suitable display, such as, for example, a backlit liquid crystal display (LCD), and may further include a touch screen display for additional user input modes.

(72) In an aspect, the UE **400** may include a sidelink manager **470** coupled to the processing system **410**. The sidelink manager **470** (which may correspond to sidelink manager **170** in FIG. **1**) may be a hardware, software, or firmware component that, when executed, causes the UE **400** to perform the operations described herein. For example, the sidelink manager **470** may be a software module stored in memory **414** and executable by the processing system **410**. As another example, the sidelink manager **470** may be a hardware circuit (e.g., an ASIC, an FPGA, etc.) within the UE **400**.

(73) V2X communications in NR can occur in both sub-6 GHz frequency ranges (e.g., FR1) and mmW frequency ranges (e.g., FR2). For mmW unicast D2D or V2V communications, the initial communication establishment between neighboring devices (e.g., generally described herein as V-UEs solely for illustration and not limitation) can be accomplished respectively in two different approaches in two deployment options, a standalone (SA) deployment and a non-standalone (NSA) deployment. In an SA deployment, only the mmW frequency band is used. A mmW radio sidelink can be established between two V-UEs without the support of any other previously established communication link that may be, for example, in a different frequency band or in a different RAT.

(74) Alternatively, establishment of the unicast mmW sidelink, including radio bearer establishment and associated QoS negotiation, can occur in an NSA deployment option. In an NSA deployment option, V-UEs can support communication in both FR1 and FR2. Thus, it is possible that the D2D or V2V mmW sidelink in FR2 (which uses a specific type of radio bearer configured for communication in mmW) is established with the support of a previously established direct link/connection (e.g., sidelink **330** where sidelink **330** is established in FR1) between the two V-UEs in FR1 with PC5-RRC signaling and/or device-to-device discovery mechanisms. In this approach, for example, one or more signaling radio bearers (SRBs) may be established over the FR1 sidelink first, and then one or more data radio bearers (DRBs) may be established over the FR2 sidelink.

(75) Radio bearers are logical communication channels offered by Layer 2 (which includes a service data adaptation protocol (SDAP) layer, a PDCP layer, an RLC layer, and a MAC layer) to higher layers (e.g., the RRC and AS layers) for the transfer of either user data (on DRBs) for a communication session, or control data (on SRBs) for the communication session. An SRB carries dedicated control channel (DCCH) signaling data for a communication session. (A DCCH is a point-to-point dedicated channel for transmitting control information between a UE and the network or between the UE and another UE.) An SRB is used during connection establishment to

deliver control signaling while on the connection. During connection establishment, an RRC Connection Setup procedure establishes the SRB. The SRB is then used to send all subsequent control signaling (e.g., physical layer, MAC layer, and other access layer control information) to start the desired communication session and establish the DRBs for the communication session. A DRB carries dedicated traffic channel (DTCH) data for a communication session. (A DTCH is a point-to-point dedicated channel for transmitting user/application data/traffic between a UE and the network or between the UE and another UE.) Establishment of the DRB(s) is achieved using a radio bearer (RB) Setup procedure on the SRB. The RB Setup procedure configures how both the DCCH and DTCH will be carried on the respective radio bearers.

(76) Using the SRB, the configuration of the different access protocol layers is of a semi-static nature. Physical layer control is of a more dynamic nature in order to control resource allocation, in terms of time, frequency, space, and/or power. The access protocol layer configurations over the SRB occur at the time the radio bearer is being set up. The physical layer control and adaptation occur at the time the data is being exchanged.

(77) The various aspects disclosed herein include techniques for establishing a mmW D2D data session in an NSA deployment. More specifically, the various aspects disclosed include techniques for establishing a DRB in a mmW band (e.g., FR2) with the support of a previously established communication session in an FR1 band. Given the nature of mmW communications (e.g., short range, high propagation loss), the problems related to beam discovery (e.g., the determination of the BPL that best serves the bidirectional communication between the two UEs) need to be solved along with the problem of establishing the radio bearers for the D2D/P2P/V2X unicast link.

(78) The various aspects disclosed herein also include techniques for establishing the unicast radio bearers for a mmW sidelink in an NSA deployment option. Use of a previously established FR1 communication link makes the establishment of QoS-based FR2 radio bearers possible for mmW D2D or V2X unicast communications.

(79) FIG. 5 illustrates an exemplary flow between an initiator device **520** and a target device **530**, according to aspects of the disclosure. The devices **520** and **530** may be UEs (e.g., any of the UEs described herein). In the example of FIG. 5, because the FR2 sidelink described below is established in NSA mode, the FR2 sidelink is established after RRC setup of a sidelink in FR1, and this previously established sidelink in FR1 is used to establish the new sidelink in FR2.

(80) At **502**, a D2D discovery procedure can be performed at an application layer. For example, a D2D (e.g., V2V, V2X, etc.) peer discovery procedure can be performed in FR1 via broadcast/groupcast, as described above with reference to FIG. 3, using V2V for illustration. For example, the initiator device **520** may identify and locate candidate devices for unicast communications based on a BSM broadcasted by nearby UEs (e.g., target device **530**). The BSM may include location information (e.g., GPS coordinates) of the broadcasting or groupcasting UE, security and identity information, and vehicle information (e.g., speed, maneuver, size, etc.) for the corresponding device, as appropriate. This service announcement may be an upper layer signal.

(81) At **504**, the devices **520** and **530** establish an RRC connection and an SRB on a unicast link in FR1 via a D2D RRC interface (e.g., an RRC procedure over the PC5 interface) and D2D signaling (e.g., PC5-S), as discussed above with reference to FIG. 3. As discussed above with reference to FIG. 3, a PC5 unicast RRC establishment in FR1 may also include a capability exchange between devices **520** and **530**. Such capabilities may include, for example, whether the devices **520** and **530** support an FR2 band and simultaneous transmission and reception in both FR1 and FR2. As used herein, the term “simultaneous” communication on the first frequency band and the second frequency band means that a device is capable of communicating over both frequency bands during overlapping times, but does not require that any device is sending and/or receiving data on both frequency bands at the same time.

(82) At **506**, the initiator device **520** determines that it has a new data flow for target device **530** that needs a new sidelink radio bearer (SLRB) because, for example, the new data flow requires a

certain QoS (e.g., a certain data rate, throughput, latency, etc.). Based on configuration information (e.g., from a network entity, such as a serving base station or an application server over a Uu interface), negotiation (e.g., with the target device **530** over a PC5-RRC interface or with a network entity over a Uu interface), or decision to support a specific QoS-to-SLRB mapping, the initiator device **520** determines that the new SLRB is to be in FR2. In an aspect, the configuration or QoS-to-SLRB mapping may indicate that for a data flow having a QoS requirement in terms of latency or throughput above some threshold, the initiator device **520** will attempt to establish an additional sidelink in FR2. In an aspect, a negotiation with the network entity or the target device **530** may include the initiator device **520** providing options to the target device **530** and the target device **530** making the decision.

(83) At **508**, having determined to establish an SLRB sidelink in FR2 with target device **530**, the initiator device **520** sends an RRC reconfiguration message (e.g., an RRCDirectConnectionReconfiguration message) to the target device **530** over the previously established SRB. In addition to normal PDCP/RLC/MAC layer configuration, the radio bearer configuration process includes mmW physical layer configurations for beam direction(s) and resource, timing, location, and/or sequence ID parameters for L1/L2 layer procedures.

(84) At **510**, the devices **520** and **530** perform PHY/MAC procedures in FR2 for the new mmW sidelink. The devices **520** and **530** perform PHY/MAC procedures in FR2 to determine the serving BPL and synchronization and to initiate a mmW QoS-based V2V unicast link as requested in stage **508**. The PHY/MAC procedures may include determining the direction of the transmit beam(s) used by the initiator device **520** and the receive beam(s) used by the target device **530**. Specifically, in stages **502** and/or **504**, the devices **520** and **530** exchange their geographic locations (e.g., GPS coordinates) and possibly information describing their current paths (e.g., direction of travel, speed, etc.). Based on these known locations, the devices **520** and **530** can aim their respective transmit and receive beam(s) as close as possible to the estimated direction of the other device. That is, a transmitter (e.g., initiator device **520**) can only aim a transmit beam in certain directions, and therefore, may not be able to aim a transmit beam exactly at the estimated location of the target device **530**. Instead, it selects the transmit beam(s) that can be directed in the direction(s) closest to the estimated direction of the target device **530**. The same applies to receive beams of a receiver (e.g., target device **530**).

(85) At **512**, the initiator device **520** sends an RRC reconfiguration complete message (e.g., RRCDirectConnectionReconfigurationComplete) to the target device **530** informing the target device **530** that the FR2 sidelink has been established. The initiator device **520** can then send the additional data flow (i.e., having the certain QoS requirement) over the newly established FR2 sidelink. In addition, data can flow in the reverse direction, if desired, through reflective QoS.

(86) In an alternative aspect, RRC establishment could occur in FR2 instead of FR1, and the RRC session could be used to establish a data-only sidelink in FR1. In such a case, an RRC session would be established in FR2, and the RRC reconfiguration messages would be sent on FR2. In this alternative, the SRB would be established in the FR2 band and a new DRB would be established in the FR1 band.

(87) It will be appreciated that in the first aspect discussed above, an FR2 band is used after the RRC setup messages in the FR1 band to establish the new FR2 DRB, and data is communicated in FR2 while control signaling is communicated on the SRB in FR1. In the first aspect, the signaling on the SRB in FR1 is used to establish the new mmW physical layer channel, and there is also a data session change as a new data flow (on a DRB) is added in this new band. In the alternative aspect, signaling on an SRB in FR2 can be used to establish a new FR1 DRB. Additionally, as noted above, it will be appreciated that although FIG. 5 has been described generally in terms of a V2V procedure, it is equally applicable to any D2D connection.

(88) As will be appreciated, the aspects described above with reference to FIG. 5 provide the advantage of speeding up BPL acquisition and resource utilization in the FR2 band by using the

information received over the previously established FR1 sidelink (e.g., at **504** of FIG. 5) and/or discovery procedure (e.g., at **502** of FIG. 5). For example, by using the GPS locations and/or shared path information from both devices, the initiator and target devices **520** and **530** are advantageously able to more accurately estimate initial directions for the transmit and receive beams, resulting in more effectively sweeping or scanning on a subset of transmit and receive beams, rather than having to perform full beam sweeps/scans. Further, besides beam sweeping/scanning over a limited set of beams to speed up BPL acquisition, air interface resource utilization for transmit beam sweeping can be controlled from the supporting PC5 link in the FR1 band to advantageously minimize resource utilization and collisions in the FR2 band.

(89) FIG. 6 illustrates an exemplary flow **600** for wireless communication, according to aspects of the disclosure. The flow **600** may be performed by a first UE (e.g., an initiator device), which may correspond to any of the UEs described herein.

(90) At **610**, the first UE establishes an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection. In an aspect, operation **610** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(91) At **620**, the first UE sends, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band. In an aspect, operation **620** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(92) At **630**, the first UE configures the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band. In an aspect, operation **630** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(93) In the flow **600**, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the configuring at **630** may include configuring the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the first frequency band.

(94) In the flow **600**, the flow **600** may further include (not shown) establishing the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(95) In the flow **600**, the flow **600** may further include (not shown) receiving, from the second UE, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and sending user data for the communication session to the second UE over the DRB on the second frequency band.

(96) In the flow **600**, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the first UE may send the first RRC message before the DRB is configured on the second frequency band and receive the second RRC message after the DRB is configured.

(97) In the flow **600**, where user data is sent to the second UE over the DRB on the second frequency band, the flow **600** may also include (not shown) sending user data for the communication session to the second UE over a DRB on the first frequency band.

(98) In the flow **600**, where user data is sent to the second UE over the DRB on the first frequency

band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(99) In the flow **600**, the flow **600** may further include (not shown) receiving, from the second UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and reconfiguring the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(100) In the flow **600**, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(101) In the flow **600**, the first UE may send the first RRC message over the first frequency band as a groupcast or a broadcast.

(102) In the flow **600**, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(103) In the flow **600**, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(104) In the flow **600**, the flow **600** may also include (not shown) receiving, over the SRB, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the flow **600** may include (not shown) sending, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(105) In the flow **600**, the flow **600** may also include (not shown) determining to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination at the first UE, or any combination thereof.

(106) In the flow **600**, where the configuration is negotiated with the second UE, the negotiation with the second UE may include (not shown) sending, to the second UE, an option to use the second frequency band for the data flow, and receiving, from the second UE, an indication to use the second frequency band for the data flow.

(107) In the flow **600**, the first UE may receive a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(108) In the flow **600**, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(109) FIG. 7 illustrates an exemplary flow **700** for wireless communication, according to aspects of the disclosure. The flow **700** may be performed by a first UE (e.g., an initiator device), which may correspond to any of the UEs described herein.

(110) At **710**, the first UE establishes an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection. In an aspect, operation **710** may be performed by transceiver(s)

404, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(111) At **720**, the first UE sends, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band. In an aspect, operation **720** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(112) At **730**, the first UE configures the DRB on the second frequency band based on the one or more parameters in the first RRC message. In an aspect, operation **730** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(113) In the flow **700**, the configuring at **730** may include configuring the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(114) In the flow **700**, the flow **700** may further include (not shown) establishing the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(115) In the flow **700**, the flow **700** may further include (not shown) receiving, from the second UE, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and sending user data for the communication session to the second UE over the DRB on the second frequency band.

(116) In the flow **700**, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the first UE may send the first RRC message before the DRB is configured on the second frequency band and receive the second RRC message after the DRB is configured.

(117) In the flow **700**, where user data is sent to the second UE over the DRB on the second frequency band, the flow **700** may also include (not shown) sending user data for the communication session to the second UE over a DRB on the first frequency band.

(118) In the flow **700**, where user data is sent to the second UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(119) In the flow **700**, the flow **700** may further include (not shown) receiving, from the second UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and reconfiguring the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(120) In the flow **700**, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(121) In the flow **700**, the first UE may send the first RRC message over the first frequency band as a groupcast or a broadcast.

(122) In the flow **700**, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a roadsign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(123) In the flow **700**, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(124) In the flow **700**, the flow **700** may also include (not shown) receiving, over the SRB, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the flow **700** may include (not shown) sending, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(125) In the flow **700**, the flow **700** may also include (not shown) determining to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination at the first UE, or any combination thereof.

(126) In the flow **700**, where the configuration is negotiated with the second UE, the negotiation with the second UE may include (not shown) sending, to the second UE, an option to use the second frequency band for the data flow, and receiving, from the second UE, an indication to use the second frequency band for the data flow.

(127) In the flow **700**, the first UE may receive a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(128) In the flow **700**, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(129) FIG. **8** illustrates an exemplary flow **800** for wireless communication, according to aspects of the disclosure. The flow **800** may be performed by a second UE (e.g., a target device), which may correspond to any of the UEs described herein.

(130) At **810**, the second UE establishes an SRB for a communication session with a first UE (e.g., an initiator device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection. In an aspect, operation **810** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(131) At **820**, the second UE receives, from the first UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band. In an aspect, operation **820** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(132) At **830**, the second UE configures the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band. In an aspect, operation **830** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(133) In the flow **800**, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the configuring at **830** may include configuring the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the

first frequency band.

(134) In the flow **800**, the flow **800** may further include (not shown) establishing the RRC connection for the communication session with the first UE, as described above with reference to **504** of FIG. 5.

(135) In the flow **800**, the flow **800** may further include (not shown) sending, to the first UE, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and receiving user data for the communication session from the first UE over the DRB on the second frequency band.

(136) In the flow **800**, where the second UE sends the second RRC message confirming that the DRB has been successfully configured, the second UE may receive the first RRC message before the DRB is configured on the second frequency band and send the second RRC message after the DRB is configured.

(137) In the flow **800**, where user data is received from the first UE over the DRB on the second frequency band, the flow **800** may also include (not shown) receiving user data for the communication session from the first UE over a DRB on the first frequency band.

(138) In the flow **800**, where user data is received from the first UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(139) In the flow **800**, the flow **800** may further include (not shown) sending, to the first UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and reconfiguring the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(140) In the flow **800**, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(141) In the flow **800**, the second UE may receive the first RRC message over the first frequency band as a groupcast or a broadcast.

(142) In the flow **800**, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(143) In the flow **800**, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(144) In the flow **800**, the flow **800** may also include (not shown) sending, over the SRB, capability information to the first UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the flow **800** may include (not shown) receiving, over the SRB, capability information from the first UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(145) In the flow **800**, the second UE may send a user data flow to the first UE over the DRB based on a reflective QoS procedure.

(146) In the flow **800**, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from

the first UE to the second UE.

(147) FIG. 9 illustrates an exemplary flow **900** for wireless communication, according to aspects of the disclosure. The flow **900** may be performed by a second UE (e.g., a target device), which may correspond to any of the UEs described herein.

(148) At **910**, the second UE establishes an SRB for a communication session with a first UE on a first frequency band based on an RRC connection. In an aspect, operation **910** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(149) At **920**, the second UE receives, from the first UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band. In an aspect, operation **920** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(150) At **930**, the second UE configures the DRB on the second frequency band based on the one or more parameters in the first RRC message. In an aspect, operation **930** may be performed by transceiver(s) **404**, processing system **410**, memory **414**, and/or sidelink manager **470**, any or all of which may be considered means for performing this operation.

(151) In the flow **900**, the configuring at **930** may include configuring the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(152) In the flow **900**, the flow **900** may further include (not shown) establishing the RRC connection for the communication session with the first UE, as described above with reference to **504** of FIG. 5.

(153) In the flow **900**, the flow **900** may further include (not shown) sending, to the first UE, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and receiving user data for the communication session from the first UE over the DRB on the second frequency band.

(154) In the flow **900**, where the second UE sends the second RRC message confirming that the DRB has been successfully configured, the second UE may receive the first RRC message before the DRB is configured on the second frequency band and send the second RRC message after the DRB is configured.

(155) In the flow **900**, where user data is received from the first UE over the DRB on the second frequency band, the flow **900** may also include (not shown) receiving user data for the communication session from the first UE over a DRB on the first frequency band.

(156) In the flow **900**, where user data is received from the first UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(157) In the flow **900**, the flow **900** may further include (not shown) sending, to the first UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and reconfiguring the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(158) In the flow **900**, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(159) In the flow **900**, the second UE may receive the first RRC message over the first frequency band as a groupcast or a broadcast.

(160) In the flow **900**, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(161) In the flow **900**, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(162) In the flow **900**, the flow **900** may also include (not shown) sending, over the SRB, capability information to the first UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the flow **900** may include (not shown) receiving, over the SRB, capability information from the first UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(163) In the flow **900**, the second UE may send a user data flow to the first UE over the DRB based on a reflective QoS procedure.

(164) In the flow **900**, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(165) FIG. **10** illustrates an exemplary UE apparatus **1000**, which may correspond to any of the UEs described herein. The UE apparatus **1000** may include a memory **1010** (which may correspond to memory **414**), at least one transceiver **1020** (which may correspond to transceiver(s) **404**), at least one processor **1030** (which may correspond to processing system **410**), and a sidelink manager **1040** (which may correspond to sidelink manager **470**).

(166) The sidelink manager **1040** may be a hardware, software, or firmware component that, when executed, causes the UE apparatus **1000** to perform the operations described herein. For example, the sidelink manager **1040** may be a software module stored in memory **1010** and executable by the at least one processor **1030**. As another example, the sidelink manager **1040** may be a hardware circuit (e.g., an ASIC, a field programmable gate array (FPGA), etc.) coupled to or integrated into the at least one processor **1030**.

(167) The memory **1010**, the at least one transceiver **1020**, and the at least one processor **1030** may be communicatively coupled to each other over a data bus **1050**. Where the sidelink manager **1040** is separate from the memory **1010** and the at least one processor **1030**, the sidelink manager **1040** may be communicatively coupled to the other components of the UE apparatus **1000** over the data bus **1050**.

(168) In an aspect, the UE apparatus **1000** may be a first UE (e.g., an initiator device). In a first example aspect (which may correspond to the technique illustrated in FIG. **6**), where the UE apparatus **1000** is a first UE, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to establish, via the at least one transceiver **1020**, an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(169) In the first example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to cause the at least one transceiver **1020** to send, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band.

(170) In the first example aspect, the at least one processor **1030** and/or the sidelink manager **1040**

may be further configured to configure, via the at least one transceiver **1020**, the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(171) In the first example aspect, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB may include the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the first frequency band.

(172) In a second example aspect (which may correspond to the technique illustrated in FIG. 7), where the UE apparatus **1000** is a first UE, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to establish, via the at least one transceiver **1020**, an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(173) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to cause the at least one transceiver **1020** to send, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band.

(174) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to configure, via the at least one transceiver **1020**, the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(175) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB may include the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(176) In both the first and second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to establish, via the at least one transceiver **1020**, the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(177) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to receive, from the second UE via the at least one transceiver **1020**, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and to send user data for the communication session to the second UE over the DRB on the second frequency band.

(178) In both the first and second example aspects, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the at least one processor **1030** and/or the sidelink manager **1040** may cause the at least one transceiver **1020** to send the first RRC message before the DRB is configured on the second frequency band and to receive, via the at least one transceiver **1020**, the second RRC message after the DRB is configured.

(179) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the second frequency band, the at least one processor **1030** and/or the sidelink manager **1040** may also be configured to cause the at least one transceiver **1020** to send user data for the communication session to the second UE over a DRB on the first frequency band.

(180) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be

different from a QoS for the DRB on the second frequency band.

(181) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to receive, from the second UE via the at least one transceiver **1020**, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and to reconfigure the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(182) In both the first and second example aspects, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(183) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may cause the at least one transceiver **1020** to send the first RRC message over the first frequency band as a groupcast or a broadcast.

(184) In both the first and second example aspects, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(185) In both the first and second example aspects, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(186) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to receive, over the SRB via the at least one transceiver **1020**, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to cause the at least one transceiver **1020** to send, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(187) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination at the first UE, or any combination thereof.

(188) In both the first and second example aspects, where the configuration is negotiated with the second UE, the negotiation with the second UE may include the at least one processor **1030** and/or the sidelink manager **1040** causing the at least one transceiver **1020** to send, to the second UE, an option to use the second frequency band for the data flow, and to receive, from the second UE via the at least one transceiver **1020**, an indication to use the second frequency band for the data flow.

(189) In both the first and second example aspects, the first UE may receive, via the at least one transceiver **1020**, a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(190) In both the first and second example aspects, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of

the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(191) In an aspect, the UE apparatus **1000** may be a second UE (e.g., a target device). In a first example aspect (which may correspond to the technique illustrated in FIG. 8), where the UE apparatus **1000** is a second UE, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to establish, via the at least one transceiver **1020**, an SRB for a communication session with a first UE (e.g., an initiator device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(192) In the first example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to receive, from the first UE over the SRB on the first frequency band, via the at least one transceiver **1020**, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band.

(193) In the first example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to configure, via the at least one transceiver **1020**, the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(194) In the first example aspect, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB may include the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the first frequency band.

(195) In a second example aspect (which may correspond to the technique illustrated in FIG. 9), where the UE apparatus **1000** is a second UE, the at least one processor **1030** and/or the sidelink manager **1040** may be configured to establish, via the at least one transceiver **1020**, an SRB for a communication session with a first UE on a first frequency band based on an RRC connection.

(196) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to receive, from the first UE over the SRB on the first frequency band, via the at least one transceiver **1020**, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band.

(197) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to configure, via the at least one transceiver **1020**, the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(198) In the second example aspect, the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB may include the at least one processor **1030** and/or the sidelink manager **1040** being configured to configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(199) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to establish, via the at least one transceiver **1020**, the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(200) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to receive, from the second UE via the at least one transceiver **1020**, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second

frequency band, and to send user data for the communication session to the second UE over the DRB on the second frequency band.

(201) In both the first and second example aspects, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the at least one processor **1030** and/or the sidelink manager **1040** may cause the at least one transceiver **1020** to send the first RRC message before the DRB is configured on the second frequency band and to receive, via the at least one transceiver **1020**, the second RRC message after the DRB is configured.

(202) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the second frequency band, the at least one processor **1030** and/or the sidelink manager **1040** may also be configured to cause the at least one transceiver **1020** to send user data for the communication session to the second UE over a DRB on the first frequency band.

(203) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(204) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to receive, from the second UE via the at least one transceiver **1020**, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and to reconfigure the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(205) In both the first and second example aspects, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(206) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may cause the at least one transceiver **1020** to send the first RRC message over the first frequency band as a groupcast or a broadcast.

(207) In both the first and second example aspects, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(208) In both the first and second example aspects, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(209) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to receive, over the SRB via the at least one transceiver **1020**, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band.

Alternatively, the at least one processor **1030** and/or the sidelink manager **1040** may further be configured to cause the at least one transceiver **1020** to send, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(210) In both the first and second example aspects, the at least one processor **1030** and/or the sidelink manager **1040** may be further configured to determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination

at the first UE, or any combination thereof.

(211) In both the first and second example aspects, where the configuration is negotiated with the second UE, the negotiation with the second UE may include the at least one processor **1030** and/or the sidelink manager **1040** causing the at least one transceiver **1020** to send, to the second UE, an option to use the second frequency band for the data flow, and to receive, from the second UE via the at least one transceiver **1020**, an indication to use the second frequency band for the data flow.

(212) In both the first and second example aspects, the first UE may receive, via the at least one transceiver **1020**, a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(213) In both the first and second example aspects, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(214) FIG. **11** illustrates an exemplary UE apparatus **1100**, which may correspond to any of the UEs described herein. The UE apparatus **1100** may include means for storing **1110** (which may correspond to memory **414**), means for transceiving **1120** (which may correspond to transceiver(s) **404**), means for processing **1130** (which may correspond to processing system **410**), and a sidelink manager **1140** (which may correspond to sidelink manager **470**).

(215) The sidelink manager **1140** may be a hardware, software, or firmware component that, when executed, causes the UE apparatus **1100** to perform the operations described herein. For example, the sidelink manager **1140** may be a software module stored in means for storing **1110** and executable by the means for processing **1130**. As another example, the sidelink manager **1140** may be a hardware circuit (e.g., an ASIC, a field programmable gate array (FPGA), etc.) coupled to or integrated into the means for processing **1130**.

(216) The means for storing **1110**, the means for transceiving **1120**, and the means for processing **1130** may be communicatively coupled to each other over a data bus **1150**. Where the sidelink manager **1140** is separate from the means for storing **1110** and the means for processing **1130**, the sidelink manager **1140** may be communicatively coupled to the other components of the UE apparatus **1100** over the data bus **1150**.

(217) In an aspect, the UE apparatus **1100** may be a first UE (e.g., an initiator device). In a first example aspect (which may correspond to the technique illustrated in FIG. **6**), where the UE apparatus **1100** is a first UE, the means for processing **1130** and/or the sidelink manager **1140** may be configured to establish, via the means for transceiving **1120**, an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(218) In the first example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to cause the means for transceiving **1120** to send, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band.

(219) In the first example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to configure, via the means for transceiving **1120**, the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the second UE over the first frequency band.

(220) In the first example aspect, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB may include the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB

based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the first frequency band.

(221) In a second example aspect (which may correspond to the technique illustrated in FIG. 7), where the UE apparatus **1100** is a first UE, the means for processing **1130** and/or the sidelink manager **1140** may be configured to establish, via the means for transceiving **1120**, an SRB for a communication session with a second UE (e.g., a target device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(222) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to cause the means for transceiving **1120** to send, to the second UE over the SRB on the first frequency band, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band.

(223) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to configure, via the means for transceiving **1120**, the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(224) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB may include the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(225) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to establish, via the means for transceiving **1120**, the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(226) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to receive, from the second UE via the means for transceiving **1120**, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and to send user data for the communication session to the second UE over the DRB on the second frequency band.

(227) In both the first and second example aspects, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the means for processing **1130** and/or the sidelink manager **1140** may cause the means for transceiving **1120** to send the first RRC message before the DRB is configured on the second frequency band and to receive, via the means for transceiving **1120**, the second RRC message after the DRB is configured.

(228) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the second frequency band, the means for processing **1130** and/or the sidelink manager **1140** may also be configured to cause the means for transceiving **1120** to send user data for the communication session to the second UE over a DRB on the first frequency band.

(229) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(230) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to receive, from the second UE via the means for transceiving **1120**, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and to reconfigure the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC

message.

(231) In both the first and second example aspects, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(232) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may cause the means for transceiving **1120** to send the first RRC message over the first frequency band as a groupcast or a broadcast.

(233) In both the first and second example aspects, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(234) In both the first and second example aspects, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(235) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to receive, over the SRB via the means for transceiving **1120**, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to cause the means for transceiving **1120** to send, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(236) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination at the first UE, or any combination thereof.

(237) In both the first and second example aspects, where the configuration is negotiated with the second UE, the negotiation with the second UE may include the means for processing **1130** and/or the sidelink manager **1140** causing the means for transceiving **1120** to send, to the second UE, an option to use the second frequency band for the data flow, and to receive, from the second UE via the means for transceiving **1120**, an indication to use the second frequency band for the data flow.

(238) In both the first and second example aspects, the first UE may receive, via the means for transceiving **1120**, a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(239) In both the first and second example aspects, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(240) In an aspect, the UE apparatus **1100** may be a second UE (e.g., a target device). In a first example aspect (which may correspond to the technique illustrated in FIG. 8), where the UE apparatus **1100** is a second UE, the means for processing **1130** and/or the sidelink manager **1140** may be configured to establish, via the means for transceiving **1120**, an SRB for a communication

session with a first UE (e.g., an initiator device, which may correspond to any of the UEs described herein) on a first frequency band based on an RRC connection.

(241) In the first example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be configured to receive, from the first UE over the SRB on the first frequency band, via the means for transceiving **1120**, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band.

(242) In the first example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be configured to configure, via the means for transceiving **1120**, the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure performed with the first UE over the first frequency band.

(243) In the first example aspect, the first RRC message may include one or more parameters for establishing the DRB on the second frequency band. In this aspect, the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB may include the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure performed with the second UE in the first frequency band.

(244) In a second example aspect (which may correspond to the technique illustrated in FIG. 9), where the UE apparatus **1100** is a second UE, the means for processing **1130** and/or the sidelink manager **1140** may be configured to establish, via the means for transceiving **1120**, an SRB for a communication session with a first UE on a first frequency band based on an RRC connection.

(245) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to receive, from the first UE over the SRB on the first frequency band, via the means for transceiving **1120**, a first RRC message (e.g., an RRC sidelink reconfiguration message, such as an RRCDirectConnectionReconfiguration message) to establish a DRB for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band.

(246) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to configure, via the means for transceiving **1120**, the DRB on the second frequency band based on the one or more parameters in the first RRC message.

(247) In the second example aspect, the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB may include the means for processing **1130** and/or the sidelink manager **1140** being configured to configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure performed with the second UE in the first frequency band.

(248) In both the first and second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to establish, via the means for transceiving **1120**, the RRC connection for the communication session with the second UE, as described above with reference to **504** of FIG. 5.

(249) In both the first and second example aspect, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to receive, from the second UE via the means for transceiving **1120**, a second RRC message (e.g., an RRC sidelink reconfiguration complete message, such as an RRCDirectConnectionReconfigurationComplete message) on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band, and to send user data for the communication session to the second UE over the DRB on the second frequency band.

(250) In both the first and second example aspect, where the first UE receives the second RRC message confirming that the DRB has been successfully configured, the means for processing **1130** and/or the sidelink manager **1140** may cause the means for transceiving **1120** to send the first RRC

message before the DRB is configured on the second frequency band and to receive, via the means for transceiving **1120**, the second RRC message after the DRB is configured.

(251) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the second frequency band, the means for processing **1130** and/or the sidelink manager **1140** may also be configured to cause the means for transceiving **1120** to send user data for the communication session to the second UE over a DRB on the first frequency band.

(252) In both the first and second example aspects, where user data is sent to the second UE over the DRB on the first frequency band, a QoS for the DRB on the first frequency band may be different from a QoS for the DRB on the second frequency band.

(253) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to receive, from the second UE via the means for transceiving **1120**, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band, and to reconfigure the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

(254) In both the first and second example aspects, the first frequency band may be an omni-directional frequency band (e.g., FR1) and the second frequency band comprises a frequency band in which a directional beam is used (e.g., FR2, FR3, FR4), or the first frequency band may be a frequency band in which a directional beam is used and the second frequency band comprises an omni-directional frequency band.

(255) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may cause the means for transceiving **1120** to send the first RRC message over the first frequency band as a groupcast or a broadcast.

(256) In both the first and second example aspects, the first UE may be a first vehicle and the second UE may be a second vehicle, a roadside object, a road sign, or a pedestrian. The first RRC message may be an RRC sidelink reconfiguration message, and the second RRC message may be an RRC sidelink reconfiguration complete message.

(257) In both the first and second example aspects, the first UE and the second UE may communicate over the first frequency band and the second frequency band using a PC5 D2D interface.

(258) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to receive, over the SRB via the means for transceiving **1120**, capability information from the second UE indicating an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band. Alternatively, the means for processing **1130** and/or the sidelink manager **1140** may further be configured to cause the means for transceiving **1120** to send, over the SRB, capability information to the second UE indicating an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

(259) In both the first and second example aspects, the means for processing **1130** and/or the sidelink manager **1140** may be further configured to determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement. The determination to configure the DRB on the second frequency band may be further based on a configuration to use the second frequency band for communication sessions having the given QoS requirement. The configuration may be preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, a determination at the first UE, or any combination thereof.

(260) In both the first and second example aspects, where the configuration is negotiated with the second UE, the negotiation with the second UE may include the means for processing **1130** and/or the sidelink manager **1140** causing the means for transceiving **1120** to send, to the second UE, an option to use the second frequency band for the data flow, and to receive, from the second UE via

the means for transceiving **1120**, an indication to use the second frequency band for the data flow. (261) In both the first and second example aspects, the first UE may receive, via the means for transceiving **1120**, a user data flow from the second UE over the DRB based on a reflective QoS procedure.

(262) In both the first and second example aspects, one or more parameters in the first RRC message may include physical layer configuration parameters for RF beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures. The RF beam direction may be based on geographic locations of the first UE and the second UE, or the RF beam direction may be based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

(263) FIG. **12** illustrates an exemplary first UE apparatus **1200** (e.g., any of the UEs described herein) represented as a series of interrelated functional modules, according to aspects of the disclosure. In the illustrated example, a module for establishing **1210** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for sending **1220** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for configuring **1230** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein.

(264) FIG. **13** illustrates an exemplary first UE apparatus **1300** (e.g., any of the UEs described herein) represented as a series of interrelated functional modules, according to aspects of the disclosure. In the illustrated example, a module for establishing **1310** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for sending **1320** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for configuring **1330** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein.

(265) FIG. **14** illustrates an exemplary second UE apparatus **1400** (e.g., any of the UEs described herein) represented as a series of interrelated functional modules, according to aspects of the disclosure. In the illustrated example, a module for establishing **1410** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for receiving **1420** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for configuring **1430** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein.

(266) FIG. **15** illustrates an exemplary second UE apparatus **1500** (e.g., any of the UEs described

herein) represented as a series of interrelated functional modules, according to aspects of the disclosure. In the illustrated example, a module for establishing **1510** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for receiving **1520** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein. A module for configuring **1530** may correspond to, for example, a communication device (e.g., transceiver(s) **404**) and/or a processing system (e.g., processing system **410** and/or sidelink manager **470**), optionally in conjunction with a memory (e.g., memory **414** and/or sidelink manager **470**), as discussed herein.

(267) The functionality of the modules of FIGS. **12** to **15** may be implemented in various ways consistent with the teachings herein. In some designs, the functionality of these modules may be implemented as one or more electrical components. In some designs, the functionality of these blocks may be implemented as a processing system including one or more processor components. In some designs, the functionality of these modules may be implemented using, for example, at least a portion of one or more integrated circuits (e.g., an ASIC). As discussed herein, an integrated circuit may include a processor, software, other related components, or some combination thereof. Thus, the functionality of different modules may be implemented, for example, as different subsets of an integrated circuit, as different subsets of a set of software modules, or a combination thereof. Also, it will be appreciated that a given subset (e.g., of an integrated circuit and/or of a set of software modules) may provide at least a portion of the functionality for more than one module.

(268) In addition, the components and functions represented by FIGS. **12** to **15**, as well as other components and functions described herein, may be implemented using any suitable means. Such means also may be implemented, at least in part, using corresponding structure as taught herein. For example, the components described above in conjunction with the “module for” components of FIGS. **12** to **15** also may correspond to similarly designated “means for” functionality. Thus, in some aspects one or more of such means may be implemented using one or more of processor components, integrated circuits, or other suitable structure as taught herein, including as an algorithm. One skilled in the art will recognize in this disclosure an algorithm represented in the prose described above, as well as in sequences of actions that may be represented by pseudocode. For example, the components and functions represented by FIGS. **12** to **15** may include code for performing a LOAD operation, a COMPARE operation, a RETURN operation, an IF-THEN-ELSE loop, and so on.

(269) Those of skill in the art will appreciate that information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(270) Further, those of skill in the art will appreciate that the various illustrative logical blocks, modules, circuits, and algorithm steps described in connection with the aspects disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. To clearly illustrate this interchangeability of hardware and software, various illustrative components, blocks, modules, circuits, and steps have been described above generally in terms of their functionality. Whether such functionality is implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system. Skilled artisans may implement the described functionality in varying ways for each particular application, but such implementation decisions should not be interpreted as causing a departure from the scope of the present disclosure.

(271) The various illustrative logical blocks, modules, and circuits described in connection with the aspects disclosed herein may be implemented or performed with a general purpose processor, a DSP, an ASIC, an FPGA, or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

(272) The methods, sequences and/or algorithms described in connection with the aspects disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in random access memory (RAM), flash memory, read-only memory (ROM), erasable programmable ROM (EPROM), electrically erasable programmable ROM (EEPROM), registers, hard disk, a removable disk, a CD-ROM, or any other form of non-transitory storage medium known in the art. An exemplary storage medium may be coupled to the processor such that the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. The processor and the storage medium may reside in an ASIC. The ASIC may reside in a user terminal (e.g., UE). In the alternative, the processor and the storage medium may reside as discrete components in a user terminal.

(273) In one or more exemplary aspects, the functions described may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Computer-readable media includes both computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code in the form of instructions or data structures and that can be accessed by a computer. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media.

(274) While the foregoing disclosure shows illustrative aspects of the disclosure, it should be noted that various changes and modifications could be made herein without departing from the scope of the disclosure as defined by the appended claims. The functions, steps and/or actions of the method claims in accordance with the aspects of the disclosure described herein need not be performed in any particular order. Furthermore, although elements of the disclosure may be described or claimed in the singular, the plural is contemplated unless limitation to the singular is explicitly stated.

Claims

1. An apparatus for wireless communication at a first user equipment (UE), comprising: one or more memories; and one or more processors coupled to the one or more memories, the one or more

processors, either alone or in combination, configured to: establish a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the second UE over the first frequency band.

2. The apparatus of claim 1, wherein the first RRC message includes one or more parameters for establishing the DRB on the second frequency band, and wherein to configure the DRB on the second frequency band, the one or more processors, either alone or in combination, are configured to: configure the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure with the second UE in the first frequency band.

3. The apparatus of claim 1, wherein the one or more processors, either alone or in combination, are further configured to: receive, from the second UE, a second RRC message on the SRB, the second RRC message that confirms the DRB has been successfully configured on the second frequency band; and send first user data for the communication session to the second UE over the DRB on the second frequency band.

4. The apparatus of claim 3, wherein the one or more processors, either alone or in combination, are further configured to: send the first RRC message before the DRB is configured on the second frequency band; and receive the second RRC message after the DRB is configured.

5. The apparatus of claim 3, wherein the one or more processors, either alone or in combination, are further configured to: send second user data for the communication session to the second UE over a DRB on the first frequency band.

6. The apparatus of claim 5, wherein a quality of service (QoS) for the DRB on the first frequency band is different from a QoS for the DRB on the second frequency band.

7. The apparatus of claim 1, wherein the one or more processors, either alone or in combination, are further configured to: receive, from the second UE, a second RRC message on the SRB that indicates the DRB was unsuccessfully configured on the second frequency band; and reconfigure the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.

8. The apparatus of claim 1, wherein: the first frequency band comprises an omni-directional frequency band and the second frequency band comprises a frequency band in which a directional beam is used, or the first frequency band comprises the frequency band in which the directional beam is used and the second frequency band comprises the omni-directional frequency band.

9. The apparatus of claim 1, further comprising: one or more transceivers coupled to the one or more memories and the one or more processors, and wherein the one or more processors, either alone or in combination, are configured to send, via the one or more transceivers, the first RRC message over the first frequency band as a groupcast or a broadcast.

10. The apparatus of claim 1, wherein: the first UE comprises a first vehicle and the second UE comprises a second vehicle, a roadside object, a road sign, or a pedestrian, and the first RRC message comprises an RRC sidelink reconfiguration message, and a second RRC message comprises an RRC sidelink reconfiguration complete message.

11. The apparatus of claim 1, wherein the first UE and the second UE communicate over the first frequency band and the second frequency band using a PC5 device-to-device (D2D) interface.

12. The apparatus of claim 1, wherein the one or more processors, either alone or in combination, are further configured to: receive, over the SRB, capability information from the second UE that indicate an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band; or send, over the SRB, capability information to the second UE that indicates an ability of the first UE to simultaneously communicate on the first frequency band

and the second frequency band.

13. The apparatus of claim 1, wherein the one or more processors, either alone or in combination, are further configured to: determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE that has a given QoS requirement and a configuration to use the second frequency band for communication sessions that have the given QoS requirement, and wherein the configuration is preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, determined at the first UE, or any combination thereof.

14. The apparatus of claim 1, wherein: one or more parameters in the first RRC message include physical layer configuration parameters for radio frequency (RF) beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures, and the RF beam direction is based on geographic locations of the first UE and the second UE, or the RF beam direction is based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

15. An apparatus for wireless communication at a first user equipment (UE), comprising: one or more memories; and one or more processors coupled to the one or more memories, the one or more processors, either alone or in combination, configured to: establish a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

16. The apparatus of claim 15, wherein the one or more processors to configure the DRB on the second frequency band are configured to: configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure with the second UE in the first frequency band.

17. The apparatus of claim 15, wherein the one or more processors, either alone or in combination, are further configured to: receive, from the second UE, a second RRC message on the SRB, wherein the second RRC message confirms that the DRB has been successfully configured on the second frequency band; and send first user data for the communication session to the second UE over the DRB on the second frequency band.

18. The apparatus of claim 17, wherein the one or more processors, either alone or in combination, are further configured to: send the first RRC message before the DRB is configured on the second frequency band; and receive the second RRC message after the DRB is configured.

19. The apparatus of claim 17, wherein the one or more processors, either alone or in combination, are further configured to: send second user data for the communication session to the second UE over a DRB on the first frequency band.

20. The apparatus of claim 19, wherein a quality of service (QoS) for the DRB on the first frequency band is different from a QoS for the DRB on the second frequency band.

21. The apparatus of claim 15, wherein the one or more processors, either alone or in combination, are further configured to: receive, from the second UE, a second RRC message on the SRB that indicates the DRB was unsuccessfully configured on the second frequency band; and reconfigure the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

22. The apparatus of claim 15, wherein: the first frequency band comprises an omni-directional frequency band and the second frequency band comprises a frequency band in which a directional beam is used, or the first frequency band comprises the frequency band in which the directional beam is used and the second frequency band comprises the omni-directional frequency band.

23. The apparatus of claim 15, further comprising: one or more transceivers coupled to the one or

more memories and the one or more processors, and wherein: the first UE comprises a first vehicle and the second UE comprises a second vehicle, a roadside object, a road sign, or a pedestrian, and the first RRC message comprises an RRC sidelink reconfiguration message, and wherein a second RRC message comprises an RRC sidelink reconfiguration complete message.

24. The apparatus of claim 15, wherein the one or more processors, either alone or in combination, are further configured to: receive, over the SRB, capability information from the second UE that indicates an ability of the second UE to simultaneously communicate on the first frequency band and the second frequency band; or send, over the SRB, capability information to the second UE that indicates an ability of the first UE to simultaneously communicate on the first frequency band and the second frequency band.

25. The apparatus of claim 15, wherein the one or more processors, either alone or in combination, are further configured to: determine to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE that has a given QoS requirement and a configuration to use the second frequency band for communication sessions that have the given QoS requirement, and wherein the configuration is preconfigured, received from a network entity, negotiated with the second UE, requested by the second UE, determined at the first UE, or any combination thereof.

26. The apparatus of claim 15, wherein: the one or more parameters in the first RRC message include physical layer configuration parameters for radio frequency (RF) beam direction for the DRB on the second frequency band, sequence identifier, and resource usage and timing information for Layer 1 and Layer 2 procedures, and the RF beam direction is based on geographic locations of the first UE and the second UE, or the RF beam direction is based on a limited angle beam sweep of predicted directions from the first UE to the second UE.

27. An apparatus for wireless communication at a second user equipment (UE), comprising: one or more memories; and one or more processors coupled to the one or more memories, the one or more processors, either alone or in combination, configured to: establish a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the first UE over the first frequency band.

28. The apparatus of claim 27, wherein the first RRC message includes one or more parameters to establish the DRB on the second frequency band, and wherein to configure the DRB on the second frequency band, the one or more processors, either alone or in combination, are configured to: configure the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure with the first UE in the first frequency band.

29. The apparatus of claim 27, wherein the one or more processors, either alone or in combination, are further configured to: send, to the first UE, a second RRC message on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band; and receive user data for the communication session from the first UE over the DRB on the second frequency band.

30. The apparatus of claim 27, wherein the one or more processors, either alone or in combination, are further configured to: send, to the first UE, a second RRC message on the SRB that indicates the DRB was unsuccessfully configured on the second frequency band; and reconfigure the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

31. An apparatus for wireless communication at a second user equipment (UE), comprising: one or more memories; and one or more processors coupled to the one or more memories, the one or more

processors, either alone or in combination, configured to: establish a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

32. The apparatus of claim 31, wherein to configure the DRB on the second frequency band, the one or more processors, either alone or in combination, are configured to: configure the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure with the first UE in the first frequency band.

33. The apparatus of claim 31, wherein the one or more processors, either alone or in combination, are further configured to: send, to the first UE, a second RRC message on the SRB, wherein the second RRC message confirms that the DRB has been successfully configured on the second frequency band; and receive user data for the communication session from the first UE over the DRB on the second frequency band.

34. The apparatus of claim 31, wherein the one or more processors, either alone or in combination, are further configured to: send, to the first UE, a second RRC message on the SRB that indicates the DRB was unsuccessfully configured on the second frequency band; and reconfigure the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

35. A method for wireless communication at a second user equipment (UE), comprising: establishing a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receiving, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.

36. The method of claim 35, the configuring the DRB on the second frequency band comprising: configuring the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure with the first UE in the first frequency band.

37. The method of claim 35, further comprising: sending, to the first UE, a second RRC message on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band; and receiving user data for the communication session from the first UE over the DRB on the second frequency band.

38. The method of claim 35, further comprising: sending, to the first UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band; and reconfiguring the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

39. A non-transitory computer-readable medium storing computer-executable instructions, the computer-executable instructions comprising at least one instruction for causing a second user equipment (UE) to: establish a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.

40. A method for wireless communication at a first user equipment (UE), comprising: establishing a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the second UE over the first frequency band.
41. The method of claim 40, wherein the first RRC message includes one or more parameters for establishing the DRB on the second frequency band, and the configuring the DRB on the second frequency band comprises: configuring the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure with the second UE in the first frequency band.
42. The method of claim 40, further comprising: receiving, from the second UE, a second RRC message on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band; and sending user data for the communication session to the second UE over the DRB on the second frequency band.
43. The method of claim 42, further comprising: sending the first RRC message before the DRB is configured on the second frequency band; and receiving the second RRC message after the DRB is configured.
44. The method of claim 42, further comprising: sending user data for the communication session to the second UE over a DRB on the first frequency band.
45. The method of claim 44, wherein a quality of service (QoS) for the DRB on the first frequency band is different from a QoS for the DRB on the second frequency band.
46. The method of claim 40, further comprising: receiving, from the second UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band; and reconfiguring the DRB on the second frequency band based on one or more different parameters from one or more parameters in the first RRC message.
47. The method of claim 40, further comprising: determining to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement and a configuration to use the second frequency band for communication sessions having the given QoS requirement.
48. A non-transitory computer-readable medium storing computer-executable instructions, the computer-executable instructions comprising at least one instruction for causing a first user equipment (UE) to: establish a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configure the DRB on the second frequency band based on the one or more parameters in the first RRC message.
49. A method for wireless communication at a first user equipment (UE), comprising: establishing a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; sending, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band, the first RRC message including one or more parameters for establishing the DRB on the second frequency band; and configuring the DRB on the second frequency band based on the one or more parameters in the first RRC message.
50. The method of claim 49, the configuring the DRB on the second frequency band comprising: configuring the DRB based on the one or more parameters in the first RRC message and one or more parameters in a device-to-device discovery procedure with the second UE in the first

frequency band.

51. The method of claim 49, further comprising: receiving, from the second UE, a second RRC message on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band; and sending user data for the communication session to the second UE over the DRB on the second frequency band.

52. The method of claim 49, further comprising: receiving, from the second UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band; and reconfiguring the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

53. The method of claim 49, further comprising: determining to configure the DRB on the second frequency band based on the first UE having a data flow to transmit to the second UE having a given QoS requirement and a configuration to use the second frequency band for communication sessions having the given QoS requirement.

54. A non-transitory computer-readable medium storing computer-executable instructions, the computer-executable instructions comprising at least one instruction for causing a first user equipment (UE) to: establish a signaling radio bearer (SRB) for a communication session with a second UE on a first frequency band based on a radio resource control (RRC) connection; send, to the second UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the second UE over the first frequency band.

55. A method for wireless communication at a second user equipment (UE), comprising: establishing a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receiving, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configuring the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the first UE over the first frequency band.

56. The method of claim 55, wherein the first RRC message includes one or more parameters for establishing the DRB on the second frequency band, and wherein the configuring the DRB on the second frequency band comprises: configuring the DRB based on the one or more parameters in the first RRC message and the one or more parameters in the device-to-device discovery procedure with the first UE in the first frequency band.

57. The method of claim 55, further comprising: sending, to the first UE, a second RRC message on the SRB, the second RRC message confirming that the DRB has been successfully configured on the second frequency band; and receiving user data for the communication session from the first UE over the DRB on the second frequency band.

58. The method of claim 55, further comprising: sending, to the first UE, a second RRC message on the SRB indicating that the DRB was unsuccessfully configured on the second frequency band; and reconfiguring the DRB on the second frequency band based on one or more different parameters from the one or more parameters in the first RRC message.

59. A non-transitory computer-readable medium storing computer-executable instructions, the computer-executable instructions comprising at least one instruction for causing a second user equipment (UE) to: establish a signaling radio bearer (SRB) for a communication session with a first UE on a first frequency band based on a radio resource control (RRC) connection; receive, from the first UE over the SRB on the first frequency band, a first RRC message to establish a data radio bearer (DRB) for the communication session on a second frequency band; and configure the DRB on the second frequency band based on one or more parameters of a device-to-device discovery procedure with the first UE over the first frequency band.
