

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12408332

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Fantini; Paolo et al.

Memory devices having one-time-programmable fuses and/or antifuses formed from thin-film transistors

Abstract

Memory devices, and associated systems and methods, are disclosed herein. A representative memory device comprises a substrate, an insulative layer over the substrate, and a memory array over the insulative layer. The memory device further comprises a fuse array positioned in the insulative layer and configured as a non-volatile memory that can store trimming and/or other factors. The fuse array can comprise a plurality of transistors configured as fuses and each including a source, a drain, and a gate. The transistors in a first subset of the transistors have a first resistance across one of the source, the drain, and the gate that represents a first logic state, and the transistors in a second subset of the transistors can have a second resistance across the one of the source, the drain, and the gate that is greater than the first resistance and that represents a second logic state.

Inventors: Fantini; Paolo (Vimercate, IT), Fratin; Lorenzo (Milan, IT), Pellizzer; Fabio (Boise, ID)

Applicant: Micron Technology, Inc. (Boise, ID)

Family ID: 89995902

Assignee: Micron Technology, Inc. (Boise, ID)

Appl. No.: 17/898232

Filed: August 29, 2022

Prior Publication Data

Document Identifier

Publication Date

US 20240074168 A1

Feb. 29, 2024

Publication Classification

Int. Cl.: H10B20/25 (20230101)

U.S. Cl.:

CPC H10B20/25 (20230201);

Field of Classification Search

CPC: H10B (20/25); H10B (63/10); H10B (63/34); H10B (63/845); H10B (20/20); H10N (70/20); H10N (70/231); H10N (70/823); H10N (70/8825)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9653562	12/2016	Kim	N/A	H10B 41/41
2022/0190131	12/2021	Ko	N/A	H01L 23/5283

Primary Examiner: Bernstein; Allison

Attorney, Agent or Firm: Dorsey & Whitney LLP

Background/Summary

TECHNICAL FIELD

(1) The present disclosure generally relates to semiconductor devices, such as three-dimensional (3D) memory devices, including a fuse and/or antifuse array formed from thin-film transistors (TFTs).

BACKGROUND

(2) Memory packages or modules typically include multiple memory devices mounted on a substrate. Memory devices are widely used to store information related to various electronic devices such as computers, wireless communication devices, cameras, digital displays, and the like. Information is stored by programing different states of a memory cell. Various types of memory devices exist, including magnetic hard disks, random access memory (RAM), read only memory (ROM), dynamic RAM (DRAM), synchronous dynamic RAM (SDRAM), and others. Improving memory packages, generally, may include increasing memory cell density, increasing read/write speeds or otherwise reducing operational latency, increasing reliability, increasing data retention, reducing power consumption, reducing manufacturing costs, and reducing the size or footprint of the memory packages and/or components of the memory devices, among other metrics.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Many aspects of the present technology can be better understood with reference to the following drawings. The components in the drawings are not necessarily to scale. Instead, emphasis is placed on illustrating clearly the principles of the present technology.

(2) FIG. 1 is a schematic view of a system incorporating a memory device in accordance with

embodiments of the present technology.

(3) FIG. 2 is a schematic view illustrating the electrical operation of a memory die in accordance with embodiments of the present technology.

(4) FIG. 3A is a top view of a memory die in accordance with embodiments of present technology.

(5) FIG. 3B is a side cross-sectional view of a portion of the memory die of FIG. 3A taken along the line 3B-3B shown in FIG. 3A in accordance with embodiments of the present technology.

(6) FIGS. 4A and 4B are isometric views of a transistor configured as a fuse before programming and after programming, respectively, in accordance with embodiments of the present technology.

(7) FIGS. 5A and 5B are isometric views of a transistor configured as a fuse before programming and after programming, respectively, in accordance with embodiments of the present technology.

(8) FIG. 6 is an isometric view of a transistor configured as an antifuse in accordance with embodiments of the present technology.

(9) FIG. 7 is a schematic view of a read and/or write circuit for a fuse and/or antifuse array in accordance with embodiments of the present technology.

DETAILED DESCRIPTION

(10) Embodiments of the present technology are directed to semiconductor devices, such as memory devices, and associated systems and methods. In several of the embodiments described below, a representative memory device comprises a substrate, an insulative layer over the substrate, and a memory array over the insulative layer. The memory array can be a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells. The memory device can further comprise a plurality of transistors, such as thin-film transistors (TFTs), formed in the insulative layer and each having a source, a drain, and a gate.

(11) First ones of the transistors can be electrically coupled to corresponding ones of the conductive pillars and can be used to select a conductive pillar during an access operation to one of the memory cells. The first transistors can be located under the memory array. Second ones of the transistors can be configured as fuses (or antifuses) and can form a fuse (or antifuse) array that can be programmed as a non-volatile memory (NVM) to store trim and/or other factors. The second transistors in the fuse array can each have either (i) a first resistance across one of the source, the drain, and the gate that represents a first logic state or (ii) a second resistance across the one of the source, the drain, and the gate that is greater than the first resistance. In some embodiments, the second transistors are programmed by selectively applying a programming current across the source, the drain, and/or the gate to break down (e.g., blow) a material thereof to increase the resistance of the transistor from the first resistance to the second resistance.

(12) In some aspects of the present technology, the second transistors configured as fuses can be formed in the insulative material along open regions of the substrate that do not contain other functional elements. For example, the second transistors can be formed in a region of the insulative material that is not below the memory array, such as at a periphery of the substrate. Additionally, the second transistors can be formed using the same process and manufacturing steps as the first transistors. Accordingly, some aspects of the present technology provide for the efficient formation of a fuse array without increasing the size of the memory device and without adding additional process and manufacturing steps.

(13) Numerous specific details are discussed to provide a thorough and enabling description of embodiments of the present technology. A person skilled in the art, however, will understand that the technology may have additional embodiments and that the technology may be practiced without several of the details of the embodiments described below with reference to FIGS. 1-7. In other instances, well-known structures or operations often associated with semiconductor devices, memory devices, etc., are not shown, or are not described in detail, to avoid obscuring other aspects of the technology. In general, it should be understood that various other devices and systems in addition to those specific embodiments disclosed herein may be within the scope of the present

technology.

(14) As used herein, the terms “vertical,” “lateral,” “upper,” “lower,” “above,” and “below” can refer to relative directions or positions of features in the semiconductor devices in view of the orientation shown in the Figures. For example, “upper” or “uppermost” can refer to a feature positioned closer to the top of a page than another feature. These terms, however, should be construed broadly to include semiconductor devices having other orientations, such as inverted or inclined orientations where top/bottom, over/under, above/below, up/down, and left/right can be interchanged depending on the orientation.

(15) FIG. 1 is a schematic view of a system **100** incorporating a memory device **110** in accordance with embodiments of the present technology. In the illustrated embodiment, the system **100** further includes a host device **120** and a plurality of channels **130** coupling the host device **120** with the memory device **110**. The system **100** can include one or more memory devices, but aspects of the one or more memory devices can be described in the context of a single memory device (e.g., the memory device **110**).

(16) In some embodiments, the system **100** comprises one or more portions of an electronic device, such as a computing device, a mobile computing device, a wireless device, a graphics processing device, a vehicle, and/or other system. For example, the system **100** can illustrate aspects of a computer, a laptop computer, a tablet computer, a smartphone, a cellular phone, a wearable device, an Internet-connected device, a vehicle controller, and/or the like. The memory device **110** can be a component of the system **100** configured to store data for one or more other components of the system **100**.

(17) The host device **120** can include/comprise a processor and/or other circuitry that uses memory to execute processes, such as within a computing device, a mobile computing device, a wireless device, a graphics processing device, a computer, a laptop computer, a tablet computer, a smartphone, a cellular phone, a wearable device, an internet-connected device, a vehicle controller, a system on a chip (SoC), and/or another stationary or portable electronic device. In the illustrated embodiment, the host device **120** includes an external memory controller **122**, a processor **124**, and a basic input/output system (BIOS) component **126**. The host device **120** can include more or fewer components, such as one or more peripheral components or one or more input/output controllers. The components of the host device **120** can be coupled with one another using a bus **128**. In some embodiments, the host device **120** can comprise hardware, firmware, and/or software that implements the functions of the external memory controller **122**.

(18) The processor **124** can be configured to provide control or other functionality for at least portions of the system **100** or at least portions of the host device **120**. The processor **124** can be a general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, and/or discrete hardware components. In some embodiments, the processor **124** is a central processing unit (CPU), a graphics processing unit (GPU), a general-purpose GPU (GPGPU), and/or a system on chip (SoC). In some embodiments, the external memory controller **122** can be implemented by or be a part of the processor **124**.

(19) The BIOS component **126** can be a software component that includes a BIOS operated as firmware, which can initialize and run various hardware components of the system **100** or the host device **120**. The BIOS component **126** can also manage data flow between the processor **124** and the various components of the system **100** or the host device **120**. The BIOS component **126** can include a program or software stored in one or more of read-only memory (ROM), flash memory, and/or other non-volatile memory.

(20) The memory device **110** can be an independent device or a component that is configured to provide physical memory addresses/space that can be used or referenced by the system **100**. In some embodiments, the memory device **110** is configurable to work with one or more different types of host devices **120**. Signaling between the host device **120** and the memory device **110** can

be operable to support modulation schemes to modulate the signals, various pin configurations for communicating the signals, various form factors for physical packaging of the host device **120** and the memory device **110**, clock signaling and synchronization between the host device **120** and the memory device **110**, timing conventions, and/or other factors.

(21) The memory device **110** can be configured to store data for the components of the host device **120**. In some embodiments, the memory device **110** acts as a secondary-type or dependent-type device to the host device **120** (e.g., responding to and executing commands provided by the host device **120** through the external memory controller **122**). Such commands can include a write command for a write operation, a read command for a read operation, a refresh command for a refresh operation, and/or other commands.

(22) In the illustrated embodiment, the memory device **110** includes a device memory controller **112** and one or more memory dies **114** (e.g., memory chips; individually identified as memory dies **114a-114n**) to support a desired capacity or a specified capacity for data storage. Each memory die **114** can include a local memory controller **115** (individually identified as local memory controllers **115a-115n**) and a memory array **116** (individually identified as memory arrays **116a-116n**). The memory arrays **116** can be a collection (e.g., one or more grids, one or more banks, one or more tiles, one or more sections) of memory cells, with each memory cell being operable to store at least one bit of data. When the memory device **110** includes two or more of the memory dies **114**, the memory device **110** can be referred to as a multi-die memory, a multi-die package, a multi-chip memory, and/or a multi-chip package.

(23) The memory dies **114** can be two-dimensional (2D) arrays of memory cells or can be three-dimensional (3D) arrays of memory cells. A 2D memory die **114** can include a single memory array **116**. A 3D memory die **114** can include two or more memory arrays **116**, which can be stacked on top of one another or positioned next to one another (e.g., relative to a substrate). In some embodiments, the memory arrays **116** in a 3D memory die **114** can be referred to as decks, levels, layers, or dies. A 3D memory die **114** can include any quantity of the stacked memory arrays **116** (e.g., two high, three high, four high, five high, six high, seven high, eight high, or higher). In some 3D memory dies **114**, different decks can share at least one common access line such that some decks can share a row line and/or column line. For example, as described herein, different decks can share a same pillar for accessing corresponding memory cells.

(24) The device memory controller **112** can include circuits, logic, and/or other components operable to control operation of the memory device **110**. The device memory controller **112** can include hardware, firmware, and/or instructions that enable the memory device **110** to perform various operations and can be operable to receive, transmit, or execute commands, data, and/or control information related to the components of the memory device **110**. The device memory controller **112** can be configured to communicate with the external memory controller **122**, the memory dies **114**, and/or the processor **124**. In some embodiments, the device memory controller **112** controls operation of the memory device **110** described herein in conjunction with the local memory controllers **115** of the memory dies **114**.

(25) In the illustrated embodiment, the memory device **110** further includes a fuse and/or antifuse array **118** ("fuse array **118**"). The fuse array **118** can comprise a plurality of fuses and/or antifuses that are one-time-programmable to store information related to operating parameters of the memory device **110** and/or the memory dies **114**. For example, the fuse array **118** can be programmed as a non-volatile memory (NVM) array to store trim factors (e.g., trim codes) for the memory dies **114**. The trim factors can be used for dynamic trim selection based on operating voltage levels of the memory device **110**. For example, when the memory device **110** is probed (e.g., during test procedures or probe tests), the memory device **110** can be characterized across multiple ranges of voltage levels, under which the memory device **110** could operate (e.g., the total window of voltage levels of VDD, multiple customer preferred voltage levels). In some embodiments, such multiple ranges of voltage levels may account for the entire range (e.g., window) of voltage levels of the

operating voltage (e.g., across entire VDD levels). That is, multiple sets of trimming conditions can be determined based on multiple ranges (e.g., sub-ranges) of the voltage levels that correspond to the entire range in aggregate. In some embodiments, the multiple ranges of voltage levels do not overlap each other. Each trim condition can be represented as a trim code having a certain quantity of bits (e.g., 2 bits, 3 bits, 4 bits, 5 bits). As such, a plurality of trim codes can be generated during the probe tests, where each trim code of the plurality corresponds to one of multiple ranges of voltage levels of the operating voltage.

(26) During operations of the memory device **110** (e.g., initialization procedures, power-up sequences), the memory device **110** can retrieve (e.g., read) the trim codes from the fuse array **118** and store them in one or more internal latches (e.g., registers, special purpose memory arrays) and/or other components. Further, the memory device **110** can determine that the VDD level supplied to the memory device **110** is within one of the multiple ranges of voltage levels. To that end, in some embodiments, the memory device **110** includes a voltage detection circuit configured to detect the voltage level of the operating voltage (the VDD level). In other embodiments, the memory device **110** includes a mode register configured to store an indication of the voltage level of the operating voltage. Based on determining the voltage level supplied to the memory device **110** as its operating voltage, the memory device **110** can select one of the trim codes stored in the internal latches. Subsequently, the memory device **110** can transmit the selected trim code to a trim adjustment circuit of the memory device **110** configured to adjust a set of timing and/or voltage conditions for one or more trimmable circuits of the memory device **110** (e.g., performance critical, VDD-sensitive circuits) according to the selected trim code.

(27) In this manner, various trimmable circuits of the memory device **110** can operate with the appropriate set of timing and/or voltage conditions that have been preconfigured (predetermined, preidentified) during the probe tests based on the VDD levels supplied to the memory device **110**. Further, managing the inventory of the memory device **110** can be simplified in view of the trim codes stored in the fuse array **118** of the memory device **110**, which can be retrieved and selected based on the actual voltage levels of the operating voltage supplied to the memory device **110**.

(28) In some embodiments, the memory device **110** receives data and/or commands from the host device **120**. For example, the memory device **110** can receive a write command indicating that the memory device **110** is to store data for the host device **120** or a read command indicating that the memory device **110** is to provide data stored in a memory die **114** to the host device **120**. In response to a respective command, the memory device **110** can write data to one or more memory cells (e.g., in response to a write command) or can read data from one or more memory cells (e.g., in response to a read command).

(29) The local memory controllers **115** can include circuits, logic, and/or other components configured to control operation of the memory dies **114**. In some embodiments, the local memory controllers **115** are configured to communicate (e.g., receive and/or transmit data and/or commands) with the device memory controller **112**. In some embodiments, the memory device **110** does not include the device memory controller **112**, and one or more of the local memory controllers **115** and/or the external memory controller **122** can perform various functions described herein. As such, the local memory controllers **115** can be configured to communicate with the device memory controller **112**, with other ones of the local memory controllers **115**, and/or directly with the external memory controller **122** and/or the processor **124**. Examples of components that can be included in the device memory controller **112** and/or the local memory controllers **115** can include receivers for receiving signals (e.g., from the external memory controller **122**), transmitters for transmitting signals (e.g., to the external memory controller **122**), decoders for decoding or demodulating received signals, encoders for encoding or modulating signals to be transmitted, and/or various other circuits or controllers operable for supporting described operations of the device memory controller **112** and/or the local memory controllers **115**.

(30) The external memory controller **122** can be configured to enable communication of one or

more of information, data, or commands between components of the system **100** or the host device **120** (e.g., the processor **124**) and the memory device **110**. The external memory controller **122** can convert or translate communications exchanged between the components of the host device **120** and the memory device **110**. In some embodiments, the external memory controller **122** and/or other components of the system **100**, or its functions described herein, can be implemented by the processor **124**. For example, the external memory controller **122** can comprise hardware, firmware, and/or software implemented by the processor **124** and/or another component of the system **100**. Although the external memory controller **122** is depicted as being external to the memory device **110**, in some embodiments, the external memory controller **122**, or its functions described herein, can be implemented by one or more components of a memory device **110** (e.g., the device memory controllers **112**, the local memory controllers **115**) or vice versa.

(31) The components of the host device **120** can exchange information with the memory device **110** using one or more of the channels **130**. The channels **130** can be configured to support communications between the external memory controller **122** and the memory device **110**. The channels **130** can be transmission mediums that carry information between the host device **120** and the memory device **110**, and can include one or more signal paths or transmission mediums (e.g., conductors, conductive paths operable to carry signals) between terminals associated with the components of the system **100**. For example, the channels **130** can each include a first terminal including one or more pins or pads (e.g., conductive input and/or output points) at the host device **120** and one or more pins or pads at the memory device **110**.

(32) In some embodiments, the channels **130** (and associated signal paths and terminals) are dedicated to communicating one or more types of information. For example, in the illustrated embodiment the channels **130** include (i) one or more command and address (CA) channels **132**, (ii) one or more clock signal (CK) channels **134**, (iii) one or more data (DQ) channels **136**, and (iv) one or more other channels **138**. In some embodiments, signaling can be communicated over the channels **130** using single data rate (SDR) signaling or double data rate (DDR) signaling. In SDR signaling, one modulation symbol (e.g., signal level) of a signal can be registered for each clock cycle (e.g., on a rising or falling edge of a clock signal). In DDR signaling, two modulation symbols (e.g., signal levels) of a signal can be registered for each clock cycle (e.g., on both a rising edge and a falling edge of a clock signal).

(33) In some embodiments, the CA channels **132** are configured to communicate commands between the host device **120** and the memory device **110** including control information associated with the commands (e.g., address information). For example, the CA channels **132** can include a read command with an address of the desired data. The CA channels **132** can include any quantity of signal paths to decode one or more of address or command data (e.g., eight or nine signal paths). In some embodiments, the DQ channels **136** are configured to communicate one or more of data or control information between the host device **120** and the memory device **110**. For example, the DQ channels **136** can communicate information (e.g., bi-directional) to be written to the memory device **110** or information to read from the memory device **110**.

(34) FIG. 2 is a schematic view illustrating the electrical operation of a memory die, such as one of the memory dies **114** of FIG. 1, in accordance with embodiments of the present technology. In the illustrated embodiment, the memory die **114** includes the memory array **116** formed of a plurality of memory cells **240** each positioned at an intersection of respective access lines, such as row lines **242** (identified individually as row lines RL.sub.1-RL.sub.m) and column lines **244** (identified individually as column lines CL.sub.1-CL.sub.n). In some embodiments, the access lines (e.g., the row lines **242** and the column lines **244**) are conductive lines coupled with corresponding ones of the memory cells **240** and can be used to perform access operations on the memory cells **240**. In some embodiments, the access lines are arranged in a pattern, such as a grid-like pattern. The access lines can be formed of one or more electrically conductive materials. In some embodiments, the row lines **242** can be referred to as word lines, and the column lines **244** can be referred to as

digit lines or bit lines. References to access lines, row lines, column lines, word lines, digit lines, or bit lines, or the like, are interchangeable without loss of understanding or operation.

(35) Each of the memory cells **240** can store a logic state using a configurable material, which can be referred to as a memory element, a memory storage element, a material element, a material memory element, a material portion, a polarity-written material portion, and/or the like. A configurable material of the memory cells **240** can refer to a chalcogenide-based storage component, as described in more detail with reference to FIG. **3**. For example, a chalcogenide storage element can be used in a phase change memory (PCM) cell, a thresholding memory cell, and/or a self-selecting memory cell.

(36) In some embodiments, as described in greater detail below with reference to FIG. **3**, one or more (e.g., all) of the column lines **244** extends generally perpendicularly relative to a substrate (not shown) carrying the memory array **116** and one or more (e.g., all) of the row lines **242** extend generally parallel to the substrate and generally perpendicularly to the column lines **244**. Further, in some embodiments one or more of the row lines **242** extends on a different deck or tier of the memory array **116** such that the row lines **242** are stacked above/below one another. The memory array **116** can have many other ones of the memory cells **240** positioned at the intersection of additional ones of the row lines **242** and the column lines **244**.

(37) Operations such as reading and writing can be performed on the memory cells **240** by activating or selecting one or more of the row lines **242** and/or the column lines **244**. By biasing an individual one of the row lines **242** and an individual one of the column lines **244** (e.g., by applying a voltage to the row line and/or the column line), a single one of the memory cells **240** can be accessed at their intersection. The intersection of an individual one of the row lines **242** and an individual one of the column lines **244** in either a two-dimensional or three-dimensional configuration can be referred to as an address of a corresponding one of the memory cells **240**.

(38) In the illustrated embodiment, the memory die **114** further includes a row decoder **241**, a column decoder **243**, and a local memory controller **245**. The row decoder **241** and/or the column decoder **243** can be controlled to access the memory cells. For example, the row decoder **241** can receive a row address from the local memory controller **245** and can activate one of the row lines **242** (e.g., a word line) based on the received row address. Similarly, the column decoder **243** can receive a column address from the local memory controller **245** and can activate one of the column lines **244** (e.g., a pillar) based on the received column address.

(39) In the illustrated embodiment, the memory die **114** further includes a sense component **246** configured to detect a state (e.g., a material state, a resistance, a threshold state) of the memory cells **240** and to determine a logic state of the memory cells **240** based on the stored state. The sense component **246** can include one or more sense amplifiers to amplify or otherwise convert a signal resulting from accessing one of the memory cells **240**. The sense component **246** can compare a signal detected from the one of the memory cells **240** to a reference **247** (e.g., a reference voltage or current). The detected logic state of the one of the memory cells **240** can be provided as an output of the sense component **246** to, for example, an input/output **248**, and/or can indicate the detected logic state to another component of a memory device (e.g., the memory device **110** of FIG. **1**) that includes the memory die **114**.

(40) The local memory controller **245** can control the accessing of the memory cells **240** through the various components (e.g., the row decoder **241**, the column decoder **243**, the sense component **246**). Examples of access operations can include a write operation, a read operation, a refresh operation, a precharge operation, and/or an activate operation. In some embodiments, the local memory controller **245** can perform or otherwise coordinate access operations in response to various access commands (e.g., from the host device **120** of FIG. **1**). The local memory controller **245** can be configured to perform other access operations not listed here or other operations related to the operating of the memory die **114** that are not directly related to accessing the memory cells **240**. The local memory controller **245** can be an example of the local memory controller **115**.

described with reference to FIG. 1. In some embodiments, the row decoder **241**, the column decoder **243**, and/or the sense component **246** can be co-located with the local memory controller **245**. The local memory controller **245** can be configured to (i) receive commands and/or data from one or more different memory controllers (e.g., the external memory controller **122** associated with a host device **120** of FIG. 1, another controller associated with the memory die **114**), (ii) translate the commands or the data (or both) into information that can be used by the memory die **114**, (iii) perform one or more operations on the memory die **114**, and/or (iv) communicate data from the memory die **114** to a host device (e.g., the host device **120** of FIG. 1) based on performing the one or more operations. The local memory controller **245** can generate row signals and column address signals to activate a target one of the row lines **242** and a target one of the column lines **244**. The local memory controller **245** can also generate and control various voltages or currents used during the operation of the memory die **114**. In general, the amplitude, the shape, or the duration of an applied voltage or current discussed herein can be varied and can be different for the various operations discussed in operating the memory die **114**.

(41) More specifically, the local memory controller **245** can be configured to perform a write operation (e.g., a programming operation) on one or more of the memory cells **240** of the memory die **114**. During a write operation, one or more of the memory cells **240** can be programmed to store a desired logic state. The local memory controller **245** can identify a target one of the memory cells **240** on which to perform the write operation. For example, the local memory controller **245** can identify a target one of the row lines **242** and a target one of the column lines **244** coupled with the target memory cell **240** (e.g., the address of the target memory cell **240**), and can activate the target row line **242** and the target column line **244** (e.g., by applying a voltage to the target row line **242** and/or the target column line **244**) to access the target memory cell **240**. In some embodiments, the local memory controller **245** applies a specific signal (e.g., write pulse) to the target column line **244** during the write operation to store a specific state in the storage element of the memory cell **240**. The pulse used as part of the write operation can include one or more voltage levels over a duration.

(42) Similarly, the local memory controller **245** can be configured to perform a read operation (e.g., a sense operation) on one or more memory cells **240** of the memory die **114**. During a read operation, the logic state stored in one or more of the memory cells **240** of the memory die **114** can be determined. The local memory controller **245** can identify a target one of the memory cells **240** on which to perform the read operation. For example, the local memory controller **245** can identify a target one of the row lines **242** and a target one of the column lines **244** coupled with the target memory cell **240** (e.g., the address of the target memory cell **240**), and can activate the target row line **242** and the target column line **244** (e.g., by applying a voltage to the target row line **242** and/or the target column line **244**) to access the target memory cell **240**. The sense component **246** can detect a signal received from the target memory cell **240** that is based on the pulse applied to the target row line **242**, the pulse applied to the target column line **244**, and/or a resistance or threshold characteristic of the target memory cell **240**. In some embodiments, the sense component **246** amplifies the detected signal. The local memory controller **245** can activate the sense component **246** (e.g., latch the sense component **246**) and thereby compare the signal received from the target memory cell **240** to the reference **247**. Based on the comparison, the sense component **246** can determine a logic state that is stored on the target memory cell **240**. The pulse used as part of the read operation can include one or more voltage levels over a duration.

(43) FIG. 3A is a top view of a memory die, such as one of the memory dies **114** of FIG. 1, in accordance with embodiments of present technology. FIG. 3B is a side cross-sectional view of a portion of the memory die **114** taken along the line 3B-3B shown in FIG. 3A in accordance with embodiments of the present technology. Referring first to FIG. 3A, the memory die **114** includes a substrate **350** carrying a plurality of the memory arrays **116** (identified individually as a first memory array **116a** and a second memory array **116b**). The memory arrays **116** are three-

dimensional (3D) memory arrays, such as 3D-NAND memory arrays. The substrate **350** can include a redistribution layer, an interposer, a printed circuit board, a dielectric spacer, a semiconductor die, or another suitable substrate.

(44) In the illustrated embodiment, the substrate **350** includes a first open region **352** (e.g., a peripheral open region) and a second open region **354** (e.g., an intermediate open region) at which the substrate **350** (and/or one or more layers thereon) is exposed from the memory arrays **116**. More specially, the substrate **350** can include opposing first sides **351** and opposing second sides **353**, and the first open region **352** can be positioned adjacent only one of the first and second sides **351**, **353** (e.g., one of the first sides **351**). In some embodiments, the first open region **352** can be positioned fully or partially along one or more of the first and second sides **351**, **353**. The second open region **354** can be positioned between the memory arrays **116** at least partially in a central region of the substrate **350**. The substrate **350** can include a plurality of contacts **355** at/along the first open region **352** for receiving/transmitting signals between (e.g., from/to) the memory arrays **116** and an external device, such as the host device **120** of FIG. 1. In the illustrated embodiment, the memory arrays **116** each include an array region **356** and a stepped or staircase region **358**.

(45) Referring to FIG. 3B, in the illustrated embodiment the memory array **116** includes a plurality of tiers **360** arranged in a stack on the substrate **350**. In the illustrated embodiment, the memory array **116** includes seven of the tiers **360** for ease of illustration. In practice, however, the memory array **116** can include many more tiers such as, for example, more than ten tiers, more than twenty tiers, more than fifty tiers, more than one hundred tiers, etc. In other embodiments, the memory array **116** can have fewer than seven tiers. Each of the tiers **360** can have a different lateral width (e.g., in a direction generally parallel to the substrate **350**). More particularly, a lowermost one of the tiers **360** can have the greatest lateral width, and each successive one of the tiers **360** stacked on the lowermost one of the tiers **360** can have a smaller lateral width than the ones of the tiers **360** stacked below. Accordingly, the stack of the tiers **360** can define the staircase region **358** (e.g., a staircase portion) at which a portion (e.g., a peripheral region) of each one of the tiers **360** is exposed. In other embodiments, at least some of the tiers **360** can have the same lateral width.

(46) In the illustrated embodiment, each of the tiers **360** includes a first layer **361** and a second layer **362** formed over the first layer **361**. Thus, the memory array **116** includes a plurality of alternating (e.g., interleaved) first layers **361** and second layers **362**. In some embodiments, each of the first and second layers **361**, **362** is generally planar and has substantially the same thickness. In other embodiments, the first and second layers **361**, **362** can have different and/or varying thicknesses (e.g., some or all of the first layers **361** can be thicker than the second layers **362**, some or all of the second layers **362** can be thicker than the first layers **361**).

(47) The first layers **361** are formed from (e.g., comprise, include) at least one electrically insulative material, such as oxide or nitride materials, silicon oxide, silicon nitride, and/or other electrically insulating materials. The second layers **362** each include a plurality of memory cells **340** electrically coupled to a conductive line **342** (e.g., a word line). The conductive lines **342** and the memory cells **340** can correspond (e.g., in terms of one or more functionalities) to one or more aspects of the row lines **242** and the memory cells **240**, respectively, described in detail with reference to FIG. 2. The conductive lines **342** can be formed of an electrically conductive material, such as metal (e.g., tungsten), metal alloy, conductive-metal containing material, and/or the like.

(48) In the illustrated embodiment, conductive pillars **344** (e.g., bit lines) extend through the tiers **360** in the array region **356** and are coupled to corresponding ones of the memory cells **340** in a vertical stack. That is, each of the pillars **344** is coupled to a corresponding stack of the memory cells **340**. The pillars **344** can correspond (e.g., in terms of one or more functionalities) to one or more aspects of the column lines **244** described in detail with reference to FIG. 2, and can be formed of an electrically conductive material, such as metal (e.g., tungsten), metal alloy, conductive-metal containing material, and/or the like. Therefore, each of the memory cells **340** is electrically coupled to a corresponding one of the conductive lines **342** and a corresponding one of

the pillars **344**.

(49) In some embodiments, the memory cells **340** (e.g., memory elements) can include/comprise a chalcogenide material or other alloy including selenium (Se), tellurium (Te), arsenic (As), antimony (Sb), carbon (C), germanium (Ge), silicon (Si), or indium (In), or various combinations thereof. In some embodiments, a chalcogenide material having primarily selenium (Se), arsenic (As), and germanium (Ge) may be referred to as a SAG-alloy. An SAG-alloy can also include silicon (Si) and such chalcogenide material can be referred to as SiSAG-alloy. An SAG-alloy can also include silicon (Si) and/or indium (In) and such chalcogenide materials can be referred to as SiSAGalloy or InSAG-alloy, respectively. In some embodiments, the chalcogenide material of the memory cells **340** can include additional elements such as hydrogen (H), oxygen (O), nitrogen (N), chlorine (Cl), or fluorine (F), each in atomic or molecular forms. The memory cells **340** can also be formed of other chalcogenide alloys not expressly recited herein.

(50) In the illustrated embodiment, the memory array **116** further includes an electrically insulative material **365** formed over (i) the tiers **360** in the staircase region **358** and (ii) an upper surface of the second layer **362** of the (uppermost) one of the tiers **360** in the array region **356**. The insulative material **365** can be a passivation, dielectric, or other suitable insulating material such as, for example, silicon oxide, tetraethyl orthosilicate (TEOS), and/or the like. The memory array **116** can further include a metallization structure **366** formed on and/or over at least a portion of the insulative material **365**. A plurality of conductive members **367** can extend through the insulative material **365** to electrically couple the metallization structure **366** to the conductive lines **342**. More specifically, the conductive members **367** can extend between and electrically connect the metallization structure **366** and the portion of the conductive lines **342** exposed at the staircase region **358**. The metallization structure **366** can be, for example, a redistribution layer or other structure (e.g., including a plurality of conductive traces, vias, routings, and/or the like) that is configured to electrically couple the conductive lines **342** to, for example, the row decoder **241** of FIG. 2.

(51) In the illustrated embodiment, the memory array **116** further includes a transistor (e.g., selector device) layer **368** extending below the tiers **360** over conductive access lines **369** over the substrate **350**. The access lines **369** can be formed of copper, tungsten, alloys thereof, and/or other electrically conductive materials. The transistor layer **368** can comprise a plurality of transistors **370** (e.g., selectors; identified individually as first transistors **370a** and second transistors **370b**) surrounded by an insulative material **371** such as, for example, polysilicon. In some embodiments, the transistors **370** are thin-film transistors (TFTs) having a source, a drain, and a gate. In some embodiments, the transistors **370** are identical.

(52) The first transistors **370a** can be electrically coupled in parallel (e.g., via a conductive trace **373**) between the access line **369** and a corresponding one of the conductive lines **342**. For example, a first conductive member **374a** can electrically couple the first transistors **370a** to the metallization structure **366** and a second conductive member **374b** can electrically couple the metallization structure **366** to the corresponding one of the conductive lines **342**. In some embodiments, the first conductive member **374a** can be insulated/electrically isolated from the tiers **360**. In some embodiments, one of the source or drain of each of the first transistors **370a** is electrically coupled to the conductive trace **373** and the other of the source or drain is electrically coupled to the access line **369**. The gates of the first transistors **370a** can be electrically coupled to a common source or separate sources for operating the first transistors **370a**. In the illustrated embodiment, the first transistors **370a** are electrically coupled to a fourth one of the conductive lines **342** from the bottom of the stack of the tiers **360**. However, the memory array **116** can include many more of the various components extending, for example, into the page in FIG. 3B such that the first transistors **370a** in different rows are coupled to different ones of the conductive lines **342** and different ones of the access lines **369**. The first transistors **370a** can correspond (e.g., in terms of one or more functionalities) to one or more aspects of the row decoder **241** described in detail

with reference to FIG. 2.

(53) The second transistors **370b** can be electrically coupled between the access line **369** and a corresponding one of the pillars **344**. In some embodiments, one of the source or drain of each of the second transistors **370b** is electrically coupled to the corresponding one of the pillars **344** and the other of the source or drain is electrically coupled to the access line **369**. The gates of the second transistors **370b** can be electrically coupled to a common source or separate sources for operating the second transistors **370b**. The second transistors **370b** are configured to selectively activate the pillars **344**. For example, based on a voltage applied to the access lines **369**, the corresponding second transistors **370b** may be selectively activated or deactivated. When activated (e.g., on, closed, conducting), the second transistors **370b** may couple the corresponding pillars **344** with the access line **369**, and thus the voltage of the pillars **344** may become equal or approximately equal to the voltage of the access line **369**. A pillar decoder (e.g., the column decoder **243** of FIG. 2) can be configured to selectively activate (e.g., apply a selection voltage) or deactivate (e.g., apply a deselection voltage, or remove the selection voltage) one of the access lines **369** out of a set of the access lines **369** associated with the pillar decoder. The pillar decoder, the access lines **369**, and the second transistors **370b** can correspond (e.g., in terms of one or more functionalities) to one or more aspects of the column decoder **243** described in detail with reference to FIG. 2.

(54) As described in detail above with reference to FIG. 2, various logic states can be stored by programming the electrical resistance of memory cells **340**. In some embodiments, programming the electrical resistance includes passing a current through the memory cells **340**, heating the memory cells **340**, melting the material of the memory cells **340** (e.g., wholly or partially), and/or applying a voltage of a particular polarity to the memory cells **340**. In some embodiments the memory cells **340** include one or more phase change materials (e.g., chalcogenide materials). In such embodiments, the memory cells **340** can exhibit an observable difference between resistances of a crystalline state and an amorphous state. For example, a phase change material in the crystalline state can have atoms arranged in a periodic structure, which can result in a relatively low electrical resistance. By contrast, a phase change material in an amorphous state can have no or relatively little periodic atomic structure, which can have a relatively high electrical resistance. Such a difference in resistance values between amorphous and crystalline states can be substantial. For example, a phase change material in an amorphous state can have a resistance one or more orders of magnitude greater than the resistance of the material in its crystalline state. In some embodiments, the phase change material can be partially amorphous and partially crystalline, and the resistance can be of some value between the resistances of the material in a wholly crystalline or wholly amorphous state. In such embodiments, a phase change material can be used to store more than two logic states (e.g., three or more logic states).

(55) During a programming (write) operation of a phase change memory cell (e.g., the memory cells **340**), the various parameters of the programming pulse can influence (e.g., determine, set, program) a particular behavior or characteristic of the material of the memory cells **340**, such as the threshold voltage of the material or the resistance of the material. To program a low-resistance state (e.g., a relatively crystalline state) in a target one of the memory cells **340**, a programming pulse can be applied that heats or melts the material of a storage element of the target memory cell **340**, which can be associated with forming, at least temporarily, a relatively disordered (e.g., amorphous) atomic arrangement. The amplitude of the programming pulse can be reduced (e.g., relatively slowly) over a duration to allow the material to form crystalline structures as it cools, thereby forming a stable crystalline material state. To program a high-resistance state (e.g., a relatively amorphous state) in the target memory cell **340**, a programming pulse can be applied that heats and/or melts the material of the storage element. The amplitude of the programming pulse can be reduced more quickly than the programming pulse for the low-resistance state. In such embodiments, the material can cool with atoms in a more disordered atomic arrangement because

the atoms were not able to form crystalline structures before the material reached a stable state, thereby forming a stable amorphous material state. The difference in threshold voltages or resistances of the material of the storage element depending on the logic state stored by the material of the storage element can correspond to a read window of the storage element. Therefore, in some embodiments a portion of a storage element of the memory cells **340** undergoes a material change associated with the logic states.

(56) In some embodiments, such as when the memory cells **340** are thresholding memory cells or self-selecting memory cells, some or all of a set of logic states supported by the memory cells **340** can be associated with a same state, such as an amorphous state of the chalcogenide material as opposed to a crystalline state of the chalcogenide material (e.g., the material can be operable to store different or multiple logic states while remaining in an amorphous state). In such embodiments, the material used in the memory cells **340** can be based on an alloy (such as the alloys listed above) and can be operated so as to undergo a state change during normal operation of the memory cells **340** (e.g., due to ion migration or segregation within the memory cells **340**). For example, when the memory cells **340** are self-selecting, the memory cells **340** can have a high threshold voltage state and a low threshold voltage state. A high threshold voltage state can correspond to a first logic state (e.g., a reset state) and a low threshold voltage state can correspond to a second logic state (e.g., a set state). In some embodiments, the memory cells **340** can alternatively be switched between an amorphous and crystalline state during operation, with the amorphous and crystalline states corresponding to different resistances or threshold voltages and thus to different logic states, and such operation can be referred to, for example, as phase change operation.

(57) In some embodiments, during a programming (e.g., write) operation of a self-selecting one of the memory cells **340**, a polarity of one or more pulses used for a write operation can influence (e.g., determine, set, program) a particular behavior or characteristic of the material of the self-selecting memory cell **340**, such as the threshold voltage of the material. The difference in threshold voltages of the material of the memory cell **340** depending on the logic state stored by the material of the self-selecting memory cell **340** (e.g., the difference between the threshold voltage when the material is storing a logic state '0' versus a logic state '1') can correspond to a read window of the self-selecting memory cell **340**.

(58) The memory cells **340** described herein can include, but not be limited to, phase change materials. Other types of memory cells **340** can include, for example, resistive memory or resistive RAM. In some cases, resistive RAM can use metal oxide materials whose electrical resistance is varied by controlling the ionic state of atoms in the material or by controlling the quantity or location of atomic vacancies (e.g., missing atoms) in the material.

(59) As described herein, one or more access operations can be performed on a target one of the pillars **344** to access a target one of the memory cells **340** coupled with the target pillar **344**. The target pillar **344** can be accessed or selected by applying voltages along a corresponding one of the access lines **369**, and therefore to the one of the second transistors **370b** coupled with the target pillar **344**. When reading or programming the target memory cell **340** coupled with the target pillar **344**, after selecting the target pillar **344**, a target one of the conductive lines **342** coupled with the target memory cell **340** can be activated to access the target memory cell **340** (e.g., a first voltage can be applied to the target conductive line **342**). Similarly, after selecting the target pillar **344**, a second voltage (e.g., opposite in polarity to the first voltage) can be applied to the corresponding one of the access lines **369**, and the selection voltage can be removed from the access line **369**. Based on applying the voltages to the target conductive line **342** and the respective access line **369**, a voltage difference can be applied across the target memory cell **340** (e.g., via the respective access line **369** and the target pillar **344**, and via the target conductive line **342** coupled with the target memory cell **340**).

(60) In an example of performing positive programming or a positive read on the target memory

cell **340**, the second voltage can be applied to the respective access line **369**, and the second voltage can be higher than the first voltage applied to the target conductive line **342** (e.g., the second voltage can have a positive polarity and the first voltage can have a negative polarity). In an example of performing negative programming or a negative read on the target memory cell **340**, the second voltage can be applied to the respective access line **369**, and the second voltage can be lower than the first voltage applied to the target conductive line **342** (e.g., the second voltage can have a negative polarity and the first voltage can have a positive polarity). In either positive or negative programming, a current can flow from the top to the bottom of the target pillar **344**.

(61) Referring again to FIG. **3A**, in some embodiments the memory die **114** can include one or more fuse and/or antifuse arrays **318** (“fuse arrays **318**”; e.g., including individually identified first through fourth fuse arrays **318a-318d**, respectively) in/along some or all of the open regions of the substrate **350** that are not under (e.g., exposed) from the memory arrays **116**, such as the first open region **352** and/or the second open region **354**. In the illustrated embodiment, for example, the first through third open regions **318a-318c** are positioned along/in the first open region **352** between the contacts **355**, and the fourth fuse array **318d** is positioned in the second open region **354** between the memory arrays **116**. In other embodiments, one or more of the fuse arrays **318** can be positioned in a region under the memory arrays **116**, under the contacts **355**, or elsewhere along the substrate **350** where other functional components are absent. The fuse arrays **318** can correspond (e.g., in terms of one or more functionalities) to one or more aspects of the fuse array **118** described in detail with reference to FIG. **1** and can, for example, comprise a plurality of fuses and/or antifuses that are one-time-programmable to store information related to operating parameters (e.g., trim factors) of the memory device **110** and/or the memory dies **114**.

(62) Referring to FIGS. **3A** and **3B** together, the insulative material **371** of the transistor layer **368** can extend over the substrate **350** in the first and second open regions **352**, **354**, and additional ones of the transistors **370** can be manufactured in the transistor layer **368** and configured as the fuses and/or antifuses of the fuse arrays **318**. That is, for example, the same manufacturing process used to form the transistors **370** for controlling access operations to the memory array **116** can be used to form additional ones of the transistors **370** for use in the fuse arrays **318**.

(63) More specifically, FIGS. **4A** and **4B** are isometric views of one of the transistors **370** configured as a fuse **470** before programming and after programming, respectively, in accordance with embodiments of the present technology. Referring to FIGS. **4A** and **4B** together, in the illustrated embodiment the fuse **470** is a TFT having three terminals—a source **480**, a drain **481**, and a gate **482**. The fuse **470** further includes a body **483** extending between (e.g., separating) the source **480** and the drain **481**. In some embodiments, the fuse **470** is a field-effect transistor (FET). The gate **482** can comprise a conductive material, such as a titanium nitride or another conductive metal.

(64) The source **480**, the drain **481**, and the body **483** can comprise a semiconductor structure (e.g., polysilicon) in which the source **480** and the drain **481** are differently doped than the body **483**. For example, the source **480** and the drain **481** may be conductive and may comprise a heavily-doped, e.g., degenerate, semiconductor region. The body **483** can be a lightly-doped semiconductor region or channel. If the channel is n-type (i.e., majority carriers are electrons), then the fuse **470** can be referred to as a n-type FET. If the channel is p-type (i.e., majority carriers are holes), then the fuse **470** can be referred to as a p-type FET. The body **483** may be capped by an insulating gate oxide (not shown) that separates the body **483** from the gate **482**. When the fuse **470** is configured as a transistor rather than a fuse (e.g., the first transistors **370a** and the second transistors **370b** described in detail above with reference to FIG. **3B**), the channel conductivity may be controlled by applying a voltage to the gate **482**. For example, applying a positive voltage or negative voltage to an n-type FET or a p-type FET, respectively, can result in the channel becoming conductive. The fuse **470** can be “on” or “activated” when a voltage greater than or equal to a threshold voltage of the fuse **470** is applied to the gate **482**. The fuse **470** can be “off” or “deactivated” when a voltage

less than the threshold voltage is applied to the gate **482**.

(65) In the illustrated embodiment, the gate **482** includes a channel **484** defined by a pair of side portions **485** and a pair of end portions **486**, and in which the body **483** is positioned. To enable programming of the fuse **470**, a pair of conductive contacts **490** (e.g., a supply contact and a return contact) can be formed to electrically contact the gate **482**. In the illustrated embodiment, the **490** are formed on the opposing end portions **486** of the gate **482**. With reference additional reference to FIG. **3B**, the contacts **490** can extend at least partially through the insulative material **371** of the transistor layer **368** to electrically couple the gate **482** to other electronic elements in the insulative material **371** and/or in the substrate **350**. For example, the contacts **490** can electrically couple the fuse **470** to a programming (e.g., write) circuit configured to program the fuse **470** and/or a read circuit configured to read out a state of the fuse **470**. While two contacts **490** are shown in FIGS. **4A** and **4B**, in other embodiments more than two contacts can be provided on the gate **482** to, for example, increase reliability and robustness.

(66) As shown in FIG. **4A**, before programming the fuse **470**, the gate **482** provides a conductive path between the contacts **490** having a relatively low resistance. To program the fuse **470**, a relatively large current (e.g., a fuse programming current) can be supplied across the gate **482** via the contacts **490**. Referring to FIG. **4B**, such a current can at least partially break down (e.g., blow, fuse) the gate **482** by, for example, causing warpage or breakage **487** and/or one or more voids **488** in the side portions **485** or elsewhere along the gate **482**. In some embodiments, the breakage **487** and/or voids **488** increase the resistance between the contacts **490** relative to the pre-programmed state shown in FIG. **4A**. For example, the resistance between the contacts **490** can be one or more orders of magnitude (e.g., ten or more times) greater after programming. In some embodiments, after programming, the breakage **487** and/or voids **488** cause an open circuit between the contacts **490** (e.g., an infinite resistance). The current required to fuse the gate **482** can be selected by varying one or more dimensions of the gate **482**. For example, decreasing a width W of the gate **482** can decrease the resistance of the gate **482** and thus the current required to fuse the gate **482**. In some embodiments, the width W of the gate **482** is between about 500-1000 nanometers (e.g., about 800 nanometers).

(67) FIGS. **5A** and **5B** are isometric views of one of the transistors **370** configured as a fuse **570** before programming and after programming, respectively, in accordance with additional embodiments of the present technology. As shown in FIGS. **5A** and **5B**, the fuse **570** includes the same or similar components to the fuse **470** described in detail with reference to FIGS. **4A** and **4B**, but further includes a conductive layer **589** over the drain **481** and a pair of conductive contacts **590** electrically coupled to opposing end portions of the drain **481** along the width W (FIG. **4B**) of the fuse **570**. The conductive layer **589** can have a higher conductivity (e.g., lower resistance) than the drain **481**. In some embodiments, the conductive layer **589** comprises silicide. In other embodiments, the conductive layer **589** and the contacts **590** can be formed over the source **480** rather than the drain **481**. Moreover, while two contacts **490** are shown in FIGS. **4A** and **4B**, in other embodiments more than two contacts can be provided on the gate **482** to, for example, increase reliability and robustness.

(68) As shown in FIG. **5A**, before programming the fuse **570**, the conductive layer **589** provides a conductive path between the contacts **590** having a relatively low resistance. To program the fuse **570**, a relatively large current (e.g., a fuse programming current) can be supplied across the conductive layer **589** via the contacts **590**. Referring to FIG. **5B**, such a current can at least partially break down the conductive layer **589** by, for example, causing warpage or breakage **587** and/or one or more voids **588** therein. In some embodiments, after programming, the breakage **587** and/or voids **588** cause a current between the contacts **590** to pass entirely or partially through the relatively higher resistance material of the drain **481** such that the resistance is greater relative to the pre-programmed state shown in FIG. **5A**. Accordingly, for example, after programming the fuse **570** can act as a polysilicon resistor rather than a silicide resistor. In some embodiments, the

resistance between the contacts **590** can be one or more orders of magnitude (e.g., ten or more times) greater after programming. The current required to fuse the conductive layer **589** can be selected by varying one or more dimensions of the conductive layer **589**. For example, decreasing a width, length, and/or thickness of the conductive layer **589** can decrease the resistance of the conductive layer **589** and thus the current required to fuse the conductive layer **589**. In some embodiments, the programming current can be between about 50-150 microamperes (e.g., about 100 microamperes).

(69) Referring to FIGS. 3A-5B together, in some aspects of the present technology, electrical contacts or other connections other than the contacts **487/587** need not be provided to the fuses **470/570** because they are not intended to be operated as transistors. For example, electrical contacts need not be connected to the source **480** or the drain **481** in the fuse **470** shown in FIGS. 4A and 4B, and electrical contacts need not be connected to the source **480** or the gate **482** in the fuse **570** shown in FIGS. 5A and 5B. In fact, the fuses **470/570** can be formed in the insulative material **371** of the transistor layer **368** such that these terminals of the fuses **470/570** are surrounded by the insulative material **371** and electrically insulated. Further, the fuses **470/570** are one-time programmable (OTP) because, after programming, the physical structure of the fuses **470/570** is permanently changed (e.g., by breaking down the gate **482** and/or the conductive layer **589**).

(70) FIG. 6 is an isometric view of one of the transistors **370** configured as an antifuse **670** in accordance with embodiments of the present technology. In the illustrated embodiment, the antifuse **670** includes the same or similar components to the fuses **470/570** described in detail with reference to FIGS. 4A-5B, but further includes an oxide **691** (e.g., a gate oxide; shown schematically) at least partially between (i) the gate **482** and (ii) the source **480**, the drain **481**, and/or the body **483**. In the illustrated embodiment, one or more conductive contacts **690** can be provided on (i) the gate **482** and (ii) the drain **481** and/or the source **480**. While a single one of the contacts **690** is shown on the drain **481** in FIG. 6, one or more of the contacts **690** could be alternatively or additionally be provided on the source **480**. To program the antifuse **670** as an antifuse, a relatively large current (e.g., a programming current) can be supplied between the contacts **690** to break down the oxide **691** and form a conductive channel therein. In some embodiments, after programming, the conductive channel provides a low resistance path between the gate **482** and the drain **481** and/or source **480** that is lower than the resistance in the pre-programmed state before the oxide **691** is broken down. The antifuse **670** is one-time programmable (OTP) because, after programming, the physical structure of the antifuse **670** is permanently changed by breaking down the oxide **691** to form the conductive channel between the gate **482** and the drain **481** and/or the source **480**.

(71) FIG. 7 is a schematic view of a read and/or write circuit **792** for a fuse and/or antifuse array in accordance with embodiments of the present technology. In the illustrated embodiment, a plurality of fuses and/or antifuses **770** (collectively “fuses **770**”; identified individually as fuses **770.sub.1-770.sub.n**) are formed in an array. The fuses **770** can, for example, comprise multiple ones of the fuses **470/570** and/or the antifuses **670** described in detail above with reference to FIGS. 4-6. Each of the fuses **770** can be electrically coupled between a first conductive line **794** (e.g., a column line) and a transistor **793** (e.g., a first terminal thereof; identified individually as transistors **793.sub.1-793.sub.n**). Each of the transistors **793** (e.g., a second terminal thereof) can be further electrically coupled to a corresponding electrical supply **795** (identified individually as supplies **795.sub.1-795.sub.n**) and each of the transistors **793** (e.g., a third terminal thereof) can be further electrically coupled to a corresponding second conductive line **796** (identified individually as second conductive lines **796.sub.1-796.sub.n**).

(72) To program (e.g., write) the fuses **770** (e.g., to have a high resistance corresponding to a first logic state and a low resistance corresponding to a second logic state), the voltages on the first conductive line **794** and the supplies **795** can be varied. For example, a relatively large voltage difference can be formed across select ones of the fuses **770** to break down a material thereof to

transition the fuses **770** to a high resistance state (e.g., in the instances of the fuses **470/570**) or to break down a material thereof to transition the antifuses **770** to a low resistance state (e.g., in the instance of the antifuses **670**). In this manner, as described in detail above with reference to FIG. **1**, the array of fuses **770** can be programmed as a non-volatile memory (NVM) array to store, for example, trim factors (e.g., trim codes). That is, for example, a first subset of the fuses **770** can be programmed to have a high resistance representing a first logic state by applying a programming current thereacross to break down (e.g., blow) or substantially break down a material of the fuses **770**, while a second subset of the fuses **770** can be programmed to have a low resistance representing a second logic state by selectively not applying the programming current thereacross to leave the materials of the fuses **770** intact. The fuses **770** to which the programming current is not applied can be identical in structure to the transistors **370** described in detail with reference to FIG. **3B**. Similarly, for example, a first subset of the antifuses **770** can be programmed to have a low resistance representing a first logic state by applying a programming current thereacross to break down or substantially break down a gate oxide of the antifuses **770**, while a second subset of the antifuses **770** can be programmed to have a high resistance representing a second logic state by selectively not applying the programming current thereacross to leave the gate oxide of the antifuses **770** intact. The antifuses **770** to which the programming current is not applied can be identical in structure to the transistors **370** described in detail with reference to FIG. **3B**. To read the information stored in the fuses **770** during operation, the voltages on the first conductive line **794** and the second conductive lines **796** can be varied to determine the resistances of the fuses **770** and, therefore, the associated logic states.

(73) Referring to FIGS. **3A**, **3B**, and **7** together, the fuses **770** are formed in the transistor layer **768** along/in open regions of the substrate **350** that do not contain other functional elements.

Additionally, the fuses **770** can be formed using the same process and manufacturing steps as the transistors **370** and are identical to the transistors **370** before programming. Accordingly, some aspects of the present technology provide for the efficient formation of a fuse array without increasing the size of the memory die **114** and without adding additional process and manufacturing steps.

(74) In some embodiments, the transistors **793** can be formed in the substrate **350**. In other embodiments, the transistors **793** can each comprise multiple ones of the transistors **370** connected in parallel to supply a sufficiently high voltage level. Such transistors can similarly be formed in open regions of the substrate **350** without additional process and manufacturing steps. Accordingly, in some such embodiments, all or substantially all of the circuit **792** can be formed in the transistor layer **768**—further increasing the efficiency of the memory die **114**.

(75) The following examples are illustrative of several embodiments of the present technology:

(76) 1. A memory device, comprising: a substrate; an insulative layer over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, and a gate, and wherein the transistors are configured as fuses such that (a) the transistors in a first subset of the transistors have a first resistance across the gate and (b) the transistors in a second subset of the transistors have a second resistance across the gate that is greater than the first resistance.

(77) 2. The memory device of example 1 wherein the transistors are thin-film transistors (TFTs).

(78) 3. The memory device of example 1 or example 2, further comprising a plurality of conductive contacts, wherein at least two of the conductive contacts are electrically coupled to a corresponding gate of each of the transistors and configured to receive a current sufficient to break down a material of the gate to increase the resistance of the gate from the first resistance to the second resistance.

(79) 4. The memory device of example 3 wherein the material of the gate is titanium nitride.

(80) 5. The memory device of any one of examples 1~4 wherein the substrate and the insulative layer are exposed from the memory array at an open portion, and wherein the plurality of

transistors are formed in the insulative layer at the open portion.

(81) 6. The memory device of example 5 wherein the open portion is positioned at a periphery of the substrate.

(82) 7. The memory device of any one of examples 1-6 wherein the memory array is a first memory array, and further comprising a second memory array over the insulative layer, wherein the plurality of transistors are formed in the insulative layer between the first memory array and the second memory array.

(83) 8. The memory device of any one of examples 1-7 wherein the source and the drain of each of the transistors are surrounded by an electrically insulative material.

(84) 9. The memory device of any one of examples 1-8 wherein the second resistance is at least ten times greater than the first resistance.

(85) 10. The memory device of any one of examples 1-9 wherein the transistors are first transistors, and further comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein the second transistors are electrically coupled to the memory array, and wherein the first transistors in the first subset are identical to the second transistors.

(86) 11. The memory device of example 9 wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, and wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars.

(87) 12. The memory device of any one of examples 1-11 wherein the first resistance corresponds to a first logic state, wherein the second resistance corresponds to a second logic state, and wherein the first logic states and the second logic states are configured to represent a trim factor for the memory array.

(88) 13. A memory device, comprising: a substrate; an insulative layer formed over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, a gate, and a conductive layer over one of the source and the drain, and wherein the transistors are configured as fuses such that (a) the transistors in a first subset of the transistors have a first resistance across the conductive layer and (b) the transistors in a second subset of the transistors have a second resistance across the conductive layer that is greater than the first resistance.

(89) 14. The memory device of example 13 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

(90) 15. The memory device of example 13 or example 14 wherein the conductive layer comprises silicide.

(91) 16. The memory device of any one of examples 13-15, further comprising a plurality of conductive contacts, wherein at least two of the conductive contacts are electrically coupled to a corresponding conductive layer of each of the transistors and configured to receive a current sufficient to break down a material of the conductive layer to increase the resistance across the conductive layer from the first resistance to the second resistance.

(92) 17. The memory device of any one of examples 13-16 wherein the transistors are first transistors, wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, and further comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars, and wherein the first transistors in the first subset are identical to the second transistors.

(93) 18. The memory device of any one of examples 13-17 wherein the first resistance corresponds to a first logic state, wherein the second resistance corresponds to a second logic state, and wherein the first logic states and the second logic states are configured to represent a trim factor for the

memory array.

(94) 19. A memory device, comprising: a substrate; an insulative layer over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, and a gate, wherein the transistors are configured as fuses, wherein individual ones of the fuses store a first logic state or a second logic state, wherein the first logic states and the second logic states of the fuses together represent a trim factor for the memory array, and wherein— a first subset of the fuses have received a current sufficient to break down one of the source, the drain, and the gate such that the fuses in the first subset have a first resistance across the one of the source, the drain, and the gate that represents the first logic state, and a second subset of the fuses have a second resistance across the one of the source, the drain, and the gate that is lower than the first resistance and represents the second logic state.

(95) 20. The memory device of example 19 wherein the transistors are first transistors, wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, and further comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars, and wherein the fuses in the second subset are identical to the second transistors.

(96) 21. The memory device of example 19 or example 20 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

(97) 22. A method of manufacturing a memory device, the method comprising: forming a plurality of transistors in an insulative layer over a substrate, wherein the transistors each include a source, a drain, and a gate; forming a memory array over the insulative layer; electrically coupling one of the source, the drain, and the gate of each of the transistors to two or more conductive contacts; and configuring the transistors as fuses, wherein the configuring includes selectively supplying a current to the conductive contacts sufficient to break down a material of the one of the source, the drain, and the gate of a first subset of the transistors, wherein the transistors in the first subset have a first resistance, and wherein the transistors in a second subset of the transistors have a second resistance different from the first resistance.

(98) 23. The method of example 22 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

(99) 24. The method of example 22 or example 23 wherein the configuring includes not supplying the current sufficient to break down the material to the conductive contacts of the second subset of the transistors.

(100) 25. The method of any one of examples 22-24 wherein— the transistors are first transistors, forming the memory array includes forming a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, the method further comprises forming a plurality of second transistors in the insulative layer under the 3D memory array and to be electrically coupled to corresponding ones of the conductive pillars, and the first transistors in the second subset are identical to the second transistors.

(101) Aspects of the present technology can be modified, if necessary, to employ the systems, functions, and concepts of the various references described above to provide yet further implementations of the present technology. The teachings of the present technology provided herein can be applied to other systems, not necessarily the system described above. The elements and features of the various examples described above can be combined to provide further implementations of the present technology. Some alternative implementations of the present technology may include not only additional elements to those implementations noted above, but

also may include fewer elements. Further any specific numbers noted herein are only examples: alternative implementations may employ differing values or ranges.

(102) As used herein, the use of relative terminology, such as “about”, “generally”, “approximately”, “substantially” and the like refer to the stated value plus or minus ten percent. For example, the use of the term “about 100” refers to a range of from **90** to **110**, inclusive. In instances in which the context requires otherwise and/or relative terminology is used in reference to something that does not include, or is not related to, a numerical value, the terms are given their ordinary meaning to one skilled in the art. As used herein, the term “and/or” when used in the phrase “A and/or B” means “A, or B, or both A and B.” A similar manner of interpretation applies to the term “and/or” when used in a list of more than two terms.

(103) References throughout the foregoing description to features, advantages, or similar language do not imply that all of the features and advantages that may be realized with the present technology should be or are in any single embodiment of the present technology. Rather, language referring to the features and advantages is understood to mean that a specific feature, advantage, or characteristic described in connection with an embodiment is included in at least one embodiment of the present technology. Thus, discussion of the features and advantages, and similar language, throughout this specification may, but do not necessarily, refer to the same embodiment.

(104) Furthermore, the described features, advantages, and characteristics of the present technology may be combined in any suitable manner in one or more embodiments. One skilled in the relevant art will recognize that the present technology can be practiced without one or more of the specific features or advantages of a particular embodiment. In other instances, additional features and advantages may be recognized in certain embodiments that may not be present in all embodiments of the present technology.

(105) Any patents and applications and other references noted above, including any that may be listed in accompanying filing papers, are incorporated herein by reference in the entirety, except for any subject matter disclaimers or disavowals, and except to the extent that the incorporated material is inconsistent with the express disclosure herein, in which case the language in this disclosure controls. Aspects of the present technology can be modified, if necessary, to employ the systems, functions, and concepts of the various references described above to provide yet further implementations of the present technology.

(106) Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” and the like are to be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” As used herein, the terms “connected,” “coupled,” or any variant thereof means any connection or coupling, either direct or indirect, between two or more elements; the coupling or connection between the elements can be physical, logical, or a combination thereof. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the above Detailed Description using the singular or plural number may also include the plural or singular number respectively. The word “or,” in reference to a list of two or more items, covers all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list.

(107) The above Detailed Description of examples and embodiments of the present technology is not intended to be exhaustive or to limit the present technology to the precise form disclosed above. While specific examples for the present technology are described above for illustrative purposes, various equivalent modifications are possible within the scope of the present technology, as those skilled in the relevant art will recognize.

(108) While the above description describes various embodiments of the present technology and the best mode contemplated, regardless how detailed the above text, the present technology can be practiced in many ways. Details of the system may vary considerably in its specific

implementation, while still being encompassed by the present disclosure. As noted above, particular terminology used when describing certain features or aspects of the present technology should not be taken to imply that the terminology is being redefined herein to be restricted to any specific characteristics, features, or aspects of the present technology with which that terminology is associated. In general, the terms used in the following claims should not be construed to limit the present technology to the specific examples disclosed in the specification, unless the above Detailed Description section explicitly defines such terms. Accordingly, the actual scope of the present technology encompasses not only the disclosed examples, but also all equivalent ways of practicing or implementing the present technology under the claims.

(109) From the foregoing, it will be appreciated that specific embodiments of the present technology have been described herein for purposes of illustration, but that various modifications may be made without deviating from the spirit and scope of the various embodiments of the present technology. Further, while various advantages associated with certain embodiments of the present technology have been described above in the context of those embodiments, other embodiments may also exhibit such advantages, and not all embodiments need necessarily exhibit such advantages to fall within the scope of the present technology. Accordingly, the invention is not limited, except as by the appended claims.

(110) Although certain aspects of the invention are presented below in certain claim forms, the applicant contemplates the various aspects of the invention in any number of claim forms. Accordingly, the applicant reserves the right to pursue additional claims after filing this application to pursue such additional claim forms, in either this application or in a continuing or other related application.

Claims

1. A memory device, comprising: a substrate; an insulative layer over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, and a gate, and wherein the transistors are configured as fuses such that (a) the transistors in a first subset of the transistors have a first resistance across the gate and (b) the transistors in a second subset of the transistors have a second resistance across the gate that is greater than the first resistance.
2. The memory device of claim 1 wherein the transistors are thin-film transistors (TFTs).
3. The memory device of claim 1, further comprising a plurality of conductive contacts, wherein at least two of the conductive contacts are electrically coupled to a corresponding gate of each of the transistors and configured to receive a current sufficient to break down a material of the gate to increase the resistance of the gate from the first resistance to the second resistance.
4. The memory device of claim 3 wherein the material of the gate is titanium nitride.
5. The memory device of claim 1 wherein the substrate and the insulative layer are exposed from the memory array at an open portion, and wherein the plurality of transistors are formed in the insulative layer at the open portion.
6. The memory device of claim 5 wherein the open portion is positioned at a periphery of the substrate.
7. The memory device of claim 1 wherein the memory array is a first memory array, and further comprising a second memory array over the insulative layer, wherein the plurality of transistors are formed in the insulative layer between the first memory array and the second memory array.
8. The memory device of claim 1 wherein the source and the drain of each of the transistors are surrounded by an electrically insulative material.
9. The memory device of claim 1 wherein the second resistance is at least ten times greater than the first resistance.
10. The memory device of claim 1 wherein the transistors are first transistors, and further

comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein the second transistors are electrically coupled to the memory array, and wherein the first transistors in the first subset are identical to the second transistors.

11. The memory device of claim 9 wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, and wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars.

12. The memory device of claim 1 wherein the first resistance corresponds to a first logic state, wherein the second resistance corresponds to a second logic state, and wherein the first logic states and the second logic states are configured to represent a trim factor for the memory array.

13. A memory device, comprising: a substrate; an insulative layer formed over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, a gate, and a conductive layer over one of the source and the drain, and wherein the transistors are configured as fuses such that (a) the transistors in a first subset of the transistors have a first resistance across the conductive layer and (b) the transistors in a second subset of the transistors have a second resistance across the conductive layer that is greater than the first resistance.

14. The memory device of claim 13 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

15. The memory device of claim 13 wherein the conductive layer comprises silicide.

16. The memory device of claim 13, further comprising a plurality of conductive contacts, wherein at least two of the conductive contacts are electrically coupled to a corresponding conductive layer of each of the transistors and configured to receive a current sufficient to break down a material of the conductive layer to increase the resistance across the conductive layer from the first resistance to the second resistance.

17. The memory device of claim 13 wherein the transistors are first transistors, wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, and further comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars, and wherein the first transistors in the first subset are identical to the second transistors.

18. The memory device of claim 13 wherein the first resistance corresponds to a first logic state, wherein the second resistance corresponds to a second logic state, and wherein the first logic states and the second logic states are configured to represent a trim factor for the memory array.

19. A memory device, comprising: a substrate; an insulative layer over the substrate; a memory array over the insulative layer; and a plurality of transistors positioned in the insulative layer, wherein the transistors each include a source, a drain, and a gate, wherein the transistors are configured as fuses, wherein individual ones of the fuses store a first logic state or a second logic state, wherein the first logic states and the second logic states of the fuses together represent a trim factor for the memory array, and wherein— a first subset of the fuses have received a current sufficient to break down one of the source, the drain, and the gate such that the fuses in the first subset have a first resistance across the one of the source, the drain, and the gate that represents the first logic state, and a second subset of the fuses have a second resistance across the one of the source, the drain, and the gate that is lower than the first resistance and represents the second logic state.

20. The memory device of claim 19 wherein the transistors are first transistors, wherein the memory array is a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones

of the stacks of memory cells, and further comprising a plurality of second transistors positioned in the insulative layer under the memory array, wherein individual ones of the second transistors are electrically coupled to corresponding ones of the conductive pillars, and wherein the fuses in the second subset are identical to the second transistors.

21. The memory device of claim 20 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

22. A method of manufacturing a memory device, the method comprising: forming a plurality of transistors in an insulative layer over a substrate, wherein the transistors each include a source, a drain, and a gate; forming a memory array over the insulative layer; electrically coupling one of the source, the drain, and the gate of each of the transistors to two or more conductive contacts; and configuring the transistors as fuses, wherein the configuring includes selectively supplying a current to the conductive contacts sufficient to break down a material of the one of the source, the drain, and the gate of a first subset of the transistors, wherein the transistors in the first subset have a first resistance, and wherein the transistors in a second subset of the transistors have a second resistance different from the first resistance.

23. The method of claim 22 wherein the transistors are thin-film transistors (TFTs), and wherein the second resistance is at least ten times greater than the first resistance.

24. The method of claim 22 wherein the configuring includes not supplying the current sufficient to break down the material to the conductive contacts of the second subset of the transistors.

25. The method of claim 22 wherein— the transistors are first transistors, forming the memory array includes forming a three-dimensional (3D) memory array including a plurality of memory cells arranged in stacks and a plurality of conductive pillars electrically coupled to corresponding ones of the stacks of memory cells, the method further comprises forming a plurality of second transistors in the insulative layer under the 3D memory array and to be electrically coupled to corresponding ones of the conductive pillars, and the first transistors in the second subset are identical to the second transistors.
