

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent
Kind Code
Date of Patent
Inventor(s)

12411080
B2
September 09, 2025
Mortada; Bassem et al.

On-line compensation of instrumental response drift in miniaturized spectrometers

Abstract

Aspects relate to on-line compensation of instrumental drifts in miniaturized spectrometers due to variations in environmental conditions and due to other sources of instrumental drift. The spectrometer may include a light modulator, a detector, and a processor. The spectrometer may further include a sensor configured to obtain a value of a condition contributing to instrumental drifts in the spectrometer. The processor may be configured to extract a set of correction parameters from a correction matrix associating a plurality of sets of correction parameters with sensor values based on the value and to apply the set of correction parameters to an output of the detector to produce a corrected spectrum of a sample under test. The correction matrix may be generated for the spectrometer or may be based on a global correction matrix fitted to the spectrometer.

Inventors: Mortada; Bassem (Cairo, EG), Sabry; Yasser M. (Cairo, EG), Abozyd; Samir (Tanta, EG)

Applicant: Si-Ware Systems (Cairo, EG)

Family ID: 86324409

Assignee: SI-WARE SYSTEMS (Cairo, EG)

Appl. No.: 17/989317

Filed: November 17, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230152216 A1	May. 18, 2023

Related U.S. Application Data

us-provisional-application US 63281042 20211118

Publication Classification

Int. Cl.: G01N21/31 (20060101)

U.S. Cl.:

CPC G01N21/31 (20130101); G01N2201/0231 (20130101); G01N2201/1211 (20130101)

Field of Classification Search

CPC: G01N (21/31); G01N (2201/0231); G01N (2201/1211)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5227986	12/1992	Yokota	702/22	G01J 3/28
5420877	12/1994	Sandstrom	372/20	H01S 3/13
5530551	12/1995	Cantrall	356/394	G01B 11/105
7839502	12/2009	Lukas	356/326	G01J 3/28
8989511	12/2014	Leary	382/256	G02B 21/008
10996108	12/2020	Nagai	N/A	G01J 3/28
2004/0204800	12/2003	Honda	701/1	B60W 50/00
2010/0064773	12/2009	Meredith	73/40	G01M 3/047
2011/0255075	12/2010	Kerstan	356/72	G01J 3/28
2015/0005601	12/2014	Hoss	600/347	A61B 5/1473
2019/0154656	12/2018	Bae	N/A	G01N 21/65
2019/0301939	12/2018	Medhat	N/A	G01J 3/021
2021/0025755	12/2020	Knobbe	N/A	G01J 3/0286
2022/0107265	12/2021	Gussakovsky	N/A	G01N 21/255
2022/0390279	12/2021	Peters	N/A	G01J 3/28
2023/0131902	12/2022	Daruwalla	257/414	B81B 7/02
2024/0110833	12/2023	Watanabe	N/A	G01M 11/0285

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
10-2008054056	12/2009	DE	N/A
102014013848	12/2015	DE	G01J 3/00
10-2019134456	12/2020	DE	N/A
10-2019219945	12/2020	DE	N/A
1319176	12/2004	EP	A61B 5/0075
S61213650	12/1985	JP	N/A

OTHER PUBLICATIONS

PCT/US2022/050469. International Search Report & Written Opinion (Apr. 3, 2023), 15 pages. cited by applicant

Griffiths, P.R., et al., “Fourier Transform Infrared Spectrometry”. New York: Wiley, 2007. cited by applicant

M. Ebermann, et al., “Tunable MEMS Fabry-Pérot filters for infrared microspectrometers: a review”, MOEMS and Miniaturized Systems XV, 2016. Available: 10.1117/12.2209288, URL: <http://proceedings.spiedigitallibrary.org/> (Mar. 23, 2016). cited by applicant

A. Akujarvi, et al., “MOEMS FPI sensors for NIR-MIR microspectrometer applications”, MOEMS and Miniaturized Systems XV, 2016. Available: 10.1117/12.2214710, URL: <http://proceedings.spiedigitallibrary.org/> (Mar. 21, 2016). cited by applicant

S. Kong, et al., “Infrared micro-spectrometer based on a diffraction grating”, Sensors and Actuators A: Physical, vol. 92, No. 1-3, pp. 88-95, 2001. Available: 10.1016/s0924-4247(01)00544-1. cited by applicant

H. Andersen, et al., “Comparison of noise sources in dual- and single-beam Fourier-transform near-infrared spectrometry”, Applied Optics, vol. 44, No. 29, p. 6167, 2005. Available: 10.1364/ao.44.006167. cited by applicant

K. Linga, “Design fabrication and characterization of high performance in GaAs/InP focal plane array in the 1-2.6 μm wavelength region”, 1997. cited by applicant

T. Saito, “Spectral Properties of Semiconductor Photodiodes”, Advances in Photodiodes, 2011. cited by applicant

A. Coatings and E. Inc., “Anti-Reflection (AR) Coatings | Edmund Optics”, Edmundoptics.com, 2021. [Online]. URL: <https://www.edmundoptics.com/knowledge-center/application-notes/lasers/anti-reflection-coatings/> (Dec. 29, 2022). cited by applicant

G. Barbarino, et al., “Silicon Photo Multipliers Detectors Operating in Geiger Regime: an Unlimited Device for Future Applications”, Photodiodes—World Activities in 2011, 2011. Available: 10.5772/21521 [Accessed Jun. 11, 2021]. cited by applicant

M. Saidin, et al., “Transmission Properties of Lithium Nobate and Fused Quartz as Acousto Optic Material”, J. Fiz. UTM, vol. 2, 2007. cited by applicant

D. Arteev, et al., “Investigation of Statistical Broadening in InGaN Alloys”, Journal of Physics: Conference Series, vol. 1135, p. 012050, 2018. Available: 10.1088/1742-6596/1135/1/012050 (Dec. 21, 2018). cited by applicant

S. Kahmann, et al., “Hot carrier solar cells and the potential of perovskites for breaking the Shockley-Queisser limit”, Journal of Materials Chemistry C, vol. 7, No. 9, pp. 2471-2486, 2019. Available: 10.1039/c8tc04641g. cited by applicant

X. Zhou, et al., “An InGaAlAs—InGaAs Two-Color Photodetector for Ratio Thermometry”, IEEE Transactions on Electron Devices, vol. 61, No. 3, pp. 838-843, 2014. cited by applicant

S. Yurtseven, et al., “Investigation of Enviromental Effects on the Normalized Spectral Responsivity of an InGaAs Detector”, 2019 IEEE International Symposium on Medical Measurements and Applications (MeMeA), 2019. cited by applicant

K. Stock, et al., “Spectral characterization of InGaAs trap detectors and photodiodes used as transfer standards”, Metrologia, vol. 37, No. 5, pp. 449-452, 2000. cited by applicant

A. Rogalski “Quantum well photoconductors in infrared detector technology”, Journal of Applied Physics, vol. 93, No. 3, pp. 4355-4391, 2003. Available: 10.1063/1.1558224 (Aug. 31, 2014). cited by applicant

M. Zhu, et al., “Temperature Drift Compensation for High-G MEMS Accelerometer Based on RBF NN Improved Method”, Applied Sciences, vol. 9, No. 4, p. 695, 2019. cited by applicant

J. Gao, et al., “Temperature characteristics and error compensation for quartz flexible

accelerometer”, International Journal of Automation and Computing, vol. 12, No. 5, pp. 540-550, 2015. cited by applicant

R. Olbrycht, et al., “New approach to thermal drift correction in microbolometer thermal cameras”, Quantitative InfraRed Thermography Journal, vol. 12, No. 2, pp. 184-195, 2015. Available: 10.1080/17686733.2015.1055675. cited by applicant

O. Riou, et al., “Non uniformity correction and thermal drift compensation of thermal infrared camera”, Proc. of SPIE vol. 5405 (2004). cited by applicant

Z. Zhang, et al., “Baseline correction using adaptive iteratively reweighted penalized least squares”, The Analyst, vol. 135, No. 5, p. 1138, 2010. Available: 10.1039/b922045c. cited by applicant

V. Ban, et al., “Characterization of process-induced defects in 2.6- μm InGaAs photodiodes”, Physical Concepts and Materials for Novel Optoelectronic Device ApplicationsII, 1993. Available: 10.1117/12.162766. cited by applicant

J. Ma, et al., “Design and performance analysis of extended wavelength InGaAs near-infrared photodetectors”, Japanese Journal of Applied Physics, vol. 54, No. 10, p. 104301, 2015. Available: 10.7567/jap.54.104301. cited by applicant

Krzysztof B. Bec, et al., “Miniaturized NIR Spectroscopy in Food Analysis and Quality Control: Promises, Challenges, and Perspectives”, <https://doi.org/10.3390/foods11101465>, Foods 2022, 11, 1465, 1-53. cited by applicant

O.V. Moskovkin, “Temperature Correction of the Spectral Response of a Photodiode”, Instruments and Experimental Techniques, vol. 44, No. 1, 2001, 123-125. cited by applicant

Paul J. Bowyer, et al., “Analyzing and Correcting Spectrometer Temperature Sensitivity”, Journal of Magnetic Resonance 152, 2001, 234-246. cited by applicant

Saber G. R. Salim, et al., “Temperature and nonlinearity corrections for a photodiode array spectrometer used in the field”, Applied Optics, vol. 50, No. 6, 2011, 866-875. cited by applicant

Ling Li, et al., “Temperature correction method for commercial CCD array spectrometers used in spectral radiometry measurement”, IP Conf. Series: Journal of Physics: Con. Series 972, 2018, 1-6. cited by applicant

Zhiping He, et al., “Measurement and Correction Model for Temperature Dependence of an Acousto-Optic Tunable Filter (AOTF) Infrared Spectrometer for Lunar Surface Detection”, Applied Spectroscopy, vol. 74, 2020, 81-87. cited by applicant

Primary Examiner: Iacoletti; Michelle M

Assistant Examiner: Underwood; Jarreas

Attorney, Agent or Firm: Loza & Loza, LLP

Background/Summary

PRIORITY CLAIM (1) This application claims priority to and the benefit of Provisional Application No. 63/281,042, filed in the U.S. Patent and Trademark Office on Nov. 18, 2021, the entire content of which is incorporated herein by reference as if fully set forth below in its entirety and for all applicable purposes.

TECHNICAL FIELD

(1) The technology discussed below relates generally to spectrometers, and in particular to self-correction of spectral errors due to instrumental response drifts.

BACKGROUND

- (2) A spectrometer measures a single-beam spectrum (e.g., a power spectral density (PSD)). The intensity of the single-beam spectrum is proportional to the power of the radiation reaching the detector. In spectrometry, absorbance of a sample is its fingerprint, which is used in spectral processing operations to enable material identification, along with quantitative and qualitative analysis. However, absorbance is not measured in one step. Instead, it is extracted from the measured spectrum in presence of a sample with respect to a background (BG) spectrum measurement with no sample in the light path, to account for the instrumental transfer function.
- (3) Typically, the background measurement is acquired, in the case of transmittance, by measuring the spectrum of a light beam without placing any sample in the light pass. While in diffuse reflection, a reference material with 95% or higher reflectance and approximately a flat response across the spectral range of interest, is used to obtain a background measurement. This methodology enables the compensation of instrumental response on condition of having the same instrumental drift between the background measurement and sample measurement. However, instrumental response may change with environmental conditions, and as a result, satisfying this criterion may be difficult. For example, background measurements may need to be taken more frequently or even before each sample measurement. This consumes time and effort and sometimes is not possible.
- (4) Traditionally, spectroscopists have developed algorithms to post-process the spectrometry data to decrease the negative impact of instrumental errors on the useful information. The effect of environmental conditions on instrumental response has also been studied to predict how frequently the background measurement should be taken. Additionally, models may be generated for these effects and then used to compensate for the instrumental errors, thus decreasing the background measurement repetition. Although these approaches are effective and widely used, each involves a post-processing process, which is application dependent and time consuming. Additionally, these processes need a specialist in spectroscopy to conduct them, and even with the oversight of a specialist may lead to errors in the results.

SUMMARY

- (5) The following presents a summary of one or more aspects of the present disclosure, in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated features of the disclosure, and is intended neither to identify key or critical elements of all aspects of the disclosure nor to delineate the scope of any or all aspects of the disclosure. Its sole purpose is to present some concepts of one or more aspects of the disclosure in a form as a prelude to the more detailed description that is presented later.
- (6) In an example, a spectrometer is disclosed including a light modulator optically coupled to receive input light and to produce modulated light based on the input light, a detector optically coupled to detect the modulated light in presence of a sample and to produce an output based on the modulated light, a sensor configured to obtain a value of a condition contributing to instrumental drifts in the spectrometer, a memory configured to store a correction matrix associating a plurality of sets of correction parameters with sensor values, and a processor coupled to the detector and configured to extract a set of correction parameters of the plurality of sets of correction parameters from the correction matrix based on the value. The processor can further be configured to process the output of the detector based on the set of correction parameters to produce a corrected spectrum of the sample.
- (7) These and other aspects of the disclosure will become more fully understood upon a review of the detailed description, which follows. Other aspects, features, and examples of the present disclosure will become apparent to those of ordinary skill in the art, upon reviewing the following description of specific, exemplary aspects of the present disclosure in conjunction with the accompanying figures. While features of the present disclosure may be discussed relative to certain examples and figures below, all examples of the present disclosure can include one or more of the features discussed herein. In other words, while one or more examples may be discussed as having

certain features, one or more of such features may also be used in accordance with the various examples of the disclosure discussed herein. In similar fashion, while exemplary aspects may be discussed below as device, system, or method aspects, it should be understood that such exemplary aspects can be implemented in various devices, systems, and methods.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example of a spectrometer according to some aspects
- (2) FIG. 2 is a diagram illustrating another example of a spectrometer according to some aspect.
- (3) FIG. 3 is a diagram illustrating another example of a spectrometer according to some aspects.
- (4) FIG. 4 is a diagram illustrating an example of a photodiode, which may be used in a photodetector of a spectrometer according to some aspects.
- (5) FIG. 5A is a graph illustrating ideal responsivity for photodiodes with constant quantum efficiency according to some aspects.
- (6) FIG. 5B is a graph illustrating typical responsivities of silicon (Si) and InGaAs photodiodes according to some aspects.
- (7) FIG. 6 is a graph illustrating the shift in cut-off wavelength with temperature for a semiconductor photodiode according to some aspects.
- (8) FIG. 7 is a graph illustrating the spectral temperature coefficient of the responsivity of a photodiode according to some aspects.
- (9) FIG. 8 is a graph illustrating the shift in the cut-off wavelength with temperature for a semiconductor photoconductive detector according to some aspects.
- (10) FIG. 9 is a diagram illustrating an example of a spectrometer configured for on-line compensation of instrumental drift according to some aspects.
- (11) FIG. 10 is a diagram illustrating another example of a spectrometer configured for on-line compensation of instrumental drift according to some aspects.
- (12) FIGS. 11A and 11B are diagrams illustrating the relation between temperature and wavelength according to some aspects.
- (13) FIG. 12 is a flow chart illustrating a process for on-line compensation of temperature drifts in a spectrometer according to some aspects.
- (14) FIG. 13 is a diagram illustrating an example of a spectrometer employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects.
- (15) FIG. 14 is a diagram illustrating another spectrometer employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects.
- (16) FIG. 15 is a diagram illustrating an example of a spectrometer employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects.
- (17) FIG. 16 is a diagram illustrating another example of a spectrometer employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects.
- (18) FIG. 17 is a diagram illustrating another example of a spectrometer employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects.
- (19) FIGS. 18A and 18B are diagrams illustrating another example of of a spectrometer employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects.
- (20) FIG. 19 is a diagram illustrating a thermal drift correction process using a third order polynomial fitting according to some aspects.
- (21) FIG. 20 is a graph illustrating an original response corresponding to the thermal drift taken from a background measurement along with a corrected response according to some aspects.
- (22) FIG. 21 is another graph illustrating an original response corresponding to the thermal drift

- taken from a background measurement along with a corrected response according to some aspects.
- (23) FIG. 22 is another graph illustrating an original response corresponding to the thermal drift taken from a background measurement along with a corrected response according to some aspects.
- (24) FIG. 23 is a graph illustrating a combination of the two-decomposition corrections shown in FIGS. 21 and 22 at two different values of temperature change according to some aspects.
- (25) FIG. 24 is a diagram illustrating an example of a spectrometer including a plurality of sensors according to some aspects.
- (26) FIG. 25 is a flow chart illustrating a process for generating a correction matrix for on-line compensation of temperature drifts according to some aspects.
- (27) FIG. 26 is a diagram illustrating an example of a system configured to sweep the temperature of a spectrometer to generate a correction matrix according to some aspects.
- (28) FIG. 27 is a diagram illustrating another example of a system configured to sweep the temperature of a spectrometer to generate a correction matrix according to some aspects.
- (29) FIGS. 28A and 28B are diagrams illustrating another example of a system configured to sweep the temperature of a spectrometer to generate a correction matrix according to some aspects.
- (30) FIG. 29 is a diagram illustrating an example flow for generating the correction matrix including coefficients of fitted functions as the correction parameters, according to some aspects.
- (31) FIG. 30 is a graph illustrating an example of a third-order polynomial fitting for the thermal drift at the 1850 nm wavelength point of an NIR spectrometer according to some aspects.
- (32) FIG. 31 is a diagram illustrating an example of a system configured to generate a global correction matrix according to some aspects.
- (33) FIG. 32 is a diagram illustrating another example of a system configured to generate a global correction matrix according to some aspects.
- (34) FIG. 33 is a graph illustrating the thermal drift of a typical InGaAs PIN detector responsivity according to some aspects.
- (35) FIGS. 34A and 34B are graphs illustrating an AirPLS method used to separate the baseline first order drift from the dip higher order drift according to some aspects.
- (36) FIG. 35 is a graph illustrating the common (average) correction matrix for the dip drift per degree Celsius according to some aspects.
- (37) FIG. 36 is a graph illustrating a mechanism for finding the detector feature position using the slope of the detector drift according to some aspects.
- (38) FIG. 37 is a graph illustrating a detector dip feature position according to some aspects.
- (39) FIGS. 38A and 38B are graphs illustrating the extraction of detector higher-order thermal drift caused by cut-off shift with the temperature at different temperatures according to some aspects.
- (40) FIG. 39 is a diagram illustrating another example of a system configured to generate a global correction matrix according to some aspects.

DETAILED DESCRIPTION

(41) The detailed description set forth below in connection with the appended drawings is intended as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

(42) Various aspects of the disclosure relate to on-line compensation of instrumental drifts in miniaturized spectrometers due to variations in environmental conditions, including thermal (temperature) drift and humidity drift, and due to other sources of instrumental drift, such as light source inefficiency and optical misalignment. A spectrometer may include a light modulator (e.g., an FT-IR interferometer, Fabry-Perot interferometer, diffraction grating, etc.), a detector, and a processor. The processor may be configured to apply a correction matrix to an output of the

detector to produce a corrected spectrum of a sample under test. For example, the processor may be configured to extract a set of correction parameters from the correction matrix and apply the set of correction parameters to the output of the detector (e.g., a measured spectrum of a sample) to compensate for instrumental drifts in the spectrometer. The spectrometer may further include a sensor configured to obtain a value (e.g., a real-time value during operation of the spectrometer) of a condition contributing to instrumental drifts in the spectrometer. The processor may then extract the set of correction parameters based on the value. As indicated above, the value may represent an environmental condition (e.g., thermal drift or humidity drift) or other condition (e.g., light source inefficiency or optical misalignment). The correction matrix may be generated during production of the spectrometer or may be based on a global correction matrix fitted to the spectrometer.

(43) In an example, to compensate for temperature variations, temperature sensing can be performed with the aid of a separate temperature sensor, a temperature sensor embedded in the control/detection electronics, or the photodetector may be exploited to sense the temperature based on the relation between the detector bandgap and the temperature. Temperature sensing can be performed during generation of the correction matrix or during application of the correction matrix to an output of the detector. In some examples, a heat source may be used to raise the temperature during the correction matrix generation process. The heat source can be an external heat source, such as an oven or temperature chamber, or self-heating of the spectrometer device itself, which can be due to the light source of the spectrometer or the heat generated by the electronic components, such as current driver low-dropout regulators (LDOs), analog-to-digital converters (ADCs), or processor chips.

(44) During application of the correction matrix to a detector output, a feedback system uses the temperature reading (e.g., temperature value) to correct the measured spectrum using a set of correction parameters (e.g., a pre-calibrated correction function) based on the measured temperature. The pre-calibrated correction function can be generated from a direct fitting algorithm, a decomposition algorithm, or the drift physical governing equations can be fed to a machine learning algorithm along with spectrometry raw data to create an adaptive correction model for the correction matrix. In some examples, the correction matrix can adapt automatically to each spectrometer unit. Updated correction matrices taking into account the aging effect over time can be extracted and fed back to spectrometer units through a cloud-based interface.

(45) FIG. 1 is a diagram illustrating an example of a spectrometer **100** according to some aspects. The spectrometer **100** may be, for example, a Fourier Transform infrared (FTIR) spectrometer that exploits light interference and Fourier transform to calculate the spectral content of an infrared light beam. In the example shown in FIG. 1, the spectrometer **100** is a Michelson FTIR interferometer.

(46) FTIR spectrometers measure a single-beam spectrum (power spectral density (PSD)), where the intensity of the single-beam spectrum is proportional to the power of the radiation reaching the detector. In order to measure the absorbance of a sample **112**, the background spectrum (i.e., the single-beam spectrum in absence of a sample) may first be measured to compensate for the instrument transfer function. The single-beam spectrum of light transmitted or reflected from the sample **112** may then be measured. The absorbance of the sample **112** may be calculated from the transmittance, reflectance, or trans-reflectance of the sample **112**, the former being illustrated. For example, the absorbance of the sample **112** may be calculated as the ratio of the spectrum of transmitted light, reflected light, or trans-reflected light from the sample to the background spectrum.

(47) The FT-IR spectrometer **100** includes a fixed mirror **106**, a moveable mirror **108**, a beam splitter **104**, and a detector **114** (e.g., a photodetector). A light source **102** associated with the spectrometer **100** is configured to emit an input beam and to direct the input beam towards the beam splitter **104**. The light source **102** may include, for example, a laser source, one or more wideband thermal radiation sources, or a quantum source with an array of light emitting devices that cover the wavelength range of interest.

(48) The beam splitter **104** is configured to split the input beam into two beams. One beam is reflected off of the fixed mirror **106** back towards the beam splitter **104**, while the other beam is reflected off of the moveable mirror **108** back towards the beam splitter **104**. The moveable mirror **108** may be coupled to an actuator **110** to displace the movable mirror **108** to the desired position for reflection of the beam. An optical path length difference (OPD) is then created between the reflected beams that is substantially equal to twice the mirror **108** displacement. In some examples, the actuator **110** may include a micro-electro-mechanical systems (MEMS) actuator, a thermal actuator, or other type of actuator.

(49) The reflected beams interfere at the beam splitter **104** to produce an output light beam, allowing the temporal coherence of the light to be measured at each different Optical Path Difference (OPD) offered by the moveable mirror **108**. The signal corresponding to the output light beam may be detected and measured by the detector **114** at many discrete positions of the moveable mirror **108** to produce an interferogram. In some examples, the detector **114** may include a detector array or a single pixel detector. The interferogram data verses the OPD may then be input to a processor (not shown, for simplicity). The spectrum may then be retrieved, for example, using a Fourier transform carried out by the processor.

(50) In some examples, the spectrometer **100** may be implemented as a MEMS interferometer (e.g., a MEMS chip). For example, the MEMS chip may be attached to a printed circuit board (PCB) that may include, for example, one or more processors, memory devices, buses, and/or other components. As used herein, the term MEMS refers to an actuator, a sensor, or the integration of sensors, actuators and electronics on a common silicon substrate through microfabrication technology to build a functional system. Microelectronics are typically fabricated using an integrated circuit (IC) process, while the micromechanical components are fabricated using compatible micromachining processes that selectively etch away parts of the silicon wafer or add new structural layers to form the mechanical and electromechanical components. One example of a MEMS element is a micro-optical component having a dielectric or metallized surface working in a reflection or refraction mode. Other examples of MEMS elements include actuators, detector grooves and fiber grooves.

(51) In some examples, the MEMS interferometer (FT-IR spectrometer **100**) may be fabricated using a Deep Reactive Ion Etching (DRIE) process on a Silicon On Insulator (SOI) wafer in order to produce the micro-optical components and other MEMS elements that are able to process free-space optical beams propagating parallel to the SOI substrate. For example, the electro-mechanical designs may be printed on masks and the masks may be used to pattern the design over the silicon or SOI wafer by photolithography. The patterns may then be etched (e.g., by DRIE) using batch processes, and the resulting chips (e.g., MEMS chip) may be diced and packaged (e.g., attached to the PCB).

(52) In some examples, the beam splitter **104** may be a silicon/air interface beam splitter (e.g., a half-plane beam splitter) positioned at an angle (e.g., 45 degrees) from the input beam. The input beam may then be split into two beams L1 and L2, where L1 propagates in air towards the moveable mirror **108** and L2 propagates in silicon towards the fixed mirror **106**. Here, L1 originates from the partial reflection of the input beam from the half-plane beam splitter **104**, and thus has a reflection angle equal to the beam incidence angle. L2 originates from the partial transmission of the input beam through the half-plane beam splitter **104** and propagates in silicon at an angle determined by Snell's Law. In some examples, the fixed and moveable mirrors **106** and **108** are metallic mirrors, where selective metallization (e.g., using a shadow mask during a metallization step) is used to protect the beam splitter **104**. In other examples, the mirrors **106** and **108** are vertical Bragg mirrors that can be realized using, for example, DRIE.

(53) In some examples, the MEMS actuator **110** may be an electrostatic actuator formed of a comb drive and spring. For example, by applying a voltage to the comb drive, a potential difference results across the actuator **110**, which induces a capacitance therein, causing a driving force to be

generated as well as a restoring force from the spring, thereby causing a displacement of moveable mirror **108** to the desired position for reflection of the beam back towards the beam splitter **104**. (54) FIG. **2** is a diagram illustrating another example of a spectrometer **200** according to some aspects. The spectrometer **200** may be, for example, a Fabry-Perot spectrometer that includes a fixed mirror **206**, a moveable mirror **208**, and a detector **212** (e.g., a photodetector). A light source **202** associated with the spectrometer **200** is configured to emit an input beam and to direct the input beam towards the fixed mirror **206**. The light source **202** may include, for example, a laser source, one or more wideband thermal radiation sources, or a quantum source with an array of light emitting devices that cover the wavelength range of interest.

(55) For light trapped in a Fabry-Pérot cavity formed between the fixed mirror **206** and the movable mirror **208**, maximum transmission occurs when the optical path difference between each transmitted beam is equal to one complete cycle. This phenomenon can be used to create a tuneable light filter, which can be used as a spectrometer, as shown in FIG. **2**. According to the phase shift equation, the wavelength of maximum transmission is given by:

$$\lambda_{\text{sub.max}} = 2n_{\text{sub.r}}d \cos(\theta) \quad (1)$$

where $n_{\text{sub.r}}$ is the refractive index of the cavity, d is the distance between the two mirrors **206** and **208** and θ is the incidence angle. If d changes as a result of motion of the movable mirror **208** using, for example, springs **210**, $\lambda_{\text{sub.max}}$ will change, thus forming a spectrometer. By measuring the light intensity using the photodetector **212** and measuring d , the relative intensity of each wavelength can be calculated.

(56) As with the FT-IR spectrometer **100** shown in FIG. **1**, a single-beam spectrum (power spectral density (PSD)) may be obtained using the Fabry-Perot spectrometer **200** shown in FIG. **2**, where the intensity of the single-beam spectrum is proportional to the power of the radiation reaching the detector **212**. In order to measure the absorbance of a sample **204**, the background spectrum (i.e., the single-beam spectrum in absence of a sample) may first be measured to compensate for the instrument transfer function. The single-beam spectrum of light transmitted or reflected from the sample **204**, the former being illustrated, may then be measured.

(57) FIG. **3** is a diagram illustrating another example of a spectrometer **300** according to some aspects. The spectrometer **300** may be, for example, a diffraction grating spectrometer that includes a diffraction grating **306** and a detector **308** (e.g., a photodetector). A light source **302** associated with the spectrometer **300** is configured to emit an input beam and to direct the input beam towards the diffraction grating **306**. The light source **302** may include, for example, a laser source, one or more wideband thermal radiation sources, or a quantum source with an array of light emitting devices that cover the wavelength range of interest.

(58) Diffraction grating spectrometers **300**, such as the one shown in FIG. **3**, exploit the diffraction to analyze light content at different angles, according to the equation

$$d \sin(\theta_{\text{sub.m}}) = m\lambda \quad (2)$$

where d is the periodicity of the grating, $\theta_{\text{sub.m}}$ is the angle of diffracted beam and m is the order of diffraction. By measuring light intensity at each position on the detector **308**, relative intensity for each wavelength point can be calculated. In some examples, the detector **308** may be a multi-pixel detector, as shown in FIG. **3**, to detect the different intensity of light on every point on the detector **308** and convert that to an image that can then be processed to produce the light spectrum. In other examples, a single detector can be used. However, a movable mirror or slit may be needed to direct each wavelength separately to the detector.

(59) The resulting light spectrum produced by the diffraction grating spectrometer **300** corresponds to a power spectral density (PSD), where the intensity of the spectrum is proportional to the power of the radiation reaching the detector **308** at each point. In order to measure the absorbance of a sample **304**, the background spectrum (i.e., the spectrum in absence of a sample) may first be measured to compensate for the instrument transfer function. The spectrum of light transmitted or reflected from the sample **304**, the former being illustrated, may then be measured.

(60) Temperature variations can cause a change in instrument response including interferometer, optics, and photodetector response, which can be challenging to overcome even with post-processing of data. Stabilizing the temperature is one solution; however temperature stabilization may not be possible, especially in miniaturized spectrometers, as this affects size, power consumption, and possibility of sealing. The photodetector is considered as the main source of thermal drifts in spectrometers, such as the spectrometers shown in FIGS. 1-3.

(61) FIG. 4 is a diagram illustrating an example of a photodiode 400, which may be used in a photodetector of a spectrometer according to some aspects. The photodiode 400 shown in FIG. 4 is a PIN photodiode that includes five main layers. The first layer is the substrate 404 that carries the photodiode's other layers and acts as the N region of the PIN photodiode 400. The second layer is a buffer layer 406 that prevents the migration of defects and impurities from the substrate 404 to the active layer. The buffer layer 406 also serves as a matching layer to decrease the lattice mismatch between the active layer and the substrate 404. Lattice mismatch can cause dislocation defects that increase the dark current and decrease the shunt resistance of the photodiode. The third layer is the intrinsic I active layer 408 where light is converted to electric current. The fourth layer is the cap layer 410/412 that includes the P region. The cap layer 410/412 should be built from a high bandgap material relative to the active layer 408 to prevent the surface recombination of photo-generated carriers. For example, if the cap layer 410/412 has a small bandgap, photons may be able to generate carriers in the cap layer 410/412; hence, these photons will be absorbed and will not reach the active layer 408. Moreover, these photo-generated carriers on the cap layer 410/412 may be lost as they may recombine quickly due to the high doping in the cap layer 410/412. The last layer is a dielectric layer 414/416 that serves as a passivation, protective, and antireflection coating layer. Contacts 402 and 418 may be present on either side of the PIN photodiode 400.

(62) Quantum efficiency η of a photodiode, such as the PIN photodiode shown in FIG. 4, is defined as the number of generated electrons due to electron-photon interaction, divided by the number of incident photons on the photodiode. Responsivity S of the photodiode is defined as the photodiode output electric power divided by the incident light radiant power. Therefore, quantum efficiency and responsivity are linked by the following equation:

$$(63) \quad S = \frac{e}{hc} \approx \frac{1.24}{\lambda(\text{nm})} \quad (3)$$

where e is the electron charge, c is the speed of light, λ is the wavelength, and h is the plank's constant. Therefore, if η is constant, the responsivity should be linear with wavelength. FIG. 5A is a graph illustrating ideal responsivity for photodiodes with constant quantum efficiency η .

(64) However, for practical photodiode applications, η may not be constant. FIG. 5B is a graph illustrating typical responsivities of silicon (Si) and InGaAs photodiodes. FIG. 5B shows the deviation of responsivity from the linear behaviour for typical semiconductor photodetectors shown in FIG. 5A. On the right side of each responsivity curve, the responsivity decreases sharply to reach zero at the longer wavelengths when the photon energy is smaller than the bandgap, while the left side of each responsivity curve also deviates from the expected linear behaviour.

(65) The responsivity η may also be defined as the total photon flux divided by the total electrons flux as follows:

$$(66) \quad \eta = \frac{\text{incident photons}}{\text{generated electrons}} \quad (4)$$

(67) The generated electrons can be calculated from the following equation:

$$\phi_{\text{sub}} \cdot \text{generated electrons} = \phi_{\text{sub}} \cdot \text{incident photons} \cdot (1-R) \cdot e_{\text{sub}} \cdot a_{\text{sub}} \cdot c_{\text{sub}} \cdot d_{\text{sub}} \cdot c_{\text{sub}} \cdot (1-e_{\text{sub}} \cdot a_{\text{sub}} \cdot d_{\text{sub}} \cdot a_{\text{sub}}) \cdot \xi \quad (5)$$

where R is the reflection of photons from the top surface of the photo-diode, $a_{\text{sub}} \cdot c_{\text{sub}}$ and $d_{\text{sub}} \cdot c_{\text{sub}}$ are the absorption coefficient and the thickness of the cap layer respectively, $a_{\text{sub}} \cdot a_{\text{sub}}$ and $d_{\text{sub}} \cdot a_{\text{sub}}$, are the absorption coefficient and the thickness of the active layer respectively and ξ is the fraction of absorbed photons in the active layer that leads to generation of useful electron flux. From the

previous two equations,

$$\eta = (1-R) \cdot e_{\text{sup}} \cdot a_{\text{sup}} \cdot c_{\text{sup}} \cdot d_{\text{sup}} \cdot c \cdot (1 - e_{\text{sup}} \cdot a_{\text{sup}} \cdot a_{\text{sup}} \cdot d_{\text{sup}} \cdot a) \cdot \xi \quad (6)$$

(68) Each term in Equation (6) has a contribution to the behaviour of the photodiode. In some examples, it may be desirable to decrease R to the minimum value possible. This may be done with the aid of the passivation layer, which is designed to act as an AR coating. For example, a typical AR coating may be able to decrease reflection to less than 0.5%. However, every AR coating has a bandwidth (BW). Outside the BW, reflection starts to increase, hence, quantum efficiency decreases. Thus, one reason behind the responsivity deviation from the linear behaviour is the non-constant reflection along the whole spectrum.

(69) The term $(1 - e_{\text{sup}} \cdot a_{\text{sup}} \cdot d_{\text{sup}} \cdot a_{\text{sup}} \cdot d_{\text{sup}} \cdot a)$ describes the absorption that happens in the active layer. In some examples, this term may be made as big as possible (close to 1) since the absorption of photons in the active layer is the process that leads to electrons generation. The absorption coefficient for some semiconductor materials used in the manufacturing of photodiodes may sharply increase when the photon energy exceeds the band-gap energy, especially the direct band-gap materials. This high absorption is due to the interband transition, which is the electron transition between valence and conduction bands. Indeed, electro-photon generation is an interband transition from valence to conduction band. Therefore, the responsivity of the detector approaches zero for high wavelengths when photon energy is less than the band gap. This corresponds to the cut-off wavelength of the detector

$$(70) \quad \lambda_c = \frac{hc}{E_g}.$$

The absorption coefficient for a direct band gap transition is related to the energy gap by the following relation:

$$a \propto (h\nu - E_{\text{sub.g}})_{\text{sup.m}} \quad (7)$$

where m is a material dependent parameter and it is equal to $\frac{1}{2}$ in many materials, while the indirect band transition absorption coefficient is given by:

$$a \propto (h\nu - E_{\text{sub.g}})_{\text{sup.ind}} + h\nu \quad (8)$$

(71) By inspecting the InGaAs responsivity curve in FIG. 5B, it can be noticed that at cut-off wavelength, responsivity experiences a sharp decay. However, it is not instantaneous as expected. The curve shows that there are some electrons generated even to the right of cut-off wavelength where no interband transition occurs and where absorption should be equal to zero. This is because of two reasons, the Urbach tail and thermal absorption.

(72) The Urbach tail is the representation of the non-abrupt decay of absorption beyond the cut-off wavelength. It is due to statistical broadening of the band gap energy. For example, band gap energy is not a sharp constant in every place of the material, instead, it has some sort of statistical distribution. This is due to the defects in the crystalline structure. Moreover, the change of the composition of alloy materials from place to place may cause this broadening. For example, alloy materials are deposited using epitaxial growth, which may have some variations that lead to this broadening. The Urbach tail is described by the following exponential empirical equation:

$$a = a_{\text{sub.v}} \cdot e^{\text{sup.h}\nu/E_{\text{sub.v}}} \quad (9)$$

where $a_{\text{sub.v}}$ and $E_{\text{sub.v}}$ are empirical constants that depend on the material and the fabrication process. Thermal absorption also leads to some absorption beyond the cut-off wavelength.

However, its effect is weak compared to the Urbach tail. Thermal absorption can happen due to interband transition, exciton absorption below bandgap, or phonon absorption. By combining the aforementioned equations of absorption in direct and indirect band gap transitions, it can be deduced that absorption is increasing for the wavelengths shorter than the cut-off. This means that quantum efficiency should increase and the responsivity should be higher than expected by the linear model. However, the opposite happens. As can be seen in FIG. 5B, the InGaAs curve shows that the responsivity reaches a maximum value then decays faster than expected. Moreover, below a specific wavelength (about $0.97 \mu\text{m}$), it decays exponentially.

(73) The first decay is related to the term ξ in the quantum efficiency equation. This term describes how many of the generated electrons will lead to useful electric current. For example, not all generated electrons may participate in the electric current, because some of them recombine before they reach the electrodes, and ξ decreases for shorter wavelengths because of hot carriers' effect. When electrons have higher energy than the bandgap, they can reach a higher position in the conduction band. However, this position is not stable; hence, they lose this excess energy gradually as phonons to reach the bandgap energy. This leads to a faster recombination rate of these hot electrons due to phonons assisted recombination. Furthermore, these hot electrons suffer from a higher rate of surface traps capturing, because their high energy enables them to hit the surface on a higher rate.

(74) The last term in the quantum efficiency equation $e_{\text{sup}} \cdot a_{\text{sub.c}} \cdot d_{\text{sub.c}}$ is the reason behind the exponential decay in responsivity that starts at the wavelength about $0.97 \mu\text{m}$ in the InGaAs responsivity curve in FIG. 5B. This term describes the absorption in the cap layer, where $a_{\text{sub.c}}$ is the absorption coefficient of the cap layer and $d_{\text{sub.c}}$ is its thickness. For example, the cap layer **412** in the InGaAs photodiode shown in FIG. 4 is made of InP, a material with a cut-off wavelength of $0.97 \mu\text{m}$ (this cut-off wavelength changes depending on the cap layer material). Before the cut-off, $a_{\text{sub.c}}$ is negligible and the cap layer is transparent, but after reaching the cut-off, $a_{\text{sub.c}}$ rockets up and much of the light intensity is absorbed. Absorption in the cap layer does not create electric current, because the cap layer is highly p doped, hence, the generated electrons recombine very fast. This absorption may be decreased by decreasing the thickness $d_{\text{sub.c}}$ of the cap layer; however, decreasing it lower than a certain value affects the reliability of the photodetector.

(75) As previously described, a minimum amount of photon energy, equal to the bandgap energy, is needed to raise the electron to the conduction band. Therefore, it is not possible for photons with wavelengths longer than a specific value, $\lambda_{\text{sub.cut-off}}$, to cause electron generation. However, the bandgap of most semiconductor materials decreases with temperature according to the equation:

$$(76) \quad E_{bg} = E_{bg0} - \frac{T^2}{T_+} \quad (10)$$

where α and β are fitting parameters that depend on the material. This effect is caused by the increase in lattice constant or interatomic spacing due to the increase in atoms' vibration caused by thermal energy. The increase in interatomic spacing decreases the attractive force applied on electrons by an atoms' nuclei; hence, the band-gap energy decreases.

(77) FIG. 6 is a graph illustrating the shift in cut-off wavelength with temperature for a semiconductor photodiode according to some aspects. As shown in FIG. 6, the cut-off wavelength of photodetectors shifts to higher wavelengths, as a result of the reduction in band gap energy with temperature.

(78) FIG. 7 is a graph illustrating the spectral temperature coefficient of the responsivity of a photodiode according to some aspects. As can be seen in FIG. 7, the temperature coefficient versus wavelength can be divided into two regions. The strong positive increase at the right side (right region) of the graph is due to the previously explained shift in cut-off to higher wavelengths with increasing temperature. The left region, which has a negative temperature coefficient, is due to the increase of absorption in the cap layer. Typically, the cap layer cut-off is located in the middle of the spectrum. This is the aforementioned reason behind the sharp decrease in responsivity of the photodiode at short wavelengths (e.g., because the cap layer which has a higher bandgap can absorb those photons as they have enough energy to generate electrons in the cap layer). Increasing temperature reduces the penetration depth of light. Thus, less light can reach the active layer and is absorbed in the cap layer. Moreover, the dip feature that appears in the middle of the graph shown in FIG. 7 is due to the shift of the cap layer cut-off. For example, as the temperature increases, the cap layer bandgap decreases; hence, photons with longer wavelengths can generate electrons in the cap layer, and as a consequence, some of them are absorbed in the cap layer. The position of the dip

in the spectrum depends on the cap layer material cut-off wavelength.

(79) Thermal drift affects all photodetectors whether they are photodiodes, such as InGaAs, InAs and Si, or photoconductors, such as PbSe, PbS and HgCdTe.

(80) Photoconductive detectors generally suffer from higher thermal drifts. FIG. 8 is a graph illustrating the shift in the cut-off wavelength with temperature for a semiconductor photoconductive detector (e.g., an MIR PbSe photoconductive photodetector) according to some aspects. Since the bandgap of this material increases with temperature, the cut-off wavelength decreases with temperature.

(81) To enable on-line compensation for instrumental response change causes, including temperature drift, humidity drift, light source inefficiency, optical misalignment and other suitable causes, a spectrometer may be configured with a correction matrix including a plurality of sets of correction parameters (e.g., correction functions). The correction matrix may be generated during assembly line production of the spectrometer or may be based on a global (e.g., average) correction matrix applicable to a plurality of spectrometers.

(82) FIG. 9 is a diagram illustrating an example of a spectrometer 900 configured for on-line compensation of instrumental drift according to some aspects. The spectrometer 900 includes a light modulator 906, a detector 910, and a processor 914. The light modulator 906 may use a spectroscopic technique, including, but not limited to, direct absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator 906 may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The detector 910 may correspond to, for example, to a photodetector. A light source 902 may further be coupled to or incorporated within the spectrometer 900 (the former being illustrated). The light source 902 may include, for example, a laser source, one or more wideband thermal radiation sources, or a quantum source with an array of light emitting devices that cover the wavelength range of interest.

(83) The processor 914 may include a single processing device or a plurality of processing devices. Such a processing device may be a microprocessor, micro-controller, digital signal processor, microcomputer, central processing unit, field programmable gate array, programmable logic device, logic circuitry, analog circuitry, digital circuitry, and/or any device that manipulates signals (analog and/or digital) based on hard coding of the circuitry and/or operational instructions. The processor 914 may be coupled to a memory, such as memory 920. The memory 920 may be a single memory device, a plurality of memory devices, and/or embedded circuitry of the processor 914. Such a memory device may be a read-only memory, random access memory, volatile memory, non-volatile memory, static memory, dynamic memory, flash memory, cache memory, and/or any device that stores digital information, including instructions (e.g., code) that may be executed by the processor 914.

(84) The memory 920 may further store a correction matrix 922. The correction matrix 922 may include a plurality of sets of correction parameters (e.g., correction functions) that may be utilized to provide on-line compensation of spectrum measurements. For example, the correction matrix 922 may provide on-line compensation due to variations in environmental conditions, including thermal (temperature) drift and humidity drift, and due to other sources of instrumental drift, such as light source inefficiency and optical misalignment. In some examples, the correction matrix 922 may include a plurality of correction matrices, each configured to provide on-line compensation due to a different condition. For example, the correction matrix 922 may include a temperature drift correction matrix and a humidity drift correction matrix. As another example, the correction matrix 922 may include a temperature drift correction matrix, a humidity drift correction matrix, and a light source inefficiency correction matrix. Any combination of correction matrices is within the scope of the present disclosure.

(85) The correction matrix 922 may be locally generated for the spectrometer 900 or based on a

cloud-based (global) correction matrix applicable to a plurality of spectrometers. In some examples, the correction matrix **922** may be continuously or periodically updated via a machine learning (ML) or artificial intelligence (AI) engine, which may include a local AI/ML engine and/or a cloud-based AI/ML engine. In some examples, the spectrometer **900** may further include other circuitry, such as control circuitry configured to control the light modulator **906** and light source(s) **902**, powering circuitry configured to provide power to the various components of the spectrometer **900**, communication circuitry (e.g., Wi-Fi, Bluetooth, cellular, etc.) configured to enable wireless communication with the spectrometer **900** (e.g., for cloud-based AI applications), and/or other suitable circuitry.

(86) The spectrometer **900** may further include one or more sensor(s) **916**, each configured to obtain a respective value **918** of a condition contributing to instrumental drifts in the spectrometer **900**. The sensor **916** may be a separate sensor (e.g., separate from the light modulator **906**, detector **910** and processor **914**), a sensor embedded in or coupled to the light modulator **906**, control/detection electronics, light source, or other component of the spectrometer **900**, or may be realized as an algorithm that may be executed by the processor **914** to sense the value **918** based on a relation between the detector output and the condition being sensed. Examples of values include, but are not limited to, temperature values, humidity values, light source efficiency values, and optical misalignment values.

(87) In an example operation, the light source **902** may be configured to generate input light **904** and to direct the input light to the light modulator **906**. For example, the input light **904** may be directed to the light modulator **906** via an optical fiber and/or one or more optical elements (e.g., mirrors and/or focusing lenses). The light modulator **906** may be configured to produce modulated light **908** based on the input light **904** and to direct the modulated light **908** towards the detector **910** to produce an output **912**. For example, the modulated light **908** may be directed to the detector **910** via an optical fiber and/or one or more optical elements (e.g., mirrors and/or focusing lenses). In examples in which the light modulator **906** is a FT-IR interferometer or Fabry-Perot interferometer, the modulated light **908** may correspond to interference beams produced over time with an OPD between beams. The output **912** of the detector **910** may then correspond to an interferogram. In examples in which the light modulator **906** is a diffraction grating, the modulated light **908** may correspond to diffracted light across a plurality of wavelengths. The output **912** of the detector **910** may then correspond to an image representing the light intensity at each wavelength point on the detector **910**.

(88) The output **912** of the detector **910** may then be input to the processor **914** to produce a sample spectrum of a sample under test (not shown). For example, the processor **914** may apply a Fourier transform of the interferogram data produced by the detector and the OPD in the light modulator **906** to produce the spectrum. The processor **914** may further be configured to correct the sample spectrum based on instrumental response drifts in the spectrometer **900** to produce a corrected spectrum **926**. The processor **914** may be configured to receive from the one or more sensor(s) **916** respective values **918** of one or more conditions measured by the sensor(s) **916** contributing to the instrumental drifts. The processor **914** may further be configured to access the memory **920** to retrieve a respective set of correction parameters **924** from the correction matrix **922** based on each received value **918**. The processor **914** may then be configured to apply the set(s) of correction parameters **924** to the sample spectrum to produce the corrected spectrum **926**.

(89) FIG. **10** is a diagram illustrating another example of a spectrometer **1000** configured for on-line compensation of instrumental drift according to some aspects. The spectrometer **1000** includes a spectral sensor **1002** and a digital signal processing (DSP) unit **1018**. The spectral sensor **1002** includes a light source **1004** (e.g., a wideband light source), a light modulator chip **1008** (e.g., a light modulator), a detector **1012** (e.g., a photodetector), and an electronics interface **1016**.

(90) The light modulator **1008** may use a spectroscopic technique, including, but not limited to, direct absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic

spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator **906** may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The electronics interface **1016** may include the control circuitry to control the light modulator **1008** and light source **1004**. For example, the electronics interface **1016** may be configured to provide a control signal **1040** to the light modulation chip **1008** to control operation of the light modulator. In addition, the electronics interface **1016** provides an electrical connection to the DSP unit **1018**.

(91) The spectral sensor **1002** may further include one or more environmental conditions sensor(s) **1026**, each configured to obtain a respective value **1028** of a condition contributing to instrumental drifts in the spectral sensor **1002**. In some examples, the environmental conditions sensor **1026** may be a separate sensor (e.g., separate from the light source **1004**, the light modulator **1008**, and the detector **1012** or may be a sensor embedded in or coupled to the light modulator **1008**, electronics interface **1016**, light source **1004**, or other component of the spectral sensor **1002**. Examples of values **1028** include, but are not limited to, temperature values, humidity values, light source efficiency values, and optical misalignment values.

(92) The DSP unit **1018** includes an optical signal processing unit **1020**, an artificial intelligence (AI)/machine learning (ML) engine **1030**, and a memory **1032**. The optical signal processing unit **1020** may include a single processing device or a plurality of processing devices. Such a processing device may be a microprocessor, micro-controller, digital signal processor, microcomputer, central processing unit, field programmable gate array, programmable logic device, logic circuitry, analog circuitry, digital circuitry, and/or any device that manipulates signals (analog and/or digital) based on hard coding of the circuitry and/or operational instructions. The memory **1032** may be a single memory device or a plurality of memory devices. Such a memory device may be a read-only memory, random access memory, volatile memory, non-volatile memory, static memory, dynamic memory, flash memory, cache memory, and/or any device that stores digital information, including instructions (e.g., code) that may be executed by the optical signal processing unit **1020**.

(93) The memory **1032** may further store a correction matrix **1034**. The correction matrix **1034** may include a look up table of sets of correction parameters (e.g., correction functions) verses environmental conditions (or other conditions). For example, the sets of correction parameters in the correction matrix **1034** may provide on-line compensation due to variations in environmental conditions, including thermal (temperature) drift and humidity drift, and due to other sources of instrumental drift, such as light source inefficiency and optical misalignment. In some examples, the correction matrix **1034** may include a plurality of correction matrices, each configured to provide on-line compensation due to a different condition.

(94) In the example shown in FIG. **10**, the correction matrix **1034** may be generated and/or updated using the AI/ML engine **1030**. The AI/ML engine **1030** may fully reside in hardware and/or software on the spectrometer **1000** or may be implemented using a cloud-based AI/ML engine. In this example, a local AI/ML engine **1030** residing in hardware and/or software on the spectrometer may be in communication with (e.g., wireless communication) the cloud-based AI/ML engine. For example, the cloud-based AI/ML engine may provide access to one or more cloud-based correction matrices that may be downloaded into the memory **1032** and adapted (e.g., updated) for the spectrometer **1000** by the AI/ML engine **1030**. For example, the AI/ML engine **1030** may use the output (e.g., values **1028**) obtained by one or more environmental sensors **1026** at each sample measurement, along with the sample spectrum (e.g., power spectral density (PSD)) of each sample measurement to update the correction matrix **1034**. As another example, instead of having a dedicated environmental conditions sensor **1026** on the spectral sensor, the sensor value (e.g., an environment conditions measurement **1024**) may be obtained by the optical signal processing unit **1020** during processing of the PSD **1022**. The environment conditions measurement **1024**, together with the PSD **1022** may be input to the AI/ML engine **1030** to update the correction matrix **1034**. In

some examples, the DSP unit **1018** may include circuitry configured to execute the AI/ML engine **1030** (e.g., software or instructions for performing ML functions). In other examples, the DSP unit **1018** may include dedicated ML circuitry (e.g., one or more application specific integrated circuits (ASICs)) configured to perform one or more functions of the AI/ML engine **1030**.

(95) In an example operation, the light source **1004** may be configured to generate input light **1006** and to direct the input light to the light modulator **1008**. For example, the input light **1006** may be directed to the light modulator **1008** via an optical fiber and/or one or more optical elements (e.g., mirrors and/or focusing lenses). The light modulator **1008** may be configured to produce modulated light **1010** based on the input light **1006** and to direct the modulated light **1010** towards the detector **1012** to produce an output **1014**. For example, the modulated light **1010** may be directed to the detector **1012** via an optical fiber and/or one or more optical elements (e.g., mirrors and/or focusing lenses). In examples in which the light modulator **1008** is a FT-IR interferometer or Fabry-Perot interferometer, the modulated light **1010** may correspond to interference beams produced over time with an OPD between beams. The output **1014** of the detector **1012** may then correspond to an interferogram. In examples in which the light modulator **1008** is a diffraction grating, the modulated light **1010** may correspond to diffracted light across a plurality of wavelengths. The output **1014** of the detector **1012** may then correspond to an image representing the light intensity at each wavelength point on the detector **1012**.

(96) The output **1014** of the detector **1012** may then be output from the electronics interface **1016** to the DSP unit **1018**. The optical signal processing unit **1020** within the DSP unit **1018** may process the output **1014** of the detector **1012** to produce a sample spectrum (e.g., a PSD) of a sample under test (not shown). For example, the optical signal processing unit **1020** may transform the interferogram **1014** provided by the detector **1012** to a PSD using a Fast Fourier transform (FFT). The optical signal processing unit **1020** may further be configured to correct the sample spectrum based on instrumental response drifts in the spectral sensor **1002** to produce a corrected spectrum (e.g., corrected optical PSD) **1038**. For example, the optical signal processing unit **1020** may be configured to receive from the AI/ML engine **1030** a set of correction parameters (e.g., a correction signal) **1036** to be applied to the PSD to produce the corrected PSD **1038**. In an example, the AI/ML engine **1030** may receive from one or more environmental conditions sensor(s) **1026** and/or from the optical signal processing unit **1020**, respective values **1028** and/or **1024** of one or more conditions measured by the sensor(s) **1026** and/or optical signal processing unit **1020** contributing to the instrumental drifts. The AI/ML engine **1030** may further be configured to access the memory **1032** to retrieve a respective set of correction parameters **1036** from the correction matrix **1034** based on each received value **1028/1024**. The optical signal processing unit **1020** may then be configured to apply the set(s) of correction parameters **1036** to the sample spectrum (PSD) to produce the corrected spectrum (corrected PSD) **1038**.

(97) In some examples, the correction matrix may be a temperature correction matrix that is based on the wavelength cut-off of the detector (e.g., detector **1012**). The cut-off of photodetectors responsivity shifts with temperature. For example, in InGaAs detectors, the shift takes place due to heat-assisted electron generation. There is an approximately linear relation between temperature and the wavelength at 10% of the power spectral density (PSD) maximum value, denoted as $\lambda_{\text{sub.10\% PSDmax}}$, of a spectrometer that includes an InGaAs photodetector.

(98) FIGS. **11A** and **11B** are diagrams illustrating the relation between temperature and wavelength according to some aspects. FIG. **11A** illustrates the PSD of the spectrometer at two different temperatures and the corresponding extracted 10% wavelengths. The relation may be described by the equation:

$$T = A * \lambda_{\text{sub.10\% PSDmax}} + C \quad (11)$$

(99) Furthermore, as shown in FIG. **11B**, the slope A is nearly constant for the same type of detector, while C can be changing from spectrometer unit to spectrometer unit. Higher order polynomials can be used as well to increase the accuracy if needed. In principle any criteria rather

than the 10% wavelength can be used to define a threshold for the calculations of the shift.

(100) In some examples, the detector cut-off may be utilized in generating the correction matrix by extracting the change in temperature T from the change in the cut-off wavelength. In other examples, the temperature T may be measured using a dedicated temperature sensor. In the former case, in order to discern the temperature, the parameter C or other higher order polynomial fitting parameters can be calibrated for each spectrometer unit using a single calibration measurement at room temperature.

(101) FIG. 12 is a flow chart illustrating a process for on-line compensation of temperature drifts in a spectrometer according to some aspects. As described below, some or all illustrated features may be omitted in a particular implementation within the scope of the present disclosure, and some illustrated features may not be required for implementation of all examples. In some examples, the process may be performed by a processor, processing unit, or processing system of a spectrometer, or by any suitable means for carrying out the described functions.

(102) At block 1202, the processor may obtain a PSD based on an output of a detector of a spectrometer. At block 1204, the processor may obtain a temperature sensor reading. For example, the temperature sensor reading may be a temperature value provided by a dedicated temperature sensor within the spectrometer. As another example, the temperature sensor reading (indicated as a change in temperature) may be extracted by the processor based on a change in the cut-off wavelength of the spectrometer. At block 1206, the processor may enter the temperature value into an algorithm executed by the processor for correcting the PSD.

(103) At block 1208, the processor may select a set of correction parameters from a stored correction matrix based on the temperature value. The selected set of correction parameters may indicate a correction function to be applied to the PSD. For example, at 1210, the processor may calculate a drift percentage (e.g., a percentage of drift of the PSD) from the correction parameters. At 1212, the processor may divide the original PSD obtained at block 1202 by the calculated drift percentage to obtain a corrected PSD.

(104) FIG. 13 is a diagram illustrating an example of a spectrometer 1300 employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer 1300 includes a light source 1302 (e.g., a wideband light source), a light modulator 1306, a detector 1310, an electronics interface 1314, a processor 1316 and a memory 1320. The light modulator 1306 may use a spectroscopic technique, including, but not limited to, direct absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator 1306 may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The detector 1310 may correspond to, for example, to a photodetector. The memory 1320 may further store a correction matrix 1324. The correction matrix 1324 may include a look up table of sets of correction parameters (e.g., correction functions) verses temperature (T).

(105) Thermal drift in the spectrometer 1300 may occur, for example, due to heat excitation raising the temperature of the detector 1310 during operation. The heat source can be the environmental conditions or heat generated internally in the spectrometer 1300 during operation. By using a wideband light source 1302 to direct input light 1304 to the light modulator 1306 and applying a normal actuation signal 1330 to the light modulator 1306 to produce modulated light 1308 based on the input light 1304, a PSD can be generated by the processor 1316 from the detector output 1312 versus wavelength. For example, in the case of FT-IR, the light modulator 1306 may be an interferometer and the detector output may be the interferogram signal versus the interferometer mirror motion (OPD). By applying FFT, the PSD may be obtained. An analog-to-digital converter (ADC) may be used to digitize the detector output.

(106) The processor 1316 can extract the cut-off wavelength 1318 from the PSD curve and feed the

cut-off wavelength **1318** to the memory **1320**. Based on the stored relation between the temperature and the cut-off wavelength, which can be a simple linear relation as mentioned before, the processor **1316** can extract the temperature **1322** and feed the temperature **1322** to the correction matrix **1324** stored in the memory **1320**. Based on the temperature **1322**, the processor **1316** can select the set of correction parameters **1326** from the correction matrix **1324** (e.g., from a look-up table), which is fed back to the processor **1316**. The processor **1316** can then use the previously obtained PSD and the set of correction parameters **1326** to obtain a new PSD **1328** that is corrected from the temperature drift.

(107) FIG. **14** is a diagram illustrating another spectrometer **1400** employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer **1400** includes a light source **1402** (e.g., a wideband light source), a light modulator **1406**, a detector **1410**, an electronics interface **1414**, a processor **1416** and a memory **1420**. The light modulator **1406** may use a spectroscopic technique, including, but not limited to, direct absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator **1406** may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The detector **1410** may correspond to, for example, to a photodetector. The memory **1420** may further store a correction matrix **1424**. The correction matrix **1424** may include a look up table of sets of correction parameters (e.g., correction functions) verses temperature (T). (108) Again, by using a wideband light source **1402** to direct input light **1404** to the light modulator **1406** and applying a normal actuation signal **1430** to the light modulator **1406** to produce modulated light **1408** based on the input light **1404**, a PSD **1418** can be generated by the processor **1416** from the detector output **1412** versus wavelength. In the example shown in FIG. **14**, the temperature can be extracted from PSD measurement **1418** with the aid of a PLS method or other similar method. By generating a model that correlates temperature values with the measured PSDs of a specific sample, the temperature **1422** can be calculated from any PSD **1418** for the same sample without the need for calculating the detector-cut-off wavelength. Based on the temperature **1422**, the processor **1416** can select the set of correction parameters **1426** from the correction matrix **1424** (e.g., from a look-up table), which is fed back to the processor **1416**. The processor **1416** can then use the previously obtained PSD and the set of correction parameters **1426** to obtain a new PSD **1428** that is corrected from the temperature drift.

(109) FTIR spectrometers may include a temperature sensor to monitor the temperature of the spectrometer and shut it down if the temperature exceeds a specified value. Temperature sensor readings can be also used to extract the temperature of one of the spectrometer components, where:

$$T_{\text{sub.spectrometer}} = a * T_{\text{sub.sensor}} + b \quad (12)$$

(110) Other relations of higher orders or different functions can be used as well. In most of the cases, the relation is found to be approximately linear, while the y-axis crossing point, the b parameter, may change from one spectrometer unit another spectrometer unit depending on the offset calibration (or bias) of the temperature sensor used. In some cases, the gain/slope parameter a may also change from one spectrometer to another. Therefore, the change in temperature T can be extracted from the temperature sensor reading directly, while the absolute value may not be needed, and thus changes in the parameter b may not be significant. For example, the change in detector temperature $\Delta T_{\text{sub.det}}$ can be calculated from the change in the sensor temperature reading $a \Delta T_{\text{sub.sensor}}$.

(111) FIG. **15** is a diagram illustrating an example of a spectrometer **1500** employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer **1500** includes a light source **1502** (e.g., a wideband light source), a light modulator **1506**, a detector **1510**, an electronics interface **1514**, a processor **1516** and a memory **1520**. The light modulator **1506** may use a spectroscopic technique, including, but not limited to, direct

absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator **1506** may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The detector **1510** may correspond to, for example, to a photodetector. The memory **1520** may further store a correction matrix **1524**. The correction matrix **1524** may include a look up table of sets of correction parameters (e.g., correction functions) verses temperature (T). (112) By using a wideband light source **1502** to direct input light **1504** to the light modulator **1506** and applying a normal actuation signal **1532** to the light modulator **1506** to produce modulated light **1508** based on the input light **1504**, a PSD can be generated by the processor **1516** from the detector output **1512** versus wavelength. In the example shown in FIG. **15**, a temperature sensor **1518** is configured to measure a temperature value **1530** (e.g., change in temperature value) of the detector **1510** (or other component of the spectrometer **1500**). The measured temperature value **1530** (T.sub.sensor) may be fed to the memory **1520**. Based on the stored relation between the temperature sensor value (T.sub.sensor) and the detector temperature (T.sub.det), as mentioned before, the processor **1516** can extract the detector temperature **1522** and feed the detector temperature **1522** to the correction matrix **1524** stored in the memory **1520**. Based on the detector temperature **1522**, the processor **1516** can select the set of correction parameters **1526** from the correction matrix **1524** (e.g., from a look-up table), which is fed back to the processor **1516**. The processor **1516** can then use the previously obtained PSD and the set of correction parameters **1526** to obtain a new PSD **1528** that is corrected from the temperature drift.

(113) In some examples, calibration of the temperature sensor **1518** can be carried out by a few measurements to enable the electronics and spectrometer to heat up, while monitoring the temperature of the spectrometer **1500** using a calibrated temperature sensor (not shown) and comparing it to the reading of the temperature sensor **1518**.

(114) In some examples, the temperature sensor **1518** may be a thermistor or a thermocouple to measure the spectrometer temperature. However, these type of temperature sensors typically utilize a specific electronic interface that consumes power and needs a hosting package that consumes area too. Therefore, this configuration may be costly, but does provide the flexibility to choose the location of the temperature sensor in the optimal location minimizing the error between the actual temperature of the component of interest and the predicted temperature from the sensor reading.

(115) FIG. **16** is a diagram illustrating another example of a spectrometer **1600** employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer **1600** includes a light source **1602** (e.g., a wideband light source), a light modulator **1606**, a detector **1610**, an electronics interface **1614** (e.g., an ASIC chip), a processor **1618**, and a memory **1622**. The light modulator **1606** may use a spectroscopic technique, including, but not limited to, direct absorption spectroscopy, indirect absorption spectroscopy, such as photo-acoustic spectroscopy, photo-thermal spectroscopy, or Raman spectroscopy. In some examples, the light modulator **1606** may include a diffraction element, a Michelson interferometer, a Fabry-Perot cavity, a spatial light modulator, or a birefringent device. For example, the light modulator may include a MEMS interference device. The detector **1610** may correspond to, for example, to a photodetector. The memory **1622** may further store a correction matrix **1626**. The correction matrix **1626** may include a look up table of sets of correction parameters (e.g., correction functions) verses temperature (T).

(116) By using a wideband light source **1602** to direct input light **1604** to the light modulator **1606** and applying a normal actuation signal **1636** to the light modulator **1606** from actuation circuitry **1634** within the electronics interface **1614** to produce modulated light **1608** based on the input light **1604**, a PSD can be generated by the processor **1618** from the detector output **1612** versus wavelength. In the example shown in FIG. **16**, a temperature sensor **1620** configured to measure a temperature value **1628** (e.g., change in temperature value) of the spectrometer **1600** is not a

separate chip, but rather a sensor that is embedded in the electronics interface **1614**. Here, the electronics interface **1614** is a central chip including an ADC **1616** for converting the output **1612** of the detector **1610** to a digital signal for input to the processor **1618** and the actuation circuitry **1634**. In other examples, the temperature sensor **1620** may be embedded in a processing unit chip including the processor **1618** or a separate chip providing the actuation signal **1636**.

(117) The measured temperature value **1628** (T.sub.sensor) may be fed to the memory **1622**. Based on the stored relation between the temperature sensor value (T.sub.sensor) and the detector temperature (T.sub.det), as mentioned before, the processor **1618** can extract the detector temperature **1624** and feed the detector temperature **1624** to the correction matrix **1626** stored in the memory **1622**. Based on the detector temperature **1624**, the processor **1618** can select the set of correction parameters **1630** from the correction matrix **1626** (e.g., from a look-up table), which is fed back to the processor **1618**. The processor **1618** can then use the previously obtained PSD and the set of correction parameters **1630** to obtain a new PSD **1632** that is corrected from the temperature drift.

(118) FIG. **17** is a diagram illustrating another example of a spectrometer **1700** employing a dedicated temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer **1700** includes a spectral sensor **1702** including a light source **1704** (e.g., a wideband light source), a light modulator **1708** (e.g., a silicon (Si) light modulation chip), a detector **1716** and an electronics interface **1720**. In the example shown in FIG. **17**, the light modulator **1708** includes an optical MEMS device **1712** (e.g., an FT-IR MEMS-based interferometer) and light guides (e.g., optical fibers) **1710a** and **1710b** for guiding input light **1706** from the light source **1704** into the optical MEMS device **1712** and guiding modulated light **1714** (e.g., interference beams over time with OPDs therebetween) from the optical MEMS device **1712** to the detector **1716**. The light modulator **1708** may further be actuated by a control signal **1726** (e.g., actuation signal) supplied by the electronics interface **1720**. The detector **1716** may correspond to, for example, to a photodetector. The output **1718** of the detector **1716** (e.g., an interferogram) may be provided to the electronics interface **1720**, which may provide the interferogram **1718** (e.g., a digital signal representing the interferogram) to a processor (not shown).

(119) In the example shown in FIG. **17**, a temperature sensor **1722** configured to measure a temperature value **1724** (e.g., change in temperature value) of the spectrometer **1700** is fabricated on the light modulation chip **1708**. For example, the temperature sensor **1722** may be a piezoresistive temperature sensor fabricated on the same MEMS chip used in the light modulation element. The piezoresistive temperature sensor **1722** can be made of a double-layer cantilever beam, where each layer has a different thermal expansion coefficient. When the temperature changes, the cantilever beam will bend up or down based on the sign of the temperature change. This bending will cause strain. Hence, by placing a piezoresistive element at the maximum strain position near the fixed end of the cantilever, the resistance of the piezoresistive element will change and, hence, the temperature can be measured. The piezoresistive element can be made on the crystalline silicon of the silicon wafer of the light modulation chip **1708** using, for example, ion implantation of p-type impurities. In some examples, four piezoresistive elements can be used to form a Wheatstone bridge for better resistance change sensing. By placing the temperature sensor **1722** on the light modulation chip **1708**, the resulting temperature value **1722** reflects the actual temperature value of the light modulator **1708**. In addition, fabrication of a piezoresistive temperature sensor is compatible with light modulation element fabrication, as it requires a few simple surface micromachining steps.

(120) Each photodetector has a shunt resistance. Shunt resistance decreases with temperature increase. If this resistance is calculated and calibrated with temperature values, it can be used to calculate the temperature. However, it may not be practical to measure the shunt resistance of the detector while being in operation. It is also known that the thermal noise of the detector is

proportional to shunt resistance. Therefore, calculating the noise level can be used as a calibration for shunt resistance, and hence, a calibration for temperature. In order to calculate the root mean square (RMS) noise level, and consequently extracting the corresponding temperature, a dark measurement is obtained by the photodetector.

(121) FIGS. **18A** and **18B** are diagrams illustrating another example of a spectrometer **1800** employing the detector as a temperature sensor to be used for the correction of thermal drift according to some aspects. The spectrometer **1800** includes a light source **1806** (e.g., a wideband light source), a light modulator **1808**, a detector **1810**, an electronics interface **1822**, and a DSP Unit **1826** (e.g., a processor).

(122) As shown in FIG. **18A**, the relation between dark measurements and temperature may be calibrated using a temperature sensor **1830** embedded in or coupled to the spectrometer **1800**. For each dark measurement **1812** (e.g., without illumination by the light source **1806**) obtained by the spectrometer **1800**, a temperature reading **1814** is obtained by the temperature sensor **1830**. Based on the dark measurement, the RMS noise level may be calculated (e.g., by the processor/DSP unit **1826**) and both the RMS noise level and corresponding temperature reading may be stored in a matrix **1816**. The matrix **1816** may then be fed into a regression module **1818** to extract the relation **1820** between the RMS noise level and temperature. The relation **1820** may be stored, for example, within a memory of the spectrometer **1800** to be used during on-line compensation of illuminated spectral measurements.

(123) For example, as shown in FIG. **18B**, a spectral sensor **1802** including a light modulation module **1832** including, for example, at least the light modulator **1808** and the detector **1810**, may be configured to obtain a dark interferogram **1812** that is provided by the electronics interface **1822** to the DSP unit **1826**. The dark interferogram **1812** may be obtained, for example, immediately prior to obtaining an illuminated interferogram **1824** of a sample under test. Based on the stored relation **1820** between the RMS noise level of the dark interferogram **1812** and the temperature, as mentioned before, the DSP unit **1826** can extract the temperature **1814** and feed the temperature **1814** to a correction matrix (not shown) to select a set of correction parameters therefrom. The DSP unit **1826** can then use the illuminated interferogram **1824** (e.g., the PSD obtained from the illuminated interferogram) and the set of correction parameters to obtain a new PSD **1828** that is corrected from the temperature drift.

(124) In some examples, the application of the set of correction parameters (e.g., a correction signal) may include three steps. The first step includes measuring the spectrometer temperature using any of the aforementioned mechanisms. In the second step, the temperature value can be delivered as a feedback to tailor the correction matrix that corresponds to the spectrometer temperature. In the third step, the tailored correction matrix is applied to the original PSD to produce the corrected PSD.

(125) For example, the stored correction matrix can be retrieved for any temperature measurement and the temperature drift can then be calculated at all wavelengths for the measured temperature. The thermal drift is additive in absorbance and multiplicative in reflection, transmission and PSD domains. Therefore, the correction can be applied on the PSD itself, and then transformed into the needed response to save processing time. In an example, the correction can be done according to the following equation:

$$PSD_{c.sub.orrected} = PSD_{sub.orginal} / ((S_{sub.dpa} * \Delta T)) \quad (13)$$

where $S_{sub.apa}$ is the spectrum of drift per degree Celsius.

(126) FIG. **19** is a diagram illustrating a thermal drift correction process using a third order polynomial fitting according to some aspects. In the example shown in FIG. **19**, a background measurement **1904** may be taken at, for example, $T=25^{\circ}\text{C}$. The temperature value $T_{sub.BG}$ **1916** (e.g., $T=25^{\circ}\text{C}$.) of the background measurement **1904** can be fed into the correction matrix **1906**, along with a temperature value **1912** of a sample measurement **1902**. Based on the temperature values **1912** and **1916**, a set of correction parameters (e.g., a correction function) **1918** may be

provided to a compensation unit **1908** (e.g., a processor) configured to correct for the thermal drift in the sample measurement **1902** based on the correction function **1918** and the background measurement **1904**. As shown in FIG. **20**, an original response (Experimental) corresponding to the thermal drift taken from a background measurement **1904** using a background temperature T.sub.BG of 10° C. is illustrated along with a corrected response (Fitting corrected spectra). The corrected response repeated on approximately 100 different spectrometer units showed a flat spectrum with no second order drifts and even the first order drifts were decreased down to 1/10 in all tested units.

(127) Referring now to FIG. **21**, in some examples, the stored correction matrix can be retrieved and tailored for correction according to the following equation:

$$PSD.sub.corrected(\lambda) = PSD.sub.orginal(\lambda) / ((S.sub.dpa(\lambda - \lambda.sub.sh1) * \Delta T) * (a) * \Delta T.sup.b) \quad (14)$$

where a and b are equal to fitting parameters that can be set to unity if not needed. However, they can be used as a tuning factor for better correction to account for the variations from spectrometer unit to spectrometer unit. As the drift as a function of temperature may change from unit to unit, thus, a and b can be used to account for a nonlinear temperature-drift relation. Moreover, the position of the dip changes across units, but it can be determined using a few measurements, then a shift ($\lambda.sub.sh1$) in the position of the correction matrix can be performed to produce a global correction matrix. As can be seen in FIG. **21**, tuning the value of a and b in the global correction matrix leads to a better correction performance. The global correction matrix was applied on **130** miniaturized near infrared (NIR) spectrometers and the dip drift decreased to less than 15% of its value in most of them.

(128) Referring now to FIG. **22**, the detector cut-off shift feature is not linear through the temperature range. Therefore, the temperature range can be divided into regions and a piecewise correction function can be used to cover the whole temperature range and account for the change in detector cut-off shift feature in each region. The correction function can be retrieved according to the temperature value measured by one of the aforementioned mechanisms. For example, temperatures from 20 degrees to 25 degrees can have a specific correction function. Then, correction can be applied according to the following equation:

$$PSD.sub.corrected(\lambda) = PSD.sub.orginal(\lambda) / (S.sub.apa(\lambda - \lambda.sub.sh2) * (a) * \Delta T.sup.b) \quad (15)$$

(129) A shift ($\lambda.sub.sh2$) in the position of the correction matrix is needed as in the case of dip correction. Moreover, a and b may be used to improve correction, as in the case of dip correction. This correction was applied on 102 units and cut-off drift decreased to less than 15% of its value in most of the miniaturized spectrometers.

(130) FIG. **23** is a graph illustrating a combination of the two-decomposition corrections shown in FIGS. **21** and **22** at two different values of ΔT . As can be seen in FIG. **23**, the higher order drifts were corrected and the only remaining drift component is a first order baseline drift that can be removed by simple pre-processing before chemometrics analysis.

(131) Background measurements may enable the instrumental response to be removed, thus allowing only the sample response to be measured. Background measurements typically have approximately the same instrumental response as the sample measurements, though as discussed herein, the instrumental response may also change with environmental conditions. In some examples, a background measurement may be taken every certain period of time, e.g., one hour. However, some applications require using the same background measurement for a longer period of time. Hence, a generalized background measurement may be acquired by measuring all the instrumental response drift causes, making models for them and compensating these drifts to restore the same instrumental response of the background measurement.

(132) The main conditions contributing to instrumental response change include, as discussed above, temperature variations, humidity variations, light source efficiency and optical misalignment. For example, humidity can cause some absorption features and photometric errors. Optical misalignment can cause baseline drifts especially in the shorter wavelengths. In some

examples, models (e.g., correction matrices) for these other conditions can be generated in the same way used for temperature drift compensation discussed above.

(133) FIG. **24** is a diagram illustrating an example of a spectrometer **2400** including a plurality of sensors according to some aspects. The spectrometer **2400** includes a spectral sensor **2402**, an electronics interface **2416**, a processor **2418**, a plurality of sensors **2420**, **2422**, and **2424**, and a memory **2426**. The plurality of sensors include different sensors **2420**, **2422**, and **2424** for temperature, humidity, and source consumption and optical alignment (e.g., light source efficiency and misalignment), respectively. The memory **2426** may store a correction matrix **2432** including, for example, a lookup table of correction parameters mapped to sensor readings. In addition, the memory **2426** may further store a factory-saved background measurement **2428** of a stored background measurement. In some examples, the stored background measurement **2428** may be modified to include current variations with respect to stored background conditions.

(134) The spectral sensor **2402** includes a light source **2404** (e.g., a wideband light source), a light modulator **2408**, and a detector **2412**. The light source **2404** may be configured to direct input light **2406** to the light modulator **2408**. The light modulator **2408** may then produce modulated light **2410** (e.g., interference beams over time with OPDs therebetween) based on the input light **2406** and may further direct the modulated light **2410** to the detector **2412**. The light modulator **2408** may further be actuated by an actuation signal **2438** provided by an electronics interface **2416**. The detector **2412** may correspond to, for example, to a photodetector. The output **2414** of the detector **2412** (e.g., an interferogram) may be provided to the electronics interface **2416**, which may provide the interferogram **2414** (e.g., a digital signal representing the interferogram) to the processor **2418**.

(135) The processor **2418** may process the output **244** of the detector **2412** to produce a sample spectrum (e.g., a PSD) of a sample under test (not shown). For example, the processor **2418** may transform the interferogram **2414** provided by the detector **2412** to a PSD using a Fast Fourier transform (FFT). The processor **2418** may further be configured to correct the sample spectrum based on instrumental response drifts in the spectral sensor **2402** and the factory stored background **2428** to produce a corrected spectrum (e.g., corrected optical PSD) **2436**. For example, one or more of the sensors **2420**, **2422**, and/or **2424** may obtain a respective sensor reading (e.g., value), which may be fed to a sensor readings reception algorithm **2430** in the memory **2426**. The processor **2418** may be configured to execute the sensor readings reception algorithm **2430** to feed the sensor reading(s) to the correction matrix **2432** stored in the memory **2426**. Based on the sensor reading(s), the processor **2418** can select the set(s) of correction parameters **2434** from the correction matrix **2432** (e.g., from a look-up table), which is fed back to the processor **2418**. The processor **2418** can then use the previously obtained PSD, the factory-saved background measurement **2428**, and the set(s) of correction parameters **2434** to obtain a new PSD **2436** that is corrected from the instrumental drift(s).

(136) Creating the correction matrix involves not only the total measured intensity at the detector output, but also the power spectral density (PSD), at each wavelength. Since the drift may change from spectrometer unit to spectrometer unit, a unique correction matrix can be created for each unit. The correction matrix can be calculated by measuring the instrumental response while sweeping across temperature. The responses can then be stored and processed to obtain a correction function (e.g., indicated by the correction matrix) that relates the thermal drift of the PSD at different wavelengths across temperatures.

(137) FIG. **25** is a flow chart illustrating a process for generating a correction matrix for on-line compensation of temperature drifts according to some aspects. As described below, some or all illustrated features may be omitted in a particular implementation within the scope of the present disclosure, and some illustrated features may not be required for implementation of all examples. In some examples, the process may be performed by a processor, processing unit, or processing system of a spectrometer, or by any suitable means for carrying out the described functions.

(138) At block **2502**, the processor may take a spectrometer measurement (e.g., a PSD) of a

sample. In addition, at block **2504**, the spectrometer temperature may be measured (e.g., by a dedicated temperature sensor within the spectrometer). At block **2506**, the temperature value may be assigned to the spectrometer measurement.

(139) At block **2508**, the processor may determine whether the temperature range of interest is covered. If the temperature range of interest has not been covered (N branch of block **2508**), at block **2510**, the spectrometer may be heated and the process repeated to assign a respective temperature value across the range of interest to each spectrometer measurement. Once the temperature range of interest has been covered (Y branch of block **2508**), at block **2512**, the processor may extract the relation between drift and temperature, and at block **2514**, store the extracted relation as the correction matrix.

(140) Sweeping of the temperature to generate the correction matrix can be performed in different ways. FIG. **26** is a diagram illustrating an example of a system **2600** configured to sweep the temperature of a spectrometer **2602** to generate a correction matrix according to some aspects. In the example shown in FIG. **26**, the spectrometer **2602** includes a light source **2606**, a light modulator **2608**, and a detector **2610**. The spectrometer **2602** may be inserted into an oven or a temperature chamber **2604** having a controller **2622** configured to control the spectrometer temperature by controlling the chamber temperature. A temperature sensor **2624** in the chamber **2604** (or the spectrometer **2602**), the former being illustrated, may be configured to measure a temperature (e.g., obtain a temperature reading **2614**) of the chamber **2604**/spectrometer **2602** for each spectrometer measurement **2612** (e.g., PSD versus wavelength at that temperature). Both the spectrometer measurement **2612** and the corresponding temperature reading **2614** may be stored in a matrix **2616**. To cover all possible temperature conditions, the matrix **2616** may then be fed into a regression module **2618** to extract the relation **2620** between the spectrometer measurement **2612** and temperature **2614**. The relation **2620** may be stored, for example, as the correction matrix within a memory of the spectrometer **2602** to be used during on-line compensation.

(141) FIG. **27** is a diagram illustrating another example of a system **2700** configured to sweep the temperature of a spectrometer **2702** to generate a correction matrix according to some aspects. In the example shown in FIG. **27**, the spectrometer **2702** includes a light source **2706**, a light modulator **2708**, and a detector **2710**. Instead of inserting the spectrometer **2702** into an oven or a temperature chamber, as shown in FIG. **26**, in the example shown in FIG. **27**, a Peltier element in a thermos-electric cooler or heater (TEC) **2704** may be attached to the detector **2710** or placed in close proximity thereto. A temperature sensor **2722** attached to or embedded in the spectrometer **2702**, the former being illustrated, may be configured to measure a temperature (e.g., obtain a temperature reading **2714**) of the spectrometer **2702** for each spectrometer measurement **2712** (e.g., PSD versus wavelength at that temperature). Both the spectrometer measurement **2712** and the corresponding temperature reading **2714** may be stored in a matrix **2716**. To cover all possible temperature conditions, the matrix **2716** may then be fed into a regression module **2718** to extract the relation **2720** between the spectrometer measurement **2712** and temperature **2714**. The relation **2720** may be stored, for example, as the correction matrix within a memory of the spectrometer **2702** to be used during on-line compensation.

(142) FIGS. **28A** and **28B** are diagrams illustrating another example of a system **2800** configured to sweep the temperature of a spectrometer **2802** to generate a correction matrix according to some aspects. In the example shown in FIGS. **28A** and **28B**, the heat energy emerging from electronics (e.g., electronic components **2806** producing heat) and a light source **2804** in the spectrometer **2802** can be exploited to raise the temperature of temperature sensitive elements **2810** in the spectrometer **2802**, such as the photodetector or the light modulation/MEMS chip. Heating can further be accelerated by using a thermally insulating enclosure **2812** to prevent heat from escaping outside the spectrometer **2802**.

(143) A temperature sensor **2824** within the enclosure **2812** and/or attached to or embedded in the spectrometer **2802** may be configured to measure a temperature (e.g., obtain a temperature reading

2816) of the spectrometer **2802** for each spectrometer measurement **2814** (e.g., PSD verses wavelength at that temperature). Both the spectrometer measurement **2814** and the corresponding temperature reading **2816** may be stored in a matrix **2818**. To cover all possible temperature conditions, the matrix **2818** may then be fed into a regression module **2820** to extract the relation **2822** between the spectrometer measurement **2814** and temperature **2816**. The relation **2822** may be stored, for example, as the correction matrix within a memory of the spectrometer **2802** to be used during on-line compensation.

(144) In some examples, the correction matrix can include coefficients of fitted functions that relate the PSD change of each wavelength/wavenumber point with temperature. These fitted functions can be polynomial, exponential, or others, depending on the thermal drift characteristics of the instrument.

(145) FIG. **29** is a diagram illustrating an example process flow for generating the correction matrix including coefficients of fitted functions as the correction parameters, according to some aspects. In the example shown in FIG. **29**, a control module **2902** (e.g., a controller) may be configured to control a temperature sweep of a spectrometer **2904** (e.g., from **T1** to **T2**). For example, the control module **2902** may be configured to control a scan time or frequency of capturing spectrometer measurements and corresponding temperature values. In some examples, the control module **2902** may be configured to perform continuous or periodic multiple scans of the spectrometer **2904**. The spectrometer measurements (e.g., PSD) verses temperature (**T**) **2906** may be output by the spectrometer **2904** and provided to a post processing unit **2908** configured to calculate the correction matrix using an N^{sup}.th order polynomial fitting. The correction matrix **2912** may then be output by the post processing unit **2908** and stored in a memory (not shown) of the spectrometer **2904** by a memory controller **2910**. For example, the correction matrix **2912** may include the drift fitting coefficients for each wavelength point as a function of temperature (e.g., based on a polynomial fitting relation).

(146) FIG. **30** is a graph illustrating an example of a third-order polynomial fitting for the thermal drift at the 1850 nm wavelength point of an NIR spectrometer according to some aspects. In the example shown in FIG. **30**, the minimum temperature of -10 degrees is taken as a reference.

(147) Although generating a unique correction matrix for each spectrometer unit may be accurate, this process may not be practical in some cases as it requires a relatively long testing time, which may slow down the production line of the spectrometer units. Therefore, in some examples a general (global) correction matrix can be calculated for the common or mean behaviour of the spectrometer units and production line testing of each spectrometer unit may focus on the variation between spectrometer units that can be extracted in a relatively short time. The general correction matrix and the features that vary from spectrometer unit to spectrometer unit may be extracted with a machine learning algorithm, which may use less extensive and less time-consuming testing to extract the non-common features that are unique to each unit.

(148) FIG. **31** is a diagram illustrating an example of a system **3100** configured to generate a global correction matrix according to some aspects. In the example shown in FIG. **31**, each of a plurality of spectrometer units **3102a**, **3102b**, . . . , **3102N** may obtain spectrometer measurement/temperature data **3108** (e.g., PSD verses temperature) and transmit the spectrometer measurement/temperature data **3108** over a network (e.g., via cloud **3106**) to an AI/ML engine **3104** (e.g., a neural network). The AI/ML engine **3104** may be configured to fit a respective correction matrix for each spectrometer unit **3102a**, **3102b**, . . . , **3102N** to produce fitting correction matrices **3110** that may be used to build a ML model to produce a global correction matrix. The AI/ML engine **3104** can further be configured to modify the global correction matrix for each spectrometer unit **3102a**, **3102b**, . . . , **3102N** using minimal spectrometer measurement/temperature data **3108** from each spectrometer unit **3102a**, **3102b**, . . . , **3102N** to produce respective updated correction matrices **3112** for each spectrometer unit **3102a**, **3102b**, . . . , **3102N**.

(149) FIG. 32 is a diagram illustrating another example of a system 3200 configured to generate a global correction matrix according to some aspects. In the example shown in FIG. 32, each of a plurality of spectrometer units 3202a, 3202b, . . . , 3202N may obtain spectrometer measurement/temperature data 3206 (e.g., PSD verses temperature) and transmit the spectrometer measurement/temperature data 3206 over a network (e.g., via cloud 3205) to an AI/ML engine (e.g., a neural network), represented by boxes 3208 and 3210. The AI/ML engine at box 3208 may be configured to fit a respective correction matrix for each spectrometer unit 3202a, 3202b, . . . , 3202N and produce an average correction matrix (e.g., a global correction matrix) based on the respective correction matrices. The AI/ML engine at box 3210 can further be configured to adaptively scale the average correction matrix using two spectrometer measurements at two different temperatures for each spectrometer unit 3202a, 3202b, . . . , 3202N and compare the drift at each wavelength point with the expected drift from the average correction matrix. Then, the ratio between the actual and expected drifts can be used to scale the average correction matrix to produce a respective updated correction matrix 3212 for each of the spectrometer units 3202a, 3202b, . . . , 3202N. In some examples, an average correction matrix can be calculated for each production lot to account for the differences in drifts from lot to lot, hence, decreasing the error in correction. In some examples, this may decrease the testing time per unit as fewer measurements may be needed to spot the drift variations for each spectrometer unit.

(150) The thermal drift of spectrometers includes different superimposed components. Some of these components are approximately constant for all units, for example the detector drift features, while others vary from one spectrometer to another, for example the MEMS drift features in miniaturized spectrometers. It is possible to decompose the drift components using wavelet transform, polynomial fitting, morphological weighted penalized least squares, adaptive iterative reweight penalized least squares, automatic iterative moving average, asymmetric least squares or any another decomposition method. The example below is based on an adaptive iteratively reweighted penalized least squares (AirPLS) algorithm.

(151) The PLS algorithm has a roughness term:

$$(152) \quad R = \sum_{i=2}^m (z_i - z_{i-1})^2 \quad (16)$$

(153) In addition, the PLS algorithm has a fidelity term:

$$(154) \quad F = \sum_{i=1}^m w_i (x_i - z_i)^2 \quad (17)$$

where x is the vector of the measured spectrum, z is the fitted vector, and w is the fidelity weight. A balanced combination of fidelity and roughness is given by $Q=F+IR$, where l is a user defined parameter that controls the roughness of the fitted curve. Taking a partial derivative of Q with respect to z and setting the derivative to zero gets $(W+1 D'D) \cdot z = Wx$. A traditional PLS algorithm solves the last equation to get the fitted curve z and by changing it can be used as a smoothing method. However, if W can be tuned to detect the maximas and prevent the fitted curve from following them, PLS can be used as a baseline extraction method. Although many methods exist to detect the optimal W automatically for each curve, AirPLS is the simplest and most effective in that AirPLS uses an iterative algorithm to adaptively change the value of W in the following equation:

$$(155) \quad Q^t = \sum_{i=1}^m w_i^t \cdot \sum_{j=2}^m (x_j - z_j^t)^2 + l \sum_{j=2}^m (z_j^t - z_{j-1}^t)^2 \quad (18)$$

where W is defined according to the following iteration equation:

$$(156) \quad w_i^t = \begin{cases} 0 & x_i \geq z_i^{t-1} \\ e^{\frac{t(x_i - z_i^{t-1})}{\sum_{i=1}^m d_i^t \cdot \sum_{i=1}^m d_i^t}} & x_i < z_i^{t-1} \end{cases} \quad (19)$$

(157) Using an AirPLS method, a correction matrix for only the high order global features can be built. After applying this correction matrix and removing the global features, only a linear baseline

drift may be left in the response. Linear baseline drift can be easily corrected using any simple pre-processing before chemometrics analysis of the spectral data.

(158) In extended InGaAs NIR detectors, a feature appears in the middle of the spectrum when the temperature varies, as shown in FIG. 33, which illustrates the thermal drift of a typical InGaAs PIN detector responsivity. This feature represents a reduction in responsivity with the temperature at a specific position. This dip feature represents a second-order drift that is not easily recognized as a baseline drift in chemometrics analysis. In some examples, the AirPLS method can also be exploited to extract a correction matrix for this feature.

(159) For example, the ratio between the measured PSD at room temperature and a higher temperature by $\Delta T=25^\circ \text{C}$. can be calculated as

$$(160) \%S = \frac{\text{PSD}_{T_0 + T}}{\text{PSD}_{T_0}} \times 100 \quad (20)$$

(161) Ideally % S should be 100% corresponding to the 100% line. Then, denoising of S can be performed by smoothing of the spectrum using the AirPLS method. After that, the drifted 100% line can be converted to absorbance according to:

$$A = 2 - \log_{10}(\% S) \quad (21)$$

(162) Then, the AirPLS method is used, as shown in FIGS. 34A and 34B, to separate the baseline first order drift from the dip higher order drift. In FIG. 34A, the dotted lines represent the first-order baseline drift in the absorbance domain, while the solid line represents the original drift. FIG. 34B illustrates the result of subtracting the baseline first-order drift from the original drift and represents the dip feature of the detector near the responsivity knee around 1850 nm.

(163) Clipping of the undesired range of wavelengths can then be carried out, and the 100% line can then be converted back to percentage according to:

$$S_{\text{sub.d}} = 10^{\frac{2-A_{\text{sup.drift}}}{2}} \quad (22)$$

(164) The drift function per degree can then be calculated according to:

$$(165) S_{\text{dpd}} = 1 - \frac{100 - S_d}{T} \quad (23)$$

(166) By repeating this algorithm on a number of different spectrometer units, the average correction matrix can be extracted for the common drift response, as shown in FIG. 35. For example, FIG. 35 is a graph illustrating the common (average) correction matrix for the dip drift per degree Celsius according to some aspects.

(167) The position of the detector feature may change from spectrometer unit to spectrometer unit. Therefore, the position of the detector dip feature can be detected and then the correction function can be repositioned based on that. This can be performed using two measurements at two different temperatures of a standard reference sample, such as using a 95% diffuse reflection standard in case of reflection-mode spectrometers. The position can be defined by applying the dip feature extraction algorithm on two or more measurements. Then, the slope of the dip feature

$$(168) \frac{\partial S_d}{\partial}$$

can be calculated and the wavelength that corresponds to the value of zero slope in a range of wavelengths (for example 1750 nm to 1900 nm) can correspond to the feature minima, as shown in FIG. 36. For example, FIG. 36 is a graph illustrating a mechanism for finding the detector feature position using the slope of the detector drift according to some aspects.

(169) The detector dip feature position may be also determined by subtracting the measurement with higher temperature from the background. The feature minimum is at the minimum value of the resulted spectrum, as shown in FIG. 37. This position value can then be used to shift the correction file to the correct position. In some examples, this process may be performed only one time for each lot, as the position of the detector dip feature does not change dramatically in the same lot.

(170) In most PIN photodiode IR detectors, responsivity increases with temperature at longer wavelengths, which causes a shift in the cut-off wavelength of the detector. This positive temperature coefficient at longer wavelengths is caused by the heat-assisted generation of carriers

in the depletion region of the PIN diode, or can be explained by the reduction in the band gap with temperature. As a result, photocurrent corresponding to the longer wavelength photons increases. To extract a correction matrix for the responsivity cut-off shift, the following equation may be used:

$$(171) \quad S = \frac{PSD_{T = \text{high}}}{PSD_{T = \text{low}}} \quad (24)$$

(172) With $dT=25^{\circ}$ C. between the background measurement and the spectrometer measurement and smoothing of this spectrum using the AirPLS method, the position of cut off drift feature shifts with temperature is shown in FIGS. 38A and 38B. FIGS. 38A and 38B are graphs illustrating the extraction of detector higher-order thermal drift caused by cut-off shift with the temperature at different temperatures according to some aspects. In FIG. 38A, the dotted lines represent the cut-off drift in the reflectance domain after removing the features that change from spectrometer unit to spectrometer unit, while the solid line is the original cut-off drift. In FIG. 38B, the same dotted line as in FIG. 38A is shown; however, FIG. 38B illustrates the feature of the cut-off drift and how its slope changes and its position shifts at different temperatures.

(173) A correction matrix can be extracted for multiple temperature points with a certain temperature change/step (for example 5 degrees). This algorithm can be repeated on certain number of different spectrometer units (for example 10 units) and the average correction matrix can be saved.

(174) FIG. 39 is a diagram illustrating another example of a system 3900 configured to generate a global correction matrix according to some aspects. In the example shown in FIG. 39, with the aid of physical equations (governing equations) 3910 that govern the thermal drift in spectrometers' photodetectors and other components, an AI/ML engine (e.g., a neural network) 3904 can create a guided machine learning (ML) algorithm to generate the thermal drift model with a few successive measurements. The ML algorithm can be trained by feeding an enough amount of spectrometry data linked to temperature values (e.g., PDS, T data) 3908. The data 3908 can be collected from the production line or from a plurality of spectrometer units 3902a, 3902b, . . . , 3902N by connecting the units 3902a, 3902b, . . . , 3902N to the cloud 3906 and sending their temperature states and the measured power spectral density in the presence of a reference sample, the latter being illustrated in FIG. 39. In addition, the ordinary performance tests, whether production line or calibration at spectrometers, which are done on any spectrometer may be valuable for the ML training process. This data may be stored in an online cloud for future usage.

(175) As indicated above, the ML algorithm training can be enhanced and take less time if provided with the governing equations 3910 of thermal drift in the spectrometer. With the aid of these equations 3910, the ML training process is only looking for the fitting parameters in the equations with the least provided data. Based on the updated ML model that is online, a feedback to the cloud 3906 can be optionally used to improve the on-line compensation for instrumental drifts at the user side (e.g., during operation of the spectrometer units 3902a, 3902b, . . . , 3902N). For example, instrumental response may change with the aging of the spectrometer, which may decrease the performance of thermal drift correction algorithm. With the aid of the ML algorithm on the cloud, each spectrometer unit 3902a, 3902b, . . . , 3902N may be recalibrated. For example, the AI/ML engine 3904 can be configured to use a few measurements with corresponding temperatures of each spectrometer unit to provide respective updated correction matrices 3912 for each spectrometer unit 3902a, 3902b, . . . , 3902N.

(176) Within the present disclosure, the word “exemplary” is used to mean “serving as an example, instance, or illustration.” Any implementation or aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects of the disclosure. Likewise, the term “aspects” does not require that all aspects of the disclosure include the discussed feature, advantage or mode of operation. The term “coupled” is used herein to refer to the direct or indirect coupling between two objects. For example, if object A physically touches object B, and

object B touches object C, then objects A and C may still be considered coupled to one another even if they do not directly physically touch each other. For instance, a first object may be coupled to a second object even though the first object is never directly physically in contact with the second object. The terms “circuit” and “circuitry” are used broadly, and intended to include both hardware implementations of electrical devices and conductors that, when connected and configured, enable the performance of the functions described in the present disclosure, without limitation as to the type of electronic circuits, as well as software implementations of information and instructions that, when executed by a processor, enable the performance of the functions described in the present disclosure.

(177) One or more of the components, steps, features and/or functions illustrated in FIGS. 1-39 may be rearranged and/or combined into a single component, step, feature or function or embodied in several components, steps, or functions. Additional elements, components, steps, and/or functions may also be added without departing from novel features disclosed herein. The apparatus, devices, and/or components illustrated in FIGS. 1-39 may be configured to perform one or more of the methods, features, or steps described herein. The novel algorithms described herein may also be efficiently implemented in software and/or embedded in hardware.

(178) It is to be understood that the specific order or hierarchy of steps in the methods disclosed is an illustration of exemplary processes. Based upon design preferences, it is understood that the specific order or hierarchy of steps in the methods may be rearranged. The accompanying method claims present elements of the various steps in a sample order, and are not meant to be limited to the specific order or hierarchy presented unless specifically recited therein.

(179) The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but are to be accorded the full scope consistent with the language of the claims, wherein reference to an element in the singular is not intended to mean “one and only one” unless specifically so stated, but rather “one or more.” Unless specifically stated otherwise, the term “some” refers to one or more. A phrase referring to “at least one of” a list of items refers to any combination of those items, including single members. As an example, “at least one of: a, b, or c” is intended to cover: a; b; c; a and b; a and c; b and c; and a, b and c. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. No claim element is to be construed under the provisions of 35 U.S.C. § 112(f) unless the element is expressly recited using the phrase “means for” or, in the case of a method claim, the element is recited using the phrase “step for.”

Claims

1. A spectrometer, comprising: a light modulator optically coupled to receive input light and to produce modulated light based on the input light; a detector optically coupled to detect the modulated light in presence of a sample and to produce an output based on the modulated light; a sensor configured to obtain a value of a condition contributing to instrumental drifts in the spectrometer; a memory configured to store a correction matrix associating a plurality of sets of correction parameters with sensor values; and a processor coupled to the detector and configured to extract a set of correction parameters of the plurality of sets of correction parameters from the correction matrix based on the value, the processor further configured to calculate a drift percentage resulting from the instrumental drifts from the set of correction parameters and to divide

the output of the detector by the calculated drift percentage to correct the instrumental drifts across all components of the spectrometer including the detector and the light modulator to produce a corrected spectrum of the sample.

2. The spectrometer of claim 1, wherein the value comprises a temperature value.

3. The spectrometer of claim 2, wherein the memory is further configured to store a mapping between temperature values and detector cut-off wavelengths, wherein the sensor comprises the detector and the processor, the processor being further configured to: generate a power spectral density (PSD) from the output of the detector versus wavelength and to extract a detector cut-off wavelength from the PSD; extract the temperature value from the memory based on the mapping; and obtain a new PSD corresponding to the corrected spectrum based on the set of correction parameters associated with the temperature value.

4. The spectrometer of claim 2, wherein the memory is further configured to store a mapping between temperature values and power spectral densities (PSDs) of a sample, wherein the sensor comprises the detector and the processor, the processor being further configured to: generate a power spectral density (PSD) from the output of the detector versus wavelength; extract the temperature value from the memory based on the mapping; and obtain a new PSD corresponding to the corrected spectrum based on the set of correction parameters associated with the temperature value.

5. The spectrometer of claim 2, wherein the sensor comprises a temperature sensor configured to obtain the temperature value.

6. The spectrometer of claim 5, wherein the temperature value corresponds to a first change in detector temperature calculated from a second change in sensor temperature reading of the temperature sensor.

7. The spectrometer of claim 5, wherein the temperature sensor comprises a thermistor or thermocouple configured to measure the temperature value of the spectrometer.

8. The spectrometer of claim 5, wherein the temperature sensor is embedded in a processing unit chip comprising the processor or a control chip of the spectrometer configured to control at least the light modulator.

9. The spectrometer of claim 5, wherein the temperature sensor comprises a piezoresistive temperature sensor fabricated on a micro-electro-mechanical systems (MEMS) chip comprising the light modulator.

10. The spectrometer of claim 2, wherein the memory is further configured to store a mapping between root mean square (RMS) noise levels proportional to shunt resistance values of the detector and temperature values, wherein the sensor comprises the detector and the processor, the detector configured to produce a dark interferogram in an absence of light, the processor being further configured to: process the dark interferogram to calculate an RMS noise level; extract the temperature value based on the mapping; and obtain an optical power spectral density (PSD) corresponding to the corrected spectrum based on the output of the detector and the set of correction parameters associated with the temperature value.

11. The spectrometer of claim 2, wherein the processor is configured to generate a power spectral density (PSD) based on the output of the detector and to transform the PSD to produce a corrected PSD corresponding to the corrected spectrum based on the set of correction parameters.

12. The spectrometer of claim 11, wherein the detector is further configured to produce a background measurement at a fixed temperature and the processor is further configured to transform the PSD to produce the corrected PSD based on the background measurement.

13. The spectrometer of claim 11, wherein the correction matrix comprises a global correction matrix applicable to a plurality of spectrometers, and the processor is further configured to apply the set of correction parameters to the PSD based on a wavelength shift applied to the correction matrix to account for operation of the spectrometer and one or more fitting parameters configured to account for variations between the plurality of spectrometers.

14. The spectrometer of claim 2, wherein the processor is further configured to generate the correction matrix, wherein the correction matrix indicates respective thermal drift of power spectral density (PSD) at a plurality of wavelengths across a plurality of temperatures.
 15. The spectrometer of claim 14, further comprising: a temperature chamber comprising the spectrometer or a Peltier element in a thermos-electric cooler or heater (TEC) proximal to the detector configured to sweep a spectrometer temperature to produce the correction matrix.
 16. The spectrometer of claim 14, further comprising: a heat trapping enclosure surrounding the spectrometer configured to trap heat from heat generating components in the spectrometer to heat the spectrometer to produce the correction matrix.
 17. The spectrometer of claim 14, wherein the correction matrix comprises coefficients of fitted functions that relate a change in PSD of each wavelength with temperature, the fitted functions comprising polynomial or exponential fitted functions.
 18. The spectrometer of claim 2, wherein the correction matrix comprises a scaled global correction matrix scaled based on power spectral density (PSD) measurements across a plurality of wavelengths obtained at a subset of a plurality of temperatures, the scaled global correction matrix being based on a machine learning correction matrix generated based on data collected from a plurality of spectrometers.
 19. The spectrometer of claim 18, wherein the plurality of spectrometers associated with the global correction matrix are within a same production lot.
 20. The spectrometer of claim 1, wherein each of the plurality of sets of correction parameters comprises a correction function extracted from a direct fitting algorithm or a decomposition algorithm.
 21. The spectrometer of claim 1, wherein the correction matrix comprises a machine learning correction matrix generated based on data collected from a plurality of spectrometers.
 22. The spectrometer of claim 1, wherein the sensor comprises a humidity sensor, a light source efficiency sensor or an optical misalignment sensor.
 23. The spectrometer of claim 1, wherein the detector is further configured to produce a background measurement and the processor is further configured to: correct the background measurement based on the set of correction parameters to produce a corrected background measurement; and produce the corrected spectrum based on the corrected background measurement.
-