

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12408207
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Sen; Pinar et al.

Demodulation reference signal configuration for uplink messages

Abstract

Methods, systems, and devices for wireless communications are described. A user equipment (UE) may receive control signaling indicating a demodulation reference signal (DMRS) configuration for an uplink message that may indicate for the UE to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The UE may encode the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The UE may transmit the uplink message based on encoding the uplink message, and a network entity may receive and decode the uplink message. In some examples, the network entity may receive signaling that includes a set of uplink messages from different UEs. As such, the network entity may decode each, using a respective Reed-Muller (RM) code in accordance with a multi-user decoding algorithm.

Inventors: Sen; Pinar (San Diego, CA), Kwak; Yongjun (San Diego, CA), Yang; Wei (San Diego, CA), Kwon; Hwan Joon (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 87136266

Assignee: Qualcomm Incorporated (San Diego, CA)

Appl. No.: 17/844554

Filed: June 20, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230413339 A1	Dec. 21, 2023

Publication Classification

Int. Cl.: H04W74/0833 (20240101); H04L5/00 (20060101); H04W72/0453 (20230101); H04W74/00 (20090101); H04W74/08 (20090101)

U.S. Cl.:

CPC H04W74/0841 (20130101); H04L5/0051 (20130101); H04W72/0453 (20130101); H04W74/004 (20130101); H04W74/0866 (20130101);

Field of Classification Search

CPC: H04W (74/0841); H04W (72/0453); H04W (74/004); H04W (74/0866); H04L (5/0051); H04L (1/0075); H04L (1/0057)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10609735	12/2019	Ko et al.	N/A	N/A
11212053	12/2020	Manolakos et al.	N/A	N/A
2020/0267774	12/2019	Vos	N/A	H04W 74/0833
2020/0366451	12/2019	Lei	N/A	H04L 5/0094
2021/0014900	12/2020	Lei	N/A	H04W 52/42
2021/0184697	12/2020	Yang et al.	N/A	N/A
2021/0289561	12/2020	Liu	N/A	H04W 74/0833
2021/0315016	12/2020	Taherzadeh Boroujeni	N/A	H04W 74/0833
2021/0378027	12/2020	Wang	N/A	H04W 36/0077
2021/0410182	12/2020	Zhang et al.	N/A	N/A
2022/0132595	12/2021	Ko	N/A	H04L 5/0048
2022/0190906	12/2021	Haghighat	N/A	H04W 24/08
2022/0191937	12/2021	Lei	N/A	H04L 5/0091
2022/0287107	12/2021	Kim	N/A	H04W 72/0453
2022/0369375	12/2021	Lin	N/A	H04W 74/004
2023/0208556	12/2022	Zhang	375/295	H04J 13/12
2023/0291523	12/2022	Hasegawa	N/A	H04L 5/0094
2023/0318686	12/2022	Kwak	455/101	H04B 7/088
2024/0048427	12/2023	Zhang	N/A	H04L 5/0044

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
WO-2022078511	12/2021	WO	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion—PCT/US2023/024966—ISA/EPO—Sep. 25, 2023. cited by applicant

Primary Examiner: Chang; Yu-Wen

Attorney, Agent or Firm: Holland & Hart LLP

Background/Summary

FIELD OF TECHNOLOGY

(1) The following relates to wireless communications, including demodulation reference signal (DMRS) configuration for uplink messages.

BACKGROUND

(2) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations, each supporting wireless communication for communication devices, which may be known as user equipment (UE).

SUMMARY

(3) The described techniques relate to improved methods, systems, devices, and apparatuses that support demodulation reference signal (DMRS) configuration for uplink messages. For example, the described techniques provide for a network entity and a user equipment (UE) to decrease DMRS port leakage by operating in accordance with techniques for a DMRS configuration with respect to uplink messages. In some implementations, the network entity may configure the UE to perform a non-coherent physical uplink shared channel (PUSCH) transmission using Reed-Muller (RM) coding techniques. As such, the UE may encode a signal in accordance with a configured RM code and transmit the encoded signal to the network entity. On the decoding side at the network, the network entity may use non-coherent decoding on one or more encoded signals from multiple UEs in accordance with a multi-user decoding algorithm.

(4) Additionally, or alternatively, the network entity may perform channel estimation for a PUSCH using an associated physical random access channel (PRACH) portion of the uplink message. For example, the network entity may configure a UE to use a full DMRS, a partial DMRS, or no DMRS such as when transmitting a first message (e.g., Msg-A) in a PRACH procedure. In examples where the UE is configured to not transmit DMRS, the network entity may perform channel estimation from the PRACH preamble and extrapolate channel coefficients to use for resource elements of the associated PUSCH. In some examples, the network entity may configure the UE to apply a comb structure when transmitting the PRACH preamble. In some examples, the network entity may configure the UE to transmit a partial DMRS in frequency ranges not covered by the PRACH. In some examples, the network entity may configure the UE to transmit a full

DMRS in symbols at the end of a slot and after transmission of the PUSCH.

(5) A method for wireless communications at a UE is described. The method may include receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, encoding the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and transmitting the uplink message based on encoding the uplink message.

(6) An apparatus for wireless communications at a UE is described. The apparatus may include a processor, memory coupled with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to receive control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, encode the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and transmit the uplink message based on encoding the uplink message.

(7) Another apparatus for wireless communications at a UE is described. The apparatus may include means for receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, means for encoding the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and means for transmitting the uplink message based on encoding the uplink message.

(8) A non-transitory computer-readable medium storing code for wireless communications at a UE is described. The code may include instructions executable by a processor to receive control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, encode the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and transmit the uplink message based on encoding the uplink message.

(9) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding, using a RM code, the uplink message without the DMRSs included in the first portion in accordance with the DMRS configuration.

(10) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the DMRS configuration includes a field indicating that the UE may be to refrain from including the DMRSs in the first portion of the uplink message.

(11) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the DMRS configuration includes a field indicating a low-density parity-check code and a RM code for the UE to use for encoding the uplink message and the field may be included in an uplink channel resource information element.

(12) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for selecting a PRACH preamble to include in the uplink message and generating a scrambling identification associated with the UE based on the PRACH preamble, or based on radio resource control signaling (RRC) indicating the scrambling identification, or both, where encoding the uplink message may be based on the scrambling identification.

(13) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the DMRS configuration may include operations, features, means, or instructions for receiving an indication of whether the UE may be to include the DMRSs in a second portion of the uplink message on a frequency bandwidth that may be covered by a random

access channel of the uplink message, where the random access channel may be included in the first portion of the uplink message.

(14) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the indication may include operations, features, means, or instructions for receiving a first configuration indicating for the UE to include one or more demodulated reference signals in each frequency resource of the frequency bandwidth covered by the random access channel, receiving a second configuration indicating for the UE to include the one or more demodulated reference signals in a subset of frequency resources of the frequency bandwidth covered by the random access channel, and receiving a third configuration indicating for the UE to refrain from including demodulated reference signals in the second portion of the uplink message.

(15) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the DMRS configuration may include operations, features, means, or instructions for receiving an indication of a PRACH comb pattern to apply to the first portion of the uplink message.

(16) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the uplink message without the DMRSs in any portion of the uplink message in accordance with the DMRS configuration.

(17) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the first portion of the uplink message in accordance with a PRACH comb pattern based on the DMRS configuration.

(18) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the uplink message to include one or more DMRSs in a second portion of the uplink message in accordance with the DMRS configuration.

(19) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the second portion of the uplink message to include the one or more DMRSs at a start or at an end of the second portion in accordance with the DMRS configuration.

(20) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the second portion of the uplink message to include the one or more DMRSs in a set of frequency resources without random access channel signals in accordance with the DMRS configuration.

(21) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, encoding the uplink message may include operations, features, means, or instructions for encoding the second portion of the uplink message to include the one or more DMRSs in a set of frequency resources that include random access channel signals in the first portion based on the DMRS configuration.

(22) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the DMRS configuration may be based on an amount of Doppler spread at the UE.

(23) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, transmitting the uplink message may include operations, features, means, or instructions for transmitting a PRACH in a first set of frequency resources in the first portion of the uplink message in accordance with the DMRS configuration and transmitting an uplink shared channel in a second set of frequency resources in a second portion of the uplink message in accordance with the DMRS configuration, where the first set of frequency resources and the second set of frequency resources include a same set of frequency resources or a subset of same frequency

resources.

(24) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the DMRS configuration may be based on the first set of frequency resources including the second set of frequency resources.

(25) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the DMRS configuration may be based on the second set of frequency resources including the first set of frequency resources.

(26) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the control signaling may include operations, features, means, or instructions for receiving an RRC message including the DMRS configuration for the uplink message.

(27) A method for wireless communications at a network entity is described. The method may include transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, receiving the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and decoding the uplink message based on the DMRS configuration.

(28) An apparatus for wireless communications at a network entity is described. The apparatus may include a processor, memory coupled with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to transmit control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, receive the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and decode the uplink message based on the DMRS configuration.

(29) Another apparatus for wireless communications at a network entity is described. The apparatus may include means for transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, means for receiving the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and means for decoding the uplink message based on the DMRS configuration.

(30) A non-transitory computer-readable medium storing code for wireless communications at a network entity is described. The code may include instructions executable by a processor to transmit control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRSs in at least a first portion of the uplink message based on the DMRS configuration, receive the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration, and decode the uplink message based on the DMRS configuration.

(31) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving a signal including a set of uplink messages from different UEs, where each uplink message of the set of uplink messages may be associated with a RM code.

(32) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, decoding the uplink message may include operations, features, means, or instructions for decoding, using a respective RM code, the uplink message, where the uplink message may be without the DMRSs included in the first portion of the uplink message in accordance with the DMRS configuration and canceling the decoded uplink message from the signal including the set of uplink messages in accordance with a multi-user decoding algorithm.

(33) In some examples of the method, apparatuses, and non-transitory computer-readable medium

described herein, the DMRS configuration includes a field indicating a low-density parity-check code and a RM code for the UE to use for encoding the uplink message and the field may be included in an uplink channel resource information element.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example of a wireless communications system that supports demodulation reference signal (DMRS) configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (2) FIG. 2 illustrates an example of a wireless communications system that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (3) FIG. 3 illustrates an example of a multi-user decoding algorithm that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (4) FIGS. 4 through 8 illustrate examples of uplink message configurations that support DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (5) FIG. 9 illustrates an example of a process flow that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (6) FIGS. 10 and 11 show block diagrams of devices that support DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (7) FIG. 12 shows a block diagram of a communications manager that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (8) FIG. 13 shows a diagram of a system including a device that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (9) FIGS. 14 and 15 show block diagrams of devices that support DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (10) FIG. 16 shows a block diagram of a communications manager that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (11) FIG. 17 shows a diagram of a system including a device that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.
- (12) FIGS. 18 through 21 show flowcharts illustrating methods that support DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure.

DETAILED DESCRIPTION

(13) In some examples of wireless communications, one or more wireless devices (e.g., a user equipment (UE)) may contend for access for a channel with a network entity. As such, each of the one or more UEs may operate in accordance with a random access channel (RACH) procedure (e.g., a 2-step or 4-step RACH procedure). For example, a first UE may transmit a first message (e.g., Msg-A) to the network entity that includes a physical RACH (PRACH) preamble for identification of the UE and uplink data transmitted over a physical uplink shared channel (PUSCH) occasion. In some examples, the PRACH preamble may be mapped to a set of time and frequency resources and demodulation reference signal (DMRS) ports, where the DMRS ports may be used by the network entity for channel estimation of the associated PUSCH. In some cases, however, multiplexing for multiple UEs contending for channel access may result in DMRS port leakage resulting in asynchronous transmissions. As such, it may be advantageous for the network entity to perform channel estimation for a PUSCH with reduced DMRS or without the use of DMRS.

(14) The network entity and UE may decrease DMRS port leakage by operating in accordance with techniques for a DMRS configuration for uplink messages as described herein. In some implementations, the network entity may configure the UE to perform a non-coherent PUSCH

transmission using Reed-Muller (RM) coding techniques. As such, the UE may generate an encoded signal in accordance with a configured RM code and transmit the encoded signal to the network entity. In some cases, the encoded signal may not include DMRS. On the decoding side at the network, the network entity may use non-coherent decoding on the encoded signals from one or more UEs in accordance with a multi-user decoding algorithm in which the network entity may decode data and perform channel estimation for each UE based on the RM code. The network entity may repeat iterations until each UE is correctly decoded or there is no improvement in decoding.

(15) Additionally, or alternatively, the network entity may perform channel estimation for a PUSCH using the associated PRACH portion of the PUSCH. In some implementations, the network entity may configure a UE with a DMRS configuration, such as with respect to a bandwidth that is spanned by PRACH. For example, the UE may be configured to use a full DMRS (e.g., DMRS spanning the full PRACH bandwidth), a partial DMRS (e.g., DMRS included across a subset of the PRACH bandwidth), or no DMRS (e.g., DMRS not included in any of the PRACH bandwidth) such as when transmitting first message (e.g., Msg-A) in a PRACH procedure. In examples where the UE is configured to not transmit DMRS, the network entity may perform channel estimation from the PRACH preamble and extrapolate channel coefficients to use for resource elements of the associated PUSCH. In some examples, the network entity may configure the UE to apply a comb structure when transmitting the PRACH preamble (without DMRS). In some examples, the network entity may configure the UE to transmit DMRS in frequency ranges not covered by the PRACH. In some examples, the network entity may configure the UE to transmit DMRS in symbols at the end of a slot and after transmission of the PUSCH. Accordingly, based on the configuration, the network entity may receive an uplink message (e.g., Msg-A, for example), and derive channel estimation of a PUSCH using a PRACH, or a combination of PRACH and DMRS.

(16) Aspects of the disclosure are initially described in the context of wireless communications systems. Aspects of the disclosure are further illustrated by and described with reference to a multi-user decoding algorithm and uplink message configurations. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to DMRS configuration for uplink messages.

(17) FIG. 1 illustrates an example of a wireless communications system **100** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The wireless communications system **100** may include one or more network entities **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, a New Radio (NR) network, or a network operating in accordance with other systems and radio technologies, including future systems and radio technologies not explicitly mentioned herein.

(18) The network entities **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may include devices in different forms or having different capabilities. In various examples, a network entity **105** may be referred to as a network element, a mobility element, a radio access network (RAN) node, or network equipment, among other nomenclature. In some examples, network entities **105** and UEs **115** may wirelessly communicate via one or more communication links **125** (e.g., a radio frequency (RF) access link). For example, a network entity **105** may support a coverage area **110** (e.g., a geographic coverage area) over which the UEs **115** and the network entity **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a network entity **105** and a UE **115** may support the communication of signals according to one or more radio access technologies (RATs).

(19) The UEs **115** may be dispersed throughout a coverage area **110** of the wireless

communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** or network entities **105**, as shown in FIG. 1.

(20) As described herein, a node of the wireless communications system **100**, which may be referred to as a network node, or a wireless node, may be a network entity **105** (e.g., any network entity described herein), a UE **115** (e.g., any UE described herein), a network controller, an apparatus, a device, a computing system, one or more components, or another suitable processing entity configured to perform any of the techniques described herein. For example, a node may be a UE **115**. As another example, a node may be a network entity **105**. As another example, a first node may be configured to communicate with a second node or a third node. In one aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a UE **115**. In another aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a network entity **105**. In yet other aspects of this example, the first, second, and third nodes may be different relative to these examples. Similarly, reference to a UE **115**, network entity **105**, apparatus, device, computing system, or the like may include disclosure of the UE **115**, network entity **105**, apparatus, device, computing system, or the like being a node. For example, disclosure that a UE **115** is configured to receive information from a network entity **105** also discloses that a first node is configured to receive information from a second node.

(21) In some examples, network entities **105** may communicate with the core network **130**, or with one another, or both. For example, network entities **105** may communicate with the core network **130** via one or more backhaul communication links **120** (e.g., in accordance with an S1, N2, N3, or other interface protocol). In some examples, network entities **105** may communicate with one another over a backhaul communication link **120** (e.g., in accordance with an X2, Xn, or other interface protocol) either directly (e.g., directly between network entities **105**) or indirectly (e.g., via a core network **130**). In some examples, network entities **105** may communicate with one another via a midhaul communication link **162** (e.g., in accordance with a midhaul interface protocol) or a fronthaul communication link **168** (e.g., in accordance with a fronthaul interface protocol), or any combination thereof. The backhaul communication links **120**, midhaul communication links **162**, or fronthaul communication links **168** may be or include one or more wired links (e.g., an electrical link, an optical fiber link), one or more wireless links (e.g., a radio link, a wireless optical link), among other examples or various combinations thereof. A UE **115** may communicate with the core network **130** through a communication link **155**.

(22) One or more of the network entities **105** described herein may include or may be referred to as a base station **140** (e.g., a base transceiver station, a radio base station, an NR base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a 5G NB, a next-generation eNB (ng-eNB), a Home NodeB, a Home eNodeB, or other suitable terminology). In some examples, a network entity **105** (e.g., a base station **140**) may be implemented in an aggregated (e.g., monolithic, standalone) base station architecture, which may be configured to utilize a protocol stack that is physically or logically integrated within a single network entity **105** (e.g., a single RAN node, such as a base station **140**).

(23) In some examples, a network entity **105** may be implemented in a disaggregated architecture (e.g., a disaggregated base station architecture, a disaggregated RAN architecture), which may be configured to utilize a protocol stack that is physically or logically distributed among two or more network entities **105**, such as an integrated access backhaul (IAB) network, an open RAN (O-RAN) (e.g., a network configuration sponsored by the O-RAN Alliance), or a virtualized RAN (vRAN) (e.g., a cloud RAN (C-RAN)). For example, a network entity **105** may include one or more of a

central unit (CU) **160**, a distributed unit (DU) **165**, a radio unit (RU) **170**, a RAN Intelligent Controller (RIC) **175** (e.g., a Near-Real Time RIC (Near-RT RIC), a Non-Real Time RIC (Non-RT RIC)), a Service Management and Orchestration (SMO) **180** system, or any combination thereof. An RU **170** may also be referred to as a radio head, a smart radio head, a remote radio head (RRH), a remote radio unit (RRU), or a transmission reception point (TRP). One or more components of the network entities **105** in a disaggregated RAN architecture may be co-located, or one or more components of the network entities **105** may be located in distributed locations (e.g., separate physical locations). In some examples, one or more network entities **105** of a disaggregated RAN architecture may be implemented as virtual units (e.g., a virtual CU (VCU), a virtual DU (VDU), a virtual RU (VRU)).

(24) The split of functionality between a CU **160**, a DU **165**, and an RU **175** is flexible and may support different functionalities depending upon which functions (e.g., network layer functions, protocol layer functions, baseband functions, RF functions, and any combinations thereof) are performed at a CU **160**, a DU **165**, or an RU **175**. For example, a functional split of a protocol stack may be employed between a CU **160** and a DU **165** such that the CU **160** may support one or more layers of the protocol stack and the DU **165** may support one or more different layers of the protocol stack. In some examples, the CU **160** may host upper protocol layer (e.g., layer 3 (L3), layer 2 (L2)) functionality and signaling (e.g., Radio Resource Control (RRC), service data adaptation protocol (SDAP), Packet Data Convergence Protocol (PDCP)). The CU **160** may be connected to one or more DUs **165** or RUs **170**, and the one or more DUs **165** or RUs **170** may host lower protocol layers, such as layer 1 (L1) (e.g., physical (PHY) layer) or L2 (e.g., radio link control (RLC) layer, medium access control (MAC) layer) functionality and signaling, and may each be at least partially controlled by the CU **160**. Additionally, or alternatively, a functional split of the protocol stack may be employed between a DU **165** and an RU **170** such that the DU **165** may support one or more layers of the protocol stack and the RU **170** may support one or more different layers of the protocol stack. The DU **165** may support one or multiple different cells (e.g., via one or more RUs **170**). In some cases, a functional split between a CU **160** and a DU **165**, or between a DU **165** and an RU **170** may be within a protocol layer (e.g., some functions for a protocol layer may be performed by one of a CU **160**, a DU **165**, or an RU **170**, while other functions of the protocol layer are performed by a different one of the CU **160**, the DU **165**, or the RU **170**). A CU **160** may be functionally split further into CU control plane (CU-CP) and CU user plane (CU-UP) functions. A CU **160** may be connected to one or more DUs **165** via a midhaul communication link **162** (e.g., F1, F1-c, F1-u), and a DU **165** may be connected to one or more RUs **170** via a fronthaul communication link **168** (e.g., open fronthaul (FH) interface). In some examples, a midhaul communication link **162** or a fronthaul communication link **168** may be implemented in accordance with an interface (e.g., a channel) between layers of a protocol stack supported by respective network entities **105** that are in communication over such communication links.

(25) In wireless communications systems (e.g., wireless communications system **100**), infrastructure and spectral resources for radio access may support wireless backhaul link capabilities to supplement wired backhaul connections, providing an IAB network architecture (e.g., to a core network **130**). In some cases, in an IAB network, one or more network entities **105** (e.g., IAB nodes **104**) may be partially controlled by each other. One or more IAB nodes **104** may be referred to as a donor entity or an IAB donor. One or more DUs **165** or one or more RUs **170** may be partially controlled by one or more CUs **160** associated with a donor network entity **105** (e.g., a donor base station **140**). The one or more donor network entities **105** (e.g., IAB donors) may be in communication with one or more additional network entities **105** (e.g., IAB nodes **104**) via supported access and backhaul links (e.g., backhaul communication links **120**). IAB nodes **104** may include an IAB mobile termination (IAB-MT) controlled (e.g., scheduled) by DUs **165** of a coupled IAB donor. An IAB-MT may include an independent set of antennas for relay of

communications with UEs **115**, or may share the same antennas (e.g., of an RU **170**) of an IAB node **104** used for access via the DU **165** of the IAB node **104** (e.g., referred to as virtual IAB-MT (vIAB-MT)). In some examples, the IAB nodes **104** may include DUs **165** that support communication links with additional entities (e.g., IAB nodes **104**, UEs **115**) within the relay chain or configuration of the access network (e.g., downstream). In such cases, one or more components of the disaggregated RAN architecture (e.g., one or more IAB nodes **104** or components of IAB nodes **104**) may be configured to operate according to the techniques described herein.

(26) In the case of the techniques described herein applied in the context of a disaggregated RAN architecture, one or more components of the disaggregated RAN architecture may be configured to support DMRS configuration for uplink messages as described herein. For example, some operations described as being performed by a UE **115** or a network entity **105** (e.g., a base station **140**) may additionally, or alternatively, be performed by one or more components of the disaggregated RAN architecture (e.g., IAB nodes **104**, DUs **165**, CUs **160**, RUs **170**, RIC **175**, SMO **180**).

(27) A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

(28) The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the network entities **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. 1.

(29) The UEs **115** and the network entities **105** may wirelessly communicate with one another via one or more communication links **125** (e.g., an access link) over one or more carriers. The term “carrier” may refer to a set of RF spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a RF spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. Communication between a network entity **105** and other devices may refer to communication between the devices and any portion (e.g., entity, sub-entity) of a network entity **105**. For example, the terms “transmitting,” “receiving,” or “communicating,” when referring to a network entity **105**, may refer to any portion of a network entity **105** (e.g., a base station **140**, a CU **160**, a DU **165**, a RU **170**) of a RAN communicating with another device (e.g., directly or via one or more other network entities **105**).

(30) Signal waveforms transmitted over a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may refer to resources of one symbol period (e.g.,

a duration of one modulation symbol) and one subcarrier, in which case the symbol period and subcarrier spacing may be inversely related. The quantity of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both) such that the more resource elements that a device receives and the higher the order of the modulation scheme, the higher the data rate may be for the device. A wireless communications resource may refer to a combination of an RF spectrum resource, a time resource, and a spatial resource (e.g., a spatial layer, a beam), and the use of multiple spatial resources may increase the data rate or data integrity for communications with a UE **115**.

(31) The time intervals for the network entities **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of $T_{\text{sub.S}} = 1/(\Delta f_{\text{sub.max}} \cdot N_{\text{sub.f}})$ seconds, where $\Delta f_{\text{sub.max}}$ may represent the maximum supported subcarrier spacing, and $N_{\text{sub.f}}$ may represent the maximum supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

(32) Each frame may include multiple consecutively numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a quantity of slots. Alternatively, each frame may include a variable quantity of slots, and the quantity of slots may depend on subcarrier spacing. Each slot may include a quantity of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots containing one or more symbols. Excluding the cyclic prefix, each symbol period may contain one or more (e.g., $N_{\text{sub.f}}$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

(33) A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., a quantity of symbol periods in a TTI) may be variable. Additionally, or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

(34) Physical channels may be multiplexed on a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed on a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a control resource set (CORESET)) for a physical control channel may be defined by a set of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to an amount of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

(35) In some examples, a network entity **105** (e.g., a base station **140**, an RU **170**) may be movable and therefore provide communication coverage for a moving coverage area **110**. In some examples, different coverage areas **110** associated with different technologies may overlap, but the different coverage areas **110** may be supported by the same network entity **105**. In some other examples, the

overlapping coverage areas **110** associated with different technologies may be supported by different network entities **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the network entities **105** provide coverage for various coverage areas **110** using the same or different radio access technologies.

(36) The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC). The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions. Ultra-reliable communications may include private communication or group communication and may be supported by one or more services such as push-to-talk, video, or data. Support for ultra-reliable, low-latency functions may include prioritization of services, and such services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, and ultra-reliable low-latency may be used interchangeably herein.

(37) In some examples, a UE **115** may be able to communicate directly with other UEs **115** over a device-to-device (D2D) communication link **135** (e.g., in accordance with a peer-to-peer (P2P), D2D, or sidelink protocol). In some examples, one or more UEs **115** of a group that are performing D2D communications may be within the coverage area **110** of a network entity **105** (e.g., a base station **140**, an RU **170**), which may support aspects of such D2D communications being configured by or scheduled by the network entity **105**. In some examples, one or more UEs **115** in such a group may be outside the coverage area **110** of a network entity **105** or may be otherwise unable to or not configured to receive transmissions from a network entity **105**. In some examples, groups of the UEs **115** communicating via D2D communications may support a one-to-many (1:M) system in which each UE **115** transmits to each of the other UEs **115** in the group. In some examples, a network entity **105** may facilitate the scheduling of resources for D2D communications. In some other examples, D2D communications may be carried out between the UEs **115** without the involvement of a network entity **105**.

(38) The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the network entities **105** (e.g., base stations **140**) associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

(39) The wireless communications system **100** may operate using one or more frequency bands, which may be in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. The UHF waves may be blocked or redirected by buildings and environmental features, which may be referred to as clusters, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. The transmission of UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to transmission using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

(40) The wireless communications system **100** may utilize both licensed and unlicensed RF spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology in an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. While operating in unlicensed RF spectrum bands, devices such as the network entities **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations in unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating in a licensed band (e.g., LAA). Operations in unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

(41) A network entity **105** (e.g., a base station **140**, an RU **170**) or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a network entity **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a network entity **105** may be located in diverse geographic locations. A network entity **105** may have an antenna array with a set of rows and columns of antenna ports that the network entity **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may have one or more antenna arrays that may support various MIMO or beamforming operations. Additionally, or alternatively, an antenna panel may support RF beamforming for a signal transmitted via an antenna port.

(42) Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a network entity **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating at particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

(43) The wireless communications system **100** may be a packet-based network that operates according to a layered protocol stack. In the user plane, communications at the bearer or PDCP layer may be IP-based. An RLC layer may perform packet segmentation and reassembly to communicate over logical channels. A MAC layer may perform priority handling and multiplexing of logical channels into transport channels. The MAC layer may also use error detection techniques, error correction techniques, or both to support retransmissions at the MAC layer to improve link efficiency. In the control plane, the RRC protocol layer may provide establishment, configuration, and maintenance of an RRC connection between a UE **115** and a network entity **105** or a core network **130** supporting radio bearers for user plane data. At the PHY layer, transport channels may be mapped to physical channels.

(44) In some examples of wireless communication system **100**, one or more wireless devices (e.g., UEs **115**) may contend for access for a channel with a network entity **105**. As such, each of the one or more UEs **115** may operate in accordance with a RACH procedure. For example, a first UE **115** may transmit a first message to the network entity **105** that includes a PRACH preamble for

identification of the UE **115** and uplink data transmitted over a PUSCH occasion. In some examples, the PRACH preamble may be mapped to a set of time and frequency resources and DMRS ports, where the DMRS ports may be used by the network entity **105** for channel estimation of the associated PUSCH.

(45) Techniques for performing channel estimation may be improved. For example, the channel estimation techniques described herein may allow a device (e.g., a UE **115**, a network entity **105**) to perform channel estimation based on parameters other than DMRS (e.g., a RM code, PRACH). In some cases, the techniques described herein may allow for DMRS-less channel estimation. In some implementations, the network entity **105** may configure the UE **115** to perform a non-coherent PUSCH transmission using RM coding techniques. For example, the UE **115** may generate an encoded signal in accordance with a configured RM code and transmit the encoded signal to the network entity **105**. On the decoding side at the network, the network entity **105** may use non-coherent decoding on one or more encoded signals from multiple UEs **115** in accordance with a multi-user decoding algorithm in which the network entity **105** may decode data and perform channel estimation for each UE **115** based on the RM code associated with the transmission. The network entity **105** may repeat iterations until each UE **115** is correctly decoded or there is no improvement in decoding.

(46) Additionally, or alternatively, the network entity **105** may perform channel estimation for a PUSCH using the associated PRACH portion of the PUSCH. For example, the network entity **105** may configure a UE **115** to include full DMRS, partial DMRS, or no DMRS in the uplink message (e.g., Msg-A). In examples where the UE **115** is configured to not transmit DMRS, the network entity **105** may perform channel estimation from the PRACH preamble and extrapolate channel coefficients to use for resource elements of the associated PUSCH. In some examples, the network entity **105** may configure the UE **115** to apply a comb structure when transmitting the PRACH preamble (as illustrated with reference to FIG. 5). In some examples, the network entity **105** may configure the UE **115** to transmit DMRS in frequency ranges not covered by the PRACH (as illustrated with reference to FIG. 6). In some examples, the network entity **105** may configure the UE **115** to transmit DMRS in symbols at the end of a slot and after transmission of the PUSCH (as illustrated with reference to FIG. 8). Accordingly, based on the configuration, the network entity **105** may receive an uplink message and derive channel estimation of a PUSCH using a PRACH, or a combination of PRACH and DMRS.

(47) FIG. 2 illustrates an example of a wireless communications system **200** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, wireless communications system **200** may implement one or more aspects of wireless communications system **100**. For instance, a UE **115a** and a network entity **105-a** may be respective examples of a UE **115** and a network entity **105**, with reference to FIG. 1. While examples are discussed herein, any number of devices and device types may be used to accomplish implementations described in the present disclosure. Wireless communications system **200** may support control signaling between the UE **115-a** and the network entity **105-a** that indicates for the UE **115-a** to refrain from including DMRS in at least a first portion of an uplink message **215** based on receiving a DMRS configuration message **205**.

(48) In some examples of wireless communications system **200**, the UE **115-a** may contend for access for a channel with the network entity **105-a**. As such, the UE **115-a** may operate in accordance with a RACH procedure (e.g., a 2-step RACH procedure, 4-step RACH, among other examples). In an example of a 2-step RACH procedure, the UE **115-a** may transmit to the network entity **105-a**, a first message of a RACH procedure (e.g., Msg-A) that may include a PRACH preamble for identification of the UE **115-a** and uplink data transmitted over a PUSCH occasion. In some examples, the UE **115-a** may select a PRACH preamble from a set of PRACH preambles configured by the network and transmit the PRACH preamble during a RACH occasion. The UE **115-a** may select the PRACH preamble randomly, such as from a set of 64 preambles. Additionally,

or alternatively, the PRACH preamble may be mapped to a set of time and frequency resources and DMRS ports. In some examples, the DMRS ports may be used by the network entity **105-a** for channel estimation of the associated PUSCH transmission.

(49) In some cases, however, multiplexing for multiple UEs **115** contending for channel access may result in an increased channel estimation complexity at the network entity **105-a**. For example, the network may support a number of orthogonal DMRS ports (e.g., 12 orthogonal DMRS ports), where the finite number of DMRS ports may result in a bottleneck as the number of multiplexed UEs **115** increases. In some examples, the bottleneck associated with the DMRS ports may result in DMRS port shifting, in which the DMRS ports are no longer orthogonal (e.g., leakage between DMRS ports). In some instances, DMRS port leakage may result in asynchronous transmissions for each UE **115** which may result in a loss of timing advance (TA) information for each respective PUSCH transmission. Additionally, or alternatively, the use of DMRS may increase signaling overhead of the wireless communications system **200**. As such, it may be advantageous for the network entity **105-a** to perform channel estimation for a PUSCH with reduced DMRS occasions.

(50) The network entity **105-a** may perform channel estimation without the use of DMRS or with reduced DMRS according to the techniques described herein. For example, the network entity **105-a** may transmit a DMRS configuration message **205** to the UE **115-a**, which may indicate for the UE **115-a** to encode an uplink message **215** such that at least a first portion (e.g., a time range, a frequency range, or a combination thereof) of the uplink message **215** may not include DMRS. For example, the UE **115-a** may generate the uplink message **215** in accordance with uplink message configuration **220** as illustrated in FIG. 2. In such examples, the uplink message configuration **220** may include a set of PRACH resources **225** during a first set of time and frequency resources, a set of PUSCH resources **235** during a second set of time and frequency resources, and a set of blank resources **230** between the PRACH resources **225** and the PUSCH resources **235**. As such, the uplink message configuration **220** may refrain from including DMRS resources during at least a first portion of the uplink message **215**. Further examples of various uplink message configurations **220** are described herein, including with reference to FIGS. 4 through 8.

(51) In some implementations, the DMRS configuration message **205** may indicate for the UE **115-a** to perform a non-coherent PUSCH transmission in accordance with RM coding techniques to allow the network entity **105-a** to perform channel estimation without DMRS or with reduced DMRS occasions. In such implementations, the DMRS configuration message **205** may include one or more fields indicating for the UE **115-a** to refrain from including DMRS in the uplink message **215**. For example, the DMRS configuration message **205** may be an example of a control message (e.g., an RRC message, a medium access control-control element (MAC-CE) message, a downlink control information (DCI) message) that configures DMRS for use by the UE **115-a** in a RACH procedure (e.g., MsgA-DMRS-Config-r16) which may include a field indicating the length of the associated DMRS (e.g., msgA-MaxLength-r16). As such, the network entity **105-a** may set the length of the associated DMRS to a value '0' to indicate for the UE **115-a** to not use DMRS.

(52) Additionally, or alternatively, the DMRS configuration message **205** may be an example of a control message that configures resources for a PUSCH at the UE **115-a** (e.g., MsgA-PUSCH-Resource-r16) that includes a field indicating a number of DMRSs to use in the PUSCH (e.g., nrofDMRS-Sequences-r16). As such, the network entity **105-a** may set the number of DMRSs to a value '0' to indicate for the UE **115-a** to not use DMRS in the uplink message **215**. In some examples, the DMRS configuration message **205** may also include a field indicating a low-density parity-check (LDPC) code and/or an RM code for the UE **115-a** to use for encoding the uplink message **215** (e.g., msgA-code-r16 ENUMERATED {LDPC, RAI}). As such, the UE **115-a** may perform uplink message encoding **210** in accordance with the LDPC code and/or the RM code indicated in the DMRS configuration message **205**.

(53) In some examples, the UE **115-a** may select a PRACH preamble to include in the uplink message **215** based on the DMRS configuration message **205**. The UE **115-a** may also generate a

scrambling ID associated with the UE **115-a** based on the PRACH preamble, based on control signaling indicating the scrambling ID (e.g., RRC signaling), or both. In some examples, the UE **115-a** may perform the uplink message encoding **210** based on the scrambling ID and transmit the encoded uplink message **215** to the network entity **105-a**. As such, the network entity **105-a** may receive the encoded uplink message **215** and use non-coherent decoding on scrambled signals from multiple UEs **115** in accordance with a multi-user decoding algorithm in which the network entity **105-a** concurrently decodes data and performs channel estimation for a single UE **115** at a time based on the RM code associated with the transmission. The network entity **105-a** may repeat iterations of the multi-user decoding algorithm until all UEs **115** are correctly decoded or there is no improvement in decoding. Further discussion of the multi-user decoding algorithm at the network entity **105-a** in accordance with a non-coherent PUSCH are described herein, including with reference to FIG. 3.

(54) In some cases, wireless communications system **200** may utilize a non-coherent PUSCH for the uplink message **215** for smaller data payloads (e.g., data less than 200 bits). In some examples, the non-coherent PUSCH may be applied to PUSCH types other than a RACH PUSCH (e.g., a configured grant PUSCH or a grant-based PUSCH). In examples of the non-coherent PUSCH, the PUSCH resources **235** may be independent from the PRACH resources **225**.

(55) In some examples, the UE **115-a** may select a PRACH preamble to include in the uplink message **215** based on the DMRS configuration message **205**. The UE **115-a** may also generate a scrambling ID associated with the UE **115-a** based on the PRACH preamble, based on control signaling indicating the scrambling ID (e.g., RRC signaling), or both. In some examples, the UE **115-a** may perform the uplink message encoding **210** based on the scrambling ID and transmit the encoded uplink message **215** to the network entity **105-a**. As such, the network entity **105-a** may receive the encoded uplink message **215** and use non-coherent decoding on scrambled signals from multiple UEs **115** in accordance with a multi-user decoding algorithm in which the network entity **105-a** concurrently decodes data and performs channel estimation for a single UE **115** at a time based on the RM code associated with the transmission. The network entity **105-a** may repeat iterations of the multi-user decoding algorithm until all UEs **115** are correctly decoded or there is no improvement in decoding. Further discussion of the multi-user decoding algorithm at the network entity **105-a** in accordance with a non-coherent PUSCH are described herein, including with reference to FIG. 3.

(56) In some cases, wireless communications system **200** may utilize a non-coherent PUSCH for the uplink message **215** for smaller data payloads (e.g., data less than 200 bits). In some examples, the non-coherent PUSCH may be applied to PUSCH types other than a RACH PUSCH (e.g., a configured grant PUSCH or a grant-based PUSCH). In examples of the non-coherent PUSCH, the PUSCH resources **235** may be independent from the PRACH resources **225**.

(57) Additionally or alternatively to implementing a non-coherent PUSCH transmission, the network entity **105-a** may perform channel estimation for PUSCH resources **235** using corresponding PRACH resources **225** in order to perform channel estimation without the use of DMRS or with reduced DMRS occasions. As such, the DMRS configuration message **205** may indicate for the UE **115-a** to use a full DMRS, a partial DMRS, or no DMRS when transmitting the uplink message **215**. In such implementations, the DMRS configuration message **205** may be an example of a control message (e.g., an RRC message) that configures DMRS for use by the UE **115-a** in a RACH procedure (e.g., MsgA-DMRS-Config-r16) which may include a field indicating an associated DMRS version (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {full, partial, none}). For example, the DMRS configuration message **205** may indicate whether UE **115-a** is to transmit DMRS on a bandwidth that is covered by PRACH, where the UE **115-a** may be configured to transmit DMRS over a consecutive frequency resources that encompass the PUSCH, over frequency resources that partially encompass the PUSCH, or to refrain from transmitting DMRS.

- (58) In examples where the UE **115-a** is configured to not transmit DMRS, the network entity **105-a** may perform channel estimation from the PRACH preamble (e.g., the PRACH resources **225**) and extrapolate channel coefficients to use for the PUSCH resources **235**. Further discussion where the UE **115-a** is configured to not transmit DMRS is described herein, including with reference to FIG. 4.
- (59) In some examples, the network entity **105-a** may configure the UE **115-a** to apply a comb structure to the uplink message configuration **220** for the PRACH resources **225**. Further discussion of uplink message **215** transmission using a comb structure are described herein, including with reference to FIG. 5.
- (60) In some examples, the network entity **105-a** may configure the UE **115-a** to transmit a partial DMRS in frequency resources not covered by the PRACH resources **225**. Further discussion of partial DMRS configurations are described herein, including with reference to FIG. 6.
- (61) In some examples, the network entity **105-a** may configure a first UE **115** and a second UE **115** to use different DMRS configurations (e.g., transmitting respective DMRS configuration messages **205** to each UE **115**). Further discussion of indicating different DMRS configurations to respective UEs **115** is described herein, including with reference to FIG. 7.
- (62) In some examples, the network entity **105-a** may configure the UE **115-a** to transmit a full DMRS at the end of a slot and after transmission of the PUSCH resources **235**. Further discussion of full DMRS configurations are described herein, including with reference to FIG. 8.
- (63) The wireless communications system **200** may utilize a PRACH based channel estimation for low mobility internet of things (IoT) applications, for cases where the PUSCH bandwidth is included in the PRACH bandwidth, for cases where the time gap between the PRACH resources **225** and PUSCH resources **235** are below a configured threshold, or a combination thereof.
- (64) FIG. 3 illustrates an example of a multi-user decoding algorithm **300** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the multi-user decoding algorithm **300** may implement one or more aspects of wireless communications system **100** and wireless communications system **200**. For instance, multi-user decoding algorithm **300** may be implemented by a network entity **105**, with reference to FIG. 1. Additionally, or alternatively, the multi-user decoding algorithm **300** may be an example of the multi-user decoding algorithm used by network entity **105-a**, with reference to FIG. 2. The multi-user decoding algorithm **300** may support decoding multiplexed signaling from multiple UEs **115** contending for access to channels associated with the network entity **105**, where the multiplexed signaling includes non-coherent PUSCH transmissions.
- (65) In some cases, wireless devices may perform coherent communications in which a transmitting device may include pilot symbols (e.g., DMRS symbols) in a data transmission. A receiving device may perform channel estimation using the pilot symbols and extrapolate the channel estimation to the data symbols. The receiving device may then demodulate and decode the data symbols based on the extrapolated channel estimation. In some other cases, wireless devices may perform non-coherent communications in which a transmitting device does not include pilot symbols in the data transmission. As such, each symbol in the data transmission may be used for data which may improve throughput. However, the receiving device would infer (e.g., demodulate and decode) the data information directly from the received signal without performing channel estimation.
- (66) In order to successfully infer the data information without performing channel estimation, channel coherence may be exploited. Namely, the noncoherent communication scheme may exploit the fact that the channel realization for adjacent coded symbols (e.g., either in adjacent time or frequency resources) may be the same or strongly correlated. For example, in differential modulation, information may be modulated on the phase difference between adjacent coded symbols and in sequence-based scheme, information may be modulated jointly on a sequence of symbols. In order to have a high performance at low SNR, the noncoherent communication scheme

will exploit as much channel coherence as possible. However, longer channel coherence results in longer memory, and hence increased receiver complexity. The complexity of optimal decoding may be exponential in the channel coherence, and in the payload size. Therefore, the techniques described here exploit the channel coherence, but with much reduced complexity by using RM coding techniques that exploit the differential structure of the code.

(67) RM codes are algebraic codes and an RM codeword can be thought of as a binary polynomial, and hence mathematically, the decoding may include polynomial reconstruction. Specifically, the goal of the decoding is to recover the coefficients of the polynomials that represents a RM codeword. The coefficients of different polynomial orders may be reconstructed at different steps of the decoding procedure, where the main property of the RM code that can be exploited for non-coherent communications is the differential property of RM codes. The differential of an RM code of order r is a RM code of order $r-1$. For example, a decoding procedure may start with an order r code and may apply the differentials along the direction α which may result in an RM code of order $r-1$. The differential property is beneficial because assuming the channel is the same, the channel coefficient can be removed in order to perform non-coherent coding using $r-1$.

(68) For example, the network entity **105** may receive a multiplexed uplink message that includes a set of uplink messages (e.g., packets) from a set of different UEs **115**. In some examples, each uplink message of the set of uplink messages may be associated with a respective RM code. In some examples, each RM code may be a unique RM code associated with a respective UE **115**. For example, as described with reference to FIG. 2, the network entity **105** may transmit a DMRS configuration message **205** to each UE **115** that indicates a respective LDPC code and RM code unique to the receiving UE **115**. Additionally, or alternatively, each UE **115** may uniquely determine a respective RM code. In some cases, each UE **115** may signal the RM code to the network entity **105** and/or the network entity **105** may be able to identify each RM code associated with each UE **115**. Additionally, or alternatively, the network entity **105** and the set of UEs **115** may determine which wireless communications may use RM coding techniques. For example, the network entity **105** may transmit respective control signals to each of the set of UEs **115** indicating a set of one or more transmissions in which to use RM coding. As such, each of the set of UEs **115** may transmit acknowledgment messages indicating the use of RM coding for the one or more transmissions.

(69) As such, the network entity **105** may utilize the respective RM codes in accordance with the multi-user decoding algorithm **300** to decode each of the set of uplink messages and perform channel estimation of the respective non-coherent PUSCH transmissions. For example, the network entity **105** may have an associated non-coherent decoder **305** that the network entity **105** may use to decode the multiple non-coherent PUSCH transmissions in the set of uplink messages. In some examples, the network entity **105** may decode each of the set of uplink messages separately. For example, the network entity **105** may decode the multiplexed uplink message using a first respective RM code associated with a first UE **115** and a first uplink message. By using the first respective RM code, the network entity **105** may attempt to decode (e.g., descramble) the contents of the first uplink message from the multiplexed uplink message. As such, the network entity **105** may perform a channel estimation **310** on the PUSCH transmission of the first uplink message in accordance with the first respective RM code. In some examples, the network entity **105** may decode an uplink message and perform the channel estimation **310** concurrently. Based on decoding and performing the channel estimation **310**, the network entity **105** may perform signal construction **315**, to construct the first uplink message independent from the multiplexed uplink message.

(70) As such, the network entity **105** may utilize the respective RM codes in accordance with the multi-user decoding algorithm **300** to decode each of the set of uplink messages and perform channel estimation of the respective non-coherent PUSCH transmissions. For example, the network entity **105** may have an associated non-coherent decoder **305** that the network entity **105** may use

to decode the multiple non-coherent PUSCH transmissions in the set of uplink messages. In some examples, the network entity **105** may decode each of the set of uplink messages separately. For example, the network entity **105** may decode the multiplexed uplink message using a first respective RM code associated with a first UE **115** and a first uplink message.

(71) By using the first respective RM code, the network entity **105** may attempt to decode (e.g., descramble) the contents of the first uplink message from the multiplexed uplink message. As such, the network entity **105** may perform a channel estimation **310** on the PUSCH transmission of the first uplink message in accordance with the first respective RM code. In some examples, the network entity **105** may decode an uplink message and perform the channel estimation **310** concurrently. Based on decoding and performing the channel estimation **310**, the network entity **105** may perform signal construction **315**, to construct the first uplink message independent from the multiplexed uplink message.

(72) In some examples, and as described herein, each RM codeword may be a binary polynomial. As such, the network entity may decode the data associated with the RM codeword based on performing a polynomial reconstruction. For instance, the network entity **105** may recover the coefficients of the polynomials that represent a given RM codeword. The network entity may recover the coefficient of the polynomials by utilizing a differential property of RM coding in which a differential of an RM code of order r may have an order of $r-1$. As such, the network entity **105** may receive the multiplexed uplink message across a set of receive antennas, and may compute a differential of the multiplexed signal based on how it is received at each of the set of receive antennas. In some examples, the network entity **105** may combine each of the differentials across the set of receive antennas to construct a $r-1$ projection of tensor (e.g., an algebraic object that describes a multilinear relationship between sets of algebraic objects related to a vector space) associated with the r .sup.th order binary polynomial for the RM codeword.

(73) Based on constructing the $r-1$ projection, the network entity may reconstruct a square tensor from the projections and cancel the contributions of the square tensor from the set of receive antennas. As such, the network entity **105** may compute another set of differentials as another channel output after canceling the contributions of the square tensor. In some examples, the network entity may recursively reconstruct a set of square tensors to obtain the RM codeword and the associated data at the network entity **105** for a given UE **115**.

(74) Based on successfully decoding, performing channel estimation **310**, and performing signal construction **315** for the first uplink message, the network entity **105** may remove (e.g., cancel) the first uplink message from the multiplexed uplink message. That is, the network entity **105** may remove the first UEs **115** contribution to the overall signal. For example, the network entity **105** may perform interference cancelation **320**, in which the network entity **105** cancels the contents of the first uplink message from the received multiplexed uplink message.

(75) Subsequently or concurrently to applying the multi-user decoding algorithm **300** to the first UE **115**, the network entity **105** may perform the multi-user decoding algorithm **300** using a second respective RM code to decode, perform channel estimation **310**, and perform signal construction **315** for a second uplink message associated with the second respective RM code. In some examples, the network entity **105** may repeat iterations of the multi-user decoding algorithm **300** until each UE **115** associated with the multiplexed uplink message is correctly decoded and/or until algorithm results in no additional improvements of each decoded uplink message from the multiplexed uplink message.

(76) In some implementations, the network entity **105** may simultaneously decode each respective uplink message from the multiplexed uplink message using the multi-user decoding algorithm **300**. In such cases, the network entity **105** may utilize each of the respective decoded uplink messages, individually, or as a whole, to determine whether any improvements may be made to one or more of the decoded uplink messages. If improvements may be made, the network entity **105** may apply all or a portion of the multi-user decoding algorithm **300** to a specific one or more uplink messages

that can be improved, or to the complete set of uplink messages associated with the multiplexed uplink message.

(77) In some examples, the network entity **105** may refrain from repeating the multi-user decoding algorithm **300** if the network entity **105** identifies no improvement in decoding the multi-user decoding algorithm **300**. For instance, one or more parameters associated with decoding the multiplexed uplink message (e.g., time to decode message, power used to decode message, etc.) may satisfy one or more configured thresholds, indicating for the network entity **105** to conclude the multi-user decoding algorithm **300**.

(78) FIG. 4 illustrates an example of an uplink message configuration **400** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the uplink message configuration **400** may implement one or more aspects of wireless communications system **100** and wireless communications system **200**. For instance, uplink message configuration **400** may be an example of the uplink message configuration **220**, with reference to FIG. 2. Additionally, or alternatively, the PRACH resources **405**, blank resources **410**, and PUSCH resources **415** may be respective examples of PRACH resources **225**, blank resources **230**, and PUSCH resources **235**, with reference to FIG. 2. The uplink message configuration **400** may support transmission of an uplink message from a UE **115** to a network entity **105** without DMRS in at least a first portion of the uplink message.

(79) In some examples, the UE **115** may generate the uplink message configuration **400** in accordance with control signaling (e.g., RRC signaling) received from the network entity **105**. For example, with reference to FIG. 2, the uplink message configuration **400** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field (e.g., parameter) indicating for the UE **115** to not include DMRS (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {none}). Additionally, or alternatively, the uplink message may include a field indicating whether the UE **115** is to transmit DMRS on a frequency range (e.g., bandwidth) that is covered by PRACH resources **405**. As such, the UE **115** may generate the uplink message configuration **400** with no DMRS.

(80) As illustrated in FIG. 4, the uplink message configuration **400** includes a set of PRACH resources **405** during a first time range that spans a first frequency range, and may include a set of PUSCH resources **415** during a second time range that spans a second frequency range. In some examples of uplink message configuration **400**, the second frequency range associated with the PUSCH resources **415** may be included in the first frequency range associated with the PRACH resource **405** (e.g., PUSCH bandwidths PRACH bandwidth). For example, as illustrated in FIG. 4, the PRACH resources **405** may span 12 resources blocks of the frequency and the PUSCH resources may span 6 resources blocks of the frequency, where the 6 resource blocks may be a subset of the 12 resources blocks. In some implementations, the UE **115** may be configured to generate the uplink message configuration **400** with no DMRS based on the second frequency range being included in the first frequency range (e.g., when the PRACH BW includes the PUSCH BW). In some cases, the UE **115** may be configured to generate the uplink message configuration **400** with no DMRS based on a format of the PRACH resources **405**, the PUSCH resources **415**, or both. For example, the UE **115** may be configured to generate the uplink message configuration **400** with no DMRS based on being configured to transmit the PRACH resources **405** in accordance with a short format (e.g., 12 resource blocks based on 15 kHz SCS) and/or transmit the PUSCH resources **415** in accordance with a long format (e.g., 6 resource blocks based on 15 kHz SCS).

(81) Additionally, or alternatively, the uplink message configuration **400** may include a small time gap between the PRACH resources **405** and PUSCH resources **415** (e.g., the number of blank resources **410** between the end of PRACH resources **405** and the start of PUSCH resources **415** may be below a configured threshold).

(82) As such, the UE **115** may transmit an uplink message to the network entity **105** in accordance with the uplink message configuration **400**. In some examples, the network entity **105** may perform

channel estimation on the PUSCH resources **415** based on performing a channel estimation on the PRACH resources **405**. For example, the network entity **105** may perform a direct Fourier transform (DFT) based channel estimation (e.g., sounding reference signal (SRS) based channel estimation) for the set of PRACH resources **405**. In some examples, the network entity **105** may perform channel estimation of the PRACH resources **405** via Zadoff-Chu sequences. Based on performing the channel estimation on the PRACH preamble, the network entity **105** may extrapolate the channel coefficients to use for the PUSCH resources **415** (e.g., adjust channel coefficients based on a change in frequency and time between the PUSCH resources **415** and the PRACH resources **405**) without using DMRS.

(83) Based on the UE **115** not including DMRS in the uplink message, the UE **115** and network entity **105** may benefit from a lower coding rate associated with the uplink message.

(84) FIG. 5 illustrates an example of an uplink message configuration **500** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the uplink message configuration **500** may implement one or more aspects of wireless communications system **100**, wireless communications system **200**, and uplink message configuration **400**. For instance, uplink message configuration **500** may be an example of the uplink message configuration **220**, with reference to FIG. 2. Additionally, or alternatively, the PRACH resources **505**, blank resources **510**, and PUSCH resources **515** may be respective examples of PRACH resources **225**, blank resources **230**, and PUSCH resources **235**, with reference to FIG. 2. The uplink message configuration **500** may support transmission of an uplink message from a UE **115** to a network entity **105** without DMRS in at least a first portion of the uplink message.

(85) In some examples, the UE **115** may generate the uplink message configuration **500** in accordance with control signaling received from the network entity **105**. For example, with reference to FIG. 2, the uplink message configuration **500** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field indicating for the UE **115** to not include DMRS (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {none}). As such, the UE **115** may generate the uplink message configuration **500** with no DMRS.

(86) As illustrated in FIG. 5, the uplink message configuration **500** includes a set of PRACH resources **505** during a first time range that spans a first frequency range, and may include a set of PUSCH resources **515** during a second time range that spans a second frequency range. In some examples, the UE **115** may configure PRACH resources **505** of the uplink message configuration **500** in accordance with a comb structure. In some examples, the UE **115** may use a comb structure for the PRACH resource **505** based on receiving an RRC message, or some other control message, indicating the use of a comb (e.g., comb-1/2/3/4). In some cases, the control message may indicate the UE **115** is to implement a comb structure and the UE **115** may select which comb structure to use. In such cases, the UE **115** may transmit to the network entity **105**, an indication of which comb structure the UE **115** applied or will apply to the PRACH resources **505**. In some cases, the control message may indicate a particular comb structure for the UE **115** to apply to the PRACH resources **405**. In some implementations, the UE **115** may be configured to apply a comb structure so that the PRACH resources **505** span a frequency range that includes a frequency range covered by the PUSCH resources **515** (e.g., as depicted in FIG. 5).

(87) By adding a comb structure to PRACH resources **505**, the PRACH transmission may cover a larger frequency band. For example, for a sub-carrier spacing (SCS) of 15 kHz, a PRACH transmission filling a total of 12 resource blocks in frequency would span a total of 18 resource blocks in frequency (e.g., including the blank resources **510** in between the PRACH resources **505**). In another example, for a SCS of 30 kHz, a PRACH transmission filling a total of 6 resource blocks in frequency would span a total of 12 resource blocks in frequency (e.g., as illustrated in FIG. 5). In an example, each 32 PRACH preamble may be mapped to one half of PUSCH. Therefore, the PUSCH bandwidth may be divided into four, and the comb plus the 32 preambles

may be mapped to a quarter. In some examples, using a comb structure for PRACH transmissions may increase a number of UEs **115** that may be multiplexed for a given uplink transmission to the network entity **105**.

(88) As described with reference to FIG. **4**, the UE **115** may transmit an uplink message to the network entity **105** in accordance with the uplink message configuration **500**. In some examples, the network entity **105** may perform channel estimation on the PUSCH resources **515** based on performing a channel estimation on the PRACH resources **505**. Based on performing the channel estimation on the PRACH preamble, the network entity **105** may extrapolate the channel coefficients to use for the PUSCH resources **515** (e.g., adjust channel coefficients based on a change in frequency and time between the PUSCH resources **515** and the PRACH resources **505**) without using DMRS.

(89) FIG. **6** illustrates an example of an uplink message configuration **600** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the uplink message configuration **600** may implement one or more aspects of wireless communications system **100**, wireless communications system **200**, and uplink message configuration **400**. For instance, uplink message configuration **600** may be an example of the uplink message configuration **220**, with reference to FIG. **2**. Additionally, or alternatively, the PRACH resources **605**, blank resources **610**, and PUSCH resources **615** may be respective examples of PRACH resources **225**, blank resources **230**, and PUSCH resources **235**, with reference to FIG. **2**. The uplink message configuration **600** may support transmission of an uplink message from a UE **115** to a network entity **105** without DMRS in at least a first portion of the uplink message.

(90) In some examples, the UE **115** may generate the uplink message configuration **600** in accordance with control signaling received from the network entity **105**. For example, with reference to FIG. **2**, the uplink message configuration **600** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field indicating for the UE **115** to not include DMRS in a first portion of the uplink message but may configure the UE **115** to include DMRS in a second portion (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {partial}). As such, the UE **115** may generate the uplink message configuration **600** with a partial DMRS (e.g., DMRS included in a subset of the frequency resources of the uplink message, in a subset of time resources of the uplink message, or a combination thereof).

(91) As illustrated in FIG. **6**, the uplink message configuration **600** includes a set of PRACH resources **605** during a first time range that spans a first frequency range, and may include a set of PUSCH resources **615** during a second time range that spans a second frequency range. In some examples, the second time range that includes the set of PUSCH resources **615** may also include a set DMRS resources **620** in accordance with the DMRS configuration message **205** indicating a partial DMRS configuration. In some examples, the DMRS resources **620** of the partial DMRS configuration may span resources over the frequency resources not covered by the PRACH resources **605** (e.g., as illustrated in FIG. **6**). In some examples, the UE **115** may generate the uplink message configuration **600** in accordance with the techniques described with reference to FIGS. **4** and **5**. For example, the UE **115** may receive an RRC message from the network entity **105** indicating to use a comb structure for the PRACH resources **605** and insert the DMRS resources **620** in the blank frequency resources of the comb structure, where the blank frequency resource may be in a time range associated with the PRACH resources **405**, or a time range associated with the PUSCH resources **415**, or a combination thereof. For example, the UE **115** may be configured to include DMRS in all or a subset of frequency resources not covered by PRACH and may include the DMRS with the PRACH or the PUSCH. Additionally, or alternatively, the UE **115** may generate the uplink message configuration **600** such that the PUSCH bandwidth .Math. PRACH bandwidth.

(92) As such, the UE **115** may transmit an uplink message to the network entity **105** in accordance

with the uplink message configuration **600**. In some examples, the network entity **105** may perform channel estimation on the PUSCH resources **615** based on performing a channel estimation on the PRACH resources **605** in combination with a channel estimation of the DMRS resources **620**. For example, as discussed with reference to FIG. **4**, the network entity **105** may perform channel estimation of the PRACH resources **605** via Zadoff-Chu sequences and further perform channel estimation of the DMRS resources **620**. As such, the network entity **105** may combine the PRACH and DMRS channel estimations and extrapolate channel coefficients to use for the PUSCH resources **615**. By combining channel estimation from the partial DMRS and the PRACH, the network entity **105** may benefit from an increase in reliability for performing PUSCH channel estimation.

(93) FIG. **7** illustrates an example of uplink message configurations **700** that may include uplink message configurations **700-a** and **700-b** that support DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the uplink message configuration **700** may implement one or more aspects of wireless communications system **100**, wireless communications system **200**, and uplink message configuration **400**. For instance, uplink message configurations **700-a** and **700-b** may be respective examples of an uplink message configurations **220** for a first UE **115** and a second UE **115**, with reference to FIGS. **1** and **2**. Additionally, or alternatively, the PRACH resources **705**, blank resources **710**, and PUSCH resources **715** may be respective examples of PRACH resources **225**, blank resources **230**, and PUSCH resources **235**, with reference to FIG. **2**. The uplink message configuration **700** may support transmission to a network entity **105** of respective uplink messages from the first UE **115** and the second UE **115** using different DMRS configurations.

(94) In some examples, the first and second UE **115** may generate the uplink message configurations **700-a** and **700-b** in accordance with respective control signaling received from the network entity **105**. For example, with reference to FIG. **2**, the uplink message configuration **700-a** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field indicating for the first UE **115** to include a full DMRS (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {full}). Additionally, or alternatively, the uplink message configuration **700-b** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field indicating for the second UE **115** to include a no DMRS (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {none}). While FIG. **7** illustrates two different DMRS configurations for two UEs **115**, it is understood that the network entity **105** may configure any number of UEs **115** using any of the different DMRS configurations described herein.

(95) As illustrated in FIG. **7**, the uplink message configuration **700-a** may not include a set of PRACH resources **705**, and instead includes a full DMRS and a PUSCH transmission over a second time range, where the DMRS resources **720** span the same frequency resources as the PUSCH resources **715**. Additionally, or alternatively, the uplink message configuration **700-b** includes a set of PRACH resources **705** during a first time range that spans a first frequency range, and may include a set of PUSCH resources **715** during the second time range that spans a second frequency range. In some examples of uplink message configuration **700-b**, the second frequency range associated with the PUSCH resources **715** may be included in the first frequency range associated with the PRACH resource **705** (e.g., PUSCH bandwidth .Math. PRACH bandwidth).

(96) As such, the first UE **115** and the second UE **115** may transmit respective uplink messages to the network entity **105** in accordance with the uplink message configuration **700-a** and **700-b**. In some examples, the network entity **105** may perform channel estimation on the PUSCH from the first UE **115** using the received DMRS resources **720**. Additionally, or alternatively, the network entity **105** may perform channel estimation on the PUSCH resources **715** from the second UE **115** based on performing a channel estimation on the PRACH resources **705** and extrapolating channel coefficients using techniques described with reference to FIG. **4**. By using different DMRS

configurations for different UEs **115**, the network entity **105** may benefit from being able to use the various PUSCH channel estimation techniques described herein while reducing the total number of DMRS resources **720** used.

(97) FIG. **8** illustrates an example of an uplink message configuration **800** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, the uplink message configuration **800** may implement one or more aspects of wireless communications system **100**, wireless communications system **200**, and uplink message configuration **400**. For instance, uplink message configuration **800** may be an example of the uplink message configuration **220**, with reference to FIG. **2**. Additionally, or alternatively, the PRACH resources **805**, blank resources **810**, and PUSCH resources **815** may be respective examples of PRACH resources **225**, blank resources **230**, and PUSCH resources **235**, with reference to FIG. **2**. The uplink message configuration **800** may support transmission of an uplink message from a UE **115** to a network entity **105** without DMRS in at least a first portion of the uplink message.

(98) In some examples, the UE **115** may generate the uplink message configuration **800** in accordance with control signaling received from the network entity **105**. For example, with reference to FIG. **2**, the uplink message configuration **800** may be an example of a configuration generated based on receiving a DMRS configuration message **205** including a field indicating for the UE **115** to include DMRS is a portion of the uplink message (e.g., MsgA-PUSCH-DMRS-version ENUMERATED {full}). As such, the UE **115** may generate the uplink message configuration **800** with a full DMRS (e.g., DMRS that spans a set of frequency resources that include the PUSCH frequency resources). In some examples, the DMRS configuration message **205** may also include a field that indicates for the UE **115** to include the DMRS resources **820** for the full DMRS at the end of a time slot associated with the PUSCH transmission of the uplink message configuration **800**. Additionally, or alternatively, the UE **115** may determine or be preconfigured to include the DMRS at the end of the slot. For example, the UE **115** may receive an indication or be configured to refrain from including DMRS with the PRACH and therefore when the UE **115** is configured to include full DMRS with the uplink message, the UE **115** may determine to include the DRMS after the PUSCH.

(99) In some examples, the network entity **105** may indicate for the UE **115** to use incorporate DMRS in cases where Doppler for one or more channels between the UE **115** and network entity **105** are above a configured threshold. In some cases, the UE **115** may be configured to incorporate DMRS at the end of an uplink message in high doppler scenario. For instance, if the UE **115** is operating in a high mobility environment (e.g., on a high-speed train) the UE **115** may experience frequency Doppler shifting for a set of time-frequency resources as the UE **115** moves relative to the network entity **105**. For example, channel estimates based on PRACH resources **805** may no longer be completely accurate by the time of the PUSCH resources **815** due to the high doppler. By interpolating the channel coefficients from the PRACH resources **805** before the PUSCH transmission and the channel coefficients of the DMRS resources **820** after the PUSCH transmission, the network entity **105** may identify and mitigate time and frequency resource shifting incurred by Doppler to increase channel estimation of the PUSCH resources **815**.

(100) As illustrated in FIG. **8**, the uplink message configuration **800** includes a set of PRACH resources **805** during a first time range that spans a first frequency range, and may include a set of PUSCH resources **815** and DMRS resources **820** during a second time range that spans a second frequency range.

(101) As such, the UE **115** may transmit an uplink message to the network entity **105** in accordance with the uplink message configuration **800**. In some examples, the network entity **105** may perform channel estimation on the PUSCH resources **815** based on performing a channel estimation on the PRACH resources **805** in combination with a channel estimation of the DMRS resources **820**. For example, as discussed with reference to FIG. **4**, the network entity **105** may perform channel

estimation of the PRACH resources **805** via Zadoff-Chu sequences and further perform channel estimation of the DMRS resources **820**. As such, the network entity **105** may combine the PRACH and DMRS channel estimations and interpolate channel coefficients to use for the PUSCH resources **815**. By interpolating channel estimation from the partial DMRS and the PRACH, the network entity **105** may benefit from an increase in reliability for performing PUSCH channel estimation.

(102) FIG. **9** illustrates an example of a process flow **900** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. In some examples, process flow **900** may implement aspects of wireless communications system **100**, wireless communications system **200**, multi-user decoding algorithm **300**, uplink message configurations **400** through **800**, or a combination thereof. Process flow **900** includes a UE **115-b** and a network entity **105-b**, which may be respective examples of a UE **115** and a network entity **105**, as described with reference to FIGS. **1** and **2**. Alternative examples of the following may be implemented, where some steps may be performed in a different order than described or are not performed at all. In some cases, steps may include additional features not mentioned below, or further steps may be added. In addition, while process flow **900** shows processes between a single UE **115** and a single network entity **105**, it should be understood that these processes may occur between any number of wireless devices, network devices, and/or network device types.

(103) At **905**, the UE **115-b** may receive from the network entity **105-b** control signaling indicating a DMRS configuration for an uplink message. In some examples, the control signaling may indicate that the UE **115-b** may be to refrain from including DMRS in at least a first portion of the uplink message in accordance with the DMRS configuration. In some examples, the UE **115-b** may receive an RRC message (or some other control message) including the DMRS configuration for the uplink message. In some examples, the DMRS configuration may be based on an amount of Doppler spread at the UE **115-b**.

(104) In some examples, the DMRS configuration may include a field indicating that the UE **115-b** may refrain from including the DMRS in the first portion of the uplink message. Additionally, or alternatively, the DMRS configuration includes a field indicating an LDPC code and an RM code for the UE **115-b** to use for encoding the uplink message. In some cases, the field may be included in an uplink channel resource information element.

(105) In some examples, the UE **115-b** may receive an indication of whether the UE **115-b** may include the DMRS in a second portion of the uplink message on a frequency bandwidth that may be covered by a RACH of the uplink message. In some cases, the RACH may be included in the first portion of the uplink message. For instance, the UE **115-b** may receive a first configuration indicating for the UE **115-b** to include one or more DMRSs in each frequency resource of the frequency bandwidth covered by the RACH. Additionally, or alternatively, the UE **115-b** may receive a second configuration indicating to include the one or more DMRSs in a subset of frequency resources of the frequency bandwidth covered by the RACH. Additionally, or alternatively, the UE **115-b** may receive a third configuration indicating the UE **115-b** to refrain from including DMRSs in the second portion of the uplink message.

(106) In some instances, the UE **115-b** may receive an indication of a PRACH comb pattern to apply to the first portion of the uplink message.

(107) In some examples, at **910**, the UE **115-b** may select a PRACH preamble to include in the uplink message. Additionally, or alternatively, the UE **115-b** may generate a scrambling ID associated with the UE **115-b** based on the PRACH preamble, or based on RRC signaling (e.g., from the network entity **105-b**) indicating the scrambling ID, or both. In such examples, encoding the uplink message may be based on the scrambling identification.

(108) At **915**, the UE **115-b** may encode the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode, using a RM code, the uplink message without the DMRS included in the

first portion in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode the uplink message without the DMRS in any portion of the uplink message in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode the first portion of the uplink message in accordance with a PRACH comb pattern based on the DMRS configuration. In some examples, the UE **115-b** may encode the uplink message to include one or more DMRS in a second portion of the uplink message in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode the second portion of the uplink message to include the one or more DMRS at a start or at an end of the second portion in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode the second portion of the uplink message to include the one or more DMRS in a set of frequency resources without RACH signals in accordance with the DMRS configuration. In some examples, the UE **115-b** may encode the second portion of the uplink message to include the one or more DMRS in a set of frequency resources that include RACH signals in the first portion based on the DMRS configuration. (109) At **920**, the UE **115-b** may transmit the uplink message based on encoding the uplink message. In some examples, the UE **115-b** may transmit a PRACH in a first set of frequency resources in the first portion of the uplink message in accordance with the DMRS configuration, and transmit an uplink shared channel (e.g., a PUSCH) in a second set of frequency resources in a second portion of the uplink message in accordance with the DMRS configuration. In some examples, the first set of frequency resources and the second set of frequency resources include a same set of frequency resources or a subset of same frequency resources. In some cases, the DMRS configuration may be based on the first set of frequency resources including the second set of frequency resources. In some cases, the DMRS configuration may be based on the second set of frequency resources including the first set of frequency resources.

(110) In some examples, the network entity **105-b** may receive a signal including a set of uplink messages from multiple UEs **115** (not illustrated in FIG. **9**), where each uplink message of the set of uplink messages may be associated with a RM code.

(111) At **925**, the network entity **105-b** may decode the uplink message based on the DMRS configuration. In examples where the network entity **105-b** receives the signal including a set of uplink messages from different UEs **115**, the network entity **105-b** may decode, using a respective RM code, the uplink message, where the uplink message may be without the DMRS included in the first portion of the uplink message in accordance with the DMRS configuration. As such, the network entity **105-b** may cancel the decoded uplink message from the signal including the set of uplink messages in accordance with a multi-user decoding algorithm.

(112) FIG. **10** shows a block diagram **1000** of a device **1005** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The device **1005** may be an example of aspects of a UE **115** as described herein. The device **1005** may include a receiver **1010**, a transmitter **1015**, and a communications manager **1020**. The device **1005** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(113) The receiver **1010** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to DMRS configuration for uplink messages). Information may be passed on to other components of the device **1005**. The receiver **1010** may utilize a single antenna or a set of multiple antennas.

(114) The transmitter **1015** may provide a means for transmitting signals generated by other components of the device **1005**. For example, the transmitter **1015** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to DMRS configuration for uplink messages). In some examples, the transmitter **1015** may be co-located with a receiver **1010** in a transceiver module. The transmitter **1015** may utilize a single antenna or a set

of multiple antennas.

(115) The communications manager **1020**, the receiver **1010**, the transmitter **1015**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1020**, the receiver **1010**, the transmitter **1015**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

(116) In some examples, the communications manager **1020**, the receiver **1010**, the transmitter **1015**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a digital signal processor (DSP), a central processing unit (CPU), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

(117) Additionally, or alternatively, in some examples, the communications manager **1020**, the receiver **1010**, the transmitter **1015**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **1020**, the receiver **1010**, the transmitter **1015**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

(118) In some examples, the communications manager **1020** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1010**, the transmitter **1015**, or both. For example, the communications manager **1020** may receive information from the receiver **1010**, send information to the transmitter **1015**, or be integrated in combination with the receiver **1010**, the transmitter **1015**, or both to obtain information, output information, or perform various other operations as described herein.

(119) The communications manager **1020** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **1020** may be configured as or otherwise support a means for receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The communications manager **1020** may be configured as or otherwise support a means for encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The communications manager **1020** may be configured as or otherwise support a means for transmitting the uplink message based on encoding the uplink message.

(120) By including or configuring the communications manager **1020** in accordance with examples as described herein, the device **1005** (e.g., a processor controlling or otherwise coupled with the receiver **1010**, the transmitter **1015**, the communications manager **1020**, or a combination thereof) may support techniques for reducing bottleneck of DMRS ports by reducing DMRS in an uplink message which may read to reduced signaling overhead, reduced power consumption, and a more efficient utilization of communication resources.

(121) FIG. **11** shows a block diagram **1100** of a device **1105** that supports DMRS configuration for

uplink messages in accordance with one or more aspects of the present disclosure. The device **1105** may be an example of aspects of a device **1005** or a UE **115** as described herein. The device **1105** may include a receiver **1110**, a transmitter **1115**, and a communications manager **1120**. The device **1105** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(122) The receiver **1110** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to DMRS configuration for uplink messages). Information may be passed on to other components of the device **1105**. The receiver **1110** may utilize a single antenna or a set of multiple antennas.

(123) The transmitter **1115** may provide a means for transmitting signals generated by other components of the device **1105**. For example, the transmitter **1115** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to DMRS configuration for uplink messages). In some examples, the transmitter **1115** may be co-located with a receiver **1110** in a transceiver module. The transmitter **1115** may utilize a single antenna or a set of multiple antennas.

(124) The device **1105**, or various components thereof, may be an example of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1120** may include a control signaling reception component **1125**, an encoding component **1130**, an uplink message transmission component **1135**, or any combination thereof. The communications manager **1120** may be an example of aspects of a communications manager **1020** as described herein. In some examples, the communications manager **1120**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1110**, the transmitter **1115**, or both. For example, the communications manager **1120** may receive information from the receiver **1110**, send information to the transmitter **1115**, or be integrated in combination with the receiver **1110**, the transmitter **1115**, or both to obtain information, output information, or perform various other operations as described herein.

(125) The communications manager **1120** may support wireless communications at a UE in accordance with examples as disclosed herein. The control signaling reception component **1125** may be configured as or otherwise support a means for receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The encoding component **1130** may be configured as or otherwise support a means for encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The uplink message transmission component **1135** may be configured as or otherwise support a means for transmitting the uplink message based on encoding the uplink message.

(126) FIG. **12** shows a block diagram **1200** of a communications manager **1220** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The communications manager **1220** may be an example of aspects of a communications manager **1020**, a communications manager **1120**, or both, as described herein. The communications manager **1220**, or various components thereof, may be an example of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1220** may include a control signaling reception component **1225**, an encoding component **1230**, an uplink message transmission component **1235**, a PRACH preamble selection component **1240**, a scrambling ID generation component **1245**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(127) The communications manager **1220** may support wireless communications at a UE in accordance with examples as disclosed herein. The control signaling reception component **1225** may be configured as or otherwise support a means for receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The encoding component **1230** may be configured as or otherwise support a means for encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The uplink message transmission component **1235** may be configured as or otherwise support a means for transmitting the uplink message based on encoding the uplink message.

(128) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding, using a RM code, the uplink message without the DMRS included in the first portion in accordance with the DMRS configuration.

(129) In some examples, the DMRS configuration includes a field indicating that the UE is to refrain from including the DMRS in the first portion of the uplink message.

(130) In some examples, the DMRS configuration includes a field indicating a LDPC code and a RM code for the UE to use for encoding the uplink message. In some examples, the field is included in an uplink channel resource information element.

(131) In some examples, the PRACH preamble selection component **1240** may be configured as or otherwise support a means for selecting a PRACH preamble to include in the uplink message. In some examples, the scrambling ID generation component **1245** may be configured as or otherwise support a means for generating a scrambling identification associated with the UE based on the PRACH preamble, or based on RRC signaling indicating the scrambling identification, or both, where encoding the uplink message is based on the scrambling identification.

(132) In some examples, to support receiving the DMRS configuration, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving an indication of whether the UE is to include the DMRS in a second portion of the uplink message on a frequency bandwidth that is covered by a RACH of the uplink message, where the RACH is included in the first portion of the uplink message.

(133) In some examples, to support receiving the indication, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving a first configuration indicating for the UE to include one or more demodulated reference signals in each frequency resource of the frequency bandwidth covered by the RACH. In some examples, to support receiving the indication, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving a second configuration indicating for the UE to include the one or more demodulated reference signals in a subset of frequency resources of the frequency bandwidth covered by the RACH. In some examples, to support receiving the indication, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving a third configuration indicating for the UE to refrain from including demodulated reference signals in the second portion of the uplink message.

(134) In some examples, to support receiving the DMRS configuration, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving an indication of a PRACH comb pattern to apply to the first portion of the uplink message.

(135) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the uplink message without the DMRS in any portion of the uplink message in accordance with the DMRS configuration.

(136) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the first portion of the uplink message in accordance with a PRACH comb pattern based on the DMRS configuration.

(137) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the uplink message to include one or more DMRS in a second portion of the uplink message in accordance with the DMRS configuration.

(138) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the second portion of the uplink message to include the one or more DMRS at a start or at an end of the second portion in accordance with the DMRS configuration.

(139) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the second portion of the uplink message to include the one or more DMRS in a set of frequency resources without RACH signals in accordance with the DMRS configuration.

(140) In some examples, to support encoding the uplink message, the encoding component **1230** may be configured as or otherwise support a means for encoding the second portion of the uplink message to include the one or more DMRS in a set of frequency resources that include RACH signals in the first portion based on the DMRS configuration.

(141) In some examples, the DMRS configuration is based on an amount of Doppler spread at the UE.

(142) In some examples, to support transmitting the uplink message, the uplink message transmission component **1235** may be configured as or otherwise support a means for transmitting a PRACH in a first set of frequency resources in the first portion of the uplink message in accordance with the DMRS configuration. In some examples, to support transmitting the uplink message, the uplink message transmission component **1235** may be configured as or otherwise support a means for transmitting an uplink shared channel in a second set of frequency resources in a second portion of the uplink message in accordance with the DMRS configuration, where the first set of frequency resources and the second set of frequency resources include a same set of frequency resources or a subset of same frequency resources.

(143) In some examples, the DMRS configuration is based on the first set of frequency resources including the second set of frequency resources.

(144) In some examples, the DMRS configuration is based on the second set of frequency resources including the first set of frequency resources.

(145) In some examples, to support receiving the control signaling, the control signaling reception component **1225** may be configured as or otherwise support a means for receiving a RRC message including the DMRS configuration for the uplink message.

(146) FIG. **13** shows a diagram of a system **1300** including a device **1305** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The device **1305** may be an example of or include the components of a device **1005**, a device **1105**, or a UE **115** as described herein. The device **1305** may communicate (e.g., wirelessly) with one or more network entities **105**, one or more UEs **115**, or any combination thereof. The device **1305** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **1320**, an input/output (I/O) controller **1310**, a transceiver **1315**, an antenna **1325**, a memory **1330**, code **1335**, and a processor **1340**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1345**).

(147) The I/O controller **1310** may manage input and output signals for the device **1305**. The I/O controller **1310** may also manage peripherals not integrated into the device **1305**. In some cases, the I/O controller **1310** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **1310** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system.

Additionally, or alternatively, the I/O controller **1310** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **1310** may be implemented as part of a processor, such as the processor **1340**. In some cases, a user may interact with the device **1305** via the I/O controller **1310** or via hardware components controlled by the I/O controller **1310**.

(148) In some cases, the device **1305** may include a single antenna **1325**. However, in some other cases, the device **1305** may have more than one antenna **1325**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **1315** may communicate bi-directionally, via the one or more antennas **1325**, wired, or wireless links as described herein. For example, the transceiver **1315** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1315** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **1325** for transmission, and to demodulate packets received from the one or more antennas **1325**. The transceiver **1315**, or the transceiver **1315** and one or more antennas **1325**, may be an example of a transmitter **1015**, a transmitter **1115**, a receiver **1010**, a receiver **1110**, or any combination thereof or component thereof, as described herein.

(149) The memory **1330** may include random access memory (RAM) and read-only memory (ROM). The memory **1330** may store computer-readable, computer-executable code **1335** including instructions that, when executed by the processor **1340**, cause the device **1305** to perform various functions described herein. The code **1335** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1335** may not be directly executable by the processor **1340** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1330** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(150) The processor **1340** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **1340** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1340**. The processor **1340** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1330**) to cause the device **1305** to perform various functions (e.g., functions or tasks supporting DMRS configuration for uplink messages). For example, the device **1305** or a component of the device **1305** may include a processor **1340** and memory **1330** coupled with or to the processor **1340**, the processor **1340** and memory **1330** configured to perform various functions described herein.

(151) The communications manager **1320** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **1320** may be configured as or otherwise support a means for receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The communications manager **1320** may be configured as or otherwise support a means for encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The communications manager **1320** may be configured as or otherwise support a means for transmitting the uplink message based on encoding the uplink message.

(152) By including or configuring the communications manager **1320** in accordance with examples as described herein, the device **1305** may support techniques for reducing bottleneck of DMRS ports by reducing DMRS in an uplink message which may read to reduced signaling overhead, reduced power consumption, improved coordination between devices, longer battery life, improved

utilization of processing capability, and a more efficient utilization of communication resources.

(153) In some examples, the communications manager **1320** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **1315**, the one or more antennas **1325**, or any combination thereof. Although the communications manager **1320** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1320** may be supported by or performed by the processor **1340**, the memory **1330**, the code **1335**, or any combination thereof. For example, the code **1335** may include instructions executable by the processor **1340** to cause the device **1305** to perform various aspects of DMRS configuration for uplink messages as described herein, or the processor **1340** and the memory **1330** may be otherwise configured to perform or support such operations.

(154) FIG. **14** shows a block diagram **1400** of a device **1405** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The device **1405** may be an example of aspects of a network entity **105** as described herein. The device **1405** may include a receiver **1410**, a transmitter **1415**, and a communications manager **1420**. The device **1405** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(155) The receiver **1410** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **1405**. In some examples, the receiver **1410** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **1410** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

(156) The transmitter **1415** may provide a means for outputting (e.g., transmitting, providing, conveying, sending) information generated by other components of the device **1405**. For example, the transmitter **1415** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **1415** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **1415** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **1415** and the receiver **1410** may be co-located in a transceiver, which may include or be coupled with a modem.

(157) The communications manager **1420**, the receiver **1410**, the transmitter **1415**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1420**, the receiver **1410**, the transmitter **1415**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

(158) In some examples, the communications manager **1420**, the receiver **1410**, the transmitter **1415**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a DSP, a CPU, an ASIC, an FPGA or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one

or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

(159) Additionally, or alternatively, in some examples, the communications manager **1420**, the receiver **1410**, the transmitter **1415**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **1420**, the receiver **1410**, the transmitter **1415**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

(160) In some examples, the communications manager **1420** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1410**, the transmitter **1415**, or both. For example, the communications manager **1420** may receive information from the receiver **1410**, send information to the transmitter **1415**, or be integrated in combination with the receiver **1410**, the transmitter **1415**, or both to obtain information, output information, or perform various other operations as described herein.

(161) The communications manager **1420** may support wireless communications at a network entity in accordance with examples as disclosed herein. For example, the communications manager **1420** may be configured as or otherwise support a means for transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The communications manager **1420** may be configured as or otherwise support a means for receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The communications manager **1420** may be configured as or otherwise support a means for decoding the uplink message based on the DMRS configuration.

(162) By including or configuring the communications manager **1420** in accordance with examples as described herein, the device **1405** (e.g., a processor controlling or otherwise coupled with the receiver **1410**, the transmitter **1415**, the communications manager **1420**, or a combination thereof) may support techniques for reducing bottleneck of DMRS ports by reducing DMRS in an uplink message which may read to reduced signaling overhead, reduced power consumption, and a more efficient utilization of communication resources.

(163) FIG. **15** shows a block diagram **1500** of a device **1505** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The device **1505** may be an example of aspects of a device **1405** or a network entity **105** as described herein. The device **1505** may include a receiver **1510**, a transmitter **1515**, and a communications manager **1520**. The device **1505** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(164) The receiver **1510** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **1505**. In some examples, the receiver **1510** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **1510** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

(165) The transmitter **1515** may provide a means for outputting (e.g., transmitting, providing,

conveying, sending) information generated by other components of the device **1505**. For example, the transmitter **1515** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **1515** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **1515** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **1515** and the receiver **1510** may be co-located in a transceiver, which may include or be coupled with a modem.

(166) The device **1505**, or various components thereof, may be an example of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1520** may include a control signaling transmission component **1525**, an uplink message reception component **1530**, a decoding component **1535**, or any combination thereof. The communications manager **1520** may be an example of aspects of a communications manager **1420** as described herein. In some examples, the communications manager **1520**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1510**, the transmitter **1515**, or both. For example, the communications manager **1520** may receive information from the receiver **1510**, send information to the transmitter **1515**, or be integrated in combination with the receiver **1510**, the transmitter **1515**, or both to obtain information, output information, or perform various other operations as described herein.

(167) The communications manager **1520** may support wireless communications at a network entity in accordance with examples as disclosed herein. The control signaling transmission component **1525** may be configured as or otherwise support a means for transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The uplink message reception component **1530** may be configured as or otherwise support a means for receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The decoding component **1535** may be configured as or otherwise support a means for decoding the uplink message based on the DMRS configuration.

(168) FIG. **16** shows a block diagram **1600** of a communications manager **1620** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The communications manager **1620** may be an example of aspects of a communications manager **1420**, a communications manager **1520**, or both, as described herein. The communications manager **1620**, or various components thereof, may be an example of means for performing various aspects of DMRS configuration for uplink messages as described herein. For example, the communications manager **1620** may include a control signaling transmission component **1625**, an uplink message reception component **1630**, a decoding component **1635**, an uplink message cancelation component **1640**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses) which may include communications within a protocol layer of a protocol stack, communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack, within a device, component, or virtualized component associated with a network entity **105**, between devices, components, or virtualized components associated with a network entity **105**), or any combination thereof.

(169) The communications manager **1620** may support wireless communications at a network entity in accordance with examples as disclosed herein. The control signaling transmission component **1625** may be configured as or otherwise support a means for transmitting control

signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The uplink message reception component **1630** may be configured as or otherwise support a means for receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The decoding component **1635** may be configured as or otherwise support a means for decoding the uplink message based on the DMRS configuration.

(170) In some examples, the uplink message reception component **1630** may be configured as or otherwise support a means for receiving a signal including a set of uplink messages from different UEs, where each uplink message of the set of uplink messages is associated with a RM code.

(171) In some examples, to support decoding the uplink message, the decoding component **1635** may be configured as or otherwise support a means for decoding, using a respective RM code, the uplink message, where the uplink message is without the DMRS included in the first portion of the uplink message in accordance with the DMRS configuration. In some examples, to support decoding the uplink message, the uplink message cancelation component **1640** may be configured as or otherwise support a means for canceling the decoded uplink message from the signal including the set of uplink messages in accordance with a multi-user decoding algorithm.

(172) In some examples, the DMRS configuration includes a field indicating a LDPC code and a RM code for the UE to use for encoding the uplink message. In some examples, the field is included in an uplink channel resource information element.

(173) FIG. **17** shows a diagram of a system **1700** including a device **1705** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The device **1705** may be an example of or include the components of a device **1405**, a device **1505**, or a network entity **105** as described herein. The device **1705** may communicate with one or more network entities **105**, one or more UEs **115**, or any combination thereof, which may include communications over one or more wired interfaces, over one or more wireless interfaces, or any combination thereof. The device **1705** may include components that support outputting and obtaining communications, such as a communications manager **1720**, a transceiver **1710**, an antenna **1715**, a memory **1725**, code **1730**, and a processor **1735**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1740**).

(174) The transceiver **1710** may support bi-directional communications via wired links, wireless links, or both as described herein. In some examples, the transceiver **1710** may include a wired transceiver and may communicate bi-directionally with another wired transceiver. Additionally, or alternatively, in some examples, the transceiver **1710** may include a wireless transceiver and may communicate bi-directionally with another wireless transceiver. In some examples, the device **1705** may include one or more antennas **1715**, which may be capable of transmitting or receiving wireless transmissions (e.g., concurrently). The transceiver **1710** may also include a modem to modulate signals, to provide the modulated signals for transmission (e.g., by one or more antennas **1715**, by a wired transmitter), to receive modulated signals (e.g., from one or more antennas **1715**, from a wired receiver), and to demodulate signals. The transceiver **1710**, or the transceiver **1710** and one or more antennas **1715** or wired interfaces, where applicable, may be an example of a transmitter **1415**, a transmitter **1515**, a receiver **1410**, a receiver **1510**, or any combination thereof or component thereof, as described herein. In some examples, the transceiver may be operable to support communications via one or more communications links (e.g., a communication link **125**, a backhaul communication link **120**, a midhaul communication link **162**, a fronthaul communication link **168**).

(175) The memory **1725** may include RAM and ROM. The memory **1725** may store computer-readable, computer-executable code **1730** including instructions that, when executed by the processor **1735**, cause the device **1705** to perform various functions described herein. The code

1730 may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1730** may not be directly executable by the processor **1735** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1725** may contain, among other things, a BIOS which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(176) The processor **1735** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA, a microcontroller, a programmable logic device, discrete gate or transistor logic, a discrete hardware component, or any combination thereof). In some cases, the processor **1735** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1735**. The processor **1735** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1725**) to cause the device **1705** to perform various functions (e.g., functions or tasks supporting DMRS configuration for uplink messages). For example, the device **1705** or a component of the device **1705** may include a processor **1735** and memory **1725** coupled with the processor **1735**, the processor **1735** and memory **1725** configured to perform various functions described herein. The processor **1735** may be an example of a cloud-computing platform (e.g., one or more physical nodes and supporting software such as operating systems, virtual machines, or container instances) that may host the functions (e.g., by executing code **1730**) to perform the functions of the device **1705**.

(177) In some examples, a bus **1740** may support communications of (e.g., within) a protocol layer of a protocol stack. In some examples, a bus **1740** may support communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack), which may include communications performed within a component of the device **1705**, or between different components of the device **1705** that may be co-located or located in different locations (e.g., where the device **1705** may refer to a system in which one or more of the communications manager **1720**, the transceiver **1710**, the memory **1725**, the code **1730**, and the processor **1735** may be located in one of the different components or divided between different components).

(178) In some examples, the communications manager **1720** may manage aspects of communications with a core network **130** (e.g., via one or more wired or wireless backhaul links). For example, the communications manager **1720** may manage the transfer of data communications for client devices, such as one or more UEs **115**. In some examples, the communications manager **1720** may manage communications with other network entities **105**, and may include a controller or scheduler for controlling communications with UEs **115** in cooperation with other network entities **105**. In some examples, the communications manager **1720** may support an X2 interface within an LTE/LTE-A wireless communications network technology to provide communication between network entities **105**.

(179) The communications manager **1720** may support wireless communications at a network entity in accordance with examples as disclosed herein. For example, the communications manager **1720** may be configured as or otherwise support a means for transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The communications manager **1720** may be configured as or otherwise support a means for receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The communications manager **1720** may be configured as or otherwise support a means for decoding the uplink message based on the DMRS configuration.

(180) By including or configuring the communications manager **1720** in accordance with examples as described herein, the device **1705** may support techniques for reducing bottleneck of DMRS ports by reducing DMRS in an uplink message which may read to reduced signaling overhead,

reduced power consumption, improved coordination between devices, longer battery life, improved utilization of processing capability, and a more efficient utilization of communication resources.

(181) In some examples, the communications manager **1720** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the transceiver **1710**, the one or more antennas **1715** (e.g., where applicable), or any combination thereof. Although the communications manager **1720** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1720** may be supported by or performed by the processor **1735**, the memory **1725**, the code **1730**, the transceiver **1710**, or any combination thereof. For example, the code **1730** may include instructions executable by the processor **1735** to cause the device **1705** to perform various aspects of DMRS configuration for uplink messages as described herein, or the processor **1735** and the memory **1725** may be otherwise configured to perform or support such operations.

(182) FIG. **18** shows a flowchart illustrating a method **1800** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The operations of the method **1800** may be implemented by a UE or its components as described herein. For example, the operations of the method **1800** may be performed by a UE **115** as described with reference to FIGS. **1** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(183) At **1805**, the method may include receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The operations of **1805** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1805** may be performed by a control signaling reception component **1225** as described with reference to FIG. **12**.

(184) At **1810**, the method may include encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The operations of **1810** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1810** may be performed by an encoding component **1230** as described with reference to FIG. **12**.

(185) At **1815**, the method may include transmitting the uplink message based on encoding the uplink message. The operations of **1815** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1815** may be performed by an uplink message transmission component **1235** as described with reference to FIG. **12**.

(186) FIG. **19** shows a flowchart illustrating a method **1900** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The operations of the method **1900** may be implemented by a UE or its components as described herein. For example, the operations of the method **1900** may be performed by a UE **115** as described with reference to FIGS. **1** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(187) At **1905**, the method may include receiving control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that the UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The operations of **1905** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1905** may be performed by a control signaling reception component **1225** as described with reference to FIG. **12**.

(188) At **1910**, the method may include receiving an indication of whether the UE is to include the DMRS in a second portion of the uplink message on a frequency bandwidth that is covered by a RACH of the uplink message, where the RACH is included in the first portion of the uplink message. The operations of **1910** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1910** may be performed by a control signaling reception component **1225** as described with reference to FIG. **12**.

(189) At **1915**, the method may include encoding the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The operations of **1915** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1915** may be performed by an encoding component **1230** as described with reference to FIG. **12**.

(190) At **1920**, the method may include transmitting the uplink message based on encoding the uplink message. The operations of **1920** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1920** may be performed by an uplink message transmission component **1235** as described with reference to FIG. **12**.

(191) FIG. **20** shows a flowchart illustrating a method **2000** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The operations of the method **2000** may be implemented by a network entity or its components as described herein. For example, the operations of the method **2000** may be performed by a network entity as described with reference to FIGS. **1** through **9** and **14** through **17**. In some examples, a network entity may execute a set of instructions to control the functional elements of the network entity to perform the described functions. Additionally, or alternatively, the network entity may perform aspects of the described functions using special-purpose hardware.

(192) At **2005**, the method may include transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The operations of **2005** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2005** may be performed by a control signaling transmission component **1625** as described with reference to FIG. **16**.

(193) At **2010**, the method may include receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The operations of **2010** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2010** may be performed by an uplink message reception component **1630** as described with reference to FIG. **16**.

(194) At **2015**, the method may include decoding the uplink message based on the DMRS configuration. The operations of **2015** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2015** may be performed by a decoding component **1635** as described with reference to FIG. **16**.

(195) FIG. **21** shows a flowchart illustrating a method **2100** that supports DMRS configuration for uplink messages in accordance with one or more aspects of the present disclosure. The operations of the method **2100** may be implemented by a network entity or its components as described herein. For example, the operations of the method **2100** may be performed by a network entity as described with reference to FIGS. **1** through **9** and **14** through **17**. In some examples, a network entity may execute a set of instructions to control the functional elements of the network entity to perform the described functions. Additionally, or alternatively, the network entity may perform aspects of the described functions using special-purpose hardware.

(196) At **2105**, the method may include transmitting control signaling indicating a DMRS configuration for an uplink message, where the control signaling further indicates that a UE is to refrain from including DMRS in at least a first portion of the uplink message based on the DMRS configuration. The operations of **2105** may be performed in accordance with examples as disclosed

herein. In some examples, aspects of the operations of **2105** may be performed by a control signaling transmission component **1625** as described with reference to FIG. **16**.

(197) At **2110**, the method may include receiving the uplink message without the DMRS in at least the first portion of the uplink message in accordance with the DMRS configuration. The operations of **2110** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2110** may be performed by an uplink message reception component **1630** as described with reference to FIG. **16**.

(198) At **2115**, the method may include receiving a signal including a set of uplink messages from different UEs, where each uplink message of the set of uplink messages is associated with a RM code. The operations of **2115** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2115** may be performed by an uplink message reception component **1630** as described with reference to FIG. **16**.

(199) At **2120**, the method may include decoding the uplink message based on the DMRS configuration. The operations of **2120** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2120** may be performed by a decoding component **1635** as described with reference to FIG. **16**.

(200) The following provides an overview of aspects of the present disclosure: Aspect 1: A method for wireless communications at a UE, comprising: receiving control signaling indicating a DMRS configuration for an uplink message, wherein the control signaling further indicates that the UE is to refrain from including DMRSs in at least a first portion of the uplink message based at least in part on the DMRS configuration; encoding the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration; and transmitting the uplink message based at least in part on encoding the uplink message. Aspect 2: The method of aspect 1, wherein encoding the uplink message further comprises: encoding, using a RM code, the uplink message without the DMRSs included in the first portion in accordance with the DMRS configuration. Aspect 3: The method of any of aspects 1 through 2, wherein the DMRS configuration comprises a field indicating that the UE is to refrain from including the DMRSs in the first portion of the uplink message. Aspect 4: The method of any of aspects 1 through 3, wherein the DMRS configuration comprises a field indicating a low-density parity-check code and a RM code for the UE to use for encoding the uplink message, the field is included in an uplink channel resource information element. Aspect 5: The method of any of aspects 1 through 4, further comprising: selecting a PRACH preamble to include in the uplink message; and generating a scrambling identification associated with the UE based at least in part on the PRACH preamble, or based on RRC signaling indicating the scrambling identification, or both, wherein encoding the uplink message is based at least in part on the scrambling identification. Aspect 6: The method of any of aspects 1 through 5, wherein receiving the DMRS configuration further comprises: receiving an indication of whether the UE is to include the DMRSs in a second portion of the uplink message on a frequency bandwidth that is covered by a random access channel of the uplink message, wherein the random access channel is included in the first portion of the uplink message. Aspect 7: The method of aspect 6, wherein receiving the indication further comprises: receiving a first configuration indicating for the UE to include one or more demodulated reference signals in each frequency resource of the frequency bandwidth covered by the random access channel; receiving a second configuration indicating for the UE to include the one or more demodulated reference signals in a subset of frequency resources of the frequency bandwidth covered by the random access channel;

(201) or receiving a third configuration indicating for the UE to refrain from including demodulated reference signals in the second portion of the uplink message. Aspect 8: The method of any of aspects 1 through 7, wherein receiving the DMRS configuration comprises: receiving an indication of a PRACH comb pattern to apply to the first portion of the uplink message. Aspect 9: The method of any of aspects 1 through 8, wherein encoding the uplink message further comprises:

encoding the uplink message without the DMRSs in any portion of the uplink message in accordance with the DMRS configuration. Aspect 10: The method of any of aspects 1 through 9, wherein encoding the uplink message further comprises: encoding the first portion of the uplink message in accordance with a PRACH comb pattern based at least in part on the DMRS configuration. Aspect 11: The method of any of aspects 1 through 10, wherein encoding the uplink message further comprises: encoding the uplink message to include one or more DMRSs in a second portion of the uplink message in accordance with the DMRS configuration. Aspect 12: The method of aspect 11, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more DMRSs at a start or at an end of the second portion in accordance with the DMRS configuration. Aspect 13: The method of any of aspects 11 through 12, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more DMRSs in a set of frequency resources without random access channel signals in accordance with the DMRS configuration. Aspect 14: The method of any of aspects 11 through 13, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more DMRSs in a set of frequency resources that include random access channel signals in the first portion based at least in part on the DMRS configuration. Aspect 15: The method of any of aspects 1 through 14, wherein the DMRS configuration is based at least in part on an amount of Doppler spread at the UE. Aspect 16: The method of any of aspects 1 through 15, wherein transmitting the uplink message further comprises: transmitting a PRACH in a first set of frequency resources in the first portion of the uplink message in accordance with the DMRS configuration; and transmitting an uplink shared channel in a second set of frequency resources in a second portion of the uplink message in accordance with the DMRS configuration, wherein the first set of frequency resources and the second set of frequency resources comprise a same set of frequency resources or a subset of same frequency resources. Aspect 17: The method of aspect 16, wherein the DMRS configuration is based at least in part on the first set of frequency resources including the second set of frequency resources. Aspect 18: The method of any of aspects 16 through 17, wherein the DMRS configuration is based at least in part on the second set of frequency resources including the first set of frequency resources. Aspect 19: The method of any of aspects 1 through 18, wherein receiving the control signaling further comprises: receiving a RRC message comprising the DMRS configuration for the uplink message. Aspect 20: A method for wireless communications at a network entity, comprising: transmitting control signaling indicating a DMRS configuration for an uplink message, wherein the control signaling further indicates that a UE is to refrain from including DMRSs in at least a first portion of the uplink message based at least in part on the DMRS configuration; receiving the uplink message without the DMRSs in at least the first portion of the uplink message in accordance with the DMRS configuration; and decoding the uplink message based at least in part on the DMRS configuration. Aspect 21: The method of aspect 20, further comprising: receiving a signal comprising a set of uplink messages from different UEs, wherein each uplink message of the set of uplink messages is associated with a RM code. Aspect 22: The method of aspect 21, wherein decoding the uplink message further comprises: decoding, using a respective RM code, the uplink message, wherein the uplink message is without the DMRSs included in the first portion of the uplink message in accordance with the DMRS configuration; and canceling the decoded uplink message from the signal comprising the set of uplink messages in accordance with a multi-user decoding algorithm. Aspect 23: The method of any of aspects 20 through 22, wherein the DMRS configuration comprises a field indicating a low-density parity-check code and a RM code for the UE to use for encoding the uplink message, the field is included in an uplink channel resource information element. Aspect 24: An apparatus for wireless communications at a UE, comprising a processor; memory coupled with the processor; and instructions stored in the memory and executable by the processor to cause the apparatus to perform a method of any of aspects 1 through 19. Aspect 25: An apparatus for wireless

communications at a UE, comprising at least one means for performing a method of any of aspects 1 through 19. Aspect 26: A non-transitory computer-readable medium storing code for wireless communications at a UE, the code comprising instructions executable by a processor to perform a method of any of aspects 1 through 19. Aspect 27: An apparatus for wireless communications at a network entity, comprising a processor; memory coupled with the processor; and instructions stored in the memory and executable by the processor to cause the apparatus to perform a method of any of aspects 20 through 23. Aspect 28: An apparatus for wireless communications at a network entity, comprising at least one means for performing a method of any of aspects 20 through 23. Aspect 29: A non-transitory computer-readable medium storing code for wireless communications at a network entity, the code comprising instructions executable by a processor to perform a method of any of aspects 20 through 23.

(202) It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

(203) Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

(204) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(205) The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

(206) The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

(207) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk

storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers.

Combinations of the above are also included within the scope of computer-readable media.

(208) As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(209) The term “determine” or “determining” encompasses a variety of actions and, therefore, “determining” can include calculating, computing, processing, deriving, investigating, looking up (such as via looking up in a table, a database, or another data structure), ascertaining and the like. Also, “determining” can include receiving (such as receiving information), accessing (such as accessing data in a memory) and the like. Also, “determining” can include resolving, obtaining, selecting, choosing, establishing and other such similar actions.

(210) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

(211) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

(212) The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A method for wireless communications at a user equipment (UE), comprising: receiving control signaling indicating a demodulation reference signal configuration for an uplink message, wherein the demodulation reference signal configuration indicates a low-density parity-check code and a Reed-Muller code for the UE to use for encoding the uplink message or the demodulation reference signal configuration indicates a physical random access channel comb pattern for the UE to apply to a first portion of the uplink message, and wherein the control signaling further indicates that the UE is to refrain from including demodulation reference signals in at least the first portion of the uplink message based at least in part on the demodulation reference signal configuration, wherein refraining from including the demodulation reference signals in at least the first portion of the uplink message is associated with a channel estimation for a second portion of the uplink message; encoding the uplink message without the demodulation reference signals in at least the first portion of the uplink message in accordance with the demodulation reference signal configuration; and transmitting the uplink message based at least in part on encoding the uplink message.
2. The method of claim 1, wherein encoding the uplink message further comprises: encoding, using the Reed-Muller code, the uplink message without the demodulation reference signals included in the first portion in accordance with the demodulation reference signal configuration.
3. The method of claim 1, wherein the demodulation reference signal configuration comprises a field indicating that the UE is to refrain from including the demodulation reference signals in the first portion of the uplink message.
4. The method of claim 1, wherein the demodulation reference signal configuration comprises a field indicating the low-density parity-check code and the Reed-Muller code for the UE to use for encoding the uplink message, wherein the field is included in an uplink channel resource information element.
5. The method of claim 1, further comprising: selecting a physical random access channel preamble to include in the uplink message; and generating a scrambling identification associated with the UE based at least in part on the physical random access channel preamble, or based on radio resource control signaling indicating the scrambling identification, or both, wherein encoding the uplink message is based at least in part on the scrambling identification.
6. The method of claim 1, wherein receiving the demodulation reference signal configuration further comprises: receiving an indication of whether the UE is to include the demodulation reference signals in the second portion of the uplink message on a frequency bandwidth that is covered by a random access channel of the uplink message, wherein the random access channel is included in the first portion of the uplink message.
7. The method of claim 6, wherein receiving the indication further comprises: receiving a first configuration indicating for the UE to include one or more demodulated reference signals in each frequency resource of the frequency bandwidth covered by the random access channel; receiving a second configuration indicating for the UE to include the one or more demodulated reference signals in a subset of frequency resources of the frequency bandwidth covered by the random access channel; or receiving a third configuration indicating for the UE to refrain from including demodulated reference signals in the second portion of the uplink message.
8. The method of claim 1, wherein encoding the uplink message further comprises: encoding the uplink message without the demodulation reference signals in any portion of the uplink message in accordance with the demodulation reference signal configuration.
9. The method of claim 1, wherein encoding the uplink message further comprises: encoding the first portion of the uplink message in accordance with the physical random access channel comb pattern based at least in part on the demodulation reference signal configuration.
10. The method of claim 1, wherein encoding the uplink message further comprises: encoding the uplink message to include one or more demodulation reference signals in the second portion of the uplink message in accordance with the demodulation reference signal configuration.

11. The method of claim 10, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more demodulation reference signals at a start or at an end of the second portion in accordance with the demodulation reference signal configuration.
12. The method of claim 10, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more demodulation reference signals in a set of frequency resources without random access channel signals in accordance with the demodulation reference signal configuration.
13. The method of claim 10, wherein encoding the uplink message further comprises: encoding the second portion of the uplink message to include the one or more demodulation reference signals in a set of frequency resources that include random access channel signals in the first portion based at least in part on the demodulation reference signal configuration.
14. The method of claim 1, wherein the demodulation reference signal configuration is based at least in part on an amount of Doppler spread at the UE.
15. The method of claim 1, wherein transmitting the uplink message further comprises: transmitting a physical random access channel in a first set of frequency resources in the first portion of the uplink message in accordance with the demodulation reference signal configuration; and transmitting an uplink shared channel in a second set of frequency resources in the second portion of the uplink message in accordance with the demodulation reference signal configuration, wherein the first set of frequency resources and the second set of frequency resources comprise a same set of frequency resources or a subset of same frequency resources.
16. The method of claim 15, wherein the demodulation reference signal configuration is based at least in part on the first set of frequency resources including the second set of frequency resources.
17. The method of claim 15, wherein the demodulation reference signal configuration is based at least in part on the second set of frequency resources including the first set of frequency resources.
18. The method of claim 1, wherein receiving the control signaling further comprises: receiving a radio resource control message comprising the demodulation reference signal configuration for the uplink message.
19. A method for wireless communications at a network entity, comprising: transmitting control signaling indicating a demodulation reference signal configuration for an uplink message, wherein the demodulation reference signal configuration indicates a low-density parity-check code and a first Reed-Muller code for a user equipment (UE) to use for encoding the uplink message or the demodulation reference signal configuration indicates a physical random access channel comb pattern for the UE to apply to a first portion of the uplink message, and wherein the control signaling further indicates that the UE is to refrain from including demodulation reference signals in at least the first portion of the uplink message based at least in part on the demodulation reference signal configuration, wherein refraining from including the demodulation reference signals in at least the first portion of the uplink message is associated with a channel estimation for a second portion of the uplink message; receiving the uplink message without the demodulation reference signals in at least the first portion of the uplink message in accordance with the demodulation reference signal configuration; and decoding the uplink message based at least in part on the demodulation reference signal configuration.
20. The method of claim 19, further comprising: receiving a signal comprising a set of uplink messages from different UEs, wherein each uplink message of the set of uplink messages is associated with a respective Reed-Muller code.
21. The method of claim 20, wherein decoding the uplink message further comprises: decoding, using the first Reed-Muller code, the uplink message, wherein the uplink message is without the demodulation reference signals included in the first portion of the uplink message in accordance with the demodulation reference signal configuration; and canceling the decoded uplink message from the signal comprising the set of uplink messages in accordance with a multi-user decoding

algorithm.

22. The method of claim 19, wherein the demodulation reference signal configuration comprises a field indicating the low-density parity-check code and the first Reed-Muller code for the UE to use for encoding the uplink message, wherein the field is included in an uplink channel resource information element.

23. An apparatus for wireless communications at a user equipment (UE), comprising: one or more processors; memory coupled with the one or more processors; and instructions stored in the memory and executable by the one or more processors to cause the apparatus to: receive control signaling indicating a demodulation reference signal configuration for an uplink message, wherein the demodulation reference signal configuration indicates a low-density parity-check code and a Reed-Muller code for the UE to use for encoding the uplink message or the demodulation reference signal configuration indicates a physical random access channel comb pattern for the UE to apply to a first portion of the uplink message, and wherein the control signaling further indicates that the UE is to refrain from including demodulation reference signals in at least the first portion of the uplink message based at least in part on the demodulation reference signal configuration, wherein refraining from including the demodulation reference signals in at least the first portion of the uplink message is associated with a channel estimation for a second portion of the uplink message; encode the uplink message without the demodulation reference signals in at least the first portion of the uplink message in accordance with the demodulation reference signal configuration; and transmit the uplink message based at least in part on encoding the uplink message.

24. The apparatus of claim 23, wherein the instructions to encode the uplink message are further executable by the one or more processors to cause the apparatus to: encode, using the Reed-Muller code, the uplink message without the demodulation reference signals included in the first portion in accordance with the demodulation reference signal configuration.

25. The apparatus of claim 23, wherein the demodulation reference signal configuration comprises a field indicating that the UE is to refrain from including the demodulation reference signals in the first portion of the uplink message.

26. An apparatus for wireless communications at a network entity, comprising: one or more processors; memory coupled with the one or more processors; and instructions stored in the memory and executable by the one or more processors to cause the apparatus to: transmit control signaling indicating a demodulation reference signal configuration for an uplink message, wherein the demodulation reference signal configuration indicates a low-density parity-check code and a first Reed-Muller code for a user equipment (UE) to use for encoding the uplink message or the demodulation reference signal configuration indicates a physical random access channel comb pattern for the UE to apply to a first portion of the uplink message, and wherein the control signaling further indicates that the UE is to refrain from including demodulation reference signals in at least the first portion of the uplink message based at least in part on the demodulation reference signal configuration, wherein refraining from including the demodulation reference signals in at least the first portion of the uplink message is associated with a channel estimation for a second portion of the uplink message; receive the uplink message without the demodulation reference signals in at least the first portion of the uplink message in accordance with the demodulation reference signal configuration; and decode the uplink message based at least in part on the demodulation reference signal configuration.

27. The apparatus of claim 26, wherein the instructions are further executable by the one or more processors to cause the apparatus to: receive a signal comprising a set of uplink messages from different UEs, wherein each uplink message of the set of uplink messages is associated with a respective Reed-Muller code.

28. The apparatus of claim 27, wherein the instructions to decode the uplink message are further executable by the one or more processors to cause the apparatus to: decode, using the first Reed-Muller code, the uplink message, wherein the uplink message is without the demodulation

reference signals included in the first portion of the uplink message in accordance with the demodulation reference signal configuration; and cancel the decoded uplink message from the signal comprising the set of uplink messages in accordance with a multi-user decoding algorithm.

29. The apparatus of claim 26, wherein the demodulation reference signal configuration comprises a field indicating the low-density parity-check code and the first Reed-Muller code for the UE to use for encoding the uplink message, wherein the field is included in an uplink channel resource information element.
