



US012403776B2

(12) **United States Patent**
Ebisumoto et al.

(10) **Patent No.:** **US 12,403,776 B2**
(45) **Date of Patent:** **Sep. 2, 2025**

(54) **CONTROL DEVICE FOR ELECTRIC VEHICLE**

(56) **References Cited**

U.S. PATENT DOCUMENTS

(71) Applicant: **Mazda Motor Corporation**, Hiroshima (JP)

11,271,504 B2 3/2022 Itasaka et al.
2007/0037661 A1* 2/2007 Yang B60K 6/42
477/115
2008/0029361 A1* 2/2008 DeRoo B60W 10/02
192/48.8
2014/0277014 A1* 9/2014 Higgins A61B 17/320758
606/159

(72) Inventors: **Hirofumi Ebisumoto**, Aki-gun (JP);
Tomohiro Yoshizue, Aki-gun (JP);
Tsukasa Sori, Aki-gun (JP)

(73) Assignee: **Mazda Motor Corporation**, Hiroshima (JP)

FOREIGN PATENT DOCUMENTS

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 348 days.

JP 2021027615 A 2/2021

* cited by examiner

(21) Appl. No.: **18/188,728**

Primary Examiner — Edwin A Young

(22) Filed: **Mar. 23, 2023**

(74) *Attorney, Agent, or Firm* — Alleman Hall & Tuttle LLP

(65) **Prior Publication Data**

US 2023/0311672 A1 Oct. 5, 2023

(57) **ABSTRACT**

(30) **Foreign Application Priority Data**

Apr. 5, 2022 (JP) 2022-062954

(51) **Int. Cl.**

B60W 10/02 (2006.01)
B60L 15/20 (2006.01)
B60W 10/08 (2006.01)
B60W 30/18 (2012.01)
B60W 30/182 (2020.01)

(52) **U.S. Cl.**

CPC **B60L 15/2054** (2013.01); **B60W 10/02** (2013.01); **B60W 10/08** (2013.01); **B60W 30/18172** (2013.01); **B60W 30/182** (2013.01); **B60W 2720/26** (2013.01)


(58) **Field of Classification Search**


CPC ... B60L 15/2054; B60W 10/02; B60W 10/08;
B60W 30/18172; B60W 30/182; B60W
2720/26

See application file for complete search history.

A control device for an electric vehicle is provided, which includes a drive motor of which magnetic poles of a rotor are comprised of variable magnetism magnets, and a clutch disposed between the drive motor and driving wheels. When the electric vehicle travels, the control device performs a torque control, and a first clutch control in which an engaging torque of the clutch is controlled to be higher than a demanded torque. When performing a magnetization control when the electric vehicle travels, the control device changes the clutch control from the first clutch control to a second clutch control in which the engaging torque is made to coincide with the demanded torque, before the execution of the magnetization control, and adds a given slip torque to the demanded torque to start a micro slip control in which the clutch is transitioned from an engaged state into a micro slip state.

8 Claims, 13 Drawing Sheets








FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7





FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14

1

CONTROL DEVICE FOR ELECTRIC VEHICLE

TECHNICAL FIELD

The disclosed technique relates to a control device for an electric vehicle (including a hybrid vehicle) capable of traveling using electric power.

BACKGROUND OF THE DISCLOSURE

JP2021-027615A discloses a hybrid vehicle which carries a permanent magnet synchronous drive motor. This drive motor uses variable magnetism magnets, which can change the magnetism, for the permanent magnets which are installed in the rotor.

The output range of the drive motor is divided into a plurality of magnetization ranges, and an optimum magnetism value is set to each magnetization range. When the output of the drive motor shifts between these magnetization ranges, the magnetism of the variable magnetism magnet is changed to the optimum magnetism value for the transitional destination.

When changing the magnetism of the variable magnetism magnet, a large current for magnetization (so-called d-axis current) is applied to stator coils of the drive motor. Therefore, this interferes with a driving current (so-called q-axis current) for changing a torque. That is, the d-axis current is a component perpendicular to the q-axis current, which generates the torque. Therefore, although the large current itself will not be outputted as the torque, it interferes with the q-axis current for changing the torque.

If the change in the magnetism is a demagnetization (decrease in the magnetism), the torque changes to be lower, and if the change in the magnetism is a magnetization (increase in the magnetism), the torque changes to be higher. Therefore, when changing the magnetism of the variable magnetism magnet to magnetize, a high torque is outputted from the drive motor. Generally, since an engaging torque of a clutch provided between the drive motor and driving wheels is higher than a demanded torque, when the torque is transmitted to the driving wheels, a torque shock occurs on the traveling vehicle, and it may give uncomfortableness to a driver.

In order to suppress such a torque shock, a slip of the clutch installed between the drive motor and the driving wheels may be induced. That is, if the clutch is made to slip, even when the high torque is outputted from the drive motor, the torque transmitted to the driving wheels can be reduced, which can ease the torque shock.

However, when the clutch is made to slip, a phenomenon in which rotation of the drive motor increases rapidly (so-called "sudden speed rise") occurs. Such a phenomenon of the sudden speed rise may damage the clutch with frictional heat caused by the slip, if it is not eliminated promptly.

Thus, the present inventors proposed previously a technique for promptly eliminating the sudden speed rise of the drive motor accompanying such a slip of the clutch (JP2022-187694A).

According to this technique, roughly, when the slip of the clutch occurs by the magnetization, the control is changed from a torque control in which the output is controlled using the demanded torque as a target to a power control in which the output is controlled using the outputted power as a target. Therefore, the rotational speed can also be converged along

2

with the outputted torque, and the sudden speed rise of the drive motor can be eliminated promptly.

Problem of Friction Coefficient Difference of Clutch

Generally, a coefficient of dynamic friction (μ_d) of the clutch is set equivalent to a coefficient of static friction (μ_s). Therefore, even when the friction coefficient changes while engaging the clutch, the torque shock hardly occurs. Therefore, there is no problem also in the previously proposed technique.

However, depending on the clutch, the coefficient of dynamic friction may be lower than the coefficient of static friction, and the difference therebetween may be large. In such a case, also in the previously proposed technique, the torque shock which originates in the friction coefficient difference during engagement of the clutch may occur, and it may cause uncomfortableness for the driver.

SUMMARY OF THE DISCLOSURE

The disclosed technique suppresses a torque variation which occurs with a magnetism change in a drive motor, without being influenced by the performance of a clutch.

The disclosed technique relates to a control device for an electric vehicle including a drive motor of which magnetic poles of a rotor are comprised of variable magnetism magnets that are able to change magnetism, and a clutch disposed between the drive motor and driving wheels, the electric vehicle being travelable using electric power.

When the electric vehicle travels, the control device performs a torque control in which a motor torque outputted from the drive motor is controlled so that the motor torque coincides with a demanded torque demanded to be outputted to the driving wheels, and a first clutch control in which an engaging torque of the clutch is controlled to be higher than the demanded torque.

Further, when performing a magnetization control in which the magnetism of the variable magnetism magnet is changed to magnetize the variable magnetism magnet when the electric vehicle travels, the control device changes the clutch control from the first clutch control to a second clutch control in which the engaging torque is made to coincide with the demanded torque, before the execution of the magnetization control, and adds a given slip torque to the demanded torque based on a coefficient of dynamic friction and a coefficient of static friction of the clutch to start a micro slip control in which the clutch is transitioned from an engaged state into a micro slip state.

That is, according to this configuration, similarly to the previously proposed technique, when performing the magnetization control while the electric vehicle travels, the first clutch control is changed to the second clutch control in which the engaging torque is made to coincide with the demanded torque, before the execution of the magnetization control. Thus, the clutch slips, and the torque shock which originates in the magnetization can be suppressed.

Further, by adding the given slip torque to the demanded torque based on the coefficient of dynamic friction and the coefficient of static friction of the clutch, the micro slip control for transitioning the clutch from the engaged state to the micro slip state is started.

That is, the clutch is not transitioned from the engaged state to the disengaged state at the timing of the magnetization control when the rotational speed difference of the clutch increases rapidly, but before that, it is transitioned from the engaged state to the micro slip state by adding the given slip torque to the demanded torque. Therefore, since the friction coefficient can be changed beforehand from the

3

coefficient of static friction to the coefficient of dynamic friction under a condition of the small rotational speed difference, the torque shock which originates in the friction coefficient difference can be suppressed.

Therefore, according to this control device, the torque variation which occurs with the magnetism change of the drive motor can be suppressed, without being influenced by the performance of the clutch.

When the micro slip control is started, a transitional control may be performed. The transitional control may include adjusting a hydraulic pressure of the clutch so that a torque variation caused in connection with transitioning the clutch from the engaged state to the micro slip state is canceled out.

When the micro slip control is started, the clutch changes from the engaged state to the micro slip state. In connection with the change in the state of the clutch, the torque variation resulting from the friction coefficient difference of the clutch occurs, although it is smaller than at the timing of the magnetization control.

Unlike the outputted torque in the magnetization control which is irregular and is difficult to be identified beforehand, the slip torque which is increased or decreased in the micro slip control is set beforehand. Since the torque variation which occurs in connection with the change in the friction coefficient when the micro slip control is started is defined by the slip torque, an adjustment according to the torque variation can be performed, even if the control is the hydraulic control which is inferior in the response.

Therefore, by setting a condition of the hydraulic control which can cancel out the torque variation and adjusting the hydraulic pressure (pressing force) of the clutch based on the condition, the micro torque shock which occurs at the start of the micro slip control can also be suppressed.

During the execution of the micro slip control, a power control may be performed, instead of the torque control. The power control may include controlling the motor torque so that power outputted from the driving wheels coincides with a given target power value.

Unlike in the torque control in which the rotational speed is only made to follow the torque, according to the power control, both the rotational speed and the torque can be adjusted with sufficient balance. Thus, during the execution of the micro slip control, the state can be stably converged to the micro slip state by adjusting both the torque and the rotational speed of the drive motor with sufficient balance.

After the execution of the magnetization control, a feedback control may be performed based on a difference between a rotational speed on an input side of the clutch and a rotational speed on an output side to converge the state to the micro slip state during the execution of the power control.

Thus, the state can be quickly converged to the micro slip state.

When the micro slip control is ended, a transitional control may be performed. The transitional control may include adjusting the hydraulic pressure of the clutch so that a torque variation caused in connection with transitioning the clutch from the micro slip state to the engaged state is canceled out.

Thus, the micro torque shock which occurs when the micro slip control is ended can also be suppressed. As a result, the magnetism change of the drive motor in an almost shockless state becomes possible.

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 is a schematic view illustrating a main configuration of an automobile to which the disclosed technique is applied.

4

FIG. 2 is an outline cross-sectional view illustrating a configuration of a drive motor.

FIG. 3 is a block diagram illustrating a motor control unit (MCU) and primary input/output (I/O) devices relevant to the MCU.

FIG. 4 is a graph illustrating an output range of the drive motor.

FIG. 5 is a system chart related to a control of the drive motor illustrated in a simplified manner.

FIG. 6 is a flowchart illustrating one example of the control of the drive motor.

FIG. 7 is a flowchart illustrating a flow of main processing of a magnetism transitional control.

FIG. 8 is a chart illustrating a generation of a torque shock.

FIG. 9 is a block diagram illustrating a transmission control unit (TCU) and primary I/O devices relevant to the TCU.

FIG. 10 is a chart for illustrating a phenomenon of sudden speed rise.

FIG. 11 is a chart illustrating a problem of a friction coefficient difference of a transmission clutch.

FIG. 12 is a time chart of primary properties before and after a magnetization control to which the disclosed technique is applied.

FIG. 13 is a flowchart illustrating one example of a control corresponding to FIG. 12.

FIG. 14 is a flowchart continued from FIG. 13.

DETAILED DESCRIPTION OF THE DISCLOSURE

Hereinafter, the disclosed technique is described. However, the following description is only illustration essentially.

Electric Vehicle

FIG. 1 illustrates an automobile 1 (one example of an electric vehicle) to which the disclosed technique is applied. This automobile 1 is a hybrid vehicle capable of traveling by electric power. An engine 2 and a drive motor 3 are mounted as drive sources of the automobile 1. These collaborate with each other to drive, among four wheels 4F, 4F, 4R, and 4R, two wheels (driving wheels 4R) located in a left-right symmetry manner. Thus, the automobile 1 travels. Note that the automobile 1 may be an electric vehicle only carrying the drive motor 3. The automobile 1 may be a four-wheel-drive vehicle.

In this automobile 1, the engine 2 is disposed at the front side of the vehicle body, and the driving wheels 4R are disposed at the rear side of the vehicle body. That is, this automobile 1 is a so-called "front-engine, rear-wheel-drive (FR) vehicle." Further, in this automobile 1, the engine 2 mainly serves as a drive source, rather than the drive motor 3, and the drive motor 3 is used to assist the drive of the engine 2 (so-called "mild hybrid"). Further, the drive motor 3 is not only used as the drive source, but also used as a generator during regeneration.

The automobile 1 includes, in addition to the engine 2 and the drive motor 3, a relay clutch 5, an inverter 6, a transmission 8, a differential gear 9, and a battery 10, as devices in the drive system. The automobile 1 also includes, as devices in the control system, an engine control unit (ECU) 20, a motor control unit (MCU) 21, a transmission control unit (TCU) 22, a brake control unit (BCU) 23, and a general control unit (GCU) 24. An engine speed sensor 50, a motor rotation sensor 51, a current sensor 52, a magnetism sensor

53, an accelerator sensor **54**, and a transmission sensor **55** are installed in the automobile **1** along with the devices in the control system.

Devices in Drive System

The engine **2** is an internal combustion engine which combusts, for example, gasoline used as fuel. Further, the engine **2** is a so-called four-cycle engine which generates a rotational motive force by repeating a cycle of intake, compression, expansion, and exhaust. Although there are various kinds and modes of the engine **2**, such as a diesel engine, the kind or the mode of the engine is not limited in particular in this disclosed technique.

In this automobile **1**, the engine **2** is disposed in a substantially center part in the vehicle width direction so that an output shaft which outputs the rotational motive force is oriented in the front-and-rear direction of the vehicle body. Although various devices and mechanisms accompanying the engine **2**, such as an intake system, an exhaust system, and a fuel feed system, are installed in the automobile **1**, illustration and description thereof are omitted.

The drive motor **3** is disposed in series to the engine **2**, behind the engine **2** via the relay clutch **5**. The drive motor **3** is a permanent-magnet type synchronous motor which is driven by three-phase alternating current. As illustrated in FIG. **2** in a simplified manner, the drive motor **3** is roughly comprised of a motor case **31**, a shaft **32**, a rotor **33**, and a stator **34**.

The motor case **31** is comprised of a container having a cylindrical space therein, where a front end surface and a rear end face are closed, and is fixed to the vehicle body of the automobile **1**. The rotor **33** and the stator **34** are accommodated in the motor case **31**. The shaft **32** is rotatably supported by the motor case **31** in a state where a front end part and a rear end part project from the motor case **31**.

The relay clutch **5** is installed so that it intervenes between the front end part of the shaft **32** and the output shaft of the engine **2**. The relay clutch **5** is configured to be able to change between a state where the output shaft of the engine **2** is coupled to the shaft **32** (engaged state) and a state where the output shaft of the engine **2** is decoupled from the shaft **32** (disengaged state).

The rear end part of the shaft **32** is coupled to an input shaft **80** of the transmission **8**. Note that a second relay clutch may be provided between the shaft **32** and the input shaft **80** of the transmission **8**.

The rotor **33** is comprised of a cylindrical member configured by laminating a plurality of metal plates, each having a shaft hole at the center. The rotor **33** is integrated with the shaft **32** by fixing an intermediate part of the shaft **32** to the shaft hole of the rotor **33**.

A magnet **35** is installed throughout an outer circumferential part of the rotor **33**. The magnet **35** is configured so that different magnetic poles (i.e., S-pole and N-pole) are located alternately at equal intervals in the circumferential direction. The magnet **35** may be comprised of a sole cylindrical magnet having a plurality of magnetic poles, or may be comprised of a plurality of arc-shaped magnets, each constituting one of the magnetic poles.

Further, the drive motor **3** is configured so that the magnet **35** is able to change the magnitude of the magnetism (variable magnetism magnet **35**). Normally, for this kind of the drive motor **3**, a magnet (permanent magnet) in which a coercivity (coercive force) is large and the magnetism stays over a long period of time is used. In this drive motor **3**, a permanent magnet with a small coercivity is used as the variable magnetism magnet **35** so that the magnetism can be changed comparatively easily.

There are various kinds of permanent magnets, such as a ferrite magnet, a neodymium magnet, a samarium cobalt magnet, and an Alnico magnet, with different coercivities. The kind and the material of the variable magnetism magnet **35** may be selected according to specifications, and are not limited in particular.

The cylindrical stator **34** is installed around the rotor **33** with a small gap (inner rotor type). The stator **34** has a stator core **34a** comprised of a plurality of laminated metal plates, and a plurality of coils **36** configured by winding electric wires around the stator core **34a**.

The stator core **34a** is provided with a plurality of teeth **34b** which project radially inwardly, and the plurality of coils **36** are formed by winding the electric wires around the teeth **34b** in a given order. These coils **36** constitute three-phase coil groups of U-phase, V-phase, and W-phase.

In order to supply each phase of coil group, a connecting cable **36a** is drawn from each phase of coil group to the outside of the motor case **31**. These connecting cables **36a** are coupled to the battery **10** mounted on the vehicle as a driving power source via the inverter **6**. In this automobile **1**, the battery **10** is a direct-current battery below 50V (in detail, 48V) in the rated voltage.

The battery **10** supplies direct current power to the inverter **6**. The inverter **6** converts the direct current power into three-phase alternating current, and supplies the current to the drive motor **3**. Therefore, the rotor **33** rotates, and the power (rotational motive force) of the drive motor **3** is outputted to the transmission **8** via the shaft **32**.

In this automobile **1**, the transmission **8** is a multi-stage automatic transmission (so-called "AT"). As illustrated in FIG. **1**, the transmission **8** has the input shaft **80** at one end thereof, and the input shaft **80** is coupled to the drive motor **3** (shaft **32**). The other end of the transmission **8** has an output shaft **81** which rotates independently from the input shaft **80**. Between the input shaft **80** and the output shaft **81**, a transmission mechanism comprised of a torque converter **84**, a plurality of planetary gear mechanisms **82**, and a plurality of transmission clutches **83** (including brake(s)) is incorporated.

By switching the transmission mechanism, a change in the gear ratio, such as a change between traveling forward and rearward (reverse), a change into a different rotational speed between the input shaft **80** and the output shaft **81** of the transmission **8**.

For example, an input side **83a** of each transmission clutch **83** can be coupled to the input shaft **80** via the torque converter **84**. An output side **83b** of each transmission clutch **83** is coupled to the output shaft **81** via the corresponding planetary gear mechanism **82**. When a specific transmission clutch **83** is selected and this transmission clutch **83** is engaged, the input shaft **80** of the transmission **8** is coupled to the output shaft **81** via the transmission clutch **83** and the corresponding planetary gear mechanism **82**. Therefore, the gear ratio is changed.

The output shaft **81** is coupled to the differential gear **9** via a propeller shaft **11** which extends in the front-and-rear direction of the vehicle body and is disposed coaxially with the output shaft **81**. The differential gear **9** is coupled to a pair of driving shafts **13** which extend in the vehicle width direction and are coupled to the left and right driving wheels **4R**. The rotational motive force outputted through the propeller shaft **11** is divided by the differential gear **9**, and is transmitted to the driving wheels **4R** through the pair of driving shafts **13**, respectively. A brake **14** is attached to each of the wheels **4F** and **4R** in order to brake the rotation.

Devices in Control System

In the automobile 1, the modules, such as the ECU 20, the MCU 21, the TCU 22, the BCU 23, and the GCU 24, which are described above, are installed in order to control the traveling of the automobile 1 according to driver's operation. Each of these modules is comprised of hardware, such as a processor, memory, and an interface, and software, such as a database and a control program. These modules are connected with each other, for example, via a CAN (Controller Area Network), and are configured to be telecommunicatable with each other.

The ECU 20 is a module which mainly controls operation of the engine 2. The MCU 21 is a module which mainly controls operation of the drive motor 3. The TCU 22 is a module which mainly controls operation of the transmission 8. The BCU 23 is a module which mainly controls operation of the brake 14. The GCU 24 is a high-order or host module which is electrically connected to the ECU 20, the MCU 21, the TCU 22, and the BCU 23, and comprehensively controls these modules.

One example of the control device in the disclosed technique is control device 100 (see FIG. 1) comprised of these modules. Particularly, the MCU 21 which mainly controls the operation of the drive motor 3 and the TCU 22 which mainly controls the operation of the transmission 8 mainly constitute the control device 100. By these modules collaborating with each other, a micro slip control which will be described later is performed.

The engine speed sensor 50 is attached to the engine 2, detects an engine speed of the engine 2, and outputs it to the ECU 20. The motor rotation sensor 51 is attached to the drive motor 3, detects a rotational speed and a rotational position of the drive motor 3, and outputs them to the MCU 21. The current sensor 52 is attached to the connecting cable 36a, detects a value of current which is supplied to each coil 36, and outputs it to the MCU 21.

The magnetism sensor 53 is attached to the drive motor 3, detects a magnetism of the variable magnetism magnet 35, and outputs it to the MCU 21. The accelerator sensor 54 is attached to an accelerator pedal (accelerator 15) which is stepped on by the driver when driving the automobile 1, detects an accelerator opening corresponding to the output demanded for driving the automobile 1, and outputs it to the ECU 20. The transmission sensor 55 detects a rotational speed and an engaging torque of each transmission clutch 83, a rotational speed of the output shaft 81, etc., and outputs them to the TCU 22.

By the modules collaborating and controlling the devices in the drive system based on signals of the detection values inputted from these sensors, the automobile 1 travels. For example, when the automobile 1 travels with the driving force of the engine 2, the ECU 20 controls the operation of the engine 2 based on the detection values of the accelerator sensor 54 and the engine speed sensor 50.

Further, the TCU 22 controls so that the relay clutch 5 becomes in an engaged state, and changes the transmission mechanism of the transmission 8 according to the operating state of the automobile 1. During braking of the automobile 1, the BCU 23 controls each brake 14. During braking with regeneration, the TCU 22 controls the relay clutch 5 to be in a disengaged state or a partially engaged state, and engages a given transmission clutch 83 of the transmission 8. Thus, the MCU 21 generates power with the drive motor 3, and it controls so that the electric power is collected by the battery 10.

Control of Drive Motor

The MCU 21 controls so that the automobile 1 travels while using the power outputted from the drive motor 3 in a state where the drive motor 3 solely outputs the power, or in a state where the drive motor 3 assists the output of the engine 2 as needed.

In detail, the ECU 20 sets the torque outputted from the engine 2 based on the detection values of the accelerator sensor 54, the engine speed sensor 50, etc. Accordingly, the GCU 24 sets a demanded amount of torque to the drive motor 3 (demanded torque) within a given output range according to a preset distribution ratio of the output between the engine 2 and the drive motor 3. The MCU 21 controls the drive motor 3 so that the demanded torque is outputted.

FIG. 3 illustrates the MCU 21 and primary input/output (I/O) devices relevant to the MCU 21. The MCU 21 is provided with a motor output controller 21a and a magnetization controller 21b, which are comprised of hardware and software, as functional configurations. The motor output controller 21a has a function for controlling the drive of the drive motor 3, and makes the drive motor 3 output the demanded power by controlling driving current which flows into the coils 36.

On the other hand, the magnetization controller 21b has a function for raising a power factor of the drive motor 3, and converts the magnetism of the variable magnetism magnet 35 by controlling magnetizing current which flows into the coils 36. In detail, the magnetism of the variable magnetism magnet 35 is changed so that it may substantially coincide with an electromagnetic force which is caused in the coils 36 by the driving current.

The power factor is a ratio of available power (electric power actually consumed) to apparent power (electric power supplied to the drive motor 3). If the power factor is low, it becomes necessary to supply large current to obtain the same output. Thus, the motor needs to be enlarged. Therefore, by raising the power factor of the drive motor 3, the drive motor 3 can be reduced in the weight and the size. Further, as the power factor increases, the generating capacity during regeneration also increases.

Output Range of Drive Motor

FIG. 4 illustrates the output range of the drive motor 3. The output range is defined by a maximum load line indicative of an upper limit of the torque (load) according to the rotational speed.

In detail, the upper limit of the torque is held at a maximum torque (T2) in a low-speed range up to a given rotational speed (r1). In a middle-speed range and a high-speed range where the rotational speed is higher than in the low-speed range, the upper limit of the torque is gradually decreased until the rotational speed reaches an upper limit (r2).

In the MCU 21, data, such as a map and a table, which defines such an output range is set beforehand. The motor output controller 21a controls the drive motor 3 in its output range by looking up the data.

Further, this output range of the drive motor 3 is divided into a plurality of magnetization ranges. The magnetization controller 21b changes the magnetism of the variable magnetism magnet 35 according to each magnetization range.

As illustrated in FIG. 4, in this embodiment, the output range of the drive motor 3 is divided into four magnetization ranges (first to fourth magnetization ranges). In detail, it is divided into a first magnetization range Rm1 which eccentrically resides on the low-speed side, and which is high in the load, including the maximum torque T2, a second magnetization range Rm2 which extends from the low-speed

side to the high-speed side, which is lower in the load than the first magnetization range **Rm1**, and which has a torque peak in the middle speed, a third magnetization range **Rm3** which is lower in the load than the second magnetization range **Rm2**, and of which the torque peak shifts to the higher-speed side than in the second magnetization range **Rm2**, and a fourth magnetization range **Rm4** which is lower in the load than the third magnetization range **Rm3**, and which includes a torque **T1** at which the drive motor **3** idles (a torque which does not contribute to the traveling of the automobile **1**).

An optimal magnetism value (optimum magnetism value) for achieving the high power factor is set to each of the magnetization ranges, corresponding to each output. For example, in the first magnetization range **Rm1**, an initial magnetism of the variable magnetism magnet **35** is set as the optimum magnetism value (first optimum magnetism value). In the second magnetization range **Rm2**, a lower optimum magnetism value than the first optimum magnetism value is set (second optimum magnetism value). Further, in the third magnetization range **Rm3**, a third optimum magnetism value lower than the second optimum magnetism value is set, and in the fourth magnetization range **Rm4**, a fourth optimum magnetism value lower than the third optimum magnetism value is set.

The magnetization controller **21b** estimates the optimal magnetization range based on the operating state of the automobile **1**, and when the magnetization range shifts to another, adjacent magnetization range, it changes the magnetism of the variable magnetism magnet **35** to the optimum magnetism value corresponding to the magnetization range. For example, when shifting from the first magnetization range **Rm1** to the second magnetization range **Rm2**, demagnetization processing is performed in the drive motor **3** so that the magnetism of the variable magnetism magnet **35** is changed from the first optimum magnetism value to the second optimum magnetism value.

Moreover, for example, when shifting from the third magnetization range **Rm3** to the second magnetization range **Rm2**, magnetization processing is performed in the drive motor **3** so that the magnetism of the variable magnetism magnet **35** is changed from the third optimum magnetism value to the second optimum magnetism value.

Concrete Example of Control of Drive Motor

FIG. 5 illustrates a simplified system chart related to the control of the drive motor **3**. FIG. 6 illustrates one example of the control of the drive motor **3** performed by the MCU **21**. A flow of the concrete control of the drive motor **3** is described with reference to these drawings. Note that the drive motor **3** is controlled by a vector control which uses a torque current command I_q^* and an exciting current command I_d^* .

When the automobile **1** becomes in a travelable state, the detection values are always inputted from the current sensor **52**, the motor rotation sensor **51**, and the magnetism sensor **53** into the MCU **21** (Step **S1**). Further, the detection values are always inputted from the accelerator sensor **54** and the engine speed sensor **50** similarly into the ECU **20**.

The GCU **24** acquires the detection value of the accelerator sensor **54** from the ECU **20**, and sets a torque which is requested to the drive motor **3** (demanded torque) among the torques to be outputted to the driving wheels **4R** according to the preset distribution ratio of the output between the engine **2** and the drive motor **3**. The GCU **24** outputs a command for outputting the demanded torque (torque command value T^*) to the MCU **21**.

That is, the MCU **21** controls the output of the drive motor **3** based on a given target torque (so-called "torque control"). By the torque control, the torque outputted from the drive motor **3** (motor torque) is controlled to coincide with the target torque. Therefore, when the command described above is inputted while the automobile **1** travels, the MCU **21** controls the drive motor **3** by using the demanded torque as the target torque. By the torque control of the drive motor **3**, the automobile **1** travels according to the driver's demand.

As described above, while the automobile **1** travels, the torque control is interrupted when the magnetization range shifts, and a control for applying a high voltage to the coils **36** of the drive motor **3** is performed (magnetism transitional control). By the magnetism transitional control, the magnetism of the variable magnetism magnet **35** is changed.

In detail, when the torque command value T^* is inputted (Yes at Step **S2**), the MCU **21** (motor output controller **21a**) performs computational processing of a command (driving current command value I_{dq}^*) which outputs an amount of change in the driving current (torque current component) which causes the torque (Step **S3**). Further, the MCU **21** (magnetization controller **21b**) performs computational processing of a command (magnetized state command value Φ^*) which outputs an optimum magnetism value corresponding to the suitable magnetization range (Step **S4**). The magnetization controller **21b** performs computational processing of a command (magnetism current command value I_{dq}^*) which outputs a torque current component equivalent to an amount of change in the magnetism of the variable magnetism magnet **35** based on the magnetized state command value Φ^* (Step **S5**).

The MCU **21** determines whether the magnetism of the variable magnetism magnet **35** needs to be changed, based on the driving current command value I_{dq}^* and the magnetism current command value I_{dq}^* which are calculated (Step **S6**). For example, as described above, if the demanded torque is outputted, it is determined that the magnetism of the variable magnetism magnet **35** needs to be changed, when the magnetization range shifts to another magnetization range, and even if the demanded torque is outputted, when the magnetization range stays the same, it is determined that the change in the magnetism of the variable magnetism magnet **35** is not necessary.

Then, if the MCU **21** determines that the change in the magnetism of the variable magnetism magnet **35** is not necessary, it determines whether the output torque is larger than the torque **T1** when the drive motor **3** idles (Step **S7**). Then, if the output torque is larger than the torque **T1**, the MCU **21** controls the drive motor **3** by the normal vector control.

That is, the motor output controller **21a** performs, by a current control, computational processing of a command (voltage command value V_{uvw}^*) which is outputted for performing a pulse width modulation (PWM) control, based on the detection values of the current sensor **52** and the motor rotation sensor **51** (Step **S8**). Then, a switching command value is calculated by the PWM control (Step **S9**).

By the switching command value being outputted to the inverter **6** through the driver circuit, a plurality of switching elements are on-off controlled inside the inverter **6**. Therefore, the given three-phase alternating current (driving current) is supplied to each coil group so that the drive motor **3** rotates with the demanded torque (Step **S10**).

On the other hand, if the MCU **21** determines that the magnetism of the variable magnetism magnet **35** needs to be changed (No at Step **S6**), the magnetization controller **21b** performs the magnetism transitional control (Step **S11**).

11

Further, even if the MCU 21 determines that the change in the magnetism of the variable magnetism magnet 35 is not necessary, if it is determined that the output torque is less than the torque T1 at which the drive motor 3 idles (No at Step S7), the magnetization controller 21b performs the magnetism transitional control (Step S11).

That is, when the demanded amount of the rotational motive force of the drive motor 3 becomes almost 0 (zero), the variable magnetism magnet 35 is reset so that the magnetism is changed to the initial state. For example, the automobile 1 may accelerate rapidly from the idle state or the stopped state when the accelerator 15 being depressed instantaneously.

Since the initial magnetism is set highly in the variable magnetism magnet 35 according to the high load, the drive motor 3 can be driven appropriately by resetting the magnetism at idle, even when such a rapid acceleration is performed.

FIG. 7 illustrates a flow of main processing of the magnetism transitional control. If the magnetism transitional control is requested, the magnetization controller 21b determines a direction of the magnetization processing based on the magnetized state command value Φ^* . That is, it determines whether processing for increasing the magnetism of the variable magnetism magnet 35 (magnetization processing) is to be performed, or processing for decreasing the magnetism of the variable magnetism magnet 35 (demagnetization processing) is to be performed. Further, the magnetization controller 21b identifies an amount of change in the magnetism to increase or decrease.

Then, the magnetization controller 21b determines whether the position of the rotor 33 with respect to the stator 34 (a position in the rotational direction) is located at a position suitable for the magnetization processing based on the detection value of the motor rotation sensor 51 (Step S21), and if the rotor 33 is located at the suitable position, it outputs the magnetizing current (Step S22). The magnetizing current is pulse-shaped current which generates an electromagnetic force larger than the coercivity of the variable magnetism magnet 35. The direction of the magnetic flux line of the electromagnetic force is opposite between the magnetization processing and the demagnetization processing.

The magnetization controller 21b determines whether the magnetism of the variable magnetism magnet 35 is substantially the same as the optimum magnetism value specified by the magnetized state command value Φ^* (Step S23), and it performs the magnetization processing until the magnetism of the variable magnetism magnet 35 becomes substantially the same as the optimum magnetism value. When resetting the magnetism of the variable magnetism magnet 35, the magnetization processing is performed until the magnetism becomes substantially the same as the initial magnetism.

Then, when the magnetism of the variable magnetism magnet 35 becomes substantially the same as the optimum magnetism value or the initial magnetism, it ends the magnetism transitional control, and as illustrated in FIG. 6, it controls the drive motor 3 by the normal vector control (Steps S8 to S10).

Slip of Clutch

As described above, in this automobile 1, the magnetism transitional control is performed also while the automobile 1 travels. While the automobile 1 is traveling, if the magnetism transitional control to magnetize (magnetization control) is performed, a torque shock may occur in the traveling automobile 1 so that it may give uncomfortableness to the driver.

12

The upper figure of FIG. 8 illustrates a chronological change in a motor torque T_m during the magnetization control. In this illustration, the magnetization processing is performed during a period from time t1 to time t1'. Further, a period from t1' to t2 is a period in which the change in the magnetism is confirmed, and a control (learning control) for learning so that the driving current value (q-axis current value) corresponds to the increased magnetism is performed to make the motor torque T_m coincide with the demanded torque. The learning control is a control accompanying the magnetization and is included in the magnetization control. T_a is the demanded torque. During the traveling of the automobile 1, since the drive motor 3 is torque controlled, the motor torque T_m before the execution of the magnetization control coincides with the demanded torque T_a .

Tt is a clutch engaging torque in the transmission 8. The clutch engaging torque Tt is an engaging torque of the transmission clutch 83 which couples the input shaft 80 of the transmission 8 to the output shaft 81, and is equivalent to a torque which the transmission clutch 83 can transmit to the output side 83b. In order to certainly transmit the motor torque T_m to the driving wheels 4R, the clutch engaging torque Tt is normally controlled so that it is higher than the demanded torque T_a (first clutch control).

During the magnetization control, in order to generate a large electromagnetic force, magnetizing current (d-axis current) is supplied to the coils 36. Therefore, a high voltage greatly exceeding the driving voltage is applied to the drive motor 3. Therefore, as illustrated in the upper figure of FIG. 8, during the magnetization control, a peak-shaped high motor torque T_m greatly exceeding the demanded torque T_a is outputted from the drive motor 3. As a result, the torque shock occurs in the traveling automobile 1 so that it may give uncomfortableness to the driver.

Thus, in order to suppress such a torque shock, in this automobile 1, the MCU 21 collaborates with the TCU 22 to make the transmission clutch 83 slip during the magnetization control (including the accompanying learning control). In detail, it controls so that the clutch engaging torque Tt coincides with the demanded torque T_a (second clutch control).

FIG. 9 illustrates the TCU 22 and primary I/O devices relevant to the TCU 22. The TCU 22 is provided with a relay clutch controller 22a and a transmission clutch controller 22b by hardware and software, as functional configurations. The relay clutch controller 22a controls operation of the relay clutch 5. The transmission clutch controller 22b controls operation of each of the transmission clutches 83. The transmission clutch controller 22b performs the first clutch control and the second clutch control.

When information on the execution of the magnetism transitional control is acquired from the GCU 24, the transmission clutch controller 22b controls the operation of the transmission clutch 83 in use. In detail, as illustrated in the lower figure of FIG. 8, the transmission clutch controller 22b changes the clutch control from the first clutch control to the second clutch control immediately before (time t0) the start (time t1) of the magnetization control. Therefore, it reduces the clutch engaging torque Tt. As a result, the transmission clutch 83 slips.

At this time, the clutch engaging torque Tt is controlled so that it coincides with the demanded torque. By performing the second clutch control, the torque exceeding the demanded torque can be prevented from being transmitted to the driving wheels 4R, even if the high motor torque T_m is outputted from the drive motor 3. As a result, the torque shock resulting from the magnetization can be suppressed.

Problems in Second Clutch Control and its Solution

When the transmission clutch **83** is made to slip, the phenomenon in which the rotation of the drive motor **3** increases rapidly occurs (so-called "sudden speed rise").

FIG. **10** illustrates a relationship between the motor torque T_m and a motor rotational speed R_m during the magnetization control. Note that, here, since the output of the engine **2** is not taken into consideration, the motor rotational speed R_m is also the rotational speed of the input shaft **80** of the transmission **8**. Further, the motor torque T_m is equivalent to the torque inputted into the transmission **8** (torque on the input side **83a** of the transmission clutch **83**: transmission input torque). Since the clutch engaging torque T_t is controlled so that it coincides with the demanded torque, it is equivalent to the torque outputted from the transmission **8** (torque on the output side **83b** of the transmission clutch **83**: transmission output torque).

The drive motor **3** before the execution of the magnetization control rotates at a given rotational speed R_a . Further, at this time, since the transmission clutch **83** in use is engaged, both the input side **83a** and the output side **83b** of the transmission clutch **83** also rotate at the rotational speed R_a . Note that the output shaft **81** of the transmission **8** rotates at a rotational speed which is reduced by the planetary gear mechanism **82** corresponding to the transmission clutch **83**.

As illustrated in FIG. **10**, when the transmission clutch **83** is made to slip during the magnetization control, since the drive motor **3** becomes in the idle state, the motor rotational speed R_m increases instantaneously from the rotational speed R_a corresponding to the demanded torque T_a . The motor rotational speed R_m further increases also during the learning control, and remains high. This sudden speed rise phenomenon may damage the transmission clutch **83** by frictional heat caused by the slip, unless it is eliminated promptly.

Further, in the torque control, the motor torque T_m is controlled so as to coincide with the target torque (demanded torque T_a) according to the current rotational speed. Therefore, after the rotational speed increases according to the sudden speed rise phenomenon, the rotational speed is maintained. That is, the sudden speed rise phenomenon cannot be eliminated by the conventional torque control alone.

In order to promptly eliminate the sudden speed rise phenomenon, the clutch engaging torque T_t which has been coincided with the demanded torque T_a may be increased immediately after the magnetization control. Since the slip decreases, the motor rotational speed R_m decreases so that the sudden speed rise phenomenon can be eliminated. However, accordingly, since the high motor torque T_m is transmitted to the driving wheels **4R** as a reaction, the torque shock occurs.

Another measure for promptly eliminating the sudden speed rise phenomenon is to make the target torque in the torque control smaller than the demanded torque T_a , so that the motor torque T_m itself becomes smaller, immediately after the magnetization control. Thus, since the motor rotational speed R_m decreases, the sudden speed rise phenomenon can be eliminated.

However, accordingly, the motor rotational speed R_m may decrease to be lower than the initial rotational speed R_a . In that case, after the sudden speed rise phenomenon is eliminated, the motor rotational speed R_m will not be resumed to the initial state, even if the motor torque T_m is resumed to the demanded torque by the torque control. Because of the shortage of the power of the drive motor **3**, uncomfortableness may be given to the driver.

Thus, the previously proposed technique is devised so that, after the magnetization control, the power control for controlling the motor torque T_m is performed based on the power outputted from the drive motor **3** to promptly converge the torque and the rotational speed outputted from the drive motor **3**. However, it was found that this technique may cause the torque shock depending on the performance of the transmission clutch **83** to give uncomfortableness to the driver, and therefore, there is room for improvement.

Problem of Friction Coefficient Difference of Transmission Clutch

Generally, the coefficient of dynamic friction (μ_d) of the transmission clutch **83** is set equivalent to the coefficient of static friction (μ_s).

When engaging the transmission clutch **83**, the friction coefficient is changed from the coefficient of dynamic friction to the coefficient of static friction. If the coefficient of dynamic friction is equivalent to the coefficient of static friction, the torque shock which gives uncomfortableness to the driver during the engagement of the transmission clutch **83** accompanying the magnetization control will not occur. Therefore, there is no problem also in the previously proposed technique.

However, depending on the transmission clutch **83**, the coefficient of dynamic friction may be lower than the coefficient of static friction, and the difference may be large. In such a case, also in the previously proposed technique, the torque shock may occur during the engagement of the transmission clutch **83** accompanying the magnetization control so that it may give uncomfortableness to the driver.

This will be described concretely with reference to FIG. **11**. The lower figure of FIG. **11** illustrates a chronological change in the rotational speed difference between the input side **83a** and the output side **83b** of the transmission clutch **83**, and the magnetization control is initiated at t_1 . When there is a difference between the coefficient of dynamic friction and the coefficient of static friction of the transmission clutch **83**, the torque control may be a control suited to the coefficient of dynamic friction (μ_d -suited control) and a control suited to the coefficient of static friction (μ_s -suited control).

The upper figure of FIG. **11** illustrates the μ_d -suited control. The middle figure of FIG. **11** illustrates the μ_s -suited control. In these figures, broken lines correspond to the transmission input torque T_m , and solid lines correspond to the transmission output torque T_t . In the μ_d -suited control, since it is controlled based on the coefficient of dynamic friction (μ_d), the target transmission input torque T_m becomes a value obtained by multiplying a hydraulic pressure (pressing force) which acts on the transmission clutch **83** by the coefficient of dynamic friction. On the other hand, in the μ_s -suited control, since it is controlled based on the coefficient of static friction (μ_s), the target transmission input torque T_m becomes a value obtained by multiplying the hydraulic pressure (pressing force) which acts on the transmission clutch **83** by the coefficient of static friction.

In the μ_d -suited control, when the transmission clutch **83** begins to slip with the start of the magnetization control, the transmission output torque T_t also increases up to its upper limit with the increase in the rotational speed difference (the value obtained by multiplying the pressing force by the coefficient of static friction). When a change in the transmission output torque T_t (dashing-out shock) exceeds the human perception level, it may give uncomfortableness to the driver.

Further, in the μ_s -suited control, when the transmission clutch **83** begins to slip with the start of the magnetization

15

control, the transmission output torque T_t decreases to the value obtained by multiplying the pressing force by the coefficient of dynamic friction, in association with the change in the friction coefficient. This state is held until the magnetization control is finished and the transmission clutch **83** is again engaged. When the change in the transmission output torque T_t during this period (drawing-in shock) exceeds the human perception level, it may give uncomfortableness to the driver.

In either control, when the difference between the coefficient of static friction and the coefficient of dynamic friction of the transmission clutch **83** is large, the torque shock which originates in the friction coefficient difference occurs with the magnetization control so that it may give uncomfortableness to the driver.

The torque shock may be suppressed by adjusting the pressing force of the transmission clutch **83** during engagement by the hydraulic control. However, the hydraulic control is slow in the response, and it cannot react quickly. It is not easy to stably suppress the torque shock accompanying the irregular magnetization control with the slow-response hydraulic control.

Thus, this control device **100** is devised so that the change in the magnetism of the drive motor (in detail, the intolerable torque variation which may occur with the magnetization control) can be suppressed by the control of the transmission clutch **83**.

In detail, similarly to the previously proposed technique, the first clutch control is performed along with the torque control while the automobile **1** travels. Then, when performing the magnetization control while the automobile **1** travels, the first clutch control is changed to the second clutch control before the execution of the magnetization control. That is, by making the transmission clutch **83** slip, the torque shock which originates in the magnetization is suppressed.

In this control device **100**, a given slip torque is added to the demanded torque based on the coefficient of dynamic friction and the coefficient of static friction of the transmission clutch **83** to set a new demanded torque (slight-increase demanded torque). Then, along with the change to the second clutch control (i.e., before the execution of the magnetization control), a control (micro slip control) for making the transmission clutch **83** from the engaged state to a micro slip state based on the slight-increase demanded torque is started.

That is, the transmission clutch **83** is not changed from the engaged state to the disengaged state at the timing where the rotational speed difference of the transmission clutch **83** increases rapidly (when the magnetization is started), but, before that, it is changed to the state where the transmission clutch **83** slips slightly (micro slip state). Therefore, since the friction coefficient can be changed beforehand from the coefficient of static friction to the coefficient of dynamic friction under the condition of the small rotational speed difference, the torque shock which originates in the friction coefficient difference can be suppressed.

In the micro slip state, the transmission clutch **83** is not fully engaged, but the friction coefficient is changed from the coefficient of static friction to the coefficient of dynamic friction. By the change to the second clutch control, the clutch engaging torque coincides with the demanded torque. Therefore, the slip torque which is added to the demanded torque may be any torque as long as it is necessary and sufficient for producing the micro slip state.

During the execution of the micro slip control, it is preferred to perform the power control, instead of the torque control. Further, it is more preferred to perform, after the

16

execution of the magnetization control, a feedback control based on the difference between the rotational speed on the input side **83a** of the transmission clutch **83** and the rotational speed on the output side **83b** to converge the state to the micro slip state during the execution of the power control.

Thus, along with the torque outputted from the drive motor **3**, its rotational speed can also be adjusted with sufficient balance so that the sudden speed rise phenomenon is eliminated promptly. Therefore, the drive motor **3** can be resumed to its initial state in a short period of time after the magnetization.

Power Control and Feedback Control Accompanying Micro Slip Control

In the power control, the torque is controlled so that the power outputted from the driving wheels **4R** (i.e., the multiplication value of a torque T and a rotational speed R of the driving wheels **4R**) may become a given target power value.

That is, in the power control, the torque control in which not the demanded torque T_a but the motor torque T_m corresponding to the target power value is used as the target torque is performed. If the target power value is constant, when the motor rotational speed R_m is high like at the peak of the sudden speed rise phenomenon, the target torque becomes lower accordingly, and the sudden speed rise phenomenon becomes weaker, and when the motor rotational speed R_m becomes lower, the target torque becomes higher. Therefore, according to the power control, unlike in the torque control, both the rotational speed and the torque can be adjusted with sufficient balance.

Here, the target power value is a value at which the transmission clutch **83** becomes in the micro slip state. Thus, during the execution of the micro slip control, the state can be stably converged to the micro slip state by adjusting both the torque and the rotational speed of the drive motor **3** with sufficient balance.

In detail, here, the target power value is a value obtained by multiplying the slight-increase demanded torque by the rotational speed. For example, the target power value can be set by multiplying a value, which is obtained by multiplying the demanded torque T_a by an actual rotational speed of the drive motor **3**, by a given slip ratio (for example, 105%).

The target power value is a value obtained by multiplying the demanded torque T_a by the actual rotational speed and the given slip ratio. Thus, the power control is a supplemental control of the torque control, and is compatible to the torque control. Therefore, these controls can be changed to each other smoothly and easily, and are excellent in the control stability.

After the execution of the magnetization control, the motor torque T_m decreases by the power control, and the motor rotational speed R_m also decreases. However, here, the motor rotational speed R_m changes passively according to the change in the torque. Thus, the motor rotational speed R_m decreases gently. Accordingly, it requires a comparatively long period of time until the motor rotational speed R_m converges to the rotational speed in the micro slip state (micro-slip rotational speed).

Therefore, after the execution of the magnetization control, the feedback control is performed based on the difference between the rotational speed on the input side **83a** of the transmission clutch **83** in use and the rotational speed on the output side **83b** (rotational speed difference) to converge the state to the micro slip state during the execution of the power control.

When the feedback control is started, a gain adjustment of the torque control is performed according to the rotational speed difference so that the state becomes the micro slip state promptly. Therefore, the transmission clutch **83** can be converged to the initial micro slip state promptly.

Transitional Control

Further, when the micro slip control is started and/or ended, it is preferred to perform a cooperative control utilizing a hydraulic control. In detail, a control for adjusting the hydraulic pressure of the transmission clutch **83** (transitional control) is performed, together with the adjustment of the torque, so that the torque variation (torque shock) which occurs in connection with the change in the state of the transmission clutch **83** before and after the micro slip control may be canceled out.

For example, when the micro slip control is started, the transmission clutch **83** changes from the engaged state to the micro slip state. When the micro slip control is ended, the transmission clutch **83** changes from the micro slip state to the engaged state. In connection with the change in the state of the transmission clutch **83**, the torque variation resulting from the friction coefficient difference of the transmission clutch **83** occurs.

Unlike the outputted torque in the magnetization control which is irregular and is difficult to be identified beforehand, the slip torque which is increased or decreased in the micro slip control is a value set beforehand. Since the torque variation which occurs in connection with the change in the friction coefficient when the micro slip control is started or ended is defined by the slip torque, an adjustment according to the torque variation can be performed, even if the control is the hydraulic control which is inferior in the response.

For example, a condition of the hydraulic control which can cancel out the torque variation accompanying the change in the slip torque is set by a preliminary examination, etc., and the hydraulic pressure (pressing force) of the transmission clutch **83** is adjusted based on the condition. Thus, the micro torque shock resulting from the friction coefficient difference which occurs in connection with the micro slip control can also be suppressed. As a result, the magnetism change of the drive motor **3** in the almost shockless state becomes possible.

Concrete Example of Control

FIGS. **12** to **14** illustrate a concrete example of the micro slip control. FIG. **12** is a time chart of primary properties before and after the magnetization control. FIGS. **13** and **14** are flowcharts of the control corresponding to FIG. **12** which is performed by the control device **100**.

In FIG. **12**, the upper chart is a time chart related to the torque. A solid line indicates the transmission input torque (motor torque T_m), and a broken line indicates the transmission output torque.

The middle chart is a time chart related to the hydraulic pressure of the transmission **8** (the pressing force of the transmission clutch **83**). The lower chart is a time chart related to the rotational speed difference. It indicates the difference between the rotational speed on the input side **83a** of the transmission clutch **83** in use, and the rotational speed on the output side **83b**.

As illustrated in FIG. **13**, the MCU **21** determines whether the magnetization control is to be performed (Step **S30**). Then, if it is determined that the magnetization control is to be performed, the TCU **22** changes the clutch control from the first clutch control to the second clutch control (Step **S31**). Therefore, the clutch engaging torque T_t coincides with the demanded torque T_a .

Further, the TCU **22** starts the adjustment of the hydraulic pressure suited to the transitional control performed thereafter (Step **S32**). In detail, the hydraulic pressure supplied to the transmission **8** is reduced in advance to a given hydraulic pressure setting P_t set beforehand.

Then, after the hydraulic pressure becomes the hydraulic pressure setting P_t (t_0 in FIG. **12**), the MCU **21** interrupts the torque control, and starts the torque adjustment of the transitional control (Step **S33**). That is, the demanded torque T_a is changed to the slight-increase demanded torque T_a' by adding the slip torque so that the transmission clutch **83** in use changes from the engaged state to the micro slip state.

Accordingly, the transmission clutch **83** starts the micro slip, and the rotational speed difference increases (t_0 to t_1 in FIG. **12**). Since the friction coefficient changes from the coefficient of static friction to the coefficient of dynamic friction, the transmission output torque decreases accordingly. Note that this example of control illustrates a case where the torque control performs the μ_s -suited control described above.

The TCU **22** raises the hydraulic pressure as the transmission output torque decreases so that the reduction of the transmission output torque is canceled out (t_0 to t_2 in FIG. **12**). Thus, the torque shock resulting from the friction coefficient difference is suppressed, and the torque variation is reduced below the level perceptible to a human. Therefore, the transmission clutch **83** can be changed from the engaged state to the micro slip state, without giving uncomfortableness to the driver.

When the rotational speed difference reaches a rotational speed R_s (micro-slip rotational speed) corresponding to the micro slip state (t_1 in FIG. **12**), the MCU **21** starts the power control aiming at the micro slip state (Step **S34**). Therefore, the transmission clutch **83** is converged to the micro slip state, and this state is held. The transmission input torque is stabilized at the slight-increase demanded torque T_a' , and the rotational speed difference is stabilized at the micro-slip rotational speed R_s (at or after t_2 in FIG. **12**). The hydraulic pressure is similarly stabilized at a given hydraulic pressure.

When the transmission clutch **83** becomes in the micro slip state, the MCU **21** starts the magnetization control (Step **S35**). The period from time t_3 to time t_4 in FIG. **12** corresponds to the magnetization control (including the learning control). During this period, as described above, the high motor torque T_m is outputted from the drive motor **3**. Accordingly, the motor rotational speed R_m increases and the rotational speed difference also increases (sudden speed rise phenomenon).

Meanwhile, by the second clutch control, the clutch engaging torque T_t coincides with the demanded torque T_a . Thus, even if the high motor torque T_m is outputted by the magnetization control, the transmission output torque which is substantially the same as the demanded torque T_a is outputted to the downstream side of the transmission clutch **83**. Therefore, the torque shock resulting from the magnetization can be suppressed.

When the magnetization control is ended (Yes at Step **S36**), the transmission input torque decreases. The power control is performed also during this period. In the power control, as described above, the torque control is performed using the target torque corresponding to the target power value. Therefore, in association with the end of the magnetization control, the increased transmission input torque decreases, and the rotational speed difference also decreases.

However, the rotational speed difference at this time decreases gently. Thus, it takes a comparatively long period of time until it is converged to the micro-slip rotational

speed R_s . Therefore, the MCU 21 collaborates with the TCU 22 (transmission clutch controller 22b) and starts the feed-back control during the execution of the power control.

That is, as illustrated in FIG. 14, if the rotational speed difference becomes below a reference value R_f (Yes at Step S37), the feedback control is started (Step S38). The reference value R_f is set for the TCU 22 according to the specifications of the transmission 8.

The TCU 22 compares a rotational speed difference which is actually measured or estimated based on the detection value of the transmission sensor 55 with the reference value R_f . Then, if the rotational speed difference is determined to be below the reference value R_f (t5 in FIG. 12), the feedback control is started for the rotational speed of the transmission clutch 83 so that the state is converged to the micro slip state (i.e., the rotational speed difference becomes the micro-slip rotational speed R_s). By the execution of the feedback control, the transmission clutch 83 can be resumed to the micro slip state promptly.

Then, if the rotational speed difference reaches the micro-slip rotational speed R_s (i.e., if the transmission clutch 83 is resumed to the micro slip state) (Yes at Step S39), the power control and the feedback control are ended, and the transitional control is started (Step S40, and t6 in FIG. 12).

That is, the MCU 21 changes the slight-increase demanded torque T_a' to the demanded torque T_a by removing the slip torque so that the transmission clutch 83 changes from the micro slip state to the engaged state.

Accordingly, the rotational speed difference decreases (t6 to t7 in FIG. 12). When the transmission clutch 83 is engaged, since the friction coefficient changes from the coefficient of dynamic friction to the coefficient of static friction, the transmission output torque increases accordingly.

The TCU 22 reduces the hydraulic pressure suited to the increase in the transmission output torque so that the increase in the transmission output torque is canceled out. Thus, the torque shock resulting from the friction coefficient difference is suppressed, and the torque variation is reduced below the level perceptible to a human. Therefore, the transmission clutch 83 can be changed from the micro slip state to the engaged state, without giving uncomfortableness to the driver.

By the series of processings, the sudden speed rise phenomenon is eliminated, and the motor torque T_m and the motor rotational speed R_m are resumed to their initial states. The transmission clutch 83 is also resumed to the engaged state (t7 in FIG. 12). Therefore, the MCU 21 resumes the torque control (Step S41).

The TCU 22 changes the clutch control from the second clutch control to the first clutch control (Step S42). Thus, the clutch engaging torque T_t rises to a normal value (at or after t7 in FIG. 12). The TCU 22 also raises the hydraulic pressure supplied to the transmission 8 to a normal value. Therefore, the drive motor 3 and the transmission 8 are resumed to the state before the magnetization control.

Thus, according to the control device 100 to which the disclosed technique is applied, even if the magnetization control in which the motor torque T_m higher than the demanded torque occurs is performed while the automobile 1 travels, the torque shock which originates in the magnetization can be suppressed by the second clutch control. Further, since the sudden speed rise phenomenon of the drive motor 3 which occurs with the slip of the transmission clutch 83 can also be eliminated promptly by the power control and the feedback control, the suitable control state can be resumed smoothly.

Further, the torque shock which originates in the friction coefficient difference of the transmission clutch 83 can also be suppressed by the micro slip control. Therefore, even when there is a large difference between the coefficient of dynamic friction and the coefficient of static friction of the transmission clutch 83, there is no concern of giving uncomfortableness to the driver.

According to this control device 100, the torque variation which occurs with the magnetism change of the drive motor 3 can be suppressed, without being influenced by the performance of the transmission clutch 83. Since the applicable range of the transmission clutch 83 expands, it excels in convenience.

Note that the disclosed technique is not limited to the above embodiment, and it also includes various other configurations. For example, various kinds of configurations exist for the drive motor 3, the transmission 8, etc. The same is true for the automobile 1. Therefore, these configurations may be selected according to the specifications, and the disclosed technique may be applied according to the specifications.

It should be understood that the embodiments herein are illustrative and not restrictive, since the scope of the invention is defined by the appended claims rather than by the description preceding them, and all changes that fall within metes and bounds of the claims, or equivalence of such metes and bounds thereof, are therefore intended to be embraced by the claims.

DESCRIPTION OF REFERENCE CHARACTERS

- 1 Automobile (Electric Vehicle)
- 2 Engine
- 3 Drive Motor
- 4R Driving Wheel
- 5 Relay Clutch
- 8 Transmission
- 10 Battery
- 20 Engine Control Unit (ECU)
- 21 Motor Control Unit (MCU)
- 21a Motor Output Controller
- 21b Magnetization Controller
- 22 Transmission Control Unit (TCU)
- 22a Relay Clutch Controller
- 22b Transmission Clutch Controller
- 23 Brake Control Unit (BCU)
- 24 General Control Unit (GCU)
- 33 Rotor
- 34 Stator
- 35 Magnet (Variable Magnetism Magnet)
- 80 Input Shaft
- 81 Output Shaft
- 82 Planetary Gear Mechanism
- 83 Transmission Clutch
- 83a Input Side
- 83b Output Side

What is claimed is:

1. A control device for an electric vehicle including a drive motor of which magnetic poles of a rotor are comprised of variable magnetism magnets that are able to change magnetism, and a clutch disposed between the drive motor and driving wheels, the electric vehicle being travelable using electric power, the control device being configured to:

when the electric vehicle travels, perform a torque control in which a motor torque outputted from the drive motor is controlled so that the motor torque coincides with a

21

demanded torque demanded to be outputted to the driving wheels, and a first clutch control in which an engaging torque of the clutch is controlled to be higher than the demanded torque; and

when performing a magnetization control in which the magnetism of the variable magnetism magnets is changed to magnetize the variable magnetism magnets when the electric vehicle travels:

change a clutch control from the first clutch control to a second clutch control in which the engaging torque is made to coincide with the demanded torque, before the execution of the magnetization control; and

add a given slip torque to the demanded torque based on a coefficient of dynamic friction and a coefficient of static friction of the clutch to start a micro slip control in which the clutch is transitioned from an engaged state into a micro slip state.

2. The control device of claim 1, wherein when the micro slip control is started, a transitional control is performed, the transitional control including adjusting a hydraulic pressure of the clutch so that a torque variation caused in connection with the clutch transitioning from the engaged state to the micro slip state is canceled out.

3. The control device of claim 2, wherein during the execution of the micro slip control, a power control is performed instead of the torque control, the power control including controlling the motor torque so that power outputted from the driving wheels coincides with a given target power value.

22

4. The control device of claim 3, wherein after the execution of the magnetization control, a feedback control is performed based on a difference between a rotational speed on an input side of the clutch and a rotational speed on an output side to converge a state to the micro slip state during the execution of the power control.

5. The control device of claim 1, wherein when the micro slip control is ended, a transitional control is performed, the transitional control including adjusting a hydraulic pressure of the clutch so that a torque variation caused in connection with transitioning the clutch from the micro slip state to the engaged state is canceled out.

6. The control device of claim 1, wherein during the execution of the micro slip control, a power control is performed instead of the torque control, the power control including controlling the motor torque so that power outputted from the driving wheels coincides with a given target power value.

7. The control device of claim 6 wherein after the execution of the magnetization control, a feedback control is performed based on a difference between a rotational speed on an input side of the clutch and a rotational speed on an output side to converge a state to the micro slip state during the execution of the power control.

8. The control device of claim 7, wherein when the micro slip control is ended, a transitional control is performed, the transitional control including adjusting a hydraulic pressure of the clutch so that a torque variation caused in connection with transitioning the clutch from the micro slip state to the engaged state is canceled out.

* * * * *