

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418952
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Wu; Chih-Hsiang

Secondary cell group failure in dual connectivity

Abstract

A user device operating in dual-mode connectivity with a master node and a secondary node detects a failure of a secondary cell group associated with the secondary node (**1004**). In response, the user device suspends an secondary cell group transmission (**1006**). The user device generates a message related to a status of the SCG for transmission to the MN (**1008**) and transmitting the message to the MN when the SCG transmission is suspended (**1010**).

Inventors:	Wu; Chih-Hsiang (Taoyuan, TW)
Applicant:	GOOGLE LLC (Mountain View, CA)
Family ID:	1000008818259
Assignee:	GOOGLE LLC (Mountain View, CA)
Appl. No.:	17/430133
Filed (or PCT Filed):	February 10, 2020
PCT No.:	PCT/US2020/017469
PCT Pub. No.:	WO2020/167644
PCT Pub. Date:	August 20, 2020

Prior Publication Data

Document Identifier	Publication Date
US 20220104301 A1	Mar. 31, 2022

Related U.S. Application Data

us-provisional-application US 62804202 20190211

Publication Classification

Int. Cl.: H04W76/19 (20180101); H04W24/10 (20090101); H04W76/16 (20180101); H04W76/20 (20180101)

U.S. Cl.:

CPC H04W76/19 (20180201); H04W24/10 (20130101); H04W76/16 (20180201); H04W76/20 (20180201);

Field of Classification Search

CPC: H04W (24/10); H04W (76/20); H04W (88/06); H04W (76/18); H04W (76/15); H04W (76/19); H04W (76/27); H04W (80/02); H04W (84/18); H04W (76/16); H04W (24/04)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9232418	12/2015	Lindoff	N/A	H04W 76/16
9451609	12/2015	Fukuta et al.	N/A	N/A
9504052	12/2015	Wu	N/A	H04W 72/542
9820332	12/2016	Lee	N/A	H04W 76/38
9907110	12/2017	Susitaival et al.	N/A	N/A
10440615	12/2018	Wu	N/A	H04W 36/0027
11165632	12/2020	Lee	N/A	H04W 74/0833
11206707	12/2020	Deogun	N/A	H04W 76/27
11219079	12/2021	Lee	N/A	H04L 1/1874
11582625	12/2022	Wu	N/A	H04L 5/0098
12069759	12/2023	Jung	N/A	H04L 1/1812
2015/0223282	12/2014	Vajapeyam et al.	N/A	N/A
2015/0358957	12/2014	Kim	455/450	H04W 72/21
2016/0044743	12/2015	Xu	370/329	H04W 76/34
2018/0302834	12/2017	Zhang et al.	N/A	N/A
2018/0368029	12/2017	Wu	N/A	H04W 36/0069
2019/0090144	12/2018	Wu	N/A	H04L 41/0816
2020/0305213	12/2019	Teyeb et al.	N/A	N/A
2021/0153281	12/2020	Deogun	N/A	H04W 24/10
2024/0292291	12/2023	Orsino	N/A	H04W 76/19

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
103597899	12/2013	CN	N/A
105960772	12/2015	CN	N/A

106576381	12/2016	CN	N/A
107925905	12/2017	CN	N/A
108924866	12/2017	CN	N/A
109076383	12/2017	CN	N/A
2 874 460	12/2014	EP	N/A
3 051 916	12/2015	EP	N/A
WO-2012/139798	12/2011	WO	N/A
WO-2016/195735	12/2015	WO	N/A
WO-2017/014686	12/2016	WO	N/A
WO-2018/182254	12/2017	WO	N/A
WO-2018/203710	12/2017	WO	N/A
WO-2020/162704	12/2019	WO	N/A

OTHER PUBLICATIONS

Huawei, HiSilicon, “Change Request on 38.331 for SCG failure in NR-DC”, 3GPP TSG RAN WG2 Meeting #104, R2-1817368, Nov. 2018, 5 Pages (Year: 2018). cited by examiner

International Search Report and Written Opinion for Application No. PCT/US2020/017469, dated May 20, 2020. cited by applicant

First Examination Report for India Application No. 202147038643, dated Mar. 8, 2022. cited by applicant

Office Action for Chinese Patent Application No. 202080026772.6, dated Jun. 30, 2023. cited by applicant

Office Action for European Application No. 20711368.9, dated Jun. 19, 2023. cited by applicant

“5G; NR; Radio Resource Control (RRC); Protocol specification (3GPP TS 38.331 version 15.4.0 Release 15),” ETSI TS 138 331 V15.4.0 (Aug. 2019). cited by applicant

“LTE; Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification (3GPP TS 36.331 version 15.3.0 Release 15),” Etsi TS 136 331 V15.3.0 (Oct. 2018). cited by applicant

“Universal Mobile Telecommunications System (UMTS); LTE; 5G; NR; Multi-connectivity; Overall description; Stage-2 (3GPP TS 37.340 version 15.4.0 Release 15),” ETSI TS 137 340 V15.4.0 (Apr. 2019). cited by applicant

Second Office Action for Chinese Patent Application No. 202080026772.6, dated Jan. 25, 2024. cited by applicant

Primary Examiner: Connor; Brian T O

Attorney, Agent or Firm: MARSHALL, GERSTEIN & BORUN LLP

Background/Summary

FIELD OF THE DISCLOSURE

(1) This disclosure relates generally to wireless communications and, more particularly, to methods and apparatus to handle secondary cell group (SCG) failures in dual connectivity (DC).

BACKGROUND

(2) A user device (or user equipment, commonly denoted by acronym “UE”) in some cases can operate in DC with a master node (MN) and a secondary node (SN). The MN and the SN are base stations that can operate according to the same radio access technology (RAT) or, in a multi-radio DC (MR-DC) configuration, different RATs. Two configurations in which the MN supports

Evolved Universal Terrestrial Radio Access (EUTRA) and the SN supports 5G new radio (NR) are referred to as EN-DC and NGEN-DC, and a configuration in which the MN supports NR and the SN supports EUTRA is referred to as NE-DC. Yet another configuration, NN-DC, has both the MN and SN supporting NR. DC is described in, for example, the 3rd Generation Partnership Project (3GPP) standard TS 37.340 v. 15.4.0.

(3) The MN can provide a control plane connection and a user plane connection to a core network (CN), whereas the SN generally provides a user plane connection. The cells associated with the MN define a master cell group (MCG), and the cells associated with the SN define the SCG.

(4) The UE and the base stations MN and SN can use signaling radio bearers (SRBs) to exchange radio link control (RRC) messages, as well as non-access stratum (NAS) messages. There are several types of SRBs that UEs can use when operating in DC. SRB1 and SRB2 resources allow the UE and the MN to exchange RRC messages related to the MN, and to embed RRC messages related to the SN, and can be referred to as MCG SRBs. SRB3 resources allow the UE and the SN to exchange RRC messages related to the SN, and can be referred to as SCG SRBs. Split SRBs allow the UE to exchange RRC messages directly with the MN and the SN. Further, the UE and the base stations MN and SN use data radio bearers (DRBs) to transport data on a user plane. DRBs terminated at the MN and using the lower-layer resources of only the MN can be referred to as MCG DRBs, DRBs terminated at the SN and using the lower-layer resources of only the SN can be referred to as SCG DRBs, and DRBs terminated at the MCG but using the lower-layer resources of both the MN and the SN can be referred to as split DRBs.

(5) There are scenarios in which the UE can detect SCG failure, which can be a radio link failure (RLF), a failure of SCG reconfiguration with synchronization, an SCG configuration failure for RRC messaging on SRB3, etc. For example, the UE in EN-DC with a master evolved Node B (MeNB) and a secondary 5G node B (SgNB) can detect an SCG failure associated with the SgNB (NR SCG failure). Upon detecting an NR SCG failure, the UE suspends NR SCG transmission for all SRBs and DRBs configured to use the resources provided by the SgNB as, for example, required by the 3GPP standard TS 38.331 v15.4.0.

(6) However, because another standard, 3GPP TS 36.331 v15.3.0, prevents the UE from reporting the NR SCG failure to the MeNB because the NR SCG transmission is suspended, the MeNB is unaware of the NR SCG failure. As a result, the MeNB cannot take remedial action such as informing the NR SCG failure to the SgNB or releasing the SgNB from the current DC configuration of the UE. This in turn causes the SgNB to transmit data to the UE, which the UE cannot receive due to the SCG failure. For similar reasons, when MN is an gNB and the SN is an eNB, the UE suspends EUTRA SCG transmissions and cannot report the EUTRA SCG failure to the MN. Further, when the UE suspends SCG transmission, the UE in some scenarios cannot deliver a measurement report to the MN.

SUMMARY

(7) Generally speaking, the techniques of this disclosure allow UEs and base stations to handle SCG failures in DC for single RAT and dual RAT configurations. An example UE of this disclosure detects SCG failure and suspends SCG transmission. The UE then reports SCG failure to the MN even though the SCG has been suspended. In another case, the UE generates a measurement report and transmits the measurement report to the MN when the SCG has been suspended. Thus, in a sense, the UE overrides the SCG suspension to transmit an indication of SCG failure or a measurement to the MN.

(8) In an example scenario, a UE operating in EN-DC (or NGEN-DC) generates a measurement report in accordance with the measurement configuration from the SgNB. The UE then initiates transmission of the measurement report to the SgNB using the corresponding SCG SRB (e.g., SRB3) and detects NR SCG failure (e.g., based on the indication from lower layers). The UE accordingly suspends NR SCG transmission. The UE then transmits SCGFailureInformationNR (which is an RRC message that reports SCG failure for an NR connection to the SgNB) to the

MeNB (or a Master next generation eNB in the case of the NGEN-DC) while the NR SCG transmission is suspended. To this end, the UE can use a EUTRA SRB1 to transmit the SCGFailureInformationNR and transmit the measurement report (if not yet transmitted to the SgNB before detecting the NR SCG failure) to the MeNB (or the Master next generation eNB in case of the NGEN-DC).

(9) In another example scenario, the UE operating in NE-DC detects EUTRA SCG failure and accordingly suspends EUTRA SCG transmission. The UE then transmits the SCGFailureInformationEUTRA message to the MgNB using an NR SRB1 while the EUTRA SCG transmission is suspended.

(10) In still other scenarios, the UE generates a measurement report and transmits the report to the MN when the NR SCG transmission is suspended in EN-DC and NGEN-DC configurations or when EUTRA SCG transmission is suspended in NE-DC configurations.

(11) An example embodiment of these techniques is a method in a UE operating in DC connectivity with an MN and a SN. The method comprises detecting, by processing hardware, a failure of an SCG associated with the SN; suspending, by the processing hardware, an SCG transmission in response to detecting the failure of the SCG; generating, by the processing hardware, a message related to a status of the SCG for transmission to the MN; and transmitting, by the processing hardware, the message to the MN when the SCG transmission is suspended.

(12) Another example embodiment of these techniques is a UE comprising processing hardware configured to implement the method above.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a block diagram of an example wireless communication network in which a UE handles SCG failures in dual connectivity in accordance with disclosure;

(2) FIGS. 2-5 are messaging diagrams of example scenarios in which a UE notifies the MN of a SCG failure when the SCG transmission is suspended, in particular:

(3) FIG. 2 illustrates an example scenario in which a UE transmits to an MN an indication of SCG failure for an NR or EUTRA connection;

(4) FIG. 3 illustrates an example scenario in which a EUTRA module operating in the UE transmits to an MeNB an indication of SCG failure for an NR connection;

(5) FIG. 4 illustrates an example scenario in which an NR module operating in the UE transmits to an MgNB an indication of SCG failure for a EUTRA connection.

(6) FIGS. 5-8 are messaging diagrams of example scenarios in which a UE transmits a measurement report to the MN when the SCG transmission is suspended, in particular:

(7) FIG. 5 illustrates an example scenario in which a UE transmits a measurement report to the MN on an SRB1;

(8) FIG. 6 illustrates an example scenario in which a UE transmits a measurement report on an SRB1 as well as an indication of SCG failure to the MN;

(9) FIG. 7 illustrates an example scenario in which a EUTRA module operating in the UE transmits a measurement report to a MeNB as well as an indication of SCG failure to the MN; and

(10) FIG. 8 illustrates an example scenario in which an NR module operating in the UE transmits a measurement report to a MgNB as well as an indication of SCG failure to the MN.

(11) FIG. 9 is a flow diagram of an example method for reporting SCG failure in dual connectivity, which can be implemented in the UE of FIG. 1.

(12) FIG. 10 is a flow diagram of an example method for providing measurement reports in dual connectivity, which can be implemented in the UE of FIG. 1.

DETAILED DESCRIPTION OF THE DRAWINGS

(13) FIG. 1 depicts an example wireless communication network **100** in which an example UE **102** operates in DC with a MN **104** and a SN **106**. To enable the communication network **100** to properly handle SCG failures, the UE **102** (which can be any suitable device capable of wireless communications, as discussed below) implements the techniques below to report SCG failures and measurement reports to the MN even when the SCG has been suspended.

(14) More particularly, the UE **102** is equipped with processing hardware **110** that can include one or more general-purpose processors such as central processing units (CPUs) and non-transitory computer-readable memory storing machine-readable instructions executable on the one or more general-purpose processors, and/or special-purpose processing units. The processing hardware **110** in an example implementation includes a EUTRA module **114** and an NR module **116**, which in turn include an SCG failure handler **118A** and an SCG failure handler **118B**, respectively. In general, the functionality discussed below with reference to the SCG failure handler **118A** or **118B** can be implemented in the EUTRA module **114**, the NR module **116**, or as a separate module. In the discussion of SCG failure handling below, references to the SCG failure handler **118A** and the EUTRA module **114**, as well as the SCG failure handler **118B** and the NR module **116**, can be used interchangeably.

(15) In operation, the SCG failure handler **118A** or **118B** can detect an SCG failure and transmit a notification to the MN **104**, or cause the EUTRA module **114** or the NR module **116** generate and transmit this notification. The SCG failure handler **118A** or **118B** additionally or alternatively causes the UE **102** to transmit a measurement report to the MN **106**, under certain circumstances related to SCG failure.

(16) The UE **102** communicates with the MN **104** that covers an MCG **124** made up of one or more cells, and the SN **106** that covers an SCG **126** made up of one or more cells. In different configurations of the network **100**, the MN **104** can be implemented as a master eNB (MeNB) or a master gNB (MgNB) node, the SN **106** can be implemented as a secondary eNB (SeNB) or a secondary gNB (SgNB) node, and the UE **102** communicates with the MN **104** and SN **106** via the same RAT such as EUTRA or NR, or different RATs such as EUTRA and NR. In some cases, the MeNB or SeNB is implemented as an ng-eNB rather than an eNB. The MN **104** and the SN **106** can be coupled to a core network **110**. For example, the core network **110** can be a 5G core network (5GC) or an evolved packet core (EPC). Some of these example configurations are discussed in more detail below.

(17) Although handling of SCG is discussed in this disclosure with reference to these RATs and core network technologies, more generally these techniques can be used with any suitable systems in which SCG failures triggers suspension of certain transmissions. Further, these techniques can be used when the UE **102** operates in dual connectivity via a single RAT or different RATs.

(18) Next, several scenarios corresponding to different DC configurations and/or different UE implementations are discussed with reference to FIGS. 2-9.

(19) Referring first to FIG. 2, the UE **102** at the beginning of the scenario is communicating in DC with the MN **104** and the SN **106**. The UE **102** is configured with an SRB1 (e.g., a EUTRA SRB1 or an NR SRB1) to exchange EUTRA RRC messages (when operating in EN-DC or NGEN-DC, for example) or NR RRC messages (when operating in NE-DC) with the MN **104**. The UE **102** is also configured with at least one DRB that utilizes resources of the SCG **124** provided by the SN **106**. For example, the UE **102** can be configured with an SRB3 (e.g., NR SRB3 or EUTRA SRB3) to exchange NR RRC messages with the SN **106**.

(20) The UE **102** detects an SCG failure associated with the SN **106**. For example, referring back to FIG. 1, the SCG failure handler **118A** or **118B** can detect RLF, failure of SCG reconfiguration with synchronization, SCG configuration failure for RRC message on SRB3 and SCG integrity check failure, etc.

(21) In response to detecting the SCG failure, the UE **102** (e.g., the SCG failure handler **118A**, **118B** or another suitable component) suspends SCG transmissions. In some implementations,

the UE **102** suspends the SCG transmissions for the SRB(s) and the one or more DRBs configured to use SCG radio resources of the SN **106**. When an SRB/DRB is configured to use the SCG radio resources before detecting the SCG failure, the UE **102** has nothing to suspend for the SRB/DRB. (22) In one example scenario, the MN **104** configures the UE **102** with an SRB1 (e.g., an EUTRA SRB1 or an NR SRB1) that only uses MCG radio resources to transmit RRC messages and receive RRC messages. When the SN **106** configures the UE **102** with an SRB3 (e.g., an NR SRB3 or EUTRA SRB3) that only uses the SCG radio resources to transmit RRC messages and receive RRC messages, the UE **102** suspends the SCG transmission for the SRB3 in response to the SCG failure. More particularly, the SCG failure handler **118A** or **118B** prevents the UE **102** from transmitting to the SN **106** an RRC message corresponding to the SRB3 using the SCG radio resources during the SCG failure.

(23) In another example scenario, the MN **104** or the SN **106** configures the UE **102** with a DRB that uses the SCG radio resources to transmit (or receive) Packet Data Convergence Protocol (PDCP) Protocol Data Units (PDUs). The UE **102** suspends the NR SCG transmission for the DRB in response to the SCG failure. More particularly, the SCG failure handler **118A** or **118B** in this case prevents the UE **102** from transmitting to (or receiving from) the SN **106** a PDCP PDU corresponding to the DRB using the SCG radio resources during the SCG failure. In this case, the DRB can be a split bearer or an SCG bearer.

(24) The UE **102** generates **240** an indication of the SCG failure (e.g., an SCGFailureInformationNR or SCGFailureInformationEUTRA message) and transmits **242** the indication even though the UE **102** previously suspended the SCG transmissions (event **230**), and the SCG transmissions remain in the suspended state **250**. The UE **102** can transmit this indication on the SRB1, for example. In some implementations, the UE **102** transmits the SCGFailureInformationNR or SCGFailureInformationEUTRA message in an RRC message format of the MN. The MN **104** receives the SCGFailureInformationNR or SCGFailureInformationEUTRA message and becomes aware of the SCG failure. The MN **104** then can take remedial action.

(25) In some implementations, the UE **102** may include a first SCG failure type of the SCG failure in the SCGFailureInformationNR or SCGFailureInformationEUTRA message. When the SCG failure is RLF, the first SCG failure type indicates the RLF. When the SCG failure is failure of SCG reconfiguration with synchronization, the first SCG failure type indicates the failure of SCG reconfiguration with synchronization. When the SCG failure is SCG configuration failure for RRC message on SRB3, the first SCG failure type indicates the SCG configuration failure for RRC message on SRB3. When the SCG failure is SCG integrity check failure, the first SCG failure type indicates the SCG integrity check failure.

(26) In some cases, the UE **102** cannot handle uplink transmission timing difference between a primary cell (PCell) of the MCG and a primary secondary cell (PSCell) of the SCG (e.g., the timing difference exceeds a maximum uplink transmission timing difference). The UE **102** can determine that exceeding maximum uplink transmission timing difference is the SCG failure. In the SCGFailureInformationNR message, the UE sets the first SCG failure type to indicate one of the RLF, failure of SCG reconfiguration with synchronization, SCG configuration failure for RRC message on SRB3, SCG integrity check failure.

(27) In some implementations, in addition to including the first SCG failure type in the SCGFailureInformationNR message, the UE can further include a second SCG failure type in the SCGFailureInformationNR message to indicate that the maximum uplink transmission timing difference was exceeded. An indication that the maximum uplink transmission timing difference was exceeded may be a new SCG failure type compared to legacy SCG failure types such as the RLF, failure of SCG reconfiguration with synchronization, SCG configuration failure for RRC message on SRB3 and SCG integrity check failure. The MN **104** in some implementations may not recognize the new SCG failure type and ignore a SCGFailureInformationNR message, which

includes the new SCG failure type but does not include a legacy SCG failure type. To prevent the MN **104** from ignoring this information, the UE **102** can include the first SCG failure type and the second SCG failure type in the SCGFailureInformationNR message. The MN **104** that does not recognize the second SCG failure type still can recognize and process the first SCG failure type, and thus the MN **104** in this case does not ignore the SCGFailureInformationNR message including the first SCG failure type and the second SCG failure type.

(28) The MN **104** in some cases can perform a procedure for recovering from SCG failure (not illustrated in FIG. 2 to avoid clutter). To this end, the MN **104** can transmit to the UE **102** an EUTRA RRC message (e.g., a EUTRA RRC Connection Reconfiguration message) or NR RRC message (e.g., an NR RRC Reconfiguration message) on the SRB1, depending on the DC mode. The EUTRA RRC message may include a NR RRC message (e.g., a NR RRC Reconfiguration message), which in turn may include NR configurations. The NR RRC message may include a EUTRA RRC message (e.g., a EUTRA RRC Connection Reconfiguration message), which in turn may include EUTRA configurations. The UE **102** resumes the NR or EUTRA SCG transmission in accordance with the NR or EUTRA configuration included in the EUTRA or NR RRC message with the SN **106** or another SN (not shown in FIG. 2). The UE **102** then can transmit a EUTRA RRC response message (e.g., a EUTRA RRC Connection Reconfiguration Complete message) on the SRB1 to the MN **104** to respond to the EUTRA RRC message, or an NR RRC response message (e.g., an NR RRC Reconfiguration Complete message) to respond to the NR RRC message. The UE **102** may include a NR RRC response message (e.g., a NR RRC Reconfiguration Complete message) in the EUTRA RRC response message to respond to the NR RRC message; or the UE **102** may include a EUTRA RRC response message (e.g., a EUTRA RRC Connection Reconfiguration Complete message) in the NR RRC response message. The MN **104** may forward the NR RRC response message or the EUTRA RRC response message to the SN **106** or the other SN.

(29) In another scenario, the MN **104** transmits to the UE **102** a EUTRA RRC message (e.g., a EUTRA RRC Connection Reconfiguration message) on the SRB1 to the UE **102** to place the UE **102** is a non-DC configuration when/after receiving the SCGFailureInformationNR message, or the MN **104** transmits to the UE **102** an NR RRC message (e.g., an NR RRC Reconfiguration message) on the SRB1 to the UE **102** to place the UE **102** is a non-DC configuration when/after receiving the SCGFailureInformationEUTRA message. The UE **102** transmits a EUTRA RRC response message (e.g., a EUTRA RRC Connection Reconfiguration Complete message) or an NR RRC response message (e.g., a NR RRC Reconfiguration Complete message) on the SRB1 to the MN **104**. The UE **102** releases the resources of the NR or EUTRA configuration associated with the SN **106** in response to the EUTRA RRC or the EUTRA RRC message, respectively. In some cases, the UE **102** receives the NR or EUTRA configuration from the SN **106** via the MN **104** or via the SRB3 before the SCG failure occurs.

(30) Now referring to FIG. 3, the UE **102** initially is communicating **302** in DC with the MN **104** and the SN **106**, similar to the communication **202** of FIG. 2. In this case, the UE may be operating EN-DC or NGEN-DC.

(31) The UE NR module **116** (e.g., the SCG failure handler **118B**) detects **320** SCG failure. In response, the UE NR module **116** suspends **330** NR SCG transmissions, similar to the event **230** discussed above. The NR module **116** also indicates **332** the SCG failure to the EUTRA module **114** via, for example, an internal SCG failure indication message.

(32) The EUTRA module **114** generates **340** an indication of the SCG failure (e.g., an SCGFailureInformationNR message) and transmits **342** this indication to the MN **104** over the SRB1, even though the SCG transmissions are in the suspended state **350**. In some scenarios, the EUTRA module **114** generates the SCGFailureInformationNR message in a EUTRA RRC message format. The MN **104** receives the SCGFailureInformationNR message, becomes aware of the SCG failure, and perform a procedure for recovering from SCG failure or take other remedial action.

(33) In some implementations, the NR module **116** may send one or more measurement results to the EUTRA module **114** in response to detecting the SCG failure. The EUTRA module **114** may include the one or more measurement results in the SCGFailureInformationNR message. In one aspect, when the NR module **116** sends the one or more measurement results to the EUTRA module **114**, the NR mode **116** removes the one or more measurement results (i.e., the one or more measurement results is not valid to be reported). In another aspect, when EUTRA module **114** includes the one or more measurement results in the SCGFailureInformationNR message, the EUTRA module **114** indicates the NR mode **116** to remove the one or more measurement results (i.e., the one or more measurement results is not valid to be reported).

(34) Referring to FIG. 4, the UE **102** initially is communicating **402** in DC with the MgNB **104** and the SeNB **106**. In this case, the UE may be operating NE-DC. In this scenario, the EUTRA module **114** (e.g., the SCG failure handler **118A**) detects **420** SCG failure. In response, the EUTRA module **114** suspends **430** EUTRA SCG transmissions, similar to the event **230** discussed above. The EUTRA module **114** also indicates **432** the SCG failure to the UE NR module **116** via, for example, an internal SCG failure indication message.

(35) The NR module **116** generates **440** an indication of the SCG failure (e.g., an SCGFailureInformationEUTRA message) and transmits **442** this indication to the MgNB **104** **104** over the SRB1, even though the SCG transmissions are in the suspended state **440**. This message can conform to the NR RRC message format. The MgNB **104** receives the SCGFailureInformationEUTRA message, becomes aware of the SCG failure, and performs a procedure for recovering from SCG failure or take other remedial action (similar to the remedial action discussed above with reference to FIG. 2, for example). As discussed above, the SCGFailureInformationEUTRA message can be defined to convey SCG failure for a EUTRA interface between a UE and an SN (e.g., the SeNB **106**), or the message can conform to the format of the existing SCGFailureInformation message but include an additional information element, which can be defined specifically for indicating SCG failure.

(36) In some implementations, the EUTRA module **114** can send one or more measurement results to the NR module **116** in response to detecting the SCG failure. The NR module **116** can include the one or more measurement results in the SCGFailureInformationEUTRA message. In one aspect, when the EUTRA module **114** sends the one or more measurement results to the NR module **116**, the EUTRA mode **114** removes the one or more measurement results (i.e., the one or more measurement results is not valid to be reported). In another aspect, when NR module **116** includes the one or more measurement results in the SCGFailureInformationEUTRA message, the NR module **116** indicates the EUTRA mode **116** to remove the one or more measurement results (i.e., the one or more measurement results is not valid to be reported).

(37) In the scenario of FIG. 5, the UE **102** initially is communicating **502** in DC with the MN **104** and the SN **106**. The scenario of FIG. 5 can pertain to at least the EN-DC, NGEN-DC, NR-NR DC (NN-DC), and the NE-DC modes of DC.

(38) The UE **102** is configured with an SRB1 to exchange RRC messages with the MN **104**. The UE **102** is also configured with at least one DRB that utilizes resources of the SCG **124** provided by the SN **106**. Still further, the SN **106** configures the UE **102** with at least one measurement configuration. As one example, the SN **106** can provide the UE **102** one, some or all of the measurement configuration settings via the MN **104**. In another example, the SN **106** can provide the UE **102** one, some or all of the measurement configuration settings over the SRB3.

(39) The UE **102** triggers measurement reporting in accordance with one of the at least one measurement configuration and generates **510** a measurement report. More specifically, the configuration can specify that the UE **102** should generate a measurement report in response to a particular event or, in another scenario, periodically in accordance with a certain schedule.

(40) The UE **102** then attempts **512** to transmit the measurement report (e.g., in the form of a MeasurementReport message) in response to the triggering. In particular, the UE **102** initiates

transmission of the MeasurementReport message on the SRB3 to the SN **106**.

(41) The UE **102** then detects **520** an SCG failure and, in response, suspends **530** SCG transmissions (e.g., NR SCG transmission or EUTRA SCG transmission, depending on the DC mode). Subsequently, the UE **102** again triggers measurement reporting in accordance with the measurement configuration received from the SN **106** (events or procedure **502**). The UE **102** generates **550** a measurement and transmits **572** a corresponding MeasurementReport message.

(42) The UE **102** initiates transmission of the MeasurementReport message to the MN **104** when the SCG transmissions remain in the suspended state **550**. In response to the initiation event, the UE **102** transmits the MeasurementReport message over the SRB1 to the MN **104**.

(43) When the scenario of FIG. 5 is implemented in the EN-DC mode or the NGEN-DC mode, the UE **102** in some cases transmits the MeasurementReport message over the SRB1 (i.e., an EUTRA SRB1) by including the MeasurementReport message in an UL Information Transfer for MR-DC (ULInformationTransferMRDC) message and transmitting the ULInformationTransferMRDC message on the SRB1 to the MN **104**. Upon receiving the ULInformationTransferMRDC message, the MN **104** in some implementations extracts the MeasurementReport message out of the ULInformationTransferMRDC message and forwards the MeasurementReport message to the SN **106**.

(44) When the scenario of FIG. 5 is implemented in the NN-DC mode or the NE-DC mode, the UE **102** in some cases transmits the MeasurementReport message over the SRB1 (i.e., an NR SRB1) by including the MeasurementReport message in an UL Information Transfer for MR-DC (ULInformationTransferMRDC) message and transmitting the ULInformationTransferMRDC message on the SRB1 to the MN **104**. Upon receiving the ULInformationTransferMRDC message, the MN **104** in some implementations extracts the MeasurementReport message out of the ULInformationTransferMRDC message and forwards the MeasurementReport message to the SN **106**. Alternatively, the UE **102** can utilize a ULInformationTransferNRDC or ULInformationTransferNEDC messages.

(45) In another implementations for the NN-DC or NE-DC modes of DC, the UE **102** transmits the MeasurementReport message on the SRB1 (i.e., a NR SRB1) by including the MeasurementReport in a UL Information Transfer (ULInformationTransfer) message and transmitting the ULInformationTransfer message on the SRB1 to the MN **104**. Upon receiving the ULInformationTransfer message, the MN **104** can extract the MeasurementReport message from the ULInformationTransfer message and forward the MeasurementReport message to the SN.

(46) In case of the EN-DC, NGEN-DC or NN-DC, the MeasurementReport messages are NR MeasurementReport messages. In case of the NE-DC, the MeasurementReport messages are EUTRA MeasurementReport messages.

(47) Thus, the UE **102** in this scenario provides a measurement report to the MN **104** even though the SCG transmissions were suspended. For example, similar to the examples above, the MN **104** can attempt to recover from the SCG failure. When the UE **102** is operating in the EN-DC or NGEN-DC mode, the UE **102** can transmit a EUTRA RRC message (e.g., a EUTRA RRC Connection Reconfiguration message) on the SRB1 to recover from the SCG failure. The EUTRA RRC message may include a NR RRC message (e.g., a NR RRC Reconfiguration message). The NR RRC message can include a certain NR configuration. The UE **102** can resume the NR SCG transmission according to the NR RRC message with the SN **106** or another SN (not shown in FIG. 5). After the UE **102** resumes NR SCG transmissions, the UE **102** can transmit a MeasurementReport message on the SRB3. The UE **102** can transmit a EUTRA RRC response message (e.g., a EUTRA RRC Connection Reconfiguration Complete message) on the SRB1 to the MN **104** to respond to the EUTRA RRC message. The UE **102** can include a NR RRC response message (e.g., a NR RRC Reconfiguration Complete message) in the EUTRA RRC response message to respond to the NR RRC Reconfiguration message. The MN **104** may forward the NR RRC response message to the SN **106** or the other SN.

(48) When the UE **102** is operating in the EN-DC or NGEN-DC mode, the MN **104** in an example scenario transmits, to the UE **102**, a EUTRA RRC message (e.g., a EUTRA RRC Connection Reconfiguration message) on the SRB1, so as to configure the UE **102** to not operate in the DC mode after receiving an SCGFailureInformationNR message. The UE **102** can transmit an EUTRA RRC response message (e.g., a EUTRA RRC Connection Reconfiguration Complete message) on the SRB1 to the MN to respond to the EUTRA RRC message. The UE **102** then can release NR configurations (including the at least one measurement configuration) associated with the SN **106**, in response to the EUTRA RRC message. The UE **102** may receive the NR configurations from the SN **106** via the MN **104** or via the SRB3, prior to the SCG failure.

(49) As illustrated in FIGS. **6-8**, the UE **102** can implement both the techniques for transmitting an indication of SCG failure as well as a measurement report to the MN, when the SCG transmission is suspended.

(50) Referring first to FIG. **6**, the UE **102** at the beginning of the scenario is communicating **602** in DC with the MN **104** and the SN **106**. The UE **102** is configured with an SRB1 and an SRB3 for communication with the MN **104** and the SN **106**, respectively. The UE **102** also is configured with a measurement configuration by the SN **106**. The UE **102** triggers measurement reporting in accordance with the measurement configuration and generates **610** a measurement report. The UE **102** transmits **612** the measurement report to the SN **106**. After the UE **102** detects **620** SCG failure, the UE **102** suspends **630** NR or EUTRA SCG transmissions, depending on the configuration of DC mode, and generates **640** an appropriate SCG suspension indication.

(51) The UE **102** transmits **642** the indication to the MN **104** when the SCG transmissions are in the suspended state **650**. The SCGFailureInformation indication can be specific to the SCG such as SCGFailureInformationNR for EN-DC and NGEN-DC modes or SCGFailureInformationEUTRA for NE-DC mode. The UE **102** also generates **660** a measurement in accordance with the previously received measurement configuration and formats **670** a measurement report. The UE **102** then transmits **672** the measurement report to the MN **104** while the SCG transmissions remain in the suspended state **650**. If desired, the order of the events **642** and **672** can be reversed.

(52) In the scenario of FIG. **7**, the EUTRA module **114** transmits both the SCGFailureInformationNR message and a measurement report to the MeNB **104**. The events **702**, **710**, **712**, **720**, **730**, **740**, **742**, **760**, **770**, and **772** are similar to the events **602**, **610**, **612**, **620**, **630**, **640**, **642**, **660**, **670**, and **672** discussed with reference to FIG. **6**, and the state **750** is similar to the state **650**. However, the NR module **116** in this scenario indicates **732** the SCG failure to the EUTRA module **114** via an internal SCG failure indication message, for example, and the EUTRA module **114** reports the SCG failure to the MeNB **104**. The NR module **116** also transmits **762** the measurement report to the EUTRA module **114** via an internal message, and the EUTRA module **114** again forwards **772** the measurement report to the MeNB **104**.

(53) On the other hand, in the scenario of FIG. **8**, it is the NR module **116** rather than the EUTRA module **114** that provides both an SCG failure indication and a measurement report to the MN when SCG transmissions are suspended. More specifically, the NR module **116** transmits both the SCGFailureInformationEUTRA message and a measurement report to the MgNB **104**. The events **802**, **810**, **812**, **820**, **830**, **840**, **842**, **860**, **870**, and **872** are similar to the events **602**, **610**, **612**, **620**, **630**, **640**, **642**, **660**, **670**, and **672** discussed with reference to FIG. **6**, and the state **850** is similar to the state **650**. However, the EUTRA module **114** in this scenario indicates **832** the SCG failure to the NR module **116** via an internal SCG failure indication message, for example, and the NR module **116** reports the SCG failure to the MgNB **104**. The EUTRA module **114** also transmits **862** the measurement report to the NR module **116** via an internal message, and the NR module **116** again forwards **872** the measurement report to the MgNB **104**.

(54) Referring generally to the figures above, prior to transitioning to the EN-DC, NGEN-DC, or NN-DC mode, the UE **102** can connect to the MN **104** and obtain an SRB1 configuration for the MN **104** (which in various configurations can be an MeNB, a master ng-eNB or an MgNB). The

UE **102** then can transmit a MeasurementReport message on the SRB1 to the MN **104**. The MN **104** can determine that it should configure the UE **102** to connect to the SN **106** (e.g., an SgNB) in response to the MeasurementReport message. The MN **104** can make this determined based on the indication in the MeasurementReport message that the UE **102** receives a signal of sufficient strength, quality, etc. on a downlink carrier of the SN **106**. The MN **104** then can initiate an SN Addition procedure by sending a SN Addition Request message to the SN **106**.

(55) Next, the SN **106** can generate a first RRC Reconfiguration message and include this message in an SN Addition Request Acknowledge message. The SN **106** can send the SN Addition Request Acknowledge message to the MN **104** in response to the SN Addition Request message. When the MN **104** is implemented as an MeNB or a master ng-eNB, the MN **104** can include the first RRC Reconfiguration message in an RRC Connection Reconfiguration message. The MN **104** can transmit the UE the RRC Connection Reconfiguration message in response to the SN Addition Request Acknowledge message and receives an RRC Connection Reconfiguration Complete message from the UE **102** in response to the RRC Connection Reconfiguration message. In some implementations, the UE **102** can include a first RRC Reconfiguration Complete message in the RRC Connection Reconfiguration Complete message to respond to the first RRC Reconfiguration message. The MN **104** can forward the first RRC Reconfiguration Complete message to the SN **106**. The SRB1 can be a EUTRA SRB1. The MeasurementReport message, the RRC Connection Reconfiguration message, and the RRC Connection Reconfiguration Complete message can be in a EUTRA RRC message format.

(56) When the MN **102** is an MgNB, the MN **104** includes the first RRC Reconfiguration message in a second RRC Reconfiguration message generated by the MN **104**. The MN **104** transmits the second RRC Reconfiguration message to the UE **102** in response to the SN Addition Request Acknowledge message and receives a second RRC Reconfiguration Complete message from the UE **102** in response to the second RRC Reconfiguration message. In some implementations, the UE **102** may include a first RRC Reconfiguration Complete message in the second RRC Reconfiguration Complete message to respond to the first RRC Reconfiguration Complete message. The MN **104** can forward the first RRC Reconfiguration Complete message to the SN **106**. In this case, the SRB1 can be an NR SRB1. The MeasurementReport message, the first RRC Reconfiguration message, the first RRC Reconfiguration Complete message, the second RRC Reconfiguration message, and the second RRC Reconfiguration Complete message can be in an NR RRC message format. In both cases discussed above, the UE **102** can perform a random access procedure with the SN **106** in response to/according to the first RRC Reconfiguration message.

(57) In the example above, the first RRC Reconfiguration message can include a CellGroupConfig IE for an SCG the UE **102** can use to communicate with the SN **106**. In another example, the SN **106** can include a Radio Bearer Configuration (RadioBearerConfig) which configures an SRB3 (i.e., a NR SRB3) or a DRB in the SN Addition Request Acknowledge message. The MN **104** can include the RadioBearerConfig in the RRC Connection Reconfiguration message or the second RRC Reconfiguration message. The SRB3 or the DRB can be an SCG bearer when the MN **104** does not configure MCG radio resources for the SRB3 or the DRB. The SRB3 or the DRB can be an SCG split bearer if the MN **104** configures MCG radio resources for the SRB3 or the DRB. As an additional example, the SN **106** does not include the RadioBearerConfig in the SN Addition Request Acknowledge message. The MN **104** does not include the RadioBearerConfig in the RRC Connection Reconfiguration message. The MN **104** can generate and include another RadioBearerConfig in the RRC Connection Reconfiguration message or the second RRC Reconfiguration message.

(58) Further, the first RRC Reconfiguration message can include one, some or all of the measurement configuration settings discussed above. In another example, the SN **106** can transmit, to the UE **102** on the SRB3, a third RRC Reconfiguration message configuring one, some or all of the at least one measurement configuration settings discussed above.

(59) Referring generally to the figures above, prior to transitioning to the NE-DC mode, the UE **102** can connect to the MN **104** and obtain an SRB1 configuration for the MN **104** (which in various configurations can be an MgNB). The UE **102** then can transmit a MeasurementReport message on the SRB1 to the MN **104**. The MN **104** can determine that it should configure the UE **102** to connect to the SN **106** (e.g., an SgNB) in response to the MeasurementReport message. The MN **104** can make this determined based on the indication in the MeasurementReport message that the UE **102** receives a signal of sufficient strength, quality, etc. on a downlink carrier of the SN **106**. The MN **104** then can initiate an SN Addition procedure by sending a SN Addition Request message to the SN **106**.

(60) Next, the SN **106** can generate an RRC Connection Reconfiguration message and include this message in an SN Addition Request Acknowledge message. The SN **106** can send the SN Addition Request Acknowledge message to the MN **104** in response to the SN Addition Request message. The MN **104** can include the RRC Connection Reconfiguration message in an RRC Reconfiguration message. The MN **104** can transmit the UE the RRC Reconfiguration message in response to the SN Addition Request Acknowledge message and receives an RRC Reconfiguration Complete message from the UE **102** in response to the RRC Reconfiguration message. In some implementations, the UE **102** can include a RRC Connection Reconfiguration Complete message in the RRC Reconfiguration Complete message to respond to the RRC Connection Reconfiguration message. The MN **104** can forward the RRC Connection Reconfiguration Complete message to the SN **106**. The SRB1 can be a NR SRB1. The MeasurementReport message, the RRC Reconfiguration message, and the RRC Reconfiguration Complete message can be in a NR RRC message format. The RRC Connection Reconfiguration message and the RRC Connection Reconfiguration Complete message can be in a EUTRA RRC message format.

(61) In the example above, the RRC Connection Reconfiguration message can include a RadioResourceConfigDedicated IE for an SCG the UE **102** can use to communicate with the SN **106**. In another example, the SN **106** can include a Radio Bearer Configuration (RadioBearerConfig) which configures an SRB3 (i.e., a NR SRB3) or a DRB in the SN Addition Request Acknowledge message. The MN **104** can include the RadioBearerConfig in the RRC Reconfiguration message. The SRB3 or the DRB can be an SCG bearer when the MN **104** does not configure MCG radio resources for the SRB3 or the DRB. The SRB3 or the DRB can be an SCG split bearer if the MN **104** configures MCG radio resources for the SRB3 or the DRB. As an additional example, the SN **106** does not include the RadioBearerConfig in the SN Addition Request Acknowledge message. The MN **104** does not include the RadioBearerConfig in the RRC Reconfiguration message. The MN **104** can generate and include another RadioBearerConfig in the RRC Reconfiguration message.

(62) Further, the RRC Connection Reconfiguration message can include one, some or all of the measurement configuration settings discussed above. In another example, the SN **106** can transmit, to the UE **102** on the SRB3, another RRC Connection Reconfiguration message configuring one, some or all of the at least one measurement configuration settings discussed above.

(63) Now referring to FIG. 9, an example method **900** for reporting SCG failure in dual connectivity can be implemented in the UE **102** of FIG. 1, for example. The method **1000** can be implemented using hardware, software, firmware, or any suitable combination of hardware, software, and firmware.

(64) The method **900** begins at block **902**, where the UE **102** establishes dual connectivity with an MN and a SN (events **202**, **302**, **402**, **502**, **602**, **702**, and **802** of FIGS. 2-8). Next, at block **904**, the UE detects SCG failure (events **220**, **320**, **420**, **520**, **620**, **720**, and **820** of FIGS. 2-8). In response, the UE **102** at block **906** suspends SCG transmissions (events **230**, **330**, **430**, **530**, **630**, **730**, and **830** of FIGS. 2-8). At block **908**, the UE **102** then generates an indication of SCG failure for the MN (events **240**, **340**, and **440** of FIGS. 2-4; events **640**, **740**, and **840** of FIGS. 6-8). At block **910**, the UE **102** transmits the indication of SCG failure to the MN (event **242**, **342**, and **442** of FIGS. 2-

4; events **642, 742, and 842** of FIGS. **6-8**) while the SCG transmissions remain suspended (state **250, 350, 450, 550, 650, 750, and 850** of FIGS. **2-8**).

(65) FIG. **10** is a flow diagram of example method **1000** for providing measurement reports in dual connectivity, which can be implemented in the UE **102** of FIG. **1**. Similar to the method **900** discussed above, the method **1000** can be implemented using hardware, software, firmware, or any suitable combination of hardware, software, and firmware.

(66) The method **1000** begins at block **1002**, where the UE **102** establishes dual connectivity with an MN and a SN (events **202, 302, 402, 502, 602, 702, and 802** of FIGS. **2-8**). Next, at block **1004**, the UE detects SCG failure (events **220, 320, 420, 520, 620, 720, and 820** of FIGS. **2-8**). In response, the UE **102** at block **1006** suspends SCG transmissions (events **230, 330, 430, 530, 630, 730, and 830** of FIGS. **2-8**). The UE **102** at block **1008** generates a measurement report for the MN (events **570, 670, 770, and 870** of FIGS. **5-8**). At block **1010**, the UE **102** transmits the measurement report to the MN (events **572, 672, 772, and 872** of FIGS. **5-8**) while the SCG transmissions remain suspended (state **250, 350, 450, 550, 650, 750, and 850** of FIGS. **2-8**).

(67) The following additional considerations apply to the foregoing discussion.

(68) A user device in which the techniques of this disclosure can be implemented (e.g., the UE **102**) can be any suitable device capable of wireless communications such as a smartphone, a tablet computer, a laptop computer, a mobile gaming console, a point-of-sale (POS) terminal, a health monitoring device, a drone, a camera, a media-streaming dongle or another personal media device, a wearable device such as a smartwatch, a wireless hotspot, a femtocell, or a broadband router. Further, the user device in some cases may be embedded in an electronic system such as the head unit of a vehicle or an advanced driver assistance system (ADAS). Still further, the user device can operate as an internet-of-things (IoT) device or a mobile-internet device (MID). Depending on the type, the user device can include one or more general-purpose processors, a computer-readable memory, a user interface, one or more network interfaces, one or more sensors, etc.

(69) Certain embodiments are described in this disclosure as including logic or a number of components or modules. Modules may be software modules (e.g., code, or machine-readable instructions stored on non-transitory machine-readable medium) or hardware modules. A hardware module is a tangible unit capable of performing certain operations and may be configured or arranged in a certain manner. A hardware module can comprise dedicated circuitry or logic that is permanently configured (e.g., as a special-purpose processor, such as a field programmable gate array (FPGA) or an application-specific integrated circuit (ASIC), a digital signal processor (DSP), etc.) to perform certain operations. A hardware module may also comprise programmable logic or circuitry (e.g., as encompassed within a general-purpose processor or other programmable processor) that is temporarily configured by software to perform certain operations. The decision to implement a hardware module in dedicated and permanently configured circuitry, or in temporarily configured circuitry (e.g., configured by software) may be driven by cost and time considerations.

(70) When implemented in software, the techniques can be provided as part of the operating system, a library used by multiple applications, a particular software application, etc. The software can be executed by one or more general-purpose processors or one or more special-purpose processors.

(71) Upon reading this disclosure, those of skill in the art will appreciate still additional and alternative structural and functional designs for handling SCG failures in DC through the principles disclosed herein. Thus, while particular embodiments and applications have been illustrated and described, it is to be understood that the disclosed embodiments are not limited to the precise construction and components disclosed herein. Various modifications, changes and variations, which will be apparent to those of ordinary skill in the art, may be made in the arrangement, operation and details of the method and apparatus disclosed herein without departing from the spirit and scope defined in the appended claims.

Claims

1. A method in a user device operating in dual-mode (DC) connectivity with a master node (MN) and a secondary node (SN), the method comprising: detecting a failure of a secondary cell group (SCG) associated with the SN; suspending an SCG transmission in response to detecting the failure of the SCG; generating a message related to a status of the SCG for transmission to the MN, the message including a first SCG failure type and a second SCG failure type; and transmitting the message to the MN when the SCG transmission is suspended.
2. The method of claim 1, further comprising: communicating with the MN using a first RAT, and communicating with the SN using a second RAT different from the first RAT.
3. The method of claim 1, wherein generating the message includes generating an indication of the SCG failure.
4. The method of claim 3, wherein: the user device communicates with the SN and the MN using a first radio access technology (RAT) and a second RAT, respectively; and the indication of the SCG failure is related to the first RAT.
5. The method of claim 3, wherein generating the indication of the SCG failure includes generating a message in a radio resource control (RRC) format of the first RAT.
6. The method of claim 3, further comprising: subsequently to suspending the SCG transmission, receiving, from the MN, a command to recover the SCG transmission; and recovering the SCG transmission in response to the command.
7. The method of claim 3, further comprising: generating a measurement report; and transmitting the measurement report to the MN **104** when the SCG transmission is suspended.
8. The method of claim 1, wherein generating the message includes generating a measurement report.
9. The method of claim 8, wherein generating the measurement report is in response to receiving a command to generate the measurement report from the SN.
10. The method of claim 8, wherein generating the measurement report is in response to detecting expiration of a periodic timer.
11. The method of claim 1, wherein transmitting the message to the MN includes transmitting the message using an uplink (UL) Information Transfer message.
12. The method of claim 1, wherein: detecting the failure of the SCG includes detecting the failure at a first RRC module configured to communicate with the SN using a first RAT, suspending the SCG transmission includes suspending the SCG transmission at the first RRC module, and transmitting the message to the MN includes using a second RRC module configured to communicate with the MN using a second RAT; the method further comprising: transmitting an internal message indicating the SCG is suspended from the first RRC module to the second RRC module.
13. The method of claim 1, wherein detecting the failure of the SCG includes transmitting a measurement report to the SN over a signaling radio bearer (SRB) of type 3 (SRB3).
14. The method of claim 1, wherein suspending the SCG transmission includes suspending every signaling radio bearer (SRB) and data radio bearer (DRB) configured to utilize SCG resources provided by the SN.
15. The method of claim 1, wherein: the first SCG failure type indicates one of (i) radio link failure (RLF), (ii) a failure of SCG configuration, (iii) a failure of SCG reconfiguration, or (iv) failure of an SCG integrity check; and the second SCG failure type indicates that a maximum uplink transmission timing difference was exceeded.
16. A user device comprising: processing hardware; a non-transitory computer-readable medium storing instructions that, when executed by the processing hardware, cause the user device to: detect a failure of a secondary cell group (SCG) associated with an SN, suspend an SCG

transmission in response to detecting the failure of the SCG, generate a message related to a status of the SCG for transmission to an MN, the message including a first SCG failure type and a second SCG failure type, and transmit the message to the MN when the SCG transmission is suspended.

17. The user device of claim 16, wherein: to generate the message, the instructions cause the user device to generate an indication of the SCG failure.

18. The user device of claim 16, wherein: the message is one of a measurement report or a UL Information Transfer message.

19. The user device of claim 16, wherein: the first SCG failure type indicates one of (i) radio link failure (RLF), (ii) a failure of SCG configuration, (iii) a failure of SCG reconfiguration, or (iv) failure of an SCG integrity check; and the second SCG failure type indicates that a maximum uplink transmission timing difference was exceeded.
