

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407272
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Leedham; Robert John

Cell assembly and converter comprising a plurality of arms, each having such a cell assembly

Abstract

Each cell of a cell assembly for a converter may include: first and second terminals, switching elements, and a capacitor. The cells are connected in series such that, for each pair of neighbouring cells, the first terminal of a first cell is connected to the second terminal of a second cell. Each cell includes a bypass connected to the first and second terminals that bypasses switching elements in a short circuit configuration and does not bypass the switching elements in an open circuit configuration. Each cell has a cell controller providing control signals to the switching elements to connect the capacitor to the first and second terminals or to bypass the capacitor. The cell controller provides a control signal to the bypass unit of neighbouring cells to change its configuration between the short circuit and open circuit configurations.

Inventors:	Leedham; Robert John (Cambridge, GB)
Applicant:	Maschinenfabrik Reinhausen GmbH (Regensburg, DE)
Family ID:	71401595
Assignee:	MASCHINENFABRIK REINHAUSEN GMBH (Regensburg, DE)
Appl. No.:	18/002067
Filed (or PCT Filed):	May 27, 2021
PCT No.:	PCT/EP2021/064167
PCT Pub. No.:	WO2022/002492
PCT Pub. Date:	January 06, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230231495 A1	Jul. 20, 2023

Foreign Application Priority Data

EP

20182875

Jun. 29, 2020

Publication Classification

Int. Cl.: H02M7/483 (20070101); H02M1/32 (20070101); H02M7/5387 (20070101)

U.S. Cl.:

CPC H02M7/4835 (20210501); H02M1/325 (20210501); H02M7/53871 (20130101);

Field of Classification Search

CPC: H02M (7/00); H02M (7/02); H02M (7/1552); H02M (7/162); H02M (7/219); H02M (7/42); H02M (7/44); H02M (7/48); H02M (7/483); H02M (7/4833); H02M (7/4835); H02M (7/4837); H02M (7/487); H02M (7/49); H02M (7/5387); H02M (7/53871); H02M (1/0067); H02M (1/007); H02M (1/0074); H02M (1/0085); H02M (1/0095); H02M (1/32); H02M (1/325); H02M (1/08); H02M (1/084); H02M (1/0006)

USPC: 363/34; 363/35; 363/37; 363/40-43; 363/50-58; 363/65; 363/71; 363/72; 363/131-134; 323/219; 323/273-276; 323/282-285; 323/351; 361/18; 361/54-61

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6222284	12/2000	Hammond et al.	N/A	N/A
9425705	12/2015	Zargari	N/A	H02M 1/32
2003/0183838	12/2002	Huang	257/107	H03K 17/08148
2010/0056710	12/2009	Oshima	N/A	N/A
2014/0042817	12/2013	Zargari et al.	N/A	N/A
2015/0333660	12/2014	Kim	363/123	H02M 7/483
2016/0056710	12/2015	Häfner et al.	N/A	N/A
2019/0296654	12/2018	Azidehak et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2000060142	12/1999	JP	N/A
2019092333	12/2018	JP	N/A
WO 2010145688	12/2009	WO	N/A
WO 2015136682	12/2014	WO	N/A
WO 2015155112	12/2014	WO	N/A
WO 2019003290	12/2018	WO	N/A

Primary Examiner: Tran; Thienvu V

Assistant Examiner: Rivera-Perez; Carlos O

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS

(1) This application is a U.S. National Phase application under 35 U.S.C. § 371 of International Application No. PCT/EP2021/064167, filed on May 27, 2021, and claims benefit to European Patent Application No. EP 20182875.3, filed on Jun. 29, 2020. The International Application was published in English on Jan. 6, 2022 as WO 2022/002492 A1 under PCT Article 21(2).

FIELD

(2) The present disclosure relates to a cell assembly and a converter comprising a plurality of arms, each having such a cell assembly.

BACKGROUND

(3) Converters may have a plurality of arms, each having a cell assembly.

(4) In electric power transmission systems, converters are used, which may also be referred to as power converters. Usually, these converters comprise a plurality of arms, also known as phase arms. Each arm of these arms comprises a cell assembly and each cell assembly comprises a plurality of cells. Each cell of the plurality of cells comprises a first terminal, a second terminal, switching elements, and a capacitance. The switching elements are adapted to connect the capacitance to the first terminal and to the second terminal and to bypass the capacitance, such that a voltage provided by the capacitance can be selectively provided by the first terminal and the second terminal. The multiple cells are connected in series in such a way that, for each pair of neighbouring cells, the first terminal of a first cell of the pair of neighbouring cells is connected to the second terminal of a second cell of the pair of neighbouring cells.

(5) Even though the cells of the cell assemblies in the state of the art are generally robust in design, a failure of at least a part of a cell, i.e. a cell failure, can occur.

(6) Generally, cells may be adapted such that when a certain switching element fails, the cell is bypassed, since the failed switching element provides a bypass for the cell, such that in certain failure modes the operability of the converter is ensured. In the context of the present disclosure a failure mode is a cause of cell failure, which can also be referred to as one possible way the cell can fail. However, the cell is only bypassed in case the right switching element fails, and, therefore, it is not possible to reliably bypass the cell in different cell failure modes. Further, switching elements, which fail such that the failed switching element provides a bypass, are often inefficient, especially due to high switching losses, and expensive. Particularly in high voltage applications, in which the switching elements perform a plurality of switching operations, switching losses should be kept to a minimum.

(7) A further attempt to ensure the operability of the converter in case of a cell failure is that, each cell may comprise a bypass unit, which is adapted to stay operational in many cell failure modes and ensures that the cell can be bypassed such that a cell failure does not result in a failure of the converter. Usually, each such cell comprises a cell controller unit, which is adapted to provide control signals to the switching elements of the cell and to the bypass unit of the cell. Further, the converter usually comprises a main controller unit, which is adapted to provide control signals to the cell controller units of the cells. In case a cell failure is so severe that the cell controller unit fails or the communication between the cell controller unit and the bypass unit of the cell or between the main controller unit of the converter and the cell controller unit is impaired or no longer possible, control signals can no longer—or at least not reliably—be provided by the cell controller unit to the bypass unit of the cell and/or from the main controller unit of the converter to the cell controller unit. Therefore, in such a case, the controllability of the cell, particularly of the

bypass unit of the cell, and the reliable functioning of the converter is impaired. This is particularly disadvantageous when a cell fails during start-up of the converter.

SUMMARY

(8) In an embodiment, the present disclosure provides a cell assembly that has a plurality of cells. Each cell of the plurality of cells includes: a first terminal, a second terminal, switching elements, and a capacitor. The switching elements are adapted to controllably: connect the capacitor to the first terminal and to the second terminal and bypass the capacitor. The cells of the plurality of cells are connected in series in such a way that, for each pair of neighbouring cells, the first terminal of a first cell of the pair of neighbouring cells is connected to the second terminal of a second cell of the pair of neighbouring cells. Each cell further includes a bypass unit, the bypass unit of each cell being connected to the first terminal and to the second terminal of the cell and adapted to controllably bypass at least one switching element of the switching elements of the cell in a short circuit configuration and to not bypass the at least one switching element in an open circuit configuration. Each cell further includes a cell controller, the cell controller of each cell is adapted to provide control signals to the switching elements of the cell, such that the switching elements controllably connect the capacitor to the first terminal and to the second terminal or the switching elements bypass the capacitor. The cell controller of each cell is also adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit controllably changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Subject matter of the present disclosure will be described in even greater detail below based on the exemplary figures. All features described and/or illustrated herein can be used alone or combined in different combinations. The features and advantages of various embodiments will become apparent by reading the following detailed description with reference to the attached drawings, which illustrate the following:
- (2) FIG. 1 schematically shows a section of a first embodiment of a converter comprising a plurality of arms;
- (3) FIG. 2 schematically shows a first embodiment of a cell of a cell assembly of an arm of the plurality of arms of the converter of which a section is shown in FIG. 1;
- (4) FIG. 3 schematically shows a second embodiment of the cell of the cell assembly of the arm of the plurality of arms of the converter of which a section is shown in FIG. 1;
- (5) FIG. 4 schematically shows a third embodiment of the cell of the cell assembly of the arm of the plurality of arms of the converter of which a section is shown in FIG. 1;
- (6) FIG. 5 schematically shows a section of a second embodiment of the converter comprising a plurality of arms;
- (7) FIG. 6 schematically shows a section of a second embodiment of the converter comprising a plurality of arms;
- (8) FIG. 7 schematically shows a fourth embodiment of a cell of a cell assembly of an arm of the plurality of arms of the converter of which a section is shown in FIG. 5;
- (9) FIG. 8 schematically shows a fifth embodiment of the cell of the cell assembly of the arm of the plurality of arms of the converter of which a section is shown in FIG. 5;
- (10) FIG. 9 schematically shows a sixth embodiment of the cell of the cell assembly of the arm of the plurality of arms of the converter of which a section is shown in FIG. 5;
- (11) FIG. 10 schematically shows a section of a first embodiment of a bypass unit of the first to sixth embodiment of the cell shown in FIGS. 2 to 4 and FIGS. 7 to 9;

- (12) FIG. 11 schematically shows a section of a second embodiment of the bypass unit of the first to sixth embodiment of the cell shown in FIGS. 2 to 4 and FIGS. 7 to 9;
- (13) FIG. 12 schematically shows a section of a third embodiment of the bypass unit of the first to sixth embodiment of the cell shown in FIGS. 2 to 4 and FIGS. 7 to 9;
- (14) FIG. 13 schematically shows a section of a fourth embodiment of the bypass unit of the first to sixth embodiment of the cell shown in FIGS. 2 to 4 and FIGS. 7 to 9; and
- (15) FIG. 14 schematically shows a section of a fifth embodiment of the bypass unit of the first to sixth embodiment of the cell shown in FIGS. 2 to 4 and FIGS. 7 to 9.

DETAILED DESCRIPTION

- (16) Generally, a reliable functioning converter is desirable.
- (17) Therefore, aspects of the present disclosure provide a reliable functioning converter.
- (18) According to a first aspect of the present disclosure, an advantageous cell assembly is provided. This advantageous cell assembly comprises a plurality of cells. Each cell of the plurality of cells comprises a first terminal, a second terminal, switching elements, and a capacitance. The switching elements are adapted to connect the capacitance to the first terminal and to the second terminal and to bypass the capacitance. The cells of the plurality of cells are connected in series in such a way that, for each pair of neighbouring cells, the first terminal of a first cell of the pair of neighbouring cells is connected to the second terminal of a second cell of the pair of neighbouring cells. Each cell further comprises a bypass unit. The bypass unit of each cell is connected to the first terminal and to the second terminal of the cell. Further, the bypass unit of each cell is adapted to bypass at least one switching element of the switching elements of the cell in a short circuit configuration and to not bypass the at least one switching element in an open circuit configuration. Further, each cell comprises a cell controller unit. The cell controller unit of each cell is adapted to provide control signals to the switching elements of the cell, such that the switching elements connect the capacitance to the first terminal and to the second terminal or the switching elements bypass the capacitance. Further, the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.
- (19) A cell assembly may include a plurality of cells. Each cell of the plurality of cells may comprise a half-bridge configuration. In case a cell comprises a half-bridge configuration, the cell can block voltage in one direction. Particularly, in case a cell comprises a half-bridge configuration, the cell forms a two level converter cell either connecting its capacitance to its first terminal and to its second terminal and thereby providing the voltage of its capacitance at its first terminal and second terminal or bypassing the capacitance and thereby not providing the voltage of its capacitance at its first terminal and second terminal. A half-bridge configuration is particularly preferred in case the number of switching elements and power losses occurring during switching operation of the switching elements should be kept low. Further, each cell of the plurality of cells may comprise a full-bridge configuration. In case a cell comprises a full-bridge configuration, the cell can block voltage in two directions. Particularly, in case a cell comprises a full-bridge configuration, the cell forms a three level converter cell connecting its capacitance to its first terminal and to its second terminal in either polarity and thereby providing the voltage of its capacitance at its first terminal and second terminal in either polarity or bypassing the capacitance and thereby not providing the voltage of its capacitance at its first terminal and second terminal. A full-bridge configuration is particularly preferred in case the capacitance should be connected to the first terminal and the second terminal in either polarity. Connecting the capacitance to the first terminal and the second terminal in either polarity improves the controllability of the converter according to the second aspect of the present disclosure.
- (20) Each cell of the plurality of cells may include a first terminal and a second terminal. The first terminal and the second terminal are each adapted to be connected to a terminal of a neighbouring

cell, such that the plurality of cells can be connected in series. Further, each cell of the plurality of cells may include switching elements. Preferably, each switching element of the switching elements is adapted to assume a closed configuration, in which an electric working current can flow through the switching element, and an open configuration, in which the electric working current cannot flow through the switching element. Further, each switching element of the switching elements may be adapted to change between the closed and open configurations, i.e. from the closed configuration to the open configuration and from the open configuration to the closed configuration, during a switching operation. Further, each cell of the plurality of cells comprises a capacitance. Preferably, the capacitance of each cell is provided by one capacitor or by multiple capacitors.

(21) The switching elements may be adapted to connect the capacitance to the first terminal and to the second terminal and to bypass the capacitance. Preferably, the switching elements are adapted such that by performing switching operations of the switching elements, the switching elements can alternately after another connect the capacitance to the first terminal and to the second terminal and to bypass the capacitance, such that the voltage of the capacitance is provided at the first terminal and second terminal and not provided at the first terminal and second terminal one after another.

(22) The cells of the plurality of cells may be connected in series in such a way that, for each pair of neighbouring cells, the first terminal of a first cell of the pair of neighbouring cells is connected to the second terminal of a second cell of the pair of neighbouring cells. Due to the series connection of the cells, coordinated switching operations of the switching elements allows to selectively connect the capacitances of the cells to the first and second terminals of the cells, which allows to provide a stepped voltage waveform that approximates very closely the waveform of a sine wave with only a minimum of harmonic distortion at each arm of the converter and thereby at each AC (alternating current) terminal of the converter.

(23) Each cell may further includes a bypass unit. The bypass unit of each cell is connected to the first terminal and to the second terminal of the cell and adapted to bypass at least one switching element of the switching elements of the cell in a short circuit configuration and to not bypass the at least one switching element in an open circuit configuration. Depending on the configuration of the cell, such as the half-bridge configuration and the full-bridge configuration, the bypass unit may be adapted to bypass one switching element or more than one switching element. In an embodiment of the cell assembly, in which the cell comprises a half-bridge configuration, the bypass unit may be adapted to bypass one switching element. Further, in an embodiment of the cell assembly, in which the cell comprises a full-bridge configuration, the bypass unit may be adapted to bypass two switching elements. Therefore, the bypass unit may be adapted to selectively bypass the at least one switching element, and, thereby, provides a bypass of the cell in case of a cell failure. Regarding the terminology used in this paragraph with respect to bypassing at least one switching element, it is noted that the bypass unit is connected to the first terminal and to the second terminal, and, thereby, the bypass unit directly connects the first terminal and the second terminal to each other essentially in the fashion of a short circuit when the bypass unit is in the short circuit configuration. In case one switching element is connected to the first terminal and to the second terminal, the bypass unit is regarded to be adapted to bypass this switching element. In case two switching elements are connected to the first terminal and to the second terminal, for example in a series connection to each other, the bypass unit is regarded to be adapted to bypass the two switching elements. Therefore, the bypass unit provides a means for bypassing the cell when the bypass unit is in the short circuit configuration. When, in the context of the present disclosure, it is referred to that the bypass unit bypasses the cell, it is preferably meant that the bypass unit is in the short circuit configuration, i.e. a direct connection between the first terminal and the second terminal is provided by the bypass unit essentially in the fashion of a short circuit.

(24) Each cell may further include a cell controller unit. The cell controller unit of each cell is

adapted to provide control signals to the switching elements of the cell, such that the switching elements connect the capacitance to the first terminal and to the second terminal or the switching elements bypass the capacitance. Since the cell controller unit of each cell is adapted to provide control signals to the switching elements of the cell, such that the switching elements connect the capacitance to the first terminal and to the second terminal or the switching elements bypass the capacitance, the cell controller unit allows coordinated switching operations at the switching elements of the cell, such that the voltage of the capacitance can selectively be provided at the first terminal and second terminal and not provided at the first terminal and second terminal in a controlled manner.

(25) The cell controller unit of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells. Since the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, the cell controller unit of each cell can control the bypass unit of at least one of its neighbouring cells. Preferably, the cell controller unit of each cell is adapted to provide a control signals to the bypass unit of one of its neighbouring cells. Further, it is particularly preferred that the cell controller unit of each cell is adapted to provide control signals to two of its neighbouring cells. The cell controller unit of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Since the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the cell controller unit of each cell can control the bypass unit of at least one of the neighbouring cells of the cell the controller unit is a part of. For example, in case a cell failure is so severe that the cell controller unit fails or the communication between the cell controller unit and the bypass unit of the cell or between the main controller unit of the converter and the cell controller unit is impaired or no longer possible, control signals can be provided by the cell controller unit of a neighbouring cell of the failed cell to the bypass unit of the failed cell. Therefore, the controllability of the failed cell, particularly of the bypass unit of the failed cell, and, therefore, the reliable functioning of the converter is improved. This is particularly advantageous when a cell fails during start-up of the converter.

(26) Preferably, the bypass unit may comprise at least one thyristor. In case the bypass unit comprises at least one thyristor, the cell controller unit of each cell may be adapted to provide a control signal to the at least one thyristor of the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Especially, when the cell controller unit of each cell is adapted to provide a control signal to the at least one thyristor of the bypass unit, the configuration of the at least one thyristor can be changed from a short circuit configuration of the at least one thyristor to an open circuit configuration of the at least one thyristor and from the open circuit configuration of the at least one thyristor to the short circuit configuration of the at least one thyristor based on the control signals received by the at least one thyristor from the cell controller unit.

(27) Particularly, since the bypass unit of a cell can be controlled by a cell controller unit of a neighbouring cell, the reliability of the converter is improved. Further, problems arising during start-up of the converter when a cell fails or a communication with a cell fails are significantly reduced, which also improves the reliability of the converter. Further, since the bypass unit of a cell can be controlled by a cell controller unit of a neighbouring cell, the configuration of the bypass unit can be changed by the cell controller unit of the neighbouring cell during start-up of the converter, which also allows testing of the cells during start-up of the converter. The testing of the cells during start-up allows to identify failed cells and disable, e.g. bypass, the failed cells during

start-up, such that the failed cells can stay disabled during the operation of the converter.

(28) Implementations of the cell assembly according to the first aspect of the present disclosure, therefore, improve the reliable functioning of a converter.

(29) Preferably, the cell controller unit of each cell is adapted to provide control signals to the bypass unit of the cell the cell controller is a part of, such that the bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. When the cell controller unit of each cell is adapted to provide control signals to the bypass unit of the cell the cell controller is a part of, such that the bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the configuration of the bypass unit of the cell can be changed by the cell controller unit of the same cell.

(30) According to a preferred embodiment of the cell assembly, each cell further comprises a power supply unit, wherein the power supply unit of each cell is adapted to provide electrical power to the bypass unit of at least one of its neighbouring cells. Since the power supply unit of each cell is adapted to provide electrical power to the bypass unit of at least one of its neighbouring cells, the power supply of the bypass unit of the at least one of the neighbouring cells is ensured even if the power supply unit of the at least one neighbouring cells has failed in case of a cell failure.

Preferably, each power supply unit is adapted to provide electrical power to the bypass unit of the cell the power supply unit is a part of. Further, it is preferred that each power supply unit is adapted to provide electrical power to the controller unit of the cell the power supply unit is a part of. Particularly, each power supply unit is adapted to provide electrical power to the capacitance of the cell the power supply unit is a part of.

(31) According to a preferred embodiment of the cell assembly, the bypass unit of each cell comprises a memory unit. Preferably, the memory unit is adapted to store information on the configuration of the bypass unit, e.g. status information of the bypass unit, such that by accessing the memory unit, e.g. from the cell controller unit of the cell or from a cell controller unit of a neighbouring cell or from the main controller unit of the converter, the configuration of the bypass unit can be inferred. Preferably, the memory unit is adapted to provide information on the configuration of the bypass unit, even after no electrical power has been provided by the power supply unit of the cell to the bypass unit of the cell for a certain period of time. Hence, the memory unit allows to infer the configuration of the bypass unit prior to the period of time during which no electrical power has been provided by the power supply unit of the cell to the bypass unit of the cell. After this period of time, the bypass unit can then be changed back to or be kept in the configuration of the bypass unit prior to the period of time. In a particular preferred embodiment of the cell assembly, the memory unit of the bypass unit of each cell may preserve the configuration of the bypass unit of the cell from prior the period of time during the period of time such that during and after the period of time the bypass unit maintains its configuration from prior to the period of time. This can, for example, be achieved, when the memory unit comprises a latching relay, as described further below.

(32) According to a preferred embodiment of the cell assembly, the memory unit of each cell is connected to the cell controller unit of the cell, such that a status information of the bypass unit, which represents the configuration of the bypass unit, can be written to the memory unit by the cell controller unit of the cell. The control signals received by the bypass unit from the cell controller unit may represent status information, which can be written to the memory unit by the cell controller unit of the cell. The status information may represent the configuration of the bypass unit, particularly the current configuration of the bypass unit and/or the desired configuration of the bypass unit. In case the status information represents the configuration of the bypass unit, the status information may also be called status information of the bypass unit. Preferably, the current configuration of the bypass unit is the configuration in which the bypass unit is currently in.

Similarly, it is preferred that the desired configuration of the bypass unit may be the configuration in which the bypass unit needs to be in, such that the at least one switching element of the switching elements is bypassed or not bypassed, depending on the situation.

(33) According to a preferred embodiment of the cell assembly, the memory unit comprises a data storage unit. Preferably, the data storage unit is adapted to retain digital data, especially the status information of the bypass unit.

(34) According to a preferred embodiment of the cell assembly, the data storage unit is a non-volatile data storage unit. A non-volatile data storage unit is particularly preferred if the status information of the bypass unit is to be retrieved after the memory unit of the cell has been power cycled.

(35) According to a preferred embodiment of the cell assembly, the memory unit comprises a latching relay. A latching relay is particularly preferred when the memory unit of the bypass unit of each cell may preserve the configuration of the bypass unit of the cell from prior a period of time during which no electrical power has been provided by the power supply unit of the cell to the bypass unit of the cell, during this period of time such that during and after the period of time the bypass unit maintains its configuration from prior to the period of time. The latching relay may comprise input terminals adapted to receive control signals from the cell controller unit and normally open contact terminals adapted to be in an open configuration and in a closed configuration and changed from the open configuration to the closed configuration and from the closed configuration to the open configuration depending on the control signals received from the cell controller unit, such that the configuration of a thyristor can be changed from a short circuit configuration to an open circuit configuration and from the open circuit configuration to the short circuit configuration.

(36) According to a preferred embodiment of the cell assembly, the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Since the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of one of its neighbouring cells, such that the bypass unit of the one of the neighbouring cells changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the cell controller unit of each cell can control the bypass unit of the one of the neighbouring cells of the cell the controller unit is a part of. It is particularly preferred that the bypass unit of each cell is provided with control signals from the cell controller unit of the cell and in addition provided with control signals from the cell controller unit of one neighbouring cell. Therefore, in case the cell controller unit of a cell fails or the communication between the cell controller unit and the bypass unit of the cell or between the main controller unit of the converter and the cell controller unit of the cell is impaired or no longer possible, control signals can be provided by the cell controller unit of the one neighbouring cell of the failed cell to the bypass unit of the failed cell. It is preferred that when the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the power supply unit of each cell is adapted to provide electrical power to the bypass unit of the one of the neighbouring cells.

(37) According to a preferred embodiment of the cell assembly, the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of two of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Since the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of two of its neighbouring cells, such that the respective bypass unit changes its configuration from the short

circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the cell controller unit of each cell can control the bypass unit of the two of the neighbouring cells of the cell the controller unit is a part of. It is particularly preferred that the bypass unit of each cell is provided with control signals from the cell controller unit of the cell and in addition provided with control signals from the cell controller unit of two neighbouring cells. Therefore, in case the cell controller unit of a cell fails or the communication between the cell controller unit and the bypass unit of the cell or between the main controller unit of the converter and the cell controller unit of the cell is impaired or no longer possible, control signals can be provided by the cell controller unit of the two neighbouring cells of the failed cell to the bypass unit of the failed cell. It is preferred that when the cell controller unit of each cell is adapted to provide a control signal to the bypass unit of two of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, the power supply unit of each cell is adapted to provide electrical power to the bypass unit of the two neighbouring cells.

(38) According to a preferred embodiment of the cell assembly, the bypass unit of each cell is adapted to bypass one switching element of the switching elements of the cell in the short circuit configuration and to not bypass the one switching element in the open circuit configuration. It is preferred that the bypass unit of each cell is adapted to bypass one switching element of the switching elements of the cell in the short circuit configuration and to not bypass the one switching element in the open circuit configuration in cases when the cell comprises a half-bridge configuration.

(39) According to a preferred embodiment of the cell assembly, the bypass unit of each cell is adapted to bypass two switching elements of the switching elements of the cell in the short circuit configuration and to not bypass the two switching elements in the open circuit configuration. It is preferred that the bypass unit of each cell is adapted to bypass two switching elements of the switching elements of the cell in the short circuit configuration and to not bypass the two switching elements in the open circuit configuration in cases when the cell comprises a full-bridge configuration.

(40) According to a preferred embodiment of the cell assembly, the switching elements of each cell comprise two switching elements, which are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a first switching element of the two switching elements is connected to a first terminal of the capacitance and a second switching element of the two switching elements is connected to a second terminal of the capacitance at a second connection point, which is connected to the second terminal of the cell. When the switching elements of each cell comprise two switching elements, which are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a first switching element of the two switching elements is connected to a first terminal of the capacitance and a second switching element of the two switching elements is connected to a second terminal of the capacitance at a second connection point, which is connected to the second terminal of the cell, a half-bridge configuration of the cell can be provided.

(41) According to a preferred embodiment of the cell assembly, the switching elements of each cell comprise four switching elements, wherein a first switching element of the four switching elements and a second switching element of the four switching elements are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a third switching element of the four switching elements and a fourth switching element of the four switching elements are connected to one another at a second connection point, which is connected to the second terminal of the cell, wherein the first switching element and the third switching element are connected to one another at a third connection point, which is connected to a first terminal of the capacitance of the cell and the second switching element and the fourth switching element are connected to one another at a fourth connection point, which is connected to a second terminal of

the capacitance of the cell. When the switching elements of each cell comprise four switching elements, wherein a first switching element of the four switching elements and a second switching element of the four switching elements are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a third switching element of the four switching elements and a fourth switching element of the four switching elements are connected to one another at a second connection point, which is connected to the second terminal of the cell, wherein the first switching element and the third switching element are connected to one another at a third connection point, which is connected to a first terminal of the capacitance of the cell and the second switching element and the fourth switching element are connected to one another at a fourth connection point, which is connected to a second terminal of the capacitance of the cell, a full-bridge configuration can be provided.

(42) According to a preferred embodiment of the cell assembly, each switching element of the at least one switching element of each cell comprises a transistor. Further, each switching element of the at least one switching element of each cell may comprise an insulated gate bipolar transistor (IGBT), a metal oxide semiconductor field effect transistor (MOSFET), a high electron mobility transistor (HEMT) and/or a thyristor. Preferably, each switching element of the at least one switching element of each cell is formed of Silicon (Si), Silicon Carbide (SiC) and/or Gallium Arsenide (GAN).

(43) According to a second aspect of the present disclosure, a converter with improved reliability is provided. The converter comprises a plurality of arms. Each arm of the plurality of arms comprises a cell assembly according to the first aspect of the present disclosure.

(44) The converter comprises a plurality of arms. Preferably, the converter comprises three arms. However, it is also preferred that the converter comprises six arms. In any case, the number of arms of the converter can be chosen depending on the application of the converter. Further, the converter may comprise one arm per phase of the converter. Alternatively, the converter may comprise two or more arms per phase of the converter. Preferably, the number of arms per phase, i.e. one arm per phase, two arms per phase or more than two arms per phase, can be chosen depending on the application of the converter. Each arm of the plurality of arms comprises a cell assembly according to the first aspect of the present disclosure.

(45) Preferably, the converter according to the second aspect of the present disclosure is a multi level converter, preferably a modular multilevel converter (MMC). It is particularly preferred that the converter is a three phase modular multilevel converter. Preferably, the converter according to the second aspect of the present disclosure is adapted to convert electric power from high voltage alternating current to high voltage direct current. Further, it is preferred that the converter according to the second aspect of the present disclosure is adapted to convert electric power from high voltage direct current to high voltage alternating current. Further, the converter according to the second aspect of the present disclosure can be adapted to convert electric power from high voltage alternating current to high voltage direct current and from high voltage direct current to high voltage alternating current. In case the converter is adapted to convert electric power from high voltage direct current to high voltage alternating current, from high voltage alternating current to high voltage direct current, or from high voltage alternating current to high voltage direct current and from high voltage direct current to high voltage alternating current, the converter can be referred to as a high voltage alternating current to high voltage direct current (HVDC) converter. Particularly, in embodiments, in which each switching element of the at least one switching element of each cell comprises a transistor, the converter according to the second aspect of the present disclosure can be referred to as a voltage source converter (VSC). It is preferred that the converter according to the second aspect of the present disclosure is adapted for medium voltage (MV) drive applications. In a particularly preferred embodiment of the converter according to the second aspect of the present disclosure, the converter forms a converter of a static synchronous compensator (STATCOM). It is particularly preferred that in case the converter forms a converter

of a static synchronous compensator, the static synchronous compensator forms a part of a unified power flow controller (UPFC). In a preferred embodiment, the converter is a single phase modular multilevel converter. In a further preferred embodiment, the converter is a matrix converter.

(46) The features, technical effects and/or advantages described in connection with the first aspect of the present disclosure also apply to the second aspect of the present disclosure at least in an analogous manner, so that no corresponding repetition is made here. Even though the method steps are described in a certain order, implementation forms according to the present disclosure are not restricted to this order. Rather, the individual method steps can be carried out in any meaningful sequence.

(47) Further features, advantages and application possibilities of the present disclosure may be derived from the following description of exemplary embodiments and/or the figures. Thereby, all described and/or visually depicted features for themselves and/or in any combination may form an advantageous subject matter and/or features of the present disclosure independent of their combination in the individual claims or their dependencies. Furthermore, in the figures, same reference signs may indicate same or similar objects.

(48) FIG. 1 shows a section of a first embodiment of a converter **1** comprising six arms **3**. Each arm **3** comprises a cell assembly **5** and an inductance **7**. Each cell assembly **5** comprises a plurality of cells **9**. Each arm **3** is connected to a DC (direct current) terminal **11** of two DC terminals **11** and to an AC (alternating current) terminal **13** of three AC terminals **13**. The arms **3** form three arm pairs, wherein each arm pair of the arm pairs comprises a first arm **3** and a second arm **3**, wherein the first arm **3** and the second arm **3** are connected to the same AC terminal **13** and to different DC terminals **11**. Further, each arm pair is connected to a different AC terminal **13**.

(49) FIG. 2 shows a first embodiment of a cell **9** of a cell assembly **5** of an arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 1. The cell **9** comprises a first terminal **15** and a second terminal **17**. The plurality of cells **9** of each cell assembly **5** shown in FIG. 1 are connected in series in such a way that, for each pair of neighbouring cells **9**, the first terminal **15** of a first cell **9** of the pair of neighbouring cells **9** is connected to the second terminal **17** of a second cell **9** of the pair of neighbouring cells **9**.

(50) Further, the cell **9** comprises two switching elements **19** and a capacitance **21**. The switching elements **19** are adapted to connect the capacitance **21** to the first terminal **15** and to the second terminal **17** and to bypass the capacitance **21**, such that a voltage provided by the capacitance V_c can be selectively provided as a cell output voltage V_o by the first terminal **15** and the second terminal **17**. Each of the switching elements **19** shown in FIG. 2 comprises an insulated-gate bipolar transistor (IGBT) **23** and a diode **25**. The two switching elements **19** are connected to one another at a first connection point. The first connection point is connected to the first terminal **15** of the cell **9**. A first switching element **19** of the two switching elements **19** is connected to a first terminal of the capacitance **21** and a second switching element **19** of the two switching elements **19** is connected to a second terminal of the capacitance **21** at a second connection point. The second connection point is connected to the second terminal **17** of the cell **9**.

(51) The cell **9** further comprises a bypass unit (bypass) **27**. The bypass unit **27** is connected to the first terminal **15** and to the second terminal **17** of the cell **9**. Further, the bypass unit **27** is adapted to be in a short circuit configuration and in an open circuit configuration. The bypass unit **27** is adapted to switch back and forth between these two configurations. In the short circuit configuration, the bypass unit **27** bypasses the lower switching element **19** of the two switching elements **19** shown in FIG. 2. In the open circuit configuration, the bypass unit **27** does not bypass the lower switching element **19** of the two switching elements **19** shown in FIG. 2.

(52) Further, the cell **9** comprises a cell controller unit (cell controller) **29**. The cell controller unit **29** of the cell **9** is adapted to provide control signals to the switching elements **19** of the cell **9**, such that the switching elements **19** connect the capacitance **21** to the first terminal **15** and to the second terminal **17** or the switching elements **19** bypass the capacitance **21**. Further, the cell controller unit

29 of the cell **9** is adapted to provide control signals to the bypass unit **27** of the cell **9**, such that the bypass unit **27** of the cell **9** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the cell controller unit **29** of the cell **9** is adapted to provide a control signal to the bypass unit **27** of at least one of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Particularly, the cell controller unit **29** of the cell **9** may be adapted to provide a control signal to the bypass unit **27** of one of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the cell controller unit **29** of the cell **9** may alternatively be adapted to provide a control signal to the bypass unit **27** of two of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.

(53) The cell **9** further comprises a power supply unit (power supply) **31**. The power supply unit **31** is adapted to provide electrical power to the bypass unit **27** of the cell **9**, to the controller unit **29** of the cell **9**, and to the capacitance **21** of the cell **9**. The power supply unit **31** is further adapted to provide electrical power to the bypass unit **27** of at least one of its neighbouring cells **9**.

(54) FIG. 3 shows a second embodiment of the cell **9** of the cell assembly **5** of the arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 1. The second embodiment of the cell **9** shown in FIG. 3 is essentially identical to the first embodiment of the cell **9** shown in FIG. 2. However, the bypass unit **27** of the second embodiment of the cell **9** comprises two thyristors **33**. Both thyristors **33** are connected to the first terminal **15** and to the second terminal **17**. A first thyristor **33** of the two thyristors **33** is connected with its anode to the first terminal **15** and with its cathode to the second terminal **17**. A second thyristor **33** of the two thyristors **33** is connected with its cathode to the first terminal **15** and with its anode to the second terminal **17**.

(55) Each thyristor **33** of the two thyristors **33** is adapted to bypass the lower switching element **19** of the two switching elements **19** shown in FIG. 3 in a short circuit configuration and to not bypass the lower switching element **19** in an open circuit configuration. Each thyristor **33** of the two thyristors **33** is adapted to switch back and forth between these two configurations. Due to the two thyristors **33**, the bypass unit **27** is adapted to be in a first short circuit configuration, in a second short circuit configuration, and in an open circuit configuration. In the first short circuit configuration of the bypass unit **27**, the left thyristor **33** in FIG. 3 is in the short circuit configuration and bypasses the lower switching element **19** and the right thyristor **33** in FIG. 3 is in an open circuit configuration and does not bypass the lower switching element **19**. Further, in the second short circuit configuration of the bypass unit **27**, the right thyristor **33** in FIG. 3 is in a short circuit configuration and bypasses the lower switching element **19** and the left thyristor **33** in FIG. 3 is in an open circuit configuration and does not bypass the lower switching element **19**. Further, in the open circuit configuration of the bypass unit **27**, the left thyristor **33** and the right thyristor **33** in FIG. 3 are both in the open circuit configuration and both do not bypass the lower switching element **19**. Due to the two thyristors **33**, the bypass unit **27** can selectively bypass the lower switching element **19** in two directions, i.e. from the first terminal **15** to the second terminal **17** and from the second terminal **17** to the first terminal **15**.

(56) Further, the cell controller unit **29** is connected to the gates of the two thyristors **33** and is adapted to provide control signals to the two thyristors **33**, such that the configuration of each of the two thyristors **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. Thereby, the configuration of the bypass unit **27** can be changed from the first short circuit configuration to the second short circuit configuration, from the second short circuit configuration to the first short

circuit configuration, from the first short circuit configuration to the open circuit configuration, from the open circuit configuration to the first short circuit configuration, from the second short circuit configuration to the open circuit configuration, and from the open circuit configuration to the second short circuit configuration. Hence, the direction in which the bypass unit **27** bypasses the lower switching element **19** can be controlled.

(57) FIG. **4** shows a third embodiment of the cell **9** of the cell assembly **5** of the arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. **1**. The third embodiment of the cell **9** shown in FIG. **4** is essentially identical to the first embodiment of the cell **9** shown in FIG. **2**. However, the cell **9** comprises the first terminal **15**, the second terminal **17**, and a third terminal **35**, which is connected to the first terminal of the capacitance **21**. The first terminal **15** and the second terminal **17** are adapted as described above in connection with the other embodiments. For example, the voltage provided by the capacitance V_c can be selectively provided as a cell output voltage V_o by the first terminal **15** and the second terminal **17**. Further, the bypass unit **27** of the third embodiment of the cell **9** comprises three thyristors **33**. A first thyristor **33** of the three thyristors **33** is connected to the first terminal **15** of the cell **9** and to the second terminal **17** of the cell **9**, a second thyristor **33** of the three thyristors **33** is connected to the first terminal **15** of the cell **9** and to the third terminal **35** of the cell **9**, and a third thyristor **33** of the three thyristors **33** is connected to the second terminal **17** of the cell **9** and to the third terminal **35** of the cell **9**. The first thyristor **33** is connected with its anode to the second terminal **17** and with its cathode to the first terminal **15**. The second thyristor **33** of the three thyristors **33** is connected with its anode to the first terminal **15** and with its cathode to the third terminal **35**. The third thyristor **33** of the three thyristors **33** is connected with its anode to the third terminal **35** and with its cathode to the second terminal **17**.

(58) Further, the first thyristor **33** is and the second and third thyristors **33** are adapted to bypass the lower switching element **19** of the two switching elements **19** shown in FIG. **4** in a short circuit configuration and to not bypass the lower switching element **19** in an open circuit configuration. The thyristors **33** are adapted to switch back and forth between these configurations. Due to the three thyristors **33**, the bypass unit **27** is adapted to be in a first short circuit configuration, in a second short circuit configuration, and in an open circuit configuration. In the first short circuit configuration of the bypass unit **27**, the first thyristor **33** in FIG. **4** is in the short circuit configuration and bypasses the lower switching element **19** and the second and third thyristors **33** in FIG. **4** are in an open circuit configuration and do not bypass the lower switching element **19**. Further, in the second short circuit configuration of the bypass unit **27**, the second and third thyristors **33** in FIG. **4** are in a short circuit configuration and bypasses the lower switching element **19** and the first thyristor **33** in FIG. **4** is in an open circuit configuration and does not bypass the lower switching element **19**. Further, in the open circuit configuration of the bypass unit **27**, the first, second and third thyristors **33** in FIG. **4** are in the open circuit configuration and do not bypass the lower switching element **19**. Due to the three thyristors **33**, the bypass unit **27** can selectively bypass the lower switching element **19** in two directions, i.e. from the first terminal **15** to the second terminal **17** and from the second terminal **17** to the first terminal **15**.

(59) Further, the cell controller unit **29** is connected to the gates of the three thyristors **33** and is adapted to provide control signals to the three thyristors **33**, such that the configuration of each of the three thyristors **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. Thereby, the configuration of the bypass unit **27** can be changed from the first short circuit configuration to the second short circuit configuration, from the second short circuit configuration to the first short circuit configuration, from the first short circuit configuration to the open circuit configuration, from the open circuit configuration to the first short circuit configuration, from the second short circuit configuration to the open circuit configuration, and from the open circuit configuration to the second short circuit configuration. Hence, the direction in which the bypass unit **27** bypasses

the lower switching element **19** can be controlled.

(60) FIG. 5 shows a section of a second embodiment of the converter **1** comprising three arms **3**. Each arm **3** comprises a cell assembly **5** and an inductance **7**. Each cell assembly **5** comprises a plurality of cells **9**. Each arm **3** is connected to two AC terminals **13** of three AC terminals **13**. The arms **3** form three arm pairs, wherein each arm pair of the arm pairs comprises a first arm **3** and a second arm **3**, wherein the first arm **3** and the second arm **3** are connected to the same AC terminal **13**. Further, each arm pair is connected to a different same AC terminal **13**.

(61) FIG. 6 shows a section of a third embodiment of the converter **1**. The converter comprises three sub-converters **2**. Each sub-converter comprises three arms **3**. Therefore, the converter **1** can be regarded as comprising nine arms **3**. Each arm **3** comprises a cell assembly **5** and an inductance **7**. Each cell assembly **5** comprises a plurality of cells **9**. Each arm **3** is connected to a first AC terminal **13** of three first AC terminals **13** via an inductance **7** and to a second AC terminal **13** of three second AC terminals **13** via an inductance **7**. The arms **3** form three sets of arms, wherein each set of arms comprises three arms **3** and can be regarded as forming a section of one of the three sub-converters **2**. The arms **3** of each set of arms are connected to the same first AC terminal **13** and are connected to different second AC terminals **13**.

(62) Even though two cells **9** of a pair of cells **9** comprising a first cell **9** of a first cell assembly **5** of a first arm **3** and a second cell **9** of a second cell assembly **5** of a second arm **3** are not connected to each other in series within the same cell assembly **5**, the first cell **9** and the second cell **9** may be connected to each other and/or interact with each other in the same way as the cells **9** of a pair of neighbouring cells **9** are connected to each other and/or interact with each other according to the present disclosure. For example, the cell controller unit **29** of the first cell **9** may be adapted to provide a control signal to the bypass unit **27** of the second cell **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. The above may apply to each pair of cells **9** comprising cells **9** not belonging to the same cell assembly **5** and can also apply to each pair of cells **9** belonging to the same cell assembly **5**, however, not being neighbouring cells **9**. Further, the above may apply to each feature and feature combination, individually and in combination, in connection with two neighbouring cells, and in particular for each embodiment of the present disclosure.

(63) FIG. 7 shows a fourth embodiment of a cell **9** of a cell assembly **5** of an arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 5. The fourth embodiment of the cell **9** shown in FIG. 7 can also form a cell **9** of a cell assembly **5** of an arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 6. The cell **9** comprises the first terminal **15** and the second terminal **17**. The plurality of cells **9** of each cell assembly **5** shown in FIG. 5 and in FIG. 6 are connected in series in such a way that, for each pair of neighbouring cells **9**, the first terminal **15** of a first cell **9** of the pair of neighbouring cells **9** is connected to the second terminal **17** of a second cell **9** of the pair of neighbouring cells **9**.

(64) The cell **9** comprises four switching elements **19** and a capacitance **21**. The switching elements **19** are adapted to connect the capacitance **21** to the first terminal **15** and to the second terminal **17** and to bypass the capacitance **21**, such that a voltage provided by the capacitance V_c can be selectively provided as a cell output voltage V_o by the first terminal **15** and the second terminal **17**. Compared to the first embodiment of the cell **9** shown in FIG. 2, the four switching elements **19** are adapted to connect the capacitance **21** to the first terminal **15** and to the second terminal **17** such that the voltage provided by the capacitance V_c can be selectively provided as the cell output voltage V_o by the first terminal **15** and the second terminal **17**, particularly with alternating polarity. For example, V_o may successively be equal to V_c and $-V_c$.

(65) Each of the switching elements **19** shown in FIG. 7 comprises an IGBT **23** and a diode **25**. A first switching element **19** of the four switching elements **19** and a second switching element **19** of the four switching elements **19** are connected to one another at a first connection point. The first

connection point is connected to the first terminal **15** of the cell **9**. The first switching element **19** is connected to the first terminal of the capacitance **21** and the second switching element **19** is connected to the second terminal of the capacitance **21**. A third switching element **19** of the four switching elements **19** and a fourth switching element **19** of the four switching elements **19** are connected to one another at a second connection point. The second connection point is connected to the second terminal **17** of the cell **9**. The third switching element **19** is connected to the first terminal of the capacitance **21** and the fourth switching element **19** is connected to the second terminal of the capacitance **21**. The first switching element **19** and the third switching element **19** are connected to one another at a third connection point, which is connected to the first terminal of the capacitance **21**. The second switching element **19** and the fourth switching element **19** are connected to one another at a fourth connection point, which is connected to the second terminal of the capacitance **21**.

(66) The cell **9** further comprises a bypass unit **27**. The bypass unit **27** is connected to the first terminal **15** and to the second terminal **17**. Further, the bypass unit **27** is adapted to be in a short circuit configuration and in an open circuit configuration. The bypass unit **27** is adapted to switch back and forth between these two configurations. In the short circuit configuration, the bypass unit **27** bypasses the first and third switching elements **19** as well as the second and fourth switching elements **19** shown in FIG. 7. In the open circuit configuration, the bypass unit **27** does not bypass the first, second, third, and fourth switching elements **19**.

(67) Further, the cell **9** comprises a cell controller unit **29**. The cell controller unit **29** of the cell **9** is adapted to provide control signals to the switching elements **19** of the cell **9**, such that the switching elements **19** connect the capacitance **21** to the first terminal **15** and to the second terminal **17** or the switching elements **19** bypass the capacitance **21**. Further, the cell controller unit **29** of the cell **9** is adapted to provide control signals to the bypass unit **27** of the cell **9**, such that the bypass unit **27** of the cell **9** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the cell controller unit **29** of the cell **9** is adapted to provide control signals to the bypass unit **27** of at least one of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Particularly, the cell controller unit **29** of the cell **9** may be adapted to provide control signals to the bypass unit **27** of one of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the cell controller unit **29** of the cell **9** may alternatively be adapted to provide control signals to the bypass unit **27** of two of its neighbouring cells **9**, such that the respective bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.

(68) The cell **9** further comprises a power supply unit **31**. The power supply unit **31** is adapted to provide electrical power to the bypass unit **27** of the cell **9**, to the controller unit **29** of the cell **9**, and to the capacitance **21** of the cell **9**. The power supply unit **31** is further adapted to provide electrical power to the bypass unit **27** of at least one of its neighbouring cells **9**.

(69) FIG. 8 shows a fifth embodiment of the cell **9** of the cell assembly **5** of the arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 5. The fifth embodiment of the cell **9** shown in FIG. 8 can also form a cell **9** of a cell assembly **5** of an arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. 6. The fifth embodiment of the cell **9** shown in FIG. 8 is essentially identical to the fourth embodiment of the cell **9** shown in FIG. 7. However, the bypass unit **27** of the fifth embodiment of the cell **9** comprises two thyristors **33**. Both thyristors **33** are connected to the first terminal **15** and to the second terminal **17**. A first thyristor **33** of the two thyristors **33** is connected with its anode to the first terminal **15** and with its cathode to the second terminal **17**. A second thyristor **33** of the two thyristors **33** is connected with its cathode

to the first terminal **15** and with its anode to the second terminal **17**.

(70) Each thyristor **33** is adapted to be in a short circuit configuration, in which the thyristor **33** bypasses the first and third switching elements **19** as well as the second and fourth switching elements **19**. Further, each thyristor **33** is adapted to be in an open circuit configuration, in which the thyristor **33** does not bypass the first, second, third, and fourth switching elements **19**. Each thyristor **33** is adapted to switch back and forth between the short circuit configuration and the open circuit configuration.

(71) Due to the two thyristors **33**, the bypass unit **27** is adapted to be in a first short circuit configuration, in a second short circuit configuration, and in an open circuit configuration. In the first short circuit configuration of the bypass unit **27**, the first thyristor **33** in FIG. **8** is in the short circuit configuration and bypasses the first, second, third, and fourth switching elements **19** and the second thyristor **33** in FIG. **8** is in an open circuit configuration and does not bypass the first, second, third, and fourth switching elements **19**. Further, in the second short circuit configuration of the bypass unit **27**, the second thyristor **33** in FIG. **8** is in a short circuit configuration and bypasses the first, second, third, and fourth switching elements **19** and the first thyristor **33** in FIG. **8** is in an open circuit configuration and does not bypass the first, second, third, and fourth switching elements **19**. Further, in the open circuit configuration of the bypass unit **27**, the first thyristor **33** and the second thyristor **33** in FIG. **8** are both in the open circuit configuration and both do not bypass the first, second, third, and fourth switching elements **19**. Due to the two thyristors **33**, the bypass unit **27** can selectively bypass the first, second, third, and fourth switching elements **19** in two directions, i.e. from the first terminal **15** to the second terminal **17** and from the second terminal **17** to the first terminal **15**.

(72) Further, with respect to FIG. **8**, the cell controller unit **29** is connected to the gates of the two thyristors **33** and is adapted to provide control signals to the two thyristors **33**, such that the configuration of each of the two thyristors **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. Thereby, the configuration of the bypass unit **27** can be changed from the first short circuit configuration to the second short circuit configuration, from the second short circuit configuration to the first short circuit configuration, from the first short circuit configuration to the open circuit configuration, from the open circuit configuration to the first short circuit configuration, from the second short circuit configuration to the open circuit configuration, and from the open circuit configuration to the second short circuit configuration. Hence, the direction in which the bypass unit **27** bypasses the first, second, third, and fourth switching elements **19** can be controlled.

(73) FIG. **9** shows a sixth embodiment of the cell **9** of the cell assembly **5** of the arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. **5**. The fifth embodiment of the cell **9** shown in FIG. **9** can also form a cell **9** of a cell assembly **5** of an arm **3** of the plurality of arms **3** of the converter **1** of which a section is shown in FIG. **6**. The sixth embodiment of the cell **9** shown in FIG. **9** is essentially identical to the fifth embodiment of the cell **9** shown in FIG. **8**. However, the bypass unit **27** of the sixth embodiment of the cell **9** comprises a thyristor **33** and four diodes **25**. A first diode **25** of the four diodes **25** and a second diode **25** of the four diodes **25** are connected to the first terminal **15** and on opposite sides to the thyristor **33**. A third diode **25** of the four diodes **25** and a fourth diode **25** of the four diodes **25** are connected to the second terminal **17** and on opposite sides to the thyristor **33**. The first diode **25** is connected with its anode to the first terminal **15** and with its cathode to the anode of the thyristor **33**. The second diode **25** is connected with its cathode to the first terminal **15** and with its anode to the cathode of the thyristor **33**. The third diode **25** is connected with its cathode to the second terminal **17** and with its anode to the cathode of the thyristor **33**. The fourth diode **25** is connected with its anode to the second terminal **17** and with its cathode to the anode of the Thyristor **33**.

(74) The thyristor **33** is adapted to be in a short circuit configuration and in an open circuit

configuration and is adapted to switch back and forth between the short circuit configuration and the open circuit configuration. When the thyristor **33** is in the short circuit configuration, the bypass unit **27** is also in the short circuit configuration and bypasses the first, second, third, and fourth switching elements **19**. Particularly, due to the arrangement of the four diodes **25** and the thyristor **33**, when the bypass unit **27** is in the short circuit configuration, the bypass unit **27** can bypass the first, second, third, and fourth switching elements **19** in two directions, i.e. from the first terminal **15** to the second terminal **17** and from the second terminal **17** to the first terminal **15**. Preferably, the direction of the bypassing depends on the voltage present at the first terminal **15** and the second terminal **17**. When the thyristor **33** is in the open circuit configuration, the bypass unit **27** is also in the open circuit configuration and does not bypass the first, second, third, and fourth switching elements **19**.

(75) Further, the cell controller unit **29** is connected to the gate of the thyristor **33** and is adapted to provide control signals to the thyristor **33**, such that the configuration of the thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. Thereby, the configuration of the bypass unit **27** can be changed from the short circuit configuration to the open circuit configuration. Hence, configuration of the bypass unit **27** can be controlled by only controlling the thyristor **33**.

Therefore, the bypass unit **27** shown in FIG. **9** provides a bypass unit **27**, which is easy and energy efficient to control. Further, the bypass unit **27** shown in FIG. **9** only requires one thyristor **33**.

(76) FIG. **10** shows a section of a first embodiment of a bypass unit **27** of the first to sixth embodiment of the cell **9** shown in FIGS. **2** to **4** and **7** to **9**. The thyristor **33** shown in FIG. **10** may be any thyristor **33** shown in FIGS. **3**, **4**, **8**, and **9**. The cell controller unit **29** is connected to the gate of the thyristor **33** via a latching relay **37**, which may form a memory unit (memory) or a part of a memory unit and which comprises input terminals **39** adapted to receive control signals from the cell controller unit **29** and normally open contact terminals **41** adapted to be in an open configuration and in a closed configuration and changed from the open configuration to the closed configuration and from the closed configuration to the open configuration depending on the control signals received from the cell controller unit **29**, such that the configuration of the thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration.

(77) FIG. **11** shows a section of a second embodiment of the bypass unit **27** of the first to sixth embodiment of the cell **9** shown in FIGS. **2** to **4** and **7** to **9**. The thyristor **33** shown in FIG. **11** may be any thyristor **33** shown in FIGS. **3**, **4**, **8**, and **9**. A diode **25** is connected to the thyristor **33**, wherein the anode of the diode **25** is connected to the anode of the thyristor **33** and the cathode of the diode **25** is connected to the gate of the thyristor **33**. Due to this configuration, the thyristor **33** may act as a diode in case the bypass unit **27** needs to be forced into the short circuit configuration, for example in case of a bond wire failure of a diode **25** of one of the switching elements **19**.

(78) FIG. **12** shows a section of a third embodiment of the bypass unit **27** of the first to sixth embodiment of the cell **9** shown in FIGS. **2** to **4** and **7** to **9**. The thyristor **33** shown in FIG. **12** may be any thyristor **33** shown in FIGS. **3**, **4**, **8**, and **9**. The cell controller unit **29** is connected to the gate of the thyristor **33** via a latching relay **37**, which may form a memory unit or a part of a memory unit, a resistance **43**, which may be formed by a resistor, and an n-channel metal oxide semiconductor field-effect transistor (n-channel MOSFET) **45**. The latching relay **37** comprises input terminals **39** adapted to receive control signals from the cell controller unit **29** and normally open contact terminals **41** adapted to be in an open configuration and in a closed configuration and adapted to be changed from the open configuration to the closed configuration and from the closed configuration to the open configuration depending on the control signals received from the cell controller unit **29**, such that the configuration of the thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. To change the configuration of the thyristor **33**, the latching relay **37** is

connected to the thyristor **33** via the resistance **43** and the n-channel MOSFET **45**. A first contact terminal of the contact terminals **41** is connected to the cathode of the thyristor **33**. A second contact terminal of the contact terminals **41** is connected to a first terminal of the resistance **43** and a gate of the n-channel MOSFET **45**. A second terminal of the resistance **43** is connected to a drain of the n-channel MOSFET **45** and to the anode of the thyristor **33**. Further, a source of the n-channel MOSFET **45** is connected to the gate of the thyristor **33**, such that the configuration of the thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration based on the control signals received from the cell controller unit **29** at the latching relay **37**.

(79) FIG. **13** shows a section of a fourth embodiment of the bypass unit **27** of the first to sixth embodiment of the cell **9** shown in FIGS. **2** to **4** and **7** to **9**. The thyristor **33** shown in FIG. **13** may be any thyristor **33** shown in FIGS. **3**, **4**, **8**, and **9**. The cell controller unit **29** is connected to the gate of the thyristor **33** via a memory unit, which comprises a data storage unit **47**, a resistance **43**, which may be formed by a resistor, and two n-channel MOSFETs **45**. To change the configuration of the thyristor **33** from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration, the memory unit is connected to the thyristor **33** via the resistance **43** and the two n-channel MOSFET **45**. A first terminal of the memory unit is connected to a source of a first n-channel MOSFET **45** of the two n-channel MOSFETs **45** and to the cathode of the thyristor **33**. A second terminal of the memory unit is connected to a gate of the first n-channel MOSFET **45**. A drain of the first n-channel MOSFET **45** is connected to the first terminal of the resistance **43** and a gate of a second n-channel MOSFET **45** of the two n-channel MOSFETs **45**. A second terminal of the resistance **43** is connected to a drain of the second n-channel MOSFET **45** and to the anode of the thyristor **33**. Further, a source of the second n-channel MOSFET **45** is connected to the gate of the thyristor **33**, such that the configuration of the thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration based on the control signals received from the cell controller unit **29** at the memory unit.

(80) The control signals received from the cell controller unit **29** may represent status information, which can be written to the data storage unit **47** of the memory unit by the cell controller unit **29** of the cell **9**. Preferably, the data storage unit **47** is a non-volatile data storage unit. The status information may represent the configuration of the bypass unit **27**, particularly the current configuration of the bypass unit **27** and/or the desired configuration of the bypass unit **27**, and/or the configuration of the thyristor **33**, particularly the current configuration of the thyristor **33** and/or the desired configuration of the thyristor **33**. In case the status information may represent the configuration of the bypass unit **27**, the status information may also be called status information of the bypass unit **27**. In case the status information may represent the configuration of the thyristor **33**, the status information may also be called status information of the thyristor **33**. The current configuration of the bypass unit **27** is the configuration in which the bypass unit **27** is currently in. Similarly, the current configuration of the thyristor **33** is the configuration in which the thyristor **33** is currently in. The desired configuration of the bypass unit **27** may be the configuration in which the bypass unit **27** needs to be in, such that the at least one switching element **19** of the switching elements **19** is bypassed or not bypassed. The desired configuration of the thyristor **33** may be the configuration in which the thyristor **33** needs to be in, such that the bypass unit **27** is in its desired configuration.

(81) FIG. **14** shows a section of a fifth embodiment of the bypass unit **27** of the first to sixth embodiment of the cell **9** shown in FIGS. **2** to **4** and **7** to **9**. The fifth embodiment of the bypass unit **27** shown in FIG. **14** is essentially identical to the third embodiment of the bypass unit **27** shown in FIG. **12**.

(82) A first thyristor **33** shown on the left in FIG. **12** may be any thyristor **33** shown in FIGS. **3**, **4**, **8**, and **9**. The cell controller unit **29** not shown in FIG. **14** is connected to the gate of the first

thyristor **33** via a latching relay **37**, which may form a memory unit or a part of a memory unit, a resistance **43**, which may be formed by a resistor, and an n-channel MOSFET **45**. The latching relay **37** comprises input terminals **39** adapted to receive control signals from the cell controller unit **29** and normally open contact terminals **41** adapted to be in an open configuration and in a closed configuration and adapted to be changed from the open configuration to the closed configuration and from the closed configuration to the open configuration depending on the control signals received from the cell controller unit **29**, such that the configuration of the first thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration. To change the configuration of the first thyristor **33**, the latching relay **37** is connected to the first thyristor **33** via the resistance **43** and the n-channel MOSFET **45**. A first contact terminal of the contact terminals **41** is connected to the cathode of the first thyristor **33**. A second contact terminal of the contract terminals **41** is connected to a first terminal of the resistance **43** and a gate of the n-channel MOSFET **45**. A second terminal of the resistance **43** is connected to a drain of the n-channel MOSFET **45** and to the anode of the first thyristor **33**. Further, a source of the n-channel MOSFET **45** is connected to the gate of the first thyristor **33**, such that the configuration of the first thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration based on the control signals received from the cell controller unit **29** at the latching relay **37**.

(83) Further, the bypass unit **27** comprises a second thyristor **33** shown on the right in FIG. **14**. The anode of the second thyristor **33** is connected to the cathode of the first thyristor **33** and the cathode of the second thyristor **33** is connected to the anode of the first thyristor **33**. The bypass unit **27** comprises a diode **25**, which is connected to the second thyristor **33**. The anode of the diode **25** is connected to the cathode of the first thyristor **33** and to the anode of the second thyristor **33**. Further, the cathode of the diode **25** is connected to the gate of the second thyristor **33**. Due to this configuration, the second thyristor **33** may act as a diode in case the bypass unit **27** needs to be forced into the short circuit configuration, for example in case of a bond wire failure of a diode **25** of one of the switching elements **19**.

(84) Further, a first transformer **49** and a second transformer **49** are shown in FIG. **14**. The first transformer **49** and the second transformer **49** are each connected to a power and data recovery block **51** of the bypass unit **27**. Further, the first transformer **49** is connected to a first neighbouring cell **9** of the cell **9** the bypass unit **27** is a part of and the second transformer **49** is connected to a second neighbouring cell **9** of the cell **9** the bypass unit **27** is a part of. The cell **9** and the first neighbouring cell **9** form a pair of neighbouring cells **9**. Similarly, the cell **9** and the second neighbouring cell **9** form a pair of neighbouring cells **9**. The power and data recovery block **51** comprises output terminals, which are connected to the input terminals **39** of the latching relay **37**.

(85) The first neighbouring cell **9** comprises a cell controller unit **29**, which is adapted to provide a control signal to the bypass unit **27** of which a section is shown in FIG. **14** via the first transformer **49**. The power and data recovery block **51** comprises input terminals adapted to receive control signals from the cell controller unit **29** of the first neighbouring cell **9** via the first transformer **49**. The latching relay **37** receives control signals from the power and data recovery block **51** depending on the control signals the power and data recovery block **51** receives from the cell controller unit **29** of the first neighbouring cell **9**, such that the configuration of the first thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration depending on the control signals the power and data recovery block **51** receives from the cell controller unit **29** of the first neighbouring cell **9**. Therefore, the cell controller unit **29** of the first neighbouring cell **9** is adapted to provide control signals to the bypass unit **27** of which a section is shown in FIG. **14**, such that the bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the

first neighbouring cell **9** comprises a power supply unit **31**. The power supply unit **31** of the first neighbouring cell **9** is adapted to provide electrical power to the bypass unit **27** via the first transformer **49**.

(86) Moreover, the second neighbouring cell **9** comprises a cell controller unit **29**, which is adapted to provide a control signal to the bypass unit **27** of which a section is shown in FIG. **14** via the second transformer **49**. The input terminals of the power and data recovery block **51** are also adapted to receive control signals from the cell controller unit **29** of the second neighbouring cell **9** via the second transformer **49**. The latching relay **37** receives control signals from the power and data recovery block **51** depending on the control signals the power and data recovery block **51** receives from the cell controller unit **29** of the second neighbouring cell **9**, such that the configuration of the first thyristor **33** can be changed from the short circuit configuration to the open circuit configuration and from the open circuit configuration to the short circuit configuration depending on the control signals the power and data recovery block **51** receives from the cell controller unit **29** of the second neighbouring cell **9**. Therefore, the cell controller unit **29** of the second neighbouring cell **9** is adapted to provide control signals to the bypass unit **27** of which a section is shown in FIG. **14**, such that the bypass unit **27** changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration. Further, the second neighbouring cell **9** comprises a power supply unit **31**. The power supply unit **31** of the second neighbouring cell **9** is adapted to provide electrical power to the bypass unit **27** via the second transformer **49**.

(87) In summary, the bypass unit **27** of which a section is shown in FIG. **14** can be controlled by the cell controller unit **29** of the first neighbouring cell **9** and by the cell controller unit **29** of the second neighbouring cell **9**. Further, the power supply unit **31** of the first neighbouring cell **9** and the power supply unit **31** of the second neighbouring cell **9** are both adapted to provide electrical power to the bypass unit **27** of which a section is shown in FIG. **14**. Hence, the control of the bypass unit **27** and the power supply of the bypass unit **27** is ensured even if the cell controller unit **29** and/or the power supply unit **31** of the cell **9** the bypass unit **27** is a part of has/have failed in case of a cell failure. Additionally, the control of the bypass unit **27** and the power supply of the bypass unit **27** is still ensured even if the cell controller unit **29** and/or the power supply unit **31** of the cell **9** the bypass unit **27** is a part of has/have failed in case of a cell failure as well as the cell controller unit **29** and/or the power supply unit **31** of either the first neighbouring cell **9** or the second neighbouring cell **9** has/have failed in case of a cell failure of the first or second neighbouring cell **9**.

(88) It is additionally pointed out that “comprising” does not rule out other elements, and “a” or “an” does not rule out a multiplicity. It is also pointed out that features that have been described with reference to one of the above exemplary embodiments may also be disclosed as in combination with other features of other exemplary embodiments described above. Reference signs in the claims are not to be regarded as restrictive.

(89) While subject matter of the present disclosure has been illustrated and described in detail in the drawings and foregoing description, such illustration and description are to be considered illustrative or exemplary and not restrictive. Any statement made herein characterizing the invention is also to be considered illustrative or exemplary and not restrictive as the invention is defined by the claims. It will be understood that changes and modifications may be made, by those of ordinary skill in the art, within the scope of the following claims, which may include any combination of features from different embodiments described above.

(90) The terms used in the claims should be construed to have the broadest reasonable interpretation consistent with the foregoing description. For example, the use of the article “a” or “the” in introducing an element should not be interpreted as being exclusive of a plurality of elements. Likewise, the recitation of “or” should be interpreted as being inclusive, such that the recitation of “A or B” is not exclusive of “A and B,” unless it is clear from the context or the

foregoing description that only one of A and B is intended. Further, the recitation of “at least one of A, B and C” should be interpreted as one or more of a group of elements consisting of A, B and C, and should not be interpreted as requiring at least one of each of the listed elements A, B and C, regardless of whether A, B and C are related as categories or otherwise. Moreover, the recitation of “A, B and/or C” or “at least one of A, B or C” should be interpreted as including any singular entity from the listed elements, e.g., A, any subset from the listed elements, e.g., A and B, or the entire list of elements A, B and C.

REFERENCE SIGNS

(91) **1** converter **3** arm **5** cell assembly **7** inductance **9** cell **11** DC (direct current) terminal **13** AC (alternating current) terminal **15** first terminal of the cell **17** second terminal of the cell **19** switching element **21** capacitance of the cell **23** insulated-gate bipolar transistor (IGBT) **25** diode **27** bypass unit **29** cell controller unit **31** power supply unit **33** thyristor **35** third terminal of the cell **37** latching relay **39** input terminals **41** contact terminals **43** resistance **45** N-channel MOSFET **47** data storage unit **49** transformer **51** power and data recovery block

Claims

1. A modular multilevel converter (MMC) comprising a plurality of arms, wherein each arm comprises a respective cell assembly, the cell assembly comprising a plurality of cells, wherein each cell of the plurality of cells comprises: a first terminal, a second terminal, switching elements, and a capacitor, wherein the switching elements are adapted to controllably: connect the capacitor to the first terminal and to the second terminal and bypass the capacitor, wherein the cells of the plurality of cells are connected in series in such a way that, for each pair of neighbouring cells, the first terminal of a first cell of the pair of neighbouring cells is connected to the second terminal of a second cell of the pair of neighbouring cells, wherein each cell further comprises a bypass unit, wherein the bypass unit of each cell is connected to the first terminal and to the second terminal of the cell and adapted to controllably bypass at least one switching element of the switching elements of the cell in a short circuit configuration and to not bypass the at least one switching element in an open circuit configuration, wherein each cell further comprises a cell controller, wherein the cell controller of each cell is adapted to provide control signals to the switching elements of the cell, such that the switching elements controllably connect the capacitor to the first terminal and to the second terminal or the switching elements bypass the capacitor, wherein the cell controller of each cell is adapted to provide a control signal to the bypass unit of at least one of its neighbouring cells, such that the respective bypass unit controllably changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration, wherein the bypass unit of each cell comprises at least one thyristor, wherein each cell further comprises a power supply, wherein the power supply of each cell is adapted to provide electrical power to the bypass unit of at least one of its neighbouring cells, wherein the cell controller of each cell is connected to a gate of the thyristor of at least one of its neighbouring cells via an n-channel metal-oxide semiconductor field-effect transistor (MOSFET), and wherein the cell controller is adapted to provide control signals to the thyristor via the gate for switching between the open and closed configuration.

2. The MMC according to claim 1, wherein the bypass unit of each cell comprises a memory.

3. The MMC according to claim 2, wherein the memory of each cell is connected to the cell controller of the cell, such that a status information of the bypass unit, which represents the configuration of the bypass unit, is writable to the memory by the cell controller of the cell.

4. The MMC according to claim 2, wherein the memory comprises a data storage.

5. The MMC according to claim 4, wherein the data storage is a non-volatile data storage.

6. The MMC according to claim 2, wherein the memory comprises a latching relay.

7. The MMC according to claim 1, wherein the cell controller of each cell is adapted to provide a

- control signal to the bypass unit of one of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.
8. The MMC according to claim 1, wherein the cell controller of each cell is adapted to provide a control signal to the bypass unit of two of its neighbouring cells, such that the respective bypass unit changes its configuration from the short circuit configuration to the open circuit configuration or from the open circuit configuration to the short circuit configuration.
9. The MMC according to claim 1, wherein the bypass unit of each cell is adapted to bypass one switching element of the switching elements of the cell in the short circuit configuration and to not bypass the one switching element in the open circuit configuration.
10. The MMC according to claim 1, wherein the bypass unit of each cell is adapted to bypass two switching elements of the switching elements of the cell in the short circuit configuration and to not bypass the two switching elements in the open circuit configuration.
11. The MMC according to claim 1, wherein the switching elements of each cell comprise two switching elements, which are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a first switching element of the two switching elements is connected to a first terminal of the capacitor and a second switching element of the two switching elements is connected to a second terminal of the capacitor at a second connection point, which is connected to the second terminal of the cell.
12. The MMC according to claim 1, wherein the switching elements of each cell comprise four switching elements, wherein a first switching element of the four switching elements and a second switching element of the four switching elements are connected to one another at a first connection point, which is connected to the first terminal of the cell, wherein a third switching element of the four switching elements and a fourth switching element of the four switching elements are connected to one another at a second connection point, which is connected to the second terminal of the cell, wherein the first switching element and the third switching element are connected to one another at a third connection point, which is connected to a first terminal of the capacitor of the cell and the second switching element and the fourth switching element are connected to one another at a fourth connection point, which is connected to a second terminal of the capacitor of the cell.
13. The MMC according to claim 1, wherein each switching element of the at least one switching element of each cell comprises a transistor.
14. A modular multilevel converter (MMC) comprising a plurality of arms, wherein each arm comprises a respective cell assembly each configured according to the cell assembly of claim 1.
-