

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent
Kind Code
Date of Patent
Inventor(s)

12413105
B2
September 09, 2025
Cabrol; Patrick et al.

Methods and apparatus for load-based access control in resonance magnetic coupled networks

Abstract

The disclosure pertains to methods and apparatus for operation by a wireless transmit/receive unit (WTRU). In one embodiment, a method includes receiving from a first device, a request to send a transmission to a second device via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device; sending to the first device, measurement configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device; and (2) at least one load termination state of the set of load termination states to be used by the first device when performing measurements; receiving from the first device, measurement information resulting from measurements performed by the first device in accordance with the sent measurement configuration information; determining a load termination state for the first device based on the measurement information; and sending to the first device, information indicating the determined load termination state for the first device.

Inventors:	Cabrol; Patrick (Bayshore, NY), Haque; Tanbir (Jackson Heights, NY), Elkotby; Hussain (Conshohocken, PA), Pragada; Ravikumar (Warrington, PA)
Applicant:	DRNC Holdings, Inc. (Wilmington, DE)
Family ID:	80119505
Assignee:	DRNC Holdings, Inc. (Wilmington, DE)
Appl. No.:	18/266759
Filed (or PCT Filed):	December 09, 2021
PCT No.:	PCT/US2021/062614
PCT Pub. No.:	WO2022/132561

PCT Pub. Date: June 23, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240113566 A1	Apr. 04, 2024
US 20250183728 A9	Jun. 05, 2025

Related U.S. Application Data

us-provisional-application US 63125045 20201214
us-provisional-application US 63146981 20210208

Publication Classification

Int. Cl.: H02J50/80 (20160101); H02J50/12 (20160101)

U.S. Cl.:

CPC H02J50/80 (20160201); H02J50/12 (20160201);

Field of Classification Search

CPC: H02J (50/80); H02J (50/12)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8810072	12/2013	Tsai	307/104	H02J 50/80
8855786	12/2013	Derbas	336/198	H01F 5/00
8981600	12/2014	Tsai	320/108	H02J 50/12
9601946	12/2016	Bae	N/A	H02J 50/12
2011/0221391	12/2010	Won	320/108	H02J 50/80
2011/0291489	12/2010	Tsai	307/104	H02J 50/402
2011/0299636	12/2010	Tsai	307/104	H02J 50/80
2012/0095531	12/2011	Derbas	343/866	H01Q 1/38
2012/0193998	12/2011	Tsai	307/104	H02J 50/70
2012/0235636	12/2011	Partovi	320/108	H02J 7/0042
2013/0154387	12/2012	Lee	307/104	H02J 50/12
2016/0056662	12/2015	Yoon	320/108	H02J 50/80
2016/0056664	12/2015	Partovi	307/104	B60L 53/122
2017/0149286	12/2016	Joye	N/A	H04B 5/79
2017/0237296	12/2016	Keith	307/104	H02J 50/40
2019/0097448	12/2018	Partovi	N/A	B60L 53/12
2019/0140491	12/2018	Tsai	N/A	H02J 50/80
2019/0296590	12/2018	Chae	N/A	H02J 7/02
2021/0028651	12/2020	Goodchild	N/A	H02J 50/90

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
WO 2020131854	12/2019	WO	N/A
WO 2021155101	12/2020	WO	N/A

OTHER PUBLICATIONS

Karalis et al., “Efficient Wireless Non-Radiative Mid-Range Energy Transfer”, Annals of Physics, vol. 323, No. 1, Jan. 2008, 19 pages. cited by applicant

Mongia et al., “RF and Microwave Coupled-Line Circuits: Second Edition”, Artech House Publishers, Boston, Massachusetts, 2007, 618 pages. cited by applicant

Kurs et al., “Wireless Power Transfer via Strongly Coupled Magnetic Resonances”, American Association for the Advancement of Science (AAAS), ScienceMag, vol. 317, No. 5834, Jul. 6, 2007, 4 pages. cited by applicant

Sample et al., “Analysis, Experimental Results, and Range Adaptation of Magnetically Coupled Resonators for Wireless Power Transfer”, Institute of Electrical and Electronics Engineers (IEEE), IEEE Transactions on Industrial Electronics, vol. 58, Issue No. 2, Feb. 2011, 11 pages. cited by applicant

Choma et al., “Feedback Networks: Theory and Circuit Applications”, World Scientific Publishing Company, Advanced Series in Circuits and Systems, vol. 5, Sections 3.3.0 to 3.3.5, 2007, pp. 238-254. cited by applicant

Primary Examiner: Barnie; Rexford N

Assistant Examiner: Warmflash; Michael J

Attorney, Agent or Firm: Volpe Koenig

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) The application is a U.S. National Stage Application under 35 U.S.C. § 371 of International Patent Application No PCT/US2021/062614, filed Dec. 9, 2021, which claims the benefit of priority to U.S. Provisional Patent Application Ser. No. 63/125,045, filed Dec. 14, 2020, and U.S. Provisional Patent Application Ser. No. 63/146,981, filed Feb. 8, 2021, the contents of each of which is incorporated herein by reference.

FIELD

(1) Embodiments disclosed herein generally relate to wireless communications and, for example to methods and apparatus for load-based access control to a Resonance Magnetic Coupled (RMC) network.

BACKGROUND

(2) Wireless power transfer (WPT), as a result of the recent universal adoption of portable electronic devices, has attracted considerable attention in many commercial applications including smartphones, medical instruments, electric vehicles (EVs), wireless sensors, and other IoT devices.

(3) Conventional radiative energy transfer, used mainly for transferring information, may pose some difficulties for power transfer applications. For instance, power transfer using omnidirectional radiation patterns may be inefficient, while unidirectional radiation, while more efficient in terms of energy transfer, may use (e.g., require) line of sight and special tracking

mechanisms to accommodate mobility.

(4) Previous works have demonstrated power delivery at mid-field with higher efficiency than far-field approaches, and at longer distances than traditional inductive coupled systems. Subsequent work managed to overcome the fixed distance and orientation limitations associated with the previously mentioned studies, where efficiency would fall-off rapidly when the receiving device is relocated away from its optimal operating coordinates.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) A more detailed understanding may be had from the detailed description below, given by way of example in conjunction with the drawings appended hereto. Figures in such drawings, like the detailed description, are exemplary. As such, the Figures and the detailed description are not to be considered limiting, and other equally effective examples are possible and likely. Furthermore, like reference numerals (“ref.”) in the Figures (“FIGS.”) indicate like elements, and wherein:

- (2) FIG. 1A is a system diagram illustrating an example communications system in which one or more disclosed embodiments may be implemented;
- (3) FIG. 1B is a system diagram illustrating an example wireless transmit/receive unit (WTRU) that may be used within the communications system illustrated in FIG. 1A according to one embodiment;
- (4) FIG. 1C is a system diagram illustrating an example radio access network (RAN) and an example core network (CN) that may be used within the communications system illustrated in FIG. 1A according to one embodiment;
- (5) FIG. 1D is a system diagram illustrating a further example RAN and a further example CN that may be used within the communications system illustrated in FIG. 1A according to one embodiment;
- (6) FIG. 2 is a diagram of a resonance magnetic wireless power transfer and communications system;
- (7) FIG. 3 is a graph of resonance magnetic frequency as a function of distance for a resonance magnetically coupled system;
- (8) FIG. 4 is a diagram of a resonant magnetic power transfer circuit model;
- (9) FIG. 5 is a diagram showing a resonance magnetic broadcast group;
- (10) FIG. 6 is a diagram illustrating the two main frameworks for medium access in communication networks, namely, centralized medium access and distributed medium access;
- (11) FIGS. 7A, 7B, and 7C illustrate network topology for a wireline network, a far-field wireless network, and a mid-field wireless network, respectively;
- (12) FIGS. 8A and 8B are a loading model and a transformer representation of a plurality of load devices coupled to a single power source;
- (13) FIGS. 9A and 9B illustrate contents of a control plane frame in accordance with two exemplary embodiments;
- (14) FIGS. 10A and 10B illustrate content for a downlink control plane frame and an uplink control plane frame in accordance with one embodiment;
- (15) FIG. 11 is a graph illustrating load termination state assignment as a function of signal strength in accordance with one embodiment;
- (16) FIG. 12 is a graph illustrating a scheme for load termination state assignments for multiple devices in multiple time slots in accordance with one embodiment;
- (17) FIG. 13 is a flowchart illustrating sharing of the BCH among multiple devices in accordance with one embodiment;
- (18) FIG. 14 is a diagram illustrating load termination states of three devices over a period of 6

- times slots in accordance with one embodiment;
- (19) FIG. 15 is a diagram illustrating load termination states of three devices over a period of 6 times slots in accordance with another embodiment;
- (20) FIG. 16 is a diagram illustrating load termination states of three devices over a period of 6 times slots in accordance with yet another embodiment;
- (21) FIG. 17 is a flowchart illustrating a load-based access scheme from the device perspective in accordance with one embodiment;
- (22) FIG. 18 is a graphic representation of the relationship between real, reactive, and apparent power in a system;
- (23) FIG. 19 is a circuit diagram of a model circuit for simultaneous transfer of power and information in accordance with one embodiment;
- (24) FIG. 20 is a flowchart describing a procedure for selecting a complex impedance for energy harvesting or communication. in accordance with one embodiment;
- (25) FIG. 21 is a flowchart describing the procedure for selecting a complex impedance for energy harvesting or communication in accordance with one embodiment;
- (26) FIG. 22 is a diagram illustrating several possible frequency and magnitude configurations for the power harvesting signal and the various communication channels in accordance with embodiments;
- (27) FIG. 23 is diagram illustrating how devices may transmit data on the CW energy tone in the BCH by load modulating the CW energy tone in accordance with one embodiment;
- (28) FIG. 24 is a signal flow diagram illustrating a method performed by a cluster head to maximize the number of devices able to communicate on the Broadcast Channel and allocate resources based on need in accordance with one embodiment;
- (29) FIG. 25 is a signal flow diagram illustrating a method performed by a cluster head for managing device-pairs connected via unicast links and allocating medium resources (bandwidth, time slots) in accordance with one embodiment;
- (30) FIG. 26 is a flowchart illustrating an exemplary method performed by a cluster head (CLH) to manage a new device joining the cluster;
- (31) FIG. 27 is a diagram illustrating time division multiplexing of energy transfer and information transfer in accordance with one embodiment;
- (32) FIG. 28 is a flowchart illustrating a representative method implemented by a WTRU;
- (33) FIG. 29 is a flowchart illustrating a representative method implemented by a first device;
- (34) FIG. 30 is a flowchart illustrating a representative method implemented by a WTRU in communication on a common channel via resonance magnetic coupling with one or more first devices;
- (35) FIG. 31 is a flowchart illustrating a representative method implemented by a cluster head for controlling device access in a resonance magnetic coupled (RMC) network;
- (36) FIG. 32 is a flowchart illustrating a further representative method implemented by a WTRU; and
- (37) FIG. 33 is a flowchart illustrating a representative method implemented in a cluster head of a resonance magnetic coupling network.

DETAILED DESCRIPTION

Introduction

(38) In the following detailed description, numerous specific details are set forth to provide a thorough understanding of embodiments and/or examples disclosed herein. However, it will be understood that such embodiments and examples may be practiced without some or all of the specific details set forth herein. In other instances, well-known methods, procedures, components and circuits have not been described in detail, so as not to obscure the following description. Further, embodiments and examples not specifically described herein may be practiced in lieu of, or in combination with, the embodiments and other examples described, disclosed or otherwise

provided explicitly, implicitly and/or inherently (collectively “provided”) herein.

(39) Example Networks for Implementation of the Invention

(40) FIG. 1A is a diagram illustrating an example communications system **100** in which one or more disclosed embodiments may be implemented. The communications system **100** may be a multiple access system that provides content, such as voice, data, video, messaging, broadcast, etc., to multiple wireless users. The communications system **100** may enable multiple wireless users to access such content through the sharing of system resources, including wireless bandwidth. For example, the communications systems **100** may employ one or more channel access methods, such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), single-carrier FDMA (SC-FDMA), zero-tail unique-word DFT-Spread OFDM (ZT UW DTS-s OFDM), unique word OFDM (UW-OFDM), resource block-filtered OFDM, filter bank multicarrier (FBMC), and the like.

(41) As shown in FIG. 1A, the communications system **100** may include wireless transmit/receive units (WTRUs) **102a**, **102b**, **102c**, **102d**, a RAN **104/113**, a CN **106/115**, a public switched telephone network (PSTN) **108**, the Internet **110**, and other networks **112**, though it will be appreciated that the disclosed embodiments contemplate any number of WTRUs, base stations, networks, and/or network elements. Each of the WTRUs **102a**, **102b**, **102c**, **102d** may be any type of device configured to operate and/or communicate in a wireless environment. By way of example, the WTRUs **102a**, **102b**, **102c**, **102d**, any of which may be referred to as a “station” and/or a “STA”, may be configured to transmit and/or receive wireless signals and may include a user equipment (UE), a mobile station, a fixed or mobile subscriber unit, a subscription-based unit, a pager, a cellular telephone, a personal digital assistant (PDA), a smartphone, a laptop, a netbook, a personal computer, a wireless sensor, a hotspot or Mi-Fi device, an Internet of Things (IoT) device, a watch or other wearable, a head-mounted display (HMD), a vehicle, a drone, a medical device and applications (e.g., remote surgery), an industrial device and applications (e.g., a robot and/or other wireless devices operating in an industrial and/or an automated processing chain contexts), a consumer electronics device, a device operating on commercial and/or industrial wireless networks, and the like. Any of the WTRUs **102a**, **102b**, **102c** and **102d** may be interchangeably referred to as a UE.

(42) The communications systems **100** may also include a base station **114a** and/or a base station **114b**. Each of the base stations **114a**, **114b** may be any type of device configured to wirelessly interface with at least one of the WTRUs **102a**, **102b**, **102c**, **102d** to facilitate access to one or more communication networks, such as the CN **106/115**, the Internet **110**, and/or the other networks **112**. By way of example, the base stations **114a**, **114b** may be a base transceiver station (BTS), a Node-B, an eNode B, a Home Node B, a Home eNode B, a gNB, a NR NodeB, a site controller, an access point (AP), a wireless router, and the like. While the base stations **114a**, **114b** are each depicted as a single element, it will be appreciated that the base stations **114a**, **114b** may include any number of interconnected base stations and/or network elements.

(43) The base station **114a** may be part of the RAN **104/113**, which may also include other base stations and/or network elements (not shown), such as a base station controller (BSC), a radio network controller (RNC), relay nodes, etc. The base station **114a** and/or the base station **114b** may be configured to transmit and/or receive wireless signals on one or more carrier frequencies, which may be referred to as a cell (not shown). These frequencies may be in licensed spectrum, unlicensed spectrum, or a combination of licensed and unlicensed spectrum. A cell may provide coverage for a wireless service to a specific geographical area that may be relatively fixed or that may change over time. The cell may further be divided into cell sectors. For example, the cell associated with the base station **114a** may be divided into three sectors. Thus, in one embodiment, the base station **114a** may include three transceivers, e.g., one for each sector of the cell. In an embodiment, the base station **114a** may employ multiple-input multiple output (MIMO) technology and may utilize multiple transceivers for each sector of the cell. For example, beamforming may be

used to transmit and/or receive signals in desired spatial directions.

(44) The base stations **114a**, **114b** may communicate with one or more of the WTRUs **102a**, **102b**, **102c**, **102d** over an air interface **116**, which may be any suitable wireless communication link (e.g., radio frequency (RF), microwave, centimeter wave, micrometer wave, infrared (IR), ultraviolet (UV), visible light, etc.). The air interface **116** may be established using any suitable radio access technology (RAT).

(45) More specifically, as noted above, the communications system **100** may be a multiple access system and may employ one or more channel access schemes, such as CDMA, TDMA, FDMA, OFDMA, SC-FDMA, and the like. For example, the base station **114a** in the RAN **104/113** and the WTRUs **102a**, **102b**, **102c** may implement a radio technology such as Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access (UTRA), which may establish the air interface **115/116/117** using wideband CDMA (WCDMA). WCDMA may include communication protocols such as High-Speed Packet Access (HSPA) and/or Evolved HSPA (HSPA+). HSPA may include High-Speed Downlink (DL) Packet Access (HSDPA) and/or High-Speed UL Packet Access (HSUPA).

(46) In an embodiment, the base station **114a** and the WTRUs **102a**, **102b**, **102c** may implement a radio technology such as Evolved UMTS Terrestrial Radio Access (E-UTRA), which may establish the air interface **116** using Long Term Evolution (LTE) and/or LTE-Advanced (LTE-A) and/or LTE-Advanced Pro (LTE-A Pro).

(47) In an embodiment, the base station **114a** and the WTRUs **102a**, **102b**, **102c** may implement a radio technology such as NR Radio Access, which may establish the air interface **116** using New Radio (NR).

(48) In an embodiment, the base station **114a** and the WTRUs **102a**, **102b**, **102c** may implement multiple radio access technologies. For example, the base station **114a** and the WTRUs **102a**, **102b**, **102c** may implement LTE radio access and NR radio access together, for instance using dual connectivity (DC) principles. Thus, the air interface utilized by WTRUs **102a**, **102b**, **102c** may be characterized by multiple types of radio access technologies and/or transmissions sent to/from multiple types of base stations (e.g., an eNB and a gNB).

(49) In other embodiments, the base station **114a** and the WTRUs **102a**, **102b**, **102c** may implement radio technologies such as IEEE 802.11 (e.g., Wireless Fidelity (WiFi)), IEEE 802.16 (e.g., Worldwide Interoperability for Microwave Access (WiMAX)), CDMA2000, CDMA2000 1×, CDMA2000 EV-DO, Interim Standard 2000 (IS-2000), Interim Standard 95 (IS-95), Interim Standard 856 (IS-856), Global System for Mobile communications (GSM), Enhanced Data rates for GSM Evolution (EDGE), GSM EDGE (GERAN), and the like.

(50) The base station **114b** in FIG. 1A may be a wireless router, Home Node B, Home eNode B, or access point, for example, and may utilize any suitable RAT for facilitating wireless connectivity in a localized area, such as a place of business, a home, a vehicle, a campus, an industrial facility, an air corridor (e.g., for use by drones), a roadway, and the like. In one embodiment, the base station **114b** and the WTRUs **102c**, **102d** may implement a radio technology such as IEEE 802.11 to establish a wireless local area network (WLAN). In an embodiment, the base station **114b** and the WTRUs **102c**, **102d** may implement a radio technology such as IEEE 802.15 to establish a wireless personal area network (WPAN). In yet another embodiment, the base station **114b** and the WTRUs **102c**, **102d** may utilize a cellular-based RAT (e.g., WCDMA, CDMA2000, GSM, LTE, LTE-A, LTE-A Pro, NR etc.) to establish a picocell or femtocell. As shown in FIG. 1A, the base station **114b** may have a direct connection to the Internet **110**. Thus, the base station **114b** may not be required to access the Internet **110** via the CN **106/115**.

(51) The RAN **104/113** may be in communication with the CN **106/115**, which may be any type of network configured to provide voice, data, applications, and/or voice over internet protocol (VoIP) services to one or more of the WTRUs **102a**, **102b**, **102c**, **102d**. The data may have varying quality of service (QoS) requirements, such as differing throughput requirements, latency requirements,

error tolerance requirements, reliability requirements, data throughput requirements, mobility requirements, and the like. The CN **106/115** may provide call control, billing services, mobile location-based services, pre-paid calling, Internet connectivity, video distribution, etc., and/or perform high-level security functions, such as user authentication. Although not shown in FIG. **1A**, it will be appreciated that the RAN **104/113** and/or the CN **106/115** may be in direct or indirect communication with other RANs that employ the same RAT as the RAN **104/113** or a different RAT. For example, in addition to being connected to the RAN **104/113**, which may be utilizing a NR radio technology, the CN **106/115** may also be in communication with another RAN (not shown) employing a GSM, UMTS, CDMA 2000, WiMAX, E-UTRA, or WiFi radio technology.

(52) The CN **106/115** may also serve as a gateway for the WTRUs **102a**, **102b**, **102c**, **102d** to access the PSTN **108**, the Internet **110**, and/or the other networks **112**. The PSTN **108** may include circuit-switched telephone networks that provide plain old telephone service (POTS). The Internet **110** may include a global system of interconnected computer networks and devices that use common communication protocols, such as the transmission control protocol (TCP), user datagram protocol (UDP) and/or the internet protocol (IP) in the TCP/IP internet protocol suite. The networks **112** may include wired and/or wireless communications networks owned and/or operated by other service providers. For example, the networks **112** may include another CN connected to one or more RANs, which may employ the same RAT as the RAN **104/113** or a different RAT.

(53) Some or all of the WTRUs **102a**, **102b**, **102c**, **102d** in the communications system **100** may include multi-mode capabilities (e.g., the WTRUs **102a**, **102b**, **102c**, **102d** may include multiple transceivers for communicating with different wireless networks over different wireless links). For example, the WTRU **102c** shown in FIG. **1A** may be configured to communicate with the base station **114a**, which may employ a cellular-based radio technology, and with the base station **114b**, which may employ an IEEE 802 radio technology.

(54) FIG. **1B** is a system diagram illustrating an example WTRU **102**. As shown in FIG. **1B**, the WTRU **102** may include a processor **118**, a transceiver **120**, a transmit/receive element **122**, a speaker/microphone **124**, a keypad **126**, a display/touchpad **128**, non-removable memory **130**, removable memory **132**, a power source **134**, a global positioning system (GPS) chipset **136**, and/or other peripherals **138**, among others. It will be appreciated that the WTRU **102** may include any sub-combination of the foregoing elements while remaining consistent with an embodiment.

(55) The processor **118** may be a general purpose processor, a special purpose processor, a conventional processor, a digital signal processor (DSP), a plurality of microprocessors, one or more microprocessors in association with a DSP core, a controller, a microcontroller, Application Specific Integrated Circuits (ASICs), Field Programmable Gate Arrays (FPGAs) circuits, any other type of integrated circuit (IC), a state machine, and the like. The processor **118** may perform signal coding, data processing, power control, input/output processing, and/or any other functionality that enables the WTRU **102** to operate in a wireless environment. The processor **118** may be coupled to the transceiver **120**, which may be coupled to the transmit/receive element **122**. While FIG. **1B** depicts the processor **118** and the transceiver **120** as separate components, it will be appreciated that the processor **118** and the transceiver **120** may be integrated together in an electronic package or chip.

(56) The transmit/receive element **122** may be configured to transmit signals to, or receive signals from, a base station (e.g., the base station **114a**) over the air interface **116**. For example, in one embodiment, the transmit/receive element **122** may be an antenna configured to transmit and/or receive RF signals. In an embodiment, the transmit/receive element **122** may be an emitter/detector configured to transmit and/or receive IR, UV, or visible light signals, for example. In yet another embodiment, the transmit/receive element **122** may be configured to transmit and/or receive both RF and light signals. It will be appreciated that the transmit/receive element **122** may be configured to transmit and/or receive any combination of wireless signals.

(57) Although the transmit/receive element **122** is depicted in FIG. **1B** as a single element, the

WTRU **102** may include any number of transmit/receive elements **122**. More specifically, the WTRU **102** may employ MIMO technology. Thus, in one embodiment, the WTRU **102** may include two or more transmit/receive elements **122** (e.g., multiple antennas) for transmitting and receiving wireless signals over the air interface **116**.

(58) The transceiver **120** may be configured to modulate the signals that are to be transmitted by the transmit/receive element **122** and to demodulate the signals that are received by the transmit/receive element **122**. As noted above, the WTRU **102** may have multi-mode capabilities. Thus, the transceiver **120** may include multiple transceivers for enabling the WTRU **102** to communicate via multiple RATs, such as NR and IEEE 802.11, for example.

(59) The processor **118** of the WTRU **102** may be coupled to, and may receive user input data from, the speaker/microphone **124**, the keypad **126**, and/or the display/touchpad **128** (e.g., a liquid crystal display (LCD) display unit or organic light-emitting diode (OLED) display unit). The processor **118** may also output user data to the speaker/microphone **124**, the keypad **126**, and/or the display/touchpad **128**. In addition, the processor **118** may access information from, and store data in, any type of suitable memory, such as the non-removable memory **130** and/or the removable memory **132**. The non-removable memory **130** may include random-access memory (RAM), read-only memory (ROM), a hard disk, or any other type of memory storage device. The removable memory **132** may include a subscriber identity module (SIM) card, a memory stick, a secure digital (SD) memory card, and the like. In other embodiments, the processor **118** may access information from, and store data in, memory that is not physically located on the WTRU **102**, such as on a server or a home computer (not shown).

(60) The processor **118** may receive power from the power source **134**, and may be configured to distribute and/or control the power to the other components in the WTRU **102**. The power source **134** may be any suitable device for powering the WTRU **102**. For example, the power source **134** may include one or more dry cell batteries (e.g., nickel-cadmium (NiCd), nickel-zinc (NiZn), nickel metal hydride (NiMH), lithium-ion (Li-ion), etc.), solar cells, fuel cells, and the like.

(61) The processor **118** may also be coupled to the GPS chipset **136**, which may be configured to provide location information (e.g., longitude and latitude) regarding the current location of the WTRU **102**. In addition to, or in lieu of, the information from the GPS chipset **136**, the WTRU **102** may receive location information over the air interface **116** from a base station (e.g., base stations **114a**, **114b**) and/or determine its location based on the timing of the signals being received from two or more nearby base stations. It will be appreciated that the WTRU **102** may acquire location information by way of any suitable location-determination method while remaining consistent with an embodiment.

(62) The processor **118** may further be coupled to other peripherals **138**, which may include one or more software and/or hardware modules that provide additional features, functionality and/or wired or wireless connectivity. For example, the peripherals **138** may include an accelerometer, an e-compass, a satellite transceiver, a digital camera (for photographs and/or video), a universal serial bus (USB) port, a vibration device, a television transceiver, a hands free headset, a Bluetooth® module, a frequency modulated (FM) radio unit, a digital music player, a media player, a video game player module, an Internet browser, a Virtual Reality and/or Augmented Reality (VR/AR) device, an activity tracker, and the like. The peripherals **138** may include one or more sensors, the sensors may be one or more of a gyroscope, an accelerometer, a hall effect sensor, a magnetometer, an orientation sensor, a proximity sensor, a temperature sensor, a time sensor; a geolocation sensor; an altimeter, a light sensor, a touch sensor, a magnetometer, a barometer, a gesture sensor, a biometric sensor, and/or a humidity sensor.

(63) The WTRU **102** may include a full duplex radio for which transmission and reception of some or all of the signals (e.g., associated with particular subframes for both the UL (e.g., for transmission) and downlink (e.g., for reception) may be concurrent and/or simultaneous. The full duplex radio may include an interference management unit **139** to reduce and or substantially

eliminate self-interference via either hardware (e.g., a choke) or signal processing via a processor (e.g., a separate processor (not shown) or via processor **118**). In an embodiment, the WTRU **102** may include a half-duplex radio for which transmission and reception of some or all of the signals (e.g., associated with particular subframes for either the UL (e.g., for transmission) or the downlink (e.g., for reception)).

(64) FIG. 1C is a system diagram illustrating the RAN **104** and the CN **106** according to an embodiment. As noted above, the RAN **104** may employ an E-UTRA radio technology to communicate with the WTRUs **102a**, **102b**, **102c** over the air interface **116**. The RAN **104** may also be in communication with the CN **106**.

(65) The RAN **104** may include eNode-Bs **160a**, **160b**, **160c**, though it will be appreciated that the RAN **104** may include any number of eNode-Bs while remaining consistent with an embodiment. The eNode-Bs **160a**, **160b**, **160c** may each include one or more transceivers for communicating with the WTRUs **102a**, **102b**, **102c** over the air interface **116**. In one embodiment, the eNode-Bs **160a**, **160b**, **160c** may implement MIMO technology. Thus, the eNode-B **160a**, for example, may use multiple antennas to transmit wireless signals to, and/or receive wireless signals from, the WTRU **102a**.

(66) Each of the eNode-Bs **160a**, **160b**, **160c** may be associated with a particular cell (not shown) and may be configured to handle radio resource management decisions, handover decisions, scheduling of users in the UL and/or DL, and the like. As shown in FIG. 1C, the eNode-Bs **160a**, **160b**, **160c** may communicate with one another over an X2 interface.

(67) The CN **106** shown in FIG. 1C may include a mobility management entity (MME) **162**, a serving gateway (SGW) **164**, and a packet data network (PDN) gateway (or PGW) **166**. While each of the foregoing elements are depicted as part of the CN **106**, it will be appreciated that any of these elements may be owned and/or operated by an entity other than the CN operator.

(68) The MME **162** may be connected to each of the eNode-Bs **162a**, **162b**, **162c** in the RAN **104** via an S1 interface and may serve as a control node. For example, the MME **162** may be responsible for authenticating users of the WTRUs **102a**, **102b**, **102c**, bearer activation/deactivation, selecting a particular serving gateway during an initial attach of the WTRUs **102a**, **102b**, **102c**, and the like. The MME **162** may provide a control plane function for switching between the RAN **104** and other RANs (not shown) that employ other radio technologies, such as GSM and/or WCDMA.

(69) The SGW **164** may be connected to each of the eNode Bs **160a**, **160b**, **160c** in the RAN **104** via the S1 interface. The SGW **164** may generally route and forward user data packets to/from the WTRUs **102a**, **102b**, **102c**. The SGW **164** may perform other functions, such as anchoring user planes during inter-eNode B handovers, triggering paging when DL data is available for the WTRUs **102a**, **102b**, **102c**, managing and storing contexts of the WTRUs **102a**, **102b**, **102c**, and the like.

(70) The SGW **164** may be connected to the PGW **166**, which may provide the WTRUs **102a**, **102b**, **102c** with access to packet-switched networks, such as the Internet **110**, to facilitate communications between the WTRUs **102a**, **102b**, **102c** and IP-enabled devices.

(71) The CN **106** may facilitate communications with other networks. For example, the CN **106** may provide the WTRUs **102a**, **102b**, **102c** with access to circuit-switched networks, such as the PSTN **108**, to facilitate communications between the WTRUs **102a**, **102b**, **102c** and traditional land-line communications devices. For example, the CN **106** may include, or may communicate with, an IP gateway (e.g., an IP multimedia subsystem (IMS) server) that serves as an interface between the CN **106** and the PSTN **108**. In addition, the CN **106** may provide the WTRUs **102a**, **102b**, **102c** with access to the other networks **112**, which may include other wired and/or wireless networks that are owned and/or operated by other service providers.

(72) Although the WTRU is described in FIGS. 1A-1D as a wireless terminal, it is contemplated that in certain representative embodiments that such a terminal may use (e.g., temporarily or

permanently) wired communication interfaces with the communication network.

(73) In representative embodiments, the other network **112** may be a WLAN.

(74) A WLAN in Infrastructure Basic Service Set (BSS) mode may have an Access Point (AP) for the BSS and one or more stations (STAs) associated with the AP. The AP may have an access or an interface to a Distribution System (DS) or another type of wired/wireless network that carries traffic in to and/or out of the BSS. Traffic to STAs that originates from outside the BSS may arrive through the AP and may be delivered to the STAs. Traffic originating from STAs to destinations outside the BSS may be sent to the AP to be delivered to respective destinations. Traffic between STAs within the BSS may be sent through the AP, for example, where the source STA may send traffic to the AP and the AP may deliver the traffic to the destination STA. The traffic between STAs within a BSS may be considered and/or referred to as peer-to-peer traffic. The peer-to-peer traffic may be sent between (e.g., directly between) the source and destination STAs with a direct link setup (DLS). In certain representative embodiments, the DLS may use an 802.11e DLS or an 802.11z tunneled DLS (TDLS). A WLAN using an Independent BSS (IBSS) mode may not have an AP, and the STAs (e.g., all of the STAs) within or using the IBSS may communicate directly with each other. The IBSS mode of communication may sometimes be referred to herein as an “ad-hoc” mode of communication.

(75) When using the 802.11ac infrastructure mode of operation or a similar mode of operations, the AP may transmit a beacon on a fixed channel, such as a primary channel. The primary channel may be a fixed width (e.g., 20 MHz wide bandwidth) or a dynamically set width via signaling. The primary channel may be the operating channel of the BSS and may be used by the STAs to establish a connection with the AP. In certain representative embodiments, Carrier Sense Multiple Access with Collision Avoidance (CSMA/CA) may be implemented, for example in 802.11 systems. For CSMA/CA, the STAs (e.g., every STA), including the AP, may sense the primary channel. If the primary channel is sensed/detected and/or determined to be busy by a particular STA, the particular STA may back off. One STA (e.g., only one station) may transmit at any given time in a given BSS.

(76) High Throughput (HT) STAs may use a 40 MHz wide channel for communication, for example, via a combination of the primary 20 MHz channel with an adjacent or nonadjacent 20 MHz channel to form a 40 MHz wide channel.

(77) Very High Throughput (VHT) STAs may support 20 MHz, 40 MHz, 80 MHz, and/or 160 MHz wide channels. The 40 MHz, and/or 80 MHz, channels may be formed by combining contiguous 20 MHz channels. A 160 MHz channel may be formed by combining 8 contiguous 20 MHz channels, or by combining two non-contiguous 80 MHz channels, which may be referred to as an 80+80 configuration. For the 80+80 configuration, the data, after channel encoding, may be passed through a segment parser that may divide the data into two streams. Inverse Fast Fourier Transform (IFFT) processing, and time domain processing, may be done on each stream separately. The streams may be mapped on to the two 80 MHz channels, and the data may be transmitted by a transmitting STA. At the receiver of the receiving STA, the above described operation for the 80+80 configuration may be reversed, and the combined data may be sent to the Medium Access Control (MAC).

(78) Sub 1 GHz modes of operation are supported by 802.11af and 802.11ah. The channel operating bandwidths, and carriers, are reduced in 802.11af and 802.11ah relative to those used in 802.11n, and 802.11ac. 802.11af supports 5 MHz, 10 MHz and 20 MHz bandwidths in the TV White Space (TVWS) spectrum, and 802.11ah supports 1 MHz, 2 MHz, 4 MHz, 8 MHz, and 16 MHz bandwidths using non-TVWS spectrum. According to a representative embodiment, 802.11ah may support Meter Type Control/Machine-Type Communications, such as MTC devices in a macro coverage area. MTC devices may have certain capabilities, for example, limited capabilities including support for (e.g., only support for) certain and/or limited bandwidths. The MTC devices may include a battery with a battery life above a threshold (e.g., to maintain a very long battery

life).

(79) WLAN systems, which may support multiple channels, and channel bandwidths, such as 802.11n, 802.11ac, 802.11af, and 802.11ah, include a channel which may be designated as the primary channel. The primary channel may have a bandwidth equal to the largest common operating bandwidth supported by all STAs in the BSS. The bandwidth of the primary channel may be set and/or limited by a STA, from among all STAs in operating in a BSS, which supports the smallest bandwidth operating mode. In the example of 802.11ah, the primary channel may be 1 MHz wide for STAs (e.g., MTC type devices) that support (e.g., only support) a 1 MHz mode, even if the AP, and other STAs in the BSS support 2 MHz, 4 MHz, 8 MHz, 16 MHz, and/or other channel bandwidth operating modes. Carrier sensing and/or Network Allocation Vector (NAV) settings may depend on the status of the primary channel. If the primary channel is busy, for example, due to a STA (which supports only a 1 MHz operating mode), transmitting to the AP, the entire available frequency bands may be considered busy even though a majority of the frequency bands remains idle and may be available.

(80) In the United States, the available frequency bands, which may be used by 802.11ah, are from 902 MHz to 928 MHz. In Korea, the available frequency bands are from 917.5 MHz to 923.5 MHz. In Japan, the available frequency bands are from 916.5 MHz to 927.5 MHz. The total bandwidth available for 802.11ah is 6 MHz to 26 MHz depending on the country code.

(81) FIG. 1D is a system diagram illustrating the RAN **113** and the CN **115** according to an embodiment. As noted above, the RAN **113** may employ an NR radio technology to communicate with the WTRUs **102a**, **102b**, **102c** over the air interface **116**. The RAN **113** may also be in communication with the CN **115**.

(82) The RAN **113** may include gNBs **180a**, **180b**, **180c**, though it will be appreciated that the RAN **113** may include any number of gNBs while remaining consistent with an embodiment. The gNBs **180a**, **180b**, **180c** may each include one or more transceivers for communicating with the WTRUs **102a**, **102b**, **102c** over the air interface **116**. In one embodiment, the gNBs **180a**, **180b**, **180c** may implement MIMO technology. For example, gNBs **180a**, **180b** may utilize beamforming to transmit signals to and/or receive signals from the gNBs **180a**, **180b**, **180c**. Thus, the gNB **180a**, for example, may use multiple antennas to transmit wireless signals to, and/or receive wireless signals from, the WTRU **102a**. In an embodiment, the gNBs **180a**, **180b**, **180c** may implement carrier aggregation technology. For example, the gNB **180a** may transmit multiple component carriers to the WTRU **102a** (not shown). A subset of these component carriers may be on unlicensed spectrum while the remaining component carriers may be on licensed spectrum. In an embodiment, the gNBs **180a**, **180b**, **180c** may implement Coordinated Multi-Point (CoMP) technology. For example, WTRU **102a** may receive coordinated transmissions from gNB **180a** and gNB **180b** (and/or gNB **180c**).

(83) The WTRUs **102a**, **102b**, **102c** may communicate with gNBs **180a**, **180b**, **180c** using transmissions associated with a scalable numerology. For example, the OFDM symbol spacing and/or OFDM subcarrier spacing may vary for different transmissions, different cells, and/or different portions of the wireless transmission spectrum. The WTRUs **102a**, **102b**, **102c** may communicate with gNBs **180a**, **180b**, **180c** using subframe or transmission time intervals (TTIs) of various or scalable lengths (e.g., containing varying number of OFDM symbols and/or lasting varying lengths of absolute time).

(84) The gNBs **180a**, **180b**, **180c** may be configured to communicate with the WTRUs **102a**, **102b**, **102c** in a standalone configuration and/or a non-standalone configuration. In the standalone configuration, WTRUs **102a**, **102b**, **102c** may communicate with gNBs **180a**, **180b**, **180c** without also accessing other RANs (e.g., such as eNode-Bs **160a**, **160b**, **160c**). In the standalone configuration, WTRUs **102a**, **102b**, **102c** may utilize one or more of gNBs **180a**, **180b**, **180c** as a mobility anchor point. In the standalone configuration, WTRUs **102a**, **102b**, **102c** may communicate with gNBs **180a**, **180b**, **180c** using signals in an unlicensed band. In a non-standalone

configuration WTRUs **102a**, **102b**, **102c** may communicate with/connect to gNBs **180a**, **180b**, **180c** while also communicating with/connecting to another RAN such as eNode-Bs **160a**, **160b**, **160c**. For example, WTRUs **102a**, **102b**, **102c** may implement DC principles to communicate with one or more gNBs **180a**, **180b**, **180c** and one or more eNode-Bs **160a**, **160b**, **160c** substantially simultaneously. In the non-standalone configuration, eNode-Bs **160a**, **160b**, **160c** may serve as a mobility anchor for WTRUs **102a**, **102b**, **102c** and gNBs **180a**, **180b**, **180c** may provide additional coverage and/or throughput for servicing WTRUs **102a**, **102b**, **102c**.

(85) Each of the gNBs **180a**, **180b**, **180c** may be associated with a particular cell (not shown) and may be configured to handle radio resource management decisions, handover decisions, scheduling of users in the UL and/or DL, support of network slicing, dual connectivity, interworking between NR and E-UTRA, routing of user plane data towards User Plane Function (UPF) **184a**, **184b**, routing of control plane information towards Access and Mobility Management Function (AMF) **182a**, **182b** and the like. As shown in FIG. 1D, the gNBs **180a**, **180b**, **180c** may communicate with one another over an Xn interface.

(86) The CN **115** shown in FIG. 1D may include at least one AMF **182a**, **182b**, at least one UPF **184a**, **184b**, at least one Session Management Function (SMF) **183a**, **183b**, and possibly a Data Network (DN) **185a**, **185b**. While each of the foregoing elements are depicted as part of the CN **115**, it will be appreciated that any of these elements may be owned and/or operated by an entity other than the CN operator.

(87) The AMF **182a**, **182b** may be connected to one or more of the gNBs **180a**, **180b**, **180c** in the RAN **113** via an N2 interface and may serve as a control node. For example, the AMF **182a**, **182b** may be responsible for authenticating users of the WTRUs **102a**, **102b**, **102c**, support for network slicing (e.g., handling of different PDU sessions with different requirements), selecting a particular SMF **183a**, **183b**, management of the registration area, termination of NAS signaling, mobility management, and the like. Network slicing may be used by the AMF **182a**, **182b** in order to customize CN support for WTRUs **102a**, **102b**, **102c** based on the types of services being utilized WTRUs **102a**, **102b**, **102c**. For example, different network slices may be established for different use cases such as services relying on ultra-reliable low latency (URLLC) access, services relying on enhanced massive mobile broadband (eMBB) access, services for machine type communication (MTC) access, and/or the like. The AMF **162** may provide a control plane function for switching between the RAN **113** and other RANs (not shown) that employ other radio technologies, such as LTE, LTE-A, LTE-A Pro, and/or non-3GPP access technologies such as WiFi.

(88) The SMF **183a**, **183b** may be connected to an AMF **182a**, **182b** in the CN **115** via an N11 interface. The SMF **183a**, **183b** may also be connected to a UPF **184a**, **184b** in the CN **115** via an N4 interface. The SMF **183a**, **183b** may select and control the UPF **184a**, **184b** and configure the routing of traffic through the UPF **184a**, **184b**. The SMF **183a**, **183b** may perform other functions, such as managing and allocating UE IP address, managing PDU sessions, controlling policy enforcement and QoS, providing downlink data notifications, and the like. A PDU session type may be IP-based, non-IP based, Ethernet-based, and the like.

(89) The UPF **184a**, **184b** may be connected to one or more of the gNBs **180a**, **180b**, **180c** in the RAN **113** via an N3 interface, which may provide the WTRUs **102a**, **102b**, **102c** with access to packet-switched networks, such as the Internet **110**, to facilitate communications between the WTRUs **102a**, **102b**, **102c** and IP-enabled devices. The UPF **184a**, **184b** may perform other functions, such as routing and forwarding packets, enforcing user plane policies, supporting multi-homed PDU sessions, handling user plane QoS, buffering downlink packets, providing mobility anchoring, and the like.

(90) The CN **115** may facilitate communications with other networks. For example, the CN **115** may include, or may communicate with, an IP gateway (e.g., an IP multimedia subsystem (IMS) server) that serves as an interface between the CN **115** and the PSTN **108**. In addition, the CN **115** may provide the WTRUs **102a**, **102b**, **102c** with access to the other networks **112**, which may

include other wired and/or wireless networks that are owned and/or operated by other service providers. In one embodiment, the WTRUs **102a**, **102b**, **102c** may be connected to a local Data Network (DN) **185a**, **185b** through the UPF **184a**, **184b** via the N3 interface to the UPF **184a**, **184b** and an N6 interface between the UPF **184a**, **184b** and the DN **185a**, **185b**.

(91) In view of FIGS. **1A-1D**, and the corresponding description of FIGS. **1A-1D**, one or more, or all, of the functions described herein with regard to one or more of: WTRU **102a-d**, Base Station **114a-b**, eNode-B **160a-c**, MME **162**, SGW **164**, PGW **166**, gNB **180a-c**, AMF **182a-b**, UPF **184a-b**, SMF **183a-b**, DN **185a-b**, and/or any other device(s) described herein, may be performed by one or more emulation devices (not shown). The emulation devices may be one or more devices configured to emulate one or more, or all, of the functions described herein. For example, the emulation devices may be used to test other devices and/or to simulate network and/or WTRU functions.

(92) The emulation devices may be designed to implement one or more tests of other devices in a lab environment and/or in an operator network environment. For example, the one or more emulation devices may perform the one or more, or all, functions while being fully or partially implemented and/or deployed as part of a wired and/or wireless communication network in order to test other devices within the communication network. The one or more emulation devices may perform the one or more, or all, functions while being temporarily implemented/deployed as part of a wired and/or wireless communication network. The emulation device may be directly coupled to another device for purposes of testing and/or may performing testing using over-the-air wireless communications.

(93) The one or more emulation devices may perform the one or more, including all, functions while not being implemented/deployed as part of a wired and/or wireless communication network. For example, the emulation devices may be utilized in a testing scenario in a testing laboratory and/or a non-deployed (e.g., testing) wired and/or wireless communication network in order to implement testing of one or more components. The one or more emulation devices may be test equipment. Direct RF coupling and/or wireless communications via RF circuitry (e.g., which may include one or more antennas) may be used by the emulation devices to transmit and/or receive data.

(94) Wireless Power Transfer

1. BACKGROUND

(95) The feasibility of using resonant objects coupled through their nonradiative fields for mid-range energy transfer have been demonstrated. Intuitively, two resonant objects tuned at the same resonant frequency may tend to exchange energy efficiently. In addition, since most common materials do not interact with magnetic fields, magnetic resonance systems may be particularly suitable for everyday applications.

(96) When multiple come within range of each other, they may (e.g., there arises a need to) coordinate their interaction and/or minimize cross-interference.

(97) In LTE and other cellular systems, a Common Control Channel (CCCH) may be responsible for transferring control information between all mobile devices (e.g., WTRUs **102**) and the Base Transceiver Station (BTS). This is (e.g., necessary) for the implementation of “call origination” and/or “call paging” functions.

(98) A Physical Broadcast Channel (PBCH) may carry system information for UEs attempting to access the network. In Universal Mobile Telecommunication System (UMTS), the group of Broadcast Channels (BCHs) may include three channels, namely, Broadcast Control Channel (BCCH), Frequency Correction Channel (FCCH), and/or Synchronization Channel (SCH). A Cell Broadcast Channel (CBCH) may be used to transmit messages to be broadcast to all Mobile Stations (MSs) within a cell. A MS may (e.g., then) move to a dedicated channel in order to proceed with either call setup, response to a paging message, Location Area Update, or Short Message Service (SMS).

(99) The Medium Access Control (MAC) layer may control the higher layers' access to the PHY layer. The MAC layer may be connected to the PHY layer below it through transport channels, and to the RLC layer above it through logical channels. The MAC layer may decide which logical channels can access the transport channels at a given time and performs multiplexing and/or de-multiplexing of the data between them. The MAC layer may basically provide the radio resource allocation service and/or the data transfer service to the upper layer.

(100) 1.1. Resonance Magnetic Coupled System Overview

(101) A diagram of a resonance magnetic WPT and communications system is shown in FIG. 2. A single turn drive loop **201** coupled to a multi-turn spiral coil **203** make up the transmit antenna. In a case where the transmitter (TRX) amplifier **205** powers the drive loop **201**, the resulting oscillating magnetic field may excite the Tx coil **203**, which may store energy in the same manner as a discrete LC tank. The Rx coil **207** and/or the Load loop coil **209** on the receive side may function in a similar, complementary manner. The key interaction may occur between the Tx coil **203** and/or the Rx coil **207**, any (e.g., each) of which may be a high-Q RLC (high-quality resistor, inductor, capacitor) tank resonator. In a case where (e.g., just as) the loop and coil (**201** and **203** or **209** and **207**) may be magnetically coupled, the transmit and receive coils (**205** and **207**) may share a mutual inductance which may be a function of the geometry of the coils and/or the distance between them. FIG. 3 is a graph illustrating a typical plot of resonance magnetic frequency as a function of distance for a resonance magnetically coupled system.

(102) Equivalently, in a case where driving a wireless power system with a Radio Front end (RF) source and/or using a load resistor on the receiver to extract work from the system, the amount of coupling may define how much energy may be transferred per cycle. This means that there may be a distance (called the critical coupling point) beyond which the system may no longer drive a given load at maximum efficiency. An analytic model of the magnetically coupled resonator system is presented in the next section. This is followed by derivations of key system parameters and figures of merit. Finally, a description of adaptive tuning techniques used to achieve near constant efficiency vs. distance is presented.

(103) 1.1.1. Circuit Model and Transfer Function

(104) FIG. 4 is a diagram of a resonant magnetic power transfer circuit model. The resonance magnetic system modeled in FIG. 4 may use lumped circuit elements to describe the resonance magnetic system. It shows four circuits magnetically coupled as represented by coefficients k_{12A} , k_{AB} , k_{12B} . The drive loop, on the left side, may be excited by a source with output impedance R_s , a single turn drive loop modeled as inductor L_1 , with parasitic resistance R_{p1} . Capacitor, C_1 , along with L_1 , may set the drive loop resonance frequency.

(105) The transmit coil may comprise (e.g., consist of) a multi-turn spiral inductor (L_2), with parasitic resistance (R_{p2}) and/or self-capacitance C_2 . Inductors L_1 and L_2 may be linked with coupling coefficient k_{12A} . The receiver side may share a similar topology.

(106) The transmitter and receiver coils may be linked by coupling coefficient, k_{AB} . In a typical implementation of the system, k_{AB} may vary, for example, as a function of the distances between the transmitter and receiver.

(107) Electric circuit theory (ECT) may be one of the tools that allows the design and analysis of WPT systems. For the resonant magnetic circuit model shown in FIG. 4, the current in any (e.g., each) resonant circuit may be determined using Kirchhoff's voltage law (1-4):

$$(108) \quad I_1(R_s + R_{p1} + j\omega L_1 + \frac{1}{j\omega C_1}) + j\omega I_2 M_{12} = V_s \quad (1)$$

$$I_2(R_{p2} + j\omega L_2 + \frac{1}{j\omega C_2}) + j\omega (I_1 M_{12} - I_3 M_{23}) = 0 \quad (2)$$

$$I_3(R_{p3} + j\omega L_3 + \frac{1}{j\omega C_3}) + j\omega (I_4 M_{34} - I_2 M_{23}) = 0 \quad (3)$$

$$I_4(R_L + R_{p4} + j\omega L_4 + \frac{1}{j\omega C_4}) + j\omega I_3 M_{34} = 0 \quad (4)$$

(109) The coupling coefficient may be defined as:

$$(110) \quad k_{xy} = \frac{M_{xy}}{\sqrt{L_x L_y}}, 0 \leq k_{xy} \leq 1 \quad (5)$$

where M is mutual inductance (e.g., M.sub.12 is the mutual inductance between coils **1** and **2**); and ω is frequency.

(111) After solving these four KVL equations for the voltage across the load resistor, we have:

$$(112) \quad \frac{V_L}{V_S} = \frac{j^3 k_{12} k_{23} k_{34} L_2 L_4 \sqrt{L_1 L_4} R_L}{(k_{12}^2 k_{34}^2 L_1 L_2 L_3^4 + Z_1 Z_2 Z_3 Z_4 + (k_{12}^2 L_1 L_2 L_3 Z_4 + k_{23}^2 L_2 L_3 Z_1 Z_4 + k_{34}^2 L_3 L_4 Z_1 Z_2))} \quad (6)$$

(113) Using the following substitutions:

$$(114) \quad Z_1 = R_{p1} + R_s + j \omega L_1 - \frac{1}{j \omega C_1} \quad (7) \quad Z_2 = R_{p2} + j \omega L_2 - \frac{1}{j \omega C_2} \quad (8)$$

$$Z_3 = R_{p3} + j \omega L_3 - \frac{1}{j \omega C_3} \quad (9) \quad Z_4 = R_{p4} + R_L + j \omega L_4 - \frac{1}{j \omega C_4} \quad (10)$$

one can calculate the equivalent S.sub.21 scattering parameter using [1], [2] which results in equation:

$$(115) \quad S_{21} = 2 \frac{V_L}{V_S} \left(\frac{R_S}{R_L} \right)^{1/2} \quad (11)$$

1.1.2. Derivation of Critical Coupling and System Parameters

(116) First, the equation of critical coupling may be derived by substituting the term for series quality factor and/or resonant frequency, shown in the equation below, into the transfer function.

$$(117) \quad Q_i = \frac{1}{R_i} \sqrt{\frac{L_i}{C_i}} = \frac{j \omega L_i}{R_i} = \frac{1}{j \omega R_i C_i} \quad (12) \quad i = \frac{1}{\sqrt{L_i C_i}} \quad (13)$$

(118) The voltage gain at the center frequency $\omega_{sub.0}$ is presented in the following equation:

$$(119) \quad \left(\frac{V_L}{V_S} \right)_{\omega_{sub.0}} = \frac{ik_{cc} k_{12}^2 Q_{coil}^2 Q_{loop}^2}{k_{cc}^2 Q_{coil}^2 + (1 + k_{12}^2 Q_{coil} Q_{loop})^2} \quad (14)$$

where k.sub.cc is a notation representing the symmetric coil-to-coil coupling (e.g., k.sub.AB and k.sub.BA). Solving for k.sub.cc, notation for the symmetric coil-to-coil coupling (k.sub.AB and k.sub.BA), yields:

$$(120) \quad k_{crit} = \frac{1}{Q_{coil}} + k_{12}^2 Q_{loop} \quad (15)$$

where K.sub.crit is the critical coupling coefficient, e.g., the point above which energy transfer is no longer practical (K.sub.crit is the coupling efficiency at point **301** in the frequency/distance plot of FIG. **3**); Q.sub.coil is the quality factor of the coil; Q.sub.loop is the quality factor or the drive loop; and K.sub.12 is the coupling factor (or coupling coefficient) between the loop and the coil. At the critical coupling point:

$$(121) \quad \left(\frac{V_L}{V_S} \right)_{crit} = \frac{k_{12}^2 Q_{coil} Q_{loop}}{1 + k_{12}^2 Q_{coil} Q_{loop}} = \frac{k_{12}^2 Q_{loop}}{k_{crit}} \quad (16)$$

(122) Reducing k.sub.12, the loop-to-coil coupling, lowers k.sub.crit and (e.g., therefore) may increase range. However, according to equation (16), reducing k.sub.12 may (e.g., also) reduce efficiency.

(123) Radiative far-field communication systems may not be impacted by the number, location, and/or orientation of devices; but mid-field RMC channels, (e.g., in addition to their dependency on all the above) may be also dependent on the load termination at the devices.

(124) As the number of devices (e.g., WTRUs **102**) introduced within a given RMC range increases, the power coupled into the mid-field by a transmitter to any (e.g., each) of the devices (e.g., WTRUs **102**) may decrease, e.g., the total power coupled into the mid-field by a transmitter may be divided amongst the receiving devices. The amount of energy coupled to a receiver may be proportional to its coupling factor and/or inversely proportional to the number of receiving devices (e.g., WTRUs **102**) in range. Any remaining power, for example not absorbed by a load, may be reflected at the transmitting source.

(125) Resonance magnetic coupling may facilitate mid-field WPT. Mobility may be supported within the mid-field range at the cost of adjusting the tank circuit's resonance frequency to compensate for changes in location and/or orientation of the magnetically coupled devices. As two devices (e.g., WTRUs **102**) move relative to each other (including both rotation and translation), the coupling efficiency between them at a given frequency may change. As two devices (e.g., WTRUs **102**) move relative to each other, the optimal frequency for maximum energy coupling between the two devices (e.g., WTRUs **102**) may change.

(126) New procedures have been developed to enable device discovery within the RMC framework and/or to establish device-to-device communication.

(127) With the likely scenario of multiple device pairs communicating within the same RMC range, that may cause potential interference to adjacent device pairs, the access to the network from multiple devices (e.g., WTRUs **102**) may be moderated, for example, while taking into account the number and/or proximity of those devices.

(128) Herein are disclosed methods, apparatus, and procedures to leverage the loading effect to moderate access to RMC networks and/or to use non-transmitting devices (e.g., WTRUs **102**) to improve information transfer over active RMC links.

2. RMC IN COMMUNICATION SYSTEMS

(129) This section considers WTRUs leveraging loading effect of devices (e.g., WTRUs **102**) coupled to a common or dedicated channel to moderate/manage and/or optimize access to RMC network resources. It also considers WTRUs acting as a cluster head and/or moderating/managing devices (e.g., WTRUs **102**) inclusion and/or exclusion from a cluster to optimize links quality amongst cluster pairs over unicast and/or broadcast channels.

2.1. RMC NETWORK ACCESS CONTROL FOR INFORMATION TRANSFER

(130) FIG. 5 is a diagram illustrating a typical broadcast scenario for a cluster head A (e.g., WTRU **501**) managing a number of devices (e.g., WTRUs **102**) in a broadcast group. In this example, devices (e.g., WTRUs **102**) C and D may have an RMC data link and cluster head A (e.g., WTRU **501**) and device B may have a RMC data link. The cluster head A (e.g., WTRU **501**) may broadcast control information to (e.g., all) the devices (e.g., WTRUs **102**) under its control, e.g., B, C, and D. The individual devices (e.g., WTRUs **102**) may exchange control information amongst themselves, such as illustrated between devices (e.g., WTRUs **102**) B and D and/or between devices (e.g., WTRUs **102**) C and D.

(131) Devices E and F may have a RMC data link between them, but they are not within range of the cluster head A (e.g., WTRU **501**), and/or thus may not be managed by cluster head A (e.g., WTRU **501**). They may be managed by a different cluster head (e.g., WTRU **501**) (not shown) or may operate autonomously of any cluster head (e.g., WTRU **501**).

(132) 2.1.1. Centralized Versus Distributed Framework

(133) As illustrated in FIG. 6, two main frameworks may be typically considered to moderate the medium access: a centralized framework and a distributed framework. In centralized wireless networks, such as infrastructure mode in WLANs and cellular networks, the Access Point (AP) or Base Station (BS) may consider broadcast transmission in the down link and/or may control the uplink access, for example, according to specific Quality of Service (QoS) targets. On the other hand, distributed wireless networks, such as packet radio or ad hoc networks (as in IEEE 802.11), may have no central controller and/or may utilize techniques such as ALOHA and/or Carrier Sense Multiple Access-Collision Avoidance/Collision Detection (CSMA-CA/CD) for medium access control.

(134) In this disclosure, we consider a centralized framework where a cluster head (e.g., WTRU **501**) may be responsible for coordinating access to RMC network resources.

(135) A cluster may be formed when two or more devices (e.g., WTRUs **102**) appear within RMC range of each other, for example, following a discovery procedure initiated by one or more of those devices. Further, in this centralized framework, a cluster head (e.g., WTRU **501**) may be a device

responsible for coordinating with other cluster members to establish a common channel that may be used for broadcast communication. The ability to communicate with other cluster members with a Signal to Noise Ratio (SNR) above a minimum threshold either simultaneously or consecutively in time, may be one of the main qualifications for this function.

(136) 2.1.2. Impact of Load Termination

(137) In traditional wireline communication systems, data transmission between multiple device pairs may be conducted over a single wire/cable (the channel), using a combination of frequency division multiplexing (FDM) and/or time division multiplexing (TDM). Any (e.g., each) data link may be assigned a segment of the channel bandwidth for transmission. The receiving devices (e.g., WTRUs **102**) may be tuned to their designated channel frequencies to terminate the communication link. Owing to frequency orthogonality and/or filtering, individual link performance may not be affected by other devices (e.g., WTRUs **102**) operating in adjacent channels.

(138) Similarly, in far-field communication systems, the received signal strength by a device (e.g., WTRU **102**) may not be dependent on the power received by other devices (e.g., WTRUs **102**) in the far field. It may be a function of the distance from the transmitting device (e.g., WTRU **102**) and/or the channel characteristics, such as fading and/or frequency dependent attenuation.

(139) In resonance magnetic mid-field communication systems, energy may be coupled from the data source to the receiving devices.

(140) The three aforementioned data transmission frameworks, namely, wireline, far field, and/or mid-field, are shown in FIGS. 7A, 7B, and 7C, respectively.

(141) A good analogy for the mid-field transmission framework may be a transformer with a primary coil and multiple secondary coils, in which the coupled power may be divided amongst the multiple receiving devices. The analogy is illustrated in FIGS. 8A and 8B, which are a loading model and a transformer representation of a plurality of load devices (e.g., WTRUs **102**) coupled to a single power source, respectively. In this framework, the received signal may be dependent on the number of devices (e.g., WTRUs **102**) coupled to the mid-field source and their loading effects. If a receiving device (e.g., WTRU **102**) extracts significantly more than the minimum required signal power required to maintain a working data link, that power may not be available to a potentially “starving” link where the received signal strength may be below a minimum threshold. Load-based access control may facilitate a less wasteful allocation of signal energy, especially to devices (e.g., WTRUs **102**) operating at the outer edge of a resonance magnetic cell or cluster.

(142) Using the load termination state of devices (e.g., WTRUs **102**) during transmission and/or reception cycles, a CLH (e.g., WTRU **501**) may manage device-pairs in a unicast link to minimize interference between adjacent links. The load termination state of a device (e.g., WTRU **102**) (e.g., essentially) may be the impedance (e.g., in Ohms) that it presents to another device (e.g., WTRU **102**) to which it is magnetically coupled. This value may be dynamically set in order to control the resonance magnetic coupling efficiency between two devices. Load termination states may range from a matched conjugate termination value of 50 Ohms (e.g., in a 50 Ohms system), to a float-state where no energy may be absorbed/transferred to the device. The load termination state may take on multiple discrete values (e.g., $Z_{sub.1}$, $Z_{sub.2}$, . . . , Z_n) between and including these two settings, e.g. 75 Ohms, 100 Ohms, etc.

(143) After receiving a request for unicast link formation from device-pairs, the CLH (e.g., WTRU **501**) may assign an RMC channel along with load termination states for any (e.g., each) device.

(144) Additionally or alternately, the CLH (e.g., WTRU **501**) may assign a table of load termination states, for example, as a function of signal strength threshold levels (e.g., RSSI or SNR) to any (e.g., each) pair of devices. During normal operation, as channel conditions vary, a device (e.g., WTRU **102**) may independently select the correct load termination without direct intervention or instruction from the cluster head (e.g., WTRU **501**).

(145) The load termination state for the Tx cycle for a device (e.g., WTRU **102**) may be different than the load termination state for the receive period of the device. The load termination state may

also change from time period to time period. Unicast link TX/RX periods may be allocated amongst users according to priority levels, link quality, and/or data transfer rate needs.

(146) 2.1.3. Scheduling Functionality and Control Information

(147) In a centralized framework, the cluster head (e.g., WTRU **501**) may function as the Control Plane and may be responsible for creating a “routing/scheduling” table for data packet traffic between communicating device (e.g., WTRU **102**) pairs. To facilitate the cluster head's function, any (e.g., each) data transfer period is preceded by a control period where a device (e.g., WTRU **102**) in a cluster can share its capability and/or status with the cluster head (e.g., WTRU **501**).

(148) For example, during the control period, any of the following information may be exchanged with the cluster head (e.g., WTRU **501**): A request for link establishment with a specific device (e.g., WTRU **102**) within the cluster or directly with the cluster head (e.g., WTRU **501**); Desired QoS requirements, including, e.g., a certain priority and/or reliability requirement; Buffer status indicating how much information (e.g., needs) to be exchanged; A channel quality metric as an indication of, e.g., a supported data and/or coding rate; and/or Capability information, such as supported load termination states and/or coupling coefficients.

(149) Based on any of the link establishment requests, information provided, and/or available network resources, the cluster head (e.g., WTRU **501**) may create any of a scheduling table with time slot assignments, load termination states for non-transmitting devices (e.g., WTRUs **102**) in any (e.g., each) slot, and/or a synchronization signal for any (e.g., each) device. A grant access message may be sent to any (e.g., each) device-pair describing their behavior requirements in any (e.g., each) time-slot during the data transfer/exchange period.

(150) For better resource allocation, Time Division Multiplexing (TDM) and/or Frequency Division Multiplexing (FDM) may be combined. For instance, any (e.g., each) link may be assigned a carrier frequency and the cluster head (e.g., WTRU **501**) may further divide and/or allocate access times. As a result, two or more links may be time multiplexed on the same physical channel. The time slot usage may be proportionately divided amongst users based on any one or more of QoS (priority and/or reliability), data rate requirements, and/or buffer status.

(151) To summarize, the CLH (e.g., WTRU **501**) may act as a radio resource manager and allocate a data traffic channel (a radio channel and/or associated time-slot) for every device-pair once authentication, data requirements, and/or SNR contours have been reported over the pre-established Broadcast Channel (BCH).

(152) FIGS. **9A** and **9B** illustrate two examples of a control frame format that is exchanged during the control period. FIG. **9A** shows an exemplary format for scheduling and/or control. In this format, a device (e.g., WTRU **102**) may report (e.g., transmit information indicating) any of: its ID, a requested QoS, the CQI, and/or a buffer status. FIG. **9B** shows an exemplary format for a device (e.g., WTRU **102**) to report (e.g., transmit information indicating) its capabilities to the cluster head (e.g., WTRU **501**). In this format, a device (e.g., WTRU **102**) may report (e.g., transmit information indicating) any of: its ID, the features that it may support, the load states that may be possible, and/or the coupling coefficients that may be possible for that device. There may be two approaches/strategies for time-slot allocation, either fixed or dynamic. These approaches are described below.

(153) Fixed time-slot assignment strategies may be generally simple but may be inefficient due to the inability to reallocate slots to other devices (e.g., WTRUs **102**) when not used (e.g., needed) in every frame. It may be challenging to generate fixed schedules for an entire cluster that may use (e.g., require) adjustments for (e.g., every) change in cluster topology or traffic characteristics.

(154) Dynamic time-slot assignment strategies may allow devices (e.g., WTRUs **102**) to access the medium on demand. In particular, traffic-adaptive protocols may increase network throughput and/or energy efficiency by determining when node devices (e.g., WTRUs **102**) may be allowed to transmit, for example, based on information about the traffic on any (e.g., each) link. The last slot in the schedule may be used to announce the next schedule for the coming interval. However, such

a strategy may add considerable overhead and/or complexity to the cluster head (e.g., WTRU 501). (155) FIGS. 10A and 10B illustrate exemplary content for a downlink control plane frame (e.g., from the CLH (e.g., WTRU 501) to the linked devices (e.g., WTRUs 102)) and an uplink control plane frame (e.g., from the devices to the CLH) in accordance with an embodiment. As shown in FIG. 10A, the downlink control frame may include any of slot assignments, load termination states, and/or schedule associated with any (e.g., each) device (e.g., WTRU 102) ID. As shown in FIG. 10B, any (e.g., each) device (e.g., WTRU 102) may acknowledge reception of the downlink control information, for example, by replying according to their assigned time slots.

(156) 2.1.4. Management of Load Termination States in an RMC System

(157) In this section, using a centralized cluster framework where a cluster head (e.g., WTRU 501) may have already been selected, devices (e.g., WTRUs 102) supporting a plurality of (e.g., multiple) load termination states may consider load termination states as resources to be scheduled as part of resource allocation amongst cluster devices (e.g., WTRUs 102) to improve communication link performance. Two potential scenarios may be considered, one in which any (e.g., each) device (e.g., WTRU 102) may (e.g., only) support two (binary) load termination states (float/open and load/closed states) and another scenario in which any (e.g., each) device (e.g., WTRU 102) may support more than two load termination states.

(158) 2.1.4.1. Multiple Load Termination States Support

(159) CLH Managing Access to BCH with Multiple Load Termination States

(160) In an embodiment, a cluster head (e.g., WTRU 501) may assign a load termination state to a specific device, for example, according to experienced SNR and/or Received Signal Strength Indicator (RSSI) level. The cluster head (e.g., WTRU 501) may request and/or receive SNR tables (contours) from any number of devices (e.g., WTRUs 102) (e.g., in a first step). The CLH (e.g., WTRU 501) may determine (e.g., in a second step) a reasonable load termination state for any (e.g., each) device (e.g., WTRU 102) based on the device's supported capabilities and/or experienced SNR/RSSI level over the BCH. In this example, load termination states may range from a matched conjugate termination value of 50 Ohms (e.g., in a 50 Ohms system), to a float-state where, for example, no energy is absorbed/transferred to the device. The load termination state may then take-on a plurality of (e.g., multiple) discrete values (e.g., $Z_1, Z_2, \dots, Z_n$) between and including these two settings, e.g. 75 Ohms, 100 Ohms, etc.

(161) For example, for a device (e.g., WTRU 102) that receives a signal strength (e.g., RSSI) that may be much greater than a minimum threshold and/or above a second threshold, the cluster head (e.g., WTRU 501) may assign a load termination state such that the signal power delivered to the device (e.g., WTRU 102) will be reduced to a level below the aforementioned second threshold. This may be helpful because the excess or unused energy may remain available in the magnetic field for other cluster members to extract, as needed. In another example, for a device (e.g., WTRU 102) that may receive a signal with a strength that is marginally above the defined minimum threshold, the CLH (e.g., WTRU 501) may assign the optimum load termination state, e.g. 50 Ohms, for example, in order to enable maximum power transfer to that device.

(162) The above described scenario/example is illustrated in FIG. 11, in which an exemplary device (e.g., WTRU 102) may support three load termination states ($Z_{\text{sub.1}}, Z_{\text{sub.2}}, Z_{\text{sub.3}}$). For example, after (e.g., when) received signal strength is below THLD1, the device (e.g., WTRU 102) may switch to an optimal load termination state, $Z_{\text{sub.1}}$ (e.g., 50 Ohms). For RSSI level between the two thresholds (THLD1 and THLD2), the load state may be set to a slightly mismatched value $Z_{\text{sub.2}}$ (e.g., 30, 40 or 75 Ohms). For very strong RSSI values, e.g., above THLD2, the load state may switch to a sub-optimal value of $Z_{\text{sub.3}}$ (e.g., 100 Ohms), where, “excess” signal power may be not extracted from the resonance magnetic medium and/or may remain available for use by other devices (e.g., WTRUs 102) coupled to the channel.

(163) In various embodiments, at the cluster creation/formation phase, the CLH (e.g., WTRU 501) may assign a table of load termination states versus threshold levels to any (e.g., each) cluster

member device. During normal operation, a device (e.g., WTRU **102**) may autonomously and/or dynamically select the correct load termination without direct intervention or instruction from the cluster head (e.g., WTRU **501**). This is illustrated in FIG. **12**. For example, during Tslot-1, link LAB is not coupled to the channel and link LCD's load termination may be set according to the current, or previously measured, SNR/RSSI level between devices (e.g., WTRUs **102**) C and D. For example, if the SNR/RSSI is below THLD1, the termination may be set to Z1, if SNR/RSSI is between THLD1 and THLD2, the termination may be set to Z2, etc. The difference is that the threshold setting may be semi-static as opposed to a dynamically changing threshold based on, e.g., number of cluster members, channel conditions, traffic activity, etc. All devices (e.g., WTRUs **102**) may have the same load termination states capabilities.

(164) In various embodiments, for improvement in resource utilization on the Broadcast Channel, the CLH (e.g., WTRU **501**) may assign time slots with associated load termination states for any (e.g., each) device. The CLH (e.g., WTRU **501**) may broadcast a schedule to all cluster devices (e.g., WTRUs **102**) listing respective device (e.g., WTRU **102**) load termination states during any (e.g., each) time slot and/or transmission period. A plurality of (e.g., multiple) devices (e.g., WTRUs **102**) may be time multiplexed on the same physical channel. The time slot usage may be proportionally divided amongst users based on priority and/or data rate requirements.

(165) In various embodiments, the cluster head (e.g., WTRU **501**) may monitor the average SNR of devices (e.g., WTRUs **102**) in the cluster and may determine if (e.g., when) the average cluster SNR on BCH falls below a threshold and/or the number of members in the cluster exceeding a predetermined count. When the condition is met, the CLH (e.g., WTRU **501**) may create N subgroups of devices (e.g., WTRUs **102**), assigning devices (e.g., WTRUs **102**) to any (e.g., each) group, where one group may access the Broadcast Channel at a given time, resulting in an improved average SNR.

(166) Such an embodiment is illustrated in the flowchart of FIG. **13**. At **1301**, the CLH (e.g., WTRU **501**) may measure the average SNR for the devices (e.g., WTRUs **102**). At **1303**, the CLH (e.g., WTRU **501**) may determine if the average SNR is below a threshold. The CLH (e.g., WTRU **501**) may break the devices (e.g., WTRUs **102**) down into N sub groups (**1305**). At **1307**, the CLH (e.g., WTRU **501**) may assign a unique time slot to any (e.g., each) of the N groups for accessing the BCH and may set a counter to n=1. At **1309**, the CLH (e.g., WTRU **501**) may set the time slot to n and/or the load termination state for group n to LOAD (or ON) for that time slot (or, in a system with a plurality of (e.g., multiple) load termination states, to one of the predetermined load termination states, e.g., the most preferable one). At **1311**, the CLH (e.g., WTRU **501**) may set the load termination state of all other sub groups to FLOAT (or OFF) for that time slot (or, if the system supports a plurality of (e.g., multiple) load termination states, to another load termination state value), may broadcast the relevant control and/or configuration information to the devices (e.g., WTRUs **102**) in sub group n, and may increment the counter. At **1313**, the CLH (e.g., WTRU **501**) may determine if it has assigned any (e.g., each) sub group a time slot for using the BCH. If not, flow may proceed back to step **1309** so that the any (e.g., each) sub group is assigned a time slot in which to use the BCH. Otherwise, it may return to normal operation.

(167) The data scheduling period along with device (e.g., WTRU **102**) loading behavior may be structured by the cluster head (e.g., WTRU **501**) using information, for example, collected from cluster devices (e.g., WTRUs **102**) during the control period. FIGS. **14** and **15** show examples. In the scenario shown in FIG. **14**, the system may support a binary load termination state, wherein link AB (L.sub.AB) may be (e.g., continuously) on, whereas, links LEF and LCD may be active during their allocated time slots, for example, according to a schedule generated by the CLH **102a**.

(168) Another example of device (e.g., WTRU **102**) load termination states during a transmit period is illustrated in FIG. **15**. In this example, device A (e.g., WTRU **102a**) may transmit data in slots **1** and **2**, "FLOAT"s its coil in slots **4** and **5** and "LOAD"s the magnetic medium in slots **3** and **6** with an assigned load termination supported value of Zi. Similarly, device B (e.g., WTRU **102b**)

may transmit data in slots **4** and **5**, while, in this example, device A (e.g., WTRU **102a**) may remain in “FLOAT” state. Device C (e.g., WTRU **102c**), recruited as a facilitator, may load the medium with an assigned termination impedance value of Z_k . Device C (e.g., WTRU **102c**) may get to transmit in the remaining time slots **3** and **6** with device A acting as a facilitator terminated with value of $Z_{sub.i}$.

(169) Yet another example of device load termination states during a transmit period is illustrated in FIG. **16**. In this example, during a receive period, device A (e.g., WTRU **102a**) may receive data in slots **1** and **2**, FLOATs its coil in slots **3** and **6** to free-up medium resources, and LOADs the medium with Z_m in slots **4** and **5** in support of device B during its own receive cycle. Device B may receive data in slots **4** and **5**, FLOATs during slots **1** and **2**, and may present a load termination of to the medium in slots **3** and **6**, thus supporting device C's receive periods. Finally, device C (e.g., WTRU **102c**) LOADs the medium in slots **1** and **2** with an assigned impedance value of Z_l , FLOATs during slots **4** and **5**, and may receive in slots **3** and **6**.

(170) Mobility Control

(171) A device's mobility within the cluster may affect (e.g., both) its received signal strength and/or the link quality of adjacent device-pairs. The cluster head (e.g., WTRU **501**) may implement control procedures to mitigate the impact of mobile devices (e.g., WTRUs **102**) on the overall cluster performance.

(172) For example, after receiving a change in link quality report (e.g., SNR or RSSI falling below a pre-determined threshold) from a device (e.g., WTRU **102**) on the broadcast channel, the CLH (e.g., WTRU **501**) may proceed to determine and/or send re-balancing instructions to the device, e.g., adjustment to any of the following settings: Coupling factor; Load termination state; Assigned time slots; and/or Center frequency.

(173) The exact change to the above settings may be based on newly reported SNR versus frequency curves in tabular form. The cluster head (e.g., WTRU **501**), using these curves, may assess changes in channel responses, including bandwidth and Q and determine the best settings for new induced channel characteristics. Subsequently, the device (e.g., WTRU **102**) may send the CLH (e.g., WTRU **501**) an updated report, with new SNR/RSSI measurements, presumably confirming an improvement in the link quality.

(174) CLH Handling Request for Unicast Link Formation

(175) In various embodiments, the CLH (e.g., WTRU **501**) may receive a request from a device (A) (e.g., WTRU **102a**), to form a unicast link with another device (B) (e.g., WTRU **102b**). The CLH (e.g., WTRU **501**), using existing or updated SNR tables along with new link information and/or energy transfer requirements, may assign a channel for the unicast link formation and/or determine a load termination state for devices (e.g., WTRUs **102**) A and B to minimize potential interference to other concurrently running unicast links. The CLH (e.g., WTRU **501**) may transmit time slot assignments to the device-pair to further reduce interference or maximize cluster resource utilization.

(176) 2.1.4.2. Binary Load Termination States Support

(177) CLH Managing Devices Supporting Binary Load Termination States (e.g., Only)

(178) Since, devices (e.g., WTRUs **102**) in Float-State may not receive transmissions on the BCH, a form of scheduled access is desirable.

(179) In various embodiments, devices (e.g., WTRUs **102**) (e.g., only) supporting binary load termination states may be present, e.g., Float (Open) or Load (Closed). The CLH (e.g., WTRU **501**) may divide the cluster into two or more groups to potentially accommodate a larger number of devices (e.g., WTRUs **102**) on the BCH. The cluster head (e.g., WTRU **501**) may assign devices (e.g., WTRUs **102**) to any (e.g., each) group based on the ability to (e.g., simultaneously) couple to the BCH, for example, with a SNR/RSSI above a minimum threshold. The CLH (e.g., WTRU **501**) may generate a schedule with a time slot assignment for any (e.g., each) group, during which devices (e.g., WTRUs **102**) of a group may couple and/or load the BCH to receive broadcast

transmissions from the CLH (e.g., WTRU 501) or other devices (e.g., WTRUs 102) in the group. To reach any of (e.g., all) cluster devices (e.g., WTRUs 102), the CLH (e.g., WTRU 501) may re-broadcast its control information and/or instructions in any (e.g., each) time slot, for example, in accordance with the schedule.

(180) In various embodiments, at the cluster creation/formation phase, the CLH (e.g., WTRU 501) may also create sub-groups along with a schedule, and/or assign a table of load termination states versus threshold levels to any (e.g., each) sub-group member device. During normal operation, members of a sub-group may autonomously and/or dynamically select the correct load termination states without direct intervention or instruction from the cluster head (e.g., WTRU 501).

(181) Device Perspective

(182) An exemplary embodiment of a load-based access scheme from the device (e.g., WTRU 102) perspective is shown in FIG. 17. In a step (1701), the device (e.g., WTRU 102) may request network resources to establish a data link. If not already available to the CLH 102a, the device, may send any of: its supported load termination states, QoS requirements, supported data rates, and/or coupling coefficients (1703). The device (e.g., WTRU 102) may receive a grant from CLH (e.g., WTRU 501) comprising any of: time slot assignment, load termination state during transmit cycles and/or load termination state in non-transmitting periods, and/or timing and/or synchronization settings (1705). In a step (1707), the device (e.g., WTRU 102) may transmit in the assigned time slot(s), for example, with load termination states configured according to pre-determined values for any (e.g., each) period. The data buffer may be updated at the end of any (e.g., each) transmission period (1709 and 1711). After (e.g., when) the transmit cycle ends, e.g., the data buffer may be empty (1713), the device (e.g., WTRU 102) may switch to supporting mode using pre-assigned load termination state for non-transmit mode (1715).

2.2. CONCURRENT DELIVERY OF ENEMY AND INFORMATION IN RMC SYSTEMS

(183) The main challenge with RMC networks may be in the simultaneous transfer of power and information. The discussion above considers the communication related transmissions of RMC where information may be sent and received between a plurality of devices (e.g., WTRUs 102) within a cluster without consideration of power transfer. When energy harvesting capabilities are introduced in a cluster; where generally, a strong continuous wave (CW) tone, or other power optimized waveform, may be in the presence of a usually weaker information-carrying signal. The CW tone may behave like a jammer and/or interfere with the reception of the information signal.

(184) 2.2.1. Magnetic Coupling Domain Multiple Access (MC-DMA)

(185) This section describes methods, apparatus, and techniques for taking advantage of a new class of load-states and load management schemes for medium access, and introduces a concept of Magnetic Coupling Domain Multiple Access (MC-DMA) into the afore described resonant magnetic framework to enable this new class of load termination states.

(186) The near ideal orthogonality between real and reactive power is well understood in power transmission and distribution circuit analysis. FIG. 18 depicts the relationship between real, reactive, and apparent power. The ratio of the true (or real) power, dissipated at the load, to the apparent (or total) power, supplied by the source, is defined as the power factor. For sinusoidal waveforms, the power factor is the cosine of the angle ϕ between true power and apparent power. For a purely resistive load, the voltage and current are in phase, and the apparent power and true power are equal. However, a purely reactive load may result in a power factor of zero, since current and voltage will be 90 degrees out-of-phase.

(187) Power may be expressed in complex form as shown in the following equation:

$$S=P+jQ \quad (17)$$

where, P is the true power and Q the reactive power.

2.2.2. Leveraging of Complex Load Termination States

(188) A complex impedance may comprise two parts: the real or resistive part dissipating active power (e.g., heat), and the imaginary part comprising an inductive or capacitive reactance or both,

which is frequency dependent and responsible for the reactive power present in the circuit. The reactive power may be generated by a current charging a capacitor, or creating a magnetic field around a coil. This current may be out of phase with the voltage.

(189) A device (e.g., WTRU **102**) with a complex load impedance termination may simultaneously harvest energy with the real part of its load termination and/or receive information by coupling or tapping into the reactive power available in the magnetic field induced by the WTRU or a cluster head (e.g., WTRU **501**).

(190) Similarly, a number of devices (e.g., WTRUs **102**), based on their respective requirements, may harvest energy by coupling a resistive load to the resonant magnetic field emanating from a WTRU while other devices (e.g., WTRUs **102**), instead, use complex load impedance terminations, mostly reactive with small resistive components, to extract signal energy from the magnetic field.

(191) Although most of the discussion herein is written in terms of an exemplary embodiment in which different devices (e.g., WTRUs **102**) simultaneously transfer data and energy harvest, it should be noted that any single device (e.g., WTRU **102**) also may simultaneously conduct data transfer and energy harvesting in accordance with the principles disclosed herein.

(192) FIG. **19** illustrates the concept of magnetic coupling domain multiple access in accordance with an embodiment. On the primary side of the transformer, voltage source $V_{\text{sub.A}}$ with an internal complex impedance value of $Z_{\text{sub.A}}$, and voltage source $V_{\text{sub.B}}$ with an internal impedance value of $Z_{\text{sub.B}}$, may be linearly combined or added to produce an input signal to the primary side of the resonant magnetic circuit model. The secondary side of the transformer may comprise two windings, $L_{\text{sub.A}}$ terminated with impedance $Z'_{\text{sub.A}}$ and $L_{\text{sub.B}}$ terminated with complex impedance $Z'_{\text{sub.B}}$.

(193) FIG. **20** depicts voltage signals associated with the circuit model of FIG. **19**. Part a of FIG. **20** shows a voltage source $V_{\text{sub.A}}$ running at frequency $f_{\text{sub.A}}$, and source $V_{\text{sub.B}}$ at frequency $f_{\text{sub.B}}$ are shown. Part b of FIG. **20** shows the voltage component associated with any (e.g., each) source measured across the complex load $Z'_{\text{sub.A}}$ of FIG. **19**. When $Z'_{\text{sub.A}}$ is equal to $Z^*_{\text{sub.A}}$ (where $Z^*_{\text{sub.A}}$ is the complex conjugate match of $Z_{\text{sub.A}}$ of the source $V_{\text{sub.A}}$), it obtains an optimal match, and therefore maximum power transfer can take place from source $V_{\text{sub.A}}$ to the load $Z'_{\text{sub.A}}$.

(194) However, the component of source $V_{\text{sub.B}}$ delivered across $Z'_{\text{sub.A}}$ may be very small since its source impedance $Z_{\text{sub.B}}$ is not a conjugate match to the load $Z'_{\text{sub.A}}$. As a result, we may observe a tiny fraction of the source voltage $V_{\text{sub.B}}$ delivered to the load $Z'_{\text{sub.A}}$.

(195) Similarly for $Z'_{\text{sub.B}}$, as shown in part c of FIG. **20**, the impedance $Z_{\text{sub.B}}$ of the voltage source $V_{\text{sub.B}}$ is a complex conjugate and results in maximum power transfer. However, $Z_{\text{sub.A}}$ from the source $V_{\text{sub.A}}$ is not a perfect match and potentially may result in a severe attenuation of that voltage across $Z'_{\text{sub.B}}$.

(196) Therefore, careful selection of source and load complex impedances may help enable this magnetic coupling domain multiple access (or MC-DMA) scheme, by selectively presenting an optimal load termination for a desired signal and presenting, practically, and open circuit to unwanted signals. A complex load impedance termination may be represented by an equivalent series or parallel R, L, C passive network, where the passive components may comprise, e.g., a combination of electronically selectable or tunable components connected to arrive at, or approximate, the desired impedance value.

(197) FIG. **21** is a flowchart describing the procedure for selecting a complex impedance for energy harvesting or communication. At **2101**, a device (e.g., WTRU **102**) may request network resources for establishing a data link with the network. At **2103**, the device (e.g., WTRU **102**) may receive a configuration from the CLH **102a**, which may include any of: a time slot assignment, timing/frame synchronization data, and/or information about the load state in other time slots. The information about the load state in other time slots may be useful to the device (e.g., WTRU **102**) in determining what its load state should be in timeslots in which it is not transmitting insofar as the

cluster head (e.g., WTRU 501) may want this device (e.g., WTRU 102) to unload the resonant magnetic medium (or couple sub-optimally) to free-up energy/power of other devices (e.g., WTRUs 102).

(198) At 2105, the device (e.g., WTRU 102) may determine whether or not it will harvest power from the CLH 102a. If it will harvest power, flow may proceed to 2107, where the device (e.g., WTRU 102) may inform the CLH (e.g., WTRU 501) that it wishes to harvest energy (effectively a request for the CLH (e.g., WTRU 501) to transmit to the device (e.g., WTRU 102) a complex load setting optimized for energy harvesting). At 2109, the device (e.g., WTRU 102) may receive and set itself to the load setting received from the CLH (e.g., WTRU 501) (e.g., a complex impedance state optimized for power harvesting without interfering with other information signals being transmitted/received by the CLH 102a). This load impedance preferably may be selected such that it presents an ideal conjugate match to the energy source (e.g., the CW signal), but a near-open circuit to the information source. Next, the device (e.g., WTRU 102) may start harvesting energy from the CW signal.

(199) An energy harvesting scheme may be implemented in any number of ways. In one embodiment illustrated in the flowchart, the device (e.g., WTRU 102) harvests energy for a predetermined period of time, e.g., Td seconds (step 2111). At the end of that period, the device (e.g., WTRU 102) may determine if the charging cycle is to be ended (step 2113). This may occur when the device (e.g., WTRU 102) has harvested what it deems to be an adequate amount of power. In various embodiments, step 2113 may include the device (e.g., WTRU 102) listening to the Broadcast Channel (BCH) every Td seconds for potential control messages coming from the CLH (e.g., WTRU 501) (e.g., there may be a request to temporarily halt energy harvesting or modify settings). If, in step 2113, there is no relevant instruction on the BCH to halt charging and/or the desired level of charging has not yet been reached, charging may continue for another Td period. The process may repeat until completion of the charging cycle.

(200) After (e.g., when) the energy harvesting cycle is finished, then flow may proceed from step 2113 to step 2115, in which the device (e.g., WTRU 102) may configure itself with the complex load settings optimized for information transfer and may commence information transmission/reception in the assigned time slots (2117). The impedance for this scenario may present a conjugate load match to the information source, but a near-open circuit to the energy harvesting voltage source.

(201) The optimal complex load impedance determined by the CLH (e.g., WTRU 501) (and transmitted to the device) may have different values for transmitting and for receiving. In particular, it may depend on signal quality factors, such as SNR, RSSI. Also, the CLH (e.g., WTRU 501) may determine a power budget that may support the various energy transfer and/or information transfer requests that it has received from the various devices (e.g., WTRUs 102), and this also potentially may have bearing on the CLH's determination of load impedance states for the various devices (e.g., WTRUs 102).

(202) In an embodiment, the device (e.g., WTRU 102) may receive from the CLH (e.g., WTRU 501) the load settings for transmission and reception of data at the same time that it may receive the load setting for power harvesting. In an embodiment, it may send another load setting request to the CLH (e.g., WTRU 501) (and receive the load settings for transmission and reception of data) in conjunction with step 2115 so that the load settings may be based on the most recent SNR and/or RSSI.

(203) Returning to step 2105, if the device (e.g., WTRU 102) does not intend to harvest energy from the CLH 102a, then flow may proceed from step 2105 (e.g., directly) to steps 2115 and 2117 to configure itself with the complex load settings optimized for information transfer and/or commence information transmission/reception in the assigned time slots.

(204) 2.2.3. Selection and Allocation of EH Channel for CW Tone

(205) A CLH (e.g., WTRU 501) may designate a dedicated frequency or range of frequencies for a

CW tone used for energy harvesting. Broadcast and all unicast data links may operate outside of that range. When the devices (e.g., WTRUs **102**) wish to harvest energy rather than transfer data, they may adjust their coupling and load termination to maximize harvested energy from the CW tone. In the presence of relatively strong CW levels as compared to the data signal strengths, devices (e.g., WTRUs **102**) in unicast links may weakly couple or load the CW, while still harvesting at an adequate regime. This is illustrated in part a of FIG. **22**.

(206) In various embodiments, a CLH (e.g., WTRU **501**) may dynamically select and/or allocate a channel for an energy CW tone while accounting for and minimizing effect on adjacent links signal quality. Alternately or additionally, the CLH (e.g., WTRU **501**) may request devices (e.g., WTRUs **102**) to move to a new center frequency to establish better communication links with minimalized interference from the CW power tone, as shown in part b of FIG. **22**. The CLH (e.g., WTRU **501**) may move the CW tone to a new frequency in the band, as the cluster topology changes over time.

(207) In various embodiments depicted in part c of FIG. **22**, the CLH (e.g., WTRU **501**) may transmit modulated tones on the BCH for both energy harvesting and communication on the BCH. As needed, cluster devices (e.g., WTRUs **102**) harvest energy and/or decode broadcast information from the CLH (e.g., WTRU **501**) by adjusting their load terminations. Devices may transmit on the BCH by load modulating the CW energy tone.

(208) In an embodiment, devices (e.g., WTRUs **102**) may transmit on the BCH by load modulating the CW energy tone and, therefore, introduce a changing current that can be decoded by the CLH **102a**. This concept is depicted in FIG. **23**, which shows the baseband data signal at (a) and the CW energy transfer tone at (b). By load modulating the data signal (a) onto the CW tone (b), using, e.g., amplitude shift keying (ASK), the combined signal, as shown at (c) in FIG. **23** may be used both for energy harvesting and data transfer.

(209) Using a low modulation depth, the resulting modulated signal may maintain most of the original CW tone amplitude, while the information or modulation depth may be sufficient for detection by a receiver within RMC range.

(210) In various embodiments, a modulated tone may be placed in a unicast link where both energy and information may be exchanged.

(211) In various embodiments, a modulated tone may be used in a unicast link where both energy and information may be exchanged similar to the above description.

(212) Time Division Multiplexing

(213) When or if the above options are not feasible or practical, a time-multiplexed (TDM) based approach may be used where the EH signal and data may be assigned to specific timeslots, for example, according to a predetermined schedule. For example, in a time-based approach, in a first timeslot, the CLH (e.g., WTRU **501**) may transmit its modulated power waveform and, in a second timeslot, turn off its transmitter and/or switch to receive mode. Then, devices (e.g., WTRUs **102**) may take turns transmitting on the BCH according to a predetermined schedule.

(214) FIG. **27** illustrate this embodiment by showing the time slot configurations for the CLH (e.g., WTRU **501**) and two devices (e.g., WTRUs **102**) (device A and device B) that are in communication with the CLH **102a**. As shown, during a first time slot, the CLH (e.g., WTRU **501**) may be configured to transmit data (e.g., on the BCH), while the devices (e.g., WTRUs **102**) may be configured to receive those transmissions. During this time slot, the CLH (e.g., WTRU **501**) may transmit the energy harvesting signal (and any of the devices (e.g., WTRUs **102**) may use it to harvest energy as needed. In the second time slot, (1) the CLH (e.g., WTRU **501**) may turn off the energy harvesting beacon and/or may be configured to receive on the BCH, (2) device A may be configured to transmit during this time slot, and (3) device B may be floating. In the third time slot, (1) the CLH (e.g., WTRU **501**) may keep the energy harvesting beacon off and/or may remain configured to receive on the BCH, (2) device B may be configured to transmit during this time slot, and (3) device A may be floating. This cycle may continue to repeat for as long needed (e.g., until another device joins the CLH (e.g., WTRU **501**) and/or the schedule may need to be modified to

accommodate the third device).

(215) In yet another exemplary embodiment, the CLH (e.g., WTRU **501**) may assign time-slots for data transmission for any (e.g., each) device along with associated load-states.

(216) In an even further exemplary embodiment, the CLH (e.g., WTRU **501**) may assign time-slots for energy transfer for any (e.g., each) device (e.g., WTRU **102**) along with associated load-states.

2.3. CLUSTER MEMBERSHIP AND POWER SAVING STRATEGIES

(217) 2.3.1. New Device Coining or Leaving a Cluster

(218) A new device (e.g., WTRU **102**) detected and authenticated by the CLH (e.g., WTRU **501**) after a discovery procedure may request to join the cluster and establish a unicast data link with a current cluster member device (e.g., WTRU **102**) for the purpose of exchanging information and/or other resources. Since the CLH (e.g., WTRU **501**) has a table/list of supported features and current configuration for any (e.g., each) device (e.g., WTRU **102**) in the cluster, it may assist in the selection of a candidate device, with the relevant features or settings to support the unicast link requested by the joining device. The CLH (e.g., WTRU **501**) may then assess the loading effect of the potential new link on the existing link's QoS. If the RSSI or CQI reduction impact is below a first threshold, the CLH (e.g., WTRU **501**) may grant permission for the new link. If RSSI reduction is above that first threshold, the CLH (e.g., WTRU **501**) may grant permission for Load-based Access, if there is a load termination setting supported on the device (e.g., WTRU **102**) side that is capable of reducing the performance impact below that first threshold.

(219) If the performance impact remains above the first threshold but below a second threshold, the CLH (e.g., WTRU **501**) may instead grant permission for time slot-based load access on the medium. If loading impact is above the second threshold, the CLH (e.g., WTRU **501**) may reject the device's request for a new unicast link formation.

(220) From the device (e.g., WTRU **102**) perspective, the new device (e.g., WTRU **102**) may receive authentication information request from CLH **102a**. Then, the device (e.g., WTRU **102**) may report (e.g., transmit information indicating) any of: its ID, SNR table, priority level, supported features, etc. to the CLH **102a**. The device (e.g., WTRU **102**) may move to designated center frequency based on the CLH (e.g., WTRU **501**) request and may adjust its coupling coefficient and load termination state based on CLH (e.g., WTRU **501**) request. If a time slot-based access is selected by the CLH **102a**, the device (e.g., WTRU **102**) may switch between load and float-states, for example, according to the assigned time slot schedule from CLH **102a**.

(221) For a device (e.g., WTRU **102**) wanting to exit its current cluster, the CLH **102a**, after (e.g., upon) receiving exit notice from the departing cluster device, may send an ACK and a request for link quality measurements from the remaining device (e.g., WTRU **102**) members to assess overall cluster performance. If link quality falls below a pre-determined threshold, the CLH (e.g., WTRU **501**) may issuing any number of the following to any number of the remaining devices (e.g., WTRUs **102**) in the cluster: Load termination state changes, schedule and time slot updates, and/or frequency adjustments.

(222) 2.3.2. Inter-Cluster Operation

(223) In a scenario where two adjacent clusters exist with their respective cluster heads operating on their respective BCHs, the cluster heads (e.g., WTRUs **501**) may be aware of the neighboring cluster(s) as a result of a discovery procedure and/or a device (e.g., WTRU **102**) reporting (e.g., transmitting information indicating) the presence of an adjacent device (e.g., WTRU **102**) belonging to a different cluster.

(224) If the overall cluster performance measured on the BCH falls below a predetermined threshold, the CLH (e.g., WTRU **501**) of that cluster may negotiate with an adjacent/offending CLH (e.g., WTRU **501**) to adjust to the BCH settings of the CLH (e.g., WTRU **501**) of the adjacent/offending cluster. The adjustment may include, for example, a change in the BCH center frequency and/or a change in the load termination state of devices (e.g., WTRUs **102**) listening to their own BCH such that the loading on the adjacent BCH is reduced. The adjustment also may

comprise one or both of the adjacent/offending CLHs scheduling access to their BCHs during a designated time slot for any (e.g., each) cluster. In an embodiment, a type of DRX may be implemented on the BCH, in which the cluster not currently listening to its BCH may enter a float-state, thus unloading the medium shared with the adjacent cluster.

(225) 2.3.3. Discontinuous Reception (DRX) Strategies

(226) Discontinuous reception may be used not (e.g., only) to extend the battery life of the mobile device, but also to periodically decouple the device (e.g., WTRU **102**) from the RMC cluster and free-up network resources.

(227) DRX implementations may include any of the following: The device (e.g., WTRU **102**) and the CLH (e.g., WTRU **501**) may negotiate (or the cluster head (e.g., WTRU **501**) may simply assign) the periods during which data transfer may occur and/or the DRX periods. The device (e.g., WTRU **102**) receiver is active (e.g., only) at the beginning of any (e.g., each) relevant time slot in order to determine if data is being transmitted in that time slot intended for that device. If it determines that there is no data in this time slot intended for it, the device (e.g., WTRU **102**) may turn its receiver off and/or may enter a low power state. A polling technique, where the device (e.g., WTRU **102**) is placed in standby for a given duration. A beacon may be periodically sent by the CLH (e.g., WTRU **501**) to indicate (e.g., transmit information indicating) when there is data waiting for any of the devices (e.g., WTRUs **102**) within a configured DRX period, as well as CLH intention to schedule those devices (e.g., WTRUs **102**) for data reception. A hybrid method comprising a combination of the above techniques.

(228) In one example, a device (e.g., WTRU **102**) may receive any of: a scheduling table, time slot assignment, and/or load termination state setting for any (e.g., each) time slot from the cluster head (e.g., WTRU **501**). The device (e.g., WTRU **102**) may then transmit according to its assigned transmission time slots. The device (e.g., WTRU **102**) may periodically switch from power saving mode or float-state to load termination state according to a CLH (e.g., WTRU **501**) assigned receive time slot or schedule.

(229) In an embodiment, devices (e.g., WTRUs **102**) belonging to a cluster but not actively part of a data communication link, still may be used by the cluster head (e.g., WTRU **501**) to help improve RMC link quality for currently connected device-pairs.

(230) In an embodiment, the CLH (e.g., WTRU **501**) may determine that its cluster performance is sub-optimal or recognize a need to improve existing link performance. Knowing the device (e.g., WTRU **102**) capabilities and/or SNR tables of all cluster members, in such a case, the CLH (e.g., WTRU **501**) may instruct those cluster members that are not currently in a unicast or multicast link (e.g., devices (e.g., WTRUs **102**) that have relinquished the resonance magnetic medium, but periodically access it to receive control information on the broadcast channel). CLH **102a**, requesting a change in the device (e.g., WTRU **102**) load termination state to modify channel and/or link characteristics such as any of: Common channel center frequency to optimize the BCH; Location of resonant peaks to optimize current device-pairs links qualities; and/or Coupling efficiency between existing links.

Device Mobility

(231) The non-transmitting device (e.g., WTRU **102**) also may be subject to mobility within the cluster, which may affect other device-pair links. The cluster head (e.g., WTRU **501**) may implement periodic control procedures to assess the continued usefulness of the device (e.g., WTRU **102**) in helping with overall cluster performance and/or mitigate potential negative impact introduced by the change in the device (e.g., WTRU **102**) location.

(232) For example, devices (e.g., WTRUs **102**) may continuously report (e.g., transmit information indicating) changes in link quality to the CLH (e.g., WTRU **501**) on the BCH and receive re-balancing instructions from the CLH **102a**. The CLH (e.g., WTRU **501**) may request non-transmitting devices (e.g., WTRUs **102**) to move to float-state so that the CLH (e.g., WTRU **501**) can measure that device's impact on cluster performance. If the device (e.g., WTRU **102**) is having

a sufficiently detrimental effect on cluster performance, the CLH (e.g., WTRU 501) may request that non-transmitting device (e.g., WTRU 102) to switch to a new load termination state for designated time slots.

2.4. EXEMPLARY EMBODIMENTS

2.4.1. Exemplary Embodiment 1

(233) FIG. 24 is a signal flow diagram illustrating an exemplary method performed by a CLH (e.g., WTRU 501) to maximize the number of devices (e.g., WTRUs 102) able to communicate on the BCH and/or allocate resources based on need by leveraging the load termination state of devices (e.g., WTRUs 102) within its range. The method may comprise a CLH (e.g., WTRU 501) receiving measurement reports (e.g. channel quality/SNR tables), device (e.g., WTRU 102) capabilities (e.g. supported load termination states) from all devices (e.g., WTRUs 102) in range (within the served cluster), with all devices (e.g., WTRUs 102) configured with their default load termination state value (2401). Using the received measurement reports and/or device (e.g., WTRU 102) capabilities, the CLH (e.g., WTRU 501) may assign any (e.g., each) device (e.g., WTRU 102) to one of N sub-groups (2403). The CLH (e.g., WTRU 501) also may assign load termination states for any (e.g., each) device (e.g., WTRU 102) based on their respective group assignment to use in receive mode (or listening on BCH) (2405).

(234) For example, the CLH (e.g., WTRU 501) may assign load termination states for any (e.g., each) device (e.g., WTRU 102) based on its respective group assignment to use during transmit cycle on BCH, where device (e.g., WTRU 102) TX load termination state may provide better match or termination to the RMC channel resulting in stronger RSSI at the CLH (e.g., WTRU 501) receiver. Assigned RX load termination state settings may be different from assigned TX load termination state, e.g., RX load termination may be set to a sub-optimal value of 75 or 100 Ohms in order to receive a signal slightly above a minimum SNR, whereas TX load may be set to 50 Ohms (in a 50 Ohm system) to provide an optimal match and/or better efficiency during the device (e.g., WTRU 102) transmit cycle on the RMC channel. Other TX/RX load termination pairs may include, for example, the following (Tx, Rx) couples: (75,50), (100, 100), (50,50), (75, 100), etc. For a device (e.g., WTRU 102) listening for broadcast information from the CLH 102a, its receiver load termination state may be set to a pre-assigned RX termination value. When transmitting on BCH, for example, during a random access cycle (RACH), or a form of carrier-sense multiple access with collision avoidance (CSMA/CA) scheme, the device (e.g., WTRU 102) load termination state may be changed to a pre-assigned TX load termination (e.g., Z.sub.1=25, Z.sub.2=50, Z.sub.3=75 or Z.sub.i=100 Ohms).

(235) In addition, the CLH (e.g., WTRU 501) may utilize measurement reports to determine a set of edge devices (e.g., WTRUs 102) and/or assign them to a single group. The CLH (e.g., WTRU 501) also may schedule measurement occasions for combinations of device (e.g., WTRU 102) sub-groups (transmitting versus receiving) within the identified group of edge users over combinations of time, frequency, and/or load termination states. The CLH (e.g., WTRU 501) also may determine any (e.g., each) device's SNR curves versus frequency per load termination state and device (e.g., WTRU 102) sub-group configuration. The CLH (e.g., WTRU 501) also may determine/calculate load termination state for any (e.g., each) device (e.g., WTRU 102) based on measured/determined SNR/RSSI curves and expected/planned BCH scheduling configuration.

(236) Next, the CLH (e.g., WTRU 501) may assign time slots for transmission for any (e.g., each) device (e.g., WTRU 102) with associated load termination states and broadcast a schedule to all cluster devices (e.g., WTRUs 102) with designated time slot and/or transmission periods (2407). Time slot usage may be proportionately divided amongst users based on priority and/or data rate requirements.

(237) Additionally, the CLH (e.g., WTRU 501) may create subgroups of devices (e.g., WTRUs 102) within its cluster, where devices (e.g., WTRUs 102) may be assigned to a subgroup based on either SNR/RSSI, priority level, supported features, etc. (2409).

(238) Furthermore, the CLH (e.g., WTRU **501**) may assign DRX periods to any (e.g., each) subgroup, where any (e.g., each) subgroup will take turn listening to the BCH according to its assigned DRX period (**2411**).

(239) Yet further, the CLH (e.g., WTRU **501**) may request devices (e.g., WTRUs **102**) currently not communicating on the BCH and/or devices (e.g., WTRUs **102**) that have relinquished the medium to change load termination state to help shape the channel response, e.g., channel quality factor (Q), in order to optimize/maximize the channel usage and/or bandwidth (**2413**). After (e.g., when) cluster conditions have changed, the CLH (e.g., WTRU **501**) may request a device (e.g., WTRU **102**) to exit this facilitator-mode by relinquishing the medium and, for example, reverting to a power saving mode or a sleep-mode, etc.

(240) In an embodiment, no sub-groups are created by the CLH **102a**. Rather, (e.g., only) the leveraging of individual device (e.g., WTRU **102**) load termination states may be used. A CLH (e.g., WTRU **501**) may receive frequency versus SNR curves and supported load termination states from all devices (e.g., WTRUs **102**) in range, with all devices (e.g., WTRUs **102**) configured with their default load termination state value. The CLH (e.g., WTRU **501**) may determine/calculate load termination state for any (e.g., each) device (e.g., WTRU **102**) based on reported SNR/RSSI. The CLH (e.g., WTRU **501**) may assign load termination states for any (e.g., each) device (e.g., WTRU **102**) to use in receive mode (or listening on BCH). The CLH (e.g., WTRU **501**) may assign load termination states for any (e.g., each) device (e.g., WTRU **102**) to use during transmit cycle on BCH, where device (e.g., WTRU **102**) TX load termination state may provide better match or termination to the RMC channel resulting in stronger RSSI at the CLH (e.g., WTRU **501**) receiver. Assigned RX load termination state settings may be different from assigned TX load termination state, e.g., RX load termination may be set to a sub-optimal value of 75 or 100 Ohms, in order to receive a signal slightly above a minimum SNR, whereas TX load maybe set to 50 Ohms (in a 50 Ohm system) to provide an optimal match and/or better efficiency during the device (e.g., WTRU **102**) transmit cycle on the RMC channel. Other TX/RX load termination pairs may include, for example, the following (Tx, Rx) couples: (75,50), (100, 100), (50,50), (75, 100), etc.

(241) For a device (e.g., WTRU **102**) listening for broadcast information from the CLH **102a**, its receiver load termination state may be set to a pre-assigned RX termination value. When transmitting on BCH, for example, during a random access cycle (RACH), or a form of carrier-sense multiple access with collision avoidance (CSMA/CA) scheme, the device (e.g., WTRU **102**) load termination state may be changed to a pre-assigned TX load termination (e.g., $Z_1=25$, $Z_2=50$, $Z_3=75$ or $Z_i=100$ Ohms).

(242) In an embodiment, a sub-group comprising (e.g., consisting of) cell edge devices (e.g., WTRUs **102**) with SNR reported (marginally) above a first threshold but below a second threshold, may be created by the CLH (e.g., WTRU **501**) to leverage the sub-group device (e.g., WTRU **102**) load termination state, while keeping overall cluster management overhead to a reasonable or acceptable level. In an embodiment, the cluster head (e.g., WTRU **501**) may receive any of: measurement reports (e.g. channel quality/SNR tables), device (e.g., WTRU **102**) capabilities (e.g. supported load termination states) from all devices (e.g., WTRUs **102**) in range (within the served cluster), with all devices (e.g., WTRUs **102**) configured with their default load termination state value.

(243) Using the received measurement reports and/or device (e.g., WTRU **102**) capabilities, the CLH (e.g., WTRU **501**) may assign any (e.g., each) device (e.g., WTRU **102**) to one of 2 groups, namely, a group for devices (e.g., WTRUs **102**) reporting (e.g., transmitting information indicating) a SNR level below a pre-determined threshold and/or a general group for all other devices (e.g., WTRUs **102**).

(244) The CLH (e.g., WTRU **501**) also may assign load termination states for any (e.g., each) device (e.g., WTRU **102**) based on their respective group assignment to use in receive mode (or listening on BCH). General group load termination states may be assigned for relatively long

durations, e.g., $n \gg m \cdot \text{sub.slots}$, with $m \cdot \text{sub.slots} = \text{number of time slots}$. Edge device (e.g., WTRU **102**) group load termination states may be assigned periodically with high frequency, e.g., device (e.g., WTRU **102**) load termination states are updated at a much higher rate than the general group device (e.g., WTRU **102**) load termination states.

(245) The CLH (e.g., WTRU **501**) may assign load termination states for any (e.g., each) device (e.g., WTRU **102**) to use during transmit cycle on BCH, where device (e.g., WTRU **102**) TX load termination state may provide better match or termination to the RMC channel resulting in stronger RSSI at the CLH (e.g., WTRU **501**) receiver. Assigned RX load termination state settings may be different from assigned TX load termination state, e.g., RX load termination may be set to a sub-optimal value of 75 or 100 Ohms, in order to receive a signal slightly above a minimum SNR, whereas TX load may be set to 50 Ohms (in a 50 Ohms system) to provide an optimal match and/or better efficiency during the device (e.g., WTRU **102**) transmit cycle on the RMC channel. Other TX/RX load termination pairs may include, for example, the following (Tx, Rx) couples: (75,50), (100, 100), (50,50), (75, 100), etc.

(246) For a device (e.g., WTRU **102**) listening for broadcast information from the CLH **102a**, its receiver load termination state may be set to a pre-assigned RX termination value. When transmitting on BCH, for example, during a random access cycle (RACH), or a form of carrier-sense multiple access with collision avoidance (CSMA/CA) scheme, the device (e.g., WTRU **102**) load termination state may be changed to a pre-assigned TX load termination (e.g., $Z1=25$, $Z2=50$, $Z3=75$ or $Zi=100$ Ohms).

2.4.2. Exemplary Embodiment 2

(247) FIG. **25** is a signal flow diagram illustrating an exemplary method performed by a cluster head (e.g., WTRU **501**) managing device-pairs connected via unicast links and/or allocating medium resources (bandwidth, time slots) and/or minimizing interference between adjacent links by using the load termination state of devices (e.g., WTRUs **102**) during transmission and/or reception cycles. The method may comprise a CLH (e.g., WTRU **501**) receiving supported load termination states, e.g. capabilities, from all devices (e.g., WTRUs **102**) in range (within the served cluster), with all devices (e.g., WTRUs **102**) configured with their default load termination state value.

(248) The CLH (e.g., WTRU **501**) may receive any of link establishment requests, scheduling control information (e.g. quality of service, buffer status, . . . etc.), and/or capabilities (e.g., **2501**, **2503**) in a control period preceding the data scheduling period from the devices (e.g., WTRUs **102**) wishing to establish a RMC link with each other (e.g., devices (e.g., WTRUs **102**) A and B and devices (e.g., WTRUs **102**) C and D).

(249) The CLH (e.g., WTRU **501**) may determine scheduling measurement occasions for devices (e.g., WTRUs **102**) that are part of the link establishment requests over a combination of time, frequency, and/or load termination states and/or transmits the measurement occasions schedule to all such devices (e.g., WTRUs **102**) (**2507**). At **2509**, the CLH (e.g., WTRU **501**) may receive the requested measurements, such as SNR as a function of frequency, load termination state, etc. Based on those measurements and/or any other relevant factors (e.g., QoS requirements, buffer statuses, etc.), the CLH (e.g., WTRU **501**) may determine any (e.g., each) device's SNR curve and/or a best load termination state for any (e.g., each) of transmitting and/or receiving for any (e.g., each) such device (e.g., WTRU **102**) (**2511**). The CLH (e.g., WTRU **501**) may transmit the assigned load termination states and/or channel assignments for any (e.g., each) link to the individual devices (e.g., WTRUs **102**) (e.g., **2513**, **2517**). It may assign and/or transmit a time slot schedule for any (e.g., each) link (e.g., **2515**, **2519**). Thereafter the devices (e.g., WTRUs **102**) may begin communicating over the RMC links (e.g., **2521**, **2523**).

(250) In an embodiment, the measurement occasions may be scheduled every control/data scheduling period, preceding the data transfer period, but following the control period.

(251) In an embodiment, the measurement occasions may be periodic with a period that may span a

plurality of (e.g., multiple) control/data scheduling periods and/or may further comprise the CLH **102a**: scheduling measurement occasions at the beginning of the measurement period for combinations of device (e.g., WTRU **102**) groups, time, frequency, and/or load termination states; determining any (e.g., each) device's SNR curves vs frequency per load termination state and/or device (e.g., WTRU **102**) group configuration; receiving link establishment requests, scheduling control information, and/or capabilities in a control period preceding every data transfer period within the measurement period; and/or determining/calculating load termination state for any (e.g., each) device (e.g., WTRU **102**) based on measured/determined SNR/RSSI curves, link establishment requests in a current control/data transfer period, QoS requirements, and/or buffer status.

(252) The CLH (e.g., WTRU **501**) may assign time periods for TX/RX cycles for any (e.g., each) device-pair, where both devices (e.g., WTRUs **102**) forming a unicast link can complete a transmit-receive cycle before entering a DTX/DRX load termination state, e.g., a Float-State, while other device-pairs may enter their respective transmit cycles.

(253) The unicast link Tx/Rx period may be proportionately allocated amongst users based on priority and/or data rate requirements.

(254) From the device (e.g., WTRU **102**) perspective, the method may comprise a device (e.g., WTRU **102**) performing any number of the following actions: The device (e.g., WTRU **102**) requesting access to, or formation of a unicast link for the purpose of exchanging information; The device (e.g., WTRU **102**) sending a candidate device (e.g., WTRU **102**) ID for the unicast link formation or may be assigned a device (e.g., WTRU **102**) by the CLH **102a**; The device (e.g., WTRU **102**) receiving load termination values for transmit and/or receive cycles from CLH **102a** The assigned transmit load termination state may be different from the receive load termination state; and/or The device (e.g., WTRU **102**) communicating with the assigned device (e.g., WTRU **102**) on assigned unicast link using assigned TX load termination state during transmit cycles and switching to assigned receive load termination state during RX cycles.

(255) In addition, the device (e.g., WTRU **102**) may receive time period assignments for TX/RX cycles, where both devices (e.g., WTRUs **102**) forming a unicast link can complete a transmit-receive cycle before entering a DTX/DRX load termination state, e.g., a Float-State, while other device-pairs may start their respective transmit cycles

(256) A unicast link TX/RX period may be proportionately allocated amongst users based on priority and/or data rate requirements.

(257) A device (e.g., WTRU **102**) may enter an assigned DTX/DRX load termination state after completing TX/RX cycles.

(258) A device (e.g., WTRU **102**) may exit DRX/DTX float-state after a pre-allocated time period and/or resume normal TX/RX cycles on the unicast link.

2.4.3. Exemplary Embodiment 3

(259) FIG. **26** is a flowchart illustrating an exemplary method performed by a CLH (e.g., WTRU **501**) to manage a new device (e.g., WTRU **102**) joining the cluster.

(260) After (e.g., when) a new device (e.g., WTRU **102**) joins a cluster, after a discovery procedure in which the cluster head (e.g., WTRU **501**) establishes a communication link with the new device (e.g., WTRU **102**) (not shown), the cluster head (e.g., WTRU **501**) may authenticate the new device (e.g., WTRU **102**) configured with its default load termination state value and/or may receive a request from new device (e.g., WTRU **102**) to join the BCH (**2601**). In response, the CLH (e.g., WTRU **501**) may assess loading effect of potential new link on existing BCH links QoS (**2603**). At **2605**, the CLH (e.g., WTRU **501**) may determine if RSSI reduction (Δ RSSI) is below a first threshold. If so, the CLH (e.g., WTRU **501**) may grant permission for new link (**2613**). If not, flow may proceed to step **2607** where the CLH (e.g., WTRU **501**) may determine if RSSI reduction is between a first and a second threshold. If, loading impact is above the second threshold, the CLH (e.g., WTRU **501**) may reject new link request and/or the device (e.g., WTRU **102**) may be

requested to switch to FLOAT state (2615).

(261) If, on the other hand, the load impact is determined in step 2607 to be between the first and second thresholds, the CLH (e.g., WTRU 501) may request the new device (e.g., WTRU 102) to change its load termination state as deemed desirable (2609) and/or may check if the new load setting causes the load impact to drop below the first threshold (2611). If so, the CLH (e.g., WTRU 501) may grant permission for load-based access (2613). If, on the other hand, the new load setting does not reduce the load impact below the first threshold, the CLH (e.g., WTRU 501) may grant permission for time slot-based load access (2617).

(262) Newly admitted devices (e.g., WTRUs 102) in the cluster, that are not currently communicating on BCH or a unicast link, may be configured as a facilitator and/or help shape and/or improve the channel response for other links, for example, by setting its termination load to a pre-assigned value.

(263) From the device (e.g., WTRU 102) perspective, a new device (e.g., WTRU 102) may receive an authentication info request from the CLH (e.g., WTRU 501) and/or may send its settings and supported features (e.g., ID, SNR table, priority level, load termination states) to the CLH 102a. The device (e.g., WTRU 102) may move to the designated center frequency on CLH (e.g., WTRU 501) request, may adjust its coupling coefficient and/or load termination state upon CLH (e.g., WTRU 501) request and/or may switch to float-state according to time slot schedule from CLH (e.g., WTRU 501) (optional).

(264) After (e.g., when) a device (e.g., WTRU 102) exits a cluster, the CLH (e.g., WTRU 501) may receive an exit notice from the cluster device (e.g., WTRU 102) and/or may send an ACK to the device. The CLH (e.g., WTRU 501) may request and/or receive link quality data from the remaining cluster members, for example, in order to assess cluster performance on the BCH. The CLH (e.g., WTRU 501) may issue any number of: load termination state changes; schedule and/or time slot updates; frequency setting adjustments; and/or coupling coefficient modifications.

(265) FIG. 28 is a flowchart illustrating a representative method implemented by a WTRU.

(266) Referring to FIG. 28, the representative method 2800 may include, at block 2810, receiving from a first device (e.g., WTRU 102a), a request to send a transmission to a second device (e.g., WTRU 102b) via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device. At block 2820, the WTRU 501 may send to the first device (e.g., WTRU 102a), measurement configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device (e.g., WTRU 102a); and/or (2) at least one load termination state of the set of load termination states to be used by the first device (e.g., WTRU 102a) when performing measurements. At block 2830, the WTRU 501 may receive from the first device, measurement information resulting from measurements performed by the first device (e.g., WTRU 102a) in accordance with the sent measurement configuration information. At block 2840, the WTRU 501 may determine a load termination state for the first device (e.g., WTRU 102a) based on the measurement information. At block 2850, the WTRU 501 may send to the first device, information indicating the determined load termination state for the first device.

(267) In certain representative embodiments, the load termination state may be determined per time slot and/or frequency assignments for use by the first device (e.g., WTRU 102a).

(268) In certain representative embodiments, the first device (e.g., WTRU 102a), information indicating time slot and/or frequency assignments for use by the first device (e.g., WTRU 102a).

(269) In certain representative embodiments, the WTRU 501 may send to the first device (e.g., WTRU 102a), information indicating an operation mode corresponding to any of a transmit mode, a receive mode, or facilitate mode and/or corresponding load termination state.

(270) In certain representative embodiments, the load termination state may be determined among the set of load termination states indicated by the capability information.

(271) In certain representative embodiments, the measurement information includes information indicating any of: signal to noise ratio (SNR) and/or reported signal strength (RSS).

(272) In certain representative embodiments, the received request includes information indicating any of: a requested Quality of Service (QoS), a priority indicator, an indicator of a required level of reliability of communications, a buffer status indicative of an amount of data to be communicated via the requested transmission, a channel quality metric, and/or capability information indicative of coupling coefficients supported by the first device (e.g., WTRU **102a**); and/or wherein the WTRU may determine a load termination state for the first device (e.g., WTRU **102a**) may be based on at least the information included in the received request.

(273) In certain representative embodiments, the WTRU **501** may be a cluster head (e.g., WTRU **501**) WTRU, and/or the second device (e.g., WTRU **102b**) may be managed by the cluster head WTRU **501**.

(274) In certain representative embodiments, the WTRU **501** may determine a load termination state for the second device (e.g., WTRU **102b**) based on the measurement information; and/or may send to the second device (e.g., WTRU **102b**), information indicating the determined load termination state for the second device (e.g., WTRU **102b**).

(275) In certain representative embodiments, the WTRU **501** may receive from the first device (e.g., WTRU **102a**), a request to send a transmission to a second device (e.g., WTRU **102b**) via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device, and/or the second device. At block **2820**, the WTRU **501** may send to the first device (e.g., WTRU **102a**) and/or the second device (e.g., WTRU **102b**), measurement configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device (e.g., WTRU **102a**) and/or the second device (e.g., WTRU **102b**); and/or (2) at least one load termination state of the set of load termination states to be used by the first device (e.g., WTRU **102a**) and/or the second device (e.g., WTRU **102b**), when performing measurements. At block **2830**, the WTRU **501** may receive from the first device and/or the second device (e.g., WTRU **102b**), measurement information resulting from measurements performed by the first device (e.g., WTRU **102a**) and/or the second device (e.g., WTRU **102b**) in accordance with the sent measurement configuration information. At block **2840**, the WTRU **501** may determine a load termination state for the first device (e.g., WTRU **102a**) and/or the second device (e.g., WTRU **102b**) based on the measurement information. At block **2850**, the WTRU **501** may send to the first device and/or the second device (e.g., WTRU **102b**), information indicating the determined load termination state for the first device.

(276) FIG. **29** is a flowchart illustrating a representative method implemented by a first device (e.g., WTRU **102a**).

(277) Referring to FIG. **29**, the representative method **2900** may include, at block **2910**, sending to a WTRU **501**, a request to send a transmission to a second device (e.g., WTRU **102b**) via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device (e.g., WTRU **102a**). At block **2920**, the device may receive from the WTRU **501**, measurement configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device (e.g., WTRU **102a**); and/or (2) at least one load termination state of the set of load termination states to be used by the first device (e.g., WTRU **102a**) when performing measurements. At block **2930**, the device may send to the WTRU **501**, measurement information resulting from measurements performed by the first device (e.g., WTRU **102a**) in accordance with the received measurement configuration information. At block **2940**, the device may receive from the WTRU **501**, information indicating a determined load termination state for the first device (e.g., WTRU **102a**).

(278) In certain representative embodiments, the load termination state may be determined per time

slot and/or frequency assignments for use by the first device (e.g., WTRU **102a**).

(279) In certain representative embodiments, the device may receive from the WTRU **501**, information indicating time slot and/or frequency assignments for use by the first device (e.g., WTRU **102a**).

(280) In certain representative embodiments, the device may receive from the WTRU **501**, information indicating an operation mode corresponding to any of a transmit mode, a receive mode, or facilitate mode and/or corresponding load termination state.

(281) In certain representative embodiments, the load termination state may be determined among the set of load termination states indicated by the capability information.

(282) In certain representative embodiments, the measurement information includes information indicating any of: signal to noise ratio (SNR) and/or reported signal strength (RSS).

(283) In certain representative embodiments, the receive request includes information indicating any of: a requested Quality of Service (QoS), a priority indicator, an indicator of a required level of reliability of communications, a buffer status indicative of an amount of data to be communicated via the requested transmission, a channel quality metric, and/or capability information indicative of coupling coefficients supported by the first device (e.g., WTRU **102a**).

(284) In certain representative embodiments, the WTRU **501** may be a cluster head WTRU, and the second device (e.g., WTRU **102b**) may be managed by the cluster head WTRU.

(285) FIG. **30** is a flowchart illustrating a representative method implemented by a WTRU **501** in communication on a common channel via resonance magnetic coupling with one or more first devices (e.g., WTRUs **102a**).

(286) Referring to FIG. **30**, the representative method **3000** may include, at block **3010**, establishing a communication link with a second device (e.g., WTRU **102b**), the second device (e.g., WTRU **102b**) being configured with a first load termination state. At block **3020**, the WTRU **501** may receive from the second device (e.g., WTRU **102b**), a request to access the common channel. At block **3030**, the WTRU **501** may request to at least one device of the first devices (e.g., WTRUs **102a**), measurement information, indicative of a signal strength received via the common channel by the at least one device of the first devices (e.g., WTRUs **102a**), considering the access to the common channel by the second device (e.g., WTRU **102b**). At block **3040**, the WTRU **501** may receive, from the at least one device of the first devices (e.g., WTRUs **102a**), measurement information. At block **3050**, the WTRU **501** may authorize the second device (e.g., WTRU **102b**) to access the common channel based on the measurement information.

(287) In certain representative embodiments, the common channel may be a broadcast/unicast channel.

(288) In certain representative embodiments, the measurement information includes any of: signal to noise ratio (SNR) and/or reported signal strength (RSS).

(289) In certain representative embodiments, the measurement information includes a signal quality value indicative of a change in the signal strength received via the common channel by the at least one device of the first devices (e.g., WTRUs **102a**), considering the access to the common channel by the second device (e.g., WTRU **102b**).

(290) In certain representative embodiments, the WTRU **501** may authorize the second device (e.g., WTRU **102b**) to access the common channel, on condition that the signal quality value may be lower than a threshold, the threshold being indicative of a maximum allowable reduction of quality level of the common channel.

(291) In certain representative embodiments, the WTRU **501** may determine a second load termination state for the second device (e.g., WTRU **102b**) based on the measurement information; and/or may send to the second device (e.g., WTRU **102b**), information indicating the determined second load termination state for the second device (e.g., WTRU **102b**), and/or wherein the first load termination state may be determined per time slot assignments of the common channel for use by the second device (e.g., WTRU **102b**), and/or wherein the second load termination state may be

determined per time slot assignments of the common channel for use by at least one device of the first devices (e.g., WTRUs **102a**).

(292) In certain representative embodiments, the WTRU **501** may determine a second load termination state for the at least one device of the first devices (e.g., WTRUs **102a**) based on the measurement information; and/or send to the at least one device of the first devices (e.g., WTRUs **102**), information indicating the determined second load termination state for the at least one device of the first devices (e.g., WTRUs **102a**). In certain representative embodiments, the first load termination state may be determined per time slot assignments of the common channel for use by the second device (e.g., WTRU **102b**), and/or the second load termination state may be determined per time slot assignments of the common channel for use by at least one device of the first devices (e.g., WTRUs **102a**).

(293) In certain representative embodiments, on condition that the signal quality value may be greater than a first threshold and lower than a second threshold, the first threshold being indicative of a first maximum allowable reduction of quality level of the common channel and/or the second threshold being indicative of a second higher reduction of quality level of the common channel, the WTRU **501** may determine a second load termination state for the second device (e.g., WTRU **102b**) based on the measurement information; and/or may send to the second device (e.g., WTRU **102b**), information indicating the determined second load termination state for the second device (e.g., WTRU **102b**).

(294) In certain representative embodiments, the second load termination state may be determined per time slot assignments of the common channel for use by the second device (e.g., WTRU **102b**), and/or wherein the second load termination state may be used as a default load termination for access to the common channel by the second device (e.g., WTRU **102b**).

(295) In certain representative embodiments, the WTRU **501** may determine a third load termination state for the at least one device of the first devices (e.g., WTRUs **102a**) based on the measurement information; and/or may send to the at least one device of the first devices (e.g., WTRUs **102a**), information indicating the determined third load termination state for the at least one device of the first devices (e.g., WTRUs **102a**). In certain representative embodiments, the second load termination state may be determined per time slot assignments of the common channel for use by the second device (e.g., WTRU **102b**), and/or the third load termination state may be determined per time slot assignments of the common channel for use by at least one device of the first devices (e.g., WTRUs **102a**).

(296) FIG. **31** is a flowchart illustrating a representative method implemented by a cluster head (e.g., WTRU **501**) for controlling device access in a resonance magnetic coupled (RMC) network.

(297) Referring to FIG. **31**, the representative method **3100** may include, at block **3110**, receiving from a first device (e.g., WTRU **102a**) a request to establish a RMC connection with a second device (e.g., WTRU **102b**), the request including at least one of; a requested Quality of Service (QoS); a priority indicator; an indicator of a required level of reliability of communications; a buffer status indicative of an amount of data to be communicated over the requested RMC connection; a channel quality metric; capability information indicative of load termination states supported by the first device (e.g., WTRU **102a**); and/or capability information indicative of coupling coefficients supported by the first device (e.g., WTRU **102a**). At block **3120**, the cluster head (e.g., WTRU **501**) may generate a schedule for use of frequency and/or time resources of the network by the first and/or second devices (e.g., WTRUs **102b**) as a function of at least the information contained in the request and/or available network resources.

(298) In certain representative embodiments, the second device (e.g., WTRU **102b**) may be one of another device managed by the cluster head (e.g., WTRU **501**) or the cluster head (e.g., WTRU **501**) itself.

(299) In certain representative embodiments, the schedule may comprise at least time slot assignments for use by the first and/or second devices (e.g., WTRUs **102b**) and/or load termination

states.

(300) In certain representative embodiments, the schedule may be a schedule for use of a broadcast channel (BCH).

(301) In certain representative embodiments, the schedule may comprise a frequency assignment.

(302) In certain representative embodiments, if the first device (e.g., WTRU **102a**) has a receive signal strength greater than a minimum threshold and greater than a second, higher threshold, the cluster head (e.g., WTRU **501**) may assign a load state such that the signal power delivered to the device may be reduced to a level below the second threshold and above the first threshold.

(303) FIG. **32** is a flowchart illustrating a representative method implemented by a WTRU.

(304) Referring to FIG. **32**, the representative method **3200** may include, at block **3210**, receiving a configuration from a wireless network for connecting to an access point of the network via resonance magnetic coupling. At block **3220**, the WTRU **501** may determine whether the connection to the access point will be used for harvesting power from the access point or for data transfer with the access point. At block **3230**, if the connection is determined to be for power harvesting, the WTRU **501** may set a complex load impedance of the WTRU for the connection to a first state optimized for harvesting energy from the access point. At block **3240**, if the connection is determined to be for data transfer, the WTRU **501** may set the complex load impedance of the WTRU for the connection to a second state optimized for data transfer with the access point. At block **3250**, the WTRU **501** may commence energy harvesting if the impedance is set to the first setting or commencing data transfer if the impedance is set to the second setting.

(305) In certain representative embodiments, the WTRU **501** may receive the complex load impedance setting from the network.

(306) In certain representative embodiments, the complex load impedance comprises a real part and/or a reactive part.

(307) In certain representative embodiments, the first load impedance state and/or the second load impedance state are orthogonal to each other.

(308) In certain representative embodiments, for power harvesting, the WTRU **501** may couple to a CW tone at a first frequency; and/or for data transfer, the WTRU **501** may couple to a data channel at a second frequency.

(309) FIG. **33** is a flowchart illustrating a representative method implemented in a cluster head **501** of a resonance magnetic coupling network.

(310) Referring to FIG. **33**, the representative method **3300** may include, at block **3310**, transmitting a CW signal for use for energy harvesting by WTRUs **102** coupling to the cluster head (e.g., WTRU **501**). At block **3320**, the cluster head **501** may receive a request for data transfer with an access point of the network from at least one first WTRU **102a**. At block **3330**, the cluster head **501** may receive a request to harvest power from the access point from at least one second WTRU **102b**. At block **3340**, the cluster head **501** may determine a complex impedance load state for each first WTRU **102a** and each second WTRU **102b**, wherein the complex load state for each first WTRU **102a** may be optimized for data transfer with the cluster head **501** and/or the complex load state for each second WTRU **102b** may be optimized for energy harvesting from the CW signal of the cluster head **501**. At block **3350**, the cluster head **501** may transmit to each of the first at least one WTRU **102a** and/or the second at least one WTRU **102b** the complex load impedance state determined for each such WTRU.

(311) In certain representative embodiments, the cluster head **501** may determine a power budget for supporting data transfer with the first at least one WTRU **102a** and/or energy transfer with the at least one second WTRU **102b**.

(312) In certain representative embodiments, the determination of load impedance states for the WTRUs may be based on at least one of signal to noise ratio (SNR) and/or reported signal strength (RSS) of the first and/or second WTRUs.

(313) In certain representative embodiments, the load impedance states for the first WTRU **102a**

and/or the second WTRU **102b** are orthogonal to each other.

(314) In certain representative embodiments, the CW tone may have a frequency that is different than a frequency of any data transfer channel of the cluster head **501**.

(315) In certain representative embodiments, the CW tone may have a substantially greater amplitude than is used for the data transfer channels.

(316) In certain representative embodiments, the frequency of the CW tone may be dynamically selected as a function of data communications occurring on data transfer channels.

(317) In certain representative embodiments, the cluster head **501** may instruct the first at least one WTRU to use a data transfer channel having a frequency selected in order to minimize interference between the CW and/or the selected data channel.

(318) In certain representative embodiments, the frequency of the CW tone may be located in the frequency range of Broadcast Channel (BCH) of the cluster head **501** and/or the CW may be modulated with a data signal.

CONCLUSION

(319) Although features and elements are described above in particular combinations, one of ordinary skill in the art will appreciate that each feature or element can be used alone or in any combination with the other features and elements. In addition, the methods described herein may be implemented in a computer program, software, or firmware incorporated in a computer readable medium for execution by a computer or processor. Examples of non-transitory computer-readable storage media include, but are not limited to, a read only memory (ROM), random access memory (RAM), a register, cache memory, semiconductor memory devices, magnetic media such as internal hard disks and removable disks, magneto-optical media, and optical media such as CD-ROM disks, and digital versatile disks (DVDs). A processor in association with software may be used to implement a radio frequency transceiver for use in a WTRU **102**, WTRU, terminal, base station, RNC, or any host computer.

(320) Moreover, in the embodiments described above, processing platforms, computing systems, controllers, and other devices containing processors are noted. These devices may contain at least one Central Processing Unit (“CPU”) and memory. In accordance with the practices of persons skilled in the art of computer programming, reference to acts and symbolic representations of operations or instructions may be performed by the various CPUs and memories. Such acts and operations or instructions may be referred to as being “executed,” “computer executed” or “CPU executed.”

(321) One of ordinary skill in the art will appreciate that the acts and symbolically represented operations or instructions include the manipulation of electrical signals by the CPU. An electrical system represents data bits that can cause a resulting transformation or reduction of the electrical signals and the maintenance of data bits at memory locations in a memory system to thereby reconfigure or otherwise alter the CPU's operation, as well as other processing of signals. The memory locations where data bits are maintained are physical locations that have particular electrical, magnetic, optical, or organic properties corresponding to or representative of the data bits. It should be understood that the exemplary embodiments are not limited to the above-mentioned platforms or CPUs and that other platforms and CPUs may support the provided methods.

(322) The data bits may also be maintained on a computer readable medium including magnetic disks, optical disks, and any other volatile (e.g., Random Access Memory (“RAM”)) or non-volatile (e.g., Read-Only Memory (“ROM”)) mass storage system readable by the CPU. The computer readable medium may include cooperating or interconnected computer readable medium, which exist exclusively on the processing system or are distributed among a plurality of (e.g., multiple) interconnected processing systems that may be local or remote to the processing system. It is understood that the representative embodiments are not limited to the above-mentioned memories and that other platforms and memories may support the described methods.

(323) In an illustrative embodiment, any of the operations, processes, etc. described herein may be implemented as computer-readable instructions stored on a computer-readable medium. The computer-readable instructions may be executed by a processor of a mobile unit, a network element, and/or any other computing device.

(324) There is little distinction left between hardware and software implementations of aspects of systems. The use of hardware or software is generally (but not always, in that in certain contexts the choice between hardware and software may become significant) a design choice representing cost vs. efficiency tradeoffs. There may be various vehicles by which processes and/or systems and/or other technologies described herein may be effected (e.g., hardware, software, and/or firmware), and the preferred vehicle may vary with the context in which the processes and/or systems and/or other technologies are deployed. For example, if an implementer determines that speed and accuracy are paramount, the implementer may opt for a mainly hardware and/or firmware vehicle. If flexibility is paramount, the implementer may opt for a mainly software implementation. Alternatively, the implementer may opt for some combination of hardware, software, and/or firmware.

(325) The foregoing detailed description has set forth various embodiments of the devices and/or processes via the use of block diagrams, flowcharts, and/or examples. Insofar as such block diagrams, flowcharts, and/or examples contain one or more functions and/or operations, it will be understood by those within the art that each function and/or operation within such block diagrams, flowcharts, or examples may be implemented, individually and/or collectively, by a wide range of hardware, software, firmware, or virtually any combination thereof. Suitable processors include, by way of example, a general purpose processor, a special purpose processor, a conventional processor, a digital signal processor (DSP), a plurality of microprocessors, one or more microprocessors in association with a DSP core, a controller, a microcontroller, Application Specific Integrated Circuits (ASICs), Application Specific Standard Products (ASSPs); Field Programmable Gate Arrays (FPGAs) circuits, any other type of integrated circuit (IC), and/or a state machine.

(326) Although features and elements are provided above in particular combinations, one of ordinary skill in the art will appreciate that each feature or element can be used alone or in any combination with the other features and elements. The present disclosure is not to be limited in terms of the particular embodiments described in this application, which are intended as illustrations of various aspects. Many modifications and variations may be made without departing from its spirit and scope, as will be apparent to those skilled in the art. No element, act, or instruction used in the description of the present application should be construed as critical or essential to the invention unless explicitly provided as such. Functionally equivalent methods and apparatuses within the scope of the disclosure, in addition to those enumerated herein, will be apparent to those skilled in the art from the foregoing descriptions. Such modifications and variations are intended to fall within the scope of the appended claims. The present disclosure is to be limited only by the terms of the appended claims, along with the full scope of equivalents to which such claims are entitled. It is to be understood that this disclosure is not limited to particular methods or systems.

(327) It is also to be understood that the terminology used herein is for the purpose of describing particular embodiments only, and is not intended to be limiting. As used herein, when referred to herein, the terms “station” and its abbreviation “STA”, “user equipment” and its abbreviation “UE” may mean (i) a wireless transmit and/or receive unit (WTRU), such as described infra; (ii) any of a number of embodiments of a WTRU, such as described infra; (iii) a wireless-capable and/or wired-capable (e.g., tetherable) device configured with, inter alia, some or all structures and functionality of a WTRU, such as described infra; (iii) a wireless-capable and/or wired-capable device configured with less than all structures and functionality of a WTRU, such as described infra; or (iv) the like. Details of an example WTRU, which may be representative of any WTRU recited

herein, are provided below with respect to FIGS. 1A-1D.

(328) In certain representative embodiments, several portions of the subject matter described herein may be implemented via Application Specific Integrated Circuits (ASICs), Field Programmable Gate Arrays (FPGAs), digital signal processors (DSPs), and/or other integrated formats. However, those skilled in the art will recognize that some aspects of the embodiments disclosed herein, in whole or in part, may be equivalently implemented in integrated circuits, as one or more computer programs running on one or more computers (e.g., as one or more programs running on one or more computer systems), as one or more programs running on one or more processors (e.g., as one or more programs running on one or more microprocessors), as firmware, or as virtually any combination thereof, and that designing the circuitry and/or writing the code for the software and/or firmware would be well within the skill of one of skill in the art in light of this disclosure. In addition, those skilled in the art will appreciate that the mechanisms of the subject matter described herein may be distributed as a program product in a variety of forms, and that an illustrative embodiment of the subject matter described herein applies regardless of the particular type of signal bearing medium used to actually carry out the distribution. Examples of a signal bearing medium include, but are not limited to, the following: a recordable type medium such as a floppy disk, a hard disk drive, a CD, a DVD, a digital tape, a computer memory, etc., and a transmission type medium such as a digital and/or an analog communication medium (e.g., a fiber optic cable, a waveguide, a wired communications link, a wireless communication link, etc.).

(329) The herein described subject matter sometimes illustrates different components contained within, or connected with, different other components. It is to be understood that such depicted architectures are merely examples, and that in fact many other architectures may be implemented which achieve the same functionality. In a conceptual sense, any arrangement of components to achieve the same functionality is effectively “associated” such that the desired functionality may be achieved. Hence, any two components herein combined to achieve a particular functionality may be seen as “associated with” each other such that the desired functionality is achieved, irrespective of architectures or intermediate components. Likewise, any two components so associated may also be viewed as being “operably connected”, or “operably coupled”, to each other to achieve the desired functionality, and any two components capable of being so associated may also be viewed as being “operably couplable” to each other to achieve the desired functionality. Specific examples of operably couplable include but are not limited to physically mateable and/or physically interacting components and/or wirelessly interactable and/or wirelessly interacting components and/or logically interacting and/or logically interactable components.

(330) With respect to the use of substantially any plural and/or singular terms herein, those having skill in the art can translate from the plural to the singular and/or from the singular to the plural as is appropriate to the context and/or application. The various singular/plural permutations may be expressly set forth herein for sake of clarity.

(331) It will be understood by those within the art that, in general, terms used herein, and especially in the appended claims (e.g., bodies of the appended claims) are generally intended as “open” terms (e.g., the term “including” should be interpreted as “including but not limited to,” the term “having” should be interpreted as “having at least,” the term “includes” should be interpreted as “includes but is not limited to,” etc.). It will be further understood by those within the art that if a specific number of an introduced claim recitation is intended, such an intent will be explicitly recited in the claim, and in the absence of such recitation no such intent is present. For example, where only one item is intended, the term “single” or similar language may be used. As an aid to understanding, the following appended claims and/or the descriptions herein may contain usage of the introductory phrases “at least one” and “one or more” to introduce claim recitations. However, the use of such phrases should not be construed to imply that the introduction of a claim recitation by the indefinite articles “a” or “an” limits any particular claim containing such introduced claim recitation to embodiments containing only one such recitation, even when the same claim includes

the introductory phrases “one or more” or “at least one” and indefinite articles such as “a” or “an” (e.g., “a” and/or “an” should be interpreted to mean “at least one” or “one or more”). The same holds true for the use of definite articles used to introduce claim recitations. In addition, even if a specific number of an introduced claim recitation is explicitly recited, those skilled in the art will recognize that such recitation should be interpreted to mean at least the recited number (e.g., the bare recitation of “two recitations,” without other modifiers, means at least two recitations, or two or more recitations). Furthermore, in those instances where a convention analogous to “at least one of A, B, and C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, and C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). In those instances where a convention analogous to “at least one of A, B, or C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, or C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). It will be further understood by those within the art that virtually any disjunctive word and/or phrase presenting two or more alternative terms, whether in the description, claims, or drawings, should be understood to contemplate the possibilities of including one of the terms, either of the terms, or both terms. For example, the phrase “A or B” will be understood to include the possibilities of “A” or “B” or “A and B.” Further, the terms “any of” followed by a listing of a plurality of items and/or a plurality of categories of items, as used herein, are intended to include “any of,” “any combination of,” “any multiple of,” and/or “any combination of” multiples of the items and/or the categories of items, individually or in conjunction with other items and/or other categories of items. Moreover, as used herein, the term “set” or “group” is intended to include any number of items, including zero. Additionally, as used herein, the term “number” is intended to include any number, including zero.

(332) In addition, where features or aspects of the disclosure are described in terms of Markush groups, those skilled in the art will recognize that the disclosure is also thereby described in terms of any individual member or subgroup of members of the Markush group.

(333) As will be understood by one skilled in the art, for any and all purposes, such as in terms of providing a written description, all ranges disclosed herein also encompass any and all possible subranges and combinations of subranges thereof. Any listed range can be easily recognized as sufficiently describing and enabling the same range being broken down into at least equal halves, thirds, quarters, fifths, tenths, etc. As a non-limiting example, each range discussed herein may be readily broken down into a lower third, middle third and upper third, etc. As will also be understood by one skilled in the art all language such as “up to,” “at least,” “greater than,” “less than,” and the like includes the number recited and refers to ranges which can be subsequently broken down into subranges as discussed above. Finally, as will be understood by one skilled in the art, a range includes each individual member. Thus, for example, a group having 1-3 cells refers to groups having 1, 2, or 3 cells. Similarly, a group having 1-5 cells refers to groups having 1, 2, 3, 4, or 5 cells, and so forth.

(334) Moreover, the claims should not be read as limited to the provided order or elements unless stated to that effect. In addition, use of the terms “means for” in any claim is intended to invoke 35 U.S.C. § 112, ¶6 or means-plus-function claim format, and any claim without the terms “means for” is not so intended.

(335) Although the invention is illustrated and described herein with reference to specific embodiments, the invention is not intended to be limited to the details shown. Rather, various modifications may be made in the details within the scope and range of equivalents of the claims and without departing from the invention.

(336) Throughout the disclosure, one of skill understands that certain representative embodiments

may be used in the alternative or in combination with other representative embodiments.

(337) Although features and elements are described above in particular combinations, one of ordinary skill in the art will appreciate that each feature or element can be used alone or in any combination with the other features and elements. In addition, the methods described herein may be implemented in a computer program, software, or firmware incorporated in a computer readable medium for execution by a computer or processor. Examples of non-transitory computer-readable storage media include, but are not limited to, a read only memory (ROM), random access memory (RAM), a register, cache memory, semiconductor memory devices, magnetic media such as internal hard disks and removable disks, magneto-optical media, and optical media such as CD-ROM disks, and digital versatile disks (DVDs). A processor in association with software may be used to implement a radio frequency transceiver for use in a UE, WTRU, terminal, base station, RNC, or any host computer.

(338) Moreover, in the embodiments described above, processing platforms, computing systems, controllers, and other devices containing processors are noted. These devices may contain at least one Central Processing Unit (“CPU”) and memory. In accordance with the practices of persons skilled in the art of computer programming, reference to acts and symbolic representations of operations or instructions may be performed by the various CPUs and memories. Such acts and operations or instructions may be referred to as being “executed,” “computer executed” or “CPU executed.”

(339) One of ordinary skill in the art will appreciate that the acts and symbolically represented operations or instructions include the manipulation of electrical signals by the CPU. An electrical system represents data bits that can cause a resulting transformation or reduction of the electrical signals and the maintenance of data bits at memory locations in a memory system to thereby reconfigure or otherwise alter the CPU's operation, as well as other processing of signals. The memory locations where data bits are maintained are physical locations that have particular electrical, magnetic, optical, or organic properties corresponding to or representative of the data bits.

(340) The data bits may also be maintained on a computer readable medium including magnetic disks, optical disks, and any other volatile (e.g., Random Access Memory (“RAM”)) or non-volatile (“e.g., Read-Only Memory (“ROM”)) mass storage system readable by the CPU. The computer readable medium may include cooperating or interconnected computer readable medium, which exist exclusively on the processing system or are distributed among multiple interconnected processing systems that may be local or remote to the processing system. It is understood that the representative embodiments are not limited to the above-mentioned memories and that other platforms and memories may support the described methods.

(341) No element, act, or instruction used in the description of the present application should be construed as critical or essential to the invention unless explicitly described as such. In addition, as used herein, the article “a” is intended to include one or more items. Where only one item is intended, the term “one” or similar language is used. Further, the terms “any of” followed by a listing of a plurality of items and/or a plurality of categories of items, as used herein, are intended to include “any of,” “any combination of,” “any multiple of,” and/or “any combination of multiples of” the items and/or the categories of items, individually or in conjunction with other items and/or other categories of items. Further, as used herein, the term “set” is intended to include any number of items, including zero. Further, as used herein, the term “number” is intended to include any number, including zero.

(342) Moreover, the claims should not be read as limited to the described order or elements unless stated to that effect. In addition, use of the term “means” in any claim is intended to invoke 35 U.S.C. § 112, ¶6, and any claim without the word “means” is not so intended.

(343) Suitable processors include, by way of example, a general purpose processor, a special purpose processor, a conventional processor, a digital signal processor (DSP), a plurality of

microprocessors, one or more microprocessors in association with a DSP core, a controller, a microcontroller, Application Specific Integrated Circuits (ASICs), Application Specific Standard Products (ASSPs); Field Programmable Gate Arrays (FPGAs) circuits, any other type of integrated circuit (IC), and/or a state machine.

(344) A processor in association with software may be used to implement a radio frequency transceiver for use in a wireless transmit receive unit (WTRU), user equipment (UE), terminal, base station, Mobility Management Entity (MME) or Evolved Packet Core (EPC), or any host computer. The WTRU may be used in conjunction with modules, implemented in hardware and/or software including a Software Defined Radio (SDR), and other components such as a camera, a video camera module, a videophone, a speakerphone, a vibration device, a speaker, a microphone, a television transceiver, a hands free headset, a keyboard, a Bluetooth® module, a frequency modulated (FM) radio unit, a Near Field Communication (NFC) Module, a liquid crystal display (LCD) display unit, an organic light-emitting diode (OLED) display unit, a digital music player, a media player, a video game player module, an Internet browser, and/or any Wireless Local Area Network (WLAN) or Ultra Wide Band (UWB) module.

(345) Although the invention has been described in terms of communication systems, it is contemplated that the systems may be implemented in software on microprocessors/general purpose computers (not shown). In certain embodiments, one or more of the functions of the various components may be implemented in software that controls a general-purpose computer.

(346) In addition, although the invention is illustrated and described herein with reference to specific embodiments, the invention is not intended to be limited to the details shown. Rather, various modifications may be made in the details within the scope and range of equivalents of the claims and without departing from the invention.

REFERENCES

(347) The following references may have been referred to hereinabove and are incorporated in full herein by reference. [1] R. Mongia, Rf and Microwave Coupled-Line Circuits. City: Artech House Publishers, 2007. [2] J. Chen, Feedback Networks: theory and circuit application. City: World Scientific Publishing Company, 2007.

Claims

1. A method implemented by a Wireless Transmit/Receive Unit (WTRU), the method comprising: receiving from a first device configured to send a transmission via resonance magnetic coupling, measurement information resulting from measurements performed by the first device; determining a load termination state for the first device based on the measurement information; and sending to the first device, information indicating the determined load termination state for the first device.
2. The method according to claim 1, wherein the load termination state is determined per time slot and/or frequency assignments for use by the first device.
3. The method according to claim 1, comprising sending to the first device, information indicating time slot and/or frequency assignments for use by the first device.
4. The method according to claim 1, comprising sending to the first device, information indicating an operation mode corresponding to any of a transmit mode, a receive mode, or facilitate mode and/or corresponding load termination state.
5. The method according to claim 1, comprising: receiving from the first device, a request to send a transmission to a second device via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device, and wherein the load termination state is determined among the set of load termination states indicated by the capability information.
6. The method according to claim 1, wherein the measurement information includes information indicating any of: signal to noise ratio and/or reported signal strength.

7. The method according to claim 1, wherein the received request includes information indicating any of: a requested quality of service, a priority indicator, an indicator of a required level of reliability of communications, a buffer status indicative of an amount of data to be communicated via the requested transmission, a channel quality metric, and capability information indicative of coupling coefficients supported by the first device; and wherein determining a load termination state for the first device is based on at least the information included in the received request.
8. The method according to claim 1, wherein the WTRU is a cluster head WTRU, and the second device is managed by the cluster head WTRU.
9. The method according to claim 1 further comprising: determining a load termination state for the second device based on the measurement information; and sending to the second device, information indicating the determined load termination state for the second device.
10. The method according to claim 1, comprising: sending to the first device, measurement configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device; and (2) at least one load termination state of a set of load termination states to be used by the first device when performing measurements, and wherein the measurement information result from measurements performed by the first device in accordance with the sent measurement configuration information.
11. A Wireless Transmit/Receive Unit (WTRU), the WTRU comprising: a transmitter/receiver unit configured to: receive from a first device configured to send a transmission via resonance magnetic coupling, measurement information resulting from measurements performed by the first device; a processor configured to determine a load termination state for the first device based on the measurement information; and wherein the transmitter/receiver unit is configured to send to the first device, information indicating the determined load termination state for the first device.
12. The WTRU according to claim 11, wherein the load termination state is determined per time slot and/or frequency assignments for use by the first device.
13. The WTRU according to claim 11, configured to send the first device, information indicating time slot and/or frequency assignments for use by the first device.
14. The WTRU according to claim 11, configured to send the first device, information indicating an operation mode corresponding to any of a transmit mode, a receive mode, or facilitate mode and/or corresponding load termination state.
15. The WTRU according to claim 11, configured to receive from the first device, a request to send a transmission to a second device via resonance magnetic coupling, the request including capability information indicating a set of load termination states supported by the first device, and wherein the load termination state is determined among the set of load termination states indicated by the capability information.
16. The WTRU according to claim 11, wherein the measurement information includes information indicating any of: signal to noise ratio and/or reported signal strength.
17. The WTRU according to claim 11, wherein the received request includes information indicating any of: a requested quality of service, a priority indicator, an indicator of a required level of reliability of communications, a buffer status indicative of an amount of data to be communicated via the requested transmission, a channel quality metric, and capability information indicative of coupling coefficients supported by the first device; and wherein determining a load termination state for the first device is based on at least the information included in the received request.
18. The WTRU according to claim 11, wherein the WTRU is a cluster head WTRU, and the second device is managed by the cluster head WTRU.
19. The WTRU according to claim 11, configured to determine a load termination state for the second device based on the measurement information; and configured to send to the second device, information indicating the determined load termination state for the second device.
20. The WTRU according to claim 11, configured to: send to the first device, measurement

configuration information, the measurement configuration information including information indicating (1) timing and/or frequency information to schedule the measurement of a signal strength received by the first device; and (2) at least one load termination state of a set of load termination states to be used by the first device when performing measurements, and wherein the measurement information result from measurements performed by the first device in accordance with the sent measurement configuration information.
